

# Two standard methods for solving the Ito equation

Alvaro Salas\*

## Abstract

In this paper we show some exact solutions for the Ito equation. These solutions are obtained by two well known methods: the tanh method and the projective Riccati equation method.

*Key words and phrases:* Nonlinear differential equation, nonlinear partial differential equation, fifth order evolution equation, fKdV, fifth order KdV equation, travelling wave solution, projective Riccati equation method, tanh method, partial differential equation, Ito equation, nonlinear evolution equation,  $\text{\textcircled{R}}$ Mathematica.

## 1 Introduction

A large variety of physical, chemical, and biological phenomena is governed by nonlinear evolution equations. The analytical study of nonlinear partial differential equations was of great interest during the last decades. Investigations of traveling wave solutions of nonlinear equations play an important role in the study of nonlinear physical phenomena. The importance of obtaining the exact solutions, if available, of those nonlinear equations facilitates the verification of numerical solvers and aids in the stability analysis of solutions. In this paper we show solutions for Ito's equation by using the tanh method [3] and the projective Riccati equation method [1]. This equation is a particular case of the general fifth order KdV equation (fKdV)

$$u_t + \omega u_{xxxxx} + \alpha u^2 u_x + \beta u_x u_{xx} + \gamma u u_{xxx} = 0, \quad (1)$$

where  $\alpha, \beta, \gamma$  and  $\omega$  are arbitrary real parameters. Ito's equation results from (1) when  $\alpha = 2, \beta = 6, \gamma = 3$  and  $\omega = 1$ . Thus, the Ito equation reads

$$u_t + u_{xxxxx} + 2u^2 u_x + 6u_x u_{xx} + 3u u_{xxx} = 0, \quad (2)$$

---

\*Department of Mathematics, Universidad de Caldas, Department of Mathematics, Universidad Nacional de Colombia, Manizales, Colombia. *email* : asalash2002@yahoo.com

To solve the equation (2) we first unite the independent variables  $x$  and  $t$  into one wave variable  $\xi = x + \lambda t$  to carry the PDE (2) into the ODE (ordinary differential equation)

$$2v'(\xi)v(\xi)^2 + 3v^{(3)}(\xi)v(\xi) + \lambda v'(\xi) + 6v'(\xi)v''(\xi) + v^{(5)}(\xi) = 0 \quad (3)$$

so that  $u(x, t) = v(\xi) = v(x + \lambda t)$ .

## 2 Solution by the tanh method

We seek solutions of equation (3) in the form

$$v(\xi) = \sum_{j=0}^M a_j \varphi^j(\xi), \quad (4)$$

where the function  $\varphi(\xi)$  satisfies the Riccati equation

$$\varphi'(\xi) = k + \varphi^2(\xi) \quad (5)$$

This equation admits the following solutions :

$$\varphi(\xi) = \sqrt{k} \tan \sqrt{k} \xi \quad \text{and} \quad \varphi(\xi) = -\sqrt{k} \cot \sqrt{k} \xi \quad \text{for} \quad k > 0. \quad (6)$$

$$\varphi(\xi) = -\sqrt{-k} \tanh \sqrt{-k} \xi \quad \text{and} \quad \varphi(\xi) = -\sqrt{-k} \coth \sqrt{-k} \xi \quad \text{for} \quad k > 0. \quad (7)$$

$$\varphi(\xi) = -\frac{1}{\xi} \quad \text{for} \quad k = 0. \quad (8)$$

Substituting (4) and (5) into the ODE (3) results in a polynomial equation in powers of  $\varphi(\xi)$ . To determine the parameter  $M$ , we usually balance the linear terms of highest order in the resulting equation with the highest order nonlinear terms. The highest order of  $v^{(p)}(\xi)$  is  $M + p$ . We write this in the form

$$O(v^{(p)}(\xi)) = O(v^p) = M + p. \quad \text{In particular,} \quad O(v(\xi)) = O(v) = M + 0 = M. \quad (9)$$

The following formulae are useful in the balancing process :

$$O(v^{(p)}v^{(q)}) = 2M + p + q; \quad O(v^p v^{(q)}) = (p + 1)M + q. \quad (10)$$

With  $M$  determined, we collect all coefficients of powers of  $\varphi(\xi)$  in the resulting equation where these coefficients have to vanish. This will give a system of algebraic equations involving the parameters  $a_i$ , ( $i = 0, 1, \dots, M$ ),  $\lambda$ , and  $k$ . Having determined these parameters, knowing that  $M$  is a positive integer in most cases, and using (4) we obtain an analytic solution. From (9) and (10) it is clear that

$O(v^2v') = O(v^2v^{(1)}) = 3M + 1$  and  $O(v^{(5)}) = M + 5$ . Balancing  $v^2(\xi)v'(\xi) = v^2v'$  with  $v^{(5)}(\xi) = v^{(5)}$  in (3) we find  $3M + 1 = M + 5$ , that is,  $M = 2$ . Thus, we look for solutions of (3) in the form

$$v(\xi) = a_0 + a_1\varphi(\xi) + a_2\varphi^2(\xi). \quad (11)$$

After substitution of the equations (11) and (5) in (3), we obtain the following system of nonlinear algebraic equations :

$$\begin{aligned} (1) \quad & 16a_1k^3 + 12a_1a_2k^3 + 6a_0a_1k^2 + 2a_0^2a_1k + \lambda a_1k = 0 \\ (2) \quad & 2ka_1^3 + 136k^2a_1 + 2a_0^2a_1 + \lambda a_1 + 24ka_0a_1 + 138k^2a_2a_1 + 12ka_0a_2a_1 = 0 \\ (3) \quad & 24a_2^2k^3 + 272a_2k^3 + 18a_1^2k^2 + 48a_0a_2k^2 + 4a_0a_1^2k + 4a_0^2a_2k + 2\lambda a_2k = 0 \\ (4) \quad & 168a_2^2k^2 + 1232a_2k^2 + 48a_1^2k + 8a_0a_2^2k + 8a_1^2a_2k + 120a_0a_2k + 4a_0a_1^2 + \\ & 4a_0^2a_2 + 2\lambda a_2 = 0 \\ (5) \quad & 10a_1a_2^2 + 150a_1a_2 + 120a_1 = 0 \\ (6) \quad & 2a_1^3 + 10ka_2^2a_1 + 240ka_1 + 18a_0a_1 + 276ka_2a_1 + 12a_0a_2a_1 = 0 \\ (7) \quad & 4a_2^3 + 144a_2^2 + 720a_2 = 0 \\ (8) \quad & 4ka_2^3 + 288ka_2^2 + 8a_0a_2^2 + 8a_1^2a_2 + 1680ka_2 + 72a_0a_2 + 30a_1^2 = 0 \end{aligned}$$

After solving this system, we get the following solutions :

**a.**  $a_0 = -5\sqrt{-\frac{\lambda}{6}}$ ,  $a_1 = 0$ ,  $a_2 = -30$ ,  $k = \frac{1}{4}\sqrt{-\frac{\lambda}{6}}$  and

$$u_1(x, t) = -\frac{5}{2}\sqrt{-\frac{\lambda}{6}} \left( 2 + 3 \tan^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} \xi \right) \right). \quad (12)$$

**b.**  $a_0 = -5\sqrt{-\frac{\lambda}{6}}$ ,  $a_1 = 0$ ,  $a_2 = -30$ ,  $k = \frac{1}{4}\sqrt{-\frac{\lambda}{6}}$  and

$$u_2(x, t) = -\frac{5}{2}\sqrt{-\frac{\lambda}{6}} \left( 2 + 3 \cot^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} \xi \right) \right). \quad (13)$$

**c.**  $a_0 = 5\sqrt{-\frac{\lambda}{6}}$ ,  $a_1 = 0$ ,  $a_2 = -30$ ,  $k = -\frac{1}{4}\sqrt{-\frac{\lambda}{6}}$  and

$$u_3(x, t) = \frac{5}{2}\sqrt{-\frac{\lambda}{6}} \left( 2 - 3 \tanh^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} \xi \right) \right). \quad (14)$$

**d.**  $a_0 = 5\sqrt{-\frac{\lambda}{6}}$ ,  $a_1 = 0$ ,  $a_2 = -30$ ,  $k = -\frac{1}{4}\sqrt{-\frac{\lambda}{6}}$  and

$$u_4(x, t) = \frac{5}{2}\sqrt{-\frac{\lambda}{6}} \left( 2 - 3 \coth^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} \xi \right) \right). \quad (15)$$

### 3 Solutions by the projective Riccati equation method

This method is due to Conte[1].

**Step 1.** We consider solutions of (3) in the form

$$v(\xi) = a_0 + \sum_{j=1}^m \sigma(\xi)^{j-1} (a_j \sigma(\xi) + b_j \tau(\xi)), \quad (16)$$

where  $\sigma(\xi)$ ,  $\tau(\xi)$  satisfy the system

$$\begin{cases} \sigma'(\xi) = e\sigma(\xi)\tau(\xi) \\ \tau'(\xi) = e\tau^2(\xi) - \mu\sigma(\xi) + r. \end{cases} \quad (17)$$

It may be proved that the first integral of this system is given by

$$\tau^2 = -e \left[ r - 2\mu\sigma(\xi) + \frac{\mu^2 + \rho}{r} \sigma^2(\xi) \right], \quad (18)$$

where  $\rho = \pm 1$  and  $e = \pm 1$ .

We consider the following solutions of the system (17).

**1. Case I:**

If  $r = \mu = 0$  then

$$\tau_1(\xi) = -\frac{1}{e\xi}, \quad \sigma_1(\xi) = \frac{C}{\xi}. \quad (19)$$

**2. Case II:**

If  $e = 1$ ,  $\rho = -1$  and  $r > 0$  :

$$\begin{cases} \sigma_1(\xi) = \frac{r \sec(\sqrt{r} \xi)}{1 + \mu \sec(\sqrt{r} \xi)}; & \tau_1(\xi) = \frac{\sqrt{r} \tan(\sqrt{r} \xi)}{1 + \mu \sec(\sqrt{r} \xi)} \\ \sigma_2(\xi) = \frac{r \csc(\sqrt{r} \xi)}{1 + \mu \csc(\sqrt{r} \xi)}; & \tau_2(\xi) = -\frac{\sqrt{r} \cot(\sqrt{r} \xi)}{1 + \mu \csc(\sqrt{r} \xi)}. \end{cases} \quad (20)$$

**3. Case III:**

If  $e = -1$ ,  $\rho = -1$  and  $r > 0$  :

$$\begin{cases} \sigma_3 = \frac{r \operatorname{sech}(\sqrt{r} \xi)}{1 + \mu \operatorname{sech}(\sqrt{r} \xi)} \\ \tau_3 = \frac{\sqrt{r} \tanh(\sqrt{r} \xi)}{1 + \mu \operatorname{sech}(\sqrt{r} \xi)}. \end{cases} \quad (21)$$

#### 4. Case IV:

If  $e = -1$ ,  $\rho = 1$  and  $r > 0$  :

$$\begin{cases} \sigma_4 = \frac{r \operatorname{csch}(\sqrt{r} \xi)}{1 + \mu \operatorname{csch}(\sqrt{r} \xi)} \\ \tau_4 = \frac{\sqrt{r} \operatorname{coth}(\sqrt{r} \xi)}{1 + \mu \operatorname{csch}(\sqrt{r} \xi)}. \end{cases} \quad (22)$$

**Step 2.** Substituting (16), along with (17) and (18) into (3) and collecting all terms with the same power in  $\sigma^i(\xi)\tau^j(\xi)$ , we get a polynomial in the two variables  $\sigma(\xi)$  and  $\tau(\xi)$ . This polynomial has the form

$$\begin{aligned} & a\sigma(\xi)^{m+5} + b\sigma(\xi)^{2m+3} + c\sigma(\xi)^{m+4}\tau(\xi) + d\sigma(\xi)^{3m+1} + \\ & + e\sigma(\xi)^{2m+2}\tau(\xi) + \text{other terms of lower degree} \end{aligned} \quad (23)$$

We assume that  $m \geq 1$  to avoid trivial solutions. The degrees of the highest terms are  $m + 5$  ( the degree of the terms  $a\sigma(\xi)^{m+5}$  and  $c\sigma(\xi)^{m+4}\tau(\xi)$ ),  $2m + 3$  ( the degree of the term  $b\sigma(\xi)^{2m+3}$  ) and  $3m + 1$  ( the degree of the term  $d\sigma(\xi)^{3m+1}$  ). There are two integer values of  $m$  for which  $3m + 1 = 2m + 3$  or  $3m + 1 = m + 5$  or  $2m + 3 = m + 5$ . These are  $m = 1$  and  $m = 2$ . We are going to find solutions for  $m = 1$  ( the case  $m = 2$  is not considered here ). When  $m = 1$  solutions have the form  $v(\xi) = a_0 + a_1\sigma(\xi) + b_1\tau(\xi)$  and equating in (24) the coefficients of every power of  $\sigma(\xi)$  and of every term of the form  $\sigma^j(\xi)\tau(\xi)$  to zero, we obtain the following algebraic system in the variables  $a_0, a_1, b_1, \dots$  :

- (1)  $e^7 (\mu^2 + \rho)^2 a_1 = 0$
- (2)  $e^8 (\mu^2 + \rho)^3 b_1 = 0$
- (3)  $e^5 (\mu^2 + \rho)^2 (12\mu e^3 - 6\mu e + a_1) b_1 = 0$
- (4)  $e^4 (\mu^2 + \rho) (16r\mu a_1 e^3 - \mu^2 b_1^2 e - \rho b_1^2 e - 8r\mu a_1 e + r a_1^2) = 0$
- (5)  $2(e - 1)(e + 1)r (15re^3 - 9re - 2a_0) b_1^2 = 0$
- (6)  $120r^2 a_1 e^7 - 120r\mu b_1^2 e^5 - 180r^2 a_1 e^5 - 18ra_0 a_1 e^4 + 162r\mu b_1^2 e^3 + 61r^2 a_1 e^3 + 8\mu a_0 b_1^2 e^2 - 6ra_1 b_1^2 e^2 + 15ra_0 a_1 e^2 - 45r\mu b_1^2 e + 2a_0^2 a_1 e + \lambda a_1 e - 4\mu a_0 b_1^2 + 4ra_1 b_1^2 = 0$
- (7)  $-480r^2 \mu a_1 e^7 + 180r\mu^2 b_1^2 e^5 + 60r\rho b_1^2 e^5 + 600r^2 \mu a_1 e^5 - 30r^2 a_1^2 e^4 + 36r\mu a_0 a_1 e^4 - 180r\mu^2 b_1^2 e^3 - 48r\rho b_1^2 e^3 - 150r^2 \mu a_1 e^3 + 21r^2 a_1^2 e^2 - 4\mu^2 a_0 b_1^2 e^2 - 4\rho a_0 b_1^2 e^2 + 12r\mu a_1 b_1^2 e^2 - 18r\mu a_0 a_1 e^2 + 4ra_0 a_1^2 e + 27r\mu^2 b_1^2 e - 4r\mu a_1 b_1^2 = 0$

$$(8) \quad e(360r\mu^2a_1e^6 + 120r\rho a_1e^6 - 60\mu^3b_1^2e^4 - 60\mu\rho b_1^2e^4 - 330r\mu^2a_1e^4 - 90r\rho a_1e^4 + 30r\mu a_1^2e^3 - 9\mu^2a_0a_1e^3 - 9\rho a_0a_1e^3 + 33\mu^3b_1^2e^2 + 33\mu\rho b_1^2e^2 + 45r\mu^2a_1e^2 - 12r\mu a_1^2e - 3\mu^2a_1b_1^2e - 3\rho a_1b_1^2e + ra_1^3) = 0$$

$$(9) \quad (e-1)(e+1)rb_1(120r^2e^6 - 120r^2e^4 - 18ra_0e^3 + 16r^2e^2 - 2rb_1^2e + 6ra_0e + 2a_0^2 + \lambda) = 0$$

$$(10) \quad b_1(720r^2\mu e^8 - 1320r^2\mu e^6 - 72r\mu a_0e^5 + 60r^2a_1e^5 + 662r^2\mu e^4 - 8r\mu b_1^2e^3 + 84r\mu a_0e^3 - 69r^2a_1e^3 + 4\mu a_0^2e^2 - 61r^2\mu e^2 + 2\lambda\mu e^2 - 8ra_0a_1e^2 + 6r\mu b_1^2e - 15r\mu a_0e + 12r^2a_1e - 2\mu a_0^2 - \lambda\mu + 4ra_0a_1) = 0$$

$$(11) \quad b_1(1800r^2\mu^2e^8 + 360r^2\rho e^8 - 2880r^2\mu^2e^6 - 480r^2\rho e^6 - 108r\mu^2a_0e^5 - 36r\rho a_0e^5 + 240r^2\mu a_1e^5 + 1186r^2\mu^2e^4 + 136r^2\rho e^4 - 12r\mu^2b_1^2e^3 - 4r\rho b_1^2e^3 + 96r\mu^2a_0e^3 + 24r\rho a_0e^3 - 228r^2\mu a_1e^3 - 75r^2\mu^2e^2 + \lambda\mu^2e^2 + 2\mu^2a_0^2e^2 + 2\rho a_0^2e^2 + 6r^2a_1^2e^2 + \lambda\rho e^2 - 16r\mu a_0a_1e^2 + 6r\mu^2b_1^2e + 2r\rho b_1^2e - 9r\mu^2a_0e + 27r^2\mu a_1e - 2r^2a_1^2 + 4r\mu a_0a_1) = 0$$

$$(12) \quad b_1(2400r\mu^3e^8 + 1440r\mu\rho e^8 - 3120r\mu^3e^6 - 1680r\mu\rho e^6 - 72\mu^3a_0e^5 - 72\mu\rho a_0e^5 + 360r\mu^2a_1e^5 + 120r\rho a_1e^5 + 930r\mu^3e^4 + 390r\mu\rho e^4 - 8\mu^3b_1^2e^3 - 8\mu\rho b_1^2e^3 + 36\mu^3a_0e^3 + 36\mu\rho a_0e^3 - 249r\mu^2a_1e^3 - 69r\rho a_1e^3 - 30r\mu^3e^2 + 12r\mu a_1^2e^2 - 8\mu^2a_0a_1e^2 - 8\rho a_0a_1e^2 + 2\mu^3b_1^2e + 2\mu\rho b_1^2e + 15r\mu^2a_1e - 2r\mu a_1^2) = 0$$

$$(13) \quad 2e^2(\mu^2 + \rho)b_1(900r\mu^2e^6 + 180r\rho e^6 - 840r\mu^2e^4 - 120r\rho e^4 - 9\mu^2a_0e^3 - 9\rho a_0e^3 + 120r\mu a_1e^3 + 135r\mu^2e^2 - \mu^2b_1^2e - \rho b_1^2e - 45r\mu a_1e + 3ra_1^2) = 0$$

**Step 3.** ( This is the more difficult step ) Solving the previous system for  $r, \mu, a_0, a_1, b_1$  with the aid of  $\text{\textcircled{R}}Mathematica 6.0$  we get  $b_1 = 0$ , so solutions have the form  $u = a_0 + a_1\sigma(x + \lambda t)$ . These solutions correspond to values  $e = 1$  and  $\rho = -1$ . They are :

$$\text{i. } a_0 = \frac{5\sqrt{-\lambda}}{2\sqrt{6}}, \quad a_1 = 15, \quad \mu = -1, \quad r = \sqrt{-\frac{\lambda}{6}} \text{ and}$$

$$u_5(x, t) = \frac{5\sqrt{-\lambda}}{2\sqrt{6}} \cdot \frac{1 + 5 \csc\left(\sqrt[4]{-\frac{\lambda}{6}}(x + \lambda t)\right)}{1 - \csc\left(\sqrt[4]{-\frac{\lambda}{6}}(x + \lambda t)\right)} \quad (24)$$

ii.  $a_0 = \frac{5\sqrt{-\lambda}}{2\sqrt{6}}$ ,  $a_1 = -15$ ,  $\mu = 1$ ,  $r = \sqrt{-\frac{\lambda}{6}}$  and

$$u_6(x, t) = \frac{5\sqrt{-\lambda}}{2\sqrt{6}} \cdot \frac{1 - 5 \csc \left( \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right)}{1 + \csc \left( \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right)} \quad (25)$$

iii.  $a_0 = \frac{5\sqrt{-\lambda}}{2\sqrt{6}}$ ,  $a_1 = -15$ ,  $\mu = 1$ ,  $r = \sqrt{-\frac{\lambda}{6}}$  and

$$u_7(x, t) = \frac{5\sqrt{-\lambda}}{2\sqrt{6}} \left( 1 - 3 \sec^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right) \right) \quad (26)$$

iv.  $a_0 = \frac{5\sqrt{-\lambda}}{2\sqrt{6}}$ ,  $a_1 = 15$ ,  $\mu = -1$ ,  $r = \sqrt{-\frac{\lambda}{6}}$  and

$$u_8(x, t) = \frac{5\sqrt{-\lambda}}{2\sqrt{6}} \left( 1 - 3 \csc^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right) \right) \quad (27)$$

v.  $a_0 = -\frac{5\sqrt{-\lambda}}{2\sqrt{6}}$ ,  $a_1 = -15$ ,  $\mu = 1$ ,  $r = -\sqrt{-\frac{\lambda}{6}}$  and

$$u_9(x, t) = -\frac{5\sqrt{-\lambda}}{2\sqrt{6}} \left( 1 - 3 \operatorname{sech}^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right) \right) \quad (28)$$

vi.  $a_0 = -\frac{5\sqrt{-\lambda}}{2\sqrt{6}}$ ,  $a_1 = 15$ ,  $\mu = -1$ ,  $r = -\sqrt{-\frac{\lambda}{6}}$  and

$$u_{10}(x, t) = -\frac{5\sqrt{-\lambda}}{2\sqrt{6}} \left( 1 + 3 \operatorname{csch}^2 \left( \frac{1}{2} \sqrt[4]{-\frac{\lambda}{6}} (x + \lambda t) \right) \right) \quad (29)$$

## 4 Conclusions

In this paper, by using the tanh method, the projective Riccati equation method and the help of symbolic computation system *Mathematica 6.0*, we obtained some exact solutions for the equation (2). The projective Riccati equation method is more complicated than other methods in comparison with the tanh method in the sense that the algebraic system in many cases demands a lot of time to be solved. On the other hand, this method allows us to obtain some new exact solutions. In fact, the projective method gave us six solutions, while with the tanh method we obtained four solutions. On the other hand, the solutions obtained by these methods are different. We apply the mentioned method to solve other nonlinear differential equations [2].

## References

- [1] R. CONTE & M. MUsETTE , *Link betwen solitary waves and projective Riccati equations*, J. Phys. A Math. **25** (1992), 5609-5623.
  
- [2] ALVARO SALAS, *Some solutions for a type of generalized Sawada-Kotera equation*, Applied Mathematics and Computation, Elsevier Editorial System, Netherlands, in press, available on line from july 17 2007 at <http://www.sciencedirect.com>