

Measurement of a time-periodic magnetic field by rotating coil

V. Marusov

GSI Helmholtzzentrum für Schwerionenforschung GmbH, Darmstadt, Germany

Abstract

A novel technique of the measurement data processing is developed which allows to apply the rotating coil method for measurement of a dynamic magnetic field, periodic in time. The developed technique allows to obtain time-dependent multipoles in a single measurement which takes place during one power cycle of the magnet or the coil rotation period, whichever is longer.

Keywords: Accelerator magnets, Magnetic measurement, Circular multipoles, Dynamic field

1. Introduction

The two-dimensional field harmonic expansion and rotating coil magnetometer are known for many years and are described in many books, reviews and accelerator schools. We refer to Jain [1],[2] and quote a few results which are needed for description of the proposed technique of the measurement data processing.

1.1. Plane circular multipoles

For most practical purposes the magnet field analysis for accelerator applications can be reduced to a two-dimensional problem and the field can be represented by the power series expansion (see [1], sections 1-2):

$$\mathbf{B}(z) = B_y + iB_x = \sum_{n=1}^{\infty} c_n \left(\frac{z}{r_{ref}} \right)^{n-1} \quad (1)$$

where B_x and B_y are the x - and y -components of the magnetic flux density, $z = x + iy$ and r_{ref} is a reference radius. The complex expansion coefficients $c_n = b_n + ia_n$ in commonly accepted jargon are called “harmonics” or “multipoles”.

1.2. Measurement of a static field

The flux $\Phi(\phi)$ through an arbitrary coil array has the form (see [2], eqn.30)

$$\begin{aligned} \Phi(\phi) &= \text{Re} \sum_{n=1}^{\infty} \underbrace{s_n c_n}_{\gamma_n} e^{in\phi} \\ &= \frac{1}{2} \sum_{n=1}^{\infty} \gamma_n e^{in\phi} + (\mathbf{c.c.}) \end{aligned} \quad (2)$$

In eqn. (2) s_n are complex “sensitivity factors”, ϕ is the angle of rotation, “(c.c.)” means complex conjugate. We introduced variables $\gamma_n = s_n c_n$ which we refer later as “reduced multipoles” in order to make further calculations less cumbersome.

In the measurement, flux as a function of the rotation angle is evaluated through the time integral of induced voltage $V(t)$ (see [2], eqns. 7,11), readings of the voltage integrator are triggered by an angular encoder. In terms of time as a function of the rotation angle $t(\phi)$

$$- \int_{t(0)}^{t(\phi)} V(t) dt = \int_{t(0)}^{t(\phi)} \frac{d\Phi}{dt} dt = \int_{t(0)}^{t(\phi)} d\Phi = \Phi(\phi) - \Phi(0) \quad (3)$$

As the $\Phi(\phi)$ is evaluated in the measurement, γ_m and consequently c_m can be found by the Fourier transform:

$$\begin{aligned} \frac{1}{\pi} \int_0^{2\pi} \Phi e^{-im\phi} d\phi &= \frac{1}{2\pi} \sum_{n=1}^{\infty} \gamma_n \underbrace{\int_0^{2\pi} e^{in\phi} e^{-im\phi} d\phi}_{2\pi\delta_{nm}} + \\ &+ \underbrace{\overline{\gamma_n} \int_0^{2\pi} e^{-in\phi} e^{-im\phi} d\phi}_0 \\ &= \gamma_m = s_m c_m \end{aligned} \quad (4)$$

2. Measurement of a time-periodic field

Let us consider a magnet which is supplied by a periodic current. If the field is measured by the rotating coil method, two cases may be separated, which are considered in the following sections.

Email address: V.Marusov@gsi.de (V. Marusov)

$$\begin{aligned}
& z_0 = b_0 \\
& \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} z_1 \\ z_3 \end{bmatrix} = \begin{bmatrix} b_1 \\ -b_1 \end{bmatrix} \\
& \begin{bmatrix} 1 & 1 & 1 \\ 1 & e^{-i\frac{2\pi}{3}} & e^{-i\frac{4\pi}{3}} \\ 1 & e^{-i\frac{4\pi}{3}} & e^{-i\frac{8\pi}{3}} \end{bmatrix} \begin{bmatrix} z_2 \\ z_4 \\ z_6 \end{bmatrix} = \begin{bmatrix} b_2 \\ e^{i\frac{2\pi}{3}} b_2 \\ e^{i\frac{4\pi}{3}} b_2 \end{bmatrix} \\
& \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} z_5 \\ z_7 \end{bmatrix} = \begin{bmatrix} b_3 \\ b_3 \end{bmatrix} \\
& z_8 = b_4
\end{aligned} \tag{16}$$

As all matrices in (16) are invertible, the case study is solved. This technique can be applied for any N , M and $K > M$.

Instead of inverting the $NK \times NK$ matrix, the problem is reduced to inverting of a number of matrices of smaller dimensions. It can be shown for the general case, that the maximum matrix dimension does not exceed $(K - M + 1) \times (K - M + 1)$.

2.2. “Fast magnet” case

Let us assume the measuring coil rotates uniformly and the magnet is cycled M times during one turn of the coil. In this case we denote as T the coil rotating period and measure time in units of $\frac{T}{2\pi}$. For the purpose of a partial reuse of results obtained in section 2.1 let us swap the meaning of indices: now k stands for the multipole number and n for term number in the Fourier expansion of the multipole:

$$\gamma_k(t) = \sum_{n=0}^{\infty} \sigma_{kn} e^{iMnt} \tag{17}$$

The flux through the coil vs. time is then given by equation which is similar to (7), except for the low limits of sums:

$$\Phi(t) = \frac{1}{2} \sum_{n=0}^{\infty} \sum_{k=1}^{\infty} \sigma_{kn} e^{i(k+Mn)t} + (\text{c.c.}) \tag{18}$$

The Fourier transform of (18) yields

$$\frac{1}{\pi} \int_0^{2\pi} \Phi e^{-i\hat{m}t} dt = \sum_{n=0}^{\infty} \sum_{k=1}^{\infty} \delta_{\hat{m},(k+Mn)} \sigma_{kn} \tag{19}$$

Let us consider a partial sum of (18) with $n < N$, $k \leq K$ and map the σ_{nk} to a vector \mathbf{z} of length NK as follows:

$$z_{k-1+nK} = \sigma_{kn} \Leftrightarrow z_j = \sigma_{j \bmod K+1, \text{floor}(\frac{j}{K})} \quad 0 \leq j < NK \tag{20}$$

The equation $k + nM = \hat{m}$ in terms of the linear index j defined in (20) can be derived as

$$(j \bmod K)(K - M) + jM = (\hat{m} - 1)K \tag{21}$$

The smallest solution of the eqn. (21) is found for $\hat{m} = 1$, $j = 0$. Let us denote $m = \hat{m} - 1$, then (19) can be rewritten in the form $\mathbf{Az} = \mathbf{b}$ where the matrix \mathbf{A} and vector \mathbf{b} are defined as:

$$\begin{aligned}
A_{mj} &= \delta_{(j \bmod K)(K-M)+jM, mK} \\
b_m &= \frac{1}{\pi} \int_0^{2\pi} \Phi e^{-i(m+1)t} dt
\end{aligned} \tag{22}$$

Comparing (22) and (10) one can see that the same matrix \mathbf{A} is obtained (albeit after swapping meanings of k and n). Therefore the consideration of the “fast magnet” case is very similar to the one of “fast coil”.

The case $K = M$ is a trivial one, because \mathbf{A} turns to the identity matrix, yielding $z_m = b_m$.

For $K > M$ each equation with $L > 1$ terms has, after mapping from z_j to σ_{kn} , the following form:

$$\sum_{l=0}^{L-1} z_{j_{\min}+l(K-M)} = b_m \Leftrightarrow \sum_{l=0}^{L-1} \sigma_{k_{\max}-Ml, n_{\min}+l} = b_m \tag{23}$$

If the measurement clock is shifted by τ , σ_{kn} and b_m are transformed as:

$$\begin{aligned}
\sigma_{kn} &\rightarrow \tilde{\sigma}_{kn} = e^{inM\tau} \sigma_{kn} \\
b_m &\rightarrow \tilde{b}_m = e^{i(m+1)\tau} b_m
\end{aligned} \tag{24}$$

In terms of equation for z_j , from the original equation (23) we can construct another one:

$$\begin{aligned}
& \sum_{l=0}^{L-1} z_{j_{\min}+l(K-M)} = b_m \rightarrow \\
& \rightarrow \sum_{l=0}^{L-1} e^{ilM\tau} \cdot z_{j_{\min}+l(K-M)} = e^{i[m+1-M \cdot \text{floor}(\frac{j_{\min}}{K})]\tau} \cdot b_m
\end{aligned} \tag{25}$$

Consequently, exactly as for the “fast coil” case, from each equation with $L > 1$ terms we construct $L - 1$ additional equations using the σ_{kn} and b_m time translation properties, obtaining a linear system with a Vandermonde matrix, which has a non-zero determinant.

Just as in the “fast coil” case, the problem is reduced to inverting a number of matrices with dimensions not exceeding $(K - M + 1) \times (K - M + 1)$.

3. Discussion

For the “fast magnet” case (Section 2.2) a good synchronization of the coil rotation and the magnet cycling is essential. As a possible implementation one can consider the magnet power supply driven by a waveform generator which is clocked by the angular encoder pulses.

Much looser requirements can be applied for the “fast coil” case (Section 2.1). The magnet cycle starts from the injection plateau and comes back to it. If multipoles

stay constant at the injection plateau then expulsion of a part of the plateau, followed by “gluing” of remaining parts preserves continuity of each multipoles as a function of time.

Therefore in the “fast coil” case the measurement can be started at any point shortly before the ramp up, and ended at any point during the injection plateau after ramp down when the coil comes back to the start angle. In other words, the magnet cycle is not required to be a multiple of the coil rotation period. This option, to choose a “fictitious” magnet cycle, may be exploited. It may be shown for a cycle with the same ramp up and ramp down rates, that the closer the “fictitious” injection plateau duration is to the duration of the cycle flat-top the lesser are higher harmonics in the Fourier expansion (5).

The developed data processing technique operates with truncated expansions (partial sums) to represent the field and multipoles. To check if upper limits of sums are large enough to provide the precision required they may be varied and the effect of variations on obtained results must be analyzed.

4. Conclusions

The data processing technique has been developed which allows the use of the rotating coil method for the measurement of a dynamic time-periodic field. This technique allows to obtain time-dependent multipoles in a single measurement which lasts one power cycle of the magnet or the coil rotation period, whichever is longer.

Acknowledgments

The author would like to thank Markus Kirk for valuable comments and help with preparation of the manuscript.

References

- [1] A.K. Jain, Basic theory of magnets, in: S. Turner (Ed.), CAS Magnetic Measurement and Alignment, no. 98-05 in CERN Yellow Reports, CERN, 1998, pp. 1-26
- [2] A.K. Jain, Harmonic coils, same CERN Yellow Report, pp. 175-218
- [3] URL: http://en.wikipedia.org/wiki/Vandermonde_matrix (last accessed on June 8, 2021)
- [4] URL: http://proofwiki.org/wiki/Inverse_of_Vandermonde's_Matrix (last accessed on June 8, 2021)