

# Method for Improved DL CoMP Implementation in Heterogeneous Networks

Faris B. Mismar

University of Texas at Austin, Austin, TX, 78721, USA

Ericsson Inc., Plano, TX 75024, USA

Email: faris.mismar@utexas.edu; faris.mismar@ericsson.com

**Abstract**—I propose a novel method for practical Joint Processing DL CoMP implementation in LTE/LTE-A systems using a supervised machine learning technique. DL CoMP has not been thoroughly studied in previous work although cluster formation and interference mitigation have been studied extensively. In this paper, I attempt to improve the cell-edge user data rate served by a heterogeneous network cluster by means of dynamically changing the DL SINR threshold at which DL CoMP is triggered. I do so by allowing the base stations to derive a threshold on the basis of machine learning inference. The simulation results show an improved user throughput at the cell edge of 40% and a 6.4% improvement to the average cell throughput compared to the baseline of static triggering.

**Index Terms**—MIMO, DL CoMP, LTE, LTE-A, machine learning, SVM, heterogeneous networks.

## I. INTRODUCTION

### A. Background

The *Downlink Coordinated Multi-Point* (DL CoMP) operation was introduced in 3gpp Rel 11 for LTE-Advanced as a feature that improves high data rates coverages and cellular capacity [1].

As far as the cellular *user equipment* (UE) is concerned, DL CoMP has several formats:

- **Joint Processing:** where data for a UE is available at more than one point participating in the data transmission in a time-frequency resource. These points (or base stations) are called the *CoMP cooperating set* and are determined by the higher layers such as the *radio resource control* (RRC) [1]. Alternatively, joint processing is also called *joint transmission*.
- **Dynamic Cell Selection:** where the UE serving cell can be changed on a per-subframe basis.
- **Coordinated Scheduling/Beamforming:** where one point in the CoMP cooperating set transmits data on the downlink, but coordinates with other points for user scheduling and beamforming decisions.

The management of the DL CoMP sets may be based on *radio resource management* (RRM) measurements. The standards require that measurements be either the *cell-specific reference symbol* (CRS) measurements or the *channel state information* (CSI) [1].

Two common scenarios exist as far as DL CoMP implementation is concerned: *inter-* and *intra-site*. In a heterogeneous network setup, the focus is mostly on the inter-site implementation, where a point-to-point fiber with negligible




Fig. 1: Typical DL CoMP Setup in a Heterogeneous Network

delay and large capacity backhaul connects the two base stations of two different transmit powers, as in Fig. 1.

### B. Motivation

The demand for data traffic over cellular networks continues to increase with emphasis on low latency and reliability [2]. Heterogeneous networks are one of the most important solutions to increase the network capacity, where low power base stations are deployed along with the existing high power macro base stations. With the links of the X2 interface connecting the low and high power nodes, a distributed MIMO channel can be formed to further bring data throughputs closer to the theoretical limits. This can be done via DL CoMP.

This paper motivates a dynamic, distributed, and optimum “network” MIMO channel composed of all the transmitting nodes in the DL CoMP cooperating set with the focus on the *joint processing* category of DL CoMP and with the use of a machine learning algorithm residing in the base station to improve end-user experience while releasing the burden off the engineer to find a *signal to interference-plus-noise ratio* (SINR) threshold for DL CoMP to be triggered therefore transmitting less power whenever possible.

In LTE-A, the UE in *closed-loop spatial multiplexing* (CLSM) MIMO measures the channel and gives quantized feedback about the CSI in the form of either periodic or aperiodic reports, which typically contain *rank indicator*, *channel quality indicator*, and *precoding matrix information* (RI, CQI, PMI) [3], [4]. Since this CSI is measured by the receiver for the *transmit* channel, literature refers to it

as CSIT [5], [6]. Clearly, this is imperfect channel state information and no transmitting end has perfect knowledge of the channel. Thus, the UE attempts to estimate a suitable CSI in order to maximize the throughput. UEs, regardless of their respective MIMO rank, must report the *reference symbol received power* (RSRP) which can be periodically reported [7].

I will measure the downlink performance in terms of the empirical CDF of the *signal to interference and noise ratio* (SINR), the average *block error rate* (BLER) on the *physical downlink shared channel* PDSCH channels, the average spectral efficiency per user, and the average end-user throughput on the downlink. I show that the RF coverage parameter—namely the RSRP—was not impacted as a result of my contribution.

In this paper, I start from a requirement that the base stations receiving the CSIT reports from one UE also receive CSIT information from all cell-edge connected UEs prior to the DL CoMP algorithm to kick-in for a small duration not exceeding the collection period duration ( $\delta_{\text{CoMP}}$ ). This is in order to ensure a minimized time varying communication channel and ensure that UEs have consistent space-time behavior [5]. Collecting reports from all UEs elicits a modification to the 3gpp standards body where the CQI-PMI reporting period  $N_{pd}$  [3] is allowed to become 1. This modification to the standards may be *unnecessary* in dense urban environments where most UEs get cell-edge performance especially if adequate measurement samples are gathered, defined by a misclassification error  $\varepsilon < 5\%$  as we shall see later.

### C. Relevant Prior Work

In [8], the authors propose a convex optimization problem to improve energy efficiency at the expense of the minimum user data rate, which I aim at improving.

Using stochastic geometry, the authors in [9] derived a closed-form integral expression for the coverage probability as a function of the SINR in a heterogeneous network. They derived an integral expression for the network coverage probability where the typical user located at an arbitrary location. They considered CSI feedback from the UE back to the CoMP measurement set; however, they did their work for single user and a single antenna (i.e., no MIMO).

The performance of the zero forcing beamforming has been evaluated in [10] and the authors did so by randomly dropping the base stations in a two-dimensional plane for multiple times. There was no reference, however, to any particular morphology and the work falls under CoMP coordinated scheduling/beamforming format (no MIMO).

Interference mitigation and handover management in CoMP-formed clusters is discussed in [11], [12]. The authors focused on joint transmission and showed outputs comparing performance with an approach similar to the approach taken in this paper; however, their clustering algorithm is intended to reduce backhaul utilization without

harming end-user throughputs. I, on the other hand, aim to improve end-user throughput.

### D. Contribution

The paper makes the following specific contributions:

- Use machine learning to derive the optimal conditions at which DL CoMP can be triggered “on the fly” instead of relying on the static DL CoMP configuration parameters from the radio engineer at the base station. See Section IV.
- Improve user downlink bitrate at the cell edge. See Section VI.
- Prove that selection of a static DL SINR threshold at which DL CoMP is triggered leads to sub-optimal downlink bitrates. See Section VI.

### E. System Description

The system described in this paper is made of two modules:

- An inter-site DL CoMP operation in a heterogeneous network composed of a three-sectored macro base station and one pico base station per macro sector connected with negligible delay and high bandwidth optical fiber.
- A machine learning algorithm based on *support vector machine* (SVM) to derive optimum DL SINR triggering point for DL CoMP to operate if applicable. This algorithm is implemented in MATLAB.

### F. Paper Organization and Notation

Section II describes the setup of the model. Section III lists the key assumptions made in running the simulations. In Section IV, I approach the problem from two angles: radio environment and machine learning. I detail the novel algorithm to trigger DL CoMP in Section V. Section VI shows the simulation results and justification of the results. I conclude the paper with Section VII with a summary of the findings and a proposed way forward.

*Notation:* Boldface lower and upper case symbols represent vectors and matrices respectively, and that includes both Latin and Greek alphabets. The column vector is grouped using  $(\cdot)$ . I use  $\mathcal{N}_{\mathbb{C}}(\boldsymbol{\mu}, \boldsymbol{\Sigma})$  to denote the circular symmetric complex Gaussian distribution with mean  $\boldsymbol{\mu}$  and covariance matrix  $\boldsymbol{\Sigma}$ .  $\mathbb{E}[\cdot]$  denotes the expectation operator. The transpose operator is given by  $(\cdot)^{\top}$ . I use the brackets  $[\cdot]$  both normal or superscripted to denote discrete time. The Euclidean norm of a vector  $\mathbf{x}$  is given by  $\|\mathbf{x}\|$ . The inner product of two vectors is given by  $\langle \cdot, \cdot \rangle$  and the  $\triangleq$  symbol means equal by definition. Indices on vectors and matrices are consistent with MATLAB notation. Finally, an  $N$ -by- $M$  matrix whose elements may be complex numbers is  $\mathbb{C}^{N \times M}$  and a real column vector with  $M$  elements is  $\mathbb{R}^M$ .

## II. SETUP

My setup for the macro base station entails a hexagonal cellular geometry of three cells, one pico cell per macro cell, non-stationary UEs with two antennas randomly placed

in the cell, *frequency-division duplex* (FDD) operation, and log-normal shadow fading. Pico base station is a *low power node* (LPN) and therefore terms are used interchangeably.

### A. OFDM

I have used *orthogonal frequency division multiplexing* (OFDM) with normal cyclic prefix. The nature of OFDM orthogonality makes *zero-forcing* (ZF) estimation quite favorable in the analysis of this paper since OFDM modulation turns a frequency-selective MIMO channel into a set of parallel frequency-flat and single-tap MIMO channels.

### B. Base Stations

The cells are hexagonal. Within each cell, UEs are placed randomly and distributed over the cell coverage area. At the center of the cell is a macro base station with directional antennas. Small cells are placed so they coincide in the sector null though in practice they should be placed in coverage holes, defined by suboptimal RSRP and SINR distributions.

For a base station to handle events such as when to trigger CoMP for a given UE, a *configuration management* (CM) database is uploaded by the operator which allows coordinated cells to select candidates for CoMP on the basis of their estimated cell-specific reference symbol SINR, estimated as a function of their reported CQI values. In fact, the 3gpp standards do not specify which parameters or physical channel measurements trigger DL CoMP [1].

### C. Propagation

No interference mitigation techniques have been implemented besides ZF to cancel intra-cell interference. I also treat inter-cell interference as noise. The average terrain height is assumed to be zero.

All channels are independent of the transmitted signal (e.g., no channel-dependent power control) for the sake of simplicity of computations and in alignment with the 3gpp standards on the downlink [3].

I also used COST-231 model to predict the path loss and find the RF coverage levels at the UEs instead of COST-231 Walfisch-Ikegami since the simulator has it built-in [13].

As stated in [14], spatial multiplexing gains may disappear where signal levels are low relative to interference.

### D. User Equipments

All UEs  $i$  are assumed to be smartphones. Based on whether admission control is set or hard-blocking occurs,  $i$  has a finite maximum per cell, which I call  $Q$ . I will use LTE category-four devices. A category-four UE cannot handle more than two layers of spatial multiplexing and that includes DL CoMP [15]. These UEs are moving at an average speed of 5 km/h and use ZF equalization.

## III. KEY ASSUMPTIONS

Below I list the key assumptions for this algorithm. These assumptions still keep system model realistic.

- The computed DL SINR target threshold will be invalidated after  $\delta_{\text{CoMP}}$  *transmit time intervals* (TTIs) with the transmit function being with respect to the base station (i.e., DL).
- DL CoMP is enabled for the entire DL CoMP cooperating set at once. Either all UEs ( $Q$ ) in this TTI get DL CoMP or none. This is the case for both the baseline and the proposed method.
- The channel is a  $2 \times 2$  distributed MIMO channel. This implies that only up to one macro base station and one low power node are engaged with one UE at any given time for a DL CoMP transmission.
- All channels are independent of the transmitted signal (e.g., no channel-dependent power control) in alignment with 3gpp standards [3].
- The simulator does not have an option for pico [13], so I used the existing femto configuration and changed the transmit power and noise figure to resemble a pico.

## IV. PROBLEM

I break down the problem into two components: radio environment and machine learning.

### A. Radio Environment

The list of the proposed radio environment parameters are listed in Table I. For the  $i$ -th UE at the  $k$ -th transmit interval,

TABLE I: Radio environment parameters

Parameter	Value
Bandwidth	10 MHz
Downlink Center Frequency	2100 MHz (Band I)
Channel model type <sup>†</sup>	EPA5
LTE cyclic prefix	normal
Scheduling algorithm	Proportional Fair
Equalizer	Zero Forcing
Propagation model	COST231
Propagation environment	urban
Number of UEs per cell	10
UE device category	LTE CAT-4
LPN (i.e., pico base station) power	37 dBm
LPN antenna height	10 m
LPN antenna model	omnidirectional
Macro site geometry	hexagonal
Macro base station power	46 dBm
Macro base station antenna height	25 m
Macro base station antenna electrical tilt	4°
Macro base station antenna model	Kathrein 742212 (X-pol)
Inter-site distance	100 m
Shadow fading margin standard deviation	8 dB
Shadow fading margin mean	0 dB
UE antenna gain	-1 dBi
BS noise figure	4 dB
UE noise figure	7 dB
UE height	1.5 m
UE average movement speed	5 km/h
Noise power density	-174 dBm/Hz

<sup>†</sup> i.e., the power delay profile.

the received signal model with frequency flat narrowband assumptions is given by [5], [16]:

$$\begin{aligned}
\mathbf{r}_i[k] = & \underbrace{\sqrt{\frac{GE_s}{N_T}} \mathbf{H}_i \mathbf{F}_i \mathbf{s}_i[k]}_{\text{own signal}} \\
& + \underbrace{\mathbf{H}_i \sum_{\substack{j=0 \\ j \neq i}}^Q \sqrt{\frac{G_j E_{s,j}}{N_{T,j}}} \mathbf{F}_j \mathbf{s}_j[k]}_{\text{intra-cellular interference}} \\
& + \underbrace{\mathbf{v}[k]}_{\text{noise}}, \\
k = & 0, \dots, \delta_{\text{CoMP}}; \quad i = 1, \dots, Q
\end{aligned} \tag{1}$$

where  $\mathbf{H}_i \in \mathbb{C}^{N_R \times N_T}$  is the normalized multivariate impulse response of a discrete-time system for user  $i$ , with  $N_R$  is the number of receive antennas and  $N_T$  is the number of transmit antennas.  $\mathbf{F}_i \in \mathbb{C}^{N_T \times N_s}$  is the precoder matrix obtained through *block diagonalization* (BD) with  $N_s \leq \min(N_R, N_T)$  being the number of spatially multiplexed data streams. The transmitted signal is  $\mathbf{s}_i[k]$ . The additive noise is  $\mathbf{v}[k]$  which is  $\sim \mathcal{N}_C(\mathbf{0}, \sigma_v^2 \mathbf{I}_{N_R})$ .  $\sigma_v^2$  is the noise power density at the receiver.  $G$  is the large-scale channel gain for the current user  $i$ ,  $E_s$  is the transmit energy per symbol. Finally, all quantities with a second index  $j$  are for the user  $j$ . The value of  $N_s$  could be either 1 or 2 depending on the CSIT feedback. The goal of BD precoding is to eliminate interference at each user due to the other users perfectly and in DL CoMP, BD is actually the joint transmission format [16].

Let us define  $\text{SNR}_i$  in linear scale (i.e., non-dB) as a direct estimate from the CQI reported by the UE  $i$ . For simulation purposes define  $\text{SNR}_i^{[k]}$  reported by the receiver to the CoMP measurement set at TTI  $k$  as [5]:

$$\text{SNR}_i^{[k]} \triangleq \frac{GP_s}{N_0 B} \frac{|\mathbf{H}_i \mathbf{F}_i|^2}{N_T} \tag{2}$$

where  $N_0$  is the noise power density measured at the UE receiver and  $B$  is the bandwidth of the transmission.  $P_s$  is the transmit power.

I shall treat cell-edge interference as Gaussian noise with the argument that we have many interferers at the cell edge thus changing  $\mathbf{v}[k]$  in Equation 1 into  $\mathbf{z}[k]$  which is now noise plus inter-cellular interference with the Gaussian distribution justified on the basis of the Central Limit Theorem thereby making  $\mathbf{z} \sim \mathcal{N}_C(\mathbf{0}, \mathbf{P}_z)$ .

With a group of interfering radio links  $N$  at the cell edge with an interfering received power of  $P_i$ , I can write the received  $\text{SINR}_i^{[k]}$  as:

$$\begin{aligned}
\text{SINR}_i^{[k]} & \triangleq \frac{GP_s}{N_0 B + \sum_{\substack{j=0 \\ j \neq i}}^N P_{z,j}} \frac{|\mathbf{H}_i \mathbf{F}_i|^2}{N_T} \\
& = \frac{GP_s}{N_0 B + \sum_{\substack{j=0 \\ j \neq i}}^N G_j P_{s,j}} \frac{|\mathbf{H}_i \mathbf{F}_i|^2}{N_T}
\end{aligned} \tag{3}$$

where  $P_{z,j}$  is the cell-edge interference due to cell  $j$ .

Standards do not require that the UE report its SINR [17], [7], and therefore a one-to-one relationship between  $\text{SINR}_i^{[k]}$  and CQI has been proposed for convenience [13], [18] treating the cell-edge interference as additive noise as mentioned earlier.

### B. Machine Learning

SVM is a supervised machine learning algorithm [19] which can analyze and classify data. It has been used in the implementation of this algorithm.

I define the learning features in a matrix  $\mathbf{X} \triangleq (\mathbf{x}_1, \mathbf{x}_2)$  as in Table II, collected from all the UEs in the CoMP coordinated set during the time frame of  $\delta_{\text{CoMP}}$ .

TABLE II: Proposed machine learning features  $\mathbf{X}$

$\mathbf{x}_1$	CQI reports
$\mathbf{x}_2$	RSRP measurement reports

I have chosen these features since the CoMP coordinated set base stations receive them as measurements from the UEs. That is, all communicating ends are aware of these quantities. All the learning features  $\mathbf{X}$  must be normalized. Normalization places the values of numeric attributes on the same scale and thus prevents features with extreme scales from biasing the solution [19].

Further, I augment the features by applying the feature expansion  $(\mathbf{x}_1, \mathbf{x}_2) \mapsto \phi(\mathbf{x}_1 - \mathbf{x}_2)$  thus writing the dual optimization problem of the SVM [19] as follows:

$$\begin{aligned}
\text{minimize:} & \quad \frac{1}{2} \boldsymbol{\lambda}^\top \mathbf{y} K(\mathbf{x}_1, \mathbf{x}_2) \mathbf{y}^\top \boldsymbol{\lambda} - \mathbf{1}^\top \boldsymbol{\lambda} \\
\text{subject to:} & \quad \boldsymbol{\lambda}^\top \mathbf{y} = 0 \\
& \quad 0 \leq \lambda_r \leq C, \quad r = 1, \dots, M
\end{aligned} \tag{4}$$

where  $M$  is the total number of reports generated by all the UEs during all the collection time for all the base stations in the cooperating set (i.e., the product of  $Q$ ,  $\delta_{\text{CoMP}}$  and the reporting frequency), and  $\boldsymbol{\lambda} \in \mathbb{R}^M$  a vector of the Lagrangian multipliers.  $C$  is a parameter to control overfitting. The element  $y_i \in \{0, 1\}$  is the supervisory label element in vector  $\mathbf{y}$ .  $K(\cdot, \cdot)$  is the SVM kernel defined as:

$$K(\mathbf{x}, \mathbf{x}') \triangleq \langle \phi(\mathbf{x}), \phi(\mathbf{x}') \rangle = \phi(\mathbf{x})^\top \phi(\mathbf{x}') \tag{5}$$

I will use the Gaussian *radial-basis function* (RBF) since the decision boundary is highly likely to be non-linear. RBF has the following kernel:

$$K(\mathbf{x}, \mathbf{x}') = \exp\left(-\frac{\|\mathbf{x} - \mathbf{x}'\|^2}{2\sigma^2}\right) \tag{6}$$

Standards specify target of 0.1 BLER for any *transport block* (TB) [3]. This value is called the *hybrid automated repeat request* (H-ARQ) target. BLER in the downlink is calculated once per codeword or TB at the base station and therefore it is convenient to define the supervisory signal labels as a function of DL BLER.

With features  $\mathbf{X}$  and supervisory signal labels  $\mathbf{y}$  being gathered at the CoMP cooperating set base stations, all what is left is for these base stations is to derive the target SINR<sub>*i*</sub><sup>[*k*]</sup> at which the DL CoMP algorithm will be triggered for this UE on the basis of the machine learning algorithm described. The data collected during ( $\delta_{\text{CoMP}}$ ) will be split 60-40 to a training set and a cross validation or testing set.

## V. ALGORITHM

The novel algorithm to trigger DL CoMP in the cooperating set is shown in Algorithm 1.

## VI. SIMULATION RESULTS

With reproducibility of results in mind, I used the Vienna LTE-A Downlink System Level Simulator [13]. MATLAB requires that The Mapping Toolbox<sup>TM</sup> and Statistics and Machine Learning Toolbox<sup>TM</sup> be installed. With a simulation of  $Q = 60$  UEs (ten UEs per cell and six cells in total: 3 macro and 3 pico),  $\delta_{\text{CoMP}} = 3$  TTIs, and a simulation time of 60 TTIs, Tables III, IV and V outline the *key performance indicators* (KPIs) and show that Scenario 2 has a better performance in all KPIs. The calculated SVM misclassification error  $m$  was between 1.2% and 4.7%.

In Fig. 2, it is clear that the Static DL CoMP algorithm




Fig. 2: DL CoMP being enabled (state = 1) and disabled (state = 0) for both schemes and same TTIs

disabled CoMP in the coordinated set for a typical user between the 8<sup>th</sup> and 11<sup>th</sup> TTI. The Improved DL CoMP algorithm on the other hand took a different approach, with disabling CoMP not only in the 10<sup>th</sup> TTI as in static DL CoMP baseline, but also enabling and disabling DL CoMP in other time instances during the simulation. I assert that the reason for this is simply because the DL BLER failed to meet the H-ARQ target during these TTIs.

TABLE III: KPI comparison between schemes

n	Scenario	UE Throughput [Mbps]			Avg. Cell Thpt.
		Peak	Avg	Edge	
1	Static CoMP <sup>†</sup>	2.86	1.30	0.10	12.99
2	Improved CoMP	<b>3.24</b>	<b>1.38</b>	<b>0.14</b>	<b>13.82</b>

<sup>†</sup> Baseline DL CoMP enabling trigger at DL SINR<sub>min</sub> of 5 dB.

---

## Algorithm 1 Improved DL CoMP in Heterogeneous Networks

---

**Input:** Improved DL CoMP feature ON, current triggering DL SINR, UE  $i$  CQI and UE  $i$  RSRP.

**Output:** Triggering DL SINR threshold for UE  $i$

```

1: repeat
2:    $T \leftarrow \delta_{\text{CoMP}}$    {collection period of features}
3:    $Q \leftarrow Q$        {number of UEs in coordinated set}
4:   for  $k \leftarrow 1$  to  $T$  do
5:     for  $j \leftarrow 1$  to  $Q$ ,  $j \neq i$  do
6:       Store measurements reported by all UEs  $j$  during all times  $k$ :
7:          $[\tilde{x}_1]_{(j,k)} \leftarrow$  CQI
8:          $[\tilde{x}_2]_{(j,k)} \leftarrow$  RSRP or simulated distance
9:          $[\tilde{x}_3]_{(j,k)} \leftarrow$  DL BLER
10:      if ( $[\tilde{x}_3]_{(j,k)} \leq 0.1$ ) then
11:         $[\tilde{y}]_{(j,k)} \leftarrow 1$ 
12:      else
13:         $[\tilde{y}]_{(j,k)} \leftarrow 0$ 
14:      end if
15:    end for
16:  end for
17: Vectorize learning features and supervisory labels:
18:    $\mathbf{x}_1 \leftarrow \text{vec}(\tilde{\mathbf{x}}_1)$ 
19:    $\mathbf{x}_2 \leftarrow \text{vec}(\tilde{\mathbf{x}}_2)$ 
20:   Impute all elements in  $\mathbf{x}_1, \mathbf{x}_2$  where a feature has  $\pm\infty$  value.
21:   Normalize  $\mathbf{x}_1, \mathbf{x}_2$ .
22:    $\mathbf{y} \leftarrow \text{vec}(\tilde{\mathbf{y}})$ 
23:    $\mathbf{X} \leftarrow [\mathbf{x}_1, \mathbf{x}_2]$ 
24:   Split  $[\mathbf{X}|\mathbf{y}]$  60-40 to  $[\mathbf{X}_{\text{training}}|\mathbf{y}_{\text{training}}]$  and  $[\mathbf{X}_{\text{validation}}|\mathbf{y}_{\text{validation}}]$ 
25:   Perform SVM on  $\mathbf{X}_{\text{training}}, \mathbf{y}_{\text{training}}$  using RBF kernel and  $[\tilde{x}_1]_{(i,k)}, [\tilde{x}_2]_{(i,k)}, [\tilde{x}_3]_{(i,k)}$  to find  $[\hat{y}]_{(i,k)}$ .
26:   Validate model with  $\mathbf{X}_{\text{validation}}$  and obtain  $\hat{\mathbf{y}}$ .
27:   Compute  $m = \|\mathbf{y}_{\text{validation}} - \hat{\mathbf{y}}\|_2^2$ .
28:   if ( $m > \varepsilon$ ) then
29:     Use operator-entered DL SINRtarget
30:   return
31: else
32:   if  $\hat{y}_{(i,T+1)}$  for  $([x_1]_{(i,T+1)}, [x_2]_{(i,T+1)}) > 0.9$  then
33:     Enable DL CoMP in this TTI for UE  $i$ : DL SINRtarget[T+1]( $i$ )  $\leftarrow -\infty$ 
34:   else
35:     Disable DL CoMP: DL SINRtarget[T+1]( $i$ )  $\leftarrow +\infty$ 
36:   end if
37: end if
38:   Use this DL SINRtarget[T+1]( $i$ ) for  $\delta_{\text{CoMP}} - 1$  more TTIs
39: until simulation time ends
40: return

```

---

TABLE IV: Link-level metrics comparison between schemes

n	Scenario	Average		
		DL BLER	DL SINR [dB] <sup>*</sup>	RSRP [dBm]
1	Static CoMP <sup>†</sup>	15.39%	7.15	-65.98
2	Improved CoMP	<b>15.31%</b>	<b>7.45</b>	-65.98

<sup>\*</sup> SINR measured per PRBs on a which transport block is scheduled.

<sup>†</sup> Baseline DL CoMP enabling trigger at DL SINR<sub>min</sub> of 5 dB.

TABLE V: Spectral efficiency comparison between schemes

n	Scenario	Average Spectral Efficiency [bits/channel use]	
		LPN only	Cluster
1	Static CoMP <sup>†</sup>	2.71	1.88
2	Improved CoMP	<b>2.78</b>	<b>1.92</b>

<sup>†</sup> Baseline DL CoMP enabling trigger at DL SINR<sub>min</sub> of 5 dB.

Notwithstanding the slight improvement in the average DL SINR and the average BLER as shown in Table IV, I see an improvement in the average UE throughput distribution with 40% and 13.29% gain in the cell edge and peak respectively as in Table III<sup>‡</sup>.




Fig. 3: DL SINR empirical CDFs for Static and Improved CoMP

## VII. CONCLUSIONS

As I was able to improve the SINR distribution on the downlink and achieve higher data rates, the average transmit power requirement can be reduced to meet the target SINR required to achieve the data rate, therefore reducing the base station power requirement and the CO<sub>2</sub> emissions. This constitutes the essence of *Green Cellular Networks*.

A way forward is to examine other features besides  $x_1^2$ ,  $x_1x_2$ , and  $x_2^2$  which are due to the RBF kernel.

With operators desiring to cut operational expenditure, further radio access features can be implemented with machine learning, effectively minimizing the need of continuous tuning of parameters. Optimizing handover thresholds is a good candidate for research to further improve the capabilities of *self-optimizing networks* (SON) which the author and others worked on [20]. With the adoption of *Internet of Things*, devices can also reveal their use capabilities creating different thresholds for different device types.

<sup>‡</sup>The slight improvement in the average DL BLER must be studied further once available in the simulator (e.g., CDF distribution before and after as in Fig. 3). I expect to see more lower BLER samples.

## ACKNOWLEDGMENT

The author thanks Prof. Brian L. Evans for his encouragement, advice, and support; Prof. Robert W. Heath Jr. for his help in securing the simulator; Mr. Pradeep C. Cruz for his support and guidance; and the reviewers for their feedback.

## REFERENCES

- [1] 3GPP, "Coordinated Multi-Point Operation for LTE," 3rd Generation Partnership Project (3GPP), TR 36.819, Sep. 2013. [Online]. Available: <http://www.3gpp.org/dynareport/36819.htm>
- [2] "Ericsson Mobility Report," February 2016. [Online]. Available: <http://www.ericsson.com/res/docs/2016/mobility-report/ericsson-mobility-report-feb-2016-interim.pdf>
- [3] 3GPP, "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures," 3rd Generation Partnership Project (3GPP), TS 36.213, Dec. 2008. [Online]. Available: <http://www.3gpp.org/dynareport/36213.htm>
- [4] J. Acharya, L. Gao, and S. Gaur, *Heterogeneous Networks in LTE-Advanced*, 1st ed. Wiley, 2014.
- [5] R. W. Heath Jr. and A. Lozano, in *Class notes for EE381S*, 2016.
- [6] A. Goldsmith, *Wireless Communications*. New York, USA: Cambridge, 2009.
- [7] 3GPP, "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification," 3rd Generation Partnership Project (3GPP), TS 36.331, Sep. 2015. [Online]. Available: <http://www.3gpp.org/dynareport/36331.htm>
- [8] K. Huq, S. Mumtaz, J. Bachmatiuk, J. Rodriguez, X. Wang, and R. Aguiar, "Green HetNet CoMP: Energy Efficiency Analysis and Optimization," *IEEE Transactions on Vehicular Technology*, vol. 64, pp. 4670–4683, 2015.
- [9] G. Nigam, P. Minero, and M. Haenggi, "Coordinated multipoint joint transmission in heterogeneous networks," *IEEE Transactions on Communications*, vol. 62, no. 11, pp. 4134–4146, Nov 2014.
- [10] P. Xia, C. H. Liu, and J. G. Andrews, "Downlink coordinated multipoint with overhead modeling in heterogeneous cellular networks," *IEEE Transactions on Wireless Communications*, vol. 12, no. 8, pp. 4025–4037, August 2013.
- [11] H. Zhang, C. Jiang, J. Cheng, and V. C. Leung, "Cooperative Interference Mitigation and Handover Management for Heterogeneous Cloud Small Cell Networks," 2015. [Online]. Available: <http://arxiv.org/pdf/1504.08076.pdf>
- [12] S. Wesemann and G. Fettweis, "Decentralized Formation of Uplink CoMP Clusters Based on Affinity Propagation," *International Symposium on Wireless Communication Systems (ISWCS)*, pp. 850–854, 2012.
- [13] M. Taranetz, T. Blazek, T. Kropfreiter, M. K. Müller, S. Schwarz, and M. Rupp, "Runtime Precoding: Enabling Multipoint Transmission in LTE-Advanced System Level Simulations," *IEEE Access*, vol. 3, pp. 725–736, Jun. 2015.
- [14] T. L. Marzetta, "Noncooperative Cellular Wireless with Unlimited Numbers of Base Station Antennas," *IEEE Transactions on Wireless Communications*, vol. 9, no. 11, pp. 3590–3600, November 2010.
- [15] 3GPP, "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) radio access capabilities," 3rd Generation Partnership Project (3GPP), TS 36.306, 2015. [Online]. Available: <http://www.3gpp.org/dynareport/36306.htm>
- [16] M. Rupp, S. Schwarz, and M. Taranetz, *The Vienna LTE-Advanced Simulators*. Vienna, Austria: Springer, 2016.
- [17] 3GPP, "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer measurements," 3rd Generation Partnership Project (3GPP), TS 36.214, Dec. 2015. [Online]. Available: <http://www.3gpp.org/dynareport/36214.htm>
- [18] C. Mehlführer, M. Wrulich, J. C. Ikuno, D. Bosanska, and M. Rupp, "SIMULATING THE LONG TERM EVOLUTION PHYSICAL LAYER." Glasgow, Scotland, Aug. 2009. [Online]. Available: [https://publik.tuwien.ac.at/files/PubDat\\_175708.pdf](https://publik.tuwien.ac.at/files/PubDat_175708.pdf)
- [19] Andrew Ng. CS229 Notes. [Online]. Available: <http://cs229.stanford.edu/materials.html>
- [20] I. da Silva, Y. Wang, F. B. Mismar, and W. Su, "Event-based performance monitoring for inter-system cell reselection: A SON enabler," in *2012 International Symposium on Wireless Communication Systems (ISWCS)*, August 2012, pp. 6–10.