

A General Framework for Covariance Matrix Optimization in MIMO Systems

Chengwen Xing, Yindi Jing, Shuai Wang, Jiaheng Wang, and Jianping An

Abstract

For multi-input multi-output (MIMO) systems, many transceiver design problems involve the optimization of the covariance matrices of the transmitted signals. Karush-Kuhn-Tucker (KKT) conditions based derivations are the most popular method, and many derivations and results have been reported for different scenarios of MIMO systems. We propose a unified framework in formulating the KKT conditions for general MIMO systems. Based on this framework, the optimal water-filling structure of the transmission covariance matrices are derived rigorously, which is applicable to a wide range of MIMO systems. Our results show that for MIMO systems with various power constraint formulations and objective functions, both the derivation logics and water-filling structures for the optimal covariance matrix solutions are fundamentally the same. Thus, our unified framework and solution reveal the underlying relationships among the different water-filling structures of the covariance matrices. Furthermore, our results provide new solutions to the covariance matrix optimization of many complicated MIMO systems with multiple users and imperfect channel state information (CSI) which were unknown before.

I. INTRODUCTION

This is an amazing era for wireless technologies with many novel and revolutionary concepts coming forth such as cloud computing, smart city, and green communications, [1]–[8]. These unprecedented concepts demonstrate the demands and the desires for innovation in the wireless technology developments. In order to realize these goals, powerful physical layer technologies

C. Xing, S. Wang, and J. An are with School of Information and Electronics, Beijing Institute of technology, Beijing 100081, China (e-mail: chengwenxing@ieee.org, swang@bit.edu.cn, and an@bit.edu.cn).

Y. Jing is with the Department of Electrical and Computer Engineering, University of Alberta, Edmonton, AB T6G 2V4, Canada (e-mail: yindi@ualberta.ca).

J. Wang is with the National Mobile Communications Research Laboratory, Southeast University, Nanjing, China (e-mail: jhwang@seu.edu.cn).

are expected, which are characterized by high power efficiency and high spectrum efficiency. Multi-input multi-output (MIMO) technologies are taken as one of the most important ingredients of a variety of complicated wireless systems [9]–[20]. From the optimization viewpoint, many design problems for MIMO systems aim to optimize the covariance matrix of the transmitted signals [9], [17].

Interestingly, for different performance metrics and different power constraints, the optimal transmission covariance matrices always have water-filling structures [10]–[20]. Such structures can greatly simplify the considered optimization problems and reveal the underlying physical meanings meanwhile. Many variants of water-filling structures have been discovered, e.g., general water-filling [21], polite water-filling [19], cluster water-filling [22], matrix-field water-filling [18], and cave water-filling [23]. Along with the evolvments and developments of wireless communication systems, the number of the papers on MIMO optimization with water-filling structures in IEEE database is surging. Up to date, a large volume of elegant results have been published for various MIMO scenarios, including single-user (SU) MIMO systems [11], multi-user (MU) MIMO systems [24], distributed MIMO networks [14], [25], and multi-hop amplify-and-forward MIMO relaying networks [26], [27]. Moreover, it has been shown that even for some transceiver optimizations with channel state information (CSI) errors, water-filling structures also hold [27]–[29]. It is desired to reconsider the large volume of closely related existing works, reveal the underlying fundamental connections of them, and propose a unified framework.

A natural question that arises is how these water-filling structures are derived. Generally speaking, there are three kinds of methods. The first one is the Karush-Kuhn-Tucker (KKT)-condition-based method [10], [28], [29]. Under some mild conditions, KKT conditions are necessary conditions for the optimal solutions [30]. Based on this fact, common properties derived from KKT conditions are the properties of the optimal solutions. The second one is based on matrix inequalities [15], [16] or majorization theory [11], [27]. Compared with the first kind of method, majorization theory is less popular from the traditional communication theoretical perspective. Roughly speaking, it can reveal the inequality relationships between the diagonal elements and eigenvalues of a matrix [31]. The third one is called matrix-monotonic optimization which exploits the monotonicity in the field of positive semi-definite matrices [26], [32], [33].

The matrix-monotonic optimization framework has very strict limitations on the objective function and constraints of the optimization problems [26], [32], [33]. Matrix inequality based

methods are usually powerful and rigorous. When the objective functions are Schur-convex or Schur-concave functions of the diagonal elements of the mean-squared-error (MSE) matrix, the optimal structure of the matrix variables can be derived [11], [27]. Unfortunately, this kind of methods also suffers from many strict limitations in its applications [34]. Generally speaking, these two kinds of methods are only applicable in single-source and single-destination systems. The KKT-condition-based method is the most widely used and has a straightforward logic. Based on complex matrix derivatives, the KKT conditions of the optimization problems are derived first, from which the structures of the optimal solutions can be obtained. It is not limited by the format of the covariance matrix e.g., single user or multiple users, nor by the format of the transmit power constraints. Thus this kind of methods has the widest range of applications.

In existing literature, the detailed derivation procedures for water-filling solutions from KKT conditions can seem to be largely different with each other [10], [28], [35]. In many works, it was argued that the derivation procedures are distinctive due to their specific system models and optimization problems, thus the works are significantly different from others. In our opinion, the fundamental theories and technologies for physical layer designs do not evolve as fast as or look as versatile as the communication system models. Due to the common root of all KKT-condition-based methods, we think that the many seemingly different mathematical derivations can be unified into a single framework when the fundamental nature is understood. This is the motivation of this work. In this paper, we investigate the most widely used KKT-condition-based method for the transmission covariance matrix optimization in MIMO systems. A unified framework is proposed for the derivations of the water-filling structure. The framework provides general modeling, formulation, and methodology for MIMO transmission covariance optimization that can lead to new discoveries and solve new problems.

The main contributions of our work are two-fold. The first is the derivations of the water-filling structure for the transmission covariance matrix based on KKT conditions. A fundamental and general solution is given based on which water-filling structures can be derived for a wide range of MIMO systems. We discover that the water-filling structures of these different MIMO systems are in nature closely related with each other. Second, based on the proposed solutions, we derive the water-filling structured transmission covariance matrices for many SU MIMO and MU MIMO systems under different objective functions, power constraints, and CSI assumptions, specifically,

- the capacity maximization for SU MIMO systems under weighted power constraint and

perfect CSI,

- the MSE minimization for SU MIMO systems under weighted power constraint and perfect CSI,
- the capacity maximization for SU MIMO systems under multiple weighted power constraints and perfect CSI,
- the MSE minimization for SU MIMO systems under multiple weighted power constraints and perfect CSI,
- the capacity maximization for SU MIMO systems with total power constraint and imperfect CSI,
- the MSE minimization for SU MIMO systems under weighted power constraint and imperfect CSI,
- the capacity maximization for SU MIMO systems under multiple weighted power constraints and CSI error,
- the MSE minimization for SU MIMO systems under multiple weighted power constraints and imperfect CSI,
- the capacity maximization for MU MIMO uplink under multiple weighted power constraints and perfect CSI,
- the capacity maximization for MU MIMO uplink under multiple weighted power constraints and imperfect CSI,
- the capacity maximization for MU MIMO downlink under multiple weighted power constraints and perfect CSI,
- the capacity maximization for MU MIMO downlink under multiple weighted power constraints and imperfect CSI error,
- the capacity maximization for network MIMO systems under multiple weighted power constraints and imperfect CSI.

Many of the proposed solutions were unknown in existing works. For example, to our best knowledge, the water-filling solutions for MIMO systems under multiple weighted power constraints and imperfect CSI are firstly revealed in this work.

Notation: Throughout this paper, without other specifications, the following notation and symbols are used. For matrix operations, the notation $(\cdot)^T$ and $(\cdot)^H$ are for the transpose and Hermitian transpose, respectively. The symbol $\mathbb{E}\{\cdot\}$ represents the expectation operation. $\mathbf{A}^{\frac{1}{2}}$ denotes the Hermitian square root of the positive semi-definite matrix \mathbf{A} . The symbol a^+ means $\max\{0, a\}$.

Proof: By left and right multiplying $\mathbf{Q}^{1/2}$ to the second equation in (1), we have the following result

$$\begin{aligned} & \mathbf{Q}^{1/2} \mathbf{H}^H \mathbf{\Pi}^{-1/2} (\mathbf{I} + \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{Q} \mathbf{H}^H \mathbf{\Pi}^{-1/2})^{-K} \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{Q}^{1/2} \\ &= \mu \mathbf{Q}^{1/2} \mathbf{\Phi} \mathbf{Q}^{1/2}. \end{aligned} \quad (4)$$

By defining the following new matrix

$$\mathbf{A} = \mathbf{\Phi}^{1/2} \mathbf{Q}^{1/2}, \quad (5)$$

Equation (4) can be rewritten as

$$\begin{aligned} & \mathbf{A}^H \mathbf{\Phi}^{-1/2} \mathbf{H}^H \mathbf{\Pi}^{-1/2} (\mathbf{I} + \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2} \mathbf{A} \\ & \times \mathbf{A}^H \mathbf{\Phi}^{-1/2} \mathbf{H}^H \mathbf{\Pi}^{-1/2})^{-K} \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2} \mathbf{A} = \mu \mathbf{A}^H \mathbf{A}. \end{aligned} \quad (6)$$

From the SVDs of \mathbf{A} and $\mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2} \mathbf{A}$, (6) implies that $\mathbf{A}^H \mathbf{A}$ and $\mathbf{A}^H \mathbf{\Phi}^{-1/2} \mathbf{H}^H \mathbf{\Pi}^{-1} \mathbf{H} \mathbf{\Phi}^{-1/2} \mathbf{A}$ have the same eigen-matrix. Therefore, It can be concluded that the left SVD unitary matrix of \mathbf{A} equals the right SVD unitary matrix of $\mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2}$.

Moreover, because $\mathbf{Q}^{1/2} \mathbf{\Psi} \mathbf{Q}^{1/2} = \mathbf{0}$, we can conclude that $\mathbf{A}^H \mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2} \mathbf{A} = \mathbf{0}$. It means that the left SVD unitary matrix of \mathbf{A} equals the eigen-matrix of $\mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2}$. In other words, the right SVD unitary matrix of $\mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2}$ equals the eigen-matrix matrix of $\mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2}$.

The first equation in (1) is equivalent to the following one

$$\begin{aligned} & \mathbf{\Phi}^{-1/2} \mathbf{H}^H \mathbf{\Pi}^{-1/2} (\mathbf{I} + \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2} \mathbf{A} \mathbf{A}^H \mathbf{\Phi}^{-1/2} \\ & \times \mathbf{H}^H \mathbf{\Pi}^{-1/2})^{-K} \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2} = \mu \mathbf{I} - \mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2}. \end{aligned} \quad (7)$$

With the following definitions

$$\begin{aligned} \sigma_i(\mathbf{A}) &= a_i, \quad \sigma_i(\mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{\Phi}^{-1/2}) = h_i, \\ \lambda_i(\mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2}) &= \psi_i, \end{aligned} \quad (8)$$

Equation (7) becomes

$$\frac{h_i^2}{(1 + a_i^2 h_i^2)^K} = \mu - \psi_i, \quad (9)$$

based on which a_i^2 's are derived to be

$$a_i^2 = \frac{(h_i^2)^{1/K}}{h_i^2} \left(\frac{1}{(\mu - \psi_i)^{1/K}} - \frac{1}{(h_i^2)^{1/K}} \right). \quad (10)$$

Actually, ψ_i can be removed. As $\mathbf{A}^H \mathbf{\Phi}^{-1/2} \mathbf{\Psi} \mathbf{\Phi}^{-1/2} \mathbf{A} = \mathbf{0}$ and together with the inequalities $\mu > 0$ and $\psi_i \geq 0$, it can be concluded that

$$\psi_i = 0 \quad \text{when } a_i^2 \geq 0 \quad (11)$$

$$\psi_i > 0 \quad \text{when } a_i^2 = 0, \quad (12)$$

based on which we can conclude that

$$\psi_i = 0 \quad \text{when } a_i^2 = \frac{(h_i^2)^{1/K}}{h_i^2} \left(\frac{1}{\mu^{1/K}} - \frac{1}{(h_i^2)^{1/K}} \right) \quad (13)$$

$$\psi_i > 0 \quad \text{when } a_i^2 = \frac{(h_i^2)^{1/K}}{h_i^2} \left(\frac{1}{(\mu - \psi_i)^{1/K}} - \frac{1}{(h_i^2)^{1/K}} \right) = 0. \quad (14)$$

To combine the previous two equations into a single one, the following equality is achieved

$$a_i^2 = \frac{(h_i^2)^{1/K}}{h_i^2} \left(\frac{1}{\mu^{1/K}} - \frac{1}{(h_i^2)^{1/K}} \right)^+. \quad (15)$$

Finally, it can be concluded that

$$\begin{aligned} \mathbf{Q} = & \mathbf{\Phi}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1/K} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{\frac{1}{K}-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ \\ & \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \mathbf{\Phi}^{-1/2}. \end{aligned} \quad (16)$$

When applying Theorem 1 to KKT-condition-based transmission covariance matrix optimization for MIMO systems, the matrix \mathbf{Q} corresponds to the covariance matrix to be optimized, \mathbf{H} corresponds to the channel matrix, $\mathbf{\Phi}$ corresponds to the power weight, $\mathbf{\Pi}$ corresponds to the noise covariance matrix, while $\mathbf{\Psi}$ corresponds to the Lagrange multipliers. It is noteworthy that the formulation and result of Theorem 1 are general and independent of specific MIMO system setups, including the detailed objective functions, power constraints, signal models, and channel assumptions. Moreover, in Theorem 1, the matrices $\mathbf{\Pi}$ and $\mathbf{\Phi}$ are not limited to be constant but can be functions of \mathbf{Q} . This is because there are no limitations on $\mathbf{\Pi}$ and $\mathbf{\Phi}$ in the mathematically rigorous proof. The conclusion given in (2) is a mathematical reformulation of the Equations in (1).

Next, we would like to discuss the main difference between our derivations and existing ones as water-filling structure derivations have been extensively studied. To our best knowledge, the logics of existing derivation methods can be classified into two categories. The first is based on matrix inequalities, e.g., [9], [11], [34]. However, it is usually very difficult to guarantee that the extreme values of the matrix inequalities can be achieved due to the variations in the objectives or constraints of the optimization problems [34]. For example, in Telatar's paper

[9], the matrix inequality $\log|\mathbf{I} + \mathbf{H}\mathbf{Q}\mathbf{H}^H| \leq \sum_i \log(1 + \lambda_i(\mathbf{H}^H\mathbf{H})\lambda_i(\mathbf{Q}))$ was used to derive the water-filling structure of the optimal solutions. If the sum power constraint $\text{Tr}(\mathbf{Q}) \leq P$ is replaced by $[\mathbf{Q}]_{i,i} \leq P_i$, the equality cannot be achieved [34]. In Section III, we will show that this problem can be overcome by using our method in Theorem 1, thanks to the fact that in Theorem 1, $\mathbf{\Pi}$ and $\mathbf{\Phi}$ can be functions of \mathbf{Q} . Thus, compared with existing works, our conclusion is more general.

The second category of derivation method is purely based on KKT conditions, which consisting of two phases. In the first phase, the argument is used that when the production of two matrices $\mathbf{\Lambda}_1\mathbf{\Lambda}_2$ is a Hermitian matrix and $\mathbf{\Lambda}_1$ is a diagonal matrix, $\mathbf{\Lambda}_2$ is a diagonal matrix. However if some diagonal elements of $\mathbf{\Lambda}_1$ are zeros, this claim does not hold. To avoid this problem, in some existing works, it is usually assumed that \mathbf{H} is full rank [35]. Different from existing works, Theorem 1 does not rely on this argument and there is no limitation on the rank of \mathbf{H} .

In the second phase of the existing KKT-condition-based derivation method [10], [28], the diagonalizable structure is used to reduce the KKT conditions to equations that involve only diagonal matrices, then to solve the optimal covariance matrix from the reduced equations. As the diagonal elements are nonnegative, the operation “+” is introduced. In Theorem 1, the operation “+” appears in the solution via rigorous mathematical derivation, where the symbol “+” is introduced for the notational simplicity. While in many applications, the insights of this solution can be explained by the physical meaning that the transmission power cannot be negative, the physical meaning cannot be used for the derivation of the result. Some existing derivations use the argument that the symbol “+” comes from the fact that \mathbf{Q} is positive semi-definite and then the negative eigenvalues must be set to be zeros. This argument may be incorrect in some applications. To see this, we can consider a positive semidefinite matrix $\mathbf{\Phi}$. Generally speaking,

$$\begin{aligned} & \mathbf{\Phi}^{-1/2}[\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\mu^{-1/K} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{\frac{1}{K}-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \\ & \quad \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \mathbf{\Phi}^{-1/2} \\ & \neq \left[\mathbf{\Phi}^{-1/2}[\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\mu^{-1/K} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{\frac{1}{K}-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2} \right) \right. \\ & \quad \left. \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \mathbf{\Phi}^{-1/2} \right]^+, \end{aligned} \quad (17)$$

where $(\mathbf{A})^+$ stands for the matrix obtained by replaying the negative eigenvalues of \mathbf{A} by zeros. The equality holds only when $\mathbf{\Phi}$ is proportional to an identity matrix.

Moreover, in some existing works, \mathbf{Q} is replaced by $\mathbf{F}\mathbf{F}^H$ in the derivation. Then the following KKT condition is achieved

$$\begin{aligned} \mathbf{H}^H \mathbf{\Pi}^{-1/2} (\mathbf{I} + \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{F} \mathbf{F}^H \mathbf{H}^H \mathbf{\Pi}^{-1/2})^{-1} \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{F} \\ = \mu \mathbf{\Phi} \mathbf{F}. \end{aligned} \quad (18)$$

In this case, as revealed in [34], due to the turning-off effect, the water-filling structure cannot be achieved. To clarify this, a brief discussion is given as follows. First, Equation (18) is not equivalent to the following one:

$$\mathbf{H}^H \mathbf{\Pi}^{-1/2} (\mathbf{I} + \mathbf{\Pi}^{-1/2} \mathbf{H} \mathbf{F} \mathbf{F}^H \mathbf{H}^H \mathbf{\Pi}^{-1/2})^{-1} \mathbf{\Pi}^{-1/2} \mathbf{H} = \mu \mathbf{\Phi}, \quad (19)$$

as the right inverse of \mathbf{F} may not exist. Furthermore, (18) is not equivalent to (1) because of the lack of $\mathbf{\Psi}$. As discussed in [34], any eigen-channel can be turned off (allocated zero power) and (18) can still be satisfied. This fact is referred to as the “turning-off effect” and because of it, Theorem 1 cannot be achieved based on (18).

Based on the KKT conditions (which are necessary for the corresponding convex or nonconvex optimization problem), Theorem 1 reveals that all solutions of \mathbf{Q} satisfying the two mathematical equations in (1) have the structure given by (3). The fundamental conclusion in Theorem 1 has the following properties:

- It is independent of whether the considered optimization problem is convex.
- It is only related with the two equations in (1), which compose a partial set of the KKT conditions, instead of the full set.
- It applies when the involved parameters are constants or functions of the variable.
- It provides a common structure of the solutions satisfying the KKT conditions.

In the following four sections, we use the result in Theorem 1, to derive the optimal water-filling structures for the transmission covariance matrices of MIMO systems with different objective functions, power constraints, and CSI assumptions. A diagram is provided as Fig. 1 to show the organization of the different scenarios, their interconnections, and our new contributions. Generally, we investigate three kinds of MIMO systems: SU MIMO systems, MU MIMO systems, and network MIMO systems.

In SU MIMO systems, first we investigate the capacity maximization and MSE minimization under a weighted power constraints and perfect CSI. In existing works, these problems have been solved via variable substitutions. Our scheme is different and relies on Theorem 1 and the

new approach provides clear understandings on the solution structures. In addition, this work finds the optimal structures for the corresponding optimization problems under imperfect CSI with Kronecker structured channel errors. For systems with transmit or receive correlation only, the optimal solutions are derived in exact closed-forms.

For MU MIMO systems, both uplink and downlink are considered for capacity maximization with perfect CSI and imperfect CSI under multiple weighted power constraints. The optimization problems are nonconvex for systems with imperfect CSI and both transmit and receive correlations. Based on Theorem 1, the optimal structures of the transmission covariance matrix are derived, from which we can found suboptimal yet low complexity algorithms with satisfactory performance. For the uplink capacity maximization with imperfect CSI and receive correlation only, the optimal solution is derived in closed-form.

Finally, the most general MIMO networks are investigated, in which multiple nodes communicate with multiple destinations with arbitrary network topologies and imperfect CSI. From Theorem 1, conditions on the optimal covariance matrix are derived in a recursive format, which can lead to low-complexity suboptimal solutions and work as a benchmark algorithm for many complicated MIMO systems.

Remark 1: Taking the transmission covariance matrices as optimization variables is a widely adopted logic for MIMO optimizations [36]–[38]. For MSE minimization, when a linear precoding matrix is adopted at the source, there may exist a constraint on the rank of the covariance matrix when the number of data streams is smaller than that of the transmit antennas. Unfortunately, this constraint is nonconvex and rank-relaxation is often needed in solving the optimization. On the other hand, for capacity maximization, there is no rank constraint since the number of information streams is not limited by the antenna number. Orthogonality between different data streams can be realized via certain coding strategies in addition to the spatial diversity provided by the antennas [37].

III. TRANSMISSION COVARIANCE MATRIX OPTIMIZATION IN SU MIMO SYSTEMS WITH PERFECT CSI

This section is on the applications of Theorem 1 in the transmission covariance matrix optimization of SU MIMO systems with perfect CSI. It is organized into two parts, one for the weighted sum power constraint and the other for multiple weighted power constraints. In each part, both capacity maximization and MSE minimization are considered.




Fig. 1. A summary diagram for the studied MIMO design problems.

In SU MIMO systems, there is one source and one destination both are equipped with multiple antennas. The signal model is

$$\mathbf{y} = \mathbf{H}\mathbf{F}\mathbf{s} + \mathbf{n}, \quad (20)$$

where \mathbf{y} is the received signal at the destination, \mathbf{H} is the channel matrix, and $\mathbf{F}\mathbf{s}$ is the transmitted signal whose covariance matrix is $\mathbf{Q} = \mathbf{F}\mathbf{F}^H$, and \mathbf{F} is the precoder. Finally, \mathbf{n} represents the additive noise at the destination and its covariance matrix is \mathbf{R}_n . The reason to investigate this simple model is two-fold. First, the optimal solutions for the related problems have been derived using other logics. Thus the cases can be used for verification. On the other hand, the results of these simple cases and their comparison with their counterparts for more complicated systems can help reveal the physical meanings and insights of the proposed solutions.

A. Single Weighted Sum Power Constraint

For MIMO systems, when the channel statistics for different antennas are similar, the sum power constraint is a very useful power model for transceiver optimization [18]. Weighted sum power constraint is a generalization of the sum power constraint, modeled as $\text{Tr}(\mathbf{W}\mathbf{Q}) \leq P$, where P is the maximum transmit power and \mathbf{W} is the weight matrix, which must be positive

definite. If \mathbf{W} has a zero eigenvalue, there is no power constraint at the corresponding direction, which is impractical.

The capacity maximization problem under the weighted sum power constraint is formulated as follows

$$\begin{aligned} \mathbf{P1:} \quad & \min_{\mathbf{Q}} \quad -\log |\mathbf{I} + \mathbf{R}_n^{-1} \mathbf{H} \mathbf{Q} \mathbf{H}^H| \\ \text{s.t.} \quad & \text{Tr}(\mathbf{W} \mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (21)$$

The KKT conditions of (21) can be derived to be

$$\begin{aligned} \mathbf{H}^H \mathbf{R}_n^{-1/2} (\mathbf{I} + \mathbf{R}_n^{-1/2} \mathbf{H} \mathbf{Q} \mathbf{H}^H \mathbf{R}_n^{-1/2})^{-1} \mathbf{R}_n^{-1/2} \mathbf{H} &= \mu \mathbf{W} - \boldsymbol{\Psi} \\ \mu \geq 0, \quad \mu(\text{Tr}(\mathbf{Q}) - P) &= 0, \quad \text{Tr}(\mathbf{Q} \boldsymbol{\Psi}) = 0, \quad \boldsymbol{\Psi} \succeq \mathbf{0} \\ \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} &\succeq \mathbf{0}, \end{aligned} \quad (22)$$

where μ is the Lagrangian multiplier corresponding to the constraint $\text{Tr}(\mathbf{Q}) \geq P$ and the positive semi-definite matrix $\boldsymbol{\Psi}$ is the Lagrangian multiplier corresponding to the constraint $\mathbf{Q} \succeq \mathbf{0}$. Based on Theorem 1 and the replacements $\mathbf{\Pi} = \mathbf{R}_n$ and $\mathbf{\Phi} = \mathbf{W}$, we have the following conclusion.

Conclusion 1: The optimal transmission covariance matrix for **P1** has the following water-filling structure

$$\begin{aligned} \mathbf{Q} &= \mathbf{W}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{1:N,1:N}^H \\ &\quad \times \mathbf{W}^{-1/2}, \end{aligned} \quad (23)$$

where the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\mathbf{R}_n^{-1/2} \mathbf{H} \mathbf{W}^{-1/2} = \mathbf{U}_{\mathcal{H}} \boldsymbol{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H. \quad (24)$$

Similarly, the MSE minimization problem can be formulated in the following form

$$\begin{aligned} \mathbf{P2:} \quad & \min_{\mathbf{Q}} \quad \text{Tr} \left[(\mathbf{I} + \mathbf{R}_n^{-1} \mathbf{H} \mathbf{Q} \mathbf{H}^H)^{-1} \right] \\ \text{s.t.} \quad & \text{Tr}(\mathbf{W} \mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (25)$$

The KKT conditions of **P2** can be derived to be

$$\begin{aligned} \mathbf{H}^H \mathbf{R}_n^{-1/2} (\mathbf{I} + \mathbf{R}_n^{-1/2} \mathbf{H} \mathbf{Q} \mathbf{H}^H \mathbf{R}_n^{-1/2})^{-2} \mathbf{R}_n^{-1/2} \mathbf{H} &= \mu \mathbf{W} - \boldsymbol{\Psi} \\ \mu \geq 0, \quad \mu(\text{Tr}(\mathbf{Q}) - P) &= 0, \quad \text{Tr}(\mathbf{Q} \boldsymbol{\Psi}) = 0, \quad \boldsymbol{\Psi} \succeq \mathbf{0} \\ \text{Tr}(\mathbf{Q}) \leq P \quad \mathbf{Q} &\succeq \mathbf{0}. \end{aligned} \quad (26)$$

Again based on Theorem 1 with the replacements $\mathbf{\Pi} = \mathbf{R}_n$ and $\mathbf{\Phi} = \mathbf{W}$, the following conclusion holds.

Conclusion 2: The optimal transmission covariance matrix for **P2** satisfies the following water-filling structure

$$\mathbf{Q} = \mathbf{W}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\mu^{-1/2} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \mathbf{W}^{-1/2}. \quad (27)$$

Comment 1: By comparing these two optimal solutions, it can be seen that the solutions for capacity maximization and MSE minimization have the same fundamental structure. The power constraint weighting matrix is reflected on the column correlation in (2). The solutions given by Conclusions 1 and 2 are exact and closed-form solutions. The Lagrange multiplier μ can be easily solved subsequently [11]. Comparing with existing works [9] and [10], in our work, the two problems are solved using the same framework and the derivation logic is much simpler and more rigorous. Specifically, different from [9] in which the derivations consist of two steps, i.e., deriving the diagonalizable structure based matrix inequality and deriving water-filling solution based on KKT conditions, our derivations need only one step to reach the optimal solution. Comparing with [10], our work does not suffer from the turning-off effect [41].

B. Multiple Weighted Power Constraints

As each antenna in an antenna array has its own amplifier, many researchers believe that per-antenna power constraints are more practical. This subsection is on the case with multiple weighted power constraints, which includes per-antenna power constraints as its special case. The constraint takes the following form

$$\text{Tr}(\mathbf{\Omega}_i \mathbf{Q}) \leq P_i, \quad (28)$$

where P_i is the i th power constraint and the positive semi-definite matrix $\mathbf{\Omega}_i$ is the corresponding weight matrix. When $\mathbf{\Omega}_i = \mathbf{b}_i \mathbf{b}_i^H$ with \mathbf{b}_i being the vector whose i th element is one and other elements are zeros, we have $\text{Tr}(\mathbf{\Omega}_i \mathbf{Q}) = \mathbf{b}_i^H \mathbf{Q} \mathbf{b}_i$. In this case, the power constraint in (28) becomes a per-antenna power constraint for the i th antenna.

The capacity maximization for SU MIMO systems under multiple weighted power constraints is formulated as follows

$$\begin{aligned} \mathbf{P3:} \quad & \min_{\mathbf{Q}} \quad -\log |\mathbf{I} + \mathbf{R}_n^{-1} \mathbf{H} \mathbf{Q} \mathbf{H}^H| \\ \text{s.t.} \quad & \text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i, \quad \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (29)$$

The corresponding KKT conditions are

$$\begin{aligned} & \mathbf{H}^H \mathbf{R}_n^{-1/2} (\mathbf{I} + \mathbf{R}_n^{-1/2} \mathbf{H} \mathbf{Q} \mathbf{H}^H \mathbf{R}_n^{-1/2})^{-1} \mathbf{R}_n^{-1/2} \mathbf{H} \\ & = \text{Tr} \left(\sum_i \{\mu_i \boldsymbol{\Omega}_i\} \mathbf{Q} \right) - \boldsymbol{\Psi} \\ & \mu_i \geq 0, \quad \mu_i [\text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) - P_i] = 0, \quad \text{Tr}(\mathbf{Q} \boldsymbol{\Psi}) = 0, \quad \boldsymbol{\Psi} \succeq \mathbf{0}, \\ & \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}, \end{aligned} \quad (30)$$

where μ_i is the Lagrangian multiplier that corresponds to the constraint $\text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i$. Based on Theorem 1, the following conclusion can be achieved for **P3**.

Conclusion 3: The optimal transmission covariance matrix for **P3** has the following water-filling structure

$$\mathbf{Q} = \boldsymbol{\Phi}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \boldsymbol{\Phi}^{-1/2}, \quad (31)$$

where $\boldsymbol{\Phi}$ is defined as

$$\boldsymbol{\Phi} = \frac{1}{\mu} \sum_i \{\mu_i \boldsymbol{\Omega}_i\} \quad (32)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\begin{aligned} \boldsymbol{\Pi}^{-1/2} \mathbf{H} \boldsymbol{\Phi}^{-1/2} &= \mathbf{U}_{\mathcal{H}} \boldsymbol{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \boldsymbol{\Lambda}_{\mathcal{H}} \searrow, \\ \boldsymbol{\Pi} &= \mathbf{R}_n. \end{aligned} \quad (33)$$

On the other hand, the optimization problem of the MSE minimization under multiple weighted power constraints is formulated as

$$\begin{aligned} \mathbf{P4:} \quad & \min_{\mathbf{Q}} \quad \text{Tr} \left[(\mathbf{I} + \mathbf{R}_n^{-1} \mathbf{H} \mathbf{Q} \mathbf{H}^H)^{-1} \right] \\ \text{s.t.} \quad & \text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i, \quad i = 1, \dots, N. \\ & \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (34)$$

After tedious but straightforward derivations, the corresponding KKT conditions can be obtained as follows

$$\begin{aligned}
& \mathbf{H}^H \mathbf{R}_n^{-1/2} \left(\mathbf{I} + \mathbf{R}_n^{-1/2} \mathbf{H} \mathbf{Q} \mathbf{H}^H \mathbf{R}_n^{-1/2} \right)^{-2} \mathbf{R}_n^{-1/2} \mathbf{H} \\
& = \text{Tr} \left(\sum_i \{ \mu_i \mathbf{\Omega}_i \} \mathbf{Q} \right) - \mathbf{\Psi}, \\
& \mu_i \geq 0, \quad \mu_i [\text{Tr}(\mathbf{\Omega}_i \mathbf{Q}) - P_i] = 0, \quad \text{Tr}(\mathbf{Q} \mathbf{\Psi}) = 0, \quad \mathbf{\Psi} \succeq \mathbf{0}, \\
& \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}.
\end{aligned} \tag{35}$$

By following exactly the same procedure as that for the capacity maximization, the optimal solution for **P4** is solved by Theorem 1 and the following conclusion is obtained.

Conclusion 4: The optimal transmission covariance matrix for **P4** has the following water-filling structure

$$\begin{aligned}
\mathbf{Q} = & \mathbf{\Phi}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\mu^{-1/2} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \\
& \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \mathbf{\Phi}^{-1/2},
\end{aligned} \tag{36}$$

where $\mathbf{\Phi}$ is defined in (32) and $\mathbf{V}_{\mathcal{H}}$ is defined in (33).

Comment 2: The solutions given in Conclusions 3 and 4 are closed-form solutions. The multiple Lagrange multipliers μ_i 's can be efficiently solved by subgradient algorithms [32]. The capacity maximization problem **P3** was studied in [35]. Our work is more general since [35] considers the special case of per-antenna power constraints and full rank channel matrix.

IV. TRANSMISSION COVARIANCE MATRIX OPTIMIZATION FOR SU MIMO SYSTEMS WITH IMPERFECT CSI

In practical wireless systems, perfect CSI is unrealistic as CSI must be estimated via training processes. The limited training length, the ubiquitous noise, together with the time varying nature of wireless channels make channel estimation errors inevitable [40]. By taking channel estimation error into account, the CSI can usually be modeled as follows [26], [28]:

$$\mathbf{H} = \bar{\mathbf{H}} + \Delta \mathbf{H} \quad \text{where} \quad \Delta \mathbf{H} = \mathbf{R}_R^{1/2} \mathbf{H}_W \mathbf{R}_T^{1/2}. \tag{37}$$

In this model, $\Delta \mathbf{H}$ is the CSI error, while \mathbf{R}_R and \mathbf{R}_T are the corresponding receive and transmit correlation matrices and without loss of generality \mathbf{H}_W is a random matrix with each element being independent and identically distributed (i.i.d.) Gaussian random variables with zero-mean and unit-variance.

A. Total Power Constraint with Imperfect CSI

With the CSI error in (37) and white noise i.e., $\mathbf{R}_n = \sigma_n^2 \mathbf{I}$, the capacity maximization problem under a total power constraint can be given as

$$\begin{aligned} \mathbf{P5}: \quad & \min_{\mathbf{Q}} \quad -\log |\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H| \\ \text{s.t.} \quad & \mathbf{K}_n = \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R \\ & \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq 0, \end{aligned} \quad (38)$$

where P is the total power constraint. Based on the following matrix derivative equation

$$\begin{aligned} & \frac{\partial \log |\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H|}{\partial \mathbf{Q}} \\ &= \bar{\mathbf{H}}^H (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \bar{\mathbf{H}} - \text{Tr}(\mathbf{K}_n^{-1} \mathbf{R}_R) \mathbf{R}_T \\ & \quad + \text{Tr}((\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \mathbf{R}_R) \mathbf{R}_T, \end{aligned} \quad (39)$$

the KKT conditions of **P5** can be derived as follows

$$\begin{aligned} & \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-1} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\ &= \mu \mathbf{I} + \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_T - \Psi \\ & \mu \geq 0, \quad \mu (\text{Tr}(\mathbf{Q}) - P) = 0, \quad \text{Tr}(\mathbf{Q} \Psi) = 0, \quad \Psi \succeq 0 \\ & \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq 0. \end{aligned} \quad (40)$$

Based on Theorem 1, the following conclusion for the optimal solution of **P5** can be obtained.

Conclusion 5: The optimal transmission covariance matrix for **P5** has the following water-filling structure

$$\mathbf{Q} = \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1} \mathbf{I} - [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2}, \quad (41)$$

where Φ is defined as

$$\Phi = \mathbf{I} + \frac{1}{\mu} \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_T \quad (42)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \Lambda_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H. \quad (43)$$

Next, two special cases are considered: 1) the transmit antennas have no spatial correlation and 2) the receive antennas have no spatial correlation. For the first case, \mathbf{R}_T is a scalar multiple

of the identity matrix, denoted as $\mathbf{R}_T \propto \mathbf{I}$. It can be shown that $\Phi \propto \mathbf{I}$ and Conclusion 5 can be greatly simplified.

Conclusion 5.1 When $\mathbf{R}_T = r_b \mathbf{I}$, the optimal solution of **P5** can be simplified as

$$\mathbf{Q} = [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\tilde{\mu}^{-1} \mathbf{I} - [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H,$$

where

$$\tilde{\mu} = \mu \left(1 + \frac{r_b}{\mu} \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \right) \quad (44)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\begin{aligned} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} &= \mathbf{U}_{\mathcal{H}} \Lambda_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H, \\ \mathbf{K}_n &= \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{Q}) \mathbf{R}_R = \sigma_n^2 \mathbf{I} + P \mathbf{R}_R. \end{aligned} \quad (45)$$

When the receive antennas have no spatial correlation, i.e., $\mathbf{R}_R = r_a \mathbf{I}$, the following equation holds

$$\mathbf{K}_n = \underbrace{(\sigma_n^2 + r_a \text{Tr}(\mathbf{Q} \mathbf{R}_T))}_{\triangleq k_n} \mathbf{I}. \quad (46)$$

Then by defining

$$\tilde{\mathbf{Q}} = \frac{1}{k_n} \mathbf{Q}, \quad (47)$$

the first KKT condition can be rewritten as

$$\begin{aligned} &\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \bar{\mathbf{H}} \\ &= \mu k_n \mathbf{I} + r_a \text{Tr} \left[\left(\mathbf{I} - \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \right) \right] \mathbf{R}_T - \Psi k_n \\ &= \mu k_n \mathbf{I} + r_a \text{Tr} \left[\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \bar{\mathbf{H}} \tilde{\mathbf{Q}} \right] \mathbf{R}_T - \Psi k_n. \end{aligned} \quad (48)$$

Taking trace on both sides, we will have

$$\begin{aligned} &\text{Tr} \left[\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \bar{\mathbf{H}} \tilde{\mathbf{Q}} \right] \\ &= \mu k_n \text{Tr}(\tilde{\mathbf{Q}}) + \text{Tr} \left[\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \bar{\mathbf{H}} \tilde{\mathbf{Q}} \right] \text{Tr}(\mathbf{R}_T \tilde{\mathbf{Q}}) r_a, \end{aligned} \quad (49)$$

based on which the following equalities are obtained

$$\begin{aligned}\text{Tr} \left[\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-1} \bar{\mathbf{H}} \tilde{\mathbf{Q}} \right] &= \frac{\mu k_n \text{Tr}(\tilde{\mathbf{Q}})}{1 - \text{Tr}(\mathbf{R}_T \tilde{\mathbf{Q}}) r_a} \\ &= \frac{\mu k_n \text{Tr}(\mathbf{Q})}{k_n - \text{Tr}(\mathbf{R}_T \mathbf{Q}) r_a} \\ &= \frac{\mu k_n P}{\sigma_n^2}.\end{aligned}\quad (50)$$

From (50), the first KKT condition in (48) becomes

$$\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-2} \bar{\mathbf{H}} = \frac{\mu k_n}{\sigma_n^2} (\sigma_n^2 \mathbf{I} + r_a P \mathbf{R}_T) - \Psi k_n. \quad (51)$$

Therefore, based on Theorem 1, the following conclusion holds.

Conclusion 5.2 When $\mathbf{R}_R = r_a \mathbf{I}$, the optimal $\tilde{\mathbf{Q}}$ has the following structure

$$\tilde{\mathbf{Q}} = \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\tilde{\mu}^{-1} \mathbf{I} - [\Lambda_{\mathcal{H}}]_{:,1:N}^{-1})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2}$$

where

$$\tilde{\mu} = \frac{\mu k_n}{\sigma_n^2}, \quad \Phi = \sigma_n^2 \mathbf{I} + r_a P \mathbf{R}_T \quad (52)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \Lambda_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \Lambda_{\mathcal{H}} \searrow. \quad (53)$$

When $\tilde{\mathbf{Q}}$ has been computed, to derive \mathbf{Q} based on (47), k_n should be computed. This is very easy as $\text{Tr}(\mathbf{Q}) = P$. Based on (47), it is obvious that

$$k_n = \frac{\text{Tr}(\mathbf{Q})}{\text{Tr}(\tilde{\mathbf{Q}})} = \frac{P}{\text{Tr}(\tilde{\mathbf{Q}})}. \quad (54)$$

Next, we consider the MSE minimization problem, which can be formulated in the following form

$$\begin{aligned}\mathbf{P6:} \quad & \min_{p_i} \quad \text{Tr} \left[\left(\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \right)^{-1} \right] \\ \text{s.t.} \quad & \mathbf{K}_n = \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R \\ & \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq 0.\end{aligned}\quad (55)$$

Based on the following matrix derivative equality

$$\begin{aligned}
& \frac{\partial \text{Tr}[(\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1}]}{\partial \mathbf{Q}} \\
&= -\bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-1} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\
&+ \text{Tr} \left[\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \right. \\
&\quad \left. \times \bar{\mathbf{H}}^H \mathbf{Q}^{1/2} \mathbf{K}_n^{-1} \mathbf{R}_R \right] \mathbf{R}_T,
\end{aligned} \tag{56}$$

the KKT conditions of **P6** can be derived to be

$$\begin{aligned}
& \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-1} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\
&= \mu \mathbf{I} + \text{Tr} \left[\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \right. \\
&\quad \left. \times \bar{\mathbf{H}}^H \mathbf{Q}^{1/2} \mathbf{K}_n^{-1} \mathbf{R}_R \right] \mathbf{R}_T - \Psi, \\
&\mu \geq 0, \quad \mu(\text{Tr}(\mathbf{Q}) - P) = 0, \quad \text{Tr}(\mathbf{Q}\Psi) = 0, \quad \Psi \succeq \mathbf{0}, \\
&\text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}.
\end{aligned} \tag{57}$$

Based on Theorem 1, we have the following conclusion.

Conclusion 6: The optimal transmission covariance matrix for **P6** has the following water-filling structure

$$\begin{aligned}
\mathbf{Q} &= \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\mu^{-1/2} [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \\
&\quad \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2},
\end{aligned} \tag{58}$$

where Φ is defined as follows

$$\begin{aligned}
\Phi &= \mathbf{I} + \frac{1}{\mu} \text{Tr} \left[\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \right. \\
&\quad \left. \times \bar{\mathbf{H}}^H \mathbf{Q}^{1/2} \mathbf{K}_n^{-1} \mathbf{R}_R \right] \mathbf{R}_T
\end{aligned} \tag{59}$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \Lambda_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \Lambda_{\mathcal{H}} \searrow.$$

Similarly, two special cases are considered. When the transmit antennas have no spatial correlation, i.e., $\mathbf{R}_T \propto \mathbf{I}$, it can be shown that $\Phi \propto \mathbf{I}$, and the following conclusion is obtained.

Conclusion 6.1 When $\mathbf{R}_T = r_b \mathbf{I}$, the optimal solution for **P6** has the following water-filling structure

$$\mathbf{Q} = [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\tilde{\mu}^{-1} [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H,$$

where

$$\tilde{\mu} = \mu \left(1 + \frac{r_b}{\mu} \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}}\mathbf{Q}\bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \right) \quad (60)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\begin{aligned} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} &= \mathbf{U}_{\mathcal{H}} \mathbf{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \\ \mathbf{K}_n &= \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{Q}) \mathbf{R}_R = \sigma_n^2 \mathbf{I} + P \mathbf{R}_R. \end{aligned} \quad (61)$$

When the receive antennas have no spatial correlation, i.e., $\mathbf{R}_R = r_a \mathbf{I}$, based on (47), the first KKT conditions can be reformulate in the following form

$$\bar{\mathbf{H}}^H \left(\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H \right)^{-2} \bar{\mathbf{H}} = \frac{\mu k_n}{\sigma_n^2} (\sigma_n^2 \mathbf{I} + P r_a \mathbf{R}_T) - \Psi k_n. \quad (62)$$

Based on **Theorem 1** and the following substitution

$$\Phi = \sigma_n^2 \mathbf{I} + P r_a \mathbf{R}_T, \quad (63)$$

we have the following conclusion.

Conclusion 6.2 When $\mathbf{R}_R = r_a \mathbf{I}$, the optimal $\tilde{\mathbf{Q}}$ for **P6** satisfies the following structure

$$\begin{aligned} \tilde{\mathbf{Q}} &= \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\tilde{\mu}^{-1/2} [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\mathbf{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \\ &\quad \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2}, \end{aligned}$$

where

$$\tilde{\mu} = \frac{\mu k_n}{\sigma_n^2} \quad (64)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \mathbf{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \mathbf{\Lambda}_{\mathcal{H}} \searrow. \quad (65)$$

Comment 3: By comparing the optimal solutions in Conclusions 5 and 6, it can be seen that the solutions for capacity maximization and MSE minimization have similar structure. The weight of the power constraint is reflected on the column correlation of the channel matrix. The solutions in Conclusions 5.1, 5.2, 6.1 and 6.2 are in exact closed-forms, while the general solutions given by Conclusions 5 and 6 can be computed using iterative schemes such as fixed point algorithms. Some similar problems have also been discussed in [27]–[29]. Compared with Ding's work in [28], [29], our derivations are much simpler and provides a unified framework optimization for both capacity maximization and MSE minimization. As discussed in [34], the

methods in [28], [29] suffer from the turning-off effect, while the proposed framework does not have this problem. It is worth highlighting that our previous work [27] cannot cover the general conclusions given by Conclusions 5 and 6 as some approximations are used.

B. Multiple Weighted Power Constraints with imperfect CSI

To our best knowledge, the transmission covariance matrix optimizations for MIMO systems under multiple weighted power constraints and imperfect CSI are still open. The capacity maximization problem can be formulated as follows

$$\begin{aligned} \mathbf{P7}: \min_{\mathbf{Q}} \quad & -\log |\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H| \\ \text{s.t.} \quad & \mathbf{K}_n = \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R, \\ & \text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i, \quad \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (66)$$

The corresponding KKT conditions are given as

$$\begin{aligned} & \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-1} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\ &= \sum_i \mu_i \boldsymbol{\Omega}_i + \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_T - \boldsymbol{\Psi} \\ & \mu \geq 0, \quad \mu(\text{Tr}(\mathbf{Q}) - P) = 0, \quad \text{Tr}(\mathbf{Q} \boldsymbol{\Psi}) = 0, \quad \boldsymbol{\Psi} \succeq \mathbf{0}, \\ & \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}. \end{aligned} \quad (67)$$

Based on Theorem 1, the following conclusion is obtained.

Conclusion 7: The optimal transmission covariance matrix for **P7** has the following structure

$$\mathbf{Q} = \boldsymbol{\Phi}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \boldsymbol{\Phi}^{-1/2}, \quad (68)$$

where

$$\begin{aligned} \boldsymbol{\Phi} &= \frac{1}{\mu} \sum_i \mu_i \boldsymbol{\Omega}_i + \frac{1}{\mu} \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_T, \\ \mathbf{K}_n &= \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R, \end{aligned} \quad (69)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \boldsymbol{\Phi}^{-1/2} = \mathbf{U}_{\mathcal{H}} \boldsymbol{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \boldsymbol{\Lambda}_{\mathcal{H}} \searrow. \quad (70)$$

For the special case that the receive antennas have no spatial correlation, i.e., $\mathbf{R}_R = r_a \mathbf{I}$, the first KKT condition can be rewritten as

$$\begin{aligned} & \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-1} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\ &= \sum_i \mu_i \boldsymbol{\Omega}_i + \text{Tr} \left[\left(\mathbf{K}_n^{-1} - (\mathbf{K}_n + \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right) \right] \mathbf{R}_T r_a - \Psi. \end{aligned} \quad (71)$$

Based on (71) and (47), we have

$$\begin{aligned} & \bar{\mathbf{H}}^H (\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H)^{-1} \bar{\mathbf{H}} \\ &= \frac{\mu k_n}{\sigma_n^2} \left[\sum_i \frac{\mu_i}{\mu} \boldsymbol{\Omega}_i \sigma_n^2 + \left(\sum_i \frac{\mu_i}{\mu} P_i \right) r_a \mathbf{R}_T \right] - \Psi k_n. \end{aligned} \quad (72)$$

From Theorem 1, the following conclusion is obtained.

Conclusion 7.1: When $\mathbf{R}_R = r_a \mathbf{I}$, the optimal $\tilde{\mathbf{Q}}$ for **P7** has the following structure

$$\tilde{\mathbf{Q}} = \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\tilde{\mu}^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2}$$

where

$$\tilde{\mu} = \frac{\mu k_n}{\sigma_n^2} \quad (73)$$

$$\Phi = \sum_i \mu_i \boldsymbol{\Omega}_i \sigma_n^2 + \left(\sum_i \mu_i P_i \right) r_a \mathbf{R}_T \quad (74)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \boldsymbol{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \boldsymbol{\Lambda}_{\mathcal{H}} \searrow. \quad (75)$$

Furthermore, the MSE minimization problem for SU MIMO systems under multiple weighted power constraint and imperfect CSI is written in the following form [27]

$$\begin{aligned} \mathbf{P8:} \quad & \min_{\mathbf{Q}} \quad \text{Tr} \left[(\mathbf{I} + \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H)^{-1} \right] \\ & \text{s.t.} \quad \mathbf{K}_n = \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R, \\ & \quad \text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i, \quad \mathbf{Q} \succeq 0. \end{aligned} \quad (76)$$

The KKT conditions are

$$\begin{aligned}
& \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-2} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\
&= \sum_i \mu_i \boldsymbol{\Omega}_i + \text{Tr} \left[\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \right. \\
&\quad \left. \times \bar{\mathbf{H}}^H \mathbf{Q}^{1/2} \mathbf{K}_n^{-1} \mathbf{R}_R \right] \mathbf{R}_T - \boldsymbol{\Psi} \\
&\mu_i \geq 0, \quad \mu_i (\text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) - P_i) = 0, \quad \text{Tr}(\mathbf{Q} \boldsymbol{\Psi}) = 0, \quad \boldsymbol{\Psi} \succeq \mathbf{0}, \\
&\text{Tr}(\boldsymbol{\Omega}_i \mathbf{Q}) \leq P_i, \quad \mathbf{Q} \succeq \mathbf{0}.
\end{aligned} \tag{77}$$

Based on Theorem 1, the following conclusion is obtained.

Conclusion 8: The optimal transmission covariance matrix of **P8** has the following structure

$$\begin{aligned}
\mathbf{Q} &= \boldsymbol{\Phi}^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} (\mu^{-1/2} [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\boldsymbol{\Lambda}_{\mathcal{H}}]_{1:N,1:N}^{-2})^+ \\
&\quad \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \boldsymbol{\Phi}^{-1/2}
\end{aligned} \tag{78}$$

where $\boldsymbol{\Phi}$ is defined as

$$\begin{aligned}
\boldsymbol{\Phi} &= \frac{1}{\mu} \sum_i \mu_i \boldsymbol{\Omega}_i + \frac{1}{\mu} \text{Tr} [\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} \\
&\quad \times (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \bar{\mathbf{H}}^H \mathbf{Q}^{1/2} \mathbf{K}_n^{-1} \mathbf{R}_R] \mathbf{R}_T
\end{aligned} \tag{79}$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\begin{aligned}
\mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \boldsymbol{\Phi}^{-1/2} &= \mathbf{U}_{\mathcal{H}} \boldsymbol{\Lambda}_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with } \boldsymbol{\Lambda}_{\mathcal{H}} \searrow \\
\mathbf{K}_n &= \sigma_n^2 \mathbf{I} + \text{Tr}(\mathbf{R}_T \mathbf{Q}) \mathbf{R}_R.
\end{aligned} \tag{80}$$

For the special case that the receive antennas have no spatial correlation, i.e., $\mathbf{R}_R = r_a \mathbf{I}$, the first KKT condition can be written as

$$\begin{aligned}
& \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2} (\mathbf{I} + \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \mathbf{Q} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1/2})^{-2} \mathbf{K}_n^{-1/2} \bar{\mathbf{H}} \\
&= \sum_i \mu_i \boldsymbol{\Omega}_i + \text{Tr} \left[\mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2} (\mathbf{I} + \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \bar{\mathbf{H}} \mathbf{Q}^{1/2})^{-2} \right. \\
&\quad \left. \times \mathbf{Q}^{1/2} \bar{\mathbf{H}}^H \mathbf{K}_n^{-1} \right] \mathbf{R}_T r_a - \boldsymbol{\Psi}.
\end{aligned} \tag{81}$$

Based on (81) and (47), we have

$$\begin{aligned}
& \bar{\mathbf{H}}^H (\mathbf{I} + \bar{\mathbf{H}} \tilde{\mathbf{Q}} \bar{\mathbf{H}}^H)^{-2} \bar{\mathbf{H}} \\
&= \frac{\mu k_n}{\sigma_n^2} \left[\sum_i \frac{\mu_i}{\mu} \boldsymbol{\Omega}_i \sigma_n^2 + \left(\sum_i \frac{\mu_i}{\mu} P_i \right) r_a \mathbf{R}_T \right] - \boldsymbol{\Psi} k_n.
\end{aligned} \tag{82}$$

Thus, the following simplified solution can be obtained from Theorem 1.

Conclusion 8.1: When $\mathbf{R}_R = r_a \mathbf{I}$, the optimal $\tilde{\mathbf{Q}}$ of **P8** satisfies the following structure

$$\begin{aligned} \tilde{\mathbf{Q}} = & \Phi^{-1/2} [\mathbf{V}_{\mathcal{H}}]_{:,1:N} \left(\tilde{\mu}^{-1/2} [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-1} - [\Lambda_{\mathcal{H}}]_{1:N,1:N}^{-2} \right)^+ \\ & \times [\mathbf{V}_{\mathcal{H}}]_{:,1:N}^H \Phi^{-1/2}, \end{aligned} \quad (83)$$

where

$$\tilde{\mu} = \frac{\mu k_n}{\sigma_n^2}, \quad (84)$$

$$\Phi = \sum_i \frac{\mu_i}{\mu} \Omega_i \sigma_n^2 + \left(\sum_i \frac{\mu_i}{\mu} P_i \right) r_a \mathbf{R}_T, \quad (85)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\bar{\mathbf{H}} \Phi^{-1/2} = \mathbf{U}_{\mathcal{H}} \Lambda_{\mathcal{H}} \mathbf{V}_{\mathcal{H}}^H \quad \text{with} \quad \Lambda_{\mathcal{H}} \searrow. \quad (86)$$

Comment 4: To our best knowledge, the water-filling structures for the optimal covariance matrices for SU MIMO systems under multiple weighted power constraints and imperfect CSI have been open problems in existing literature. The solutions given in Conclusions 7.1 and 8.1 are exact and in closed-form. The general solutions given in [Conclusions 7 and 8](#) can be computed iteratively based on fixed point algorithms.

V. TRANSMISSION COVARIANCE MATRIX OPTIMIZATION IN MU MIMO UNDER MULTIPLE WEIGHTED POWER CONSTRAINTS

In this section, the transmission covariance matrix optimization for MU MIMO systems is investigated. The MU MIMO system has one multi-antenna base station and multiple multi-antenna users. The channel between the k^{th} user and the base station is denoted by \mathbf{H}_k and the k^{th} user's transmission covariance matrix is denoted by \mathbf{Q}_k . Multiple weighted power constraints are considered with $\Omega_{k,i}$ being the weighting matrix for the i th power constraint of the k th user and $P_{k,i}$ being the corresponding power limit. The optimization for the uplink is studied first followed by the downlink.

A. MU MIMO Uplink

For the uplink where the users send information to the base station, the capacity maximization problem under multiple weighted power constraints and perfect CSI is formulated as

$$\begin{aligned} \mathbf{P9}: \quad & \min_{\mathbf{Q}_k} \quad -\log \left| \mathbf{I} + \mathbf{R}_n^{-1} \sum_{k=1}^K (\mathbf{H}_k \mathbf{Q}_k \mathbf{H}_k^H) \right| \\ \text{s.t.} \quad & \text{Tr}(\mathbf{\Omega}_{k,i} \mathbf{Q}_k) \leq P_{k,i}, \quad \mathbf{Q}_k \succeq \mathbf{0}. \end{aligned} \quad (87)$$

The KKT conditions of **P9** are

$$\begin{aligned} & \mathbf{H}_k^H \left(\mathbf{R}_n + \sum_{j \neq k} \mathbf{H}_j \mathbf{Q}_j \mathbf{H}_j^H + \mathbf{H}_k \mathbf{Q}_k \mathbf{H}_k^H \right)^{-1} \mathbf{H}_k \\ & = \sum_i \mu_{k,i} \mathbf{\Omega}_{k,i} - \mathbf{\Psi}_k, \\ & \mu_{k,i} \geq 0, \quad \mu_{k,i} (\text{Tr}(\mathbf{\Omega}_{k,i} \mathbf{Q}_k) - P_{k,i}) = 0, \quad \text{Tr}(\mathbf{Q}_k \mathbf{\Psi}_k) = 0, \\ & \mathbf{\Psi}_k \succeq \mathbf{0}, \quad \text{Tr}(\mathbf{\Omega}_{k,i} \mathbf{Q}_k) \leq P_{k,i}, \quad \mathbf{Q}_k \succeq \mathbf{0}, \end{aligned} \quad (88)$$

where $\mathbf{\Psi}_k$ is the Lagrangian multiplier corresponding to the constraint $\mathbf{Q}_k \succeq \mathbf{0}$. By using Theorem 1, the following conclusion is obtained.

Conclusion 9: The optimal transmission covariance matrices for **P9** has the following water-filling structure

$$\begin{aligned} \mathbf{Q}_k &= \mathbf{\Phi}_k^{-1/2} [\mathbf{V}_{\mathbf{H}_k}]_{:,1:N} (\mu_k^{-1} \mathbf{I} - [\mathbf{\Lambda}_{\mathbf{H}_k}]_{1:N,1:N}^{-2})^+ \\ &\quad \times [\mathbf{V}_{\mathbf{H}_k}]_{:,1:N}^H \mathbf{\Phi}_k^{-1/2}, \end{aligned} \quad (89)$$

where $\mathbf{\Phi}_k$ is defined as

$$\mathbf{\Phi}_k = \frac{1}{\mu_k} \sum_i \{\mu_{k,i} \mathbf{\Omega}_{k,i}\} \quad (90)$$

and the unitary matrix $\mathbf{V}_{\mathbf{H}_k}$ is defined by the following SVD

$$\begin{aligned} \mathbf{\Pi}_k^{-1/2} \mathbf{H}_k \mathbf{\Phi}_k^{-1/2} &= \mathbf{U}_{\mathbf{H}_k} \mathbf{\Lambda}_{\mathbf{H}_k} \mathbf{V}_{\mathbf{H}_k}^H \quad \text{with} \quad \mathbf{\Lambda}_{\mathbf{H}_k} \searrow, \\ \mathbf{\Pi}_k &= \mathbf{R}_n + \sum_{j \neq k} \mathbf{H}_j \mathbf{Q}_j \mathbf{H}_j^H. \end{aligned} \quad (91)$$

Next, MU MIMO systems with imperfect CSI is considered. The following channel model is used

$$\mathbf{H}_k = \bar{\mathbf{H}}_k + \Delta \mathbf{H}_k \quad \text{with} \quad \Delta \mathbf{H}_k = \mathbf{R}_{R,k}^{1/2} \mathbf{H}_{W,k} \mathbf{R}_{T,k}^{1/2}, \quad (92)$$

where similar to previous notation, $\Delta \mathbf{H}_k$ represents the CSI error for the channel matrix between User k and the base station, $\mathbf{R}_{R,k}$ is the receive correlation matrix corresponding to User k , $\mathbf{R}_{T,k}$ is the transmit correlation matrix corresponding to User k , and $\mathbf{H}_{W,k}$ is a random matrix whose entries are i.i.d. Gaussian random variables with zero-mean and unit-variance.

The capacity maximization problem under multiple weighted power constraints, imperfect CSI, and white noise, i.e., $\mathbf{R}_n = \sigma_n^2 \mathbf{I}$, can be formulated as follows

$$\begin{aligned} \mathbf{P10}: \quad & \min_{\mathbf{Q}_k} \quad -\log \left| \mathbf{I} + \mathbf{K}_k^{-1} \sum_{k=1}^K (\bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H) \right| \\ & \text{s.t.} \quad \mathbf{K}_k = \sigma_n^2 \mathbf{I} + \sum_k \text{Tr}(\mathbf{Q}_k \mathbf{R}_{T,k}) \mathbf{R}_R, \\ & \quad \text{Tr}(\boldsymbol{\Omega}_{k,i} \mathbf{Q}_k) \leq P_{k,i}, \quad \mathbf{Q}_k \succeq \mathbf{0}. \end{aligned} \quad (93)$$

Define the following positive semi-definite matrix

$$\boldsymbol{\Sigma}_k = \mathbf{K}_k + \sum_{j \neq k} \bar{\mathbf{H}}_j \mathbf{Q}_j \bar{\mathbf{H}}_j^H. \quad (94)$$

The KKT conditions are listed as follows

$$\begin{aligned} & \bar{\mathbf{H}}_k^H (\boldsymbol{\Sigma}_k + \bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H)^{-1} \bar{\mathbf{H}}_k = \sum_i \mu_{k,i} \boldsymbol{\Omega}_{k,i} \\ & \quad + \text{Tr} \left[\left(\boldsymbol{\Sigma}_k^{-1} - (\boldsymbol{\Sigma}_k + \bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_{T,k} - \boldsymbol{\Psi}_k, \\ & \mu_{k,i} \geq 0, \quad \mu_{k,i} (\text{Tr}(\boldsymbol{\Omega}_{k,i} \mathbf{Q}_k) - P_{k,i}) = 0, \quad \text{Tr}(\mathbf{Q}_k \boldsymbol{\Psi}_k) = 0, \\ & \text{Tr}(\boldsymbol{\Omega}_{k,i} \mathbf{Q}_k) \leq P_{k,i}, \quad \mathbf{Q}_k \succeq \mathbf{0}, \quad \boldsymbol{\Psi}_k \succeq \mathbf{0}. \end{aligned} \quad (95)$$

From Theorem 1, the following conclusion can be obtained.

Conclusion 10: The optimal transmission covariance matrices for **P10** have the following structure

$$\begin{aligned} \mathbf{Q}_k &= \boldsymbol{\Phi}_k^{-1/2} [\mathbf{V}_{\boldsymbol{\mathcal{H}}_k}]_{:,1:N} (\mu_k^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\boldsymbol{\mathcal{H}}_k}]_{1:N,1:N}^{-2})^+ \\ & \quad \times [\mathbf{V}_{\boldsymbol{\mathcal{H}}_k}]_{:,1:N}^H \boldsymbol{\Phi}_k^{-1/2}, \end{aligned} \quad (96)$$

where $\boldsymbol{\Phi}_k$ is defined as

$$\begin{aligned} \boldsymbol{\Phi}_k &= \frac{1}{\mu_k} \sum_i \mu_{k,i} \boldsymbol{\Omega}_{k,i} \\ & \quad + \frac{1}{\mu_k} \text{Tr} \left[\left(\boldsymbol{\Sigma}_k^{-1} - (\boldsymbol{\Sigma}_k + \bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H)^{-1} \right) \mathbf{R}_R \right] \mathbf{R}_{T,k} \end{aligned} \quad (97)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\begin{aligned} \mathbf{\Pi}_k^{-1/2} \bar{\mathbf{H}}_k \mathbf{\Phi}_k^{-1/2} &= \mathbf{U}_{\mathcal{H}_k} \mathbf{\Lambda}_{\mathcal{H}_k} \mathbf{V}_{\mathcal{H}_k}^H \quad \text{with } \mathbf{\Lambda}_{\mathcal{H}_k} \searrow \\ \mathbf{\Pi}_k &= \sigma_n^2 \mathbf{I} + \sum_k \text{Tr}(\mathbf{Q}_k \mathbf{R}_{T,k}) \mathbf{R}_R + \sum_{j \neq k} \bar{\mathbf{H}}_j \mathbf{Q}_j \bar{\mathbf{H}}_j^H. \end{aligned} \quad (98)$$

When only a sum power constraint for each user is considered and there is no spatial correlation at the transmit antennas, we have $\mathbf{\Omega}_{k,i} = \mathbf{I}$ and $\mathbf{R}_{T,k} = r_{b_k} \mathbf{I}$, based on which the result can be simplified as follows.

Conclusion 10.1: When $\mathbf{\Omega}_{k,i} = \mathbf{I}$ and $\mathbf{R}_{T,k} = r_{b_k} \mathbf{I}$, the optimal solution for **P10** has the following structure

$$\mathbf{Q}_k = [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N} (\mu_k^{-1} \mathbf{I} - [\mathbf{\Lambda}_{\mathcal{H}_k}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N}^H, \quad (99)$$

where the unitary matrix $\mathbf{V}_{\mathcal{H}}$ is defined by the following SVD

$$\mathbf{\Pi}_k^{-1/2} \bar{\mathbf{H}}_k = \mathbf{U}_{\mathcal{H}_k} \mathbf{\Lambda}_{\mathcal{H}_k} \mathbf{V}_{\mathcal{H}_k}^H \quad \text{with } \mathbf{\Lambda}_{\mathcal{H}_k} \searrow, \quad (100)$$

$$\mathbf{\Pi}_k = \sigma_n^2 \mathbf{I} + \sum_k P_k r_{b_k} \mathbf{R}_R + \sum_{j \neq k} \bar{\mathbf{H}}_j \mathbf{Q}_j \bar{\mathbf{H}}_j^H. \quad (101)$$

Comment 5: For the perfect CSI case, the proposed solution better shows the water-filling structure and is in a neater format than Mai's work [35]. Moreover, our method does not require the channel matrix to be full rank and **does not suffer from the turning-off effect**. Our results in Conclusions 10 and 10.1 for MU MIMO uplink with imperfect CSI are new and have not been discovered in the literature. The solutions for \mathbf{Q}_k 's given by Conclusion 10.1 are exact and in closed-form.

B. MU MIMO Downlink

The next to study is the MU MIMO downlink, where the base station sends information to all users. For the perfect CSI case and under multiple weighted power constraints, the transmission covariance matrix optimization problem for the sum-capacity maximization is formulated as

$$\begin{aligned} \mathbf{P11:} \quad & \min_{\mathbf{Q}_k} \sum_k -\log |\mathbf{I} + \mathbf{\Sigma}_k^{-1} \mathbf{H}_k \mathbf{Q}_k \mathbf{H}_k^H| \\ \text{s.t.} \quad & \mathbf{\Sigma}_k = \mathbf{R}_{n_k} + \mathbf{H}_k \sum_{j \neq k} \mathbf{Q}_j \mathbf{H}_k^H, \\ & \text{Tr}(\mathbf{\Omega}_i \sum_k \mathbf{Q}_k) \leq P_i, \quad \mathbf{Q}_k \succeq 0, \end{aligned} \quad (102)$$

where \mathbf{R}_{n_k} is the noise covariance matrix at User k . The corresponding KKT conditions are

$$\begin{aligned}
\mathbf{H}_k^H (\boldsymbol{\Sigma}_k + \mathbf{H}_k \mathbf{Q}_k \mathbf{H}_k^H)^{-1} \mathbf{H}_k &= \sum_i \mu_i \boldsymbol{\Omega}_i \\
&+ \sum_{j \neq k} \mathbf{H}_j^H \left[\boldsymbol{\Sigma}_j^{-1} - (\boldsymbol{\Sigma}_j + \mathbf{H}_j \mathbf{Q}_j \mathbf{H}_j^H)^{-1} \right] \mathbf{H}_j - \boldsymbol{\Psi}_k, \\
\mu_i &\geq 0, \quad \mu_i (\text{Tr}(\boldsymbol{\Omega}_i \sum_k \mathbf{Q}_k) - P_i) = 0, \quad \text{Tr}(\mathbf{Q}_k \boldsymbol{\Psi}_k) = 0, \\
\boldsymbol{\Psi}_k &\succeq \mathbf{0}, \quad \text{Tr}(\boldsymbol{\Omega}_i \sum_k \mathbf{Q}_k) \leq P_i, \quad \mathbf{Q}_k \succeq \mathbf{0}.
\end{aligned} \tag{103}$$

Based on Theorem 1, the following conclusions is obtained.

Conclusion 11: The optimal transmission covariance matrices for **P11** has the following structure

$$\begin{aligned}
\mathbf{Q}_k &= \boldsymbol{\Phi}_k^{-1/2} [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N} (\tilde{\mu}_k^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}_k}]_{1:N,1:N}^{-2})^+ [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N}^H \\
&\times \boldsymbol{\Phi}_k^{-1/2},
\end{aligned} \tag{104}$$

where

$$\begin{aligned}
\boldsymbol{\Phi}_k &= \frac{1}{\tilde{\mu}_k} \sum_i \{\mu_i \boldsymbol{\Omega}_{k,i}\} \\
&+ \frac{1}{\tilde{\mu}_k} \sum_{j \neq k} \mathbf{H}_j^H \left[\boldsymbol{\Sigma}_j^{-1} - (\boldsymbol{\Sigma}_j + \mathbf{H}_j \mathbf{Q}_j \mathbf{H}_j^H)^{-1} \right] \mathbf{H}_j
\end{aligned} \tag{105}$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}_k}$ is defined by the following SVD

$$\boldsymbol{\Sigma}_k^{-1/2} \bar{\mathbf{H}}_k \boldsymbol{\Phi}_k^{-1/2} = \mathbf{U}_{\mathcal{H}_k} \boldsymbol{\Lambda}_{\mathcal{H}_k} \mathbf{V}_{\mathcal{H}_k}^H \quad \text{with} \quad \boldsymbol{\Lambda}_{\mathcal{H}_k} \searrow. \tag{106}$$

When CSI error is present, by using the same model and notation as before and with white noises, i.e., $\mathbf{R}_{n_k} = \sigma_{n_k}^2 \mathbf{I}$, the sum-capacity maximization problem can be written in the following form

$$\begin{aligned}
\mathbf{P12:} \quad \min_{\mathbf{Q}_k} \quad & \sum_k -\log |\mathbf{I} + \boldsymbol{\Sigma}_k^{-1} \bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H| \\
\text{s.t.} \quad & \boldsymbol{\Sigma}_k = \sigma_{n_k}^2 \mathbf{I} + \text{Tr} \left(\sum_i \mathbf{Q}_i \mathbf{R}_T \right) \mathbf{R}_{R,k} + \bar{\mathbf{H}}_k \sum_{j \neq k} \mathbf{Q}_j \bar{\mathbf{H}}_k^H, \\
& \text{Tr} \left(\boldsymbol{\Omega}_i \sum_k \mathbf{Q}_k \right) \leq P_i, \quad \mathbf{Q}_k \succeq \mathbf{0}.
\end{aligned} \tag{107}$$

The KKT conditions are derived to be

$$\begin{aligned}
\bar{\mathbf{H}}_k^H (\boldsymbol{\Sigma}_k + \bar{\mathbf{H}}_k \mathbf{Q}_k \bar{\mathbf{H}}_k^H)^{-1} \bar{\mathbf{H}}_k &= \sum_i \mu_{k,i} \boldsymbol{\Omega}_{k,i} \\
&+ \sum_i \text{Tr} \left[\left(\boldsymbol{\Sigma}_i^{-1} - (\boldsymbol{\Sigma}_i + \bar{\mathbf{H}}_i \mathbf{Q}_i \bar{\mathbf{H}}_i^H)^{-1} \right) \mathbf{R}_{R,i} \right] \mathbf{R}_T \\
&+ \sum_{j \neq k} \bar{\mathbf{H}}_j^H \left[\boldsymbol{\Sigma}_j^{-1} - (\boldsymbol{\Sigma}_j + \bar{\mathbf{H}}_j \mathbf{Q}_j \bar{\mathbf{H}}_j^H)^{-1} \right] \bar{\mathbf{H}}_j - \boldsymbol{\Psi}_k, \\
\mu_i &\geq 0, \quad \mu_i \left[\text{Tr} \left(\boldsymbol{\Omega}_i \sum_k \mathbf{Q}_k \right) - P_i \right] = 0, \quad \text{Tr}(\mathbf{Q}_k \boldsymbol{\Psi}_k) = 0, \\
\boldsymbol{\Psi}_k &\succeq \mathbf{0}, \quad \text{Tr}(\mathbf{Q}) \leq P, \quad \mathbf{Q} \succeq \mathbf{0}.
\end{aligned} \tag{108}$$

Based on Theorem 1, the following conclusion is obtained.

Conclusion 12: The optimal transmission covariance matrices for **P12** satisfies the following structure

$$\begin{aligned}
\mathbf{Q}_k &= \Phi_k^{-1/2} [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N} \left(\tilde{\mu}_k^{-1} \mathbf{I} - [\boldsymbol{\Lambda}_{\mathcal{H}_k}]_{1:N,1:N}^{-2} \right)^+ \\
&\times [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N}^H \Phi_k^{-1/2},
\end{aligned} \tag{109}$$

where Φ_k is defined as

$$\begin{aligned}
\Phi_k &= \frac{1}{\tilde{\mu}_k} \sum_i \{ \mu_i \boldsymbol{\Omega}_{k,i} \} \\
&+ \frac{1}{\tilde{\mu}_k} \sum_i \text{Tr} \left[\left(\boldsymbol{\Sigma}_i^{-1} - (\boldsymbol{\Sigma}_i + \bar{\mathbf{H}}_i \mathbf{Q}_i \bar{\mathbf{H}}_i^H)^{-1} \right) \mathbf{R}_{R,i} \right] \mathbf{R}_T \\
&+ \frac{1}{\tilde{\mu}_k} \sum_{j \neq k} \bar{\mathbf{H}}_j^H \left[\boldsymbol{\Sigma}_j^{-1} - (\boldsymbol{\Sigma}_j + \bar{\mathbf{H}}_j \mathbf{Q}_j \bar{\mathbf{H}}_j^H)^{-1} \right] \bar{\mathbf{H}}_j
\end{aligned} \tag{110}$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}_k}$ is defined as in (106).

Comment 6: To our best knowledge, the transmission covariance matrix design for MU MIMO downlink under imperfect CSI was an open problem and our results are the first that reveal the optimal water-filling structure. Based on the results in Conclusions 11 and 12, the optimal solutions can be computed iteratively using fixed point algorithm.

Remark 2: For MU MIMO optimizations, sum-MSE minimization is not considered in this work because 1) the structure of the optimal solution for MU-MIMO uplink cannot be derived directly based on its KKT conditions and 2) the optimization solution has different structure to that for capacity maximization. Naturally, the sum-MSE minimization problem can be handled via numerical convex optimization methods such as semi-definite programming (SDP), second

order cone programming (SOCP), etc. [41]. But such solutions provide little insights and are not closely related to the main theme of this paper. Interested readers are referred to [41] and the references therein.

VI. TRANSMISSION COVARIANCE MATRIX OPTIMIZATION FOR MIMO NETWORKS

In this section, we will discuss a more general MIMO system, the MIMO network, in which multiple sources communicate with multiple destinations and each node can have multiple antennas. Every source node can send distinct information to several destinations simultaneously. On the other hand, every destination can receive distinct signals from several sources. Interference exists when a destination receives signals from sources that it does not want to communicate with. Moreover, CSI error is taken into account. To formulate the transmission covariance matrix optimization for this very general MIMO system, we use the links between the sources and the destinations as fundamental elements in the system modeling. Because wireless communications are discussed, for any source node and destination node, there always exists a link. For each channel link there is at most one desired signal. When the source of the link does not want to communicate with the destination of the link, only interference is transmitted to the link destination through the link.

In the following, the network parameters are discussed based on links. Let $\psi_{D,r}$ be the link set whose destination node is Node r , in other words, a desired signal to Node r exists on this link. The symbol $s(i)$ is the index for the desired signal vector on Link i , whose covariance matrix is denoted as $\mathbf{Q}_{s(i)}$. If there is no desired signal we define $s(i) = \text{null}$ and $\mathbf{Q}_{\text{null}} = \mathbf{0}$. Let $\psi_{I,r}$ be the link set on which there is only interference transmitting to Node r . In addition, ϕ_i denotes the index set of interferences on Link i and ψ_k denotes of the index set of the all signals transmitted from the source node of Link k . A signal on a given link cannot be both desired signal and interference simultaneously. Similar to the channel models in previous sections, for the l^{th} link, the channel matrix can be written in the following form

$$\mathbf{H}_l = \bar{\mathbf{H}}_l + \mathbf{R}_{R,l}^{1/2} \mathbf{H}_{W,l} \mathbf{R}_{T,l}^{1/2}. \quad (111)$$

With these parametrization and modeling, the capacity maximization for the MIMO network

with imperfect CSI is given in the following form

$$\begin{aligned}
\mathbf{P13:} \quad & \max_{\mathbf{Q}_i} \sum_r \log \left| \mathbf{I} + \Sigma_r^{-1} \sum_{i \in \psi_{D,r}} (\bar{\mathbf{H}}_i \mathbf{Q}_{s(i)} \bar{\mathbf{H}}_i^H) \right| \\
\text{s.t.} \quad & \Sigma_r = \mathbf{R}_{n_r} + \sum_{i \in \psi_{I,r}} \left(\bar{\mathbf{H}}_i \sum_{j \in \phi_i} \mathbf{Q}_j \bar{\mathbf{H}}_i^H \right) \\
& + \sum_{i \in \psi_{D,r} \cup \psi_{I,r}} \text{Tr} \left(\sum_{j \in i \cup \phi_i} \mathbf{Q}_j \mathbf{R}_{T,i} \right) \mathbf{R}_{R,i}, \\
& \text{Tr} \left(\Omega_{k,m} \sum_{i \in \psi_k} \mathbf{Q}_i \right) \leq P_{k,m}, \quad \mathbf{Q}_i \succeq \mathbf{0}.
\end{aligned} \tag{112}$$

In this optimization problem, the covariance matrix of the desired signal vector on each link is the optimization variable. The corresponding KKT conditions for the covariance matrix of the desired signal on Link k where $k \in \psi_{D,r}$ are

$$\begin{aligned}
& \bar{\mathbf{H}}_k^H \left[\Sigma_r + \sum_{i \in \psi_{D,r}} (\bar{\mathbf{H}}_i \mathbf{Q}_{s(i)} \bar{\mathbf{H}}_i^H) \right]^{-1} \bar{\mathbf{H}}_k = \sum_i \mu_{S(k),i} \Omega_{S(k),i} \\
& + \sum_{i \in \pi_k, m=D(i)} \text{Tr} \left(\left(\Sigma_m^{-1} - \left[\Sigma_m + \sum_{j \in \psi_{D,m}} (\bar{\mathbf{H}}_j \mathbf{Q}_{s(j)} \bar{\mathbf{H}}_j^H) \right]^{-1} \right) \mathbf{R}_{R,k} \right) \mathbf{R}_{T,k} \\
& + \sum_{i \in \pi_k, i \neq k, m=D(i)} \bar{\mathbf{H}}_i^H \left(\Sigma_m^{-1} - \left[\Sigma_m + \sum_{j \in \psi_{D,m}} (\bar{\mathbf{H}}_j \mathbf{Q}_{s(j)} \bar{\mathbf{H}}_j^H) \right]^{-1} \right) \bar{\mathbf{H}}_i - \Psi_k, \\
& \mu_{k,m} \geq 0, \quad \mu_{k,m} (\text{Tr}(\Omega_{k,i} \sum_{i \in \psi_k} \mathbf{Q}_i) - P_{k,m}) = 0, \\
& \text{Tr}(\mathbf{Q}_{s(k)} \Psi_k) = 0, \quad \Psi_k \succeq \mathbf{0}, \\
& \text{Tr} \left(\Omega_{k,m} \sum_{i \in \psi_k} \mathbf{Q}_i \right) \leq P_{k,m}, \quad \mathbf{Q}_{s(k)} \succeq \mathbf{0},
\end{aligned} \tag{113}$$

where the symbol $D(i)$ denotes the destination node of Link i and $r = D(k)$. The link set π_k consists of the links on which the $s(k)$ -th signal vector (whose covariance matrix is $\mathbf{Q}_{s(k)}$) is transmitted. For the optimization of $\mathbf{Q}_{s(k)}$, the following conclusion can be obtained based on Theorem 1.

Conclusion 13: The optimal transmission covariance matrix $\mathbf{Q}_{s(k)}$ of **P13** has the following structure

$$\mathbf{Q}_{s(k)} = \Phi_k^{-1/2} [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N} \left(\mu_k^{-1} \mathbf{I} - [\Lambda_{\mathcal{H}_k}]_{1:N,1:N}^{-2} \right)^+ \times [\mathbf{V}_{\mathcal{H}_k}]_{:,1:N}^H \Phi_k^{-1/2}, \quad (114)$$

where Φ_k is defined as

$$\begin{aligned} \Phi_k = & \frac{1}{\mu_k} \sum_i \mu_{k,i} \Omega_{k,i} + \frac{1}{\mu_k} \sum_{i \in \pi_k, m=D(i)} \text{Tr}(\Sigma_m^{-1} \\ & - \left[\Sigma_m + \sum_{j \in \psi_{D,m}} (\bar{\mathbf{H}}_j \mathbf{Q}_{s(j)} \bar{\mathbf{H}}_j^H) \right]^{-1} \mathbf{R}_{R,k}) \mathbf{R}_{T,k} \end{aligned} \quad (115)$$

and the unitary matrix $\mathbf{V}_{\mathcal{H}_k}$ is defined by the following SVD

$$\begin{aligned} \Pi_k^{-1/2} \bar{\mathbf{H}}_k \Phi_k^{-1/2} &= \mathbf{U}_{\mathcal{H}_k} \Lambda_{\mathcal{H}_k} \mathbf{V}_{\mathcal{H}_k}^H \quad \text{with } \Lambda_{\mathcal{H}_k} \searrow \\ \Pi_k &= \Sigma_k + \sum_{i \in \psi_{R,k}, i \neq k} (\bar{\mathbf{H}}_i \mathbf{Q}_{s(i)} \bar{\mathbf{H}}_i^H). \end{aligned} \quad (116)$$

Comment 6: To our best knowledge, the transmission covariance matrix optimization for MIMO networks with imperfect CSI is an open problem in existing literature. Similar to the weighted minimum-mean-squared-error (WMMSE) algorithm (which is an iterative optimization algorithm), our proposed solution also has a very wide range of applications, and can be used as a benchmark algorithm for the transceiver optimization in many complicated MIMO systems. The details of the WMMSE algorithm are given in the appendix.

VII. SUMMARIES

In this section, we summarize our work, clarify our distinct contributions for each of the problems considered in previous sections, and explain the connections among the problems. First of all, the major contribution of this paper is the proposal of a fundamental framework to derive the optimal structure of the transmission covariance matrix based on KKT conditions. Since KKT conditions are necessary conditions for the optimal solutions, the structure derived from KKT conditions must be held by the optimal solutions, i.e., the optimal solutions must have the structure derived from the KKT conditions. This is applicable to convex optimization problems, and nonconvex ones alike. In the following, our specific contributions of the aforementioned optimization problems are explained in details.

For the capacity maximization problem **P1** and the MSE minimization problem **P2** in SU MIMO systems with perfect CSI and a weighted sum power constraint, the optimal solutions have been derived in the literature [9], [10]. But our proposed method is different in the following three aspects. First, we solve the two optimizations using the same framework and case-by-case studies are avoided. Second, the proposed proofs are simpler and more rigorous. While the derivations in [9] takes two steps, i.e., deriving the diagonalizable structure based on matrix inequality and deriving water-filling solution based on KKT conditions, our work needs only one step from the KKT conditions to derive the optimal solutions. As pointed out in [34], the work in [10] suffers from the turning-off effect, while our work successfully resolve this problem. Thirdly, the optimal solutions given in Conclusions 1 and 2 are both in closed-form.

For the capacity maximization problem **P3** and the MSE minimization problem **P4** in SU MIMO systems under perfect CSI and multiple weighted power constraints, our distinct contributions are also three-fold. First, although **P3** has been studied in [35], our proposed method is simpler and overcomes the turning-off effect. Further, it is waived from the limitation that the channel matrix must be column or row full rank. Second, for **P4**, no solution has been discovered before. Based on the proposed framework, the optimal solution structure is derived for this problem. Third, our work reveals that the effect of multiple weighted constraints are in nature equivalent to a weighted power constraint by comparing the solutions for **P3** and **P4** with those for **P1** and **P2**. Again, the optimal solutions given in Conclusions 3 and 4 are both in closed-form.

For the capacity maximization **P5** and robust MSE minimization **P6** in SU MIMO systems with imperfect CSI under a sum power constraint, there have been some studies in the literature [26]–[29], but they are for special cases with only transmit correlation or receive correlation. This work considers the general case with both transmit and receive correlation, where the structures of the optimal solutions are derived and given in Conclusions 5 and 6. It should be noted that that both **P5** and **P6** are nonconvex and therefore the KKT conditions are only necessary conditions for the optimal solutions. For the special cases with only transmit correlation or receive correlation, our derived optimal solutions are in closed-form as given by Conclusions 5.1, 5.2, 6.1, and 6.2. Compared with our previous work in [26], the derivation logic in this paper is largely different and considerably simpler. Compared with the works in [28], [29], our results do not suffer from the turning-off effect.

The more complicate capacity maximization **P7** and MSE minimization **P8** for MU MIMO

systems under imperfect CSI and multiple weighted power constraints, to our best knowledge, are largely open in existing literature. The structures of the optimal solutions for **P7** and **P8** are given in Conclusions 7 and 8. Due to the generality and high complexity of the problems, the results are in complicated form and iterative schemes such as fixed point algorithm are needed to compute the solutions. Further, we discover that in the special case with only transmit correlation, the optimal solutions can be derived in closed-form as given in Conclusions 7.1 and 8.1. These cases have important practical meanings as there are transformable to the MIMO training design problems [28].

For MU MIMO systems, **P9** and **P11** are the sum-capacity maximization problems under perfect CSI and multiple weighted power constraints for the uplink and the downlink respectively. Their counterparts with imperfect CSI are presented as **P10** and **P12**. Based on the proposed framework, the optimal solution structures are derived for these problems and given in Conclusions 9-12. The problem **P9** was studied in [21]. But our proposed method is more straightforward and avoids the turning-off effect. The problems **P10**, **P11**, **P12** have been open in existing literature. Comparing the results, it can be discovered that multiple weighted power constraints have the same impact as CSI errors in MU MIMO uplink. It is also revealed that in the special case of MU MIMO uplink with sum power constraint and only receive correlation, the optimal solution is in closed-form as given in Conclusion 10.1. The general solutions given in Conclusions 10, 11, 12 need iterative numerical algorithms to solve them.

Finally, the general MIMO networks is investigated in which there are multiple communication links and on each link there are multiple sources communicate with multiple destinations. The capacity maximization problem under imperfect CSI is modeled as **P13**, which has been an open issue. The optimal structure for the solution is given by Conclusion 13 and can be solved iteratively. Though the network topology is very complicated and general, with the proposed link-based modeling and the fundamental framework in Theorem 1, the structure of the solution is obtained with simple and clean derivation logic. Our result shows the impacts of different system components and can facilitate the transceiver optimization for general MIMO networks.

Remark 3: Centralized optimization requires full CSI at the processing center. For networks consisting of a large number of nodes, timely CSI sharing among all nodes is very challenging or even impossible. Thus distributed optimization algorithms are preferred, which requires local or limited CSI only. Nowadays, great efforts have been devoted to distributed designs. The key challenge in distributed designs is how to decompose the overall optimization problem

into a series of low complexity subproblems to be handled at different nodes with limited information sharing among these subproblems. A common practice is to scrutinize the centralized optimization problem or its solution structure to find a viable decomposition. In our work, the structures of the optimal solutions for many MIMO design problems are derived, which may facilitate distributed algorithm designs. But as this paper is on the centralized MIMO designs based on KKT conditions, distributed algorithms are out of the main scope.

VIII. NUMERICAL RESULTS

In this section, the importance of the water-filling structure in transmission covariance matrix design is demonstrated by numerical results. Several representative examples are chosen. Each point in simulation figures is an average over 500 independent channel realizations.

A. Simulation Results on MU MIMO Uplink

For the MU-MIMO uplink, we consider a system where two multi-antenna users each with 4 antennas communicate with a base station equipped with 8 antennas. The signal-to-noise ratio (SNR) of the k^{th} user is defined as P_k/σ_n^2 where P_k is the sum transmit power across all transmit antennas of User k and σ_n^2 is the noise covariance at each receive antenna of the base station. For simplicity, in our simulation, the same SNR value is used for both users, i.e., $P_1/\sigma_n^2 = P_2/\sigma_n^2 = P/\sigma_n^2$. Per-antenna power constraint is considered for each user, where the power limit for the four antennas are set as 1.6, 1.2, 0.8, 0.4, respectively. In general, the power ratios between different antennas can be arbitrarily chosen. Here we set the power limits to be significantly different so that the difference from the case with a sum power constraint is large enough. The widely used Kronecker correlation model is adopted, i.e., $[\mathbf{R}_R]_{i,j} = r_r^{|i-j|}$ and $[\mathbf{R}_{T,k}]_{i,j} = r_{t_k}^{|i-j|}$. Note that as \mathbf{R}_R denotes the receive antenna correlation, in the uplink it is the same for different users.

For the perfect CSI case, the capacity maximization under per-antenna power constraint is a convex optimization problem and can be efficiently solved by numerical algorithms in CVX package [44], i.e., interior point algorithm. In Fig. 2, the sum-capacity of the proposed solution is compared with that of the solution obtained from CVX. It can be seen that the proposed closed-form solution has the same performance as the numerical solutions for different correlation parameters.




Fig. 2. The performance comparisons between the proposed closed-form solution and the solution computed by CVX for MU MIMO uplink.

B. Simulation Results on MIMO Networks

For MIMO networks, a system with four nodes including two sources and two destinations is considered. All nodes are equipped with 4 antennas. Source 1 wants to communicate with both destinations. Meanwhile, Source 2 also wants to communicate with both Destinations. At each source node, the per-antenna power constraints are set to be 2×1.6 , 2×1.2 , 2×0.8 , 2×0.4 (As each source simultaneous communicates with two destinations, the power limits is doubled). The estimated channel matrix is generated according to $\bar{\mathbf{H}}_k = \mathbf{R}_{R,k}^{1/2} \bar{\mathbf{H}}_{W,k} \mathbf{R}_{T,k}^{1/2}$ [27]. As discussed in [27], this model corresponds to some practical channel estimators. The elements of $\bar{\mathbf{H}}_{W,k}$ and $\mathbf{H}_{W,k}$ are i.i.d. Gaussian random variables. The variance of the elements of $\mathbf{H}_{W,k}$ is set to be σ_e^2 and that of $\bar{\mathbf{H}}_{W,k}$ is $1 - \sigma_e^2$. Thus, elements of \mathbf{H}_k have unit-variance. Two algorithms are chosen as performance benchmarks. For the first one, the two signal covariance matrices at each source are set to be diagonal matrices satisfying the per-antenna power constraints. The other benchmark algorithm is [the WMMSE algorithm, the details of which are provided in the](#)




Fig. 3. The performance comparison between the proposed solution, the fixed diagonal solution, and the WMMSE solution for MIMO network with perfect CSI when $r_t = 0.4$ and $r_r = 0.5$.

appendix..

In Fig. 3, the sum-capacity is shown for case of perfect CSI. It can be seen that the proposed solution has much better performance than both benchmarks. The first benchmark solution has the worst performance as it does not consider the mutual interference between different signals. The WMMSE solution performs better than the fixed diagonal solution as it optimizes the mutual interference. For the case of imperfect CSI, the sum-capacity performance is shown in Fig. 4. It can be observed that the proposed solution has better performance than its non-robust counterpart that takes the estimated CSI as the true CSI.

IX. CONCLUSIONS

For MIMO systems, the key task of many transceiver optimization problems is to optimize the covariance matrices of the transmitted signals. In this paper, a general unified framework was proposed for deriving the water-filling structures of the optimal covariance matrices based on




Fig. 4. The performance comparisons between the robust solution and non-robust solution for MIMO networks when $r_t = 0.4$ and $r_r = 0.5$.

KKT conditions. From the general solution, interesting and important underlying relationships among solutions of different MIMO optimization designs can be revealed, which help us understand related existing works much better. The general framework and solution can be applied to a wide range of applications such as complicated MIMO networks with multiple communication links and systems with imperfect CSI. The performance of the proposed solution was evaluated by numerical results. It was discovered that our proposed solutions have higher capacity for MIMO transceiver optimizations in complicated network settings than the WMMSE algorithm.

APPENDIX A

THE WMMSE ALGORITHM

To our best knowledge, transferring sum-rate or sum-capacity maximization into a WMMSE problem was firstly proposed in [42]. Following that, extensions were given by other researchers. In [43], the authors extended the WMMSE algorithm to MIMO interference broadcasting systems. In [41], the WMMSE algorithm was extended to more general network systems, e.g.,

multi-hop cooperative networks with multiple sources, multiple relays, and multiple destinations, where all nodes are equipped with multiple antennas and each source node communicates with all destination nodes. The channel information was assumed to be imperfect with Gaussian errors.

In the following, a brief description to the WMMSE algorithm used in our simulation is given. In the following, a brief description to the WMMSE algorithm used in our simulation is given. We would like to highlight that the following algorithm is more general than the one in [43] and applies to distributed network MIMO systems with channel estimation errors. It can be directly reduced to work for the perfect CSI case by the setting the channel error to be zero.

On Link r , the transceiver model is

$$\mathbf{y}_r = \mathbf{H}_r \mathbf{F}_r \mathbf{s}_r + \mathbf{v}_r, \quad (117)$$

where \mathbf{y}_r is the received signal vector at the destination of Link r . The matrix \mathbf{H}_r comprises the channel matrices over which the signals are transmitted to the destination, i.e.,

$$\mathbf{H}_r = [\bar{\mathbf{H}}_{i_1}, \bar{\mathbf{H}}_{i_2}, \dots, \bar{\mathbf{H}}_{i_{N_r}}], \quad i_n \in \psi_{D,r}, \quad (118)$$

where N_r is the cardinality of set $\psi_{D,r}$. The matrix \mathbf{F}_r is block diagonal, i.e.,

$$\mathbf{F}_r = \text{diagblk}\{[\mathbf{F}_{r,1}, \mathbf{F}_{r,2}, \dots, \mathbf{F}_{r,N_r}]\}, \quad (119)$$

whose n^{th} diagonal element is the corresponding precoding matrix for $\bar{\mathbf{H}}_{i_n}$. The vector \mathbf{s}_r contains the desired signals at the destination via stacking all the signal vectors of the sources. Without loss of generality, the covariance matrix of \mathbf{s}_r is assumed to be the identity matrix. Finally, \mathbf{v}_r is the composite vector of the additive noises and the interference signals at the destination of Link r and its covariance matrix is

$$\begin{aligned} \Sigma_r = \mathbf{R}_{\mathbf{n}_r} &+ \sum_{i \in \psi_{I,r}} \left(\bar{\mathbf{H}}_i \sum_{j \in \phi_i} \mathbf{Q}_j \bar{\mathbf{H}}_i^H \right) \\ &+ \sum_{i \in \psi_{D,r} \cup \psi_{I,r}} \text{Tr} \left(\sum_{j \in i \cup \phi_i} \mathbf{Q}_j \mathbf{R}_{T,i} \right) \mathbf{R}_{R,i}. \end{aligned} \quad (120)$$

For the perfect CSI case, the third term on the righthand side of (120) is zero.

Based on the transceiver model of Link r , the weighted MSE formula is

$$\sum_r \text{Tr} \left(\mathbf{W}_r \mathbb{E} \{ (\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r) (\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r)^H \} \right), \quad (121)$$

where the positive semi-definite matrix \mathbf{W}_r is the weighting matrix for Link r . Based on (121), the WMMSE optimization problem can be formulated as [34]

$$\begin{aligned} \min_{\mathbf{F}_r, \mathbf{G}_r, \mathbf{W}_r} \quad & \sum_r \text{Tr} \left(\mathbf{W}_r \mathbb{E} \left\{ (\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r)(\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r)^H \right\} \right) \\ & - \sum_r \log |\mathbf{W}_r| \\ \text{s.t.} \quad & \text{multiple weighted power constraints.} \end{aligned} \quad (122)$$

In finding the optimal solution, the alternative optimization is used where one set of the matrices is optimized with the other two sets fixed. It is obvious that for any given \mathbf{G}_r 's and \mathbf{W}_r 's, the weighted MSE minimization under weighted transmit power constraints is a standard quadratic matrix programming problem [41]. Thus, the optimal \mathbf{F}_r 's can be efficiently solved by standard SOCP, SDP, or other similar convex optimization algorithms. When \mathbf{F}_r 's and \mathbf{W}_r 's are fixed, the optimal \mathbf{G}_r 's are exactly the LMMSE equalizers derived based on the complex matrix derivative of (121). Finally, for given \mathbf{G}_r 's and \mathbf{F}_r 's, the optimal \mathbf{W}_r is given by the following formula

$$\mathbf{W}_r = \left(\mathbb{E} \{ (\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r)(\mathbf{G}_r \mathbf{y}_r - \mathbf{s}_r)^H \} \right)^{-1}. \quad (123)$$

Thus the corresponding WMMSE optimization problem becomes the sum capacity maximization [34]. In a nutshell, the WMMSE algorithm is an iterative alternative optimization algorithm with guaranteed convergence.

REFERENCES

- [1] H. Baligh, M. Hong, W. C. Liao, et al., "Cross-Layer Provision of Future Cellular Networks: A WMMSE-based approach," *IEEE Signal Process. Mag.*, vol. 31, no. 6, pp. 56–68, Nov. 2014.
- [2] S. Barbarossa, S. Sardellitti and P. Di Lorenzo, "Communicating While Computing: Distributed mobile cloud computing over 5G heterogeneous networks," *IEEE Signal Process. Mag.*, vol. 31, no. 6, pp. 45–55, Nov. 2014.
- [3] D. Wubben, P. Rost, J. S. Bartelt, et al., "Benefits and Impact of Cloud Computing on 5G Signal Processing: Flexible centralization through cloud-RAN," *IEEE Signal Process. Mag.*, vol. 31, no. 6, pp. 35–44, Nov. 2014.
- [4] Banelli, S. Buzzi, G. Colavolpe, et al., "Modulation Formats and Waveforms for 5G Networks: Who Will Be the Heir of OFDM?: An overview of alternative modulation schemes for improved spectral efficiency," *IEEE Signal Process. Mag.*, vol. 31, no. 6, pp. 80–93, Nov. 2014.
- [5] S. M. Razavizadeh, M. Ahn and I. Lee, "Three-Dimensional Beamforming: A new enabling technology for 5G wireless networks," in *IEEE Signal Processing Magazine*, vol. 31, no. 6, pp. 94–101, Nov. 2014.
- [6] Z. Zhang, X. Chai, K. Long, Athanasios V. Vasilakos and L. Hanzo, "Full-Duplex Techniques for 5G Networks: Self-Interference Cancellation, Protocol Design and Relay Selection," *IEEE Commun. Magazine*, vol. 53, no. 5, pp. 128–137, May 2015.

- [7] F. Rusek, D. Persson, B. K. Lau, et al., "Scaling Up MIMO: Opportunities and Challenges with Very Large Arrays," *IEEE Signal Process. Mag.*, vol. 30, no. 1, pp. 40–60, Jan. 2013.
- [8] Z. Zhang, K. Long, J. Wang, F. Dressler, "On Swarm Intelligence Inspired Self-Organized Networking: Its Bionic Mechanisms, Designing Principles and Optimization Approaches," *IEEE Commun. Surv. Tut.*, vol. 16, no. 1, pp. 513–537, FIRST QUARTER 2014.
- [9] I. E. Telatar, "Capacity of multi-antenna Gaussian channels," *European Trans. Commun.*, vol. 10, no. 2, pp. 585–595, Nov.-Dec. 1999.
- [10] H. Sampath, P. Stoica, and A. Paulraj, "Generalized linear precoder and decoder design for MIMO channels using the weighted MMSE criterion," *IEEE Trans. Commun.*, vol. 49, pp. 2198–2206, Dec. 2001.
- [11] D. P. Palomar, J. M. Cioffi, and M. A. Lagunas, "Joint Tx-Rx beamforming design for multicarrier MIMO channels: A unified framework for convex optimization," *IEEE Trans. Signal Process.*, vol. 51, no. 9, pp. 2381–2401, Sep. 2003.
- [12] A. Scaglione, P. Stoica, S. Barbarossa, G. B. Giannakis, and H. Sampath, "Optimal designs for space-time linear precoders and decoders," *IEEE Trans. Signal Process.*, vol. 50, no. 5, pp. 1051–1064, May 2002.
- [13] J. Yang and S. Roy, "On joint transmitter and receiver optimization for mutiple-input-mutiple-output (MIMO) transmission systems," *IEEE Trans. Commun.*, vol. 42, no. 12, pp. 3221–3231, Dec. 1994.
- [14] D. Schizas, G. B. Giannakis, and Z.-Q. Luo, "Distributed estimation using reduced dimensionality sensor observations," *IEEE Trans. Signal Process.*, vol. 55, pp. 4284–4299, Aug. 2007.
- [15] W. Guan and H. Luo, "Joint MMSE transceiver design in non-regenerative MIMO relay systems," *IEEE Commun. Lett.*, vol. 12, pp. 517–519, July 2008.
- [16] H. Sun and Z. Ding, "Iterative transceiver design for MIMO ARQ retransmissions with decision feedback detection," *IEEE Trans. Signal Process.*, vol. 55, pp. 3405–3416, July 2007.
- [17] W. Yu and J. M. Cioffi, "Sum capacity of Gaussian vector broadcast channels," *IEEE Trans. Infor. Theory*, vol. 50, no. 9, pp. 1875–1892, Sep. 2004.
- [18] C. Xing, Z. Fei, Y. Zhou, Z. Pan, and H. Wang, "Transceiver designs with matrix-version water-filling architecture under mixed power constraints," *Science China-Information Sciences*, vol. 59, no. 10, pp. 1–13, Oct. 2016.
- [19] A. Liu, Y. Liu, H. Xiang, and W. Luo, "MIMO B-MAC interference network optimization under rate constraints by polite water-filling and duality," *IEEE Trans. Signal Process.*, vol. 59, no. 1, pp. 263–276, Jan. 2011.
- [20] O. Munoz-Medina, J. Vidal, and A. Agustin, "Linear transceiver design in nonregenerative relays with channel state information," *IEEE Trans. Signal Process.*, vol. 55, pp. 2198–2206, June 2007.
- [21] Y. Yu and Y. Hua, "Power allocation for a MIMO relay system with multiple-antenna users," *IEEE Trans. Signal Process.*, vol. 58, no. 5, pp. 2823–2835, May 2010.
- [22] C. Xing, D. Li, S. Ma, Z. Fei and J. Kuang, "Robust transceiver designs for MIMO-OFDM systems based on cluster water-filling," *IEEE Commun. Lett.*, vol. 17, no. 7, pp. 1451–1454, July 2013.
- [23] F. Gao, T. Cui, and A. Nallanathan, "Optimal training design for channel estimation in decode-and-forward relay networks with individual and total power constraints," *IEEE Trans. Signal Process.*, vol. 56, no. 12, pp. 5937–5949, Dec. 2008.
- [24] W. Yu and T. Lan, "Transceiver optimization for the multi-antenna downlink with per-antenna power constraints," *IEEE Trans. Signal Process.*, vol. 55, no. 6, pp. 2646–2660, June 2007.
- [25] A. Liu, Y. Liu, H. Xiang, and W. Luo, "Polite water-filing for weighted sum-rate maximization in MIMO B-MAC networks under multiple linear constraints," *IEEE Trans. Signal Process.*, vol. 60, no. 2, pp. 834–847, Feb. 2012.
- [26] C. Xing, S. Ma, and Y. Zhou, "Matrix-monotonic optimization for MIMO systems," *IEEE Trans. Signal Process.*, vol. 63, no. 2, pp. 334–348, Jan. 2015.

- [27] C. Xing, Z. Fei, S. Ma, Y.-C. Wu, and H. V. Poor, "A general robust linear transceiver design for amplify-and-forward multi-hop MIMO relaying systems," *IEEE Trans. Signal Process.*, vol. 61, pp. 1196–1209, Mar. 2013.
- [28] M. Ding and S. D. Blostein, "MIMO minimum total MSE transceiver design with imperfect CSI at both ends," *IEEE Trans. Signal Process.*, vol. 57, no. 3, pp. 1141–1150, Mar. 2009.
- [29] M. Ding and S. D. Blostein, "Maximum mutual information design for MIMO systems with imperfect channel knowledge," *IEEE Trans. Infor. Theory*, vol. 56, no. 10, pp. 4793–4801, Oct. 2010.
- [30] S. Boyd and L. Vandenberghe, *Convex Optimization*. Cambridge University Press, 2004.
- [31] A. W. Marshall and I. Olkin, *Inequalities: Theory of Majorization and Its Applications*. New York: Academic Press, 1979.
- [32] C. Xing, Y. Ma, Y. Zhou, and F. Gao, "Transceiver optimization for multi-hop communications with per-antenna power constraints," *IEEE Trans. Signal Process.*, vol. 64, no. 6, pp. 1519–1534, March 2016.
- [33] C. Xing, F. Gao, and Y. Zhou, "A framework for transceiver designs for multi-hop communications with covariance shaping constraints," *IEEE Trans. Signal Process.*, vol. 63, no. 15, pp. 3930–3945, Aug. 2015.
- [34] C. Xing, Y. Jing, and Y. Zhou, "On weighted MSE model for MIMO transceiver optimization" to Appear in *IEEE Trans. Vehic. Techn.*.
- [35] V. Mai, "MIMO Capacity with Per-Antenna Power Constraint," *ArXiv e-prints:1106.5039v1*, Jun. 2011.
- [36] S. A. Jafar and A. J. Goldsmith, "Multiple-antenna capacity in correlated Rayleigh Fading with Channel Covariance Information," *IEEE Trans. Wireless Commun.*, vol. 4, no. 3, pp. 990–997, May 2005.
- [37] A. Goldsmith, S. Jafar, N. Jindal, and S. Vishwanath, "Capacity limits of MIMO channels," *IEEE Journal Select. Areas Commun.*, vol. 21, no. 5, pp. 684–702, June 2003.
- [38] S. Vishwanath, N. Jindal, and A. Goldsmith, "Duality, achievable rates, and sum-rate capacity of Gaussian MIMO broadcast channels," *IEEE Trans. Infor. Theory*, vol. 49, no. 10, pp. 2658–2668, Oct. 2003.
- [39] X. Tang and Y. Hua, "Optimal design of non-regenerative MIMO wireless relays," *IEEE Trans. Wireless Commun.*, vol. 6, pp. 1398–1407, Apr. 2007.
- [40] S. Kay, *Fundamental of Statistical Signal Processing: Estimation Theory*. Englewood Cliffs, NJ: Prentice-Hall, 1993.
- [41] C. Xing, S. Li, Z. Fei, and J. Kuang, "How to understand linear minimum mean square error transceiver design for multiple input multiple output systems from quadratic matrix programming," *IET Commun.*, vol. 7, no. 12, pp. 1231–1242, Aug. 2013.
- [42] S. S. Christensen, R. Argawal, E. de Carvalho, and J. M. Cioffi, "Weighted sum-rate maximization using weighted MMSE for MIMO-BC beamforming design," *IEEE Trans. Wireless Commun.*, vol. 7, no. 12, pp. 4792–4799, Dec. 2008.
- [43] Q. Shi, M. Razaviyayn, Z. Q. Luo, and C. He, "An iteratively weighted mmse approach to distributed sum-utility maximization for a MIMO interfering broadcast channel," *IEEE Trans. Signal Process.*, vol. 59, no. 9, pp. 4331–4340, Sep. 2011.
- [44] M. C. Grant and S. P. Boyd, *The CVX Users' Guide* (Release 2.1) CVX Research, Inc., 2015