

A Globally Stable Practically Implementable PI Passivity-based Controller for Switched Power Converters

Alexey Bobtsov¹, Romeo Ortega^{1,2}, Nikolay Nikolaev¹, Wei He^{*3}

¹Department of Control Systems and Robotics, ITMO University, Kronverkskiy av. 49, Saint Petersburg, 197101, Russia, (e-mail: bobtsov@mail.ru, nikona@yandex.ru)

²Université Paris-Saclay, CNRS, CentraleSupélec, Laboratoire des signaux et systèmes, 91190, Gif-sur-Yvette, France, (e-mail: ortega@lss.supelec.fr)

³School of Automation, Nanjing University of Information Science & Technology, Nanjing, China, (e-mail: hwei@nuist.edu.cn)

Abstract

In this paper we propose a PI passivity-based controller, applicable to a large class of switched power converters, that ensures global state regulation to a desired equilibrium point. A solution to this problem was reported in [12] but it requires *full state-feedback*, which makes it practically unfeasible. To overcome this limitation we construct a *state observer* that is implementable with measurements that are available in practical applications. The observer reconstructs the state in *finite-time*, ensuring global convergence of the PI. The excitation requirement for the observer is very weak and is satisfied in normal operation of the converters. Simulation results illustrate the excellent performance of the proposed PI.

1 Introduction

Switching power converters are, nowadays, an essential component of most electrical engineering applications. The ever increasing performance requirements on these applications translates into more stringent specifications on the quality of the converters control. The dynamics of power converters is highly nonlinear, even with fast switching when their averaged model is valid, and the validity of their linear approximation is restricted to a small neighborhood of the corresponding operating point [16]. The vast majority of power converters are controlled with classical PI loops and there is a widely accepted belief that, *if* they are properly tuned, their behavior is acceptable [17, 30, 34]. The qualifier “if” in the previous sentence is very important because, if the range of operation of the system to be controlled is “wide”—as it is required in modern applications—the task of tuning the gains of a PI (or, for that matter, of any other controller for nonlinear systems) is far from obvious. Unfortunately, to date, the only systematic procedure to carry-out this task, is invoking standard linear systems theory arguments, *e.g.*, pole location, stability margins, and applying them to the linearized model of the converter. Various procedures to re-tune the PI gains, including gain-scheduling [32], relay auto-tuning [5] and adaptation [20], have been proposed but they all suffer from, well-documented, serious limitations and drawbacks [6, 27].

The main objective of this paper is to propose a practically implementable PI controller, applicable to a large class of power converters described by average nonlinear models, which has the following properties.

- F1** *Global stability* of the closed-loop is guaranteed *for all* positive values of the PI tuning gains.
- F2** By “practically implementable” we mean that it *does not* assume the availability of the full state of the system, and it only requires the measurements used in standard PIs.
- F3** The proposed PI has a very close connection with the widely popular PQ instantaneous power controllers of [1].

Providing a theoretical framework for controller design is a topic of paramount importance. On one hand, it allows power engineer practitioners to apply the control law with confidence and, on the other hand, considerably simplifies the commissioning stage, which now that stability is guaranteed for all positive tuning gains, can concentrate on the transient performance specifications.

The approach adopted in this paper is in the line of [22] which relies on the use of energy balance concepts to control a system. Unlike most classical nonlinear control techniques found in the literature, which try to impose some predetermined dynamic behavior—usually through nonlinearity cancellation, domination of nonlinearities and high gain—energy-based methods exploit and respect the physical structure of the system. Passivity-based control (PBC) is the generic name of this controller design methodology, which achieves stabilization by exploiting the passivity properties of the system. Due to the physical appealing that this methodology has, a vast literature has been advocated to its application to mechanical, electrical and electromechanical systems, see [9, 21].

Passivity is the key property of power converters that is exploited in this paper. The first time that passivity principles were applied for power converter control is in the foundational paper [28]. It is well-known [21, 31] that wrapping a PI (or a PID) around a passive output ensures input-output stability of the system and convergence to zero of the passive output. In many applications, including power converters, the objective is to drive this output to a value *different* from zero, which is associated with the steady-state behavior of the system. In this case, we are interested in proving that the incremental model is passive. In [25] it was shown that, for a general class of models of power converters, it is possible to define an output signal such that the incremental model is passive—this result was later generalized in several directions in [12, 13]. This fundamental property, called “passivity of the nonlinear incremental model” in [14], is now referred as *shifted passivity* [31] and has played a central role in many recent developments of the control community. In the present context the main interest of this property is that, driving the shifted passive output to zero with a PI control ensures, under a precise condition on the systems dissipation, that the *full state* of the system converges to a desired equilibrium.

The PI controller of [12] has enjoyed a very wide popularity—with more than 120 cites in Google Scholar. However, its main drawback is that it requires the *measurement of the state* that, for technological and economic reasons, is unattainable in most practical applications of power converters. The *main contribution* of this note is to propose an observer that, using standard measurements, reconstructs the system state in *finite-time* giving rise to a, practically reasonable, globally stable PI design. Two additional features of the observer are, on one hand, that convergence of the state estimates is achieved under very weak excitation assumptions usually met in normal power converter operation and, on the other hand, that it does not rely on noise-sensitive high-gain injection or approximate differentiation.

The design of the observer relies on the use of the following two theoretical developments recently reported by the authors.

T1 Parameter Estimation-based Observer (PEBO) design technique first reported in [23], whose main novelty is that it translates the task of state observation into an on-line *parameter estimation* problem. In this work we use a generalization of this design, called GPEBO, recently used in [24] for the state observation of chemical-biological reactors.

T2 To estimate the parameters required by GPEBO, we use the Dynamic Regressor Extension and Mixing (DREM) procedure first proposed in [3]. The central property of DREM is that it generates, out of a q -dimensional Linear Regression Equation (LRE), q *scalar* LREs—one for each of the unknown parameters—considerably simplifying the estimation task and ensuring convergence under very weak excitation assumptions.

The remainder of the paper is organized as follows. In Section 2 we present the mathematical model of the power converters we consider in the paper, recall the state-feedback PI-PBC of [12] and formulate the observer problem, for which we give a solution in Section 3. Simulation results, which illustrate the performance of the proposed PI-PBC, are presented in Section 4. The paper is wrapped-up with concluding

remarks and future research in Section 5.

Notation. I_n is the $n \times n$ identity matrix. For $x \in \mathbb{R}^n$, we denote the Euclidean norm $|x|^2 := x^\top x$. All mappings are assumed smooth. Given a function $f : \mathbb{R}^n \rightarrow \mathbb{R}$ we define the differential operator $\nabla f := \left(\frac{\partial f}{\partial x}\right)^\top$.

2 The PI-PBC of [12] and the Observer Problem Formulation

We consider in this paper switched power converters, with switched external sources, described in port-Hamiltonian (pH) form [11, 31]

$$\dot{x} = \left(J_0 + \sum_{i=1}^m J_i u_i - R \right) \nabla H(x) + \left(G_0 + \sum_{i=1}^m G_i u_i \right) E, \quad (1)$$

where $x(t) \in \mathbb{R}^n$, consisting of inductor fluxes and capacitor charges, is the converter state, which is assumed *unknown*, $u(t) \in \mathbb{R}^m$ is the duty ratio, $E \in \mathbb{R}^n$ is the vector of constant external sources, $J_i = -J_i^\top \in \mathbb{R}^{n \times n}$, $i \in \bar{m} := \{0, \dots, m\}$, are the interconnection matrices, $R = R^\top > 0$ denotes the dissipation matrix, $H : \mathbb{R}^n \rightarrow \mathbb{R}_+$ is the total stored energy, and $G_i \in \mathbb{R}^{n \times n}$, $i \in \bar{m}$, are the input matrices. Assuming, linear capacitors and inductors, we have that

$$H(x) = \frac{1}{2} x^\top Q x,$$

with $Q \in \mathbb{R}^{n \times n}$, $Q > 0$, a diagonal matrix. We assume that all the parameters of the converter are *known*. The model (1) describes the behavior of most power converters used in practice [16, 17, 30, 34].

Control Objective Fix an admissible equilibrium point $x^* \in \mathbb{R}^n$, that is, x^* satisfies

$$0 = \left(J_0 + \sum_{i=1}^m J_i u_i^* - R \right) Q x^* + \left(G_0 + \sum_{i=1}^m G_i u_i^* \right) E, \quad (2)$$

for some $u^* \in \mathbb{R}^m$. Design a controller such that *global state regulation* is achieved, namely, that for all system and controller initial conditions,

$$\lim_{t \rightarrow \infty} x(t) = x^*, \quad (3)$$

with all signals bounded.

2.1 The full-state feedback PI-PBC of [12]

The following *full-state* feedback PI solution to the aforementioned problem was proposed in [12].

Proposition 1. Consider the switched power converter described by (1) in closed loop with the PI-PBC

$$\begin{aligned} \dot{x}_c &= \tilde{y} \\ u &= -K_P \tilde{y} - K_I x_c, \end{aligned} \quad (4)$$

with $K_P = K_P^\top \geq 0$, $K_I = K_I^\top \geq 0$ and

$$\tilde{y} = \mathcal{C}(x - x^*), \quad (5)$$

with $\mathcal{C} \in \mathbb{R}^{m \times n}$ given by

$$\mathcal{C} = \begin{bmatrix} E^\top G_1^\top - (x^*)^\top Q J_1 \\ \vdots \\ E^\top G_m^\top - (x^*)^\top Q J_m \end{bmatrix} Q =: G_N^\top(x^*) Q, \quad (6)$$

For all initial conditions $(x(0), x_c(0)) \in \mathbb{R}^n \times \mathbb{R}^m$ the trajectories of the closed-loop system are bounded and satisfy (3). $\square\square\square$

The proof of Proposition 1 is established in [12] showing that the system (1) in closed-loop with the PI-PBC (4) is described by

$$\dot{\tilde{x}} = \left(J_0 + \sum_{i=1}^m J_i u_i^* - R \right) Q \tilde{x} + G_N(x) \tilde{u}, \quad (7)$$

where the matrix $G_N(\cdot)$ is defined in (6) and we (generically) use the notation $\tilde{(\cdot)} := (\cdot) - (\cdot)^*$. Therefore, the Lyapunov function candidate

$$W(\tilde{x}, \tilde{x}_c) = \frac{1}{2} \tilde{x}^\top Q \tilde{x} + \frac{1}{2} \tilde{x}_c^\top K_I \tilde{x}_c$$

where $x_c^* := K_I^{-1} u^*$, verifies

$$\dot{W} = -\tilde{x}^\top Q R Q \tilde{x} - \tilde{y}^\top K_P \tilde{y}.$$

In [12] it is assumed that the dissipation matrix R is only positive *semidefinite*. Consequently, to ensure asymptotic stability, it is necessary to impose a detectability condition that, as shown in [9, 12, 13, 19], is satisfied in practical converter topologies. For ease of presentation, we strengthen here the assumption on R , which is tantamount to making the physically reasonable assumption that all energy storage elements—that is, inductors and capacitors—are leaky.

Remark 1. In [25] it is shown that, for a classical rectifier, one of the components of the passive output \tilde{y} , defined in (5), is related with the difference between supplied and extracted instantaneous active powers (of a suitably scaled representation) of the rectifier, the second output being the component of the input current. In this way, we make a nice connection with the widely popular *PQ instantaneous power* controllers of [1], where an outer PI loop around the output voltage is used to generate a reference for an inner PI loop acting on the aforementioned power difference. It is also possible to show that driving the passive output to zero can be reinterpreted as a power equalization objective identical to the one used in Akagi's PQ method.

2.2 State observation problem formulation

The main objective of this paper is to design a globally convergent *state observer* that, combined with the PI-PBC of Proposition 1, will give rise to a practically implementable version of it. To pose the observer design problem we assume that there exists a full-rank matrix $C \in \mathbb{R}^{p \times n}$, $p < n$, such that the vector

$$y_m = Cx, \quad (8)$$

is available for measurement. Typically, this signal will be the voltage fed to the converter, the input current flowing into it and/or the voltage provided to the load [16]. It will be shown below that—as expected—the level of excitation required to ensure convergence of the observer will reduce if the number of measurements increases—see Remark 3.

Finite-convergence Time (FCT) Observer Problem Formulation Consider the power converter (1) with *known* parameters and measurable output signals (8). Design a dynamical system

$$\begin{aligned} \dot{\chi} &= F(y_m, \chi) \\ \hat{x} &= H(y_m, \chi) \end{aligned}$$

with $\chi \in \mathbb{R}^{n_\chi}$, such that, for all initial conditions $(x(0), \chi(0)) \in \mathbb{R}^{n+n_\chi}$, all signals remain bounded and there exists $t_c \in [0, \infty)$ such that

$$\hat{x}(t) = x(t), \quad \forall t \geq t_c.$$

Remark 2. Following standard practice in observer theory [7] we assume that the the control u is such that the state trajectories of (1) are bounded.

3 Observer Design

In this section we present the main result of the paper, namely an FCT GPEBO+DREM to reconstruct the state of the system (1) with the measurable outputs (8). The excitation assumption for *global asymptotic* convergence is very weak and, as illustrated in the simulations in Section 5, is satisfied in normal operating conditions of the converters. We also present other asymptotically convergent observers, which have a below par performance with respect to the GPEBO.

3.1 GPEBO+DREM design with FCT

To streamline the presentation of the result we define the matrix

$$\Lambda(u) := \left(J_0 + \sum_{i=1}^m J_i u_i - R \right) Q, \quad (9)$$

and make the following sufficient excitation condition [18].

Assumption 1. Fix a small constant $\mu \in (0, 1)$. There is a time $t_c > 0$ such that

$$\int_0^{t_c} \Delta^2(\tau) d\tau \geq -\frac{1}{\gamma} \ln(1 - \mu). \quad (10)$$

Proposition 2. Consider the system (1) with the measurable outputs (8). Define the GPEBO via

$$\dot{\xi} = \Lambda(u)\xi + \left(G_0 + \sum_{i=1}^m G_i u_i \right) E \quad (11a)$$

$$\dot{\Phi} = \Lambda(u)\Phi, \quad \Phi(0) = I_n \quad (11b)$$

$$\dot{Y} = -\lambda Y + \lambda \Phi^\top C^\top (C\xi - y_m) \quad (11c)$$

$$\dot{\Omega} = -\lambda \Omega + \lambda \Phi^\top C^\top C \Phi \quad (11d)$$

$$\dot{\omega} = -\gamma \Delta^2 \omega, \quad \omega(0) = 1 \quad (11e)$$

$$\dot{\hat{\theta}} = \gamma \Delta (\mathcal{Y} - \Delta \hat{\theta}), \quad (11f)$$

with $\lambda > 0$, $\gamma > 0$, free tuning parameters and

$$\mathcal{Y} = \text{adj}\{\Omega\}Y, \quad \Delta = \det\{\Omega\}, \quad (12)$$

where $\text{adj}\{\cdot\}$ is the adjunct matrix. The state estimate

$$\hat{x} = \xi + \Phi \hat{\theta}_{\text{FCT}} \quad (13)$$

where we introduced the vector

$$\hat{\theta}_{\text{FCT}} := \frac{1}{1 - \omega_c} \left[\hat{\theta} - \omega_c \hat{\theta}(0) \right] \quad (14)$$

and ω_c is defined via the clipping function

$$\omega_c = \begin{cases} \omega & \text{if } \omega < 1 - \mu, \\ 1 - \mu & \text{if } \omega \geq 1 - \mu. \end{cases}$$

ensures that, for all initial conditions $(\xi(0), Y(0), \Omega(0), \hat{\theta}(0)) \in \mathbb{R}^n \times \mathbb{R}^n \times \mathbb{R}^{n \times n} \times \mathbb{R}^n$, we have that

$$\hat{x}(t) = x(t), \quad \forall t > t_c \quad (15)$$

with all signals bounded provided Δ verifies Assumption 1.

Proof. Define the signal $e := x - \xi$. From (1) and (11a) one gets the linear time-varying (LTV) system

$$\dot{e} = A(t)e,$$

where we have defined $A(t) := \Lambda(u(t))$. The state transition matrix of this LTV system satisfies the equation (11b) [26], consequently

$$e := \Phi\theta,$$

where $\theta := e(0)$ is an *unknown* constant vector. Using the definition of e we get

$$x = \xi + \Phi\theta. \quad (16)$$

Next, our task is to estimate the parameter θ so that we can reconstruct the state x using (16). Towards this end, we use the output measurements (8) to get

$$y_m = Cx = C\xi + C\Phi\theta,$$

which we can write as a LRE

$$y_m - C\xi = C\Phi\theta. \quad (17)$$

Following the DREM procedure [3] we carry out the next operations

$$\begin{aligned} \Phi^\top C^\top (y_m - C\xi) &= \Phi^\top C^\top C\Phi\theta && (\Leftarrow \Phi C^\top \times (17)) \\ \frac{\lambda}{p+\lambda} [\Phi^\top C^\top (y_m - C\xi)] &= \frac{\lambda}{p+\lambda} [\Phi^\top C^\top C\Phi]\theta && (\Leftarrow \frac{\lambda}{p+\lambda} [\cdot]) \\ Y &= \Omega\theta && (\Leftrightarrow (11c), (11d)) \\ \text{adj}\{\Omega\}Y &= \text{adj}\{\Omega\}\Omega\theta && (\Leftarrow \text{adj}\{\Omega\} \times) \\ \mathcal{Y} &= \Delta\theta && (\Leftrightarrow (12)). \end{aligned}$$

where, to obtain the last identity, we have used the fact that for any (possibly singular) $n \times n$ matrix M we have $\text{adj}\{M\}M = \det\{M\}I_n$. Replacing the latter equation in (11f) yields the error dynamics

$$\dot{\tilde{\theta}} = -\gamma\Delta^2\tilde{\theta}, \quad (18)$$

where $\tilde{\theta} := \hat{\theta} - \theta$. Since Δ is a *scalar*, the solution of the latter equation is given by

$$\tilde{\theta} = e^{-\gamma \int_0^t \Delta^2(s) ds} \tilde{\theta}(0), \quad \forall t \geq 0. \quad (19)$$

Now, notice that the solution of (11e) is

$$w(t) = e^{-\gamma \int_0^t \Delta^2(s) ds}.$$

The key observation is that, using the equation above in (19), and rearranging terms we get that

$$[1 - w(t)]\theta = \hat{\theta}(t) - w(t)\hat{\theta}(0). \quad (20)$$

Finally, observe that w is a non-increasing function and, under the interval excitation Assumption 1, we have that

$$w_c(t) = w(t) < \mu, \quad \forall t \geq t_c,$$

The proof of state estimation convergence is completed noting that the latter implies that

$$\frac{1}{1 - \omega_c(t)} \left[\hat{\theta}(t) - \omega_c(t)\hat{\theta}(0) \right] = \theta, \quad \forall t \geq t_c,$$

that, in view of (13) and (16), implies (15).

We proceed now to prove that all signals of the GPEBO are bounded. First, notice that (11a) is a copy of the converter dynamics (1). Therefore, in view of Remark 2, ξ is bounded. To prove boundedness of Φ , consider the mapping $U(\Phi) = \frac{1}{2}\text{tr}\{\Phi^\top Q\Phi\}$ whose derivative, along the trajectories of (11b) is

$$\begin{aligned}\dot{U} &= \sum_{i=1}^n \Phi_i^\top Q \Lambda(u) \Phi_i \\ &= \sum_{i=1}^n \Phi_i^\top Q R Q \Phi_i \leq -cU,\end{aligned}\tag{21}$$

where $\text{tr}\{\cdot\}$, denotes the trace, $\Phi_i \in \mathbb{R}^n$ is the i -th column of the matrix Φ and $c > 0$. Now, from (11d) we see that boundedness of Φ implies boundedness of Ω . Finally, the fact that Y is bounded, follows from the fact that $Y = \Omega\theta$. This completes the proof. $\square\square\square$

Remark 3. We make the observation that, as the number of measurements p increases, the sufficient excitation Assumption 1 is “easier” to satisfy. In the extreme case when $p = n$ the matrix Ω is positive definite, hence Δ is positive and bounded away from zero. In any case, given the monotonicity of Δ , the sufficient excitation condition of Assumption 1 is “almost always” satisfied.

Remark 4. In the time interval $[0, t_c]$ the FCT estimated parameter (14) takes the form

$$\hat{\theta}_{\text{FCT}} := \frac{1}{\mu} \left[\hat{\theta} - (1 - \mu)\hat{\theta}(0) \right].$$

Therefore, if we choose the constant μ close to zero there is a potential *high-gain* injection. On the other hand, since the right hand side of (10) becomes smaller, this “reduces” the size of t_c . The solution of this compromise is further complicated by the fact that the adaptation gain γ also appears into the picture. Unfortunately, this conundrum makes the tuning stage of the estimator quite complicated—a fact that is observed in the simulations of Section 5, where the choices of the constants λ , γ and μ are done via trial-and-error.

3.2 Other globally asymptotically convergent observers

In this subsection we present three alternative observer designs that, alas, exhibit some drawbacks, which are conspicuous by their absence from the FCT-GPEBO of Proposition 2.

An open-loop emulator

In the proof of Proposition 2 it was shown that the state transition matrix converges, exponentially fast, to zero, see (21). Consequently, the simplest way to reconstruct the system state is by setting $\hat{x} = \xi$, which from (16) and (21) has the property that $\hat{x}(t) \rightarrow x(t)$, (exp). This type of constructions, known as *emulators*, are the dominant technique in process control [10], where they are called “asymptotic observers”. There are two main drawbacks to this approach: first, the convergence rate is fixed by the system dynamics, in this case by the smallest eigenvalue of the matrix $Q^\top R Q$, and cannot be tuned. Second, being an open-loop construction, it suffers from serious robustness problems, being highly sensitive to parameter uncertainty and noise. An alternative to overcome these drawbacks in process control applications is precisely GPEBO, and it was reported in [24].

A Kalman-Bucy filter

Evaluating u along trajectories, as done in the proof of Proposition 2, it is possible to view the system (1) and (8) as an LTV system

$$\begin{aligned}\dot{x} &= A(t)x + B(t) \\ y_m &= Cx,\end{aligned}$$

with $B(t) := (G_0 + \sum_{i=1}^m G_i u_i(t)) E$. Then, we can design a classical Kalman-Bucy filter (KBF) for it [2]

$$\begin{aligned}\dot{\hat{x}} &= [A(t) - HC^\top C] \hat{x} + B(t) \\ \dot{H} &= HA^\top(t) + A(t)H - HC^\top CH + S,\end{aligned}$$

with $H(0) > 0$, $S > 0$, which ensures $\lim_{t \rightarrow \infty} |\hat{x}(t) - x(t)| = 0$ (exp), provided the pair $(A(t), C)$ is uniformly completely observable, that is, if it satisfies

$$c_1 \mathcal{I}_n \geq \int_{t_0}^{t_0+T} \Phi^\top(\tau, t_0) C^\top C \Phi(\tau, t_0) d\tau \geq c_2 \mathcal{I}_n, \quad \forall t_0 \geq 0, \quad (22)$$

for some positive constants c_1, c_2 and T —see [2]. Alas, $\Phi(t) \rightarrow 0$ (exp) for the power converter system, complicating the task of satisfying the lower bound on the inequality.

GPEBO with classical gradient estimators

From the LRE (17) we can propose a classical gradient estimator of θ , that is

$$\dot{\hat{\theta}} = \gamma \Phi^\top C^\top (y_m - C\xi - C\Phi\hat{\theta}),$$

whose error equation is given by

$$\dot{\tilde{\theta}} = -\gamma \Phi^\top C^\top C \Phi \tilde{\theta}.$$

It is well-known [29] that this error equation is globally exponentially stable if and only $C\Phi$ is PE—that is, if and only if (22) is satisfied. As discussed above, this condition is hard to satisfy in our application.

A gradient estimator can also be applied to the LRE $Y = \Omega\theta$, obtained with the dynamic regressor extension (11c), (11d). The PE requirement is now imposed to the matrix Ω , which is a far more stringent condition than Assumption 1.

Another possibility is to apply the concurrent learning algorithms proposed in [8, 15] that require only sufficient excitation of the regressor Ω . This is, again, a more stringent requirement than Assumption 1.

4 Observer-based PI-PBC

In this section we propose our output-feedback PI-PBC, which is obtained combining the PI controller of Proposition 1 with the state observer reported in the previous section.

Proposition 3. Consider the system (1) with the measurable outputs (8) in closed-loop with the PI controller of Proposition 1, where the state x is replaced by an estimate \hat{x} generated via the FCT GPEBO of Proposition 2 and Assumption 1 holds.

Then, for all initial conditions of the plant and the controller $(x(0), x_c(0)) \in \mathbb{R}^n \times \mathbb{R}^m$ and all initial conditions of the observer $(\xi(0), Y(0), \Omega(0), \hat{\theta}(0)) \in \mathbb{R}^n \times \mathbb{R}^n \times \mathbb{R}^{n \times n} \times \mathbb{R}^n$, the trajectories of the closed-loop system are bounded and satisfy (3).

Proof. First, notice that the output signal (5), evaluated with \hat{x} instead of x , may be written as

$$\begin{aligned}\mathcal{C}(\hat{x} - x^*) &= \mathcal{C}[x - x^* + \Phi(\hat{\theta}_{\text{FCT}} - \theta)] \\ &= \tilde{y} + \mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta).\end{aligned}$$

Consequently, the PI-PBC (4) takes the form

$$\begin{aligned}\dot{x}_c &= \tilde{y} + \mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta) =: F_{x_c}(x) + \mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta) \\ \tilde{u} &= -K_P\tilde{y} - K_I\tilde{x}_c - K_P\mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta).\end{aligned}$$

Replacing the control signal \tilde{u} above in the system dynamics (7) yields

$$\begin{aligned}\dot{\hat{x}} &= \left(J_0 + \sum_{i=1}^m J_i u_i^* - R \right) Q\tilde{x} - G_N(x)[K_P\tilde{y} + K_I x_c + K_P\mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta)] \\ &=: F_x(x, x_c) - G_N(x)K_P\mathcal{C}\Phi(\hat{\theta}_{\text{FCT}} - \theta),\end{aligned}$$

where $F_x(x, x_c)$ corresponds to the system in closed-loop with the full-state measurable input signal \tilde{u} .

Proposition 1 ensures that (x^*, x_c^*) is an asymptotically stable equilibrium of the unperturbed system. Now, as shown in Proposition 2, Assumption 1 ensures that $\hat{\theta}_{\text{FCT}}(t) = \theta$ for all $t \geq t_c$. Invoking the absence of finite-escape times and the aforementioned asymptotic stability allows us to conclude that (3) holds globally. $\square\square\square$

Remark 5. From (19) it is clear that, under the assumption that $\Delta \notin \mathcal{L}_2$, it is possible to globally, asymptotically reconstruct the state x with the simpler state estimate $\hat{x} = \xi + \Phi\hat{\theta}$. However, proving that the resulting certainty equivalent observer-based PI-PBC is globally stable seems very elusive. There are two technical reasons for this situation: first, that neither for the (\tilde{x}, \tilde{x}_c) subsystem nor for the $\tilde{\theta}$ subsystem, we dispose of exponential stability proofs, which are needed to dominate—with suitable negative definite quadratic terms—the sign-indefinite cross-terms appearing in the Lyapunov-based analysis. Second, the perturbation term of the \tilde{x} dynamics, although linear in $\tilde{\theta}$, is multiplied by the factor $G_N(x)$, whose boundedness is yet to be proven. On the other hand, invoking [33, Theorem 3.1], it is possible to establish a local stability result simply introducing a normalization to the DREM estimator.

5 Application to Ćuk Converter

In this section we apply the results of the paper to design of an output-feedback PI for the Ćuk converter assuming measurable the output voltage. For this example, it is possible to design an adaptive version of it, where we treat the resistive load as an *unknown* parameter.

5.1 Control problem formulation

The average model of the Ćuk converter is given by [4, 21]

$$\begin{aligned}L_1\dot{i}_1 &= -r_1i_1 - (1-u)v_2 + E, \\ C_1\dot{v}_2 &= (1-u)i_1 + ui_3, \\ L_2\dot{i}_3 &= -r_2i_3 - uv_2 - v_4, \\ C_2\dot{v}_4 &= i_3 - \frac{v_4}{r},\end{aligned}$$

where (i_1, v_2, i_3, v_4) is the state vector and $u \in (0, 1)$ is the duty ratio of the transistor switch, with the signals and all the constants shown in Fig. 1. The model can be rewritten in the form (1) with

$x = (L_1 i_1, C_1 v_2, L_2 i_3, C_2 v_4)$, $m = 1$ and the matrices

$$J_0 = \begin{bmatrix} 0 & -1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & -1 \\ 0 & 0 & 1 & 0 \end{bmatrix}, \quad J_1 = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -1 & 0 & 1 & 0 \\ 0 & -1 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}, \quad G_0 = \begin{bmatrix} 1 \\ 0 \\ 0 \\ 0 \end{bmatrix}, \quad G_1 = 0$$

$$R = \text{diag}\left\{r_1, 0, r_2, \frac{1}{r}\right\}, \quad Q = \text{diag}\left\{\frac{1}{L_1}, \frac{1}{C_1}, \frac{1}{L_2}, \frac{1}{C_2}\right\}.$$

The control objective is to drive the output voltage x_4 towards a desired value $x_4^* < 0$, assuming only partial state measurements.




Figure 1: DC-DC Ćuk converter circuit

5.2 State observation problem

The problem of state observation of this system was solved using PEBO in [23] assuming measurable either (x_2, x_4) or (x_2, x_3) . For the latter measurements an adaptive observer and an output feedback controller were designed in [4] using the immersion and invariance technique. To show the benefit of the present GPEBO approach we assume here that *only* x_4 is available for measurement—which is a physically reasonable assumption. Hence, in (8) we have $C = [0 \ 0 \ 0 \ 1]$.

Given the definitions above, the observer of Proposition 2 can be designed with

$$\Lambda(u) = \begin{bmatrix} -\frac{r_1}{L_1} & -\frac{1-u}{L_1} & 0 & 0 \\ \frac{1-u}{C_1} & 0 & \frac{u}{C_1} & 0 \\ 0 & -\frac{u}{L_2} & -\frac{r_2}{L_2} & -\frac{1}{L_2} \\ 0 & 0 & \frac{1}{C_2} & 0 \end{bmatrix}.$$

5.3 Design of the PI-PBC of Proposition 1

Some lengthy, but straightforward, calculations show that, fixing $x_4 = x_4^*$, the equilibria of the state can be parameterized as

$$x^* = \begin{bmatrix} -\frac{u^*}{r(1-u^*)} \\ -\frac{1}{u^*}\left(1 + \frac{r_2}{r}\right) \\ \frac{1}{r} \\ 1 \end{bmatrix} x_4^* =: d(u^*)x_4^*$$

with the equilibrium value for the control u^* given as

$$u^* = \frac{-a_1 + \sqrt{a_1^2 + 4a_2a_0}}{2a_2},$$

where we defined the constants

$$a_0 := (r + r_2)x_4^*, \quad a_1 := Er - 2(r + r_2)x_4^*, \quad a_2 := (r_1 + r + r_2)x_4^* - Er.$$

Given these definitions it is possible to define the incrementally passive output \tilde{y} given in (5) as

$$\tilde{y} = -(x^*)^\top QJ_1Qx = \frac{x_1^*x_2}{L_1C_1} + \frac{x_2^*}{C_1}\left(\frac{x_3}{L_2} - \frac{x_1}{L_1}\right) - \frac{x_3^*x_2}{L_2C_1}.$$

Notice that this signal does not depend on x_4 .

5.4 Simulation results

In all the simulations presented in this section the converter was put in closed-loop with the output-feedback PI-PBC of Proposition 3 with the gains $K_P = 10$ and $K_I = 5$, and the desired output voltage fixed at $x_4^* = -20$. The circuit parameters are shown in Table 1. In all simulations, the control signal was saturated to verify that it remains in the valid interval (0,1). For the sake of brevity the plots are omitted.

Table 1: Circuit parameters of the Ćuk converter.

Parameter	Symbol (unit)	Value
Input voltage	E (V)	12
Reference output voltage	x_{4^*} (V)	-20
Parasitic Resistance	r_1 (Ω)	1.7
Parasitic Resistance	r_2 (Ω)	1.7
Nominal resistance	r (Ω)	20
Inductance	L_1 (mH)	10
Inductance	L_2 (mH)	10
Capacitance	C_1 (μ F)	22
Capacitance	C_2 (μ F)	22.9

Performance of the FCT-GPEBO

First, we evaluate the effect of the *adaptation gain* γ in the FCT-GPEBO of Proposition 2. We choose $\lambda = 5$ and $\mu = 10^{-6}$. The initial conditions of the system are $x(0) = (0.75L_1, 15C_1, -1.5L_2, -18C_2)$, while those of the FCT-GPEBO are set equal to zero. The transient behavior of the state observation errors, for different adaptation gains γ , are shown in Figs. 2-4. As expected, convergence is faster, for larger γ .

In Fig. 5 we show the transients of the output voltage for two cases:

- a step change in x_4^* at $t = 0.015$ (from $x_4^* = -15$ to $x_4^* = -5$),
- a step change in the load r , at $t = 0.015$ (from $r = 20$ to $r = 30$).

As seen from the figure the regulated output follows quite rapidly the change of reference and is highly insensitive to the load change.




Figure 2: Transients of $i_1 - \hat{i}_1$ of the FCT-GPEBO for different adaptation gains




Figure 3: Transients of $v_2 - \hat{v}_2$ of the FCT-GPEBO for different adaptation gains




Figure 4: Transients of $i_3 - \hat{i}_3$ of the FCT-GPEBO for different adaptation gains

Comparison of the performance of FCT-GPEBO with other observers

Second, to compare the performance of the FCT-GPEBO of Proposition 2 with other observers, we present now simulations of the output-feedback PI-PBC where we replaced this observer by one of the observers




Figure 5: Transients of u_4 of the FCT-GPEBO for step change in reference signal and load

discussed in Subsection 3.2 and the asymptotic GPEBO of Remark 5. For all observers, the initial conditions of the converter were taken as $x(0) = \text{col}(0.75L_1, 15C_1, -1.5L_2, -18C_2)$. For the PEBOs we used $\lambda = 5$ and $\gamma = 10^{12}$. For the KBF we used $S = I_{4 \times 4}$ and $H(0) = I_{4 \times 4}$. For the classical gradient estimator we set to zero $\hat{\theta}(0)$ and used $\gamma = 10^8$. For the asymptotic GPEBO we used $\gamma = 10^{17}$.

Figs. 6-8 show the transients of the state estimation errors for the following estimation methods: FCT-GPEBO, asymptotic GPEBO, open-loop emulator, KBF and GPEBO with classical gradient estimator. The following observations are in order.

- O1** As predicted by the theory all state estimation errors of FCT-GPEBO converge in finite time with $t_c \approx 0.03\text{s}$, and the performance of this observer is superior to all the other ones.
- O2** The emulator and the KBF have almost identical behavior. Actually, in the plots the difference is indistinguishable. The performance of the KBF didn't change with other choices of S .
- O3** The asymptotic GPEBO outperforms all other observers, except the FCT-GPEBO.
- O4** The GPEBO plus gradient also converges, but has an erratic behavior, whose origin we fail to understand.

Performance of the PI-PBC with full-state measurement and FCT-GPEBO

Second, we compare the performance of the full-state feedback PI-PBC with the one using the observed state. We look in this case at the effect of the *initial conditions*. For simulations we considered the initial conditions:

$$\begin{aligned} x(0) &= \text{col}(0.5L_1, 10C_1, -1L_2, -12C_2) \\ x(0) &= \text{col}(0.25L_1, 5C_1, -0.5L_2, -6C_2) \\ x(0) &= \text{col}(0.75L_1, 15C_1, -1.5L_2, -18C_2), \end{aligned}$$

and in FCT-GPEBO we chose the parameters $\lambda = 5$, $\gamma = 10^{12}$. The behavior of the output voltage for PI-PBC with the *known* state is shown in Fig. 9, while the one of the observed state is shown in Fig. 10.




Figure 6: Transients of i_1 estimation errors for different algorithms

As seen from the figures the reconstruction of the state induces some oscillations at the beginning but the regulation of the output is achieved at almost the same time.

Finally, we compare the output-feedback PI-PBC with a *classical* PI wrapped around the output voltage error, that is

$$\begin{aligned}\dot{x}_c &= x_4^* - x_4 \\ u &= -K_P(x_4^* - x_4) - K_I x_c.\end{aligned}$$

The results are shown in Fig. 11, showing the superior performance of the PI-PBC.

It may be argued that the response of the classical PI can be improved re-tuning the gains. The usual procedure to improve the transient performance of a PI is to increase the integral gain K_I , see [34]. This is shown in Fig. 12 where the transient performance is, indeed, improved but is still inferior to the proposed PI-PBC.

6 Conclusions an Future Work

We have provided a solution to the main drawback of the popular PI-PBC of [12], namely the need to measure the full state, by proposing a globally convergent state observer. The convergence of this observer occurs in finite time and requires only a very weak excitation assumption.

In view of the high uncertainty on the converter parameters—in particular, the variations of the load—our current research focuses on the development of adaptive versions of the observer and the PI-PBC. Some results for particular converter topologies are already available and will be reported elsewhere.

We are also working on the experimental implementation of the proposed PI-PBC for a Ćuk and a quadratic converter, that we expect to have ready for the final version of this paper.

References

- [1] H. Akagi *Instantaneous Power Theory and Applications to Power Conditioning*, Wiley, Newark, 2007.




Figure 7: Transients of v_2 estimation errors for different algorithms

- [2] B. Anderson, Stability properties of Kalman-Bucy filters, *Journal of the Franklin Institute*, vol. 291, no. 2, pp. 137-144, 1971.
- [3] S. Aranovskiy, A. Bobtsov, R. Ortega, A. Pyrkin, Performance enhancement of parameter estimators via dynamic regressor extension and mixing, *IEEE Trans. Automatic Control*, vol. 62, pp. 3546-3550, 2017.
- [4] A. Astolfi, D. Karagiannis and R. Ortega, *Nonlinear and Adaptive Control with Applications*, Springer-Verlag, Berlin, Communications and Control Engineering, 2008.
- [5] K. J. Astrom and T. Hagglund, *Automatic Tuning of PID Controllers*, Instrument Society of America, NC, USA, 1988.
- [6] K. J. Astrom and R. M. Murray, *Feedback Systems An Introduction for Scientists and Engineers*, 2nd edition, Princeton University Press, 2019.
- [7] P. Bernard, *Observer Design for Nonlinear Systems*, Springer, Vol. 479, 2019.
- [8] G. Chowdhary, T. Yucelen, M. Muhlegg and E. Johnson, Concurrent learning adaptive control of linear systems with exponentially convergent bounds, *Int. J. on Adaptive Control and Signal Processing*, vol. 27, no. 4, pp. 280-301, 2013.
- [9] R. Cisneros-Montoya, *PI Passivity-Based Control: Application to Physical Systems*, Ph D. University, Paris-Saclay, HAL Id. <https://tel.archives-ouvertes.fr/tel-01368308>, 2016.
- [10] D. Dochain, State and parameter estimation in chemical and biochemical processes: a tutorial, *Journal of Process Control*, vol. 13, no. 8, pp. 801-818, 2003.
- [11] G. Escobar, A. van der Schaft and R. Ortega, A Hamiltonian viewpoint in the modeling of switching power converters, *Automatica*, vol. 35, pp. 445-452, 1999.
- [12] M. Hernandez-Gomez, R. Ortega, F. Lamnabhi-Lagarrigue and G. Escobar: Adaptive PI stabilization of switched power converters, *IEEE Trans. Control Syst. Technology*, vol. 18, no. 3, pp. 688-698, 2010.




Figure 8: Transients of i_3 estimation errors for different algorithms




Figure 9: Transients of v_4 for different initial conditions and the PI-PBC with *known* x

- [13] M. Hernandez-Gomez, R. Ortega, F. Lamnabhi-Lagarrigue and G. Escobar, Adaptive PI stabilization of switched power converters described by port-Hamiltonian models, *Dynamics and Control of Switched Electronic Systems*, eds. F. Vasca and L. Iannelli, Advances in Industrial Control, Springer, Heidelberg, pp. 355-390, 2012.
- [14] B. Jayawardhana, R. Ortega, E. Garcia-Canseco and F. Castaños, Passivity of nonlinear incremental systems: Application to PI stabilization of nonlinear RLC circuits, *Systems and Control Letters*, vol. 56, pp.618-622, 2007.
- [15] R. Kamalapurkar, B. Reish, G. Chowdhary and W. Dixon, Concurrent learning for parameter estimation using dynamic state-derivative estimators, *IEEE Trans. Automatic Control*, vol. 62, no. 7, pp. 3594-3601, 2017.
- [16] J. Kassakian, M. Schlecht and G. Verghese, *Principles of Power Electronics*, Addison-Wesley, Reading, 1991.




Figure 10: Transients of v_4 for different initial conditions and the PI-PBC with *unknown* x




Figure 11: The response curves of x_4 of the closed-loop system under traditional PI with $K_P = 0.008$, $K_I = 8$ and the output-feedback PI-PBC, with $x_4^* = -15$

- [17] M.P. Kazmierkowski, R. Krishnan, F. Blaabjerg and J.D. Irwin, *Control in Power Electronics: Selected Problems*, Academic Press Series in Engineering. Elsevier Science, 2002.
- [18] G. Kreisselmeier and G. Rietze-Augst, Richness and excitation on an interval—with application to continuous-time adaptive control, *IEEE Trans. Automatic Control*, vol. 35, no. 2, pp. 165-171, 1990.
- [19] C. Meza, D. Biel, D. Jeltsema and J. M. A. Scherpen, Lyapunov-based control scheme for single-phase grid-connected PV central inverters, *IEEE Trans. Control Systems Technology*, vol. 20, no. 2, pp. 520-529, 2011.
- [20] R. Ortega and R. Kelly, PID self-tuners: some theoretical and practical aspects, *IEEE Trans. on Ind. Electr.*, vol. 31, no.4, 1984.
- [21] R. Ortega, A. Loria, P. J. Nicklasson and H. Sira-Ramirez, *Passivity-based control of Euler-Lagrange systems*, Springer-Verlag, Berlin, Communications and Control Engineering, 2014.




Figure 12: The response curves of x_4 of the closed-loop system under traditional PI with $K_P = 0.008$ and different values of K_I , with $x_4^* = -15$

- [22] R. Ortega, A. J. van der Schaft, I. Mareels, and B. Maschke, Putting energy back in control, *IEEE Control Systems Magazine*, vol. 21, no. 2, pp. 18-33, 2001.
- [23] R. Ortega, A. Bobtsov, A. Pyrkin and A. Aranovskyi, A parameter estimation approach to state observation of nonlinear systems, *Systems and Control Letters*, Vol. 85, pp 84-94, 2015.
- [24] R. Ortega, A. Bobtsov, D. Dochain and N. Nikolayev, State observers for reaction systems with improved convergence rate, *Journal of Process Control*, Vol. 83, pp. 53-62, 2019.
- [25] M. Perez, R. Ortega and J. Espinoza, Passivity-based PI control of switched power converters, *IEEE Transactions on Control Systems Technology*, vol. 12, pp. 881-890, 2004.
- [26] W.J. Rugh, *Linear Systems Theory*, 2nd Edition, Prentice hall, NJ, 1996.
- [27] W.J. Rugh and J. Shamma, Research on gain scheduling, *Automatica*, vol. 36, no. 10, pp. 1401-1425, 2000.
- [28] S. Sanders and G. Verghese, Lyapunov-based control for switched power converters, *IEEE Trans. Power Electronics*, vol. 7, No. 1, pp. 17-24, 1992.
- [29] S. Sastry and M. Bodson, *Adaptive Control: Stability, Convergence and Robustness*, Prentice Hall, Englewood Cliffs, NJ, 1989.
- [30] H. Sira-Ramirez and R. Silva-Ortigoza, *Control Design Techniques in Power Electronics Devices*, Springer-Verlag, Berlin, Communications and Control Engineering, 2006.
- [31] A. van der Schaft, *L₂-Gain and Passivity Techniques in Nonlinear Control*, Springer, Berlin, 3rd Edition, 2016.
- [32] V. Vesely and A. Ilka, Gain-scheduled PID controller design. *Journal of Process Control*, vol. 23, pp.1141-1148, 2013.

- [33] M. Vidyasagar, Decomposition techniques for large-scale systems with non-additive interactions: stability and stabilizability, *IEEE Trans. Automatic Control*, vol. 25, no. 4, pp. 773-779, 1980.
- [34] L. Wang, S. Chai, D. Yoo, L. Gan and K. Ng, *PID and Predictive Control of Electrical Drives and Power Converters using MATLAB/Simulink*, First Edition, John Wiley & Sons Singapore, 2015.