

Simple and Cheap Setup for Measuring Timed Responses to Auditory Stimuli

Martin A. Miguel^{1,2}, Pablo Riera², and Diego Fernandez Slezak^{1,2}

¹Universidad de Buenos Aires. Facultad de Ciencias Exactas y Naturales.

Departamento de Computación. Buenos Aires, Argentina.

²CONICET-Universidad de Buenos Aires. Instituto de Investigación en Ciencias de la
Computación (ICC). Buenos Aires, Argentina.

Affiliation

Author Note

We have no known conflicts of interest to disclose.

Correspondance concerning this article should be addressed to Martin A. Miguel.

Email: mmiguel@dc.uba.ar. Address: Intendente Güiraldes 2160 - Ciudad Universitaria
- Buenos Aires, Argentina. Phone: +541152857400

Abstract

Measuring human capabilities to synchronize in time, adapt to perturbations to timing sequences or reproduce time intervals often require experimental setups that allow recording response times with millisecond precision. Most setups present auditory stimuli using either MIDI devices or specialized hardware such as Arduino and are often expensive or require calibration and advanced programming skills. Here, we present in detail an experimental setup that only requires an external sound card and minor electronic skills, works on a conventional PC, is cheaper than alternatives and requires almost no programming skills. It is intended for presenting any auditory stimuli and recording response times with within 2 milliseconds precision (up to -2ms lag). This paper shows why desired accuracy in recording response times against auditory stimuli is difficult to achieve, presents an experimental setup to overcome this and explains in detail how to set it up and use the provided code. Finally, code for analyzing input recordings was evaluated, which shows that no spurious or missing events were found in 94% of the analyzed recordings.

Simple and Cheap Setup for Measuring Timed Responses to Auditory Stimuli

Humans have a very distinct ability to synchronize motor movements to regular sound patterns. We can finger-tap or sway along to a metronomic pulse and, moreover, we are able to extract an underlying clock, the beat, from non-isochronous rhythmic patterns (Repp & Su, 2013). Beat perception is a fundamental component for experiencing music, ranked among life's greatest pleasures (Dubé & Le Bel, 2003).


This ability to synchronize movement to an external stimuli —known as sensorimotor synchronization or SMS —has been studied in detail. Studies have revealed slowest and fastest tapping rate limits, what is the most common spontaneous tapping rate and how it evolves from faster to slower with age, that age allows us to synchronize to a wider rate range and that musical training improves synchronization accuracy. Several models of how we synchronize to rhythms and perform corrections in our tapping to compensate for changes in the pacing signal have been introduced and tested experimentally. When analyzing this phenomenon from the perspective of music, studies have found that the rhythmic structure of the musical signal affects synchronization precision. For a full review, please refer to Repp (2006) and Repp and Su (2013).

To understand these phenomena, behavioural studies require an experimental setup that allows presenting an auditory stimuli and record participants' responses with great time fidelity. In several cases, it is also important to capture the asynchrony between a participant response and the onset times present in the stimulus. Figure 1 presents the common scheme of a trial in an SMS experiment.

This general scheme can be instantiated in experiments performed in the literature, as presented in figure 2. The study in Krause, Pollok, and Schnitzler (2010) explored the relationship between sensorimotor synchronization and musical training. One of the tasks consisted of tapping in synchrony to an isochronous stimuli in two modalities: visual and auditory. In the auditory modality, the trial presented an isochronous tick to which the participants had to synchronize until it stopped (see

Figure 1.

Schematic of Trial in a Sensorimotor Synchronization (SMS) Experiment.



Note. A trial consist of an auditory stimuli with identifiable onsets developing in time. A participant has to listen to the stimuli and produce responses. The measure of interest is the time interval between the participant's response and the stimulus' onset time.


figure 2a). In McAuley, Jones, Holub, Johnston, and Miller (2006), participants of different ages were asked to tap in synchrony to a metronome to study whether age changed the ability to synchronize at different tapping rates. Trials started with an isochronous tick to which the participant had to synchronize, but they were also asked to continue tapping to the metronome's rate after it had stopped. This paradigm is known as synchronization-continuation (see figure 2b). The task presented in Repp, London, and Keller (2005) asked participants to synchronize to non-isochronous stimulus by reproducing it. It also uses a synchronization-continuation paradigm where the continuation phase may contain a pacing signal instead of the original signal (see figure 2c).

Other paradigms that fit into the general experimental setup scheme proposed are auditory Go/No-Go (Barry, De Blasio, & Borchard, 2014) tasks and auditory time interval reproduction (Daikoku, Takahashi, Tarumoto, & Yasuda, 2018). The Go/No-Go task presents one of two stimuli, with one designated as *target*. During the experiment, each trial consists of presenting one of the possible stimuli and participants must respond only when the target stimuli is presented. In the auditory mode, stimuli are sounds, and target stimulus may be distinguished, for example, by pitch. In a time

interval reproduction task, a time interval is presented by two sounds separated in time. Afterwards, participants must try to reproduce the interval as accurately as possible. Both task schemes are presented in figures 2d and 2e, respectively.

Figure 2.

Instantiations of SMS Trials in Various Experiments.



Recording stimuli onset times and participants' response times precisely cannot be directly achieved in an experimental setup using only a computer and require specialized equipment or software. Setups presented in the literature either use specific input devices (mostly MIDI instruments) (Fitch & Rosenfeld, 2007; Patel, Iversen,

Chen, & Repp, 2005; Repp et al., 2005; Snyder & Krumhansl, 2001), specialized data acquisition devices (Elliott, Wing, & Welchman, 2014) or low-level programming of a microcontroller (e.g.: Arduino) to work as an acquisition device (Bavassi, Kamienkowski, Sigman, & Laje, 2017; Schultz & Palmer, 2019). Drawbacks of these setups come either from the cost of the equipment or the technical skills required. MIDI input devices and data acquisition devices (DAQs) generally used cost over 200 USD. A programmable micro-controller is cheaper (about 30 USD) but requires low level programming skills and does not include the input device.

In this paper we present an experimental setup that requires no programming skills, is simple to assemble and costs under 60 USD (including the input device). Beyond simplicity and affordability, the setup proposed focuses on reliably capturing the time interval between stimulus onset and the participant's response. To manage this using MIDI devices, latency times for both input and output devices must be verified (Finney, 2016). On the other hand, using a micro-controller can provide accurate stimulus timing but cannot easily produce rich sounds (Schultz & van Vugt, 2016). More recently, some software setups allow presenting auditory onsets with precision and ease, but still rely on expensive input equipment to gather timely responses Bridges, Pitiot, MacAskill, and Peirce (2020).

The next section (**Problem Description**) describes in detail why it is not straightforward to record stimuli to response time intervals using only a computer's input and output hardware and more sophisticated solutions are required. This section also reviews previous solutions to the problem. In section **Setup Description and Installation** the setup presented here is described in detail along with assembly instructions. The main features and limitations of the setup are described in detail there. The section **Tool Suit and Usage Workflow** presents the software tools provided to use the hardware setup and the evaluation performed on the precision of how participants' responses are collected.

Problem Description

The common expected setup to run the described experiments in a personal computer would be to have the computer present the stimuli (in this case, audio) and simultaneously record participants' responses via standard input devices such as a keyboard or a mouse. In more detail, this situation implies the following steps in time:


1. Computer program produces auditory stimuli and records stimuli onset time (o^c).
2. Sound is produced on the speakers or headphones and heard by the participant (o^p).
3. Participant produces a response by operating the input device (keyboard, mouse, etc.) (r^p).
4. The response is captured by the computer and response time is recorded (r^c).
5. Response time is calculated from the times recorded by the computer ($rt^c = r^c - o^c$).

The situation described above is depicted in Figure 3. The issue with this simple conception of the experimental setup is that the moment where the auditory stimuli is actually produced may be significantly delayed from the moment the computer program decided to produce the sound ($\Delta o = o^p - o^c$). Additionally, the time the computer learns a keyboard key is pressed can be much later than the time the key was effectively pressed ($\Delta r = r^p - r^o$). As a consequence, the response time captured (rt^c) may be different than the real response time (rt^p).

The delays in stimuli production (Δo) and response capture (Δr) are analyzed in two magnitudes: lag (or accuracy) and jitter (or precision). Lag refers to a constant delay between the two onset or response times. Jitter refers to the unknown variability in the delay. If the delay is thought of as a random variable, the lag or accuracy would be represented by the expected delay and the jitter or precision with the standard deviation. Depending on the setup and experimental question at task, lag can be cancelled out. In some setups it may be possible to measure and subtract or, if the

Figure 3.

Depiction of the Delays Between Computer and Participant's Stimuli Onset and Response Times.



Note. In a common computer setup, response times are calculated from the onset and response times known to the computer (o^c and r^c , respectively). These times may differ from the actual onset and response times perceived and produced by the participant (o^p and r^p). As a result, the obtained response time (rt^c) is different from the one that is of interest (rt^p).

question is a comparison between groups, the comparison of response times will inherently ignore such delay. On the contrary, jitter is unknown and my affect differently each trial, being therefor more difficult to disregard.

In common computers, onset delay (Δo) may be caused by several reasons. In a standard installation with an operating system, several layers of software drivers exist between the experiment's program and the sound card that translates the digital encoding of sound into electric pulses for the speakers. These layers may cause the message to be delayed between the user's software and the hardware. The conversion between digital and analogue representations of sound, made by the digital-to-analogue converter (DAC), also requires time. Finally, some sound producing devices, such as MIDI instruments, may also require time to process the onset digital signal to effectively produce sound. Regarding responses, capture delays (Δr) can also be product of the transit from the driver receiving information from hardware devices and the experiment's software. Some devices may also introduce delays between receiving the participant's pressure action and producing a signal. For example, standard

keyboards are known to have a lag larger than 10 ms, with varying jitter of about 5 ms (Bridges et al., 2020; Segalowitz & Graves, 1990; Shimizu, 2002).

Proposed approaches

There are two main approaches to overcome the latency problems described: either reduce the delays (Δo and Δr) below a required value or record the actual onset and response times perceived and provided by the participant in a way that is independent of the computer and does not introduce relevant latencies.

Finney (2001) takes on the first approach and uses MIDI devices for both input and output. The Musical Instrument Digital Interface (MIDI) is a communication protocol for sending and receiving information on how and when to play musical notes through MIDI devices. Examples are physical instruments such as keyboards or drum pads that can produce messages, synthesizers that receive MIDI messages and produce sounds or computers with MIDI ports that may do both. In his work, Finney presents FTAP, a software tool for running experiments involving auditory stimuli and response time collection. For timing precision, FTAP takes advantage of the MIDI protocol's capacity to exchange messages at approximately one message per millisecond. The software package includes an utility to test whether such exchange rate is achieved in a specific computer setup (computer, operating system, MIDI drivers and MIDI card) as not every configuration allows such optimal rate. Moreover, testing of the input and output hardware used is recommended, as it has been seen that some MIDI input devices can introduce delays of several milliseconds from the moment it is actuated until the MIDI message is sent (Finney, 2016; Schultz & van Vugt, 2016). End-to-end testing of an experimental setup implies measuring the complete time from the participant's input (pressing on the device) to the time the computer captures the message or auditory feedback is produced, depending on the requirements of the experiment. Commercial equipment for this purpose has been presented in Plant, Hammond, and Turner (2004) and an alternative using an Arduino controller is described in Schultz (2019).

Schultz and van Vugt (2016) focuses on presenting a setup to provide timely auditory feedback to a participant's response. To do so, they capture the response and provide feedback using a programmable micro-controller (namely Arduino). Micro-controllers often provide input and output pins that allow interfacing with external hardware by measuring and producing changes in the voltage of the electrical current that runs through the pins. The importance of using a microcontroller lies in that it provides the programmer with direct access to the processor and the input and output pins. This allows more precise control over the delays of processing the input and producing the output in comparison with using a computer with an operating system where the delays of the hardware drivers and those introduced by the multitasking capabilities are harder to manage or know. In their proposed setup, they capture the participant's tap using a Force Sensitive Resistor (FSR) (depicted in figure 7). An FSR is a device shaped as a flat surface that varies the voltage of an electrical current according to the pressure it receives. Such changes in voltage can be measured in an input pin in the micro-controller to recognize when the device is being pressed. Finally, they test two methods to provide feedback from the Arduino. One method is connecting a headphone directly to an output pin of the controller. This allows the program to produce feedback very quickly (delay of 0.6 ms, sd of 0.3 ms) with the caveat of it being a simple sound. Another method tested is the Wave Shield for Arduino, an extension hardware that allows reproducing any sound file. The Wave Shield feedback requires more time to emit a sound (2.6 ms in average) but still has low jitter (0.3 ms).

The timing mega-study in Bridges et al. (2020) analyzes onset lag and jitter for auditory and visual stimulus on a variety of existing software packages for designing and running behavioral experiments on PC. These packages provide utilities to generate programs that run experiments, present stimuli, collect answers, randomize trial conditions, among other features commonly used. Moreover, these software packages manage drivers and settings in order to produce onsets, both auditory and visually, with less than a millisecond unknown delay. The results of this work shows that a common computer hardware can be used to produce auditory stimuli quickly in spite of

the stack of drivers and multitasking mentioned. To do so, the right software configuration is required. For example, PsychoPy must be updated to version 3.2+ which recently included the correct software to achieve millisecond auditory onset presentation. The issue still remains on the precision of the input capture, which in Bridges et al. (2020) is solved by using a specialized response button device.

The MatTAP tool suit, presented in Elliott, Welchman, and Wing (2009), uses the second approach to work around the delays and achieve precise recording of stimuli and response times. This approach is based on using a recording device independent of the computer running the experimental procedure in such a way that producing the stimulus and recording responses is not affected by the software stack of the operating system. More specifically, they use a Data Acquisition device (DAQ). DAQs are devices that can produce and record multiple analogue and digital signals simultaneously with a sampling rate of hundreds of kilo-samples per second, providing sub-millisecond precision. The MatTAP tool suit is a MATLAB tool box that communicates with the DAQ in order provide the stimuli onset times and sounds. The DAQ then produces the sounds and simultaneously records the input from the input device. Each auditory onset is accompanied by a digital onset on a separate channel that is required to be looped back into a recording channel of the DAQ. Although it produces the stimulus without lag relative to the stimuli sequence, there may be a delay introduced by the initial communication between the computer and the DAQ. As a consequence, the loop back is required to be able to synchronize the stimuli onset times with the response times (see the next section and fig 4 for a more detailed explanation). Finally, if the DAQ has more than 2 input channels, MatTAP is capable of recording two input devices. Also, the digital output signal produced with each stimulus onset may be used to drive another output device. The MatTAP tool suit provides software utilities for creating up to two metronomes for synchronization experiments, allows managing settings for multiple trials and also collects the experiment response data for each trial. The tool suit also provides a customizable utility to analyze the input signals, extract responses and calculate stimulus to response asynchrony times.

The setup proposed here also follows the second approach. In comparison with MatTAP (Elliott et al., 2009), we use an external sound card as an acquisition device, which works as a less expensive replacement. Moreover, the software tool set provided here does not require proprietary software such as MATLAB. Finally, we present instructions to assemble an input device that can be connected to the sound card and provide accurate response time recording.

Setup Description and Installation

In **Problem Description** we established two main approaches to solve the issues that arise when recording response times to auditory stimuli due to delays in both onset presentation and response time collection. One approach is to reduce such delays below an accepted value. Another approach is to record the onset times actually perceived and produced by the participant with an independent recording device. Our setup takes the second approach and proposes to do so using either the sound card already present in common desktop computers or an inexpensive external sound card. In this section we present why our setup addresses the problem, how our setup is assembled and what is the expected workflow for running experiments with it. To complete the setup, this work presents instructions to assemble a pressable input device using a force sensitive resistor (FSR) and an open-source software tool suit to produce the stimuli, record the responses and obtain response times from our proposed input device. The instructions to assemble the input device are introduced in the next subsection. Then we present instructions to connect the input device, the recording device and test the setup connections. The tool suit is introduced in the next section.

The key component of the approach used in this setup is to be able to record both the participant's responses and the stimuli simultaneously. This allows having the stimuli synchronized with the responses on one device's timeline. Because one of the delays is introduced between the moment the experiment code produces a stimulus and when it is played on the output device, producing each stimulus separately would add variability to the inter-stimuli interval. Such behaviour can render certain experimental

conditions unusable. Our proposal is to package all stimuli onsets into one audio file.

This introduces only one delay on when the whole stimuli set is reproduced

($\Delta s = s^c - s^p$) but no variability in inter-stimuli intervals. Finally, stimuli and

participant's responses are recorded by the device. Stimuli onset times can be retrieved

by synchronizing the output audio file with the recording. Response times can be


obtained from the recorded signal relative to the beginning of the stimulus. How this

procedure is performed is explained in section **Tool Suit and Usage Workflow**. The

setup and new definition of delays is depicted in figure 4.

Figure 4.

Representation of Stimuli and Recording Times when Using an Independent Recording Device.



Note. This approach adds a new device that simultaneously records the stimuli and the responses with high accuracy. Stimuli are presented as one audio with multiple onsets (box containing lines). The stimulus presentation time may lag from the computer command but is recorded at the same time it is heard by the participant ($s^c \geq s^p$ and $s^p = s^r$). Response times (r_i) are captured in synchrony with stimulus presentation.

To achieve recording the stimuli and responses simultaneously, the recording device used must have a stereo output and at least two input channels (or one stereo input). With this, one channel of the stereo output can be looped back into one of the

input channels. Moreover, to keep the setup simple, our proposed setup requires the recording device to have a secondary output that mirrors the primary. While the primary output signal is looped-back into one input channel, the secondary output is connected to the output device (speakers or headphones). Finally, the signal of the response device is connected to the second input channel of the recording device. With this connection setup, the audio input of the recording device can be collected into a stereo file containing the stimulus in one channel and the response signal on the other. The connections mentioned are depicted in figure 5. The audio output and input signals are depicted in figure 6.


In the next subsection we present how to assemble the input device used in the complete version of the setup. Then we show how to connect the input device, the recording device and the computer, and then test that the connections work correctly.

Input device (FSR)

Our setup uses a pressable input device. The main component of the device is a Force Sensitive Resistor (FSR), a flat sensor whose electric resistance is reduced when pressed (fig 7). The variance in resistance can be used to create a variation in voltage that can be recorded by the audio input of a sound card. The proposed device uses a 3.5mm female audio jack that allows connecting the input device with the sound card using standard audio cables.

The circuit allowing this variation requires a voltage source. We propose using a standard USB (type-a) cable connected to a computer for this purpose. The voltage variation provided to the sound card can saturate the recording, depending on the device's sensitivity. This saturation can modify the activation profile captured from the FSR. The proposed circuit adds a voltage divisor that allows limiting the maximum voltage received by the sound card. In our proposal, we use a $10\text{k}\Omega$ potentiometer, another adjustable resistor, that can be set by trial and error to prevent the signal from saturating the recording.

The proposed circuit is presented in figure 7. For the voltage source we use a

Figure 5.*Schematic of the Connections of the Setup.*




Note. Computer exchanges information with the recording device (sound card). One of the device's sound output is sent to the participant, the other has one channel looped-back to one of the recording device's input channels. The response device is connected to the other input channel.

standard USB (type-a) cable connected to the computer. USB cables have 4 pins, two for data, one that drives a 5V signal (VBUS or VCC) and a ground connection (GND). The VBUS pin (fig 7, red cable) is connected to the divisor circuit which centerpiece is the potentiometer (fig 7, purple cable). The division goes to the FSR (orange cable) and back to the ground (black cable). The other end of the FSR (yellow cable) is connected to the 3.5 jack (blue) and simultaneously grounded through a 22k Ω resistor (black). More detailed instructions for assembly are presented as a video tutorial, linked in the *Open Practices Statements* section.

The next subsection explains how the FSR input device is connected with the

Figure 6.

Example of Stimulus Audio Signal (middle) and an Input Recording (bottom).

(a) Stimulus onset times**(b)** Stimulus audio**(c)** Mixed loopback and input device recording

Note. The stimulus signal is an arbitrary stereo audio file (b). In this case, it is an audio signal constructed from designated onset times (a). The input recording (c) contains on one channel the looped-back signal from the stimulus (0) and on the other the electrical signal from the input device (1).

rest of the setup and how to test the connections. It also explains how to use the potentiometer to adjust the signal amplitude to avoid saturation. The exact circuit used in this work is presented in figure 17 and replaces the potentiometer with two resistors selected for the sound card used (Behringer UCA-202). It has a further adjustment to deliver a descending (instead of ascending) voltage change when the FSR is actuated given that this sound card inverts the signal when recording. The tool suit provided here has a setting that allows managing this situation.

Setup assembly

The three key components of the setup are the recording device with two input channels and output channels, the loopback between output and input and the mixing of the input device with the loopback in the stereo input. An schematic of these connections is presented in figure 5. In figure 8 we present the same connection scheme with the picture of the devices connected. Given that our external sound card (fig 8a) uses RCA plugs, we use a male-male RCA-RCA cable to perform the loopback (fig 8b). Although we used an stereo cable, a mono cable is sufficient. Finally, we connect the FSR setup with the recording device using a 3.5mm plug to RCA cable (fig 8c). Again, we used an stereo cable, but a mono cable is sufficient.

The connections can easily be tested by playing an audio from the computer and recording the audio while tapping on the input device. In figure 9 we present part of the interface of an open-source sound recording and editing software (*Audacity (v2.2.1)*, n.d.). By recording audio from the recording device with the loopback connection, an audio track such as the one in figure 6c should be produced. The track should contain the stimulus signal on one channel and spikes corresponding the tapping on the other one.

This setup and software can also be used to inspect the recording of the FSR signal to calibrate the FSR input device. Peaks are expected too look as shown in figure 9b. In case the FSR signal saturates the audio card, the peak will contain a flat top as shown in figure 9c. This can be solved by adjusting the potentiometer which regulates the maximum height of the peak. Another issue might come from the sound card inverting the signal as in figure 9d. This can be solved by inverting the audio recording on the recorded channel. A option to manage this is provided in the tool suit described in **Tool Suit and Usage Workflow**.

A website where further detail and tutorials are provided is detailed in the *Open Practices Statements* section.

Tool Suit and Usage Workflow

To make the use of the proposed setup as convenient as possible, in this work we present a tool suit to produce the stimuli, record responses and analyze the recordings. The tools are python programs open-sourced under an MIT licence. The tool suit was developed using the UNIX Philosophy (Raymond, 2003), so each program is independent and dedicated to solving one issue.

Next we outline the workflow considered and what are the tools we provide to address each stage. An expected experiment design workflow would have the following stages:

- **Define the stimuli.** Stimuli can be any arbitrary set of audios. Many sensorimotor synchronization experiments use stimuli conformed by discrete sound onsets at designated times. We provide an utility (`beats2audio`) to transform a text file with onset times into an audio that produces a sound on each onset time.
- **Expose participants to the stimuli and collect responses.** Given a stimuli set, participants should hear each audio and produce responses by tapping on the response device. The utility provided (`runAudioExperiment`) receives a configuration file declaring the audio stimuli set and presents each one while recording the response. Responses for each trial are save as an audio file (fig 6c) on a designated output folder.
- **Extract tap times from the recordings.** Using the original stimulus and the response recording, tap times are extracted relative to the beginning of the stimulus. A different tool is provided for this purpose (`rec2taps`).

In case the stimuli to be used is an audio with simple identical onsets on designated times, the utility `beats2audio` receives a text file (figure 10) with a list of onset times in milliseconds and outputs an audio file (figure 6b). A click sound is produced on each onset time.

To run the tapping experiments, i.e.: producing the stimuli and recording the loopback and input, we provide a simple utility named `runAudioExperiment`. The

utility requires three arguments: the path to a configuration file, the path to a trial file and the path to an output directory where recordings are to be stored. The experiment execution follows the steps depicted in figure 11. Trials are run in a succession, each trial consisting of five steps. First, a black screen is presented for an specified duration. Secondly, screen turns to a (possibly) different color and white noise combined with a tone is played. This option is intended to help remove rhythmic biases between trials. Third, the screen goes black again and the trial stimulus is played as recording is enabled. Fourth, the screen stays black in silence. Recording continues in this stage. Finally, another optional colored noise screen is produced. Following this screen, the next trial, starting with the black screen, begins.

The configuration file provided as the first argument of the utility specifies the parameters of the execution of the steps mentioned above (figure 12). The trial file is a plain text file containing the stimuli set, one per line as paths to audio files. The output directory defines where the experiment outputs are to be saved. The utility produces as an output one recording per trial, as obtained from the sound device, and a `csv` file containing a table describing the details of the experiment execution (table 1). The name of the output folder can be used to identify experiment runs either by date, run id number or participant's initials.

The last utility, `rec2taps`, extracts tap times from the audio recordings produced during the experiment. To do so it requires two arguments, a trial recording audio file and its original stimulus file. The utility uses the original stimulus audio to find its starting point (s^c) in the recording. It does so by looking for the maximum cross-correlation between the stimulus and the loopback channel of the recording. Then, using the channel where the input signal is recorded, the utility finds peaks in the signal and extracts tap times as the location of the maximum of each peak. Given that the beginning of the original stimulus can be found in the trial's recording, the playback delay can be subtracted from tap times, obtaining tap times relative to the beginning of the stimulus. Tap times are printed out in milliseconds, one per line.

Detailed instructions on how to use the utilities described are provided in each

code's project readme files. Links to code projects are listed in the *Open Practices Statements* section. The next subsection informs in more detail how tap times are extracted from the recording and analyzes its accuracy.

Table 1

Example of an Output Table from an Experiment Run

index	stimulus_path	recording_path	black_duration	c1_duration	c2_duration	silence_duration
0	s1.wav	s1.rec.wav	600	300	0	1000

Signal Analysis

The goal of the setup is to be able to record a participant's tap times with high precision. In the presented setup, the signal from the input device is a function over time of the activation of the device, recorded as an audio signal. From this signal, we intend to extract individual time points that represent each actuation of the input device. In electronic input devices as the one presented here (the FSR), the activation signal is not a simple on-off function, but a curve describing the change of pressure on the device over-time. To obtain individual tap times for each actuation, the signal must be processed to recognize each activation and then select a point in time within the curve that is representative of the time of actuation.

This process raises two aspects subject to analysis. First, whether the processing misses any individual activation or detects spurious activations. Secondly, how representative the selected time point is within the activation curve of the actuation process. Considering the functionality of the FSR, the signal peak is the moment where the highest pressure is applied to the input device. We decided to select the maximum of the activation curve as a representation of the tap time. We will now focus our attention on the analysis of the performance of the signal processing algorithm used in `rec2taps` when applied to recordings performed with the presented input device.

The proposal of a Force Sensitive Resistor (FSR) as input device was due to the clarity of the signal provided. The signal is very close to zero when it is not being

actuated and then raises rapidly proportionally to the pressure applied. Figure 13a shows the shape of one FSR activation when aligned to the detected maximum and normalized to the peak's height. Figure 13c shows mean activation over time for 3000 peaks from 68 recordings. The process to detect activations starts by rectifying (setting to 0) the signal below a threshold defined as 1.5 times the standard deviation of the signal amplitude (figure 13b). Afterwards, peaks are found as points in the signal that are local maximums and have a prominence of at least the mentioned threshold and are distanced between each other at least 100 ms. The prominence of a peak measures the height relative to the smallest valleys between a possible peak and any closest greater peak. Our utility uses the function `find_peaks` from the `scipy.signal` package (version 1.2.0) (Virtanen et al., 2020).

To inspect the recall and over-sensitivity of the algorithm used, we inspected its performance over a set of tapping recordings from a beat tapping experiment using the proposed setup (Miguel, Sigman, & Slezak, 2019). The experiment required participants to listen to non-isochronous rhythmic passages performed by identical click sounds and tap to a self-selected beat. Participants were free to decide on the beat and were allowed to change the beat mid-rhythm or even pause tapping. The data set comprises 518 recordings from 21 participants. The evaluation of the peak picking process consisted on visually inspecting the recording signal with the detected tap times overlapped and annotating for each recording the number of missing and spurious activations. Inspection was performed by one of the authors. On 491 (105%) of the audios no missing or spurious activations were seen and only on 5 (%) more than 2 missing or spurious activations were reported. The experiment contained rhythms of varying complexity, some of which had a very ambiguous beat. As a consequence, some participants produced taps of varying strength, including some weak onsets. Whether these activations are to be considered may depend on the nature of the experiment and can require making the peak picking process more sensitive. The provided utility, `rec2taps`, allows configuring the mentioned detection threshold as a parameter. It also allows producing plots of the FSR signal and detected peaks to calibrate the parameter.

In the supplementary material we present plots as the one produced by the utility as examples of tap detections for both general cases and for cases with taps of varying strength to illustrate the workings of the peak picking procedure.

A final caveat of the signal processing regards the usage of a sound card as the recording device. Sound cards generally high-pass filter the signal at about 5Hz. As a consequence, the shape of the input signal may be modified, specially if the tapping action was too soft. We examined the effect of a high-pass filter on a FSR signal recorded with a digital signal acquisition device at 1000 Hz. To do so, we resampled the original 1000 Hz signal to 48000 Hz using a linear interpolation, applied a 5 Hz high-pass filter and recalculated the location in time of the peak of the modified signal. We looked into 1508 tap activation profiles from a synchronization experiment. In 67.57% of the cases, the maximum of the filtered signal remained in the same millisecond position. In 26.72% and 5.5% of the cases, the maximum of the filtered signal was one or two milliseconds ahead of the original signal, respectively. In 0.2%, the shift was greater than two milliseconds, up to -25 ms. We hypothesized the negative lag of the maximum of the filtered signal to be related with a soft tapping action. We inspected this hypothesis by looking at the maximum amplitude of the FSR signal with respect to the peak's lag. Effectively, lags greater than 2 ms were seen only in taps three times softer than average. Figure 14 presents the distribution of the amplitude of the peaks for each lag found.

Discussion

The current work presents an experimental setup intended to collect timed responses with high-precision (less than -3ms delay) synchronized to onset times in auditory stimuli. Another main characteristic of the proposed setup is its inexpensiveness and simplicity. The introduction presents the general schematic of experimental trials with auditory stimuli where the quantity of interest is elapsed time from the moment a stimuli is heard until a response is provided. In the **Problem Description** section we explained why this quantity cannot be measured in an

standard experimental setup using a computer. We also review previous approaches to the issue. In the **Setup Description and Installation** section we describe our proposed setup and provide detailed instructions for assembly. Finally, in **Tool Suit and Usage Workflow** we present an open-source software tool suit to run experiments using the presented setup.

Being able to collect response times to auditory stimuli with precision cannot be easily done using a standard computer with default input devices (keyboard or mouse). This is due to latencies introduced between the input device and the experiment software or between the experiment software and the output device. Approaches to this issue are either using specialized hardware for input and output, running the experiment using a programmable micro-controller or recording auditory output and responses in a separate recording device. Our setup uses the last method.

Although this approach has been presented before in Elliott et al. (2009), we here present a less expensive alternative by using an inexpensive recording device. Moreover, we present assembly instructions for an inexpensive input device that allows high precision recording. This setup easily allows using any audio as stimulus. In addition, we provide a open-source tool suit for using the setup that does not require proprietary software.

An evaluation of the performance of the software’s capability to detect participant’s responses is described at the end of the previous section. The evaluation showed no spurious or missing activation detections in 94% of the analyzed recordings and under 1% presented more than two. Miss-detection of activations was seen to relate to situations where the tapping action varied in strength throughout the experiment trial.

A main limitation of this setup is that it cannot respond to participants responses, either by changing the course of the experiment or providing feedback. In that situation, most inexpensive approach is given in Schultz and Palmer (2019). In case of access to precise input equipment, more direct setups can be accomplished (Bridges et al., 2020; Finney, 2001). Another caveat of the setup presented here is a

possible shift in response time in case of soft tapping (see subsection Signal Analysis). Finally, assembly of the input device requires a minimum knowledge of electronics.

In summary, we provide an inexpensive setup for recording responses to auditory stimuli with millisecond precision together with a software tool suit for using the setup. The main focus is on getting high-precision response times relative to the auditory stimulus with minimal calibration.

Acknowledgments

This work was carried out by the corresponding author under a PhD Scholarship provided by CONICET. No conflict of interests are declared.

Open Practices Statements

The software tool suit is available with an MIT license via github repositories. Data used to evaluate the precision of the tap extraction algorithm is available upon request. None of the experiments were pre-registered.


Links to open source content:

- Detailed instructions, tutorials and discussions on setup assembly:
https://github.com/m2march/tapping_setup
- Code for beats2audio utility: <https://github.com/m2march/beats2audio>
- Code for runAudioExperiment utility:
<https://github.com/m2march/runAudioExperiment>
- Code for rec2taps utility: <https://github.com/m2march/rec2taps>


Figure 7.

Setup Diagram for a Tapping Input Device Using a Force Sensitive Resistor (FSR)

(a) Schematic of the component connections



(b) Schematic of the electronic connections



Note. The setup drives current with varying voltage from a VBUS pin of a USB (type-a) connector to the pin of a 3.5mm audio jack. Voltage is limited using a voltage divisor circuit (orange and purple). Final output voltage into the audio jack depends on the resistance provided by the FSR, that drops with pressure. The higher the pressure, the higher the voltage provided in the audio jack and recorded by the sound card. Schematic was drawn using Fritzing (Knörig, Wettach, & Cohen, 2009).

Figure 8.

Reference Pictures of the Elements and Connections of the setup.

(a) Sound card with stereo


input and output and monitor

(b) Stereo male-male rca cable.

(c) Stereo male-male

output

rca-3.5mm jack cable.




(d) Picture of connections in the setup. It replicates the diagram in figure 5.



Figure 9.

Interface of Audacity (Audacity (v2.2.1), n.d.) used to test the recording



Note. To test the setup, a recording of the computer's output and inputs on the device must be performed. The input device (in case of an external sound card) must be selected (a.a), recording should be started and stopped while the input device is operated (a.b), and then the recording should be played and a mixture of the sound being played and the tapping on the input device should be heard (a.c). A peak is expected to look as presented in fig (b). Fig (c) presents the case where the peak saturated the recording, resulting in a flat top. Fig (d) presents an inverted peak, where the first peak is negative.

Figure 10.

Example text file indicating onset times in milliseconds, one per line

546
1638
1911
3003
3549
4914

Figure 11.

Depiction of a Trial.





Figure 12.

Configuration file example.

```
black_duration: 600           # Duration of black screen (in ms)
c1_duration: 3000            # Duration of first noise screen (in ms)
c1_color: "#afd444"         # Color of first noise screen
c2_duration: 000            # Duration of second noise screen (in ms)
c2_color: "#afd444"         # Color of second noise screen
randomize: false            # Whether trial order should be randomized
sound_device: "default"     # String or int identifying the sound device used
silence_duration: 1500      # Duration of silence after stimuli playback
c_volume: 1.0               # Volume of cleaning sound
```

Figure 13.


Shape of an FSR Activation Peak.



Note. Main line shows mean relative activation over-time. Time zero represents the maximum of the peak. Shading represents standard deviation of the activation.

Figure 14.

Distribution of Tap Strength for Delays of Filtered Signal Maximum



References

- Audacity (v2.2.1)*. (n.d.). Retrieved from www.audacityteam.org
- Barry, R. J., De Blasio, F. M., & Borchard, J. P. (2014). Sequential processing in the equiprobable auditory go/nogo task: children vs. adults. *Clinical Neurophysiology*, *125*(10), 1995–2006.
- Bavassi, L., Kamienkowski, J. E., Sigman, M., & Laje, R. (2017). Sensorimotor synchronization: neurophysiological markers of the asynchrony in a finger-tapping task. *Psychological research*, *81*(1), 143–156.
- Bridges, D., Pitiot, A., MacAskill, M. R., & Peirce, J. (2020). The timing mega-study: comparing a range of experiment generators, both lab-based and online.
- Daikoku, T., Takahashi, Y., Tarumoto, N., & Yasuda, H. (2018). Motor reproduction of time interval depends on internal temporal cues in the brain: sensorimotor imagery in rhythm. *Frontiers in psychology*, *9*, 1873.
- Dubé, L., & Le Bel, J. (2003). The content and structure of laypeople's concept of pleasure. *Cognition and Emotion*, *17*(2), 263–295.
- Elliott, M. T., Welchman, A. E., & Wing, A. M. (2009). Mattap: A matlab toolbox for the control and analysis of movement synchronisation experiments. *Journal of Neuroscience Methods*, *177*(1), 250–257.
- Elliott, M. T., Wing, A. M., & Welchman, A. E. (2014). Moving in time: Bayesian causal inference explains movement coordination to auditory beats. *Proceedings of the Royal Society B: Biological Sciences*, *281*(1786), 20140751.
- Finney, S. A. (2001). Ftap: A linux-based program for tapping and music experiments. *Behavior Research Methods, Instruments, & Computers*, *33*(1), 65–72.
- Finney, S. A. (2016). In defense of linux, usb, and midi systems for sensorimotor experiments: A response to schultz and van vugt (2015). *Unpublished manuscript*. Retrieved from <http://www.sfinney.com/images/pdfs/sf/finney2016a.pdf>.
- Fitch, W. T., & Rosenfeld, A. J. (2007). Perception and production of syncopated rhythms. *Music Perception: An Interdisciplinary Journal*, *25*(1), 43–58.


- Knörig, A., Wettach, R., & Cohen, J. (2009). Fritzing: a tool for advancing electronic prototyping for designers. In *Proceedings of the 3rd international conference on tangible and embedded interaction* (pp. 351–358).
- Krause, V., Pollok, B., & Schnitzler, A. (2010). Perception in action: the impact of sensory information on sensorimotor synchronization in musicians and non-musicians. *Acta psychologica*, *133*(1), 28–37.
- McAuley, J. D., Jones, M. R., Holub, S., Johnston, H. M., & Miller, N. S. (2006). The time of our lives: life span development of timing and event tracking. *Journal of Experimental Psychology: General*, *135*(3), 348.
- Miguel, M., Sigman, M., & Slezak, D. F. (2019, Oct). *Tapping to your own beat: experimental setup for exploring subjective tacti distribution and pulse clarity*. OSF. Retrieved from osf.io/7sqaw doi: 10.17605/OSF.IO/7SQAW
- Patel, A. D., Iversen, J. R., Chen, Y., & Repp, B. H. (2005). The influence of metricality and modality on synchronization with a beat. *Experimental brain research*, *163*(2), 226–238.
- Plant, R. R., Hammond, N., & Turner, G. (2004). Self-validating presentation and response timing in cognitive paradigms: How and why? *Behavior Research Methods, Instruments, & Computers*, *36*(2), 291–303.
- Raymond, E. S. (2003). *The art of unix programming*. Addison-Wesley Professional.
- Repp, B. H. (2006). Musical synchronization. *Music, motor control, and the brain*, 55–76.
- Repp, B. H., London, J., & Keller, P. E. (2005). Production and synchronization of uneven rhythms at fast tempi. *Music Perception: An Interdisciplinary Journal*, *23*(1), 61–78.
- Repp, B. H., & Su, Y.-H. (2013). Sensorimotor synchronization: a review of recent research (2006–2012). *Psychonomic bulletin & review*, *20*(3), 403–452.
- Schultz, B. G. (2019). The schultz midi benchmarking toolbox for midi interfaces, percussion pads, and sound cards. *Behavior research methods*, *51*(1), 204–234.

- Schultz, B. G., & Palmer, C. (2019). The roles of musical expertise and sensory feedback in beat keeping and joint action. *Psychological research*, *83*(3), 419–431.
- Schultz, B. G., & van Vugt, F. T. (2016). Tap arduino: An arduino microcontroller for low-latency auditory feedback in sensorimotor synchronization experiments. *Behavior research methods*, *48*(4), 1591–1607.
- Segalowitz, S. J., & Graves, R. E. (1990). Suitability of the ibm xt, at, and ps/2 keyboard, mouse, and game port as response devices in reaction time paradigms. *Behavior Research Methods, Instruments, & Computers*, *22*(3), 283–289.
- Shimizu, H. (2002). Measuring keyboard response delays by comparing keyboard and joystick inputs. *Behavior Research Methods, Instruments, & Computers*, *34*(2), 250–256.
- Snyder, J., & Krumhansl, C. L. (2001). Tapping to ragtime: Cues to pulse finding. *Music Perception: An Interdisciplinary Journal*, *18*(4), 455–489.
- Virtanen, P., Gommers, R., Oliphant, T. E., Haberland, M., Reddy, T., Cournapeau, D., . . . SciPy 1.0 Contributors (2020). SciPy 1.0: Fundamental Algorithms for Scientific Computing in Python. *Nature Methods*, *17*, 261–272. doi: 10.1038/s41592-019-0686-2


Supplementary Material

Figure 15.

Sample Depiction of Average Tap Detection Scenarios.



Note. Signal (green) is the activation of the input device (FSR) during one trial. Vertical lines (orange) are detected taps.


Figure 16.*Depiction of Worst Tap Detection Scenarios*

Note. Worst tap scenarios are considered as higher ratio of missing or spurious taps over detected taps. In most cases, missing taps are soft taps in comparison to the rest. Signal (green) is the activation of the input device (FSR) during one trial. Vertical lines (orange) are detected taps.


Figure 17.

Setup Diagram for a Tapping Input Device Used

(a) Schematic of the component connections



(b) Schematic of the electronic connections



Note. Schematic was drawn using Fritzing (Knörig et al., 2009).