

Self-Tuning Tube-based Model Predictive Control

Damianos Tranos, Alessio Russo, and Alexandre Proutiere

Abstract— We present Self-Tuning Tube-based Model Predictive Control (STT-MPC), an adaptive robust control algorithm for uncertain linear systems with additive disturbances based on the least-squares estimator and polytopic tubes. Our algorithm leverages concentration results to bound the system uncertainty set with prescribed confidence, and guarantees robust constraint satisfaction for this set, along with recursive feasibility and input-to-state stability. Persistence of excitation is ensured without compromising the algorithm’s asymptotic performance or increasing its computational complexity. We demonstrate the performance of our algorithm using numerical experiments.

I. INTRODUCTION

Model Predictive Control (MPC) [1] addresses the infinite horizon optimal control problem in the presence of input and state constraints by approximating it as a sequence of finite horizon optimization problems. When the dynamics of the system are uncertain, robust MPC methods [2] can be employed to ensure constraint satisfaction for pre-specified sets of system parameters and disturbances. This robustness comes at the cost of a reduced closed-loop performance. To mitigate this performance loss, one may leverage adaptive control techniques [3] to learn the system dynamics in an online manner, and in turn reduce the uncertainty causing this loss.

Adaptive control schemes have been developed and studied mainly for unconstrained control problems. The first results [4] concerned their asymptotic convergence properties and established conditions under which the controller derived from these schemes actually approaches the optimal feedback controller obtained by assuming the full knowledge on the system dynamics. More recently, see e.g. [5]–[7], researchers managed to quantify the convergence rate of some classical adaptive control schemes, such the celebrated self-tuning regulators, as well as the price that one has to pay (in terms of cumulative losses – often captured through the notion of regret) to learn the system dynamics. These recent important results are however restricted to the LQR problems in unconstrained linear systems.

In this paper, we investigate the design and the performance analysis of MPC schemes handling system dynamics uncertainties. We propose to combine adaptive and robust control methods. The adaptive control component of our schemes allows to rapidly reduce over time the uncertainties

in a controlled and quantifiable manner, whereas the robust control component ensures constraint satisfaction. More precisely, our contributions are as follows.

Contributions. We address the problem of controlling an uncertain linear system with parametric and additive disturbances, subject to deterministic constraints. We present Self-Tuning Tube-based Model Predictive Control (STT-MPC), an algorithm combining adaptive and robust control techniques. STT-MPC uses a simple Least Squares Estimator (LSE) for estimating the dynamics and a parameter set compatible with the observations with prescribed level of certainty. We derive tight concentration results (similar to those presented in [7] for the LQR problem) for this set, and exploit these results to construct fixed complexity polyhedral approximations of it. In STT-MPC, these approximations are used to build a polytopic tube MPC scheme [8] to ensure robust constraint satisfaction. We establish the recursive feasibility and the input-to-state stability of the proposed scheme.

In contrast to previously proposed robust MPC schemes (refer to §II for details), STT-MPC enjoys the following properties. (i) STT-MPC uses a probabilistic rather than robust estimation scheme, leading to notably faster adaptation rates and smaller parameter sets for which the constraints need to be satisfied. (ii) Persistence of Excitation (PE), required to get performance guarantees for the LSE, is achieved without modifying either the cost or objective function of the MPC. The added excitation is treated as an additive disturbance and can be chosen to decay to zero with time (e.g., at a rate $1/\sqrt{t}$). This allows us to asymptotically recover the performance of the standard MPC algorithm with full knowledge of the dynamics. (iii) An input-to-state stability analysis of STT-MPC is possible even when the PE condition is active and without imposing any additional restrictions on the choice of the estimate of the nominal model parameter.

Notations. For a time dependent vector x_t , we denote by $x_{k|t}$ its prediction at time $k+t$ given information at time t . For any two sets \mathcal{A} and \mathcal{B} , we define their Minkowski sum as the set $\mathcal{A} \oplus \mathcal{B} := \{a + b : a \in \mathcal{A}, b \in \mathcal{B}\}$. We also define, for any constant $\lambda \geq 0$, the scaled set $\lambda\mathcal{A} := \{\lambda a, a \in \mathcal{A}\}$. For any $d \in \mathbb{N}$, $x \in \mathbb{R}^d$, and $\epsilon > 0$ let $\mathcal{B}(x, \epsilon)$ denote the ϵ ball of the spectral norm centered on x . The unit ball centered at the origin is denoted simply as \mathcal{B} . For any set \mathcal{S} , and any $\epsilon > 0$ there exists a polytope \mathcal{P} that is an outer approximation of \mathcal{S} , i.e. $\mathcal{S} \subset \mathcal{P} \oplus \epsilon\mathcal{B}$. We refer to this polytope as the outer polyhedral approximation of \mathcal{S} . Finally, a function $\kappa : \mathbb{R}_+ \rightarrow \mathbb{R}_+$ is of class \mathcal{K} if it is strictly increasing and $\kappa(0) = 0$ and is of class \mathcal{K}_∞ if in addition

This work was supported by the Wallenberg AI, Autonomous Systems and Software Program (WASP) funded by the Knut and Alice Wallenberg Foundation.

D. Tranos, A. Russo, and A. Proutiere are with the Division of Decision and Control Systems, School of Electrical Engineering and Computer Science, Royal Institute of Technology (KTH), Stockholm, Sweden. Emails: {tranos@kth.se, alessior@kth.se, alepro@kth.se}.

$\kappa(x) \rightarrow \infty$ as $x \rightarrow \infty$.

II. RELATED WORK

An essential ingredient of adaptive control is Persistent Excitation (PE) [9] (which is equivalent to the notion of required exploration in reinforcement learning [10]). In the context of MPC, different solutions for PE have been investigated: [11] introduces a sufficient PE condition as an additional constraint in their MPC optimization. On the other hand, [12], [13], and later [14], propose dual-MPC schemes where the predicted parameter covariance matrix is included in the cost function, though these dual-control methods lack feasibility and stability guarantees.

In a different direction, the works of [15] and [16] introduce robust MPC schemes with guaranteed recursive feasibility and constraint satisfaction. These schemes come with the cost of only considering adaptation for the nominal model, where PE is not ensured, and robustness is guaranteed for a fixed parameter set that is not updated online. In contrast, our scheme, STT-MPC, updates the parameter set each step, and the latter rapidly concentrates around the true parameter.

In [17], the authors combine set-membership identification, which involves updating a set of parameters compatible with the observed state-trajectory, and robust constraint tightening for FIR models. This approach was later extended in [18] to the case of linear state-space models where online set-membership is combined with homothetic tube MPC [19]. Subsequently, [20] proposed an adaptive robust MPC scheme using again set-membership identification and a less conservative polytopic tube MPC scheme [8]. As in [11], they ensure PE in the form of added convex constraints and a modification of the cost function.

III. MODEL, OBJECTIVE, AND APPROACH

A. Model and assumptions

We consider the following discrete time, linear, time-invariant system:

$$x_{t+1} = A(\theta^*)x_t + B(\theta^*)u_t + w_t, \quad (1)$$

where $x_t, w_t \in \mathbb{R}^{d_x}$ and $u_t \in \mathbb{R}^{d_u}$. The state transition and state-action transition matrices $A(\theta^*)$ and $B(\theta^*)$ are initially unknown. The set of possible such matrices is parametrized by $\theta \in \mathbb{R}^{d_\theta}$ (here θ could well parametrize each entry of the matrices, in which case $d_\theta = d_x(d_x + d_u)$). To simplify the notations, for two possible parameters θ_1, θ_2 , we define $\|\theta_1 - \theta_2\| := \max(\|A(\theta_1) - A(\theta_2)\|_2, \|B(\theta_1) - B(\theta_2)\|_2)$. We make the following assumptions.

Assumption 1 (Parameter uncertainty). *For some $\epsilon_0 > 0$, $B(\theta^*, \epsilon_0) \subset \Theta_0$ where Θ_0 is a known convex polytope.*

Assumption 2 (Additive disturbance). *The sequence $(w_t)_{t \geq 0}$ is i.i.d, and for each $t \geq 0$, w_t is zero-mean, isotropic, with support in the ball $\mathcal{B}(0, 3\sigma)$. Hence, w_t is σ^2 -sub-gaussian. Further define \mathcal{W} , a convex polytope providing a conservative approximation of $\mathcal{B}(0, 3\sigma)$, i.e., $\mathcal{B}(0, 3\sigma) \subset \mathcal{W}$.*

The system also needs to obey the following state and input constraints for all $t \geq 0$,

$$Fx_t + Gu_t \leq \mathbf{1}, \quad (2)$$

where $F \in \mathbb{R}^{d_c \times d_x}$ and $G \in \mathbb{R}^{d_c \times d_u}$ define the state and input constraints respectively.

Assumption 3 (State and input constraints). *The set*

$$\mathcal{C} = \{(x, u) \in \mathbb{R}^{d_x} \times \mathbb{R}^{d_u} : Fx + Gu \leq \mathbf{1}\}$$

is compact and contains the origin in its interior.

Finally, we assume that we have access to a stabilizer K :

Assumption 4 (Stabilizing Controller). *There exists a known, robustly stabilizing feedback gain K such that $A(\theta) + B(\theta)K$ is stable (i.e., $\rho(A(\theta) + B(\theta)K) < 1$) for all $\theta \in \Theta_0$.*

B. Objective and MPC

We wish to minimize the long-term cost defined as $\limsup_{T \rightarrow \infty} \frac{1}{T} \sum_{t=0}^{T-1} x_t^\top Q x_t + u_t^\top R u_t$, through some positive semi-definite matrices Q, R . To this aim, we use MPC, with a receding horizon N . Specifically, at time t , given the current system state x_t and the past observations used to derive an estimator θ_t of θ^* , we will identify a control policy $(u_{k|t})_{k=0, \dots, N-1}$ minimizing the cost along a predicted system trajectory $(x_{k|t})_{k=0, \dots, N}$. We use the well-known dual mode prediction paradigm [21] with the following predicted control sequence,

$$u_{k|t} = \begin{cases} Kx_{k|t} + v_{k|t} & \forall k \in \{0, \dots, N-1\}, \\ Kx_{k|t} & \forall k \geq N, \end{cases} \quad (3)$$

where $\{v_{0|t}, \dots, v_{N-1|t}\}$ are the optimization variables to be determined by the MPC. The resulting prediction dynamics will be for $k \in \{0, \dots, N-1\}$,

$$x_{0|t} = x_t, \quad (4a)$$

$$x_{k+1|t} = \Phi(\theta_t)x_{k|t} + B(\theta_t)v_{k|t}, \quad (4b)$$

where $\Phi(\theta) := A(\theta) + B(\theta)K$ for any $\theta \in \Theta_0$.

C. General approach

To handle the uncertainty due to both the noise and the fact that θ^* is unknown, we apply a tube-based MPC approach. The tube used in step t is essentially constructed from a polytope approximating a ball centered at the LSE $\hat{\theta}_t$ of θ^* and whose radius corresponds to a prescribed level of confidence δ that the user wishes to guarantee. Persistent excitation is achieved by adding (bounded) noise to the input. The resulting algorithm is presented in Algorithm 1, and its ingredients are detailed in the next section. Its analysis is given in Section V.

Algorithm 1: STT-MPC

Input: Initial state x_0 ; confidence δ ; estimate θ_0 ;
uncertain parameter set Θ_0

- 1 Find stabilizing matrix K for all $\theta \in \Theta_0$
- 2 Compute matrices T and H_c using (10b)
- 3 **for** $t = 1, \dots, \mathcal{T}$ **do**
- 4 **if** $t < t^*(\delta)$ **then**
- 5 Set $\theta_t \leftarrow \theta_{t-1}$ and $\Theta_t \leftarrow \Theta_{t-1}$
- 6 **else**
- 7 Update $\theta_t \leftarrow \hat{\theta}_t$ using (5)
- 8 Compute Δ_t and set $\Theta_t \leftarrow \Theta_{t-1} \cap \Delta_t$
- 9 Compute matrices $H_t^{(j)}$ using (10a)
- 10 Obtain $P(\theta_t)$ by solving (20)
- 11 Solve $\mathcal{P}_N(x_t, \theta_{\rho(t)}, \Theta_{\rho(t)}, \bar{\mathcal{W}}_t)$
- 12 Apply $u_t = Kx_t + v_{0|t}^* + \zeta_t$

IV. SELF-TUNING TUBE-BASED MPC

A. LSE and persistent excitation

Our algorithm starts with an initial parameter $\theta_0 \in \Theta_0$, which is then updated using the LSE. We let $\theta_1 = \theta_0$. For $t \geq 2$, the LSE enjoys the following explicit expression:

$$\hat{\theta}_t = \left(\sum_{k=0}^{t-2} x_{k+1} \begin{bmatrix} x_k \\ u_k \end{bmatrix}^\top \right) \left(\sum_{k=0}^{t-2} \begin{bmatrix} x_k \\ u_k \end{bmatrix} \begin{bmatrix} x_k \\ u_k \end{bmatrix}^\top \right)^{\dagger}. \quad (5)$$

For $t \geq t^*(\delta)$, we align our prediction parameter θ_t to $\hat{\theta}_t$. As shown in [7], a finite-time analysis of the performance of the LSE is rather intricate but possible even if the feedback controller varies over time. The performance is tightly related to the minimal eigenvalue of the cumulative covariate matrix $\lambda_{\min}(\sum_{s=0}^{t-2} y_s y_s^\top)$ where $y_s = \begin{bmatrix} x_s \\ u_s \end{bmatrix}$. More precisely, for the LSE to lead to a good approximation of θ^* , we need to ensure that this eigenvalue grows with time. To this aim, we add an isotropic and bounded noise to the control input. This noise is represented by the random vector ζ_t taken to be the projection of ξ_t on $\mathcal{B}(0, 3\sigma_t)$, where ξ_t is i.i.d. according to a normal distribution, i.e., $\xi_t \sim \mathcal{N}(0, \sigma_t^2 I_{d_u})$. The choice of σ_t directly impacts the performance of the LSE but also the overall performance of the controller (a higher σ_t means higher excitation and hence better LSE, but at the expense of a worse overall controller, refer to Section VII). Here we set $\sigma_t^2 = \sqrt{d_x} \sigma^2 t^{-\alpha}$ for some $\alpha \in (0, 1)$. This ensures that (i) the LSE θ_t converges to θ^* (refer to Section V for a precise statement) and (ii) the controller converges to that obtained through a classical tube-based MPC framework with known θ^* . When analyzing the performance of the LSE, we will show that the *good event* \mathcal{G} holds with probability at least $1 - \delta$:

$$\mathcal{G} = \left(\|\hat{\theta}_t - \theta^*\| \leq \epsilon_t, \forall t \geq t^*(\delta) \right),$$

where $t^*(\delta) = c_1 + c_2 \log(1/\delta)$ and $\epsilon_t^2 = c_3 \log(t/\delta)/t^{1-\alpha}$ for some positive constants c_1, c_2, c_3 . From the above result, we define Δ_t as an outer polyhedral approximation of

$\mathcal{B}(\theta_t, 2\epsilon_t)$. We further recursively define the *uncertainty sets* as follows: $\Theta_t = \Theta_{t-1} \cap \Delta_t$ for all $t \geq t^*(\delta)$ and $\Theta_t = \Theta_0$ for $t < t^*(\delta)$. By construction, the true parameter θ^* belongs to the interior of Θ_t with high probability in the following sense:

Lemma 1. *Under event \mathcal{G} , $\mathcal{B}(\theta^*, \epsilon_t) \subset \Theta_t$ for all $t \geq 1$.*

Proof. For $t < t^*(\delta)$ we have $\Theta_t = \Theta_0$ and the result holds by Assumption 1. Let $t \geq t^*(\delta)$. We show that $\mathcal{B}(\theta^*, \epsilon_t) \subset \Delta_t$ and $\mathcal{B}(\theta^*, \epsilon_t) \subset \Theta_{t-1}$. For the first, we have for all $\theta \in \mathcal{B}(\theta^*, \epsilon_t)$, using the triangle inequality: $\|\theta - \theta_t\| \leq \|\theta - \theta^*\| + \|\theta_t - \theta^*\| \leq 2\epsilon_t$, where the second inequality holds under \mathcal{G} . Thus $\theta \in \mathcal{B}(\theta_t, 2\epsilon_t)$ and so $\mathcal{B}(\theta^*, \epsilon_t) \subset \mathcal{B}(\theta_t, 2\epsilon_t) \subset \Delta_t$. We prove $\mathcal{B}(\theta^*, \epsilon_t) \subset \Theta_{t-1}$ by induction. Assume that $\mathcal{B}(\theta^*, \epsilon_t) \subset \Theta_{t-1}$. Then we show that $\mathcal{B}(\theta^*, \epsilon_{t+1}) \subset \Theta_t$. Let θ such that $\|\theta - \theta^*\| \leq \epsilon_{t+1}$. Then $\|\theta - \theta_t\| \leq \|\theta - \theta^*\| + \|\theta_t - \theta^*\| \leq \epsilon_{t+1} + \epsilon_t$. This implies that $\theta \in \Delta_t$. In addition, $\theta \in \Theta_{t-1}$. Indeed, $\|\theta - \theta^*\| \leq \epsilon_{t+1} \leq \epsilon_t$, and we conclude using the induction assumption. Hence $\theta \in \Theta_t$. \square

B. Polytopic tubes and associated linear constraints

With the considered control inputs, the system dynamics becomes:

$$x_{t+1} = \Phi(\theta^*)x_t + B(\theta^*)(v_{0|t} + \zeta_t) + w_t. \quad (6)$$

We apply a tube-based approach, and at time t , we build a polytopic tube based on:

- (i) Θ_t , encoding the uncertainty about θ^* . We denote by m_t the number of vertices of Θ_t , and the vertices themselves by $\theta_t^{(j)}$, $j = 1, \dots, m_t$.
- (ii) A polytope $\bar{\mathcal{W}}_t$, handling the uncertainty due to the noise $B(\theta^*)\zeta_t + w_t$, including that due to the persistent excitation. To define $\bar{\mathcal{W}}_t$, let $\bar{B}_t = \max_{\theta \in \Theta_t} \|B(\theta)\|_2$. We define \mathcal{Z}_t as the outer polyhedral approximation to $\mathcal{B}(0, 3\sigma_t)$, and $\bar{\mathcal{W}}_t = \mathcal{W} \oplus \bar{B}_t \mathcal{Z}_t$.

We define the state tube cross sections as the sets: for $k = 0, \dots, N$,

$$X_{k|t} = \{x : Tx \leq \alpha_{k|t}\}, \quad (7)$$

where the matrix $T \in \mathbb{R}^{d_\alpha \times d_x}$ is chosen such that, for some $\lambda \in [0, 1)$, the set $\{x : Tx \leq \mathbf{1}\}$ is λ -contractive with respect to the system $x_{t+1} = \Phi(\theta)x_t$ for all $\theta \in \Theta_0$. This property is needed to ensure the robust positive invariance of $X_{N|t}$ (see Lemma 5.7 in [21]). To derive the associated linear constraints, we apply a standard result to ensure inclusion of polyhedra (see Proposition 3.31 in [22]). More precisely, for any $j = 1, \dots, m_t$, we have $X_{k|t} \subseteq \{x : \Phi(\theta_t^{(j)})x + B(\theta_t^{(j)})v_{k|t} + w \in X_{k+1|t}\}$ for all $w \in \bar{\mathcal{W}}_t$ if there exists $H_t^{(j)} \geq 0$ such that:

$$H_t^{(j)}T = T\Phi(\theta_t^{(j)}), \quad (8a)$$

$$H_t^{(j)}\alpha_{k|t} + TB(\theta_t^{(j)})v_{k|t} + \bar{w}_t \leq \alpha_{k+1|t}, \quad (8b)$$

where \bar{w}_t is such that $[\bar{w}_t]_i = \max_{w \in \bar{\mathcal{W}}_t} [Tw]_i$ for $i \in \{1, \dots, d_\alpha\}$. Similarly, we have $X_{k|t} \subseteq \{x : (F + GK)x +$

$G(v_{k|t} + \zeta) \leq \mathbf{1}$ for all $\zeta \in \mathcal{Z}_t$, if there exists $H_c \geq 0$, such that:

$$H_c T = F + GK \quad (9a)$$

$$H_c \alpha_{k|t} + Gv_{k|t} + \bar{\zeta}_t \leq \mathbf{1}, \quad (9b)$$

where $\bar{\zeta}_t$ is such that $[\bar{\zeta}_t]_i = \max_{\zeta \in \mathcal{Z}_t} [G\zeta]_i$ for $i \in \{1, \dots, d_c\}$.

Remark 1. For simplicity, we have chosen \bar{w}_t and $\bar{\zeta}_t$ so as to be conservative with respect to the noise we apply. However, notice that we could well pre-sample the noise sequence $(\zeta_t)_{t \geq 0}$ and use it as part of our predictions.

The matrices $H_t^{(j)}$, and H_c are chosen such that for all $i \in \{1, \dots, d_\alpha\}$ and for all $j \in \{1, \dots, m_t\}$,

$$(H_t^{(j)})_i = \arg \min_h \{ \mathbf{1}^\top h : h^\top T = (T)_i \Phi(\theta_t^{(j)}), h \geq 0 \}, \quad (10a)$$

and for all $i \in \{1, \dots, d_c\}$,

$$(H_c)_i = \arg \min_h \{ \mathbf{1}^\top h : h^\top T = (F + GK)_i, h \geq 0 \}. \quad (10b)$$

Finally, we have the terminal conditions

$$H_t^{(j)} \alpha_N + \bar{w}_t \leq \alpha_N, \quad (11)$$

$$H_c \alpha_N + \bar{\zeta}_t \leq \mathbf{1}. \quad (12)$$

C. The tube MPC problem

Fix a step t . Let $\mathbf{v}_t = \{v_{0|t}, \dots, v_{N-1|t}\}$ and $\alpha_t = \{\alpha_{0|t}, \dots, \alpha_{N|t}\}$. The resulting tube MPC problem, denoted as $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$, and evaluated at every t , is

$$\underset{\mathbf{v}_t, \alpha_t}{\text{minimize}} \sum_{k=0}^{N-1} \left(x_{k|t}^\top Q x_{k|t} + v_{k|t}^\top R v_{k|t} \right) + x_{N|t}^\top P(\theta_t) x_{N|t}$$

subject to, for all $j = 1, \dots, m_t$, and $k = 0, \dots, N-1$:

initial constraints:

$$x_{0|t} = x_t, \quad (13)$$

$$T x_{0|t} \leq \alpha_{0|t}, \quad (14)$$

system constraints,

$$x_{k+1|t} = \Phi(\theta_t) x_{k|t} + B(\theta_t) v_{k|t}, \quad (15)$$

tube constraints,

$$H_t^{(j)} \alpha_{k|t} + T B v_{k|t} + \bar{w}_t \leq \alpha_{k+1|t}, \quad (16)$$

$$H_c \alpha_{k|t} + G v_{k|t} + \bar{\zeta}_t \leq \mathbf{1}, \quad (17)$$

terminal constraints:

$$H_t^{(j)} \alpha_{N|t} + \bar{w}_t \leq \alpha_{N|t}, \quad (18)$$

$$H_c \alpha_{N|t} + \bar{\zeta}_t \leq \mathbf{1}. \quad (19)$$

where $P(\theta_t)$ is obtained by solving the Lyapunov equation:

$$P(\theta_t) - \Phi(\theta_t)^\top P(\theta_t) \Phi(\theta_t) = Q + K^\top R K \quad (20)$$

The feasibility of the above problem depends on whether $\theta^* \in \Theta_t$, i.e., on the event \mathcal{G} . However, for the sake of the analysis, we would like to ensure that the problem the algorithm solves in each step is always feasible (with

probability 1). In turn, this will allow us to analyze the performance of the LSE and to establish that indeed \mathcal{G} holds with probability at least $1 - \delta$ (refer to the next section for details). To ensure that the tube MPC problem is always feasible, i.e., even when \mathcal{G} does not occur, we instead solve $\mathcal{P}_N(x_t, \theta_{\rho(t)}, \Theta_{\rho(t)}, \bar{\mathcal{W}}_t)$ in Algorithm 1 where,

$$\rho(t) := \max\{\tau \leq t : \mathcal{P}_N(x_t, \theta_\tau, \Theta_\tau, \bar{\mathcal{W}}_t) \text{ is feasible}\}.$$

Essentially, in the unlikely event that $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$ is not feasible, we instead solve $\mathcal{P}_N(x_t, \theta_\tau, \Theta_\tau, \bar{\mathcal{W}}_t)$ using the latest estimates θ_τ and Θ_τ for which the problem is feasible. This modification is of little practical consequence as we can (and typically do) choose δ to be very small.

V. ANALYSIS

This section is devoted to the analysis of the Self-tuning Tube-based MPC (STT-MPC) algorithm. We first provides guarantees for the LSE, and then establish the recursive feasibility and the input-to-state stability of the algorithm.

A. Performance of the LSE

Theorem 1. Assume that the optimization problem $\mathcal{P}_N(x_0, \theta_0, \Theta_0, \bar{\mathcal{W}}_0)$ is feasible for initial state $x_0 \in \mathbb{R}^{d_x}$ and parameter $\theta_0 \in \Theta_0$. Under the STT-MPC algorithm, we have: for all $\delta \in (0, 1)^2$,

$$\mathbb{P}[\mathcal{G}] = \mathbb{P}[\|\hat{\theta}_t - \theta^*\| \leq \epsilon_t, \forall t \geq t^*(\delta)] \geq 1 - \delta.$$

Proof. The proof follows a similar path as that used to prove Proposition 1 in [7], and we provide a sketch of the arguments below. We first decompose the mean square error as (see the proof of Proposition 1 in [7]):

$$\|\hat{\theta}_t - \theta^*\|^2 \leq \left\| \left(\sum_{s=0}^{t-2} y_s y_s^\top \right)^{-1/2} \left(\sum_{s=0}^{t-2} y_s w_s^\top \right) \right\|^2 \times \frac{1}{\lambda_{\min} \left(\sum_{s=0}^{t-2} y_s y_s^\top \right)}.$$

The first term in the r.h.s. of the above inequality is referred to as the self-normalizing term, and it can be analyzed using Hanson-Wright inequality. Specifically, we can show as in the proof of Proposition 1 in [7] that it is smaller than $c_4 \log(t/\delta)$ with probability at least $1 - \delta/2$ for some constant $c_4 > 0$ and for any $\delta \in (0, 1)$. To prove this upper bound, we leverage the fact that the tube MPC problem solved under STT-MPC is feasible in *each* step (see Theorem 2 (ii)), which in turn ensures that y_t is bounded, and simplifies the analysis of the self-normalizing term. Next, we can derive a lower bound of the minimal eigenvalue of the cumulative covariate matrix using the techniques developed in Appendix G in [7]. As in Proposition 11 in [7], we can show that for any $\delta \in (0, 1)$, $\lambda_{\min} \left(\sum_{s=0}^{t-2} y_s y_s^\top \right) \geq c_5 t^{1-\alpha}$ with probability at least $1 - \delta$, provided that $t^{1-\alpha} \geq c_6 \log(e/\delta)$, for some

¹More precisely, the problem is obtained by replacing θ_t by $\theta_{\rho(t)}$, $H_t^{(j)}$ by $H_{\rho(t)}^{(j)}$ for all j in $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$.

²Note that the result holds for all $\delta \in (0, 1)$ and in particular for the parameter δ chosen as input of the STT-MPC algorithm.

constants $c_5, c_6 > 0$. We conclude that for any $\delta \in (0, 1)$, $\|\hat{\theta}_t - \theta^*\| \leq \epsilon_t$ with probability at least $1 - \delta$ when $t^{1-\alpha} \geq c_6 \log(e/\delta)$. The upper bound of $\|\hat{\theta}_t - \theta^*\|$ can be made uniform over time $t \geq t^*(\delta)$ applying Lemma 23 in [7], which concludes the proof. \square

B. Recursive feasibility

Theorem 2. *If the optimization problem $\mathcal{P}_N(x_0, \theta_0, \Theta_0, \bar{\mathcal{W}}_0)$ is feasible for initial state $x_0 \in \mathbb{R}^{d_x}$ and parameter $\theta_0 \in \Theta_0$, then, for all $t > 0$,*

- (i) *under event \mathcal{G} , the problem $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$ is feasible;*
- (ii) *the problem $\mathcal{P}_N(x_t, \theta_{\rho(t)}, \Theta_{\rho(t)}, \bar{\mathcal{W}}_t)$ is feasible.*

Proof. For (i), we have that \mathcal{G} holds which, together with Assumption 1, ensures that $\theta^* \in \Theta_t$ for all $t > 0$. Let $\mathcal{P}_N(x_{t-1}, \theta_{t-1}, \Theta_{t-1}, \bar{\mathcal{W}}_{t-1})$ be feasible with solution $(v_{t-1}^*, \alpha_{t-1}^*)$. We define the tail point $(\hat{v}_t, \hat{\alpha}_t)$ as

$$\begin{aligned} \hat{v}_t &= \{v_{1|t-1}^*, \dots, v_{N-1|t-1}^*, 0\}, \\ \hat{\alpha}_t &= \{\alpha_{1|t-1}, \dots, \alpha_{N|t-1}, \alpha_{N|t-1}\}, \end{aligned}$$

and we show that it is a feasible point for $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$, i.e., that it satisfies the constraints (14)-(19) at time t .

The initial constraint (14) is satisfied since $(v_{t-1}^*, \alpha_{t-1}^*)$ satisfies (16), and $\theta^* \in \Theta_{t-1}$, which together imply that $x_t \in \mathcal{X}_{1|t-1}$. The system dynamics constraint (15) holds automatically. We now consider only the vertices of Θ_{t-1} and note that $\bar{w}_{t-1} \geq \bar{w}_t$ and $\bar{\zeta}_{t-1} \geq \bar{\zeta}_t$. At time t , the tube constraints (16) and (17) for $k \in \{0, \dots, N-2\}$ are satisfied whenever the tube constraints for $k \in \{1, \dots, N-1\}$ at time $t-1$ are satisfied. Furthermore, noting that $v_{N-1|t} = 0$ and $\alpha_{N|t} = \alpha_{N|t-1}^*$, by simple substitution, we will have that (16) and (17) for $k = N-1$ at time t hold when the terminal constraints (18) and (19) at time $t-1$ hold. If the terminal constraints hold at time $t-1$, they will also hold at time t . Finally, since $\Theta_t \subseteq \Theta_{t-1}$, these constraints will also hold for every vertex of Θ_t .

For (ii) note that, due to Assumption 1, $\theta^* \in \Theta_0$ so that there will always exist $\tau \leq t$ such that $\theta^* \in \Theta_\tau$ and such that $\mathcal{P}_N(x_\tau, \theta_\tau, \Theta_\tau, \bar{\mathcal{W}}_\tau)$ is feasible. Then, using a similar argument as in (i) we will have that $\mathcal{P}_N(x_{\tau+1}, \theta_\tau, \Theta_\tau, \bar{\mathcal{W}}_{\tau+1})$ is feasible and thus $\mathcal{P}_N(x_{t+1}, \theta_\tau, \Theta_\tau, \bar{\mathcal{W}}_{t+1})$ is feasible. \square

C. Input-to-State Stability (ISS)

Let $X_{\mathcal{P}}$ be the set of states x_0 such that problem $\mathcal{P}_N(x_0, \theta_0, \Theta_0, \bar{\mathcal{W}}_0)$ is feasible. Additionally, let $J(x_t, v_t, \theta_t)$ be the objective of problem $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$, let v_t^* be its optimal solution and let $V^*(x_t, \theta_t)$ be its associated value. To simplify notations, we refer to the closed loop system (6) as,

$$x_{t+1} = f(x_t, v_t, w_t, \theta_t) \quad (21)$$

where, we refer to $B(\theta_t)\zeta_t + w_t$ as w_t . We further define the stage cost $L(x, v) = x^\top(Q + K^\top RK)x + v^\top Rv$, and terminal cost $\phi(x, \theta) = x^\top P(\theta)x$ so that

$$J(x_t, v_t, \theta_t) = \sum_{k=0}^{N-1} L(x_{k|t}, v_{k|t}) + \phi(x_{N|t}, \theta_t).$$

Lemma 2 (Theorem 3 in [23]). *The system (21) with control law $v_t(x_t, \theta_t)$ is ISS with region of attraction $\mathcal{R} \subseteq \mathbb{R}^{d_x}$ if*

- (i) *\mathcal{R} is a compact set containing the origin, and is robust positive invariant for (21).*
- (ii) *There exist \mathcal{K}_∞ -functions $\alpha_1, \alpha_2, \alpha_3$, \mathcal{K} -functions σ_1, σ_2 , and a continuous Lyapunov function $V : \mathcal{R} \rightarrow \mathbb{R}_+$ such that for all states $x_t \in \mathcal{R}$ and disturbances $w_t \in \bar{\mathcal{W}}_t$ we have,*

$$\alpha_1(\|x_t\|) \leq V(x_t) \leq \alpha_2(\|x_t\|) \quad (22)$$

$$\begin{aligned} V(x_{t+1}) - V(x_t) &\leq -\alpha_3(\|x_t\|) + \sigma_1(\|w_t\|) \\ &\quad + \sigma_2(\|\theta_t - \theta^*\|). \end{aligned} \quad (23)$$

Theorem 3. *Under event \mathcal{G} and under the STT-MPC algorithm, for all initial conditions $x_0 \in X_{\mathcal{P}}$ and all parameters $\theta^* \in \Theta_0$, the system (1) is ISS with region of attraction $X_{\mathcal{P}}$.*

It suffices to show that $X_{\mathcal{P}}$ satisfies condition (i) of Lemma 2 and $V^*(x_t, \theta_t)$ is a Lyapunov function satisfying condition (ii).

For condition (i), suppose that $\mathcal{P}_N(x_0, \theta_0, \Theta_0, \bar{\mathcal{W}}_0)$ is feasible, i.e. $X_{\mathcal{P}}$ is not empty. Then the terminal constraints (18) and (19) ensure that there exists an $\alpha_{N|0}$ such that the terminal cross-section set $X_{N|0} = \{x : Tx \leq \alpha_{N|0}\}$ satisfies the constraints (2) and $f(x, 0, \theta, w) \in X_{N|0}$ for all $x \in X_{N|0}$, $w \in \bar{\mathcal{W}}_0$, and $\theta \in \Theta_0$, i.e. it is robustly invariant. For every $x \in X_{N|0}$, the point $(v, \alpha) = (\{0, \dots, 0\}, \{\alpha_{N|0}, \dots, \alpha_{N|0}\})$ is feasible for $\mathcal{P}_N(x, \theta_0, \Theta_0, \bar{\mathcal{W}}_0)$, thus $X_{N|0} \subseteq X_{\mathcal{P}}$. The robust positive invariance of $X_{\mathcal{P}}$ will then follow directly from Theorem 2. Since $X_{N|t} \subseteq X_{\mathcal{P}}$ and $0 \in \bar{\mathcal{W}}_t$ by Assumption 2, we have $0 \in X_{\mathcal{P}}$. Finally, $X_{\mathcal{P}}$ is compact due to Assumption 3.

For condition (ii) we first show that the bound (22) holds for $V^*(x_t, \theta_t)$. For any given state x_t , and parameters $\theta_t \in \Theta_t$, and for any $Q, R \succ 0$, problem $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$ will be a quadratic program and it follows from Theorem 4 in [24] that $V^*(x_t, \theta_t)$ is a continuous function of x_t . Since Θ_t is compact by Assumption 1, it follows from Lemma 4.2 in [25] that there exist \mathcal{K}_∞ -functions α_1, α_2 such that for any $x_t \in X_{\mathcal{P}}$,

$$\alpha_1(\|x_t\|) \leq V^*(x_t, \theta_t) \leq \alpha_2(\|x_t\|).$$

We now show the bound (23). First, note that the continuity of $f(x, u, w, \theta)$, $L(x, u)$, and $\phi(x, \theta)$ with respect to x, u, w , and θ , implies that there exist \mathcal{K}_∞ -functions $\sigma_x, \sigma_w, \sigma_\theta, \sigma_L, \sigma_\phi$, so that for all $x, x_1, x_2 \in X_{\mathcal{P}}$, $v \in \mathbb{R}^{d_u}$, $w, w_1, w_2 \in \bar{\mathcal{W}}_0$, and $\theta, \theta_1, \theta_2 \in \Theta_t$,

$$\begin{aligned} \|f(x_1, v, w_1, \theta_1) - f(x_2, v, w_2, \theta_2)\| &\leq \sigma_x(\|x_1 - x_2\|) \\ &\quad + \sigma_w(\|w_1 - w_2\|) + \sigma_\theta(\|\theta_1 - \theta_2\|), \\ |L(x_1, v) - L(x_2, v)| &\leq \sigma_L(\|x_1 - x_2\|), \\ \|\phi(x_1, \theta) - \phi(x_2, \theta)\| &\leq \sigma_\phi(\|x_1 - x_2\|). \end{aligned}$$

Recall that $v_t^* = \{v_{0|t}^*, \dots, v_{N-1|t}^*\}$ is the predicted control sequence that arises from the solution of $\mathcal{P}_N(x_t, \theta_t, \Theta_t, \bar{\mathcal{W}}_t)$.

We denote by $\mathbf{x}_t^* = \{x_{0|t}^*, \dots, x_{N|t}^*\}$, the associated predicted state trajectory (using (4), with parameter θ_t , when applying \mathbf{v}_t^*). Similarly, recall the tail control sequence $\hat{\mathbf{v}}_{t+1} := \{\hat{v}_{0|t+1}, \dots, \hat{v}_{N-1|t+1}\} = \{v_{1|t}^*, \dots, v_{N-1|t}^*, 0\}$ for which we define, an associated predicted state trajectory $\hat{\mathbf{x}}_{t+1} = \{\hat{x}_{0|t+1}, \dots, \hat{x}_{N|t+1}\}$ (using (4) with parameter θ_{t+1} , when applying $\hat{\mathbf{v}}_{t+1}$) with the property that $\hat{x}_{0|t+1} = x_{1|t}^*$. To simplify the presentation, we omit references to the subscript t when there is no ambiguity. Noting the suboptimality of $\hat{\mathbf{v}}_{t+1}$, we will have

$$\begin{aligned} & J(x_{t+1}, \hat{\mathbf{v}}_{t+1}, \theta_{t+1}) - J(x_t, \mathbf{v}_t^*, \theta_t) \\ & \leq V^*(x_{t+1}, \theta_{t+1}) - V^*(x_t, \theta_t) \\ & \leq \sum_{k=0}^{N-1} L(\hat{x}_k, \hat{v}_k) - L(x_k^*, v_k^*) + \phi(\hat{x}_N, \theta_{t+1}) - \phi(x_N^*, \theta_t) \\ & = -L(x_{0|t}, v_0^*) + \sum_{k=0}^{N-2} L(\hat{x}_k, v_{k+1}^*) - L(x_{k+1}^*, v_{k+1}^*) \\ & \quad + L(\hat{x}_{N-1}, 0) + \phi(\hat{x}_N, \theta_{t+1}) - \phi(\hat{x}_{N-1}, \theta_{t+1}) \\ & \quad + \phi(\hat{x}_{N-1}, \theta_{t+1}) - \phi(x_N^*, \theta_t). \end{aligned}$$

We will proceed to upper bound the above quantities. We first note that, for some \mathcal{K}_∞ function κ_ϵ we will have,

$$\sigma_\theta(\|\theta_{t+1} - \theta_t\|) \leq \sigma_\theta(\|\theta_t - \theta^*\|) + \kappa_\epsilon(\epsilon_t)$$

and for all $k \in \{1, \dots, N-1\}$,

$$\begin{aligned} \|\hat{x}_k - x_{k+1}^*\| & \leq \sigma_x(\|\hat{x}_{k-1} - x_k^*\|) + \sigma_\theta(\|\theta_{t+1} - \theta_t\|) \\ & \leq \sigma_x(\|\hat{x}_{k-1} - x_k^*\|) + \sigma_\theta(\|\theta_t - \theta^*\|) + \kappa_\epsilon(\epsilon_t). \end{aligned}$$

Here we use the triangle inequality, the fact that event \mathcal{G} holds, and the monotonicity of ϵ_t . Applying this relation recursively leads to,

$$\begin{aligned} \|\hat{x}_k - x_{k+1}^*\| & \leq \frac{1}{2}(2\sigma_x)^k(\|\hat{x}_0 - x_1^*\|) \\ & \quad + \sum_{i=0}^{k-1} \frac{1}{2}(2\sigma_x)^i \cdot 2(\sigma_\theta(\|\theta_t - \theta^*\|) + \kappa_\epsilon(\epsilon_t)), \end{aligned}$$

where $\|\hat{x}_0 - x_1^*\| \leq \sigma_w(w_t) + \sigma_\theta(\|\theta_t - \theta^*\|) + \kappa_\epsilon(\epsilon_t)$.

Now, since $Q, R \geq 0$, there exists a \mathcal{K}_∞ -function α_3 such that $-L(x_{0|t}, v_0^*) \leq -\alpha_3(\|x_{0|t}\|)$. We will also have, for all $k \in \{0, \dots, N-2\}$,

$$|L(\hat{x}_k, v_{k+1}^*) - L(x_{k+1}^*, v_{k+1}^*)| \leq \sigma_L(\|\hat{x}_k - x_{k+1}^*\|).$$

Then, from (20) it follows that,

$$L(\hat{x}_{N-1}, 0) + \phi(\hat{x}_N, \theta_{t+1}) - \phi(\hat{x}_{N-1}, \theta_{t+1}) = 0.$$

Finally, recall that (20) is linear in $P(\theta)$ and note that its solution is unique for all $\theta \in \Theta_0$ (Theorem 3.7 [25] using that $\Phi(\theta)$ is stable). It follows then that $P(\theta)$ is Lipschitz continuous and that there will exist a \mathcal{K}_∞ -function κ_ϕ such that,

$$\begin{aligned} |\phi(\hat{x}_{N-1}, \theta_{t+1}) - \phi(x_N^*, \theta_t)| & \leq \sigma_\phi(\|\hat{x}_{N-1} - x_N^*\|) \\ & \quad + \kappa_\phi(\|\theta_t - \theta^*\|) + \kappa_\epsilon(\epsilon_t). \end{aligned}$$




Fig. 1. Average volume of $\text{Vol}(\Theta_t)$ for different values of δ . Results are averaged over 10 different runs (the small shadowed areas depicts 99.99% confidence interval).

We now group the above terms together to get,

$$\begin{aligned} V^*(x_{t+1}, \theta_{t+1}) - V^*(x_t, \theta_t) & \leq -\alpha_3(\|x_{0|t}\|) + \bar{\sigma}_w(\|w_t\|) \\ & \quad + \bar{\sigma}_\theta(\|\theta_t - \theta^*\|) + \bar{\kappa}_\epsilon(e_t) \end{aligned}$$

where $\bar{\sigma}_w, \bar{\sigma}_\theta$, and $\bar{\kappa}_\epsilon$ are \mathcal{K} -functions. Since $e_t \rightarrow 0$ as $t \rightarrow \infty$, we will have that condition (iii) is satisfied. \square

VI. NUMERICAL EXPERIMENTS

We illustrate the performance of STT-MPC on a second-order linear systems with true parameters

$$A = \begin{bmatrix} 0.6 & 0.2 \\ -0.1 & 0.4 \end{bmatrix}, \quad B = \begin{bmatrix} 1 \\ 0.6 \end{bmatrix}, \quad \sigma = 0.01, \quad (24)$$

where B is assumed to be known, while A is the uncertain parameter. The initial state is $x_0 = (6, 3)$, and we consider Θ_0 to be a 4-dimensional hypercube centered at $\theta_0 = [0.57 \ 0.17 \ -0.12 \ 0.42]$ with side length 0.14. Consequently, the resulting stabilizing feedback gain is $K = [-0.426 \ -0.290]$. The least-squares confidence region Δ_t is over-approximated by an hypercube centered in θ_t with side length $4\epsilon_t$. We consider the following state and input constraints: $[x_t]_1 \geq -0.15, [x_t]_2 \geq -1.1$ and $u_t \leq 0.5$. The matrix T is computed according to the relation (5.98) in [21], with $\lambda = 0.999$. We consider $Q = I_{d_x}, R = I_{d_u}$, and, for simplicity, we let the worst case noise realization be $\bar{w}_t = \bar{w}_0$, for all $t \geq 1$. All the simulations were performed in Python 3.9³, using the CVXPY library [26] and the MOSEK solver.

TABLE I
AVERAGE VOLUME OF $\text{VOL}(\Theta_t)$ WITH RESPECT TO $\text{VOL}(\Theta_0)$

Time step t	1	5	15	50	100
$\delta = 10^{-1}$	100%	1.312%	0.401%	0.071%	0.023%
$\delta = 10^{-2}$	100%	3.354%	0.827%	0.125%	0.038%
$\delta = 10^{-3}$	100%	7.058%	1.525%	0.205%	0.059%
$\delta = 10^{-4}$	100%	12.651%	2.593%	0.319%	0.088%

³Find the code here: <https://github.com/rssalessio/SelfTuningTubeBasedMPC>




Fig. 2. Illustration of the state trajectory using STT-MPC, and its tubes, over a single run. The gray areas depict the state constraints $[x_t]_1 \geq -0.15, [x_t]_2 \geq -1.1$. As a comparison, the plot of the state trajectory under $u_t = Kx_t$ is also shown.

Figure 1 shows the average volume of Θ_t over 10 different runs. We note that the reduction in volume is significant, and well below 1% of the volume of Θ_0 after 50 steps (see also the details in table VI; after 100 steps the volume is reduced below 0.1% of the original volume). In Figure 2 we present the trajectory of a single run of STT-MPC. In the plot are shown the tubes computed by the algorithm. We note that the constraints are robustly satisfied. Moreover, we also note a sensible reduction of the tubes over time.

VII. CONCLUSIONS

We proposed STT-MPC which combines least-squares estimation with a polytopic tube-based MPC method to ensure robust constraint satisfaction while learning the system dynamics. In contrast with existing conservative set-based identification approaches, we construct parameter sets that hold for all time with a confidence level δ chosen as a design parameter. Persistent excitation is ensured by injecting a truncated noise signal which decays at a rate $t^{-\alpha}$, with $\alpha > 0$ controlling the trade-off between (transient) estimation accuracy and controller performance. Importantly, we asymptotically recover the performance of the equivalent tube-based MPC that has full knowledge of the dynamics.

We analysed our proposed algorithm by deriving performance guarantees for the LSE, as well as by establishing recursive feasibility and input-to-state stability guarantees. We demonstrated the performance of our adaptation scheme, its dependence on δ , and the robust constraint satisfaction of STT-MPC via a numerical example.

Future work will focus on the analysis of the performance of our algorithm and quantifying the additional objective cost that must be paid for learning the dynamics. In particular, we will investigate whether a PE noise decaying as $1/\sqrt{t}$ could ensure a *regret* scaling at most as \sqrt{t} (as this was established in [7] for LQR problems).

REFERENCES

- [1] D. Q. Mayne, J. B. Rawlings, C. V. Rao, and P. O. Scokaert, "Constrained model predictive control: Stability and optimality," *Automatica*, vol. 36, no. 6, pp. 789–814, 2000.
- [2] D. Q. Mayne, M. M. Seron, and S. Raković, "Robust model predictive control of constrained linear systems with bounded disturbances," *Automatica*, vol. 41, no. 2, pp. 219–224, 2005.
- [3] D. Q. Mayne, "Model predictive control: Recent developments and future promise," *Automatica*, vol. 50, no. 12, pp. 2967–2986, 2014.
- [4] K. J. Åström and B. Wittenmark, "On self tuning regulators," *Automatica*, vol. 9, no. 2, pp. 185–199, 1973.
- [5] Y. Abbasi-Yadkori and C. Szepesvári, "Regret bounds for the adaptive control of linear quadratic systems," in *Proceedings of the 24th Annual Conference on Learning Theory*. JMLR Workshop and Conference Proceedings, 2011, pp. 1–26.
- [6] H. Mania, S. Tu, and B. Recht, "Certainty equivalence is efficient for linear quadratic control," *Advances in Neural Information Processing Systems*, vol. 32, 2019.
- [7] Y. Jedra and A. Proutiere, "Minimal expected regret in linear quadratic control," in *International Conference on Artificial Intelligence and Statistics*. PMLR, 2022, pp. 10234–10321.
- [8] J. Fleming, B. Kouvaritakis, and M. Cannon, "Robust tube mpc for linear systems with multiplicative uncertainty," *IEEE Transactions on Automatic Control*, vol. 60, no. 4, pp. 1087–1092, 2014.
- [9] K. S. Narendra and A. M. Annaswamy, "Persistent excitation in adaptive systems," *International Journal of Control*, vol. 45, no. 1, pp. 127–160, 1987.
- [10] D. Tranos, "Regret minimization in structured reinforcement learning," Ph.D. dissertation, KTH Royal Institute of Technology, 2021.
- [11] G. Marafioti, R. R. Bitmead, and M. Hovd, "Persistently exciting model predictive control," *International Journal of Adaptive Control and Signal Processing*, vol. 28, no. 6, pp. 536–552, 2014.
- [12] T. A. N. Heirung, B. Foss, and B. E. Ydstie, "Mpc-based dual control with online experiment design," *Journal of Process Control*, vol. 32, pp. 64–76, 2015.
- [13] T. A. N. Heirung, B. E. Ydstie, and B. Foss, "Dual adaptive model predictive control," *Automatica*, vol. 80, pp. 340–348, 2017.
- [14] Z. Cai and B. E. Ydstie, "Dual adaptive model predictive control with disturbances," *IFAC-PapersOnLine*, vol. 54, no. 3, pp. 206–211, 2021.
- [15] A. Aswani, H. Gonzalez, S. S. Sastry, and C. Tomlin, "Provably safe and robust learning-based model predictive control," *Automatica*, vol. 49, no. 5, pp. 1216–1226, 2013.
- [16] S. Di Cairano, "Indirect adaptive model predictive control for linear systems with polytopic uncertainty," in *2016 American Control Conference (ACC)*. IEEE, 2016, pp. 3570–3575.
- [17] M. Tanaskovic, L. Fagiano, R. Smith, and M. Morari, "Adaptive receding horizon control for constrained mimo systems," *Automatica*, vol. 50, no. 12, pp. 3019–3029, 2014.
- [18] M. Lorenzen, M. Cannon, and F. Allgöwer, "Robust mpc with recursive model update," *Automatica*, vol. 103, pp. 461–471, 2019.
- [19] S. V. Raković, B. Kouvaritakis, R. Findeisen, and M. Cannon, "Homothetic tube model predictive control," *Automatica*, vol. 48, no. 8, pp. 1631–1638, 2012.
- [20] X. Lu and M. Cannon, "Robust adaptive tube model predictive control," in *2019 American Control Conference (ACC)*. IEEE, 2019, pp. 3695–3701.
- [21] B. Kouvaritakis and M. Cannon, "Model predictive control," *Switzerland: Springer International Publishing*, vol. 38, 2016.
- [22] F. Blanchini and S. Miani, *Set-theoretic methods in control*. Springer, 2008, vol. 78.
- [23] D. Limon, T. Alamo, D. M. Raimondo, D. Pena, J. M. Bravo, A. Ferramosca, and E. F. Camacho, "Input-to-state stability: a unifying framework for robust model predictive control," in *Nonlinear model predictive control*. Springer, 2009, pp. 1–26.
- [24] A. Bemporad, M. Morari, V. Dua, and E. N. Pistikopoulos, "The explicit linear quadratic regulator for constrained systems," *Automatica*, vol. 38, no. 1, pp. 3–20, 2002.
- [25] H. K. Khalil, *Nonlinear control*. Pearson New York, 2015, vol. 406.
- [26] S. Diamond and S. Boyd, "Cvxpy: A python-embedded modeling language for convex optimization," *The Journal of Machine Learning Research*, vol. 17, no. 1, pp. 2909–2913, 2016.