

Timing and Synchronization of the DUNE Neutrino Detector

A.Barcock,^a D.Cussans,^{b,1} D. Lindebaum,^b D. Newbold,^a S.Parnesvaran,^a and S.Trilov^a

^a*STFC RAL, Didcot, UK*

^b*University of Bristol, UK*

E-mail: david.cussans@bristol.ac.uk

ABSTRACT: The DUNE neutrino experiment far detector has a fiducial mass of 40 kt. The O(1M) readout channels are distributed over the four 10kt modules and need to be synchronized with respect to each other to a precision of O(10 ns). The entire system needs to be synchronized with respect to GPS time to O(100 ns). The system needs to be reliable, simple and affordable. Clock and synchronization information encoded on the same fibre using a protocol based on duty cycle shift keying (DCSK) with 8b10b encoding to ensure DC-balance. The use of DCSK allows the clock to be recovered directly by PLL based clock generators without needing to use a separate clock and data recovery (CDR) device. Small scale tests show a timing jitter at the endpoint of ≈ 10 ps with respect to the timing master.

¹Corresponding author.

Contents

1	The DUNE Experiment	1
2	Protocol	1
2.1	Duty Cycle Shift Keying	1
2.2	Higher Level Protocol	2
3	Laboratory Tests	2
4	Implementation at DUNE	2
5	Summary	4

1 The DUNE Experiment

The Deep Underground Neutrino Experiment (DUNE) [1, 2] will detect neutrinos generated 1300 km away in Fermilab, near Chicago. The far detector will consist of four modules, each with 10 kt fiducial mass of liquid Argon, located 1.5 km underground at the Sanford Underground Research Facility (SURF).

The energy deposited by the products of neutrino interactions will be detected in two ways: ionization drifted by an applied electric field to pick-up electrodes, forming a time projection chamber (TPC), and scintillation light.

In order to reconstruct events with the photon detection system readout channels must be synchronized to each other with a precision of nanoseconds. To correlate events in the far detector with neutrino generation at Fermilab the entire detector must be synchronized to GPS time to a precision of O(100 ns).

2 Protocol

2.1 Duty Cycle Shift Keying

Earlier prototypes of the DUNE timing system [3] used non-return-to-zero encoding and ADN2814 CDR ASICs [4] to recover the clock. However, due to a potentially long term shortage of the ADN2814, the system was redesigned to use Duty Cycle Shift Keying (DCSK) [5] which allows the clock to be recovered directly by a PLL based clock generator. It is also possible to recover the clock using the clock generation modules inside Xilinx FPGAs. Data are transmitted at 62.5 Mbit/s with “0” represented by a 25% duty cycle and “1” by a 75% duty cycle. 8b/10b [6] encoding is used to ensure DC-balance. Figure 1 illustrates the values “0”, “1” and “Z” encoded with DCSK. Figure 2 illustrates an 8b/10b control character using DCSK.




Figure 1. Illustration of Duty Cycle Shift Keying (DCSK) showing the representation of '0', '1' and 'Z' values.




Figure 2. Example of 8b10b Encoded DCSK Data.

2.2 Higher Level Protocol

A continuous stream of encoded serial data is transmitted over a 1000Base-Bx [7] optical link from the timing master to timing “end points”. The data carries commands that are used to synchronize a 64-bit time-stamp counter in the end-point and propagate commands and synchronization messages. This allows the readout clocks, calibration signals, etc. to be synchronized throughout each module.

Each link from the timing master is bidirectional with data transmitted in both directions down a single fibre with different light wavelengths. Normally, data are only transmitted from the timing master to the endpoints. However, the data can be echoed by the end points and transmitted back to the timing master. This allows the timing master to measure the latency between timing master and end point and adjust the clock phase and time-stamp at the end point. This allows all end points to operate with the same time-stamp and clock phase. For links where a single fibre from the timing master is passively split to many end points only one end point at a time can transmit back to the timing master. In addition to measuring round trip delay to an endpoint the timing master can read out the status of the end points.

3 Laboratory Tests

Timing jitter performance was measured in the laboratory by connecting a prototype timing master with a prototype endpoint by optical fibre. The clock signals in the master and endpoint were compared. Timing jitter depends on the bandwidth programmed into the PLL clock generators used but is typically in the region of 10 ps. A block diagram of the apparatus used to test cycle-to-cycle timing jitter is shown in figure 3. The distribution of the time difference between clock edges at the timing master and timing endpoint is shown in figure 4. In other tests over 100 endpoints were synchronized.

4 Implementation at DUNE

The DUNE timing system is made of a mix of commercially available and custom components. At the top of each access shaft a GPS-disciplined oscillator provides timing information to a custom GPS Interface Module (GIB). Fibres from each GIB are connected to MicroTCA Interface Boards (MIBs), a custom AMC. They sit in one of the two crate controller slots of MicroTCA crates located




Figure 3. Block diagram of jitter performance test setup.




Figure 4. Distribution of time difference between clock edges at timing master and endpoint.

on each detector module. Timing signals are distributed over the backplane to commercial AMC boards [8]. Each AMC carries a fibre interface board (FIB). Each FIB has eight fibres, transmitting and receiving timing data to the detector readout electronics. Figure 5 illustrates the overall layout of the DUNE timing system. Photograph 6 shows a FIB mounted onto an AFC.

The ability of the DUNE timing system protocol to be used with passive optical splitting and combining will be used to provide hot-swap redundancy to the system. The two completely independent master timing systems will allow firmware and software updates without interrupting system running. Two independent antennae will be used: One at the top each of the two access shafts to SURF. This, together with a rubidium atomic clock in the master timing system will enable failure of the link to GPS time to be detected. The two completely independent master timing systems will also allow firmware and software updates without interrupting system running.




Figure 5. Schematic view of the DUNE timing system.

5 Summary

The DUNE timing system will provide nano-second precision synchronization of several hundred readout units distributed over a physically large detector. Laboratory tests indicate that the system will meet its specification comfortably. The novel use of Duty Cycle Shift Keying allows a clock to be recovered from a serial data stream without the use of a specialized clock and data recovery device. The use of passive optical splitting allows each fibre from the timing system to drive multiple endpoints while simultaneously allowing for a redundant system. Two GPS disciplined oscillators will be used to cross check each other and improve reliability.

References

- [1] B. Abi, R. Acciarri, M. Acero, G. Adamov, D. Adams, M. Adinolfi et al., *Volume I. introduction to DUNE*, *Journal of Instrumentation* **15** (2020) T08008.
- [2] B. Abi, R. Acciarri, M. Acero, G. Adamov, D. Adams, M. Adinolfi et al., *Volume IV. the DUNE far detector single-phase technology*, *Journal of Instrumentation* **15** (2020) T08010.
- [3] D. Cussans, *Timing and synchronization of the dune neutrino detector*, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment* **958** (2020) 162143.




Figure 6. Photograph of a DUNE timing system Fibre Interface Board mounted on a commercial FPGA based AMC.

- [4] “Analog devices inc. adn2814: *Continuous rate 10 Mb/s to 675 Mb/s clock and data recovery IC with integrated limiting amp.*”
<http://www.analog.com/static/imported-files/datasheets/ADN2814.pdf>.
- [5] S.A. Mirbozorgi, G. Nabovati and M. Maymandi-Nejad, *Duty cycle shift keying data transfer technique for bio-implantable devices*, in *2011 IEEE International Symposium of Circuits and Systems (ISCAS)*, pp. 917–920, 2011.
- [6] A.X. Widmer and P.A. Franaszek, *A DC-balanced, partitioned-block, 8b/10b transmission code*, *IBM Journal of Research and Development*. **27** (1983) 440.
- [7] “802.3-2018 - IEEE standard for ethernet.” 10.1109/IEEESTD.2018.8457469.
- [8] “Amc fmc carrier afc.” <https://ohwr.org/project/afc>.