

SPACE-TIME ADAPTIVE PROCESSING FOR RADARS IN CONNECTED AND AUTOMATED VEHICULAR PLATOONS

Zahra Esmaeilbeig^{*}, Kumar Vijay Mishra[†], and Mojtaba Soltanalian^{*}

^{*}ECE Department, University of Illinois Chicago, USA

[†]United States DEVCOM Army Research Laboratory, USA

ABSTRACT

In this study, we develop a holistic framework for space-time adaptive processing (STAP) in connected and automated vehicle (CAV) radar systems. We investigate a CAV system consisting of multiple vehicles that transmit frequency-modulated continuous-waveforms (FMCW), thereby functioning as a multistatic radar. Direct application of STAP in a network of radar systems such as in a CAV may lead to excess interference. We exploit time division multiplexing (TDM) to perform transmitter scheduling over FMCW pulses to achieve high detection performance. The TDM design problem is formulated as a quadratic assignment problem which is tackled by power method-like iterations and applying the Hungarian algorithm for linear assignment in each iteration. Numerical experiments confirm that the optimized TDM is successful in enhancing the target detection performance.

Index Terms— Advanced driver assistance systems, connected and automated vehicle systems, FMCW automotive radar multistatic radar, Munkres assignment algorithm, power method-like iterations quadratic assignment problem, transmitter scheduling.

1. INTRODUCTION

Recent innovations in connected and automated vehicle (CAV) systems provide new opportunities to enable better sensing of the environment. CAVs offer advanced collision avoidance through onboard sensor technologies like radar, cameras, and lidar [1]. Platooning in the CAV systems is when vehicles travel in groups with very short inter-vehicle spacing. The connectivity among the vehicles in a platoon enables a CAV to receive information from surrounding vehicles and infrastructure [2]. In this regard, a network of automotive radar systems assisting each other in sensing the environment is enabled. Whilst a single vehicle radar may suffer from obstruction, fading, or lack of radial velocity component of the target with respect to the radar, it is unlikely that this will be the case with multi-vehicle systems with different transmitter-target-receiver paths, also known as networked radar in the literature [3, 4].

In this study, we aim to leverage the cooperative capabilities of transportation systems—specifically, vehicle-to-vehicle (V2V) and vehicle-to-infrastructure (V2I) communications—to develop a distributed space-time adaptive processing (STAP) scheme for radars in a CAV. Each vehicle is assumed to travel at a speed and in a direction

This work was sponsored in part by the National Science Foundation Grant ECCS-1809225, and in part by the Army Research Office, accomplished under Grant Number W911NF-22-1-0263. The views and conclusions contained in this document are those of the authors and should not be interpreted as representing the official policies, either expressed or implied, of the Army Research Office or the U.S. Government. The U.S. Government is authorized to reproduce and distribute reprints for Government purposes notwithstanding any copyright notation herein.

that can be different from those of the other vehicles. However, the properties of the environment, positioning and velocity information of the vehicles in the platoon are assumed to be accessible at each vehicle through V2V communication, therefore making a cooperative STAP scheme feasible. We formulate the cooperative STAP as a decentralized multistatic target detection problem [5].

Direct application of STAP can reduce target detection performance because of high sidelobes and susceptibility to interference [6–12]. On the transmitter side, the interference can be addressed by transmitting well-designed radar signals that are nearly orthogonal to each other in the spectral or temporal domains [13]. In order to enhance robustness against interference, we propose a time division multiplexing (TDM) framework in which among all the transmitters in the CAV, only one is scheduled to transmit during each pulse. In other words, we assume that frequency-modulated continuous-waveforms (FMCW) signals with similar properties but with active or silent chirps are generated. We consider an extended version of the transmitter scheduling framework proposed by [7] and demonstrate that the transmitter scheduling problem is a quadratic assignment problem (QAP) and address it by means of power method-like iterations. At each iteration the problem is boiled down to a linear assignment problem which is efficiently solved by the Hungarian algorithm [14].

The rest of this paper is organized as follows. In the next section, we introduce the system model for the cooperative STAP in CAVs. In Section 3, we formulate the design problem for obtaining the optimal TDM in our system. Section 4 presents our approach based on the Hungarian algorithm to optimize the TDM matrix. We evaluate our methods via numerical experiments in Section 5 and conclude the paper in Section 6.

Notation: Throughout this paper, we use bold lowercase and bold uppercase letters for vectors and matrices, respectively. The (m, n) -th element of the matrix \mathbf{A} is \mathbf{A}_{mn} . The sets of complex and real numbers are \mathbb{C} and \mathbb{R} , respectively; $(\cdot)^\top$, $(\cdot)^*$ and $(\cdot)^H$ are the vector/matrix transpose, conjugate, and Hermitian transpose, respectively. The trace of a matrix is $\text{Tr}(\cdot)$; the function $\text{diag}(\cdot)$ returns the diagonal elements of the input matrix; and $\text{Diag}(\cdot)$ and $\text{Blkdiag}(\cdot)$ produce a diagonal/block-diagonal matrix with the same diagonal entries/blocks as their vector/matrices argument. The minimum eigenvalue of \mathbf{A} is denoted by $\lambda_{\min}(\mathbf{A})$. The Hadamard (element-wise) and Kronecker products are \odot and \otimes , respectively. l_2 -norm of \mathbf{a} and Frobenius norm of \mathbf{A} is denoted by $\|\mathbf{a}\|_2$ and $\|\mathbf{A}\|_F$, respectively. $\text{vec}_{M,N}^{-1}(\mathbf{a})$ reshapes the input vector $\mathbf{a} \in \mathbb{C}^{MN \times 1}$ into a matrix $\mathbf{A} \in \mathbb{C}^{M \times N}$ such that $\text{vec}(\mathbf{A}) = \mathbf{a}$.

2. SYSTEM MODEL

We consider a network of K cooperative vehicles, each equipped with radars that have N transmit antennas and M receive antennas

arranged as a uniform linear array (ULA). Each vehicle transmits L FMCW chirps during the CPI time of T , with similar bandwidth B and chirp time T_c . The transmit waveform at l -th pulse of one transmitter antenna is

$$s(t, l) = \text{rect}\left(\frac{t - lT_c}{T}\right) e^{j2\pi[f_c + \frac{B}{T}(t - lT_c)](t - lT_c)}. \quad (1)$$

We denote the position of the n -th transmitter on vehicle k by $\mathbf{p}_{T,kn} \in \mathbb{R}^{2 \times 1}$ and the position of m -th receiver on vehicle i by $\mathbf{p}_{R,im} \in \mathbb{R}^{2 \times 1}$. We further assume that the target at position $\mathbf{p}_t \in \mathbb{R}^{2 \times 1}$ is moving with a velocity $\mathbf{v}_t \in \mathbb{R}^{2 \times 1}$. The Doppler velocity of the target with respect to vehicle k is

$$\nu_k = \mathbf{v}_t^\top \mathbf{p}_{tk}, \quad (2)$$

where $\mathbf{p}_{tk} = [\sin \theta_{tk}, \cos \theta_{tk}]^\top$ is the direction vector of the target with DoA θ_{tk} with respect to vehicle k .

The range from the n -th transmitter on vehicle k to the target is

$$R_k(t, l, n) = \|\mathbf{p}_t - \mathbf{p}_{R,im}\|_2 + \nu_k(t + (n-1) + (l-1)N)T_c, \quad (3)$$

and range from target to the m -th Rx on vehicle i is

$$R_i(t, l, m) = \|\mathbf{p}_t - \mathbf{p}_{R,im}\|_2 + \nu_i(t + (m-1) + (l-1)M)T_c. \quad (4)$$

Consequently, the delay introduced from the n -th transmitter on vehicle k into the signal received at the m -th receiver on vehicle i is

$$\tau_{ki} = \frac{R_k(t, l, n) + R_i(t, l, m)}{c}, \quad (5)$$

where c is the speed of light.

We assume that each pair of vehicles $i, k \in \{1, \dots, K\}$ is connected via V2V communication links. In automotive radar, the signal processing flow sequentially comprises of sampling, range estimation, Doppler processing, and DoA estimation. In STAP, after range processing the Doppler and DoA are processed simultaneously by means of 2D adaptive matched filters [5, 16]. Therefore, after sampling the signal backscattered from the target i.e. $s(t - \tau_{ki}, l)$ and estimating the range, the received signal at the designated range bin at the m -th Rx on vehicle i from the n -th Tx on vehicle k is

$$s_{ki}(l, n, m) = \alpha_k e^{-j\frac{2\pi f_c}{c} \nu_k ((l-1)N + (n-1)T_c)} e^{-j\frac{2\pi f_c}{c} \nu_i ((l-1)M + (m-1)T_c)} e^{j2\pi f_c (\mathbf{p}_{T,kn}^\top \mathbf{p}_{tk})} e^{j2\pi f_c (\mathbf{p}_{R,im}^\top \mathbf{p}_{ti})}, \quad (6)$$

where the delay in (5) is expanded with respect to the first element of ULA in a similar manner as in [7] and α_k is the complex target reflection factor. We introduce the Doppler steering vector as

$$\mathbf{a}_{d,N}(\nu) = \left[1, e^{-j\frac{2\pi f_c \nu}{c} NT_c}, \dots, e^{-j\frac{2\pi f_c \nu}{c} (L-1)NT_c}\right]^\top, \quad (7)$$

and the auxiliary Doppler steering vector as

$$\mathbf{a}_{D,M}(\nu) = \left[1, e^{-j\frac{2\pi f_c \nu}{c} T_c}, \dots, e^{-j\frac{2\pi f_c \nu}{c} (M-1)T_c}\right]^\top. \quad (8)$$

The transmit array steering vector at vehicle k is

$$\mathbf{a}_{T,k}(\theta) = \left[e^{j2\pi f_c (\mathbf{p}_{T,k1}^\top \mathbf{p}_{tk})}, \dots, e^{j2\pi f_c (\mathbf{p}_{T,kN}^\top \mathbf{p}_{tk})}\right]^\top, \quad (9)$$



Fig. 1. A simplified illustration of a CAV platoon consisting of three vehicles, sensing a target in the FoV of all three vehicles. The radar on vehicle 1, denoted by RX/TX1, leads the platoon and is assisted by two other radars, denoted by TX2 and TX3.

and the receive array steering vector at vehicle i is

$$\mathbf{a}_{R,i}(\theta) = \left[e^{j2\pi f_c (\mathbf{p}_{R,i1}^\top \mathbf{p}_{ti})}, \dots, e^{j2\pi f_c (\mathbf{p}_{R,iM}^\top \mathbf{p}_{ti})}\right]^\top. \quad (10)$$

The snapshot signal received at vehicle i from n -th Tx on vehicle k is

$$\mathbf{s}_{ki}(n) = [\mathbf{a}_{d,N}(\nu_k) \odot \mathbf{a}_{d,M}(\nu_i)] \otimes [\mathbf{a}_{R,i}(\theta) \odot \mathbf{a}_{D,M}(\nu_i)] \in \mathbb{C}^{LM \times 1}. \quad (11)$$

By stacking the echoes from all N Tx on vehicle k , we obtain

$$\mathbf{s}_{ki} = \begin{bmatrix} \mathbf{s}_{ki}(1) \\ \vdots \\ \mathbf{s}_{ki}(N) \end{bmatrix} = (\mathbf{a}_{T,k}(\theta) \odot \mathbf{a}_{D,N}(\nu_k)) \otimes \left((\mathbf{a}_{d,N}(\nu_k) \odot \mathbf{a}_{d,M}(\nu_i)) \otimes (\mathbf{a}_{R,i}(\theta) \odot \mathbf{a}_{D,M}(\nu_i)) \right) \in \mathbb{C}^{NLM \times 1}. \quad (12)$$

As illustrated in Fig. 1, we focus on a scenario wherein vehicle i , serving as the lead in the platoon, receives assistance from all other vehicles for its sensing task. The target is in the field of view (FoV) of all vehicles and therefore the whole CAV can perform as a multi-tatic radar to sense it. To be succinct, hereafter we remove the subscript i i.e. without loss of generality \mathbf{s}_{ki} will be replaced by \mathbf{s}_k . In order to decide whether a target is present in a particular known range-cell, we perform binary hypothesis testing between \mathcal{H}_0 (target-free hypothesis) and \mathcal{H}_1 (target-present hypothesis), i.e.,

$$\begin{aligned} \mathcal{H}_0 &: \mathbf{y}_k = \mathbf{n}_k \\ \mathcal{H}_1 &: \mathbf{y}_k = \alpha_k \mathbf{s}_k + \mathbf{n}_k, \end{aligned} \quad (13)$$

where α_k is the complex target reflectivity factor and \mathbf{n}_k is the noise and interference with covariance \mathbf{R}_k [17]. The log-likelihood ratio test statistic is given by [5],

$$\zeta = \sum_{k=1}^K \frac{|\mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{y}_k|^2}{\frac{|\alpha_k|^2}{2} + \mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{s}_k} \underset{\mathcal{H}_0}{\overset{\mathcal{H}_1}{\gtrless}} \gamma. \quad (14)$$

Since $|\mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{y}_k|$ is the magnitude of a complex Gaussian random variable, the test statistic in (14) is a sum of K exponential random variables and therefore follows a hypo-exponential distribution [18].

Under \mathcal{H}_1 , we have

$$\mathbb{E}\{\zeta|\mathcal{H}_1\} = \sum_{k=1}^K \frac{\mathbf{C}_k + 2|\alpha_k|^2 \mathbf{C}_k^2}{\frac{|\alpha_k|^2}{2} + \mathbf{C}_k}, \quad (15)$$

where $\mathbf{C}_k = \mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{s}_k$. The probability of detection and false alarm are obtained respectively as

$$\begin{aligned} P_D &= \mathbb{P}\{\zeta > \gamma|\mathcal{H}_1\} = 1 - \mathbb{P}\{\zeta \leq \gamma|\mathcal{H}_1\} = 1 - F_{\zeta|\mathcal{H}_1}(\gamma|\mathcal{H}_1), \\ P_{FA} &= \mathbb{P}\{\zeta > \gamma|\mathcal{H}_0\} = 1 - \mathbb{P}\{\zeta \leq \gamma|\mathcal{H}_0\} = 1 - F_{\zeta|\mathcal{H}_0}(\gamma|\mathcal{H}_0), \end{aligned} \quad (16)$$

where $F_{\zeta|\mathcal{H}}(\cdot)$ is the cumulative distribution function of the test statistic with hypo-exponential distribution. By carefully observing (14), one can verify that the weighting $(\frac{|\alpha_k|^2}{2} + \mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{s}_k)^{-1}$ accounts for the contribution of vehicle k in the test statistic. If $\mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{s}_k \ll \frac{|\alpha_k|^2}{2}$ then we can interpret it as the signal propagated from vehicle k not reaching the receiver. Therefore, for the sake of interpretation here we assume $\mathbf{s}_k^H \mathbf{R}_k^{-1} \mathbf{s}_k \gg \frac{|\alpha_k|^2}{2}$ for all vehicles i.e. $k \in \{1, \dots, K\}$. Under this condition, (15) is

$$\mathbb{E}\{\zeta|\mathcal{H}_1\} = \sum_{k=1}^K 1 + 2|\alpha_k|^2 \mathbf{C}_k \quad (17)$$

The signal received at vehicle i from all vehicles, i.e., $k \in \{1, \dots, K\}$, is thus given by $\mathbf{s} = [\mathbf{s}_1, \dots, \mathbf{s}_K]^T \in \mathbb{C}^{KNLM}$, where \mathbf{s} is also equivalent to the 2D space-time steering vector of the target as observed at vehicle i .

3. TDM DESIGN

Since multiple signals share the same communication channel, the transmitted signals need to be orthogonal to be distinguishable at the receiver. For this matter in a CPI the antennas need to take turns to transmit. We propose to incorporate TDM by designing a transmitter scheduling matrix for the platoon of vehicles. In this particular TDM scheme, at most one antenna within the platoon is allowed to transmit during each pulse. We reformulate the steering vectors under the TDM scheme. If \mathbf{e}_{kn} is a one-hot vector of size $L \times 1$ with only one element as unity and remaining elements zero, then under TDM, (11) is

$$\mathbf{s}_{ki}(n) = [\mathbf{e}_{kn} \odot \mathbf{a}_{d,N}(\nu_k) \odot \mathbf{a}_{d,M}(\nu_i)] \otimes [\mathbf{a}_{R,i}(\theta) \odot \mathbf{a}_{D,M}(\nu_i)], \quad (18)$$

where the unity element in \mathbf{e}_{kn} , indicates the pulse at which the transmitter antenna n on vehicle k transmits. Let $\mathbf{J}_k = [\mathbf{e}_{k1} | \dots | \mathbf{e}_{kN}] \in \{0, 1\}^{L \times N}$. Following the same procedure leading to (12), we have

$$\begin{aligned} \bar{\mathbf{s}}_k &= (\text{vec}(\mathbf{J}_k) \otimes \mathbf{1}) \odot \left((\mathbf{a}_{T,k}(\theta) \odot \mathbf{a}_{D,N}(\nu_k)) \otimes \right. \\ &\quad \left. (\mathbf{a}_{d,N}(\nu_k) \odot \mathbf{a}_{d,M}(\nu_i)) \otimes (\mathbf{a}_{R,i}(\theta) \odot \mathbf{a}_{D,M}(\nu_i)) \right) \\ &= (\text{vec}(\mathbf{J}_k) \otimes \mathbf{1}) \odot \mathbf{s}_k \end{aligned} \quad (19)$$

After performing TDM the received signal $\bar{\mathbf{s}} = [\bar{\mathbf{s}}_1, \dots, \bar{\mathbf{s}}_K]^T$ is

$$\begin{aligned} \bar{\mathbf{s}} &= \begin{bmatrix} (\text{vec}(\mathbf{J}_1) \otimes \mathbf{1}) \odot \mathbf{s}_1 \\ \vdots \\ (\text{vec}(\mathbf{J}_K) \otimes \mathbf{1}) \odot \mathbf{s}_K \end{bmatrix} = (\text{vec}([\mathbf{J}_1 | \dots | \mathbf{J}_K]) \otimes \mathbf{1}_M) \odot \mathbf{s} \\ &= (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M) \odot \mathbf{s} \in \mathbb{C}^{KNLM \times 1}, \end{aligned} \quad (20)$$

where $\mathbf{J} = [\mathbf{J}_1 | \dots | \mathbf{J}_K] \in \{0, 1\}^{L \times KN}$ is the waveform selection matrix. Without loss of generality, we design a TDM scheme in which the antennas in the whole platoon take turns over the pulses to transmit. Under this scheme for a CPI of length $L = KN$, each antenna selected to transmit at pulse l , prevents all other antennas from transmitting. As a consequence, the waveform selection matrix \mathbf{J} is a permutation matrix of size $L \times L$. We intend to maximize the target detection performance. We use the mean of the test statistic as the design criteria. Consequently the TDM design problem is

$$\begin{aligned} \mathcal{P}_1 : \text{maximize} \quad & \mathbb{E}\{\zeta|\mathcal{H}_1\} \\ \text{subject to} \quad & \sum_p \mathbf{J}_{pn} = 1, \quad p, n \in \{1, \dots, L\}; \\ & \sum_n \mathbf{J}_{pn} = 1; \\ & \mathbf{J}_{pn} \in \{0, 1\}. \end{aligned} \quad (21)$$

4. SOLUTION METHODOLOGY

In this section, we first demonstrate that \mathcal{P}_1 is a QAP [19] which is a combinatorial optimization problem that is NP-hard in general form. Consequently, we introduce a computationally efficient procedure to obtain a local optimum of QAP. Our proposed method takes advantage of the power method-like iterations introduced in [20], which resembles the well-known power method for computing the dominant eigenvalue and vector pairs of matrices.

We accumulate the interference covariance matrices in \mathbf{R} such that $\mathbf{R} = \text{Blkdiag}(\mathbf{R}_1, \dots, \mathbf{R}_K)$. By substituting (20) in (17) we obtain

$$\begin{aligned} \mathbb{E}\{\zeta|\mathcal{H}_1\} &= \bar{\mathbf{s}}^H \mathbf{R}^{-1} \bar{\mathbf{s}} \\ &= \left((\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M) \odot \mathbf{s} \right)^H \mathbf{R}^{-1} \left((\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M) \odot \mathbf{s} \right) \\ &= (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M)^H \text{Diag}(\mathbf{s})^H \mathbf{R}^{-1} \text{Diag}(\mathbf{s}) (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M) \\ &= \text{Tr} \left((\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M)^H \mathbf{Q} (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M) \right) \\ &= (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M)^H \text{vec}(\mathbf{Q} (\text{vec}(\mathbf{J}) \otimes \mathbf{1}_M)) \\ &= \text{vec}(\mathbf{J})^H \mathbf{G}^H \mathbf{Q} \mathbf{G} \text{vec}(\mathbf{J}) \end{aligned} \quad (22)$$

where

$$\mathbf{Q} = \text{Diag}(\mathbf{s})^H \mathbf{R}^{-1} \text{Diag}(\mathbf{s}) \quad (23)$$

$$\mathbf{G} = (\mathbf{K}_{1,KNL} \otimes \mathbf{I}_M) (\mathbf{I}_{KNL} \otimes \mathbf{1}_M) \quad (24)$$

and $\mathbf{K}_{1,KNL}$ is the commutation matrix satisfying

$$\mathbf{K}_{1,KNL} \text{vec}(\mathbf{J}) = \text{vec}(\mathbf{J}^T). \quad (25)$$

The above algebraic manipulations cast \mathcal{P}_1 equivalent to a QAP as

$$\mathcal{P}_2 : \text{maximize}_{\mathbf{J} \in \Omega} \text{vec}(\mathbf{J})^H \mathbf{S} \text{vec}(\mathbf{J}), \quad (26)$$

where $\mathbf{S} = \mathbf{G}^H \mathbf{Q} \mathbf{G}$ and Ω is the set of permutation matrices i.e.

$$\begin{aligned} \Omega = \left\{ \mathbf{J} \mid \sum_p \mathbf{J}_{pn} = 1, \quad \sum_n \mathbf{J}_{pn} = 1, \right. \\ \left. \mathbf{J}_{pn} \in \{0, 1\}, \quad p, n \in \{1, \dots, L\} \right\}. \end{aligned} \quad (27)$$

Algorithm 1 Power method-like iterations for transmitter scheduling in CAVs.

1: **Input** The overall steering vector of the CAV $\bar{\mathbf{s}}$
2: **Initialization** $\mathbf{J}^{(0)} \in \Omega$, $s = 0$
3: $\bar{\mathbf{S}} = \lambda_m \mathbf{I} - \mathbf{S}$
4: **While** $\left| \left[f(\mathbf{J}^{(s+1)}) - f(\mathbf{J}^{(s)}) \right] / f(\mathbf{J}^{(s)}) \right| \geq \epsilon$ **do**
5: $\mathbf{C}^{(s)} = -\text{vec}_{L,L}^{-1} \left(\bar{\mathbf{S}} \text{vec} \left(\mathbf{J}^{(s)} \right) \right)$
6: $\mathbf{J}^{(s+1)} \leftarrow \text{Hungarian}(\mathbf{C}^{(s)\text{H}})$
7: $s \leftarrow s + 1$
8: $\mathbf{J}_{\text{opt}} \leftarrow \mathbf{J}^{(s)}$
9: **Output** \mathbf{J}_{opt}

By performing diagonal loading, i.e., substituting \mathbf{S} with positive semi-definite matrix $\bar{\mathbf{S}} = \lambda_m \mathbf{I} + \mathbf{S}$, with $\lambda_m \geq -\lambda_{\min}(\mathbf{S})$, \mathcal{P}_2 will be turned into the equivalent maximization problem:

$$\mathcal{P}_3 : \underset{\mathbf{J} \in \Omega}{\text{maximize}} \quad \text{vec}(\mathbf{J})^H \bar{\mathbf{S}} \text{vec}(\mathbf{J}). \quad (28)$$

One can locally optimize \mathcal{P}_3 by resorting to *power method-like* iterations of the form [20, 21]:

$$\begin{aligned} \mathcal{P}_4 : \underset{\mathbf{J}^{(s+1)} \in \Omega}{\text{minimize}} \quad & \left\| \text{vec} \left(\mathbf{J}^{(s+1)} \right) - \bar{\mathbf{S}} \text{vec} \left(\mathbf{J}^{(s)} \right) \right\|_2 \\ \equiv \underset{\mathbf{J}^{(s+1)} \in \Omega}{\text{minimize}} \quad & \left\| \mathbf{J}^{(s+1)} - \text{vec}_{L,L}^{-1} \left(\bar{\mathbf{S}} \text{vec} \left(\mathbf{J}^{(s)} \right) \right) \right\|_F. \end{aligned} \quad (29)$$

We define the matrix $\mathbf{C}^{(s)} = -\text{vec}_{L,L}^{-1} \left(\bar{\mathbf{S}} \text{vec} \left(\mathbf{J}^{(s)} \right) \right)$. It is straightforward to see

$$\begin{aligned} \left\| \mathbf{J}^{(s+1)} + \mathbf{C}^{(s)} \right\|_F^2 &= \text{Tr} \left(\left(\mathbf{J}^{(s+1)} + \mathbf{C}^{(s)} \right)^H \left(\mathbf{J}^{(s+1)} + \mathbf{C}^{(s)} \right) \right) \\ &= \text{Tr} \left(\mathbf{I} + \mathbf{C}^{(s)\text{H}} \mathbf{C}^{(s)} \right) + \text{Tr} \left(\mathbf{C}^{(s)\text{H}} \mathbf{J}^{(s+1)} + \mathbf{J}^{(s+1)\text{H}} \mathbf{C}^{(s)} \right) \\ &= \text{Tr} \left(\mathbf{I} + \mathbf{C}^{(s)\text{H}} \mathbf{C}^{(s)} \right) + 2\text{Tr} \left(\mathbf{J}^{(s+1)} \mathbf{C}^{(s)\text{H}} \right), \end{aligned} \quad (30)$$

where we used the orthogonality property of permutation matrices i.e. $\mathbf{J}^{(s+1)\text{H}} \mathbf{J}^{(s+1)} = \mathbf{I}$ in the second equality. Consequently, \mathcal{P}_4 is equivalent to

$$\mathcal{P}_5 : \underset{\mathbf{J}^{(s+1)} \in \Omega}{\text{minimize}} \quad \text{Tr} \left(\mathbf{J}^{(s+1)} \mathbf{C}^{(s)\text{H}} \right). \quad (31)$$

Note that the above problem is in fact a *linear assignment problem* with cost matrix $\mathbf{C}^{(s)\text{H}}$ that can be solved efficiently using the *Hungarian algorithm* also known as *Munkres assignment algorithm*, with computational complexity of $\mathcal{O}(L^2)$ [14]. Our final proposed algorithm for transmitter scheduling in CAVs based on power method-like iterations is presented in Algorithm 1. As shown in [20], the objective $f(\mathbf{J}) = \text{vec}(\mathbf{J})^H \bar{\mathbf{S}} \text{vec}(\mathbf{J})$ is increasing through the power method-like iterations and convergent in the sense of the objective value. Consequently, we set the stopping criteria $\left| \left[f(\mathbf{J}^{(s+1)}) - f(\mathbf{J}^{(s)}) \right] / f(\mathbf{J}^{(s)}) \right| < \epsilon$ for the algorithm.

5. NUMERICAL EXPERIMENTS

We carried out numerical experimentation to evaluate the performance of the proposed algorithm for TDM in CAVs. We considered a platoon consisting of $K = 3$ vehicles, each equipped with $M = N = 8$ Tx and Rx antennas arranged as ULA. All vehicles are assumed to have FMCW radar systems operating at carrier frequency




Fig. 2. RoC of detection for a CAV of FMCW radars. The optimized TDM is compared with uniform transmission where the antennas are activated uniformly in a sequence.

$f_c = 77$ GHz, bandwidth $B = 150$ MHz and chirp time $T_c = 8 \mu\text{s}$. The vehicles are moving with 2D velocities $\mathbf{v}_1 = [20, 20]$ m/s, $\mathbf{v}_2 = [-10, -20]$ m/s and $\mathbf{v}_3 = [30, 15]$ m/s. Algorithm 1 is performed to design the TDM for a CPI of length $L = 24$ pulses. The receiver operating characteristics (RoC) associated with the described CAV when one, two or three of the vehicles are cooperating and transmitting with optimized TDM is illustrated in Fig. 2. The results demonstrate significant improvement in comparison with sequential transmission where the transmitters on each vehicle are activated by the order of their indices $\{1, 2, \dots, N\}$, equivalent to an identity TDM matrix.

6. SUMMARY

Vehicle-to-vehicle communication is a fundamental capability that enables CAVs to perform distributed STAP. A cooperative STAP scheme for the vehicles in a CAV platoon was within the purview of this paper. Furthermore, we introduced a TDM scheme for orthogonal transmission of the antennas in the CAV platoon. The transmitter scheduling was formulated as a quadratic assignment problem. By means of the well-known power method-like iterations we showed that the TDM design problem can be reduced to a linear assignment problem in each iteration and consequently the efficient Hungarian algorithm can effectively address it. Through numerical simulations, we confirmed the efficacy of the suggested TDM approach in enhancing target detection performance.

7. REFERENCES

- [1] A. Sarker, H. Shen, M. Rahman, M. Chowdhury, K. Dey, F. Li, Y. Wang, and H. S. Narman, "A review of sensing and communication, human factors, and controller aspects for information-aware connected and automated vehicles," *IEEE Transactions on Intelligent Transportation Systems*, vol. 21, no. 1, pp. 7–29, 2020.
- [2] Y. Wang, R. Zhang, N. Masoud, and H. X. Liu, "Anomaly detection and string stability analysis in connected automated ve-

- hicular platoons,” *Transportation research part C: emerging technologies*, vol. 151, p. 104114, 2023.
- [3] H. Griffiths, “Multistatic, MIMO and networked radar: The future of radar sensors?” pp. 81–84, 2010.
- [4] H. Zhang, W. Liu, J. Shi, T. Fei, and B. Zong, “Joint detection threshold optimization and illumination time allocation strategy for cognitive tracking in a networked radar system,” *IEEE Transactions on Signal Processing*, vol. 70, pp. 5833–5847, 2022.
- [5] N. A. Goodman and D. Bruyere, “Optimum and decentralized detection for multistatic airborne radar,” *IEEE Transactions on Aerospace and Electronic Systems*, vol. 43, no. 2, pp. 806–813, 2007.
- [6] M. Alae-Kerahroodi, M. Soltanalian, P. Babu, and M. R. B. Shankar, *Signal Design for Modern Radar Systems*. Artech House, 2022.
- [7] G. Wang, K. V. Mishra *et al.*, “STAP in automotive MIMO radar with transmitter scheduling,” in *IEEE Radar Conference*, 2020, pp. 1–6.
- [8] A. Bose, B. Tang, M. Soltanalian, and J. Li, “Mutual interference mitigation for multiple connected automotive radar systems,” *IEEE Transactions on Vehicular Technology*, vol. 70, no. 10, pp. 11 062–11 066, 2021.
- [9] B. Tang and J. Tang, “Joint design of transmit waveforms and receive filters for MIMO radar space-time adaptive processing,” *IEEE Transactions on Signal Processing*, vol. 64, no. 18, pp. 4707–4722, 2016.
- [10] B. Tang, J. Tuck, and P. Stoica, “Polyphase waveform design for MIMO radar space time adaptive processing,” *IEEE Transactions on Signal Processing*, vol. 68, pp. 2143–2154, 2020.
- [11] A. Bose, B. Tang, W. Huang, M. Soltanalian, and J. Li, “Waveform design for mutual interference mitigation in automotive radar,” *arXiv preprint arXiv:2208.04398*, 2022.
- [12] Z. Esmaeilbeig, A. Bose, and M. Soltanalian, “Mutual interference mitigation in PMCW automotive radar,” 2023.
- [13] L. Xu, S. Sun, K. V. Mishra, and Y. D. Zhang, “Automotive FMCW radar with difference co-chirps,” *IEEE Transactions on Aerospace and Electronic Systems*, pp. 1–19, 2023.
- [14] H. W. Kuhn, “The hungarian method for the assignment problem,” *Naval research logistics quarterly*, vol. 2, no. 1-2, pp. 83–97, 1955.
- [15] A. Bose and M. Soltanalian, “Non-convex shredded signal reconstruction via sparsity enhancement,” in *IEEE International Conference on Acoustics, Speech and Signal Processing*, 2017, pp. 4691–4695.
- [16] D. P. Bruyere and N. A. Goodman, “Adaptive detection and diversity order in multistatic radar,” *IEEE Transactions on Aerospace and Electronic Systems*, vol. 44, no. 4, pp. 1615–1623, 2008.
- [17] Z. Esmaeilbeig, A. Eamaz, K. V. Mishra, and M. Soltanalian, “Moving target detection via multi-IRS-aided OFDM radar,” in *IEEE Radar Conference*. IEEE, 2023, pp. 1–6.
- [18] T. Rouffet, P. Vallet, E. Grivel, C. Enderli, B. Joseph, and S. Kemkemiant, “Analysis of a GLRT for the detection of an extended target,” in *IEEE Radar Conference*. IEEE, 2016, pp. 1–5.
- [19] R. E. Burkard, E. Cela, P. M. Pardalos, and L. S. Pitsoulis, *The quadratic assignment problem*. Springer, 1998.
- [20] M. Soltanalian and P. Stoica, “Designing unimodular codes via quadratic optimization,” *IEEE Transactions on Signal Processing*, vol. 62, no. 5, pp. 1221–1234, 2014.
- [21] M. Soltanalian, B. Tang, J. Li, and P. Stoica, “Joint design of the receive filter and transmit sequence for active sensing,” *IEEE Signal Processing Letters*, vol. 20, no. 5, pp. 423–426, 2013.