

Wrap-Decoding in Asynchronous Unsourcesd Multiple Access With and Without Delay Information

Jyun-Sian Wu, Pin-Hsun Lin, Marcel A. Mross, and Eduard A. Jorswieck

Institute for Communications Technology, Technische Universität Braunschweig, Germany
{jyun-sian.wu, p.lin, m.mross, e.jorswieck}@tu-braunschweig.de

Abstract—An asynchronous K_a -active-user unsourced multiple access channel (AUMAC) is a key model for uncoordinated massive access in future networks. We focus on a scenario where each transmission is subject to the maximal delay constraint (D_m), and the precise delay of each user is unknown at the receiver. The combined effects of asynchronicity and uncertain delays require analysis over all possible delay-codeword combinations, making the complexity of the analysis grow with D_m and K_a exponentially. To overcome the complexity, we employ a wrap-decoder for the AUMAC and derive a uniform upper bound on the per-user probability of error (PUPE). The numerical result shows the trade-off between energy per bit and the number of active users under various delay constraints. Furthermore, in our considered AUMAC, decoding without explicit delay information is shown to achieve nearly the same energy efficiency as decoding with perfect delay knowledge.

I. INTRODUCTION

Massive access techniques have attracted significant attention in 6G and beyond, especially for Internet-of-things, sensor networks, and massive machine-type communication [1]. A key challenge lies in designing short-blocklength codebooks to enable numerous devices to access an access point simultaneously. Conventional multiple-access channel (MAC) systems, which rely on individual codebooks per device [2], are impractical for such scenarios. To address this, the *unsourced multiple-access channel* (UMAC) was proposed [3], where all transmitters share an identical codebook.

Key results on the UMAC include asymptotic capacity analysis for user numbers scaling with blocklength [4], second-order asymptotic achievable rates in grant-free random access [5], [6], and energy efficiency under per-user probability of error (PUPE) constraints [3]. A practical T-fold ALOHA scheme for grant-free Gaussian random access has also been proposed, with energy efficiency analysis [7].

Asynchronous systems are worth investigating due to the difficulty of synchronizing a large number of devices. For asynchronous MAC, asymptotic capacity matches synchronous MAC if the delay-to-blocklength ratio asymptotically vanishes [8], [9]. For asynchronous UMAC (AUMAC), authors in [10], [11] consider T-fold ALOHA [7] in orthogonal frequency-division multiplexing (OFDM), where the length of the cyclic prefix must be greater than the maximum delay. Sparse

orthogonal frequency-division multiple access (OFDMA) and compressed sensing techniques are applied for identifying devices and decoding codewords [12]. A joint detection of delay and user activity is formulated by tropical linear algebra in [13].

The PUPE can be bounded by considering all possible incorrectly decoded codewords transmitted by the users in subsets $\mathcal{S} \subseteq [K_a]$. For UMAC, the permutation-invariant property [3] guarantees that for a given number of incorrectly decoded codewords, $|\mathcal{S}|$, the probabilities that the receiver incorrectly decodes all combinations of $|\mathcal{S}|$ out of K_a transmitted codewords are identical. This permutation-invariance, however, is destroyed by the AUMAC, where different combinations of codewords and delays are distinguishable. Therefore, even though the receiver is assumed to have perfect delay information, the PUPE of AUMAC consists of many more different error events that must be considered, leading to a more complex error bound. To overcome the difficult analysis of AUMAC, we investigate [14] the worst-case delay for an AUMAC with the assumption that the receiver decodes at the n -th channel use with perfect delay information.

Instead of decoding at the n -th channel use [14], in this work, we consider the case where the receiver decodes the transmitted codewords after receiving $n + D_m$ symbols, where D_m is the maximal delay constraint. Inspired by [9], we apply a wrap-decoding strategy to the AUMAC, where the last D_m received symbols are summed up with the first D_m received symbols. As a result, the receiver observes the sum of K_a cyclically shifted codewords plus Gaussian noise, where the power of the noise in the first D_m symbols is two times than that of noise in the remaining symbols. For AWGN and i.i.d. Gaussian codewords, the design of the wrap-decoding results in the identical PUPE for all delays, such that finding the worst case becomes unnecessary. In addition, obtaining the perfect delay information is difficult for the receiver for practical massive access systems. Therefore, in this work, we not only relax the assumption that the receiver decodes at the n -th channel use [14] but also analyze the PUPE of the AUMAC without delay information. Although evaluating the PUPE of the AUMAC without delay information is more difficult compared to the AUMAC with delay information, the wrap-decoding enables

us to derive a uniform upper bound for all combinations of codewords and delays. Consequently, the PUPE can be derived by scaling the uniform upper bounds with the number of the corresponding error events.

Our numerical results illustrate the performance loss due to the asynchronicity as well as the improvement over [14] due to decoding after $n + D_m$ received symbols. We also show that the wrap-decoder design not only makes the decoder robust against different delays but also against the lack of delay information at the receiver since the performance of the wrap-decoder with and without delay information is nearly identical.

Notation: We will denote $f^{(i)}(t)$ as the i -th derivative of $f(x)$ at the point $x = t$ and $f_{1,y}^{(i)}(x, t)$ as the i -th partial derivative of $f_1(x, y)$ with respect to y at the point $y = t$. We use the indicator function $\mathbb{1}(\cdot)$, the natural logarithm $\log(\cdot)$, and the Landau symbol $O(\cdot)$. The binomial coefficient of n out of k is represented by $\binom{n}{k}$. The number of permutations of k is denoted as $k!$. The transpose of a real matrix \mathbf{A} is denoted as \mathbf{A}^\top . We use $\|\mathbf{A}\|_1$ to denote the 1-norm of the matrix \mathbf{A} . We denote $[k] = \{1, 2, \dots, k\}$, $X_{[k]} := \{X_1, X_2, \dots, X_k\}$, and $\mathcal{F} \setminus \mathcal{T} = \{x : x \in \mathcal{F}, x \notin \mathcal{T}\}$, where \mathcal{F} and \mathcal{T} are two sets.

II. SYSTEM MODEL AND PRELIMINARIES

We consider an AUMAC with K_a active transmitters, one receiver, and additive white Gaussian noise (AWGN). All transmitters use the same codebook with the same maximal power constraint, P' , to transmit a fixed $\log_2 M$ bits payload. The codewords are independent and identically distributed (i.i.d.) generated from a Gaussian distribution with mean zero and variance P , where $P < P'$. The power backoff reduces the probability that the maximal power constraint is violated.

Definition 1: We define the asynchronicity with delay constraint D_m by a vector of delays as

$$d_{[K_a]} := [d_1, d_2, \dots, d_{K_a}] \in \{\mathbb{N}_0\}^{K_a},$$

where d_i represents the delay of the i -th received codeword, $d_i \leq d_{i+1}$, $\forall i \in [K_a - 1]$ and $d_{K_a} \leq D_m$. We define $\alpha := \frac{D_m}{n} \in [0, 1)$, which is a constant with respect to the blocklength n , and $\bar{\alpha} = 1 - \alpha$.




Fig. 1: A K_a -active-user AUMAC with $d_{[K_a]} = [0, 1, 2, 3, \dots, D_m]$.

For any $\ell \in [n]$, we define a shift function $\tau_{d_i}(X_i^n, \ell) := X_{i, \ell - d_i}$, where $X_{i, \ell - d_i}$ is the $(\ell - d_i)$ -th element of X_i^n , and if $\ell - d_i \notin [n]$, $X_{i, \ell - d_i} = 0$, $\forall i \in [K_a]$. The received symbol at the receiver at time $\ell \in [n + D_m]$ is

$$Y_\ell = \sum_{i=1}^{K_a} \tau_{d_i}(X_i^n, \ell) + Z_\ell, \quad (1)$$

where the channel input $X_i^n \in \mathcal{X}^n \subset \mathbb{R}^n$, $\mathcal{X}^n := \{x^n : x^n \in \mathbb{R}^n, \|x^n\|^2 \leq nP'\}$ satisfying the maximal power constraint,

and $Z_\ell \sim \mathcal{N}(0, 1)$, $\forall \ell \in [n + D_m]$. The received signal of a K_a -active-user AUMAC with $d_{[K_a]} = [0, 1, 2, 3, \dots, D_m]$ is illustrated in Fig. 1.

We define an AUMAC code, where the receiver does not have perfect delay information, as follows:

Definition 2: An $(n, M, \epsilon, K_a, \alpha)$ -code for an AUMAC described by $P_{Y|X_{[K_a]}}$ consists of one message set \mathcal{M} , one encoder $f : \mathcal{M} \rightarrow \mathcal{X}^n$, and one decoder $\hat{g} : \mathbb{R}^{n+D_m} \rightarrow \binom{\mathcal{M}}{K_a}$ such that for the maximal power constraint P' and any $d_{[K_a]}$ satisfying $d_i \leq \alpha n$, $\forall i \in [K_a]$, the PUPE satisfies

$$P_{\text{PUPE}} := \sum_{i=1}^{K_a} \frac{1}{K_a} \Pr(\tilde{\mathcal{E}}_i | d_{[K_a]}) \leq \epsilon, \quad (2)$$

where $\binom{\mathcal{M}}{K_a}$ is a set containing K_a distinct elements from the set \mathcal{M} , $\tilde{\mathcal{E}}_i := \{\{M_\ell = M_i, \forall \ell \in [K_a], \ell \neq i\} \cup \{M_i \notin \hat{g}(Y^{n+D_m})\} \cup \{\|f(M_i)\|^2 > nP'\}\}$, $i \in [K_a]$, and M_i is the i -th transmitted message, which is uniformly distributed in \mathcal{M} .

III. MAIN RESULTS

This section investigates the achievable PUPE upper bound of the AUMAC where the receiver decodes based on $n + D_m$ received symbols. In Theorem 1, we consider the AUMAC without delay information at the receiver. In Theorem 2, we consider the AUMAC with delay information at the receiver.

To analyze the PUPE of the AUMAC with the receiver decoding with $n + D_m$ received symbols, we consider the wrap-decoder for the AUMAC without delay information defined as follows:

$$\hat{g}(\tilde{Y}^n) = \arg \min_{X_{[K_a]}^n \in \mathcal{C}, d_{[K_a]} \in [0, D_m]^{K_a}} \left\| \tilde{Y}^n - X_{[K_a], d_{[K_a]}}^n \right\|^2, \quad (3)$$

where \mathcal{C} contains M codewords, $X_{[K_a], d_{[K_a]}}^n := \sum_{i \in [K_a]} \mathbf{S}^{d_i} X_i^n$, $\mathbf{S} := \begin{bmatrix} 0^{n-1} & & \\ \mathbf{I}_{n-1} & & \\ & & 0^{n-1} \end{bmatrix}$ is the circular shift matrix, \mathbf{I}_{n-1} is an $(n-1) \times (n-1)$ identity matrix, $\tilde{Y}^n := [Y_1, Y_2, \dots, Y_n] + [Y_{n+1}, Y_{n+2}, \dots, Y_{n+D_m}, 0^{n-D_m}]$, and 0^k is a vector of zeros of length k . Because the receiver does not have delay information, the decoder compares all combinations of delays $d_{[K_a]} \in [0, D_m]^{K_a}$ and codewords $X_{[K_a]}^n \in \mathcal{C}$.

Based on Definition 2 and the decoder defined in (3), we summarize the FBL analysis results for the AUMAC as follows:

Theorem 1: Fix $0 < P \leq P'$. There exists an $(n, M, \epsilon, K_a, \alpha)$ -code for an AUMAC such that the PUPE is upper-bounded as follows.

$$\sum_{s=1}^{K_a} \frac{s}{K_a} \binom{K_a}{s} \left\{ \min_{t>0} \left\{ \frac{\exp(g(s, t, T_s))}{T_s(1-T_s)\sqrt{2\pi}} \left(g_{t_s}^{(2)}(s, t, T_s) \right)^{\frac{-1}{2}} \right\} \right. \\ \left. + \sum_{s_1=1}^{K_a-s} \binom{K_a-s}{s_1} (1+\alpha n)^{s_1} \min_{t>0} \left\{ \frac{\exp(\bar{g}(s, s_1, t, T_s))}{T_s^* \sqrt{2\pi}} \right. \right. \\ \left. \left. \cdot \left(g_{t_s}^{(2)}(s, t, \tilde{T}_s) \right)^{\frac{-1}{2}} \right\} \right\} + p_0 + O\left(\frac{\exp(-n)}{\sqrt{n}}\right) \leq \epsilon, \quad (4)$$

if there exists $T_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $g_{t_s}^{(1)}(s, t, T_s) = 0$, $\underline{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that

$$g_{t_s}^{(1)}(s, t, \underline{T}_s) = \underline{\gamma}(s, s_1, t, \underline{T}_s), \quad (5)$$

and $\bar{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that

$$g_{t_s}^{(1)}(s, t, \bar{T}_s) = \bar{\gamma}(s, s_1, t, \bar{T}_s), \quad (6)$$

where

$$g(s, t, t_s) := t_s \log \theta(s) - \frac{n(t_s - 1)}{2} \log(1 + 2sPt) - \frac{\alpha n}{2} \log(1 + 2sPt(1 + t_s)(1 - 4t \cdot t_s)) - \frac{\bar{\alpha} n}{2} \log(1 + 2sPt(1 + t_s)(1 - 2t \cdot t_s)), \quad (7)$$

$$\theta(s) = \binom{M - K_a}{s} (1 + \alpha n)^s, \quad (8)$$

$$\bar{g}(s, s_1, t, t_s) := g(s, t, t_s) - \frac{2ns_1P(\alpha f_2 + \bar{\alpha} f_1)}{\sqrt{1 + 2\bar{\lambda} + \frac{\bar{\lambda}^2}{3}}}, \quad (9)$$

$$T^* := \min\{\bar{T}_s(1 - \bar{T}_s), \underline{T}_s(1 - \underline{T}_s)\}, \quad (10)$$

$$\tilde{T}_s := \arg \inf_{t_s \in (0, \min\{1, 1/4t\})} g_{t_s}^{(2)}(s, t, t_s), \quad (11)$$

$$f_\ell(s, t, t_s) := \frac{(1 - 2 \cdot \ell \cdot t \cdot t_s)t \cdot t_s}{1 + 2sPt(1 + t_s)(1 - 2 \cdot \ell \cdot t \cdot t_s)}, \quad \ell = \{1, 2\},$$

$$\bar{\gamma}(s, s_1, t, t_s) := \begin{cases} 2s_1 nP \left(\alpha \frac{\partial f_2}{\partial t_s} + \bar{\alpha} \frac{\partial f_1}{\partial t_s} \right), & \text{if } \frac{\partial f_2}{\partial t_s} \geq 0 \\ 4s_1 nP \frac{\partial f_1}{\partial t_s}, & \text{o.w.,} \end{cases} \quad (12)$$

$$\underline{\gamma}(s, s_1, t, t_s) := \begin{cases} \frac{2s_1 nP}{1 + 2\bar{\lambda}} \left(\alpha \frac{\partial f_2}{\partial t_s} + \bar{\alpha} \frac{\partial f_1}{\partial t_s} \right), & \text{if } \frac{\partial f_2}{\partial t_s} \geq 0 \\ 4s_1 nP \frac{\partial f_2}{\partial t_s}, & \text{o.w.,} \end{cases} \quad (13)$$

$$\bar{\lambda} := 4s_1 f_1 P, \text{ and } p_0 := \frac{K_a(K_a - 1)}{2M} + \sum_{i=1}^{K_a} \Pr(\|X_i^n\|^2 > nP').$$

The proof is relegated to Appendix A.

For an AUMAC without delay information at the receiver, the event that the receiver incorrectly decodes the messages transmitted by the user in $[s]$ consists of the following cases:

- 1) The codewords transmitted from the users in $[s]$ are incorrectly decoded with any $\hat{d}_{[s]} \in \{0, D_m\}^s$ and the codewords transmitted from $[K_a] \setminus [s]$ are correctly decoded with correct delays $d_{[K_a] \setminus [s]}$.
- 2) The codewords transmitted from the users in $[s]$ are incorrectly decoded with any $\hat{d}_{[s]} \in \{0, D_m\}^s$ and the codewords transmitted from $[K_a] \setminus [s]$ are correctly decoded with s_1 incorrect delays and $K_a - s - s_1$ correct delays, where $s_1 \in [K_a - s]$.

Therefore, by utilizing the union bound, we express the probability that the receiver incorrectly decodes the messages transmitted by the users in $[s]$ as the sum of the probabilities of the first case and the second case in (4). It is worth noting that the wrap-decoder, AWGN, and the i.i.d. Gaussian codebooks cause the PUPE to be identical for any delay $d_{[K_a]} \in \{0, D_m\}^{K_a}$ because any $d_{[K_a]} \in \{0, D_m\}^{K_a}$ has the same distribution of \tilde{Y} . As a result, Theorem 1 is independent of $d_{[K_a]}$.

For the AUMAC with delay information at the receiver, we

define an AUMAC code as follows:

Definition 3: An $(n, M, \epsilon, K_a, \alpha, d_{[K_a]})$ -code for an AUMAC described by $P_{Y|X_{[K_a]}}$ consists of one message set \mathcal{M} , one encoder $f: \mathcal{M} \rightarrow \mathcal{X}^n$, and one decoder $\hat{g}: \mathbb{R}^{n+D_m} \rightarrow \binom{\mathcal{M}}{K_a}$ such that $P_{\text{PUPE}} \leq \epsilon$ for the power constraint P' and given $d_{[K_a]}$ satisfying $d_i \leq \alpha n$, $\forall i \in [K_a]$.

We consider the decoder defined as

$$\hat{g}(\tilde{Y}^n) = \arg \min_{X_{[K_a]}^n \in \mathcal{C}, d_{[K_a]} \in \mathfrak{S}(d_{[K_a]})} \left\| \tilde{Y}^n - X_{[K_a], d_{[K_a]}}^n \right\|^2, \quad (14)$$

where $\mathfrak{S}(d_{[K_a]})$ contains all permutations of $d_{[K_a]}$. Compared to (3), for AUMAC with perfect delay information at the receiver, we only consider all permutations of $d_{[K_a]}$ instead of all combinations of possible delays.

Theorem 2: Fix $0 < P \leq P'$. There exists an $(n, M, \epsilon, K_a, \alpha, d_{[K_a]})$ -code for an AUMAC such that the PUPE can be upper-bounded as follows:

$$\sum_{s=1}^{K_a} \frac{s}{K_a} \binom{K_a}{s} \left\{ \min_{t>0} \left\{ \frac{\exp(g_2(s, t, T_s))}{T_s(1 - T_s)\sqrt{2\pi}} \left(g_{2, t_s}^{(2)}(s, t, T_s) \right)^{-\frac{1}{2}} \right\} + \sum_{s_1=1}^{K_a-s} \binom{K_a-s}{s_1} \frac{(s+s_1)!}{s!} \min_{t>0} \left\{ \frac{\exp(\bar{g}_2(s, s_1, t, \underline{T}_s))}{T^* \sqrt{2\pi}} \cdot \left(g_{2, t_s}^{(2)}(s, t, \tilde{T}_s) \right)^{-\frac{1}{2}} \right\} \right\} + p_0 + O\left(\frac{\exp(-n)}{\sqrt{n}}\right) \leq \epsilon, \quad (15)$$

if there exists $T_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $g_{2, t_s}^{(1)}(s, t, T_s) = 0$, $\underline{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $g_{2, t_s}^{(1)}(s, t, \underline{T}_s) = \underline{\gamma}(s, s_1, t, \underline{T}_s)$, and $\bar{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $g_{2, t_s}^{(1)}(s, t, \bar{T}_s) = \bar{\gamma}(s, s_1, t, \bar{T}_s) = 0$, where

$$g_2(s, t, t_s) := g(s, t, t_s) - t_s \log \frac{(1 + \alpha n)^s}{s!}, \quad (16)$$

$$\bar{g}_2(s, s_1, t, t_s) := g_2(s, t, t_s) - \frac{2ns_1P(\alpha f_2 + \bar{\alpha} f_1)}{\sqrt{1 + 2\bar{\lambda} + \frac{\bar{\lambda}^2}{3}}}, \quad (17)$$

the terms $g(s, t, t_s)$, $\bar{\lambda}$, T^* , \tilde{T}_s , $f_1(s, t, t_s)$, $f_2(s, t, t_s)$, $\bar{\gamma}(s, s_1, t, t_s)$, and $\underline{\gamma}(s, s_1, t, t_s)$ are defined in Theorem 1.

The proof is relegated to Appendix B.

Note that for a given number of incorrectly decoded codewords, $s \in [K_a]$, we derive $\bar{\gamma}(s, s_1, t, t_s)$ and $\underline{\gamma}(s, s_1, t, t_s)$ by finding the upper bound for a given number of the incorrect delays paired to the correctly decoded codewords, $s_1 \in [0, K_a - s]$. Even though the delay information is available at the receiver, the receiver may correctly decode $K_a - s$ codewords with s_1 incorrect delays. As a result, $\bar{\gamma}(s, s_1, t, t_s)$ and $\underline{\gamma}(s, s_1, t, t_s)$ are identical regardless of the availability of delay information.

IV. NUMERICAL RESULTS

Based on the results of Theorem 1 and Theorem 2 without considering $O\left(\frac{\exp(-n)}{\sqrt{n}}\right)$, we numerically evaluate $\frac{E_b}{N_0}$ versus K_a , where $\frac{E_b}{N_0} := \frac{nP'}{2 \log_2 M}$. The PUPE upper bounds from Theorem 1 and Theorem 2 are compared to UMAC and different AUMAC schemes under different scenarios with the




Fig. 2: The trade-off between $\frac{E_b}{N_0}$ and K_a

following parameters: $\log M = 100$, $n = 4000$, $\epsilon = 5 \times 10^{-2}$, and $K_a \in [50, 160]$. In Figure 2, all curves are evaluated by numerically optimizing $P < P'$. The black solid curve indicates the required $\frac{E_b}{N_0}$ of the UMAC [3]. A blue dashed curve marked with triangles indicates the required $\frac{E_b}{N_0}$ of the AUMAC where the receiver decodes at the n -th channel use with perfect delay information [14].

We evaluate the required $\frac{E_b}{N_0}$ of the AUMAC without delay information by Theorem 1 for $\alpha = 0.2$ and $\alpha = 0.4$ and that of the AUMAC with delay information by Theorem 2 with $\alpha = 0.2$. Numerical results show that for an AUMAC, a larger α causes the transmitters to consume more energy to transmit reliably. Observing the curves of Theorem 1 and Theorem 2 with $\alpha = 0.2$, we conclude that the availability of delay information at the receiver only slightly influences the required $\frac{E_b}{N_0}$. By comparing the $\frac{E_b}{N_0}$ of the AUMAC with delay information evaluated by Theorem 2 to the $\frac{E_b}{N_0}$ of [14], the energy efficiency is improved significantly by decoding with completely received codewords, especially when K_a is large.

V. CONCLUSIONS

This work investigates the FBL performance of the AUMAC where the receiver decodes with $n + D_m$ channel uses and does not have delay information. Although the asynchronous model and decoding without delay information lead to a more complex PUPE bound, we design a wrap-decoder achieving the same PUPE for all delays. In addition, the wrap-decoder enables us to derive a uniform upper bound of the PUPE for all combinations of codewords and delays. As a result, the analysis is significantly simplified by multiplying the uniform upper bound with the number of the corresponding error events instead of calculating the tail probabilities of all error events. The numerical results show the trade-off between $\frac{E_b}{N_0}$ and delay constraint D_m . By observing the $\frac{E_b}{N_0}$, the performance loss due to the asynchronicity is improved by applying the wrap-decoding to decode with completely received codewords. In addition, the wrap-decoder can efficiently overcome the lack of information on delays since the energy efficiencies of the AUMAC with and without delay information are nearly identical.

APPENDIX A PROOF OF THEOREM 1

In the following, we apply the RCU bound [15] to express the PUPE defined in Definition 2 as a sum of tail probabilities. Then, we apply the Taylor expansion, the Chernoff bound, and the inverse Laplace transform to the tail probabilities.

We define $\mathcal{E} := \{\{M_\ell \neq M_i, \forall i \neq \ell, \forall i, \ell \in [K_a]\} \cap \{\|f(M_i)\|^2 \leq nP', \forall i \in [K_a]\}\}$, which represents the event that all transmitted messages are distinct and transmitted codewords fulfill the power constraint. By Definition 2, for any $d_{[K_a]} \in [0, D_m]^{K_a}$, the PUPE of an $(n, M, \epsilon, K_a, \alpha)$ -code can be upper-bounded as follows:

$$\begin{aligned} P_{\text{PUPE}} &\leq p_0 + \sum_{\mathcal{S} \subseteq [K_a]} \frac{|\mathcal{S}|}{K_a} \Pr(M_{\mathcal{S}} \notin \hat{g}(\tilde{Y}^n), M_{\bar{\mathcal{S}}} \in \hat{g}(\tilde{Y}^n) | d_{[K_a]}, \mathcal{E}), \\ &\text{where } \bar{\mathcal{S}} := [K_a] \setminus \mathcal{S} \text{ and } p_0 \text{ is defined in Theorem 1. By} \\ &\text{substituting the wrap-decoder defined in (3), we have} \\ &\sum_{\mathcal{S} \subseteq [K_a]} \frac{|\mathcal{S}|}{K_a} \Pr(M_{\mathcal{S}} \notin \hat{g}(\tilde{Y}^n), M_{\bar{\mathcal{S}}} \in \hat{g}(\tilde{Y}^n) | d_{[K_a]}, \mathcal{E}) \\ &= \sum_{s=1}^{K_a} \frac{s \binom{K_a}{s}}{K_a} \Pr\left(\bigcup_{\substack{\bar{X}_{[s]}^n \subseteq f(\mathcal{M} \setminus M_{[K_a]}) \\ d_{[K_a]} \in [0, D_m]^{K_a}}} \|\tilde{Y} - \bar{X}_{[s]}^n - X_{[s]}^n\|^2 \leq \|\tilde{Z}^n\|^2\right), \end{aligned} \quad (18)$$

where $\bar{[s]} := [K_a] \setminus [s]$, $\tilde{Z}_i \sim \mathcal{N}(0, 2)$, $i \in [D_m]$, and $\tilde{Z}_i \sim \mathcal{N}(0, 1)$, $i \in [D_m]$ due to the wrap-decoding. The equality is because, for the wrap-decoder defined in (3), $\tilde{Y} \in \mathbb{R}^n$ is the sum of K_a i.i.d. codewords plus independent noise. Therefore, all subsets $\mathcal{S} \subseteq [K_a]$ with the same cardinality $|\mathcal{S}|$ lead to the same tail probability.

For the AUMAC without perfect delay information at the receiver, the receiver must consider all possible delays, i.e., all $\hat{d}_{[K_a]} \in [0, D_m]^{K_a}$. Then, the RCU bound [15] and the Chernoff bound with $t > 0$ are applied to (18) as follows:

$$\begin{aligned} &\Pr\left(\bigcup_{\substack{\bar{X}_{[s]}^n \subseteq f(\mathcal{M} \setminus M_{[K_a]}) \\ d_{[K_a]} \in [0, D_m]^{K_a}}} \|\tilde{Y}^n - \bar{X}_{[s]}^n - X_{[s]}^n\|^2 \leq \|\tilde{Z}^n\|^2\right) \\ &= \mathbb{E} \left[\Pr\left(\bigcup_{\substack{\bar{X}_{[s]}^n \subseteq f(\mathcal{M} \setminus M_{[K_a]}) \\ \hat{d}_{[K_a]} \in [0, D_m]^{K_a}}} \|\tilde{Y}^n - \bar{X}_{[s]}^n - X_{[s]}^n\|^2 \leq \|\tilde{Z}^n\|^2 \mid X_{[K_a]}^n, \tilde{Z}^n\right) \right] \\ &\leq \mathbb{E} \left[\min \left\{ 1, \sum_{\hat{d}_{[K_a]} \in [0, D_m]^{K_a}} \binom{M - K_a}{s} \Pr\left(\|\tilde{Y}^n - \bar{X}_{[s]}^n - X_{[s]}^n\|^2 \leq \|\tilde{Z}^n\|^2 \mid X_{[K_a]}^n, \tilde{Z}^n\right) \right\} \right] \\ &\leq \sum_{\hat{d}_{[s]} \in [0, D_m]^{K_a - s} \setminus \hat{d}_{[\bar{s}]}} \min_{t > 0} \mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(-t \|\tilde{Z}^n\|^2) \right\} \right] \end{aligned}$$

$$\begin{aligned} & \cdot \mathbb{E} \left[\exp \left(-t \left\| B_{[s]}^n + X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + \tilde{Z}^n \right\|^2 \right) \right] \\ & + \min_{t>0} \mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(t \|\tilde{Z}^n\|^2) \right. \right. \\ & \quad \left. \left. \cdot \mathbb{E} \left[\exp \left(-t \left\| X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + \tilde{Z}^n \right\|^2 \right) \right] \right\} \right], \quad (19) \end{aligned}$$

where $\theta(s) := \binom{M - K_a}{s} (1 + D_m)^s$, $B_{[s]}^n := X_{[s], d_{[s]}}^n - X_{[s], \hat{d}_{[s]}}^n$, and $B^n \sim \mathcal{N}(0^n, \Sigma(\hat{d}_{[s]}))$. The first equality follows from the random coding [15]. The first inequality follows from the union bound. The last inequality follows from the Chernoff bound and $\min\{1, a+b\} \leq \min\{1, a\} + \min\{1, b\}$ for $a, b \geq 0$. The first term in (19) represents the probability that the receiver incorrectly decodes the codewords transmitted by users in $[s]$ and correctly decodes codewords with incorrect delay $\hat{d}_{[s]}$; the second term represents the probability that the receiver incorrectly decodes the codewords transmitted by users in $[s]$ and correctly decodes codewords with correct delay $d_{[s]}$.

To derive tail probabilities, the Taylor expansion and the inverse Laplace transform are used in [14], [16], [17]. Therefore, for a given $s \in [K_a]$, $\hat{d}_{[s]} \in [0, D_m]^{K_a - s} \setminus d_{[s]}$ and $t > 0$, we apply the Taylor expansion and the inverse Laplace transform to the first term in (19) as follows:

$$\begin{aligned} & \min_{t>0} \mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(t \|\tilde{Z}^n\|^2) \right. \right. \\ & \quad \left. \left. \cdot \mathbb{E} \left[\exp \left(-t \left\| B_{[s]}^n + X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + \tilde{Z}^n \right\|^2 \right) \right] \right\} \right] \\ & \leq \frac{\exp(g(s, t, T_s) + \log \mathbb{E} \left[\exp \left(-(B_{[s]}^n)^\top \mathbf{A}(s, t, T_s) B_{[s]}^n \right) \right])}{T_s (1 - T_s) \sqrt{2\pi}} \\ & \quad \cdot \left(\frac{d^2}{dt^2} \log \mathbb{E} \left[\exp \left(-(B_{[s]}^n)^\top \mathbf{A}(s, t, T_s) B_{[s]}^n \right) \right] \right) \Big|_{t_s = T_s} \\ & \quad + g_{t_s}^{(2)}(s, t, T_s) \Big)^{-\frac{1}{2}} + O \left(\frac{\exp(-n)}{\sqrt{n}} \right), \quad (20) \end{aligned}$$

if there exists $T_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that

$$\begin{aligned} & \frac{d}{dt_s} \log \mathbb{E} \left[\exp \left(-(B_{[s]}^n)^\top \mathbf{A}(s, t, T_s) B_{[s]}^n \right) \right] \Big|_{t_s = T_s} \\ & = -g_{t_s}^{(1)}(s, t, T_s), \quad (21) \end{aligned}$$

where

$$\begin{aligned} g(s, t, T_s) & := t_s \log \theta(s) - \frac{n(t_s - 1)}{2} \log(1 + 2sPt) \\ & \quad - \frac{\alpha n}{2} \log(1 + 2sPt(1 + t_s)(1 - 4t \cdot t_s)) \\ & \quad - \frac{\bar{\alpha} n}{2} \log(1 + 2sPt(1 + t_s)(1 - 2t \cdot t_s)), \quad (22) \end{aligned}$$

the matrix $\mathbf{A}(s, t, T_s) \in \mathbb{R}^{n \times n}$ is a diagonal matrix, $A(s, t, T_s)_{i,i} = f_2(s, t, T_s)$, $\forall i \in [D_m]$, and $A(s, t, T_s)_{i,i} = f_1(s, t, T_s)$, $\forall i \in [n] \setminus [D_m]$,

$$f_1(s, t, T_s) = \frac{(1 - 2t \cdot t_s)t \cdot t_s}{1 + 2sPt(1 + t_s)(1 - 2t \cdot t_s)},$$

and

$$f_2(s, t, T_s) = \frac{(1 - 4t \cdot t_s)t \cdot t_s}{1 + 2sPt(1 + t_s)(1 - 4t \cdot t_s)}.$$

To simplify the notation, we use \mathbf{A} , f_1 , and f_2 to denote $\mathbf{A}(s, t, T_s)$, $f_1(s, t, T_s)$, and $f_2(s, t, T_s)$, respectively. It is worth noting that to guarantee the convergence of $\tilde{g}(s, s_1, t, T_s)$ in (20) for a given $t > 0$, we need $0 < t_s < \frac{1}{4t}$, and to guarantee a positive $T_s(1 - T_s)$ in (20), we need $0 < t_s < 1$.

Let $s_1 := \sum_{i \in [s]} \mathbb{1}(d_i \neq \hat{d}_i)$ be the number of incorrect delays paired to correctly decoded codewords and $\mathbf{G}(\hat{d}_{[s]}) \mathbf{G}(\hat{d}_{[s]})^\top = \Sigma(\hat{d}_{[s]})$. We derive the expectation by expressing the quadratic form as follows [18, Corollary 3.2a.2]:

$$\mathbb{E} \left[\exp \left(-(B^n)^\top \mathbf{A} B^n \right) \right] = \prod_{i=1}^r \left(1 + 2\lambda_i \left(\Sigma(\hat{d}_{[s]}) \right) \right)^{-\frac{1}{2}}, \quad (23)$$

where $r = \text{rank}(\Sigma(\hat{d}_{[s]}))$, and $\lambda_{[r]}(\Sigma(\hat{d}_{[s]}))$ are non-zero eigenvalues of $\mathbf{G}(\hat{d}_{[s]})^\top \mathbf{A} \mathbf{G}(\hat{d}_{[s]})$. To simplify the notations, we use $\lambda_{[r]}$ to represent $\lambda_{[r]}(\Sigma(\hat{d}_{[s]}))$. We substitute (23) into (20) as follows:

$$\begin{aligned} & \mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(t \|\tilde{Z}^n\|^2) \right. \right. \\ & \quad \left. \left. \cdot \mathbb{E} \left[\exp \left(-t \left\| B_{[s]}^n + X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + \tilde{Z}^n \right\|^2 \right) \right] \right\} \right] \\ & \leq \frac{\exp(\tilde{g}(s, s_1, t, T_s))}{T_s (1 - T_s) \sqrt{2\pi}} \left(\tilde{g}_{t_s}^{(2)}(s, s_1, t, T_s) \right)^{-\frac{1}{2}} + O \left(\frac{\exp(-n)}{\sqrt{n}} \right), \quad (24) \end{aligned}$$

if there exists $T_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $\tilde{g}_{t_s}^{(1)}(s, s_1, t, T_s) = 0$, where

$$\tilde{g}(s, s_1, t, T_s) := g(s, t, T_s) - \frac{1}{2} \sum_{i=1}^r \log(1 + 2\lambda_i). \quad (25)$$

For a give $\hat{d}_{[s]}$, (24) provides the probability that the decoder incorrectly decodes the codewords transmitted by users in $[s]$ and correctly decoded codewords transmitted by user in the set $[s]$ with delays $\hat{d}_{[s]}$. However, the first term in (19) requires calculating all possible $\hat{d}_{[s]} \in [0, \alpha n]^{(K_a - s)} \setminus \{0\}^{(K_a - s)}$. It requires calculating $(1 + D_m)^{(K_a - s)}$ different combinations of the delays, which is infeasible when K_a and D_m are large. To overcome the computational complexity, we derive the uniform upper bound of the probabilities for a given s_1 by upper-bounding $\tilde{g}(s, s_1, t, T_s)$, $(T_s(1 - T_s))^{-1}$, and $(\tilde{g}_{t_s}^{(2)}(s, s_1, t, T_s))^{-\frac{1}{2}}$ in (24), separately.

To find a uniform upper bound of the term $(T_s(1 - T_s))^{-1}$, we introduce the following lemma.

Lemma 1: Let $q(t_s)$ be a function with range of convergence $\tilde{\mathcal{R}}, \mathcal{R} := \tilde{\mathcal{R}} \cap (0, 1)$, and $q(t_s)$ is convex with respect to $t_s \in \mathcal{R}$. Let $T_s \in \mathcal{R}$ satisfy

$$q^{(1)}(T_s) = \sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i \Big|_{t_s = T_s}}{1 + 2\tilde{\lambda}_i},$$

where $\tilde{\lambda}_{[r]}$ are non-zero eigenvalues of a matrix $\mathbf{K} \cdot \mathbf{A}(t_s) \in$

$\mathbb{R}^{n \times n}$ with rank r , $\mathbf{K} \in \mathbb{R}^{n \times n}$ and $\mathbf{A}(t_s) \in \mathbb{R}^{n \times n}$ are positive-semidefinite, $\mathbf{A}(t_s)$ is a diagonal matrix, and $A(t_s)_{i,i}$ is convex with respect to $t_s \in \mathcal{R}$, $\forall i \in [n]$. Then, there exists \bar{T}_s and \underline{T}_s satisfying $q^{(1)}(\bar{T}_s) = q_1(\bar{T}_s)$ and $q^{(1)}(\underline{T}_s) = q_2(\underline{T}_s)$, respectively, such that $\underline{T}_s \leq T_s \leq \bar{T}_s$, where

$$q_1(t_s) := \begin{cases} \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}), & \text{if } \underline{\varrho} \geq 0 \\ \underline{\varrho} \cdot \text{Tr}(\mathbf{K}), & \text{if } \underline{\varrho} < 0 < \bar{\varrho} \\ \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}) / (1 + 2\Lambda), & \text{o.w.,} \end{cases}$$

$$q_2(t_s) := \begin{cases} \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}) / (1 + 2\Lambda), & \text{if } \underline{\varrho} \geq 0 \\ \underline{\varrho} \cdot \text{Tr}(\mathbf{K}), & \text{if } \underline{\varrho} < 0 < \bar{\varrho} \\ \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}), & \text{o.w.,} \end{cases}$$

$\Lambda := \max\{\|\mathbf{K} \cdot \mathbf{A}(t_s)\|_1\} \geq \max\{\tilde{\lambda}_{[r]}\}$, $\bar{\varrho} := \max_{i \in [n]} \{\frac{\partial}{\partial t_s} A(t_s)_{i,i}\}$, $\underline{\varrho} := \min_{i \in [n]} \{\frac{\partial}{\partial t_s} A(t_s)_{i,i}\}$, and $\text{Tr}(\mathbf{K})$ represents the trace of the matrix \mathbf{K} .

The proof of Lemma 1 is relegated to Appendix C.

By using Lemma 1, if there exists $\underline{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ and $\bar{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ satisfying (5) and (6) such that $\underline{T}_s \leq T_s \leq \bar{T}_s$ for a given $\hat{d}_{[s]}$, we have the inequality as follows:

$$\frac{1}{\bar{T}_s(1 - \underline{T}_s)} \leq \frac{1}{T^*}, \quad (26)$$

where $T^* := \min\{\bar{T}_s(1 - \bar{T}_s), \underline{T}_s(1 - \underline{T}_s)\}$. The inequality follows from the concavity of $t_s(1 - t_s)$. The terms \bar{T}_s and \underline{T}_s are identical for any $\hat{d}_{[s]}$ with a given s_1 . Therefore, (26) is a uniform upper bound for all $\hat{d}_{[s]}$ with a given s_1 . Note that to guarantee that the RHS of (20) is positive and converges, we consider $\underline{T}_s, \bar{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$. Besides, in our considered case, $f_{1,t_s}^{(1)}(s, t, t_s) \geq 0$, i.e., we have a positive $\bar{\varrho}$. Therefore, there are only two cases in (5) and (6).

To proceed, we find an upper bound of $\tilde{g}(s, s_1, t, T_s)$. The non-negative $\frac{\partial^2}{\partial t_s^2} \tilde{g}(s, s_1, t, t_s)$ results in the convex $\tilde{g}(s, s_1, t, t_s)$ with respect to $t_s \in (0, \min\{1, 1/4t\})$. Therefore, by substituting \underline{T}_s into (25), we can upper-bound $\tilde{g}(s, s_1, t, T_s)$ as follows:

$$\tilde{g}(s, s_1, t, T_s) \leq g(s, t, \underline{T}_s) - \frac{1}{2} \sum_{i=1}^r \log(1 + 2\lambda_i) \quad (27)$$

$$\leq g(s, t, \underline{T}_s) - \frac{2ns_1\text{P}(\alpha f_2 + \bar{\alpha} f_1)}{\sqrt{1 + 2\bar{\lambda} + \frac{\bar{\lambda}^2}{3}}} \quad (28)$$

$$:= \bar{g}(s, s_1, t, \underline{T}_s), \quad (29)$$

where T_s satisfies $g_{t_s}^{(1)}(s, t, T_s) = 0$, (27) follows from the fact that the convex function $g(s, s_1, t, t_s)$ achieves its minimum at the point $t_s = T_s$ satisfying $\tilde{g}_{t_s}^{(1)}(s, s_1, t, T_s) = 0$, (28) follows from inequalities, $\sqrt{1 + x + \frac{x^2}{12}} \log(1 + x) \geq x$ and $\bar{\lambda} := 4s_1 f_1 \text{P} \geq \max\{\lambda_{[r]}\}$ derived from Gershgorin circle theorem [19, Theorem 6.1.1], and the fact that the sum of all eigenvalues of a matrix is the trace of the matrix.

To upper-bound $(\tilde{g}_{t_s}^{(2)}(s, s_1, t, t_s))^{-\frac{1}{2}}$, we find the lower

bound of $\tilde{g}_{t_s}^{(2)}(s, s_1, t, t_s)$ as follows:

$$\tilde{g}_{t_s}^{(2)}(s, s_1, t, t_s) = g_{t_s}^{(2)}(s, t, t_s) - \sum_{i=1}^r \frac{\frac{\partial^2}{\partial t_s^2} \lambda_i}{1 + 2\lambda_i} + 2 \sum_{i=1}^r \left(\frac{\frac{\partial}{\partial t_s} \lambda_i}{1 + 2\lambda_i} \right)^2 \quad (30)$$

$$\geq g_{t_s}^{(2)}(s, t, t_s), \quad (31)$$

where $\frac{\partial^2}{\partial t_s^2} \lambda_{[r]}$ are non-zero eigenvalues of matrix $\mathbf{G} \frac{\partial^2}{\partial t_s^2} \mathbf{A} \mathbf{G}$. The inequality (31) follows from subtracting two positive terms, $-\sum_{i=1}^r \frac{\frac{\partial^2}{\partial t_s^2} \lambda_i}{1 + 2\lambda_i}$ and $2 \sum_{i=1}^r \left(\frac{\frac{\partial}{\partial t_s} \lambda_i}{1 + 2\lambda_i} \right)^2$. The term $-\sum_{i=1}^r \frac{\frac{\partial^2}{\partial t_s^2} \lambda_i}{1 + 2\lambda_i}$ is positive because

$$\frac{\partial^2}{\partial t_s^2} f_1 = \frac{-4t(1 + 2(s\text{P})^2 t(1 - 2t \cdot t_s)^3)}{(1 + 2s\text{P}(1 + t_s)(1 - 2t \cdot t_s))^3} - \frac{4s\text{P}t(2t + 3t^2 t_s^2 + (1 - 3t \cdot t_s)^2)}{(1 + 2s\text{P}(1 + t_s)(1 - 2t \cdot t_s))^3} \quad (32)$$

and

$$\frac{\partial^2}{\partial t_s^2} f_2 = \frac{-4t(2 + 2(s\text{P})^2 t(1 - 4t \cdot t_s)^3)}{(1 + 2s\text{P}(1 + t_s)(1 - 4t \cdot t_s))^3} - \frac{4s\text{P}t(4t + 12t^2 t_s^2 + (1 - 6t \cdot t_s)^2)}{(1 + 2s\text{P}(1 + t_s)(1 - 4t \cdot t_s))^3} \quad (33)$$

are negative for $t > 0$ and $t_s \in (0, \min\{\frac{1}{4t}, 1\})$, resulting in the negative-semidefinite matrix $\mathbf{G} \frac{\partial^2}{\partial t_s^2} \mathbf{A} \mathbf{G}$. Therefore, the non-zero eigenvalues of $\mathbf{G} \frac{\partial^2}{\partial t_s^2} \mathbf{A} \mathbf{G}$, $\frac{\partial^2}{\partial t_s^2} \lambda_{[r]}$, are negative.

However, the sign of the term $g_{2,t_s}^{(3)}(s, t, t_s)$ is not fixed for $t > 0$ and $t_s \in (0, \min\{\frac{1}{4t}, 1\})$, leading to (31) is not a non-decreasing function with respect to increasing t_s . Consequently, to lower bound $g_{t_s}^{(2)}(s, t, t_s)$, we find a

$$\tilde{T}_s := \arg \inf_{t_s \in (0, \min\{1, 1/4t\})} g_{t_s}^{(2)}(s, t, t_s) \quad (34)$$

such that

$$g_{t_s}^{(2)}(s, t, \tilde{T}_s) \leq g_{t_s}^{(2)}(s, t, t_s), \quad (35)$$

for all $t_s \in (0, \min\{\frac{1}{4t}, 1\})$.

Consequently, from (20), (29), (31), and (35), we conclude that the uniform upper bound of the PUPE for a given t, s_1, s , and any $\hat{d}_{[s]}$ as follows:

$$\begin{aligned} & \mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(t \|\tilde{Z}^n\|^2) \right. \right. \\ & \quad \left. \left. \cdot \mathbb{E} \left[\exp \left(-t \|B_{[s]}^n + X_{[s], \hat{d}_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + \tilde{Z}^n\|^2 \right) \right] \right\} \right] \\ & \leq \frac{\exp(\bar{g}(s, s_1, t, \underline{T}_s))}{T^* \sqrt{2\pi}} \left(g_{t_s}^{(2)}(s, t, \underline{T}_s) \right)^{-\frac{1}{2}} + O \left(\frac{\exp(-n)}{\sqrt{n}} \right), \end{aligned} \quad (36)$$

if there exist $\underline{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ and $\bar{T}_s \in (0, \min\{\frac{1}{4t}, 1\})$ satisfying (5) and (6), respectively.

By applying the same approach to the first term in (19), we have

$$\mathbb{E} \left[\min \left\{ 1, \theta(s) \exp(t \|\tilde{Z}^n\|^2) \right. \right.$$

$$\begin{aligned}
& \cdot \mathbb{E} \left[\exp \left(-t \| X_{[s], d_{[s]}} - \bar{X}_{[s], \hat{d}_{[s]}} + \tilde{Z}^2 \|^2 \right) \right] \\
&= \frac{\exp(g(s, t, T_s))}{T_s(1 - T_s)\sqrt{2\pi}} \left(g_{t_s}^{(2)}(s, t, T_s) \right)^{-\frac{1}{2}} + O \left(\frac{\exp(-n)}{\sqrt{n}} \right), \quad (37)
\end{aligned}$$

if there exists $T_s \in (0, \min\{\frac{1}{4t}, 1\})$ such that $g_{t_s}^{(1)}(s, t, T_s) = 0$. By substituting (19), (36), and (37) into (18), we complete the proof of Theorem 1.

APPENDIX B PROOF OF THEOREM 2

In the following, we apply the RCU bound to express the PUPE defined in Definition 3. For a given $d_{[K_a]}$, the PUPE is upper-bounded as follows:

$$\begin{aligned}
P_{\text{PUPE}} &\leq p_0 + \sum_{S \subseteq [K_a]} \frac{s^{\binom{K_a}{s}}}{K_a} \Pr \left(\bigcup_{\substack{\bar{X}_{[s]} \subseteq f(\mathcal{M} \setminus M_{[K_a]}), \\ \hat{d}_{[K_a]} \in \mathfrak{S}(d_{[K_a]})}} \|Z^n\|^2 \right. \\
&\quad \left. \geq \left\| \tilde{Y}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n - X_{[\bar{s}], \hat{d}_{[\bar{s}]}}^n \right\|^2 \right), \quad (38)
\end{aligned}$$

where $\mathfrak{S}(D^{K_a})$ is the set containing all permutations of $d_{[K_a]}$.

By applying the RCU bound to the tail probability in (38), we have

$$\begin{aligned}
&\Pr \left(\bigcup_{\substack{\bar{X}_{[s]} \subseteq f(\mathcal{M} \setminus M_{[K_a]}), \\ \hat{d}_{[K_a]} \in \mathfrak{S}(d_{[K_a]})}} \|Z^n\|^2 \geq \left\| \tilde{Y}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n - X_{[\bar{s}], \hat{d}_{[\bar{s}]}}^n \right\|^2 \right) \\
&\leq \mathbb{E} \left[\min \left\{ 1, \theta_2(s) \Pr \left(\|Z^n\|^2 \geq \right. \right. \right. \\
&\quad \left. \left. \left\| X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + Z^n \right\|^2 \middle| X_{[K_a]}^n, Z^n \right) \right\} \right] \\
&+ \sum_{\substack{\hat{d}_{[\bar{s}]} \in \mathfrak{S}([\bar{s}], d_{[K_a]}), \\ s_1 \neq 0}} \mathbb{E} \left[\min \left\{ 1, \theta_2(s) \Pr \left(\|Z^n\|^2 \geq \right. \right. \right. \\
&\quad \left. \left. \left\| X_{[s], d_{[s]}}^n - \bar{X}_{[s], \hat{d}_{[s]}}^n + B_{[s]}^n + Z^n \right\|^2 \middle| X_{[K_a]}^n, Z^n \right) \right\} \right], \quad (39)
\end{aligned}$$

where $\theta_2(s) := \binom{M-K_a}{s} s!$ and $\mathfrak{S}([\bar{s}], d_{[K_a]})$ contains all permutations of $K_a - s$ terms selected from $d_{[K_a]}$. The set $\mathfrak{S}([\bar{s}], d_{[K_a]})$ only considers all permutations of $K_a - s$ terms selected from $d_{[K_a]}$ since the permutations of delays of s incorrectly decoded codewords, i.e., $s!$, are calculated in $\theta_2(s)$.

The terms $B_{[s]}^n$ and s_1 are defined in Appendix A. The inequality follows from the RCU bound. Additionally, we express the probability that the receiver matches the delays to correctly decoded codewords ($s_1 = 0$) and the probability that the receiver mismatches the delays to correctly decoded codewords separately.

We upper-bound (39) by using the results from Theorem 1 with the term $\theta_2(s)$ modified from $\theta(s)$. Additionally, for a given $s \in [K_a]$, we upper-bound the number of permutations in the set $\mathfrak{S}([\bar{s}], d_{[K_a]})$ satisfying a given $s_1 \in [K_a - s]$ by $\binom{K_a - s}{s_1} \frac{(s + s_1)!}{s!}$, which completes the proof.

APPENDIX C PROOF OF LEMMA 1

In Lemma 1, the function $q(t_s)$ is convex by assumption, which implies $q^{(1)}(t_s)$ is a non-decreasing function with respect to increasing $t_s \in \mathcal{R}$. Additionally, we have the term $T_s \in \mathcal{R}$ satisfies

$$q^{(1)}(T_s) = \sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i \big|_{t_s=T_s}}{1 + 2\tilde{\lambda}_i}.$$

By finding the functions $q_1(t_s)$ and $q_2(t_s)$ such that

$$q_2(T_s) \leq \sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i \big|_{t_s=T_s}}{1 + 2\tilde{\lambda}_i} \leq q_1(T_s),$$

we can find the term $\bar{T}_s \geq T_s$ by fulfilling $q^{(1)}(\bar{T}_s) = q_1(\bar{T}_s)$ and the term $\underline{T}_s \leq T_s$ by fulfilling $q^{(1)}(\underline{T}_s) = q_2(\underline{T}_s)$.

To proceed, we find the functions $q_1(t_s)$ and $q_2(t_s)$. We derive $q_1(t_s)$ and $q_2(t_s)$ for $\underline{\varrho} := \min_{i \in [n]} \{\frac{\partial}{\partial t_s} A(t_s)_{i,i}\} \geq 0$, $\underline{\varrho} < 0 < \bar{\varrho} := \max_{i \in [n]} \{\frac{\partial}{\partial t_s} A(t_s)_{i,i}\}$, and $\bar{\varrho} < 0$, separately.

We first derive $q_1(t_s)$ for $\underline{\varrho} \geq 0$ as follows:

$$\sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i}{1 + 2\tilde{\lambda}_i} \leq \sum_{i=1}^r \frac{\partial}{\partial t_s} \tilde{\lambda}_i = \text{Tr} \left(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s} \right),$$

where the first inequality is because $\tilde{\lambda}_{[r]}$ are non-zero eigenvalues of a positive-semidefinite matrix, and the second equality follows from the fact that the sum of eigenvalues is the trace of the matrix. For $\underline{\varrho} < 0 < \bar{\varrho}$, we have

$$\sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i}{1 + 2\tilde{\lambda}_i} \leq \sum_{i \in \mathfrak{R}^+} \frac{\partial}{\partial t_s} \tilde{\lambda}_i \leq \bar{\varrho} \cdot \text{Tr}(\mathbf{K}),$$

where \mathfrak{R}^+ is a set containing indices of positive eigenvalues. The first inequality follows $1 + 2\tilde{\lambda}_i \geq 1$ and the removal of negative terms. The second inequality follows from the definition of $\bar{\varrho}$. For $\bar{\varrho} \leq 0$, we have

$$\sum_{i=1}^r \frac{\frac{\partial}{\partial t_s} \tilde{\lambda}_i}{1 + 2\tilde{\lambda}_i} \leq \frac{\sum_{i=1}^r \frac{\partial}{\partial t_s} \tilde{\lambda}_i}{1 + 2\Lambda} = \frac{\text{Tr}(\mathbf{K}\mathbf{A}(t_s))}{1 + 2\Lambda},$$

where the first inequality follows the definition of Λ . The second equality follows because the sum of eigenvalues is the matrix trace. Therefore, we have

$$q_1(t_s) := \begin{cases} \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}), & \text{if } \underline{\varrho} \geq 0 \\ \bar{\varrho} \cdot \text{Tr}(\mathbf{K}), & \text{if } \underline{\varrho} < 0 < \bar{\varrho} \\ \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}) / (1 + 2\Lambda), & \text{o.w.,} \end{cases}$$

By using the same approach, we have

$$q_2(t_s) := \begin{cases} \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}) / (1 + 2\Lambda), & \text{if } \underline{\varrho} \geq 0 \\ \underline{\varrho} \cdot \text{Tr}(\mathbf{K}), & \text{if } \underline{\varrho} < 0 < \bar{\varrho} \\ \text{Tr}(\mathbf{K} \frac{\partial \mathbf{A}}{\partial t_s}), & \text{o.w.,} \end{cases}$$

Consequently, we conclude the conditions of \bar{T}_s and \underline{T}_s are $q^{(1)}(\bar{T}_s) = q_1(\bar{T}_s)$ and $q^{(1)}(\underline{T}_s) = q_2(\underline{T}_s)$, respectively, which completes the proof.

REFERENCES

- [1] S.-C. Lin, T.-H. Chang, E. Jorswieck, and P.-H. Lin, *Information theory, mathematical optimization, and their crossroads in 6G system design*. Springer, 2023.
- [2] A. El Gamal and Y.-H. Kim, *Network Information Theory*. Cambridge University Press, 2011.
- [3] Y. Polyanskiy, "A perspective on massive random-access," in *2017 IEEE International Symposium on Information Theory (ISIT)*, 2017, pp. 2523–2527.
- [4] X. Chen, T.-Y. Chen, and D. Guo, "Capacity of Gaussian many-access channels," *IEEE Transactions on Information Theory*, vol. 63, no. 6, pp. 3516–3539, 2017.
- [5] R. C. Yavas, V. Kostina, and M. Effros, "Random access channel coding in the finite blocklength regime," *IEEE Transactions on Information Theory*, vol. 67, no. 4, pp. 2115–2140, 2021.
- [6] —, "Gaussian multiple and random access channels: Finite-blocklength analysis," *IEEE Transactions on Information Theory*, vol. 67, no. 11, pp. 6983–7009, 2021.
- [7] O. Ordentlich and Y. Polyanskiy, "Low complexity schemes for the random access Gaussian channel," in *2017 IEEE International Symposium on Information Theory (ISIT)*, 2017, pp. 2528–2532.
- [8] T. Cover, R. McEliece, and E. Posner, "Asynchronous multiple-access channel capacity," *IEEE Transactions on Information Theory*, vol. 27, no. 4, pp. 409–413, 1981.
- [9] H. Ebrahimzadeh Saffar, M. Badii Khuzani, and P. Mitran, "Time-asynchronous Gaussian multiple access relay channel with correlated sources," *IEEE Transactions on Information Theory*, vol. 62, no. 1, pp. 309–321, 2016.
- [10] K. Andreev, S. S. Kowshik, A. Frolov, and Y. Polyanskiy, "Low complexity energy efficient random access scheme for the asynchronous fading MAC," in *2019 IEEE 90th Vehicular Technology Conference (VTC2019-Fall)*, 2019, pp. 1–5.
- [11] S. S. Kowshik, K. Andreev, A. Frolov, and Y. Polyanskiy, "Short-packet low-power coded access for massive MAC," in *2019 53rd Asilomar Conference on Signals, Systems, and Computers*, 2019, pp. 827–832.
- [12] X. Chen, L. Liu, D. Guo, and G. W. Wornell, "Asynchronous massive access and neighbor discovery using OFDMA," *IEEE Transactions on Information Theory*, vol. 69, no. 4, pp. 2364–2384, 2023.
- [13] S. Derya, S.-C. Yu, H.-W. Young, E. A. Jorswieck, P.-H. Lin, and S.-C. Lin, "Joint delay and user activity detection in asynchronous massive access," in *2024 33rd Wireless and Optical Communications Conference (WOCC)*, 2024, pp. 175–179.
- [14] J.-S. Wu, P.-H. Lin, M. A. Mross, and E. A. Jorswieck, "Worst-case per-user error bound for asynchronous unsourced multiple access," in *IEEE International Symposium on Information Theory, ISIT 2024, Athens, Greece, July 7-12, 2024*. IEEE, 2024, pp. 3207–3212.
- [15] Y. Polyanskiy, H. V. Poor, and S. Verdú, "Channel coding rate in the finite blocklength regime," *IEEE Trans. Inf. Theory*, vol. 56, no. 5, pp. 2307–2359, 2010.
- [16] J. Jensen, *Saddlepoint approximations*. Clarendon Press Oxford, 1995, oxford Science Publications.
- [17] A. Martínez and A. G. i Fàbregas, "Saddlepoint approximation of random-coding bounds," in *2011 Information Theory and Applications Workshop*, 2011, pp. 1–6.
- [18] S. Provost and A. Mathai, *Quadratic Forms in Random Variables: Theory and Applications*, ser. Statistics : textbooks and monographs. Marcel Dekker, 1992.
- [19] R. A. Horn and C. R. Johnson, *Matrix Analysis*. Cambridge University Press, 1985.