

# The sinusoid and the phasor

Kushal Shah\*

*Faculty of Mathematics and Computer Science,  
Weizmann Institute of Science, POB 26, Rehovot 76100, Israel.*

Harishankar Ramachandran†

*Department of Electrical Engineering, Indian Institute of Technology Madras, Chennai 600036, India.*

Mathieu equation is widely used to study several natural phenomenon. In this paper, we show that replacing the sinusoid in the Mathieu equation with a phasor can lead to solutions that behave in a totally different way. Solutions of Mathieu equation are either bounded or grow unboundedly at an exponential rate. Solutions of this new equation are always unbounded and grow linearly with time.

Linear differential equations with periodic coefficients have applications in many areas like Plasma Physics [1, 2] and Condensed Matter Physics [3]. The general form for such an equation is

$$\dot{\mathbf{x}} = \mathbf{A}(t)\mathbf{x} \quad (1)$$

where  $\mathbf{x}$  is a vector and  $\mathbf{A}(t)$  is an  $n \times n$  matrix with time-periodic coefficients. For  $n = 2$ , a very important example of such a system of equations is the Mathieu equation [4, 5],

$$\ddot{x} = 2qx \cos \omega t \quad (2)$$

which can be written in the matrix form as

$$\frac{d}{dt} \begin{pmatrix} x_1 \\ x_2 \end{pmatrix} = \begin{pmatrix} 0 & 1 \\ 2q \cos \omega t & 0 \end{pmatrix} \begin{pmatrix} x_1 \\ x_2 \end{pmatrix} \quad (3)$$

where  $q$  is an arbitrary constant and  $\omega$  is the oscillation frequency of the field.

In many problems of interest in physics and engineering, the sinusoid is replaced by a phasor since it often makes the analysis easier. If we replace the sinusoid in Eq. (2) by a phasor, we get

$$\frac{d^2 y}{dt^2} = 2qy e^{j\omega t} \quad (4)$$

where  $y$  is a complex function of a real argument,  $t$ . It must be noted that Eq. (4) can also be written in form of Eq. (1) with  $n = 4$ . Transforming to the variable,  $\tau = \sqrt{\frac{8q}{\omega^2}} e^{j\omega t/2}$ , Eq. (4) becomes

$$\tau \frac{d^2 y}{d\tau^2} + \frac{dy}{d\tau} + \tau y = 0 \quad (5)$$

which is the well known Bessel equation [4]. The transformation,  $\tau = \sqrt{\frac{8q}{\omega^2}} e^{j\omega t/2}$ , used to get Eq. (5) is not one-to-one, but as we will see later, the solutions have a branch-cut, which permits the use of this transformation leading to non-periodic solutions. Equation (5) has two linearly independent solutions and any general solution can be written as a linear combination of these,

$$y(\tau) = a\phi(\tau) + b\psi(\tau) \quad (6)$$

where  $\phi, \psi$  are Bessel functions,

$$\phi(\tau) = J_0 \left( \sqrt{\frac{8q}{\omega^2}} e^{j\omega t/2} \right) \quad \text{and} \quad \psi(\tau) = Y_0 \left( \sqrt{\frac{8q}{\omega^2}} e^{j\omega t/2} \right) \quad (7)$$

The velocity of the particle at any instant of time is given by,

$$v(t) = a\phi'(t) + b\psi'(t) \quad (8)$$

---

\*Electronic address: kushal.shah@weizmann.ac.il

†Electronic address: hsr@ee.iitm.ac.in

where, ' represents differentiation w.r.t.  $t$ .

In order to find the path of the particles in phase space, we need to evaluate the bessel functions and their derivatives. The derivative of  $J_0$  is  $-J_1$  and that of  $Y_0$  is  $-Y_1$ . Though all these functions are analytic for complex arguments,  $Y_0$  and  $Y_1$  have a branch cut.  $Y_0, Y_1$  can be evaluated using the expression [6]

$$Y_0(\tau) = \frac{2}{\pi} \left[ \left( C + \log \frac{\tau}{2} \right) J_0(\tau) + 2 \sum_{n=1}^N (-1)^{n-1} \frac{J_{2n}(\tau)}{n} \right] \quad (9)$$

and

$$Y_1(\tau) = \frac{2}{\pi} \left[ \left( C + \log \frac{\tau}{2} \right) J_1(\tau) - \frac{1}{z} J_0(\tau) + \sum_{n=1}^N \frac{(-1)^n}{n} (J_{2n-1}(\tau) - J_{2n+1}(\tau)) \right] \quad (10)$$

where,  $C = 0.577215665$  is the Euler's constant. Although  $Y_0(\tau)$  and  $Y_1(\tau)$  seem to be a periodic functions of  $t$ , the condition that  $y$  and  $v$  must be continuous and differentiable imposes certain restrictions. We need to take special care of the branch cut in  $\log \frac{\tau}{2}$  term. In our problem,

$$\tau = \sqrt{\frac{8q}{\omega^2}} e^{j\omega t/2} \quad (11)$$

which implies

$$\log \frac{\tau}{2} = \log \sqrt{\frac{4q}{\omega^2}} + \frac{j\omega t}{2} \quad (12)$$

From Eq. (12), it can be seen that the continuity and differentiability condition forces  $\psi(t)$  to be growing in time. Equation (12) predicts this unbounded growth with time to be linear, whereas unbounded solutions of the Mathieu equation, Eq. (2), would have exponential-in-time growth. Also, Eq. (4) has no bounded solutions for any value of  $q$ , whereas all solutions of Eq. (2) are bounded if  $|q|$  is below a certain critical threshold.

One of the authors (KS) would like to acknowledge support of the Israel Science Foundation and the Minerva Foundation.

- 
- [1] W. Paul, Rev. Mod. Phys. 62, 531 (1990)
  - [2] K. Shah and H. S. Ramachandran, Phys. Plasmas 15, 062303 (2008)
  - [3] Charles Kittel, Introduction to Solid State Physics (Wiley, New York, 1996)
  - [4] A. Abramowitz and A. Stegun, Handbook of Mathematical Functions (Dover, New York, 1964)
  - [5] N.W. McLachlan, Theory and Application of Mathieu Functions (Dover, New York, 1964)
  - [6] M. C. Gray, Comm. ACM 4, 169 (1961)