

Completion of the integrable coupling systems

Yubin Yao[†], Chunxia Li[‡] and Shenfeng Shen^{§a)}

[†] *Department of Applied Mathematics, China Agricultural University, Beijing, 100083, PR China*

[‡] *School of Mathematical and Sciences, Capital Normal University, Beijing, 100048, PR China*

[§] *Department of Applied Mathematics, Zhejiang University of Technology, Hangzhou, 310023, PR China*

Abstract In this paper, we proposed an procedure to construct the completion of the integrable system by adding a perturbation to the generalized matrix problem, which can be used to continuous integrable couplings, discrete integrable couplings and super integrable couplings. As example, we construct the completion of the Kaup-Newell (KN) integrable coupling, the Wadati-Konno-Ichikawa (WKI) integrable couplings, vector Ablowitz-Kaup-Newell-Segur (vAKNS) integrable couplings, the Volterra integrable couplings, Dirac type integrable couplings and NLS-mKdV type integrable couplings.

Keywords: completion; matrix spectral problem; integrable couplings; Hamiltonian structure

PACS: 02.30.Ik

1 Introduction

In 1968, Lax proposed the Lax pair approach for studying the KdV equation[1]. A Lax pair formulation is generally equivalent to a zero curvature equation [2]. An system of the partial differential equations (PDEs) or differential-difference equations (DDEs) is said to be integrable, if it is generated from a continuous zero curvature equation [3]

$$U_t - V_x + [U, V] = 0, \tag{1}$$

^{a)}mathssf@zjut.edu.cn

or discrete zero curvature equation

$$U_t + UV - (EV)U = 0. \quad (2)$$

where the squares matrices, U and V , are called a Lax pair, often comes from a matrix loop algebra[4]. How to seek for new integrable system is an important and interesting topic in the study of mathematical physics. Integrable couplings, which are the integrable coupled systems containing given system as their sub-systems, have much richer mathematical structures, such as Hamiltonian structure, infinitely many symmetries and conservation laws of triangular form [5]-[15]. So integrable couplings becomes one of the important topics in the field of integrable systems. At present, based on the zero curvature presentation, a few approaches have been proposed for constructing integrable couplings, including perturbation, enlarging spectral problem and creating semi-direct sum of the Lie algebra. Mathematically, a continuous or discrete integrable system reads

$$u_t = K(u) = K(u, u_x, \dots)(or K(u, Eu, E^{-1}u)) = J \frac{\delta \mathcal{H}_1}{\delta u}, \quad (3)$$

the integrable couplings of integrable system (3) is a triangular integrable system of the following form [5]

$$\begin{cases} u_t = K(u), \\ v_t = S(u, v). \end{cases} \quad (4)$$

An example of the integrable couplings is the first-order pertubation[5]

$$\begin{cases} u_t = K(u), \\ v_t = K'[v], \end{cases} \quad (5)$$

where K' is the Gateaux derivative defined by $K'(u)[v] = \frac{\partial}{\partial \varepsilon} K(u + \varepsilon v, u_x + \varepsilon v_x, \dots)$.

Non-semisimple Lie algebra can decomposed into the semi-direct sum of the semisimple Lie algebra and solvable, so semi-direct sum of Lie algebra lay a foundation for constructing integrable couplings. Now we consider the non-semisimple Lie algebra \bar{g} consisting of the square

matrices $M(U, U_1)$ in the block form, i. e.

$$M(U, U_1) = \begin{bmatrix} U & U_1 \\ 0 & U \end{bmatrix}, \quad (6)$$

where U and U_1 are square matrices of the same order. This Lie algebra \bar{g} possess the semi-direct sum decomposition $\bar{g} = g \oplus g_c$, where $g = M(U, 0)$ is semisimple and $g_c = M(0, U_1)$ is solvable. The notation of semi-direct sum implies that the subalgebra g and g_c satisfy $[g, g_c] \subseteq g_c$, with $[\cdot, \cdot]$ denoting Lie bracket of \bar{g} . Also the closure property between g and g_c under the matrix multiplication is required, that is to say $gg_c, g_cg \subseteq g_c$.

In our paper, based on the non-semisimple Lie algebra \bar{g} , we propose a method to construct generalized integrable coupled system

$$\begin{cases} u_t = \bar{K}(u, v), \\ v_t = \bar{S}(u, v), \end{cases} \quad (7)$$

which can be reduced to the standard integrable couplings (5). In this sense, we call the system (58) "completion of the integrable couplings ". In this paper, we will apply this method to continuous integrable couplings, discrete integrable couplings and super integrable couplings. Concretely, we construct the completion of the Kaup-Newell (KN) integrable coupling, the Wadati-Konno-Ichikawa (WKI) integrable couplings, vector Ablowitz-Kaup-Newell-Segur (vAKNS) integrable couplings, the Volterra integrable couplings, Dirac type integrable couplings and NLS-mKdV type integrable couplings. What's more, we take the complete integrable system of the KN integrable coupling as an example to show that its Hamiltonian structure can be constructed by variable identity.

2 Completion of the continuous integrable couplings

2.1 Completion of the KN integrable couplings

2.1.1 Complete integrable system of the KN integrable couplings

Consider the generalized spectral problem

$$\phi_x = \bar{U}\phi, \quad u = \begin{bmatrix} p \\ q \\ r \\ s \end{bmatrix}, \quad \phi = \begin{bmatrix} \phi_1 \\ \phi_2 \\ \phi_3 \\ \phi_4 \end{bmatrix}, \quad (8)$$

where the spectral matrix \bar{U} is chosen as

$$\bar{U} = \begin{bmatrix} U & U_1 \\ 0 & U \end{bmatrix} = \left[\begin{array}{cc|cc} \lambda^2 + h & \lambda p & 0 & \lambda r \\ \lambda q & -\lambda^2 - h & \lambda s & 0 \\ \hline 0 & 0 & \lambda^2 + h & \lambda \\ 0 & 0 & \lambda q & -\lambda^2 - h \end{array} \right], \quad h = \varepsilon(ps + qr) \quad (9)$$

here a nonlinear perturbation term h is added to the spectral matrix. When $\varepsilon = 0$, it reduces to the case of KN integrable couplings[16, 17]. From the above spectral matrix, we can work out the complete system of the KN integrable couplings.

Now let us assume that W has the following form

$$\bar{W} = \begin{bmatrix} W & W_1 \\ 0 & W \end{bmatrix} = \left[\begin{array}{cc|cc} a & b & f & d \\ c & -a & g & -f \\ \hline 0 & 0 & a & b \\ 0 & 0 & c & -a \end{array} \right] \quad (10)$$

and solving the stationary zero curvature equation $\overline{W}_x = [\overline{U}, \overline{W}]$ gives

$$\begin{cases} a_x = \lambda pc - \lambda qb, \\ b_x = 2\lambda^2 b + 2hb - 2\lambda pa, \\ c_x = -2\lambda^2 c - 2hc + 2\lambda qa, \\ d_x = 2\lambda^2 d - 2\lambda ar - 2\lambda fp + 2hd, \\ f_x = -\lambda bs + \lambda rc - \lambda dq + \lambda gp, \\ g_x = -2\lambda^2 g + 2\lambda as + 2\lambda qf - 2gh. \end{cases} \quad (11)$$

Further, let a, b, c possess the Laurent expansions:

$$\begin{aligned} a &= \sum_{i \geq 0} a_i \lambda^{-2i}, \quad b = \sum_{i \geq 0} b_i \lambda^{-2i-1}, \quad c = \sum_{i \geq 0} c_i \lambda^{-2i-1}, \\ f &= \sum_{i \geq 0} f_i \lambda^{-2i}, \quad d = \sum_{i \geq 0} d_i \lambda^{-2i-1}, \quad g = \sum_{i \geq 0} g_i \lambda^{-2i-1}. \end{aligned}$$

Equivalently, the system (11) leads to the recursion relations

$$\begin{cases} a_{ix} = pc_i - qb_i, \\ b_{i+1} = \frac{1}{2}b_{ix} + pa_{i+1} - hb_i, \\ c_{i+1} = -\frac{1}{2}c_{ix} + qa_{i+1} - hc_i, \\ d_{i+1} = \frac{1}{2}d_{ix} + ra_{i+1} + pf_{i+1} - hd_i, \quad i \geq 0 \\ f_{ix} = -sb_i + rc_i - qd_i + pg_i, \\ g_{i+1} = -\frac{1}{2}g_{ix} + sa_{i+1} + qf_{i+1} - hg_i. \end{cases} \quad (12)$$

upon taking the initial data

$$a_0 = 1, \quad b_0 = p, \quad c_0 = q, \quad d_0 = r, \quad g_0 = s, \quad f_0 = 1.$$

To guarantee the uniqueness of $\{a_i, b_i, c_i, d_i, f_i, g_i | i \geq 1\}$, we impose the conditions on constants of integration.

$$a_i |_{u=0} = b_i |_{u=0} = c_i |_{u=0} = d_i |_{u=0} = f_i |_{u=0} = g_i |_{u=0}.$$

Thus, the first two sets can be listed as follows:

$$a_1 = -\frac{pq}{2}, \quad b_1 = \frac{1}{2}p_x - \frac{1}{2}p^2q - \varepsilon(ps + qr)p, \quad c_1 = -\frac{1}{2}q_x - \frac{1}{2}pq^2 - \varepsilon(ps + qr)q, \quad f_1 = -\frac{1}{2}(ps + qr),$$

$$\begin{aligned}
d_1 &= \frac{1}{2}r_x - pqr - \frac{1}{2}p^2s - \varepsilon(ps + qr)r, \quad g_1 = -\frac{1}{2}s_x - pqs - \frac{1}{2}q^2r - \varepsilon(ps + qr)s, \\
a_2 &= \frac{1}{4}(pq_x - qp_x) + \frac{3}{8}p^2q^2 + \varepsilon(ps + qr)pq, \\
b_2 &= \frac{1}{4}p_{xx} - \left(\frac{3}{4}qp + \varepsilon(ps + qr)\right)p_x + \frac{3}{8}p^3q^2 + \frac{3}{2}\varepsilon(ps + qr)p^2q + \varepsilon^2(ps + qr)^2p, \\
c_2 &= \frac{1}{4}q_{xx} + \left(\frac{3}{4}qp + \varepsilon(ps + qr)\right)q_x + \frac{3}{8}q^3p^2 + \frac{3}{2}\varepsilon(ps + qr)pq^2 + \varepsilon^2(ps + qr)^2q, \\
f_2 &= \frac{1}{4}(ps_x - sp_x - qr_x + rq_x) + \frac{3}{4}(sqq^2 + prq^2) + \varepsilon(ps + qr)^2, \\
d_2 &= \frac{1}{4}r_{xx} - \frac{3}{4}(spp_x + rqp_x + pqr_x) - \varepsilon r_x + \frac{3}{4}sqp^3 + \frac{9}{8}rp^2q^2 + \varepsilon(ps + qr)\left(\frac{3}{2}p^2s + 3rpq\right) + \varepsilon^2(ps + qr)^2r \\
g_2 &= \frac{1}{4}s_{xx} + \frac{3}{4}(pqs_x + spq_x + rqq_x) + \varepsilon s_x + \frac{3}{4}rqp^3 + \frac{9}{8}sp^2q^2 + \varepsilon(ps + qr)\left(\frac{3}{2}q^2r + 3spq\right) + \varepsilon^2(ps + qr)^2s
\end{aligned}$$

Noting

$$V^{[m]} = \lambda(\lambda^{2m+1}W)_+ + \Delta_m, \quad m \geq 0, \quad (13)$$

$$\text{where the modification term } \Delta_m = \begin{bmatrix} \delta_m & 0 & 0 & 0 \\ 0 & -\delta_m & 0 & 0 \\ 0 & 0 & \delta_m & 0 \\ 0 & 0 & 0 & -\delta_m \end{bmatrix}, \quad \delta_m \text{ is undetermined function and}$$

P_+ denotes the polynomial part of P , the corresponding zero curvature equations

$$\bar{U}_{t_m} - V_x^{[m]} + [\bar{U}, V^{[m]}] = 0, \quad m \geq 0, \quad (14)$$

give rise to a hierarchy

$$\begin{cases} p_t = 2(-b_{m+1} + pa_{m+1} + p\delta_m), \\ q_t = 2(c_{m+1} - qa_{m+1} - q\delta_m), \quad m \geq 0. \\ r_t = 2(-d_{m+1} + ra_{m+1} + pf_{m+1} + r\delta_m), \\ s_t = 2(g_{m+1} - sa_{m+1} - qf_{m+1} - s\delta_m), \\ h_t = \delta_{mx}. \end{cases} \quad (15)$$

Based on (12) and (15), we can have

$$\delta_{mx} = h_t = \varepsilon(p_t s + p s_t + q_t r + q r_t)$$

$$\begin{aligned}
&= \varepsilon[2s(-b_{m+1} + pa_{m+1} + p\delta_m) + 2p(g_{m+1} - sa_{m+1} - qf_{m+1} - s\delta_m) \\
&\quad + 2r(c_{m+1} - qa_{m+1} - q\delta_m) + 2q(-d_{m+1} + ra_{m+1} + pf_{m+1} + r\delta_m)] \\
&= 2\varepsilon(-sb_{m+1} + pg_{m+1} + rc_{m+1} - qd_{m+1}) = 2\varepsilon f_{m+1,x}.
\end{aligned}$$

So, we choose that $\delta_m = 2\varepsilon f_{m+1}$, and generate the complete system of the KN integrable couplings:

$$\begin{bmatrix} p_t \\ q_t \\ r_t \\ s_t \end{bmatrix} = \begin{bmatrix} 2(-b_{m+1} + pa_{m+1} + 2\varepsilon p f_{m+1}) \\ 2(c_{m+1} - qa_{m+1} - 2\varepsilon q f_{m+1}) \\ 2(-d_{m+1} + ra_{m+1} + pf_{m+1} + 2\varepsilon r f_{m+1}), \\ 2(g_{m+1} - sa_{m+1} - qf_{m+1} - 2\varepsilon s f_{m+1}) \end{bmatrix}, \quad m \geq 0. \quad (16)$$

A nonlinear equation in the above new system is given

$$\begin{aligned}
p_t &= -\frac{1}{2}p_{xx} + \left(\frac{1}{2}p^2 - \varepsilon pr\right)q_x + (pq - \varepsilon ps + 2\varepsilon(ps + qr))p_x - \varepsilon pqr_x + \varepsilon p^2 s_x - \varepsilon(ps + qr)p^2 q \\
&\quad + \varepsilon(3p^2 q^2 r + p^3 sq) + \varepsilon^2(ps + qr)p^2 s - \varepsilon^2(ps + qr)^2 p, \\
q_t &= \frac{1}{2}q_{xx} + (q^2 + \varepsilon qs)p_x + \left(\frac{1}{2}pq - \varepsilon qr + 2\varepsilon(ps + qr)\right)q_x - \varepsilon pq s_x + \varepsilon q^2 r_x - 3\varepsilon pq(q^2 r + pqs) \\
&\quad - 4\varepsilon^2(ps + qr)^2 - \frac{3}{4}q^3 p^2 - \varepsilon(ps + qr)pq^2 + 2\varepsilon^2(ps + qr)^2 q, \\
r_t &= -\frac{1}{2}r_{xx} + (ps + qr + \varepsilon rs)p_x + (pq + 2\varepsilon(2ps + 3qr))r_x + \left(\frac{1}{2}p^2 - \varepsilon pr\right)s_x + (pr - \varepsilon r^2)q_x \\
&\quad - 3\varepsilon pqr(qr + ps) - \varepsilon(ps + qr)p(ps + 2qr) - 6\varepsilon^2(ps + qr)^2 r, \\
s_t &= \frac{1}{2}s_{xx} + (qs + \varepsilon s^2)p_x + (ps + qr - \varepsilon sr)q_x + \left(\frac{1}{2}q^2 + \varepsilon qs\right)r_x + (pq + \varepsilon(ps + 2qr))s_x \\
&\quad - 3\varepsilon pqs(qr + ps) - 2\varepsilon^2(ps + qr)^2 s + \varepsilon(ps + qr)q(2ps + qr).
\end{aligned}$$

2.1.2 Hamiltonian structure of the complete system

In the section, we will construct the Hamiltonian structure for the complete system (16) by using the variational identity[18]

$$\frac{\delta}{\delta u} \int tr(W \frac{\partial U_1}{\partial \lambda} + W_1 \frac{\partial U}{\partial \lambda}) dx = \lambda^{-\gamma} \frac{\partial}{\partial \lambda} \lambda^\gamma tr(W \frac{\partial U_1}{\partial \bar{u}} + W_1 \frac{\partial U}{\partial \bar{u}}) \quad (17)$$

Direct computation gives

$$\begin{aligned} \text{tr}(W \frac{\partial U_1}{\partial \lambda} + W_1 \frac{\partial U}{\partial \lambda}) &= 4f\lambda + sb + rc + qd + pg, \quad \text{tr}(W \frac{\partial U_1}{\partial p} + W_1 \frac{\partial U}{\partial p}) = 2\epsilon s f + g\lambda, \\ \text{tr}(W \frac{\partial U_1}{\partial q} + W_1 \frac{\partial U}{\partial q}) &= 2\epsilon r f + d\lambda, \quad \text{tr}(W \frac{\partial U_1}{\partial r} + W_1 \frac{\partial U}{\partial r}) = 2\epsilon q f + c\lambda, \quad \text{tr}(W \frac{\partial U_1}{\partial s} + W_1 \frac{\partial U}{\partial s}) = 2\epsilon p f + b\lambda. \end{aligned}$$

Substitute the above results into the variational identity (17), we have

$$\frac{\delta}{\delta \bar{u}} \int (4f\lambda + sb + rc + qd + pg) dx = \lambda^{-\gamma} \frac{\partial}{\partial \lambda} \lambda^\gamma \begin{bmatrix} 2\epsilon s f + g\lambda \\ 2\epsilon r f + d\lambda \\ 2\epsilon q f + c\lambda, \\ 2\epsilon p f + b\lambda \end{bmatrix}, \quad (18)$$

Balancing coefficients of the λ^{-2m-3} gives

$$\frac{\delta}{\delta \bar{u}} \int (4f_{m+2} + sb_{m+1} + rc_{m+1} + qd_{m+1} + pg_{m+1}) dx = (\gamma - 2m - 2) \begin{bmatrix} 2\epsilon s f_{m+1} + g_{m+1} \\ 2\epsilon r f_{m+1} + d_{m+1} \\ 2\epsilon q f_{m+1} + c_{m+1}, \\ 2\epsilon p f_{m+1} + b_{m+1} \end{bmatrix}. \quad (19)$$

Consider the case of $m = 0$, we have $\gamma = 0$. Thus, we have

$$\frac{\delta}{\delta \bar{u}} \int -\frac{4f_{m+2} + sb_{m+1} + rc_{m+1} + qd_{m+1} + pg_{m+1}}{2m+2} dx = \begin{bmatrix} 2\epsilon s f_{m+1} + g_{m+1} \\ 2\epsilon r f_{m+1} + d_{m+1} \\ 2\epsilon q f_{m+1} + c_{m+1}, \\ 2\epsilon p f_{m+1} + b_{m+1} \end{bmatrix}. \quad (20)$$

The Hamiltonian structure can be given

$$u_{t_m} = K_m = J \frac{\delta \mathcal{H}_m}{\delta u}, \quad (21)$$

with a Hamiltonian operator

$$J = \begin{bmatrix} 0 & 0 & -2p\partial^{-1}p & 2 + 2p\partial^{-1}q \\ 0 & 0 & -2 + 2q\partial^{-1}p & -2q\partial^{-1}q \\ -2p\partial^{-1}p & 2 + 2p\partial^{-1}q & -2r\partial^{-1}p - 2p\partial^{-1}r & 2r\partial^{-1}q + 2p\partial^{-1}s \\ -2 + 2q\partial^{-1}p & -2q\partial^{-1}q & 2s\partial^{-1}p + 2q\partial^{-1}r & -2s\partial^{-1}q - 2q\partial^{-1}s \end{bmatrix},$$

and the Hamiltonian functions

$$\mathcal{H}_m = \int -\frac{4f_{m+2} + sb_{m+1} + rc_{m+1} + qd_{m+1} + pg_{m+1}}{2m+2} dx.$$

Using recursion relations (12), we can obtain the recursion operator $\Phi = (\Phi_{ij})_{4 \times 4}$ through

$$\begin{bmatrix} 2\epsilon s f_{m+1} + g_{m+1} \\ 2\epsilon r f_{m+1} + d_{m+1} \\ 2\epsilon q f_{m+1} + c_{m+1} \\ 2\epsilon p f_{m+1} + b_{m+1} \end{bmatrix} = \begin{bmatrix} \Phi_{11} & \Phi_{12} & \Phi_{13} & \Phi_{14} \\ \Phi_{21} & \Phi_{22} & \Phi_{23} & \Phi_{24} \\ \Phi_{31} & \Phi_{32} & \Phi_{33} & \Phi_{34} \\ \Phi_{41} & \Phi_{42} & \Phi_{43} & \Phi_{44} \end{bmatrix} \begin{bmatrix} 2\epsilon s f_m + g_m \\ 2\epsilon r f_m + d_m \\ 2\epsilon q f_m + c_m \\ 2\epsilon p f_m + b_m \end{bmatrix}$$

with

$$\Phi_{11} = -(\epsilon s \partial^{-1} p + \frac{1}{2} + \frac{1}{2} p q) \partial - (2\epsilon s \partial^{-1} p + 1 + p q) h + \Xi_1 \partial^{-1} p,$$

$$\Phi_{12} = -(\epsilon s \partial^{-1} q + \frac{1}{2} q^2) \partial + (2\epsilon s \partial^{-1} q + q^2) h - \Xi_1 \partial^{-1} q,$$

$$\Phi_{13} = -(\epsilon s \partial^{-1} r + \frac{1}{2} s \partial^{-1} p + \frac{1}{2} q r) \partial - (2\epsilon s \partial^{-1} r + s \partial^{-1} p + q r) h + \Xi_1 \partial^{-1} r,$$

$$\Phi_{14} = -(\epsilon s \partial^{-1} s + \frac{1}{2} s \partial^{-1} q + \frac{1}{2} q s) \partial + (2\epsilon s \partial^{-1} s + s \partial^{-1} q + q s) h - \Xi_1 \partial^{-1} s,$$

$$\Phi_{21} = -(\epsilon r \partial^{-1} p + \frac{1}{2} p \partial^{-1} p) \partial - (2\epsilon r \partial^{-1} p + p \partial^{-1} p) h + \Xi_2 \partial^{-1} p,$$

$$\Phi_{22} = -(\epsilon r \partial^{-1} q + \frac{1}{2} p \partial^{-1} q) \partial + (2\epsilon r \partial^{-1} q + p \partial^{-1} q) h - \Xi_2 \partial^{-1} q,$$

$$\Phi_{23} = -(\epsilon r \partial^{-1} r + \frac{1}{2} q \partial^{-1} p + \frac{1}{2} p \partial^{-1} r) \partial - (2\epsilon r \partial^{-1} r + q \partial^{-1} p + p \partial^{-1} r) h + \Xi_2 \partial^{-1} r,$$

$$\Phi_{24} = -(\epsilon r \partial^{-1} s + \frac{1}{2} q \partial^{-1} q + \frac{1}{2} p \partial^{-1} s) \partial + (2\epsilon r \partial^{-1} s + q \partial^{-1} q + p \partial^{-1} s) h - \Xi_2 \partial^{-1} s,$$

$$\Phi_{31} = -(\epsilon q \partial^{-1} p \partial + 2\epsilon q \partial^{-1} p h + \Xi_3 \partial^{-1} p),$$

$$\Phi_{32} = -(\epsilon q \partial^{-1} q \partial + 2\epsilon q \partial^{-1} q h - \Xi_3 \partial^{-1} q),$$

$$\Phi_{33} = -(\epsilon q \partial^{-1} r + \frac{1}{2} q \partial^{-1} p + \frac{1}{2}) \partial - (2\epsilon q \partial^{-1} r + q \partial^{-1} p + 1) h - \Xi_3 \partial^{-1} r,$$

$$\Phi_{34} = -(\epsilon q \partial^{-1} s + \frac{1}{2} q \partial^{-1} q) \partial - (2\epsilon q \partial^{-1} s + q \partial^{-1} q) h - \Xi_3 \partial^{-1} s,$$

$$\Phi_{41} = -(\epsilon p \partial^{-1} p \partial - 2\epsilon p \partial^{-1} p h + \Xi_4 \partial^{-1} p),$$

$$\Phi_{42} = -(\epsilon p \partial^{-1} q \partial + 2\epsilon p \partial^{-1} q h - \Xi_4 \partial^{-1} q),$$

$$\begin{aligned}\Phi_{43} &= -(\varepsilon p \partial^{-1} r + \frac{1}{2} p \partial^{-1} p) \partial - (2\varepsilon p \partial^{-1} r + p \partial^{-1} p) h + \Xi_4 \partial^{-1} r, \\ \Phi_{44} &= -(\varepsilon p \partial^{-1} s + \frac{1}{2} p \partial^{-1} q - \frac{1}{2}) \partial + (2\varepsilon p \partial^{-1} s + p \partial^{-1} q - 1) h - \Xi_4 \partial^{-1} s,\end{aligned}$$

where

$$\begin{aligned}\Xi_1 &= 2\varepsilon[(\varepsilon s \partial^{-1} s + \frac{1}{2} q s + \frac{1}{2} s \partial^{-1} q) \partial p + (\varepsilon s \partial^{-1} r + \frac{1}{2} q r + \frac{1}{2} s \partial^{-1} p) \partial q + (\varepsilon s \partial^{-1} q + \frac{1}{2} q^2) \partial r + (\varepsilon s \partial^{-1} p + \frac{1}{2} + \frac{1}{2} p q) \partial s + h s], \\ \Xi_2 &= 2\varepsilon[(\varepsilon r \partial^{-1} s + \frac{1}{2} q \partial^{-1} q + \frac{1}{2} p \partial^{-1} s) \partial p + (\varepsilon r \partial^{-1} r + \frac{1}{2} q \partial^{-1} p + \frac{1}{2} p \partial^{-1} r) \partial q + (\varepsilon r \partial^{-1} q + p \partial^{-1} q) \partial r + (\varepsilon r \partial^{-1} p + p \partial^{-1} p) \partial s], \\ \Xi_3 &= 2\varepsilon^2(q \partial^{-1} s \partial p + q \partial^{-1} r \partial q + q \partial^{-1} q \partial r + q \partial^{-1} p \partial s), \\ \Xi_4 &= 2\varepsilon[(\varepsilon p \partial^{-1} s + \frac{1}{2} p \partial^{-1} q - \frac{1}{2}) \partial p + (\varepsilon p \partial^{-1} r + \frac{1}{2} p \partial^{-1} p) \partial q + \varepsilon p \partial^{-1} q \partial r + \varepsilon p \partial^{-1} p \partial s + p h].\end{aligned}$$

Thus, we show that all members in the hierarchy (57) are bi-Hamiltonian

$$u_{t_m} = K_m = J \frac{\delta \mathcal{H}_m}{\delta u} = M \frac{\delta \mathcal{H}_{m-1}}{\delta u}, \quad m \geq 0, \quad (22)$$

where the second Hamiltonian operator is given by $M = J\Phi$.

So, the soliton hierarchy (57) is Liouville integrable. Particularly, it possesses infinitely many commuting conserved functions and symmetries:

$$\begin{aligned}\{H_k, H_l\}_J &= \int \left(\frac{\delta H_k}{\delta u}\right)^T J \frac{\delta H_l}{\delta u} dx = 0, \quad k, l \geq 0, \\ \{H_k, H_l\}_M &= \int \left(\frac{\delta H_k}{\delta u}\right)^T M \frac{\delta H_l}{\delta u} dx = 0, \quad k, l \geq 0,\end{aligned}$$

and

$$[K_k, K_l] = K'_k(u)[K_l] - K'_l(u)[K_k] = 0, \quad k, l \geq 0.$$

These commuting relations are also consequences of the Virasoro algebra of Lax operators[19].

2.2 Completion of the WKI integrable couplings

Consider the following generalized spectral problem

$$\phi_x = \bar{U} \phi, \quad u = \begin{bmatrix} p \\ q \\ r \\ s \end{bmatrix}, \quad \phi = \begin{bmatrix} \phi_1 \\ \phi_2 \\ \phi_3 \\ \phi_4 \end{bmatrix}, \quad (23)$$

with the spectral matrix \bar{U} as follows

$$\bar{U} = \begin{bmatrix} U & U_1 \\ 0 & U \end{bmatrix} = \left[\begin{array}{cc|cc} \lambda + h & \lambda p & 0 & \lambda r \\ \lambda q & -\lambda - h & \lambda s & 0 \\ \hline 0 & 0 & \lambda + h & \lambda p \\ 0 & 0 & \lambda q & -\lambda - h \end{array} \right], \quad h = \varepsilon(ps + qr)_x. \quad (24)$$

Here, a nonlinear perturbation term h is added to the spectral matrix. When $\varepsilon = 0$, it reduces the case of WKI integrable couplings[20, 21]. From thus spectral matrix, we can work out the complete system of the WKI integrable couplings by standard procedure.

Solving the stationary zero curvature equation $\bar{W}_x = [\bar{U}, \bar{W}]$ (\bar{W} is given in (10)) gives

$$\begin{cases} a_x = \lambda pc - \lambda qb, \\ b_x = 2\lambda b + 2hb - 2\lambda pa, \\ c_x = -2\lambda c - 2hc + 2\lambda qa, \\ d_x = 2\lambda d - 2\lambda pf - 2\lambda ra + 2hd, \\ f_x = \lambda pg + \lambda rc - \lambda sb - \lambda qd, \\ g_x = -2\lambda g + 2\lambda qf + 2\lambda sa - 2gh. \end{cases} \quad (25)$$

Further, let a, b, c possess the Laurent expansions:

$$a = \sum_{i \geq 0} a_i \lambda^{-i}, \quad b = \sum_{i \geq 0} b_i \lambda^{-i}, \quad c = \sum_{i \geq 0} c_i \lambda^{-i},$$

$$f = \sum_{i \geq 0} f_i \lambda^{-i}, \quad d = \sum_{i \geq 0} d_i \lambda^{-i}, \quad g = \sum_{i \geq 0} g_i \lambda^{-i}.$$

Equivalently, the system (25) leads to the recursion relations

$$\begin{cases} a_{ix} = pc_{i+1} - qb_{i+1}, \\ b_{ix} = 2b_{i+1} - 2pa_{i+1} + 2hb_i, \\ c_{ix} = -2c_{i+1} + 2qa_{i+1} - 2hc_i, \\ d_{ix} = 2d_{i+1} - 2ra_{i+1} - 2pf_{i+1} + 2hd_i, \\ f_{ix} = -sb_{i+1} + rc_{i+1} - qd_{i+1} + pg_{i+1}, \\ g_{ix} = -2g_{i+1} + sa_{i+1} + qf_{i+1} - hg_i. \end{cases} \quad i \geq 0 \quad (26)$$

From (26), we can find that the initial data satisfy

$$pc_0 - qb_0 = 0, \quad b_0 = pa_0, \quad c_0 = qa_0, \quad pg_0 + rc_0 - sb_0 - qd_0 = 0, \quad d_0 = pf_0 + ra_0, \quad g_0 = qf_0 + sa_0, \quad (27)$$

and a_{m+1}, e_{m+1} have the recursion relations

$$\begin{aligned} a_{m+1} &= \frac{1}{\sqrt{1+pq}} \partial^{-1} \frac{1}{\sqrt{1+pq}} \left[\frac{1}{4} pc_{mxx} - \frac{1}{4} qb_{mxx} + \frac{1}{2} p(hc_m)_x + \frac{1}{2} q(hb_m)_x - ha_{mxx} \right], \\ f_{m+1} &= \frac{1}{\sqrt{1+pq}} \partial^{-1} \frac{1}{\sqrt{1+pq}} \left[-\sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x + \frac{1}{4} pg_{mxx} + \frac{1}{2} p(hg_m)_x + \frac{1}{4} rc_{mxx} \right. \\ &\quad \left. + \frac{1}{2} r(hc_m)_x - \frac{1}{4} sb_{mxx} + \frac{1}{2} s(hb_m)_x - \frac{1}{4} qf_{mxx} + \frac{1}{2} q(hf_m)_x \right]. \end{aligned} \quad (28)$$

To guarantee the uniqueness of $\{a_i, b_i, c_i, d_i, f_i, g_i | i \geq 1\}$, we impose the conditions on constants of integration

$$a_i |_{u=0} = b_i |_{u=0} = c_i |_{u=0} = d_i |_{u=0} = f_i |_{u=0} = g_i |_{u=0}.$$

From (26) to (28), we can have

$$a_0 = \frac{1}{\sqrt{1+pq}}, \quad b_0 = \frac{p}{\sqrt{1+pq}}, \quad c_0 = \frac{q}{\sqrt{1+pq}}, \quad f_0 = -\frac{ps+qr}{2(1+pq)^{\frac{3}{2}}}, \quad d_0 = \frac{r}{\sqrt{1+pq}} - \frac{p(ps+qr)}{2(1+pq)^{\frac{3}{2}}},$$

$$g_0 = \frac{s}{\sqrt{1+pq}} - \frac{q(ps+qr)}{2(1+pq)^{\frac{3}{2}}}, \quad a_1 = \frac{1}{4} \frac{4\varepsilon pq(ps+qr)_x + pq_x - qp_x}{(1+pq)^{\frac{2}{3}}}, \quad b_1 = \frac{1}{2} \frac{2\varepsilon p(ps+qr)_x + p_x}{(1+pq)^{\frac{2}{3}}},$$

$$c_1 = -\frac{1}{2} \frac{2\varepsilon q(ps+qr)_x + q_x}{(1+pq)^{\frac{2}{3}}}$$

$$\begin{aligned} f_1 &= \frac{1}{8(1+pq)^2} [2pq(r_x - s_x) + ps(3pq_x - qp_x) + qr(pq_x - 3qp_x) - 2q_x r + 2qr_x + 2p_x s - ps_x \\ &\quad + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2)], \end{aligned}$$

$$\begin{aligned} d_1 &= \left(\frac{r}{2\sqrt{1+pq}} \right)_x - \left(\frac{p(ps+qr)}{2(1+pq)^{\frac{3}{2}}} \right)_x + \frac{r(pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}} + \frac{p}{8(1+pq)^2} [2pq(r_x - s_x) + ps(3pq_x - qp_x) + qr(pq_x - 3qp_x) \\ &\quad - 2q_x r + 2qr_x + 2p_x s - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2)] - \varepsilon \left(\frac{r}{\sqrt{1+pq}} - \frac{p(ps+3qr)}{2(1+pq)^{\frac{3}{2}}} \right) (ps+qr)_x, \end{aligned}$$

$$\begin{aligned} g_1 &= -\left(\frac{s}{2\sqrt{1+pq}} \right)_x + \left(\frac{q(ps+qr)}{4(1+pq)^{\frac{3}{2}}} \right)_x + \frac{s(pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}} + \frac{q}{8(1+pq)^2} [2pq(r_x - s_x) + ps(3pq_x - qp_x) + qr(pq_x - 3qp_x) \\ &\quad - 2q_x r + 2qr_x + 2p_x s - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2)] - \varepsilon \left(\frac{s}{\sqrt{1+pq}} - \frac{q(3ps+qr)}{2(1+pq)^{\frac{3}{2}}} \right) (ps+qr)_x. \end{aligned}$$

Taking

$$V^{[m]} = \lambda^2(\lambda^m W)_+ + \begin{bmatrix} A_m & \lambda B_m & 0 & \lambda F_m \\ \lambda C_m & -A_m & \lambda G_m & 0 \\ 0 & 0 & A_m & \lambda B_m \\ 0 & 0 & \lambda C_m & -A_m \end{bmatrix}, \quad (29)$$

where $B_m = \frac{1}{2}(b_{mx} - 2hb_m)$, $C_m = \frac{1}{2}(-c_{mx} - 2hc_m)$, $F_m = \frac{1}{2}(d_{mx} - 2hd_m)$ and $G_m = \frac{1}{2}(-g_{mx} - 2hg_m)$. Thus, the corresponding zero curvature equation (2.2) give rise to a hierarchy

$$\begin{cases} p_{t_m} = B_{mx} - 2hB_m + 2pA_m, \\ q_{t_m} = C_{mx} - 2hC_m - 2qA_m, \quad m \geq 0. \\ r_{t_m} = F_{mx} - 2hF_m + 2rA_m, \\ s_{t_m} = G_{mx} + 2hG_m - 2sA_m, \\ h_{t_m} = A_{mx}. \end{cases} \quad (30)$$

Based on (26) and (30), we can have

$$\begin{aligned} A_{mx} &= h_{t_m} = \varepsilon(p_{tm}s + ps_{tm} + q_{tm}r + qr_{tm})_x \\ &= \varepsilon[\frac{1}{2}b_{mxx}s - (hb_m)_{xs} - \frac{1}{2}pg_{mxx} - (hg_m)_{xp} - \frac{1}{2}rc_{mxx} - r(hc_m)_x + \frac{1}{2}qd_{mxx} - q(hd_m)_x + 2hf_{mx}]_x \\ &= -2\varepsilon((1+pq)f_{m+1,x} + \frac{1}{2}(pq_x + qp_x)f_{m+1} + (ps+qr)a_{m+1,x} + \frac{1}{2}(ps_x + sp_x + rq_x + qr_x)a_m + 1)_x \\ &= -2\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x]_x \end{aligned}$$

So, we can choose $A_m = -2\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x]$, and generate the complete system of the WKI integrable couplings:

$$\begin{bmatrix} p_{tm} \\ q_{tm} \\ r_{tm} \\ s_{tm} \end{bmatrix} = \begin{bmatrix} \frac{1}{2}b_{mxx} - (hb_m)_x - h(b_{mx} - 2hb_m) - 4p\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x] \\ -\frac{1}{2}c_{mxx} - (hc_m)_x - h(c_{mx} + 2hc_m) + 4q\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x] \\ \frac{1}{2}d_{mxx} - (hd_m)_x - h(d_{mx} - 2hd_m) - 4r\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x] \\ -\frac{1}{2}g_{mxx} - (hg_m)_x - h(g_{mx} - 2hg_m) + 4s\varepsilon[\sqrt{1+pq}(\sqrt{1+pq}f_{m+1})_x + \sqrt{ps+qr}(\sqrt{ps+qr}a_{m+1})_x] \end{bmatrix} \quad (31)$$

The first nonlinear equation in the above new system can be given

$$\begin{aligned}
p_{t_0} &= \left(\frac{p}{2\sqrt{1+pq}}\right)_{xx} - \varepsilon \frac{p(ps+qr)_{xx}}{\sqrt{1+pq}} - 2\varepsilon(ps+qr)_x \left(\frac{p}{\sqrt{1+pq}}\right)_x + \frac{2\varepsilon^2 p(ps+qr)_x^2}{\sqrt{1+pq}} - \varepsilon p \sqrt{1+pq} \left[\frac{1}{2(1+pq)^{\frac{3}{2}}}\right. \\
&\quad \left.(2pq(r_x-s_x) + ps(3pq_x-qp_x) + qr(pq_x-3qp_x) - 2q_xr + 2qr_x + 2p_xs - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2))\right]_x \\
&\quad - 4\varepsilon p \sqrt{ps+qr} \left[\frac{\sqrt{ps+qr}(4\varepsilon pq(ps+qr)_x + pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}}\right]_x, \\
q_{t_0} &= -\left(\frac{q}{\sqrt{1+pq}}\right)_{xx} - \varepsilon \frac{q(ps+qr)_{xx}}{\sqrt{1+pq}} - 2\varepsilon(ps+qr)_x \left(\frac{q}{\sqrt{1+pq}}\right)_x - \frac{2\varepsilon^2 q(ps+qr)_x^2}{\sqrt{1+pq}} - \varepsilon q \sqrt{1+pq} \left[\frac{1}{2(1+pq)^{\frac{3}{2}}}\right. \\
&\quad \left.(2pq(r_x-s_x) + ps(3pq_x-qp_x) + qr(pq_x-3qp_x) - 2q_xr + 2qr_x + 2p_xs - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2))\right]_x \\
&\quad - 4\varepsilon q \sqrt{ps+qr} \left[\frac{\sqrt{ps+qr}(4\varepsilon pq(ps+qr)_x + pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}}\right]_x, \\
r_{t_0} &= \left(\frac{r}{2\sqrt{1+pq}} - \frac{p(ps+qr)}{4(1+pq)^{\frac{3}{2}}}\right)_{xx} - \varepsilon(ps+qr)_{xx} \left[\frac{r}{\sqrt{1+pq}} - \frac{p(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right] - 2\varepsilon(ps+qr)_x \left[\frac{r}{\sqrt{1+pq}} - \frac{p(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right]_x \\
&\quad + 2\varepsilon^2(ps+qr)_x^2 \left[\frac{r}{\sqrt{1+pq}} - \frac{p(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right] - \varepsilon r \sqrt{1+pq} \left[\frac{1}{2(1+pq)^{\frac{3}{2}}}(2pq(r_x-s_x) + ps(3pq_x-qp_x) + qr(pq_x-3qp_x) \right. \\
&\quad \left. - 2q_xr + 2qr_x + 2p_xs - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2))\right]_x - 4\varepsilon r \sqrt{ps+qr} \left[\frac{\sqrt{ps+qr}(4\varepsilon pq(ps+qr)_x + pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}}\right]_x, \\
s_{t_0} &= -\left(\frac{s}{2\sqrt{1+pq}} - \frac{q(ps+qr)}{4(1+pq)^{\frac{3}{2}}}\right)_{xx} - \varepsilon(ps+qr)_{xx} \left[\frac{s}{\sqrt{1+pq}} - \frac{q(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right] - 2\varepsilon(ps+qr)_x \left[\frac{s}{\sqrt{1+pq}} - \frac{q(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right]_x \\
&\quad + 2\varepsilon^2(ps+qr)_x^2 \left[\frac{s}{\sqrt{1+pq}} - \frac{q(ps+qr)}{2(1+pq)^{\frac{3}{2}}}\right] - \varepsilon s \sqrt{1+pq} \left[\frac{1}{2(1+pq)^{\frac{3}{2}}}(2pq(r_x-s_x) + ps(3pq_x-qp_x) + qr(pq_x-3qp_x) \right. \\
&\quad \left. - 2q_xr + 2qr_x + 2p_xs - ps_x + 4\varepsilon(ps+qr)_x(ps+qr)(pq-2))\right]_x - 4\varepsilon s \sqrt{ps+qr} \left[\frac{\sqrt{ps+qr}(4\varepsilon pq(ps+qr)_x + pq_x - qp_x)}{4(1+pq)^{\frac{2}{3}}}\right]_x.
\end{aligned}$$

2.3 Completion of the vector AKNS integrable couplings

We consider the matrix iso-spectral problem

$$\phi_x = \bar{U}\phi, \quad \bar{U} = \begin{bmatrix} U & U_1 \\ 0 & U \end{bmatrix} = \left[\begin{array}{cc|cc} \lambda + h & p & 0 & r \\ q & -(\lambda + h)I_N & s & 0 \\ \hline 0 & 0 & \lambda + h & p \\ 0 & 0 & q & -(\lambda + h)I_N \end{array} \right], \quad h = \varepsilon(ps + rq), \quad (32)$$

where $p = (p_1, p_2, \dots, p_N)$, $q = (q_1, q_2, \dots, q_N)^T$, $r = (r_1, r_2, \dots, r_N)$, $s = (s_1, s_2, \dots, s_N)^T$, I_N is a n -order unit matrix. Here, a nonlinear perturbation term h is added to the spectral matrix. When $\varepsilon = 0$, it reduces the case of vector AKNS integrable couplings[22, 23]. Based on this spectral matrix, we can work out the complete system of the vector AKNS integrable couplings by standard procedure.

Assume

$$\overline{W} = \begin{bmatrix} W & W_1 \\ 0 & W \end{bmatrix} = \left[\begin{array}{cc|cc} a & b & d & e \\ c & -aI_N & f & -dI_N \\ \hline 0 & 0 & a & b \\ 0 & 0 & c & -aI_N \end{array} \right] \quad (33)$$

where b, e are row vectors, c, f are column vectors, and a, d are real numbers.

Solving the stationary zero curvature equation $\overline{W}_x = [\overline{U}, \overline{W}]$ gives

$$\begin{cases} a_x = pc - bq, \\ b_x = 2(\lambda + h)b - 2ap, \\ c_x = -2(\lambda + h)c + 2aq, \\ d_x = pf + rc - bs - eq, \\ e_x = 2(\lambda + h)e - 2dp - 2ar, \\ f_x = -2(\lambda + h)f + 2dq + 2as. \end{cases} \quad (34)$$

Let us seek a formal solution of the type

$$\overline{W} = \left[\begin{array}{cc|cc} a & b & d & e \\ c & -aI_N & f & -dI_N \\ \hline 0 & 0 & a & b \\ 0 & 0 & c & -aI_N \end{array} \right] = \sum_{i \geq 0} \overline{W}_i \lambda^{-i}, \quad \overline{W}_i = \left[\begin{array}{cc|cc} a_i & b_i & d_i & e_i \\ c_i & -a_i I_N & f_i & -d_i I_N \\ \hline 0 & 0 & a_i & b_i \\ 0 & 0 & c_i & -a_i I_N \end{array} \right] \quad (35)$$

The Eq. (34) recursively define all $\{a_i, b_i, c_i, d_i, f_i, g_i | i \geq 1\}$ with the initial values

$$a_0 = 1, \quad b_0 = \underbrace{(0, 0, \dots, 0)}_N, \quad c_0 = \underbrace{(0, 0, \dots, 0)^T}_N, \quad d_0 = 1, \quad e_0 = \underbrace{(0, 0, \dots, 0)}_N, \quad f_0 = \underbrace{(0, 0, \dots, 0)^T}_N.$$

For any integer $m \geq 1$, we introduce

$$V^{[m]} = (\lambda^m W)_+ + \Delta_m = \sum_{i=0}^m V_i + \Delta_m, \quad \Delta_m = \begin{bmatrix} \delta_m & 0 & 0 & 0 \\ 0 & -\delta_m I_N & 0 & 0 \\ 0 & 0 & \delta_m & 0 \\ 0 & 0 & 0 & -\delta_m I_N \end{bmatrix}, \quad (36)$$

where δ_m is undetermined function. Thus, the corresponding zero curvature equation (2.2) with \bar{U} , V defined in (32) and (36) give rise to a hierarchy

$$\begin{cases} p_{t_m} = 2b_{m+1} + 2\delta_m p, \\ q_{t_m} = -2c_{m+1} - 2\delta_m q, \quad m \geq 0. \\ r_{t_m} = 2e_{m+1} + 2\delta_m r, \\ s_{t_m} = -2f_{m+1} - 2\delta_m s, \\ h_{t_m} = \delta_{mx}. \end{cases} \quad (37)$$

Based on(34) and (37), we can have

$$\begin{aligned} \delta_{mx} &= h_{t_m} = \varepsilon(p_{tm}s + ps_{tm} + q_{tm}r + qr_{tm}) \\ &= \varepsilon(2b_{m+1}s - 2pf_{m+1} + 2e_{m+1}q - 2rc_{m+1}) = -2\varepsilon d_{m+1,x}. \end{aligned}$$

So, we can choose $\delta_m = -2\varepsilon d_{m+1}$. The complete system of the vector AKNS integrable couplings are generated

$$\begin{bmatrix} p_{tm}^T \\ q_{tm} \\ r_{tm}^T \\ s_{tm} \end{bmatrix} = \begin{bmatrix} 2b_{m+1}^T - 4\varepsilon p^T d_{m+1} \\ -2c_{m+1} + 4\varepsilon q d_{m+1} \\ 2e_{m+1}^T - 4\varepsilon r^T d_{m+1} \\ -2f_{m+1} + 4\varepsilon s d_{m+1} \end{bmatrix}, \quad m \geq 0. \quad (38)$$

The first nonlinear equation in the above new system is

$$\begin{aligned} p_{t_2} &= \frac{1}{2}p_{xx} - (pq)p - \varepsilon[(pq)r_x + (ps)s_x + 3(ps)p_x + 2(p_xq)r + (pq_x)r + (pq_x - p_xq - p_xs - r_xq + r_qx)p] \\ &\quad + 2\varepsilon^2[(ps + rq)^2p - 2(ps + rq)(pq + ps + rq)p], \end{aligned}$$

$$\begin{aligned}
q_{t_2} &= -\frac{1}{2}q_{xx} + (pq)q - \varepsilon[(r_xq)q + (pq)s_x + (p_xq)s + 2(pq_x)s + (rq)q_x + (pq_x - p_xq - p_xs - r_xq + rq_x)q] \\
&\quad - 2\varepsilon^2[(ps + rq)^2q + 2(ps + rq)(pq + ps + rq)q], \\
r_{t_2} &= \frac{1}{2}(p_{xx} + r_{xx}) - [pq + ps]p - (pq)r - \varepsilon[(rs + r_sx + 3ps)p_x + (3rq + 2ps + pq)r_x + (pq_x)r + (ps_x)p \\
&\quad + (rq_x + 2p_xq + pq_x - p_xq - p_xs - r_xq + rq_x)r] + 2\varepsilon^2[(ps + rq)^2(p + r) - 2(ps + rq)(pq + ps + rq)p], \\
s_{t_2} &= -\frac{1}{2}(q_{xx} + s_{xx}) - (pq + rq + ps)q - \varepsilon[(ps_x + r_xq + r_xs + p_xs)q + (rs + ps + 3rq)q_x + (3ps + rq)s_x \\
&\quad + (-pq_x + p_xq + p_xs + r_xq + rq_x + p_xs)s] - 2\varepsilon^2[(ps + rq)^2(q + s) - 2(ps + rq)(pq + ps + rq)s].
\end{aligned}$$

3 Completion of the discrete integrable couplings

In this section, we will show that the procedure of constructing the completion of the integrable couplings can be applied to the discrete systems. In the following, we will take the Volterra lattice hierarchy as an example to illustrate it.

3.1 Completion of the Volterra integrable couplings

A generalized discrete spectral problem for the Volterra lattice hierarchy is given by

$$E\phi = \bar{U}\phi, \quad \bar{U} = \begin{bmatrix} U & U_1 \\ 0 & U \end{bmatrix} = \left[\begin{array}{cc|cc} 1 & u+h & 0 & r \\ \lambda^{-1} & 0 & 0 & 0 \\ \hline 0 & 0 & 1 & \lambda+h \\ 0 & 0 & \lambda^{-1} & 0 \end{array} \right], \quad h = \varepsilon ur, \quad (39)$$

where E is the shift operator and $(E^m f)(n) = f^m(n) = f(n+m)$. Here, a nonlinear perturbation term h is added to the spectral matrix. When $\varepsilon = 0$, it reduces the integrable couplings of Volterra lattice hierarchy [10, 24]. Based on this spectral matrix, we can work out the complete system of the Volterra lattice integrable couplings.

Upon setting

$$\bar{\Gamma} = \begin{bmatrix} \Gamma & \Gamma_1 \\ 0 & \Gamma \end{bmatrix} = \left[\begin{array}{cc|cc} a & b & d & f \\ c & -a & g & -d \\ \hline 0 & 0 & a & b \\ 0 & 0 & c & -a \end{array} \right] \quad (40)$$

The discrete stationary zero curvature equation $(E\bar{\Gamma})\bar{U} - \bar{U}\bar{\Gamma} = 0$ gives

$$\left\{ \begin{array}{l} a^{(1)} - a + \lambda^{-1}b^{(1)} - c(h+u) = 0, \\ (h+u)(a^{(1)} + a) - b = 0, \\ c^{(1)} - \lambda^{-1}(a^{(1)} + a) = 0, \\ (h+u)c^{(1)} - \lambda^{-1}b = 0, \\ -(h+u)g - cr + d^{(1)} - d + \lambda^{-1}f^{(1)} = 0, \\ g^{(1)} - \lambda^{-1}(d^{(1)} + d) = 0, \\ r(a^{(1)} + a) + (u+h)(d^{(1)} + d) - f = 0, \\ rc^{(1)} + (u+h)g^{(1)} - \lambda^{-1}f = 0. \end{array} \right. \quad (41)$$

Let $\bar{\Gamma}$ possess the Laurent expansions

$$\bar{\Gamma} = \sum_{i \geq 0} \bar{\Gamma}_i \lambda^{-i}, \quad \bar{\Gamma}_i = \left[\begin{array}{cc|cc} a_i & b_i & d_i & f_i \\ c_i & -a_i & g_i & -d_i \\ \hline 0 & 0 & a_i & b_i \\ 0 & 0 & c_i & -a_i \end{array} \right] \quad (42)$$

The Eq. (41) equivalently leads to

$$\left\{ \begin{array}{l} a_{i+1}^{(1)} - a_{i+1} - (h+u)c_{i+1} + b_i^{(1)} = 0, \\ b_i = (h+u)(a_i^{(1)} + a_i), \\ c_{i+1}^{(1)} = a_i^{(1)} + a_i, \\ (h+u)c_{i+1}^{(1)} = b_i, \\ -(h+u)g_{i+1} - rc_{i+1} + d_{i+1}^{(1)} - d_{i+1} = -f_i^{(1)}, \\ g_{i+1}^{(1)} = d_i^{(1)} + d_i, \\ r(a_i^{(1)} + a_i) + (u+h)(d_i^{(1)} + d_i) - f_i = 0, \\ rc_{i+1}^{(1)} + (h+u)g_{i+1}^{(1)} - f_i = 0 \end{array} \right. \quad (43)$$

Upon choosing $a_0 = \frac{1}{2}$, $e_0 = \frac{1}{2}$, $a_i|_{u=0} = 0$, $e_i|_{u=0} = 0$, $i \geq 1$, all sets of the functions a_i , b_i , c_i , d_i , f_i and g_i can be uniquely determined. The first two sets are

$$\begin{aligned} a_0 &= \frac{1}{2}, \quad b_0 = u + h, \quad c_0 = 0, \quad d_0 = \frac{1}{2}, \quad f_0 = h + u + r, \quad g_0 = 0, \\ a_1 &= -(h+u), \quad c_1 = 1, \quad b_1 = -(h+u)(u^{(1)} + u), \quad d_1 = -(h+u+r), \quad g_1 = 1, \\ f_1 &= -r(u^{(1)} + u) - (h+u)(h^{(1)} + u^{(1)} + r^{(1)} + h + u + r) \end{aligned}$$

The compatibility conditions of the matrix discrete spectral problem

$$E\phi = \bar{U}\phi, \quad \phi_t = V^{[m]}\phi, \quad V^{[m]} = (\lambda^{m+1}\Gamma)_+ + \Delta_m, \quad \Delta_m = \begin{bmatrix} 0 & -b_{m+1} & 0 & -f_{m+1} \\ 0 & a_{m+1} + a_{m+1}^{(-1)} & 0 & d_{m+1} + d_{m+1}^{(-1)} \\ 0 & 0 & 0 & -b_{m+1} \\ 0 & 0 & 0 & a_{m+1} + a_{m+1}^{(-1)} \end{bmatrix}$$

determine the the complete system of the Volterra lattice integrable couplings

$$\begin{bmatrix} u_{tm} \\ r_{tm} \end{bmatrix} = \begin{bmatrix} \frac{1}{1+\varepsilon r}(-u(a_{m+1} + a_{m+1}^{(-1)}) + \varepsilon u^2(\varepsilon r + 1)(d_{m+1} + d_{m+1}^{(-1)}) + b_{m+1} - \varepsilon u f_{m+1}) \\ -(\varepsilon r + 1)u(d_{m+1} + d_{m+1}^{(-1)}) - r(a_{m+1} + a_{m+1}^{(-1)}) + f_{m+1} \end{bmatrix} \quad (44)$$

The first nonlinear equation in the above new system is

$$\begin{aligned} u_{t_0} &= \frac{1}{1+\varepsilon r}[(1+\varepsilon r^{(-1)})uu^{(-1)} - uu^{(1)} + \varepsilon u^2 r], \\ r_{t_0} &= u(E+E^{-1})(u+r) + \varepsilon[uu^{(-1)}(1+E^{-1})r + ur(E^{-1}-E+1)r + u^{(1)}(rr^{(1)} - ur - ur^{(1)})] + \varepsilon^2 ur(E^{-1}+E)ur. \end{aligned}$$

4 Completion of the super integrable couplings

In this section, we will take super Dirac and super NLS-mKdV integrable hierarchies to show that the procedure of constructing the completion of the integrable couplings can be applied to the super integrable system[25, 26, 27].

4.1 Completion of super Dirac integrable couplings

Now we consider the following super spectral problem

$$\phi_x = \bar{U}\phi, \bar{U} = \left[\begin{array}{ccc|ccc} p & \lambda + h + q & \alpha & r & s & \xi \\ -\lambda - h + q & -p & \beta & s & -r & \eta \\ \beta & -\alpha & 0 & \eta & -\xi & 0 \\ \hline 0 & 0 & 0 & p & \lambda + h + q & \alpha \\ 0 & 0 & 0 & -\lambda - h + q & -p & \beta \\ 0 & 0 & 0 & \beta & -\alpha & 0 \end{array} \right], \quad h = \varepsilon(qs + pr + \alpha\eta + \xi\beta). \quad (45)$$

Here we would like to point out that $p, q, r, s, \alpha, \beta, \xi$ and η are all functions of x and t . p, q, r, s and λ are bosonic, and α, β, ξ and η are fermionic. In the spectral problem (45), a nonlinear perturbation term h is added. When $\varepsilon = 0$, it reduces the case of super Dirac integrable couplings [28].

Upon setting

$$\bar{W} = \left[\begin{array}{ccc|ccc} c & a + b & \rho & d & f + g & \mu \\ a - b & -c & \sigma & f - g & -d & \nu \\ \sigma & -\rho & 0 & \nu & -\mu & 0 \\ \hline 0 & 0 & 0 & c & a + b & \rho \\ 0 & 0 & 0 & a - b & -c & \sigma \\ 0 & 0 & 0 & \sigma & -\rho & 0 \end{array} \right]. \quad (46)$$

Solving the stationary zero curvature equation $\overline{W}_x = [\overline{U}, \overline{W}]$ gives

$$\left\{ \begin{array}{l} a_x = -2\lambda c - 2hc + 2pb - \alpha\rho + \beta\sigma, \\ b_x = 2pa - 2qc - \alpha\rho - \beta\sigma, \\ c_x = 2\lambda a - 2qb + 2ha + \alpha\sigma + \beta\rho, \\ \rho_x = (\lambda + q)\sigma - \beta(a + b) - \alpha c + p\rho + h\sigma, \\ \sigma_x = (-\lambda + q)\rho - p\sigma - \alpha(a - b) + \beta c - h\rho, \\ d_x = 2\lambda f + 2hf - 2qg - 2bs + \alpha\gamma + \xi\sigma - \rho\eta - \mu\beta, \\ f_x = -2\lambda d - 2hd + 2pg + 2rb - \alpha\mu - \xi\rho + \eta\sigma + \beta\nu, \\ g_x = 2ra - 2qd + 2pf - 2sc - \alpha\mu - \xi\rho - \eta\sigma - \beta\nu, \\ \mu_x = \lambda\nu + p\mu + (h + q)\nu + r\rho + s\sigma - \beta(f + g) - \alpha d - \eta(a + b) - \xi c, \\ \nu_x = -\lambda\mu + (q - h)\mu - p\nu + s\rho - r\sigma + \beta d + \alpha(f + g) - \xi(a - b) + \eta c. \end{array} \right. \quad (47)$$

Let us seek a formal solution of the type

$$\overline{W} = \sum_{i \geq 0} \overline{W}_i \lambda^{-i}, \quad \overline{W}_i = \left[\begin{array}{ccc|ccc} c_i & a_i + b_i & \rho_i & d_i & f_i + g_i & \mu_i \\ a_i - b_i & -c_i & \sigma_i & f_i - g_i & -d_i & \nu_i \\ \sigma_i & -\rho_i & 0 & \nu_i & -\mu_i & 0 \\ \hline 0 & 0 & 0 & c_i & a_i + b_i & \rho_i \\ 0 & 0 & 0 & a_i - b_i & -c_i & \sigma_i \\ 0 & 0 & 0 & \sigma_i & -\rho_i & 0 \end{array} \right] \quad (48)$$

The Eq. (47) equivalently leads to

$$\left\{ \begin{array}{l} a_{i+1} = \frac{1}{2}c_{ix} + qb_i - ha_i - \frac{1}{2}\alpha\sigma_i - \frac{1}{2}\beta\rho_i, \\ b_{i+1,x} = 2pa_{i+1} - 2qc_{i+1} - \alpha\rho_{i+1} - \beta\sigma_{i+1}, \\ c_{i+1} = -\frac{1}{2}a_{ix} - hc_i + pb_i - \frac{1}{2}\alpha\rho_i + \frac{1}{2}\beta\sigma_i, \\ \sigma_{i+1} = \frac{1}{2}\rho_{ix} - q\sigma_i + \beta(a_i + b_i) + \alpha c_i - p\rho_i - h\sigma_i, \\ \rho_{i+1} = -\frac{1}{2}\sigma_x + q\rho_i - p\sigma_i - \alpha(a_i - b_i) + \beta c_i - h\rho_i, \\ f_{i+1} = \frac{1}{2}d_x - hf_i + qg_i + sb_i - \frac{1}{2}\alpha\gamma_i - \frac{1}{2}\xi\sigma_i + \frac{1}{2}\rho_i\eta + \frac{1}{2}\mu_i\beta, \\ d_{i+1} = -\frac{1}{2}f_{ix} - hd_i + pg_i + rb_i - \frac{1}{2}\alpha\mu_i - \frac{1}{2}\xi\rho_i + \frac{1}{2}\eta\sigma_i + \frac{1}{2}\beta\nu_i, \\ g_{i+1,x} = 2ra_{i+1} - 2qd_{i+1} + 2pf_{i+1} - 2sc_{i+1} - \alpha\mu_{i+1} - \xi\rho_{i+1} - \eta\sigma_{i+1} - \beta\nu_{i+1}, \\ \nu_{i+1} = \mu_{ix} - p\mu_i - (h + q)\nu_i - r\rho_i - s\sigma_i + \beta(f_i + g_i) + \alpha d_i + \eta(a_i + b_i) + \xi c_i, \\ \mu_{i+1} = -\nu_{ix} + (q - h)\mu_i - p\nu_i + s\rho_i - r\sigma_i + \beta d_i - \alpha(f_i + g_i) - \xi(a_i - b_i) + \eta c_i. \end{array} \right. \quad (49)$$

Choosing the initial values as

$$a_0 = c_0 = \rho_0 = \sigma_0 = 0, \quad b_i = 1, \quad d_0 = f_0 = \mu_0 = \nu_0 = 0, \quad g_0 = 1$$

and assuming $a_i|_{u=0} = b_i|_{u=0} = c_i|_{u=0} = d_i|_{u=0} = f_i|_{u=0} = g_i|_{u=0} = \rho_i|_{u=0} = \sigma_i|_{u=0} = \mu_i|_{u=0} = \nu_i|_{u=0} = 0$, $i \geq 1$, the recursion relation (49) uniquely defines all differential polynomial functions a_i , b_i , c_i , d_i , f_i , g_i , ρ_i , σ_i , μ_i , and ν_i . The first two sets are:

$$a_1 = q, \quad b_1 = 0, \quad c_1 = p, \quad \rho_1 = \alpha, \quad \sigma_1 = \beta, \quad d_1 = p + r, \quad f_1 = q + s, \quad g_1 = 0, \quad \mu_1 = \xi + \alpha, \quad \nu_1 = \eta + \beta,$$

$$a_2 = \frac{1}{2}p_x - \varepsilon q(qs + pr + \alpha\eta + \xi\beta), \quad b_2 = \frac{1}{2}(q^2 + p^2 + \alpha\beta), \quad c_2 = -\frac{1}{2}q_x - \varepsilon p(qs + pr + \alpha\eta + \xi\beta)$$

$$\sigma_2 = \alpha_x - \varepsilon\beta(qs + pr + \alpha\eta + \xi\beta), \quad \rho_2 = -\beta_x - \varepsilon\alpha(qs + pr + \alpha\eta + \xi\beta),$$

$$d_2 = -\frac{1}{2}(q_x + s_x) - \varepsilon(qs + pr + \alpha\eta + \xi\beta)(p + r), \quad f_2 = \frac{1}{2}(p_x + r_x) - \varepsilon(qs + pr + \alpha\eta + \xi\beta)(q + s),$$

$$\mu_2 = -\eta_x - \beta_x - \varepsilon(qs + pr + \alpha\eta + \xi\beta)(\alpha + \xi), \quad \nu_2 = \xi_x + \alpha_x - \varepsilon(qs + pr + \alpha\eta + \xi\beta)(\eta + \beta),$$

$$g_2 = pr + qs + \frac{1}{2}(p^2 + q^2) + \alpha\eta + (\alpha + \xi)\beta.$$

For any integer $m \geq 1$, we take

$$V^{[m]} = (\lambda^m W)_+ + \Delta_m = \sum_{i=0}^m V_i + \Delta_m, \quad \Delta_m = \begin{bmatrix} 0 & \delta_m & 0 & 0 & 0 & 0 \\ -\delta_m & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & \delta_m & 0 \\ 0 & 0 & 0 & -\delta_m & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix} \quad (50)$$

where δ_m is undetermined function. Thus, the corresponding zero curvature equation (2.2) with \bar{U} , V defined in (45) and (50) yields

$$\left\{ \begin{array}{l} p_{t_m} = 2a_{m+1} + 2q\delta_m, \\ q_{t_m} = -2c_{m+1} - 2p\delta_m, \quad m \geq 0. \\ r_{t_m} = 2f_{m+1} + 2s\delta_m, \\ s_{t_m} = -2d_{m+1} - 2r\delta_m, \\ \alpha_{t_m} = \sigma_{m+1} + \beta\delta_m, \\ \beta_{t_m} = -\rho_{m+1} - \alpha\delta_m, \\ \xi_{t_m} = \gamma_{m+1} + \eta\delta_m, \\ \eta_{t_m} = -\mu_{m+1} - \xi\delta_m, \\ h_{t_m} = \delta_{mx}. \end{array} \right. \quad (51)$$

Based on (47) and (51), we can have

$$\begin{aligned} \delta_{mx} = h_{t_m} &= \varepsilon(q_{tm}s + q_{stm} + p_{tm}r + pr_{tm} + \alpha\eta_{tm} + \alpha_{tm}\eta + \xi\beta_{tm} + \xi_{tm}\beta) \\ &= \varepsilon(-2sc_{m+1}s - 2qd_{m+1} + 2ra_{m+1}q + 2pf_{m+1} + \sigma_{n+1}\eta - \alpha\mu_{n+1} + \gamma_{n+1}\beta - \xi\rho_{n+1}) = \varepsilon g_{m+1,x}. \end{aligned}$$

So, we can choose $\delta_m = \varepsilon g_{m+1}$. The complete system of the super dirac integrable couplings are

generated

$$\begin{bmatrix} p_{tm} \\ q_{tm} \\ r_{tm} \\ s_{tm} \\ \alpha_{t_m} \\ \beta_{t_m} \\ \xi_{t_m} \\ \eta_{t_m} \end{bmatrix} = \begin{bmatrix} 2a_{m+1} + 2\varepsilon qg_{m+1} \\ -2c_{m+1} - 2\varepsilon pg_{m+1} \\ 2f_{m+1} + 2\varepsilon sg_{m+1} \\ -2d_{m+1} - 2\varepsilon rg_{m+1} \\ \sigma_{m+1} + \varepsilon\beta g_{m+1} \\ -\rho_{m+1} - \varepsilon\alpha g_{m+1} \\ \gamma_{m+1} + \varepsilon\eta g_{m+1} \\ -\mu_{m+1} - \varepsilon\xi g_{m+1} \end{bmatrix}, \quad m \geq 0. \quad (52)$$

The first nonlinear super system is

$$\begin{aligned} p_{t_2} &= -\frac{1}{2}q_{xx} - \frac{1}{2}(\alpha\alpha_x - \beta\beta_x) + q(q^2 + p^2 + \alpha\beta) + \varepsilon[2q(\alpha\alpha_x + \beta\beta_x + \eta\eta_x + \xi\xi_x - pq_x + sr_x \\ &\quad - rs_x - sp_x + qp_x) - 2rpp_x - 2p_x(\alpha\eta + \xi\beta)] + 4\varepsilon^2[q^2s(pr + \alpha\eta + \xi\beta) + 2q(p^2r^2 + q^2s^2 \\ &\quad + 2\alpha\eta\xi\beta) + 2pqr(\alpha\eta + \xi\beta)] + 2\varepsilon^2[(ps + rq)^2p - 2(ps + rq)(pq + ps + rq)p], \\ q_{t_2} &= \frac{1}{2}p_{xx} - \frac{1}{2}(\alpha\beta_x + \beta\alpha_x) - p(q^2 + p^2 + \alpha\beta) - 2\varepsilon[p(\alpha\alpha_x + \beta\beta_x + \eta\eta_x + \xi\xi_x - qp_x + sr_x \\ &\quad - rs_x - pq_x + rq_x) + q_x(sq + \alpha\eta + \xi\beta)] - 4\varepsilon^2[p^2r(pr + qs + \alpha\eta + \xi\beta) \\ &\quad + pqs(\beta\xi + \alpha\eta + \frac{1}{2}qs) + p\alpha\eta\xi\beta], \\ r_{t_2} &= -\frac{1}{2}(q_{xx} + s_{xx}) - \frac{1}{2}(\xi\alpha_x + \eta\beta_x) - \alpha(\xi_x + \alpha_x) - \beta(\beta_x + \eta_x) + 2q^2(r + s + q) + p^2(q + s) + 2q(\alpha\beta + ps + \alpha\eta + \beta\xi) \\ &\quad + s\alpha\beta + 2\varepsilon[s(-pq_x + \alpha\alpha_x + \beta\beta_x + \xi\xi_x + \eta\eta_x - rs_x - qr_x) - p_x(\alpha\eta + \xi\beta + pr) + r_x(\alpha\eta + \xi\beta + s^2)] \\ &\quad + 2\varepsilon^2[q^2s(s^2 + qs + \beta\xi + \alpha\eta + pr) + s(\alpha\eta + \beta\xi + spr)(pr + qs) + \alpha\beta\eta\xi(q + s) + \beta\xi pqr], \\ s_{t_2} &= \frac{1}{2}(p_{xx} + r_{xx}) - \frac{1}{2}(\xi\beta_x + \eta\alpha_x) - \beta(\xi_x + \alpha_x) - \alpha(\beta_x + \eta_x) - q^2(r + p) - p^2(p + r + 2s) - 2p(qr + \alpha\eta + \beta\xi + 2\alpha\beta) \\ &\quad - r\alpha\beta + 2\varepsilon[r(\alpha\alpha_x + \beta\beta_x + \xi\xi_x + \eta\eta_x + qp_x + sr_x - qr_x) - q_x(\alpha\eta + \xi\beta + qs) - s_x(\alpha\eta + \xi\beta + pr + qs - r^2)] \\ &\quad (\eta\beta + \alpha\xi)(pr + qs) - 4\varepsilon^2[p\alpha\eta(qs + r^2 + \xi\beta + \alpha\eta + pr) + r(\alpha\eta + p^2 + pr)(sq + \beta\xi) + p\beta\xi(qs + r^2) + q^2s^2(p + r)], \\ \alpha_{t_2} &= -\frac{1}{4}\beta_{xx} + \frac{1}{2}[(p\beta)_x - (q\alpha)_x] + \frac{1}{2}\beta(p^2 + q^2) + \varepsilon\beta(qp_x - pq_x + sr_x - rs_x + \alpha\alpha_x + \eta\eta_x + \xi\xi_x - \alpha_x\xi) \end{aligned}$$

$$\begin{aligned}
& -\varepsilon\alpha_x(pr + qs - \alpha\eta) + \varepsilon^2\beta[qs(qs + 2pr + 2\alpha\eta) + pr(pr + 2\alpha\eta)], \\
\beta_{t_2} &= \frac{1}{4}\alpha_{xx} + \frac{1}{2}[(q\beta)_x - (p\alpha)_x] - \frac{1}{2}\alpha(p^2 + q^2) + \varepsilon\alpha(pq_x - qp_x - sr_x + rs_x + \eta\eta_x + \xi\xi_x - \beta\beta_x - \beta_x\eta) \\
& -\varepsilon\beta_x(pr + qs + \xi\beta) - \varepsilon^2\alpha[pr(pr + 2qs + 2\beta\xi) + qs(qs + 2\beta\xi)], \\
\xi_{t_2} &= -(\eta_{xx} + \beta_{xx}) + \frac{1}{2}[2p\beta_x + \beta p_x - q\alpha_x - 2\alpha q_x + (\beta r)_x - (\alpha s)_x + \eta p_x + 2p\eta_x - \xi q_x - 2q\xi_x] \\
& + \frac{1}{2}(\beta + \eta)(p^2 + q^2) + \beta(ps + qr) - 2\varepsilon\alpha_x(qs + pr - \beta\xi + \frac{1}{2}\alpha\eta) - 2\varepsilon\xi_x(qs + pr + \beta\xi \\
& + \alpha\eta + \frac{1}{2}\eta\xi) + \varepsilon\eta(qp_x - pq_x + sr_x - rs_x + \beta\beta_x) + \varepsilon^2[\beta pr(pr + 2qs + 2\xi\eta + 2\alpha\eta + pr) \\
& + \beta qs(\alpha\eta + \xi\eta + qs) + \eta(p^2r^2 + q^2s^2) + 2\eta pqr s], \\
\eta_{t_2} &= \alpha_{xx} + \xi_{xx} + \frac{1}{2}[2p\alpha_x + 2q\beta_x + \beta q_x + \alpha p_x + (\beta s)_x + (\alpha r)_x + \eta q_x + 2q\eta_x + r\alpha_x + \xi p_x + 2p\xi_x] \\
& + \frac{1}{2}(\alpha - \xi)(p^2 + q^2) + \alpha(ps + qr + \frac{1}{2}\beta\xi) - 2\varepsilon\beta_x(qs + pr - \alpha\eta + \frac{3}{2}\xi\beta) - 2\varepsilon\eta_x(qs + pr + \beta\xi \\
& + \alpha\eta + \frac{1}{2}\eta\xi) - \varepsilon\xi(qp_x - pq_x - sr_x + rs_x + \alpha\alpha_x) - \varepsilon^2[\alpha pr(qs + pr + 2\beta\xi + 2\eta\xi) + \alpha qs(2\beta\xi + 2\eta\xi + qs) \\
& + \xi(p^2r^2 + q^2s^2) + 2\xi pqr s].
\end{aligned}$$

4.2 Completion of super NLS-mKdV integrable couplings

Similar to the case of the super dirac hierarchy, in this section, we will briefly show how to construct the complete system of the super NLS-mKdV integrable couplings. Firstly, we consider the following super spectral problem

$$\phi_x = \bar{U}\phi, \quad \bar{U} = \left[\begin{array}{ccc|ccc} \lambda + h & p + q & \alpha & 0 & r + s & \xi \\ -p + q & -\lambda - h & \beta & -r + s & 0 & \eta \\ \beta & -\alpha & 0 & \eta & -\xi & 0 \\ \hline 0 & 0 & 0 & \lambda + h & p + q & \alpha \\ 0 & 0 & 0 & -p + q & -\lambda - h & \beta \\ 0 & 0 & 0 & \beta & -\alpha & 0 \end{array} \right], \quad h = \varepsilon(qs - pr + \alpha\eta + \xi\beta). \quad (53)$$

with $p, q, r, s, \alpha, \beta, \xi,$ and η are all functions of x and t, p, q, r, s, λ are bosonic, and α, β, ξ, η are fermionic. Here, h is an added nonlinear perturbation term. When $\varepsilon = 0$, it reduces the case of super NLS-mKdV integrable couplings[29].

Upon setting

$$\overline{W} = \left[\begin{array}{ccc|ccc} a & b+c & \rho & d & f+g & \mu \\ b-c & -a & \sigma & f-g & -d & \nu \\ \sigma & -\rho & 0 & \nu & -\mu & 0 \\ \hline 0 & 0 & 0 & a & b+c & \rho \\ 0 & 0 & 0 & b-c & -a & \sigma \\ 0 & 0 & 0 & \sigma & -\rho & 0 \end{array} \right] = \sum_{i \geq 0} \left[\begin{array}{ccc|ccc} a_i & b_i+c_i & \rho_i & d_i & f_i+g_i & \mu_i \\ b_i-c_i & -a_i & \sigma_i & f_i-g_i & -d_i & \nu_i \\ \sigma_i & -\rho_i & 0 & \nu_i & -\mu_i & 0 \\ \hline 0 & 0 & 0 & a_i & b_i+c_i & \rho_i \\ 0 & 0 & 0 & b_i-c_i & -a_i & \sigma_i \\ 0 & 0 & 0 & \sigma_i & -\rho_i & 0 \end{array} \right] \lambda^{-i}. \quad (54)$$

The stationary zero curvature equation $\overline{W}_x = [\overline{U}, \overline{W}]$ gives rise to

$$\left\{ \begin{array}{l} a_{i+1,x} = 2pb_{i+1} - 2qc_{i+1} + \alpha\sigma_{i+1} + \beta\rho_{i+1}, \\ b_{i+1} = \frac{1}{2}c_{ix} + qa_i + \frac{1}{2}\alpha\rho_i + \frac{1}{2}\beta\sigma_i - hb_i, \\ c_{i+1} = \frac{1}{2}b_{ix} + pa_i + \frac{1}{2}\alpha\rho_i - \frac{1}{2}\beta\sigma_i - hc_i, \\ \sigma_{i+1} = -\sigma_{ix} - (p-q)\sigma_i + \alpha(c_i - b_i) + \beta a_i - h\sigma_i, \\ \rho_{i+1} = \rho_{ix} - (p+q)\rho_i + \alpha a_i + \beta(b_i + c_i) - h\rho_i, \\ d_{i+1,x} = -2sc_{i+1} + 2rb_{i+1} + 2pf_{i+1} - 2qg_{i+1} + \alpha\nu_{i+1} + \xi\sigma_{i+1} + \xi\sigma_{i+1} + \beta\mu_{i+1}, \\ f_{i+1} = \frac{1}{2}g_{ix} - hf_i + qd_i + (r+s)a_i - \frac{1}{2}\sigma_i\eta - \nu_i\beta - \mu_i\alpha - \rho_i\xi, \\ g_{i+1} = \frac{1}{2}f_{ix} - hgi + pd_i - \frac{1}{2}\eta\sigma_i - \frac{1}{2}\beta\nu_i - \frac{1}{2}\mu_i\alpha - \frac{1}{2}\rho_i\xi, \\ \mu_{i+1} = \mu_{ix} - (p+q)\nu_i - h\mu_i - (r+s)\sigma_i + \beta(f_i + g_i) + \alpha d_i + \eta(b_i + c_i) + \xi a_i, \\ \nu_{i+1} = -\nu_{ix} + (p-q)\mu_i - h\mu_i + (s-r)\rho_i + \beta d_i - \alpha(f_i - g_i) + \xi(c_i - b_i) + \eta a_i. \end{array} \right. \quad (55)$$

This system can uniquely determine all sets of functions of $a_i, b_i, c_i, d_i, f_i, g_i, \rho_i, \sigma_i, \mu_i$ and ν_i upon choosing the initial values as

$$b_0 = c_0 = f_0 = g_0 = \rho_0 = \sigma_0 = \mu_0 = \nu_0 = 0, \quad a_0 = 1, \quad d_0 = 1$$

and assuming $a_i|_{u=0} = b_i|_{u=0} = c_i|_{u=0} = d_i|_{u=0} = f_i|_{u=0} = g_i|_{u=0} = \rho_i|_{u=0} = \sigma_i|_{u=0} = \mu_i|_{u=0} =$

$\nu_i|_{u=0} = 0, i \geq 1.$

The first few sets are:

$$a_1 = 0, b_1 = q, c_1 = p, \rho_1 = \alpha, \sigma_1 = \beta, d_1 = 0, f_1 = q + s, g_1 = p + r, \mu_1 = \xi + \alpha, \nu_1 = \eta + \beta,$$

$$a_2 = \frac{1}{2}(p^2 - q^2) - \alpha\beta, b_2 = \frac{1}{2}p_x - \varepsilon q(qs - pr + \alpha\eta + \xi\beta), c_2 = \frac{1}{2}q_x - \varepsilon p(qs - pr + \alpha\eta + \xi\beta),$$

$$\rho_2 = \alpha_x - \varepsilon\alpha(qs - pr + \alpha\eta + \xi\beta), \sigma_2 = -\beta_x - \varepsilon\beta(qs - pr + \alpha\eta + \xi\beta),$$

$$f_2 = \frac{1}{2}(r_x + p_x) - \beta\eta - \alpha\xi - \varepsilon(q + s)(qs - pr + \alpha\eta + \xi\beta), g_2 = \frac{1}{2}(s_x + q_x) + \beta\eta + \alpha\xi - \varepsilon(p + r)(qs - pr + \alpha\eta + \xi\beta),$$

$$\mu_2 = \alpha_x + \xi_x - \varepsilon(qs - pr + \alpha\eta + \xi\beta)(\alpha + \xi), \nu_2 = -\eta_x - \beta_x - \varepsilon(qs - pr + \alpha\eta + \xi\beta)(\eta + \beta),$$

$$d_2 = pr - qs + \frac{1}{2}(p^2 - q^2) + \eta\alpha - (\alpha + \xi)\beta.$$

For any integer $m \geq 1$, we take

$$V^{[m]} = (\lambda^m W)_+ + \Delta_m = \sum_{i=0}^m V_i + \Delta_m, \Delta_m = \begin{bmatrix} -\varepsilon d_{m+1} & 0 & 0 & 0 & 0 & 0 \\ 0 & \varepsilon d_{m+1} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & -\varepsilon d_{m+1} & 0 & 0 \\ 0 & 0 & 0 & 0 & \varepsilon d_{m+1} & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}. \quad (56)$$

Thus, the corresponding zero curvature equation (2.2) with \bar{U} , V defined in (53) and (56)

determine the complete system of the super NLS-mKdV integrable couplings

$$\begin{bmatrix} p_{tm} \\ q_{tm} \\ r_{tm} \\ s_{tm} \\ \alpha_{tm} \\ \beta_{tm} \\ \xi_{tm} \\ \eta_{tm} \end{bmatrix} = \begin{bmatrix} 2b_{m+1} - 2\varepsilon qd_{m+1} \\ 2c_{m+1} - 2\varepsilon pd_{m+1} \\ 2f_{m+1} - 2\varepsilon sd_{m+1} \\ 2g_{m+1} - 2\varepsilon rd_{m+1} \\ \rho_{m+1} - \varepsilon \alpha d_{m+1} \\ -\sigma_{m+1} + \varepsilon \beta d_{m+1} \\ \mu_{m+1} - \varepsilon \xi d_{m+1} \\ -\nu_{m+1} + \varepsilon \eta d_{m+1} \end{bmatrix}, \quad m \geq 0. \quad (57)$$

The first nonlinear super system is

$$\begin{aligned} p_{t_2} &= \frac{1}{2}q_{xx} + \alpha\alpha_x - \beta\beta_x + q(p^2 - q^2 - 2\alpha\beta) - 2\varepsilon[q(\xi\beta)_x + (\eta\alpha)_x + qp_x - pq_x + \alpha\beta_x + \beta\alpha_x \\ &\quad + \frac{1}{2}(sp_x - qr_x + rq_x) - sp_x + qp_x + ps_x + p_x(-pr + \xi\beta + \eta\alpha)] + 4\varepsilon^2[-q^2s(pr + \alpha\beta) \\ &\quad + q^2(ps - \eta\beta + \xi\alpha) + q\beta(\xi\eta\alpha - pr\xi + p(\xi - \eta) - p\alpha - p\alpha(q(\xi + \eta) + rq\eta)], \\ q_{t_2} &= \frac{1}{2}p_{xx} + \alpha\alpha_x + \beta\beta_x + p(p^2 - q^2 - 2\alpha\beta) - 2\varepsilon[p(\eta\alpha_x + \alpha\eta_x - qp_x + pq_x + \beta\xi_x + \xi\beta_x \\ &\quad + \beta\alpha_x + \alpha\beta_x - \frac{1}{2}((qr)_x + sp_x - ps_x) + 2q\eta\beta + 2(p - q)\xi\alpha) + q_x(qs + \xi\beta + \eta\alpha)] \\ &\quad + 4\varepsilon^2[p^2(ps - \alpha\eta + \xi\beta - \alpha\beta - \frac{1}{2}pr^2)pqs(-\alpha\eta - \alpha\beta - \beta\xi) - \frac{1}{2}pq^2s^2], \\ \alpha_{t_2} &= \alpha_{xx} + \frac{1}{2}(\beta q_x + 2q\beta_x + \beta p_x + 2p\beta_x) + \frac{1}{2}\alpha(p^2 - q^2) + \frac{1}{2}\varepsilon[\alpha(rq_x - r_xq + ps_x - sp_x - 2qp_x + 2pq_x \\ &\quad + 2\beta\alpha_x + 2\beta\xi_x + 2\xi\beta_x - 2\alpha_x\eta) + 4\alpha_x(pr - qs - \xi\beta) + 4\alpha\eta\beta(p + q)] \\ &\quad + 2\varepsilon^2\alpha[pr(pr - qs - \beta\xi) + qs(qs + 2\beta\xi) - p(qs + \beta\xi)], \\ \beta_{t_2} &= -\beta_{xx} + \frac{1}{2}\alpha(p_x - q_x) + \alpha_x(p - q) + \frac{1}{2}\beta(q^2 - p^2) + \frac{1}{2}\varepsilon[\beta(p_x s - sp_x + qr_x - q_x r - 2pq_x - 2q_x p - 2\beta\alpha_x \\ &\quad - 2\eta\alpha_x - 2\alpha\eta_x - 6\xi\beta_x) + 2\beta_x(pr - qs - \eta\alpha) + 4\beta\xi\alpha(q - p)] + 2\varepsilon^2\beta[pr(qs - pr + \eta\alpha) \\ &\quad + qs(\beta p - qs - 2\eta\alpha) - \eta\alpha p], \\ r_{t_2} &= \frac{1}{2}(q_{xx} + s_{xx}) + 2(\beta\eta)_x + \beta\beta_x - \alpha\alpha_x - q(3qs - q^2 + p^2 + 2pr - 2\alpha\beta + 2\eta\alpha - 2\xi\beta) + s(p^2 - 2\alpha\beta) + \varepsilon[s(q_x r \end{aligned}$$

$$\begin{aligned}
& -3qr_x - 4qp_x + 2s(ps_x + pq_x + \alpha\beta_x + \beta\alpha_x + \eta\alpha_x + \alpha\eta_x + \beta\xi_x + \xi\beta_x - \frac{1}{2}sp_x) + 2(pr - \eta\alpha - \xi\beta)(r_x + p_x) \\
& - 2(pr + ps)(\alpha\xi + \beta\eta) + 2ps(\eta\beta + \xi\alpha) + 4\eta\beta s(p + q) + 4\varepsilon^2[p^2r^2(s + q) + 2q^2s^2(q + 2s) + 2s^2q(\alpha\beta + 2\beta\xi \\
& + 2\alpha\eta - 2pr) + 4sq^2(\alpha\eta + \beta\xi - pr) - 4r(sp + pq)(\alpha\eta + \beta\xi) - 4ps(\alpha\eta + \beta\xi + qs) + 4\alpha\beta(ps + \eta\xi(q + s))], \\
s_{t_2} = & \frac{1}{2}(p_{xx} + r_{xx}) - 2(\beta\eta)_x - \beta\beta_x + \alpha\alpha_x + p(3pr - q^2 + p^2 - 2qs - 2\xi\beta + 2\eta\alpha - 2\alpha\beta) - r(q^2 + 2\alpha\beta) + \varepsilon[-r_xq \\
& + rq_x - p_xs - 2qp_x + 2\alpha\beta_x + 2\beta\alpha_x + 2\eta\alpha_x + 2\alpha\eta_x + 2\beta\xi_x + 2\xi\beta_x + 2pq_x + 3ps_x) - 2(qs + \eta\alpha + \xi\beta)(q_x + s_x) \\
& - 4q(r + s)(\xi\alpha + \beta\eta) + 8pr(\beta\eta + \alpha\xi)] + 4\varepsilon^2[2(q^2s^2 + p^2r^2)(p + 2r) - 4r^2p(\alpha\eta + \beta\xi + qs) \\
& - 4rp^2(\alpha\eta + \beta\xi + qs) + 4qs(p + 2r)(\alpha\eta + \beta\xi) + 4pr(\alpha\beta + \alpha\eta - \beta\xi - qs) + 4\alpha\beta(rqs + \eta\xi(p + r))], \\
\mu_{t_2} = & \alpha_{xx} + \xi_{xx} + \alpha(pr - qs - 2\xi\beta - \frac{1}{2}q^2 + \frac{1}{2}p^2) + \frac{1}{2}\xi(p^2 - q^2) + (\beta_x + \eta_x)(p + q) + \frac{1}{2}(\eta + \beta)(p_x + q_x) \\
& + \beta_x(r + s) + \frac{1}{2}\beta(r_x + s_x) + \varepsilon[\xi(\alpha\beta)_x + \eta\alpha_x + \alpha\eta_x - \beta\xi_x + pq_x - qp_x + \frac{1}{2}(q_xr - qr_x + ps_x - p_xs)] \\
& + (\alpha_x + \xi_x)(pr - qs) - 2\eta\alpha(\alpha_x + \xi_x) + 2\xi\eta\beta(p + q) - \varepsilon^2[2(q^2s^2 + p^2r^2)(\xi + \alpha) + 2\alpha pr(qs + \xi\eta - \beta\xi) \\
& + 2\alpha\xi(qs + p)(\eta + \beta) - \xi pqs(r + 1)], \\
\nu_{t_2} = & -\beta_{xx} - \eta_{xx} + \frac{1}{2}(\beta + \eta)(q^2 - p^2) + \frac{1}{2}(\alpha + \xi)(p_x - q^2) + (\alpha_x + \xi_x)(p - q) + \alpha_x(r - s) + \frac{1}{2}\beta(r_x - s_x) \\
& - \beta(pr - qs + 2\alpha\eta) + \varepsilon[-\eta(\beta\alpha_x + 3\alpha\beta_x + 3\alpha\eta_x + \beta\xi_x + \xi\beta_x + (pq)_x) + \frac{1}{2}(qr_x - q_xr + p_xs - p_xs)] \\
& - 2(\beta_x + \eta_x)(qs + \beta\xi - pr) - 3] + \varepsilon^2[-(q^2s^2 + p^2r^2)(\beta + 2\eta) + 2\eta pr(qs + \xi\beta + \alpha\beta) \\
& - 4\eta qs(\xi\beta + \alpha\beta) + 2\eta p(qs + \xi\beta - \alpha\beta + \alpha\xi) + \eta\xi\alpha q].
\end{aligned}$$

5 Conclusion

To present, there many methods to generate integrable couplings. In generally, the integrable couplings is a triangular integrable system:

$$\begin{cases} u_t = K(u), \\ v_t = S(u, v). \end{cases}$$

In this system, the first equation is about u and the second equation is about u and v . At present paper, we construct a kind of new coupled system

$$\begin{cases} u_t = \bar{K}(u, v), \\ v_t = \bar{S}(u, v), \end{cases} \quad (58)$$

by adding a perturbation term h in the spectral matrix, where h may be the combination of potential function and its derivatives. We call the system (58) "completion of the integrable couplings". For this system, its Hamiltonian structure can also be constructed by variable identity. This method can be applied to continuous integrable couplings, discrete integrable couplings and super integrable couplings. As an example, we generate the complete integrable system of the KN integrable coupling and construct its Hamiltonian structure by variable identity. As application, we also construct the completion of the KN integrable coupling, the WKI integrable couplings, vAKNS integrable couplings, the Volterra integrable couplings, Dirac type integrable couplings and NLS-mKdV type integrable couplings.

Acknowledgement

This work is in part supported by the national natural science foundation of China (Grant No 11371323, 11371326 and 11271226) and Beijing Municipal Natural Science Foundation (Grand No 1162003).

References

- [1] P. D. Lax, Integrals of nonlinear equations of evolution and solitary waves, *Comm.Pure Appl. Math.*, **21** (1968) 467-490.
- [2] W. X. Ma, Lax representations of hierarchies of evolution equations with Lienard recursive structures, *Acta Math. Sci.*, **14** (1994) 409-418.
- [3] A. Das, *Integrable Models* (World Scientific Publishing, Teaneck, NJ, 1989).

- [4] V. G. Drinfel'd and V.V. Sokolov, Equations of Korteweg-de Vries type and simple Lie algebras, *Soviet Math. Dokl.*, **23** (1981) 457-462.
- [5] W. X. Ma and B. Fuchssteiner, Integrable theory of the perturbation equations, *Chaos Solitons Fract.*, **7** (1996) 457-462.
- [6] W. X. Ma, Integrable couplings of soliton equations by perturbations. I-A general theory and application to the KdV hierarchy, *Method Appl. Anal.*, **7** (2000) 21-55.
- [7] F. K. Guo, Y. F. Zhang, A new loop algebra and a corresponding hierarchy, as well as its integrable couplings, *J. Math. Phys.*, **44** (2003) 5793-5803.
- [8] Y. F. Zhang and E. G. Fan, Coupling integrable couplings and bi-Hamiltonian structure associated to the Boiti-Pempinelli-Tu hierarchy, *J. Math. Phys.*, **51** (2010) 083506.
- [9] Hon-Wah Tam and Y. F. Zhang, An integrable system and associated integrable models as well as Hamiltonian structure, *J. Math. Phys.*, **513** (2012) 103508.
- [10] L. Luo and E. G. Fan, The algebraic structure of discrete zero curvature equations associated with integrable couplings and application to enlarged Volterra systems, *Science in China Series A: Math.*, **52** (2009) 147-159.
- [11] X. X. Xu and Y. P. Sun, An integrable coupling hierarchy of Dirac integrable hierarchy, its Liouville integrability and Darboux transformation, *Journal of Nonlinear Sciences and Applications*, **10** (2017) 3328-3343.
- [12] A. M. Wazwaz, Integrable couplings of the generalized Vakhnenko equation: multiple soliton solutions, *Journal of Vibration and Control*, **22** (2016) 915-919.
- [13] J. H. Zhang and Y. Q. Yao, The Bi-Integrable Couplings of Two-Component Casimir-Qiao-Liu Type Hierarchy and Their Hamiltonian Structures, *Advances in Math. Phys.*, (2016) 6347961.

- [14] H. Y. Wei and T. C. Xia, The generalized fractional trace variational identity and fractional integrable couplings of Kaup-Newell hierarchy, *J. Math. Phys.*, **55** (2014) 083501.
- [15] W. X. Ma, Integrable couplings and matrix loop algebras, *NONLINEAR AND MODERN MATHEMATICAL PHYSICS*, **1562** (2013) 105-122.
- [16] Y. F. Zhang and H. Tam, A few new higher-dimensional Lie algebras and two types of coupling integrable couplings of the AKNS hierarchy and the KN hierarchy, *COMMUNICATIONS IN NONLINEAR SCIENCE AND NUMERICAL SIMULATION*, **16** (2011) 76-85.
- [17] F. K. Guo and Y. F. Zhang, A unified expressing model of the AKNS hierarchy and the KN hierarchy, as well as its integrable coupling system, *Chaos Solitons and Fractals*, **19** (2011) 1207-1216.
- [18] W. X. Ma and Y. Zhang, Component-trace identity for Hamiltonian structures, *Appl. Anal.*, **89** (2010) 457-472.
- [19] Ma, W. X. (2013) Lie algebra structures associated with zero curvature equations and generalized zero curvature equations. *British J. Sci. Tech.*, **3**, 1336-1344.
- [20] T. C. Xia, F. J. Yu and D. Y. Chen, The multi-component generalized Wadati-Konono-Ichikawa (WKI) hierarchy and its multi-component integrable couplings system with two arbitrary functions, *Chaos Solitons and Fractals*, **24** (2005) 877-883.
- [21] H. Y. Zhu, S. M. Yu, S. F. Shen and W. X. Ma, New integrable $sl(2, \mathbb{R})$ generalization of the classical Wadati-Konno-Ichikawa, *Commun. Nonlinear Sci. Numer. Simulat.*, **22** (2015) 1341-1349.
- [22] W. X. Ma, Integrable couplings of vector AKNS soliton equations, *J. Math. Phys.*, **46** (2005) 033507.

- [23] S. F. Shen, C. X. Li, Y. Y. Jin and S. M. Yu, Multi-component integrable couplings for the Ablowitz-Kaup-Newell-Segur and Volterra hierarchies, *Mathematical Methods in the Applied Sciences*, **38** (2015) 4345-4356.
- [24] Y. Q. Yao, Y. F. Zhang and D. Y. Chen, Discrete integrable couplings of the Volterra lattice, *Chinese Physics Letters*, **24** (2007) 308-311.
- [25] A. P. Fordy, Quantum Super-Integrable Systems as Exactly Solvable Models, *SYMMETRY INTEGRABILITY AND GEOMETRY-METHODS AND APPLICATIONS* , **3** (2007) 025.
- [26] Q. P. Liu, On the integrable hierarchies associated with the N=2 super W-n algebra, *Phy. Lett. A* , **235** (1997) 335-340.
- [27] G. Khimshiashvili and r. Przybysz, On certain super-integrable Hamiltonian systems, *Phy. Lett. A* , **8** (2002) 217-244.
- [28] F. C. You, Nonlinear Super Integrable Couplings of Super Dirac Hierarchy and Its Super Hamiltonian Structures, *Commun. Theor. Phys.*, **57** (2012) 961-966.
- [29] H. H. Dong and X. Z. Wang, Lie algebras and Lie super algebra for the integrable couplings of NLS-MKdV hierarchy , *COMMUNICATIONS IN NONLINEAR SCIENCE AND NUMERICAL SIMULATION*, **14** (2009) 4071-4077.