

Holomorphic fractional Fourier transforms

William D. Kirwin*, José Mourão, João P. Nunes[†] and Thomas Thiemann[‡]

May 13, 2019

Abstract

The Fractional Fourier Transform (FrFT) has widespread applications in areas like signal analysis, Fourier optics, diffraction theory, etc. The Holomorphic Fractional Fourier Transform (HFrFT) proposed in the present paper may be used in the same wide range of applications with improved properties. The HFrFT of signals spans a one-parameter family of (essentially) holomorphic functions, where the parameter takes values in the bounded interval $t \in (0, \pi/2)$. At the boundary values of the parameter, one obtains the original signal at $t = 0$ and its Fourier transform at the other end of the interval $t = \pi/2$. If the initial signal is L^2 , then, for an appropriate choice of inner product that will be detailed below, the transform is unitary for all values of the parameter in the interval. This transform provides a heat kernel smoothening of the signals while preserving unitarity for L^2 -signals and continuously interpolating between the original signal and its Fourier transform.

Contents

1	Introduction and Results	1
2	Holomorphic fractional Fourier transforms	4
3	Relation to the classical Segal-Bargmann transform	6
4	Explicit formulas in the basis of Hermite functions	8

1 Introduction and Results

In the present paper, we propose an holomorphic version of the Fractional Fourier Transform which will be a one-parameter family of functional transforms that interpolate between a function in $L^2(\mathbb{R}, dx)$ and its Fourier transform. At intermediate values of the parameter the

*Center for Mathematical Analysis, Geometry and Dynamical Systems, Instituto Superior Técnico, University of Lisbon, will.kirwin@gmail.com

[†]Department of Mathematics and Center for Mathematical Analysis, Geometry and Dynamical Systems, Instituto Superior Técnico, University of Lisbon, jmourao & jpnunes@math.tecnico.ulisboa.pt

[‡]Lehrstuhl für Theoretische Physik III, FAU Erlangen-Nürnberg, thomas.thiemann@gravity.fau.de

transform will yield, up to a multiplicative common factor, holomorphic functions on the complex plane.

Recall that the Fractional Fourier transform (FrFT) [Co] is a group of unitary transforms,

$$\mathcal{F}_t : L^2(\mathbb{R}) \longrightarrow L^2(\mathbb{R}), \quad t \in \mathbb{R},$$

periodic in t with period π , interpolating continuously from the identity at values $t = 0$, to the Fourier transform at $t = \frac{\pi}{2}$ and satisfying the group property,

$$\mathcal{F}_t \circ \mathcal{F}_s = \mathcal{F}_{t+s}.$$

The Fractional Fourier Transform (FrFT) has widespread applications in many areas of physics and engineering like signal analysis, Fourier optics, diffraction theory, etc. (see e.g. [Al, Co, DeB, OKM, Z]).

Our contribution in this work is two-fold:

- i) Propose a family of holomorphic Fractional Fourier Transforms (HFrFT), $A_t, t \in [0, \frac{\pi}{2}]$, which may be used in the same wide range of applications as the FrFT but with improved properties, as the HFrFT of signals span a one-parameter family of holomorphic functions, with the original signal and its Fourier transform being the boundary values of the family, at $t = 0$ and $t = \frac{\pi}{2}$ respectively. If the initial signal is L^2 then the transform is unitary for all values of the parameter in the interval. This transform provides a heat kernel smoothening of the signals and of their Fourier transforms while preserving unitarity for L^2 -signals and continuously interpolating between the original signal and its Fourier transform.
- ii) We show that the family of HFrFT transforms includes the original Segal–Bargmann transform, which is attained at the value $t = \pi/4$. The Segal-Bargmann transform has been applied to signal analysis before (see, for example, [SV]), where the use of the machinery of holomorphic function theory allows for nice inversion formulas and for the definition of numerically useful truncations. Recall that the original Segal-Bargmann transform is, in fact, a particular member of a natural continuous one-parameter family of holomorphic transforms, SB_s , labelled by $s > 0$. While this fact has apparently not been used in signal analysis, its relevance in that context is indicated by the fact that as $s \rightarrow +\infty$ the transforms SB_s approach the Fourier transform [KW].

In fact, in Theorem 3.2, we show that for $s = \tan(t)$, and up to a signal-independent factor, A_t coincides with SB_s . In the geometric context of [KMNT] where the transforms A_t arise and that we very briefly describe below, this corresponds to a highly non-trivial operator identity. Therefore, it becomes very natural, in the context of the Segal-Bargmann transform, to consider the parameter $t = \arctan(s)$ taking values in $t \in [0, \frac{\pi}{2}]$, such that at the finite value $t = \frac{\pi}{2}$ the Fourier transform is attained. The family of holomorphic transforms that we describe below corresponds, in fact, to this reparametrization of the family of Segal-Bargmann transforms, making the fact that they are HFrFT much more suggestive.

Therefore, while the usual FrFT takes L^2 functions to L^2 functions, the HFrFT that we are proposing maps L^2 signals to functions which, for $t \in (0, \frac{\pi}{2})$ and up to a common factor,

are holomorphic in the complex plane. At $t = \frac{\pi}{2}$ we recover the Fourier transform of the L^2 signal.

The following observations will not be used in the main text but we include them to explain the context in which the HFrHF arises. The original motivation for introducing the HFrFT [KMNT] comes from the field of geometric quantization. In fact, by examining explicit formulae, for example in [Co, DeB], one can check that the FrFT can be naturally interpreted as relating quantizations of the symplectic plane with wave functions (essentially) depending on rotated (polarized, in the terminology of geometric quantization) arguments

$$\psi_0(x) \mapsto \tilde{\psi}_t(x, p) = \psi_t(\cos(t)x + \sin(t)p). \quad (1.1)$$

This transform includes a functional change $\psi_0 \mapsto \psi_t$ and a rotation of the initial argument x by the flow φ_t generated by the harmonic oscillator Hamiltonian, $H = \frac{1}{2}(p^2 + x^2)$,

$$\varphi_t^*(x) = \cos(t)x + \sin(t)p. \quad (1.2)$$

For $t = \pi/2$ one gets the usual Fourier transform, while, for instance, values $t_k = \pi/2k$ are interpreted as k th roots of the Fourier transform. The level sets of ψ_t are lines which rotate counter-clockwise with t , starting with vertical lines parallel to p -axis at $t = 0$, which corresponds to the x -dependent wave functions of usual Schrödinger quantization, and becoming horizontal lines parallel to the x -axis at $t = \frac{\pi}{2}$ as appropriate for the p -dependent wave functions of quantization in momentum space. The different axis in the (x, p) plane which appear in the FrFT are therefore generated by the Hamiltonian flow of the harmonic oscillator. The explicit form of the FrFT then follows by applying methods of geometric quantization (for example as in [FMMN, KW, KMN13, KMNT]).

By considering Hamiltonian flows analytically continued to complex time [Th96, Th07, HK, MN15], or flows associated with complex Hamiltonians, one can deform continuously wave functions depending on x , i.e. in Schrödinger quantization, to wave functions depending holomorphically on a complex coordinate on the plane. These holomorphic wave functions give Hilbert spaces of so-called coherent states and, for quadratic Hamiltonians, they satisfy appropriate L^2 conditions on the plane, ensuring that the deformation is unitary. For the HFrFT that we propose in this paper, we consider the analytic continuation to complex time of the Hamiltonian flow of the hyperbolic Hamiltonian $H = \frac{1}{2}(p^2 - x^2)$ [KMNT]. The real time evolution of the function x under the flow $\tilde{\varphi}_t$ generated by this Hamiltonian is

$$\tilde{\varphi}_t^*(x) = \cosh(t)x + \sinh(t)p.$$

We see that by rotating t to the imaginary axis we get

$$\tilde{\varphi}_{-it}^*(x) = \cos(t)x + i \sin(t)p, \quad (1.3)$$

a periodic rotation very similar to the one of (1.2) but with the crucial difference that it takes place on the (x, ip) -plane instead of the (x, p) -plane. For $t \in (0, \pi/2)$ the variable $\cos(t)x + i \sin(t)p$ is associated with a Kähler polarization with holomorphic wave functions, while for $t = 0$ and $t = \pi/2$ the polarizations are real and coincide with the Schrödinger (functions of x) and the momentum representation (functions of p).

2 Holomorphic fractional Fourier transforms

Consider the usual inner product¹ in $L^2(\mathbb{R}, dx)$ normalized as

$$\langle f_1, f_2 \rangle = \sqrt{\pi} \int_{\mathbb{R}} \bar{f}_1(x) f_2(x) dx. \quad (2.1)$$

As in [GrSc12, GKRS, KMNT], let us consider an overcomplete system of normalized Gaussian coherent states in $L^2(\mathbb{R}, dx)$

$$\psi_Y(x) = \pi^{-\frac{1}{2}} e^{-iP(x-Q) - \frac{1}{2}(x-Q)^2}, \quad Y = (P, Q) \in \mathbb{R}^2. \quad (2.2)$$

The HFrFT defined below will take values in a space of functions on the (x, p) -plane which, up to an overall common factor, are holomorphic with respect to appropriate complex structures, as follows. For $t \in (0, \frac{\pi}{2})$, let us consider the holomorphic coordinate on the plane

$$w_t = \cos(t)x + i \sin(t)p.$$

Let us consider the measure

$$d\mu_t = \frac{\sqrt{\sin(2t)}}{2} dx dp,$$

the Hilbert space $L^2(\mathbb{R}^2, d\mu_t)$ and let

$$F_t(x, p) = e^{\frac{(w_t - \bar{w}_t)^2}{4 \sin(2t)}} = e^{-\frac{\tan(t)}{2} p^2}.$$

Denoting by Hol_t the space of complex-valued w_t -holomorphic functions on the plane, consider the vector space of functions on the plane

$$V_t = \{F_t \cdot f \mid f \in Hol_t\}.$$

We then have the following Hilbert space

$$\mathcal{H}_t = V_t \cap L^2(\mathbb{R}, d\mu_t).$$

Therefore, elements in \mathcal{H}_t are w_t -holomorphic functions on the plane, up to a multiplicative Gaussian factor F_t .

Let us now define the HFrFT².

Definition 2.1 For $t \in (0, \frac{\pi}{2})$, the HFrFT

$$A_t : L^2(\mathbb{R}, dx) \rightarrow \mathcal{H}_t,$$

is defined, in the overcomplete basis of coherent states (2.2), by

$$\begin{aligned} (A_t \psi_Y)(x, p) &= \alpha_t e^{-iP_t(w_t - Q_t)} e^{-\frac{\cot(\frac{\pi}{4} + t)}{2} (w_t - Q_t)^2} e^{-\frac{\tan(t)}{2} w_t^2} F_t \\ &= \beta_t e^{-iP(x-Q)} e^{-\frac{\sin(t)(p-P)^2 + \cos(t)(x-Q)^2 + 2i \sin(t)(x-Q)(p-P)}{2\sqrt{2} \sin(\frac{\pi}{4} + t)}}, \end{aligned} \quad (2.3)$$

where

$$\begin{aligned} \alpha_t &= (\sqrt{2\pi} \sin(\frac{\pi}{4} + t))^{-\frac{1}{2}} e^{\frac{\sin(2t)}{4} (P^2 + Q^2)} e^{i \sin^2(t) PQ}, \\ \beta_t &= (\sqrt{2\pi} \sin(\frac{\pi}{4} + t))^{-\frac{1}{2}} \end{aligned}$$

and $Y = (P, Q) \in \mathbb{R}^2$, $Q_t = \cos(t) Q + i \sin(t) P$, $P_t = \sin(t) Q + i \cos(t) P$.

¹The factor of $\sqrt{\pi}$ is inserted for convenience.

²In [KMNT], we used the notation U_τ with $\tau = it$.

While, here, we have defined the HFrFT on the overcomplete basis of simple Gaussian coherent states, an intrinsic definition of the HFrFT can be obtained as follows. Namely, let $W \subset L^2(\mathbb{R}, dx)$ be the dense subspace given by the span of the normalized Gaussian coherent states $\{\psi_Y\}_{Y \in \mathbb{R}^2}$. Then, intrinsically, one can define [KMNT]

$$A_t : W \rightarrow \mathcal{H}_t$$

by

$$A_t = e^{t\rho(H)} \circ e^{-t\hat{H}},$$

where

$$\rho(H) = i \left(p \frac{\partial}{\partial x} + x \frac{\partial}{\partial p} \right), \quad \hat{H} = \frac{1}{2} \left(-\frac{\partial^2}{\partial x^2} - x^2 \right),$$

are two (first and second order, respectively) differential operators naturally associated to the quantization of the hyperbolic Hamiltonian $H(x, p) = \frac{1}{2}(p^2 - x^2)$, mentioned in the Introduction, realizing a lifting of the canonical transformation in imaginary time (1.3) to the space of quantum states.

We will also see below in Theorem 3.2 that the relation of the HFrFT with the Segal-Bargmann transform (3.1), (3.2) could also be used to give an intrinsic definition of HFrFT.

Remark 2.2 Notice that the level sets of the modulus of the transformed Gaussians on the (x, p) -plane are ellipses whose major axis, for $t \in (0, \frac{\pi}{4})$, are vertical and decrease in length as t increases, so that, as the ellipses become circles, they become equal in length to the horizontal minor axis at $t = \frac{\pi}{4}$. For $t \in (\frac{\pi}{4}, \frac{\pi}{2})$ the major axis becomes horizontal and increases with t . As $t \rightarrow 0$ or $t \rightarrow \frac{\pi}{2}$ the eccentricity converges to 1. At $t = 0$ the level sets are vertical lines while at $t = \frac{\pi}{2}$ they are horizontal lines. This is an holomorphic version of and should be compared with the (usual non-holomorphic) FrFT where the vertical p -axis rotates counter-clockwise to the horizontal x -axis through a family of straight lines, as mentioned in the Introduction. \diamond

We then have

Theorem 2.3 [KMNT] *For each $t \in (0, \frac{\pi}{2})$, A_t is a unitary isomorphism of Hilbert spaces*

$$L^2(\mathbb{R}, dx) \stackrel{A_t}{\cong} \mathcal{H}_t.$$

By letting t approach the right-end of the interval, $t \rightarrow \frac{\pi}{2}$, we obtain (up to phase) the usual Fourier transform.

Definition 2.4 [KMNT] *By allowing $t = \frac{\pi}{2}$ in (2.3) we obtain (and define) for the Gaussian coherent states*

$$(A_{\frac{\pi}{2}} \psi_Y)(p, x) := \lim_{t \rightarrow \frac{\pi}{2}} (A_t \psi_Y)(p, x) = \pi^{-\frac{1}{2}} e^{-iP(x-Q)} \cdot e^{-i(x-Q)(p-P)} \cdot e^{-\frac{1}{2}(p-P)^2}, \quad (2.4)$$

for $Y = (P, Q)$.

Consider now the Fourier transform

$$\mathcal{F} : L^2(\mathbb{R}, dx) \rightarrow L^2(\mathbb{R}, dp) \quad (2.5)$$

$$f \mapsto (\mathcal{F}(f))(p) = \frac{1}{\sqrt{2\pi}} \int_{\mathbb{R}} e^{ipx} f(x) dx. \quad (2.6)$$

By evaluating the Fourier transform of the Gaussian coherent states we establish

Proposition 2.5 [KMNT] *The transformation $A_{\frac{\pi}{2}}$ coincides, up to a phase, with the Fourier transform, namely, for $f \in L^2(\mathbb{R}, dx)$, we have*

$$(A_{\frac{\pi}{2}}(f))(x, p) = e^{-ipx} (\mathcal{F}(f))(p).$$

Therefore, by taking

$$A_0 = Id_{L^2(\mathbb{R}, dx)},$$

we have a one-parameter family of unitary transforms, $\{A_t\}_{t \in [0, \frac{\pi}{2}]}$, such that for the $t \in (0, \frac{\pi}{2})$ the range is, essentially, a Hilbert space of holomorphic functions on the plane and $A_{\frac{\pi}{2}}$ is, up to a phase, the Fourier transform.

3 Relation to the classical Segal-Bargmann transform

As we now recall, the original Segal-Bargmann transform [B] is also contained in a one-parameter family of transformations SB_s , where $s \in [0, +\infty)$, with $SB_0 = Id_{L^2(\mathbb{R}, dx)}$ [Ha00a, Ha00b, Ha06, Dr, FMMN, KW].

Consider the complex structure on the plane given by the following holomorphic coordinate

$$z_s = x + isp, \quad s \in [0, +\infty)$$

and let \widetilde{Hol}_s be the space of z_s -holomorphic functions on the plane.

Note that, for $\tan(t) = s$, the coordinates w_t, z_s are holomorphic functions of each other,

$$w_t = \cos(t)z_s,$$

so that indeed, for t, s obeying this relation, $\widetilde{Hol}_s = Hol_t$.

Recall that the Segal-Bargmann transforms can be written as [Ha00a, Ha00b, Ha06]

$$SB_s = \mathcal{C}_s \circ e^{\frac{s}{2}\Delta}, \quad s \in [0, +\infty), \quad (3.1)$$

where Δ is the Euclidian Laplacian on the plane and where \mathcal{C}_s denotes analytic continuation in the z_s coordinate. The transform is therefore obtained by applying the heat kernel operator, which takes functions in $L^2(\mathbb{R}, dx)$ to real-analytic functions, and then by analytically continuing in z_s .

For $s > 0$, let us consider the Hilbert space

$$\tilde{\mathcal{H}}_s = \{f \in \widetilde{Hol}_s \mid \sqrt{s} \int_{\mathbb{R}^2} \overline{f(z_s)} f(z_s) e^{-sp^2} dx dp < \infty\}.$$

Then,

Theorem 3.1 [B, Ha00a, Ha00b, Ha06, Dr] For each $s > 0$, the transform SB_s is a unitary isomorphism of Hilbert spaces

$$L^2(\mathbb{R}, dx) \stackrel{SB_s}{\cong} \tilde{\mathcal{H}}_s.$$

We then have the remarkable identity

Theorem 3.2 Let $s > 0$, $t \in [0, \frac{\pi}{2})$, be such that $\tan(t) = s$. For $Y \in \mathbb{R}^2$ recall the Gaussian states ψ_Y in (2.2). Then,

$$A_t(\psi_Y) = (1 + s^2)^{\frac{1}{4}} e^{-\frac{s}{2}p^2} SB_s(\psi_Y). \quad (3.2)$$

Proof. In [KMNT], we consider a family of transforms U_τ depending on a parameter α . The explicit expression for $SB_s(\psi_Y)$ can be obtained from the family of transforms U_τ by taking a limit $\alpha \rightarrow 0$ with $\tau = is$. One then obtains, straightforwardly from [KMNT],

$$SB_s(\psi_Y)(x, p) = (\pi(1+s))^{-\frac{1}{2}} e^{\frac{s}{2}p^2} e^{-iP(x-Q)} e^{-\frac{1}{2}\frac{s}{1+s}(p-P)^2 - \frac{1}{2}\frac{1}{1+s}(x-Q)^2 - i\frac{s}{1+s}(x-Q)(p-P)}.$$

The result then follows by direct comparison of the exponents in the Gaussians, using the relation $s = \tan(t)$. ■

Remark 3.3 From the perspective of [KMNT], Theorem 3.2 contains a highly non-trivial, and surprising, realization of the Segal-Bargmann transforms. While, as described above, SB_s is given by the composition of the (smoothing) heat-kernel operator with the operator of analytic continuation in the variable z_s , the Theorem states that it can also be described by the composition of an unbounded operator (associated to the hyperbolic Hamiltonian $H = \frac{1}{2}(p^2 - x^2)$) and the operator of analytic continuation in the variable w_t . ◇

It has been shown [KW] that in the limit $s \rightarrow +\infty$, indeed, the Segal-Bargmann transform SB_s converges to the Fourier transform (up to a phase). The family of transforms

$$\{SB_s\}_{s>0}$$

is then also a family of holomorphic fractional³ Fourier transforms. However, in this case the Fourier transform is reached only in the limit $s \rightarrow \infty$. The geometric context of [KMNT], however, as we described above, gives a motivation for taking seriously the simple reparametrization

$$t = \arctan(s),$$

so that $t \in [0, \frac{\pi}{2}]$, with the Fourier transform now being reached in “finite time”.

One important point of this work is that while the fractional Fourier transforms of [Co] give a family of transforms mapping L^2 signals to L^2 signals, the holomorphic version that we are proposing takes L^2 signals to a family of signals which are holomorphic on the plane and, when t reaches the value $\frac{\pi}{2}$, one recovers the Fourier transformed signal. Therefore, for $t \in (0, \frac{\pi}{2})$, we get a smoothening of the original signal.

Remark 3.4 While in this paper we have, for the sake of simplicity, considered signals in $L^2(\mathbb{R}, dx)$, it is clear that results and formulas generalize straightforwardly to $L^2(\mathbb{R}^n, d^n x)$. ◇

³“Fractional” in the parameter $t = \arctan(s)$.

4 Explicit formulas in the basis of Hermite functions

In this Section we collect useful formulas for the transform SB_s (or, equivalently, for the transform A_t where $s = \tan(t)$) and, in particular, we express it in a basis of Hermite functions.

From [Ha00b], using the heat-kernel explicitly, one obtains, for $f \in L^2(\mathbb{R}, dx)$,

$$(SB_s(f))(z_s) = (2s)^{-\frac{1}{2}}\pi^{-\frac{3}{4}} \int_{\mathbb{R}} e^{-\frac{(z_s-x)^2}{2s}} f(x) dx.$$

For $s > 0$, let us consider the orthonormal basis for $L^2(\mathbb{R}, dx)$, $\{h_n^s\}_{n \in \mathbb{N}_0}$, given by the Hermite functions

$$h_n^s(x) = a_{s,n} H_n^s(x) e^{-\frac{x^2}{4s}},$$

where $a_{s,n} = (2s)^{-\frac{1}{4}}(\pi n!)^{-\frac{1}{2}} s^{\frac{n}{2}}$ and the Hermite polynomials are given by (see, for example, [Ha00b, Ab])

$$H_n^s(x) = s^{-n} e^{-\frac{s}{2} \frac{d^2}{dx^2}} \cdot x^n = (-1)^n e^{\frac{x^2}{2s}} \frac{d^n}{dx^n} e^{-\frac{x^2}{2s}} = s^{-n} \left(x - s \frac{d}{dx} \right)^n \cdot 1.$$

Note that since $e^{-\frac{s}{2} \frac{d^2}{dx^2}}$ is the inverse heat operator we have

$$SB_s(H_n^s) = s^{-n} z_s^n.$$

Proposition 4.1 *We have for $s > 0$, $n \in \mathbb{N}_0$,*

$$(SB_s(h_n^s))(z_s) = d_{s,n} z_s^n e^{-\frac{z_s^2}{6s}},$$

where $d_{s,n} = (-1)^n a_{s,n} s^{-n} \pi^{-\frac{1}{4}} 6^{-\frac{1}{2}} 3^{-n}$.

Proof. From the expression for SB_s we obtain,

$$(SB_s(h_n^s))(z_s) = a_{s,n} (2s)^{-\frac{1}{2}} \pi^{-\frac{3}{4}} \int_{\mathbb{R}} e^{-\frac{(z_s-x)^2}{2s}} e^{-\frac{x^2}{4s}} \left(\left(x - s \frac{d}{dx} \right)^n \cdot 1 \right) dx.$$

Using

$$\left(x + s \frac{d}{dx} \right) e^{-\frac{1}{2s}(\sqrt{\frac{3}{2}}x - \sqrt{\frac{2}{3}}z_s)^2} = \left(-\frac{1}{3}z_s + \frac{s}{2} \frac{d}{dz_s} \right) e^{-\frac{1}{2s}(\sqrt{\frac{3}{2}}x - \sqrt{\frac{2}{3}}z_s)^2}$$

and integrating by parts one obtains

$$(SB_s(h_n^s))(z_s) = a_{s,n} (2s)^{-\frac{1}{2}} \pi^{-\frac{3}{4}} e^{-\frac{z_s^2}{6s}} \left(-\frac{1}{3}z_s + \frac{s}{2} \frac{d}{dz_s} \right)^n \int_{\mathbb{R}} e^{-\frac{1}{2s}(\sqrt{\frac{3}{2}}x - \sqrt{\frac{2}{3}}z_s)^2} dx,$$

from which the result follows by evaluating the Gaussian integral. ■

Therefore, given a signal $f \in L^2(\mathbb{R}, dx)$ with expansion

$$f = \sum_{k=0}^{+\infty} f_k h_k^s,$$

we have

$$(SB_s(f))(z_s) = \sum_{n=0}^{+\infty} d_{s,n} f_n z_s^n e^{-\frac{z_s^2}{6s}}.$$

The inverse formula for SB_s is (see, for example, Theorem 4 in [Ha06])

$$(SB_s^{-1}g)(x) = 2^{-\frac{1}{2}} \pi^{-\frac{1}{4}} s^{\frac{1}{2}} \lim_{R \rightarrow +\infty} \int_{-R}^R g(z_s) e^{-s\frac{p^2}{2}} dp.$$

Acknowledgements

The authors JM and JPN were partially by FCT/Portugal through the projects UID/MAT/-04459/2013, PTDC/MAT-GEO/3319/2014, PTDC/MAT-OUT/28784/2017 and by the (European Cooperation in Science and Technology) COST Action MP1405 QSPACE. The authors also thank the generous support from the Emerging Field Project on Quantum Geometry from Erlangen–Nürnberg University, where this project was initiated.

References

- [Ab] G.T.F. Abreu, *Closed-form correlation functions of generalized hermite wavelets*, IEEE Trans. Signal Process. **53** (2005) 2258–2261.
- [Al] L.B. Almeida, *The fractional Fourier transform and time-frequency representations*, IEEE Trans. on Signal Process. **42** (1994) 3084–3091.
- [B] V. Bargmann, *On a Hilbert space of analytic functions and an associated integral transform, Part I*, Comm. Pure Appl. Math. **14** (1961) 187–214.
- [Co] E.U. Condon, *Immersion of the Fourier transform in a continuous group of functional transformations*, Proc. Nat. Acad. Sc. **23** (1937) 158–164.
- [DeB] H. De Bie, *Clifford algebras, Fourier transforms and quantum mechanics*, Math. Methods in the Applied Sciences **35** (2012) 2198–2228.
- [Dr] B. Driver, *On the Kakutani-Itô-Segal-Gross and Segal-Bargmann-Hall isomorphisms*, J. Funct. Anal. **133** (1995) 69–128.
- [FMMN] C. Florentino, P. Matias, J. Mourão and J. P. Nunes, *On the BKS pairing for Kähler quantizations of the cotangent bundle of a Lie group*, J. Funct. Anal. **234** (2006) 180–198.
- [GKRS] E.-M. Graefe, H. J. Korsch, A. Rush, R. Schubert, *Classical and quantum dynamics in the (non-Hermitian) Swanson oscillator*, J. Phys. A **48** (2015), no. 5, 055301.
- [GrSc12] E.-M. Graefe, R. Schubert, *Complexified coherent states and quantum evolution with non-Hermitian Hamiltonians*, J. Phys. A **45** (2012) 244033.

- [Ha00a] B. C. Hall, *Harmonic analysis with respect to heat kernel measure*, Bull. Amer. Math. Soc. **38** (2000) 43–78.
- [Ha00b] B. C. Hall, *Holomorphic methods in analysis and mathematical physics*, in *First Summer School in Analysis and Mathematical Physics*, S. Pérez-Esteva and C. Villegas-Blas, Eds., Contemp. Math. 260, Amer. Math. Soc., 2000., 1–59.
- [Ha06] B. C. Hall, *The range of the heat operator*, in *The ubiquitous heat kernel*, Contemp. Math. (2006) **398** 203–231.
- [HK] B. C. Hall and W. Kirwin, *Adapted complex structures and the geodesic flow*, Math. Ann. (2011) **350** (2011) 455–474.
- [KMN13] W. D. Kirwin, J. M. Mourão, and J. P. Nunes, *Complex time evolution in geometric quantization and generalized coherent state transforms*, J. Funct. Anal. **265** (2013) 1460–1493.
- [KMNT] W. Kirwin, J. Mourão, J. P. Nunes and T. Thiemann, *Segal-Bargmann transforms from hyperbolic Hamiltonians*, preprint 2019.
- [KW] W. D. Kirwin and S. Wu, *Geometric quantization, parallel transport and the Fourier transform*, Comm. Math. Phys. **266** (2006) 577–594.
- [MN15] J. Mourão and J. P. Nunes, *On complexified Hamiltonian flows and geodesics on the space of Kähler metrics*, Int. Math Res. Not. (2015), No. 20, 10624–10656.
- [OKM] H.M. Ozaktas, M. A. Kutay and D. Mendlovic, *Introduction to the Fractional Fourier Transform and Its Applications*, Adv. in Imaging and Electron Phys. **106** (1999) 239–291.
- [SV] L.K. Stergioulas and A. Vourdas, *The Bargmann analytic representation in signal analysis*, J. Comput. and Appl. Math. **167** (2004) 183–192.
- [Th96] T. Thiemann, *Reality conditions inducing transforms for quantum gauge field theory and quantum gravity*, Class.Quant.Grav. **13** (1996) 1383–1404.
- [Th07] T. Thiemann, *Modern canonical quantum general relativity*, Cambridge University Press, Cambridge, 2007.
- [Z] Y. Zhang et al, *A Comprehensive Survey on Fractional Fourier Transform*, Fundamenta Informaticae **151** (2017) 1–48.