

The α -Lomax Distribution: A Compound Channel Model

Osamah S. Badarneh and Daniel Benevides da Costa

Abstract—In this paper, we propose the α -Lomax distribution as a new compound fading channel model. This new distribution generalizes the recently introduced Lomax fading channel model. It is worth noting that the Lomax distribution is a decreasing function, while the α -Lomax is a unimodal function, offering greater flexibility in modeling wireless fading channels. In particular, we derive closed-form expressions for the probability density function and cumulative distribution function for the instantaneous signal-to-noise ratio (SNR). Additionally, we provide closed-form expressions for several fundamental performance metrics, including outage probability, average bit error rate, and channel capacity. Furthermore, we derive closed-form expression for the average block-length error rate in short-packet communications. Moreover, we fit the PDF of the proposed channel model to empirical data obtained from a device-to-device communication system. We also offer simple and accurate approximations for these expressions in the high SNR regime.

Index Terms—Compound fading, Gamma distribution, Lomax distribution, Rayleigh distribution, wireless communications.

I. INTRODUCTION

The efficiency and reliability of wireless systems significantly depend on the characteristics of the wireless channel through which data is transmitted. As such, wireless channel modeling plays a pivotal role in the design, optimization, and performance evaluation of wireless communication systems.

In the literature, many distributions are available that effectively describe the statistics of wireless fading channels. Very recently, the Lomax distribution was proposed as a potential model for characterizing wireless fading channels [1], [2]. To achieve this goal, the authors redefined the Lomax parameters for channel modeling. Subsequently, they provided closed-form expressions for its fundamental statistics, which were then employed to assess the performance of wireless communication systems. In [3], the Fisher–Snedecor \mathcal{F} distribution was introduced to model composite fading channels, where the root-mean-square power fluctuation of a Nakagami- m signal is assumed to be influenced by an inverse Nakagami- m random variable (RV). In [4], the authors introduced the α - μ fading distribution, which generalizes the Nakagami- m fading model by considering the nonlinearity of the propagation medium. In the literature, the Rayleigh fading distribution was used to model the conditions of strong scattering [5]. Compound distributions, which involve two distributions, were introduced to offer distributions with more realistic tails. One of these distributions is the \mathcal{K} distribution [6], in which the envelope fluctuations of the Rayleigh distribution follow a gamma random variable (RV), characterizing shadowing effects [7].

Despite the fact that the Lomax distribution is a decreasing function, it finds utility in various wireless applications [1],

[2], including ultra-reliable and low-latency communications (URLLC), content delivery within device-to-device (D2D) communications, enabling cooperative spectrum sensing in cognitive radio networks, and assessing bit error performance in the presence of interference.

Motivated by the above, in this paper, we propose a generalization of the Lomax distribution, which we call the α -Lomax distribution. In this distribution, the reciprocal of the variance in the Rayleigh distribution follows a Gamma RV, and the resulting signal power is obtained as the modulus raised to a certain given power, represented by the parameter α . Furthermore, the α -Lomax distribution can take the form of either a decreasing function or a unimodal function, depending on its parameters. As a result, it offers greater flexibility for modeling wireless fading channels when compared to its counterpart, the Lomax distribution. The contributions of this paper can be summarized as follows:

- Closed-form expressions for the probability density function (PDF) and cumulative distribution function (CDF) of the instantaneous signal-to-noise ratio (SNR) are derived.
- Closed-form expressions of some key performance metrics, such as outage probability, average bit error rate (BER), and average channel capacity, are attained. Additionally, a closed-form expression for the average block error rate (BLER) in short-packet communications is derived.
- Tight approximations at high SNR regime are derived for the achieved performance metrics.
- A physical model for generating samples of the α -Lomax distribution is introduced.

The rest of this paper is structured as follows: In Section II, it is provided a physical description of the Lomax fading distribution and then introduce the α -Lomax fading model. Additionally, it is derived the PDF and CDF of the instantaneous SNR as well as some statistical metrics, including generalized moment generating function (MGF), and n -th moment. Closed-form expressions for the outage probability, average BER, and average channel capacity are derived in Section III. Furthermore, simple and accurate approximations at high SNR regime are attained. In Section V, we present results and discussions to validate our analysis. Finally, Section VI concludes this work.

II. THE α -LOMAX FADING DISTRIBUTION

The works in [1] and [2] lack details regarding the physical generation of the Lomax distribution. Therefore, in this section, we first present a physical model for the aforementioned distribution, and then we define the α -Lomax fading distribution. The Lomax fading distribution arises when the

reciprocal of the variance in the Rayleigh distribution follows a Gamma random variable (RV). Thus, one can define the signal power, P , of the Lomax distribution as follows¹:

$$P = R^2 = X^2 + Y^2, \quad (1)$$

where R is the signal envelope, X and Y are mutually independent Gaussian processes, with mean $\mathbb{E}[X] = \mathbb{E}[Y] = 0$ and variance $\mathbb{E}[X^2] = \mathbb{E}[Y^2] = \frac{1}{2\tau}$, where $\mathbb{E}[\cdot]$ denotes expectation and τ follows the Gamma distribution whose PDF is given by

$$f_\tau(\tau) = \frac{\beta^\lambda}{\Gamma(\lambda)} \tau^{\lambda-1} \exp(-\beta\tau), \quad \tau > 0, \quad (2)$$

where $\beta > 0$ and $\lambda > 0$ are, respectively, the scale and shape parameters that determine the severity of the fading channel. $\Gamma(\cdot)$ is the gamma function [9, Eq. (8.310.1)].

Lemma 1. *The PDF and CDF of the signal power Z for the α -Lomax distribution are given as follows, respectively:*

$$f_Z(z) = \alpha \lambda \zeta z^{\alpha-1} (1 + \zeta z^\alpha)^{-(\lambda+1)}, \quad (3)$$

and

$$F_Z(z) = 1 - (1 + \zeta z^\alpha)^{-\lambda}, \quad (4)$$

where $\alpha > 0$ represents non-linearity of the propagating medium and $\zeta = \left(\frac{\Gamma(1+\frac{1}{\alpha})\Gamma(\lambda-\frac{1}{\alpha})}{\Gamma(\lambda)}\right)^\alpha$ and $\lambda > \frac{1}{\alpha}$.

Proof: See the Appendix. ■

Lemma 2. *The PDF and CDF of the instantaneous SNR for the α -Lomax distribution are given as follows, respectively:*

$$f_\Gamma(\gamma) = \frac{\alpha\lambda\zeta}{\bar{\gamma}^\alpha} \gamma^{\alpha-1} \left(1 + \frac{\zeta}{\bar{\gamma}^\alpha} \gamma^\alpha\right)^{-(\lambda+1)} \quad (5)$$

and

$$F_\Gamma(\gamma) = 1 - \left(1 + \frac{\zeta}{\bar{\gamma}^\alpha} \gamma^\alpha\right)^{-\lambda}, \quad (6)$$

where $\bar{\gamma} = \mathbb{E}[\Gamma] = \frac{P_t}{N_0}$ denotes the average SNR, P_t is the transmit power, and N_0 is the noise power.

Proof: See the Appendix. ■

To the best of the authors' knowledge, (5) and (6) represent new findings. It is important to note that the PDF in (5) is unimodal when $\alpha > 1$ and a decreasing function when $0 < \alpha \leq 1$. Additionally, it's worth mentioning that when $\alpha = 1$, (5) and (6) exactly coincide with [2, Eq. (4)] and [2, Eq. (5)], respectively. Furthermore, since the Lomax distribution, when $\alpha = 1$, is a decreasing function, it is expected that the α -Lomax distribution can provide a better description of the fading channel.

¹Unlike the α -Lomax, in [3], [8], The fluctuations of the envelope of the Nakagami- m distribution, when the variance is fixed, follow an inverse Nakagami RV.

Lemma 3. *The generalized MGF of the instantaneous SNR can be expressed as follows:*

$$\mathcal{M}_\Gamma^n(s) = \frac{\alpha}{s^n \Gamma(\lambda)} H_{2,1}^{1,2} \left[\frac{\zeta}{\bar{\gamma}^\alpha s^\alpha} \middle| \begin{matrix} (1-\lambda, 1), (1-n, \alpha) \\ (1, 1) \end{matrix} \right], \quad (7)$$

where $H_{2,1}^{1,2}[\cdot]$ denotes the Fox H-function [10, Eq. (8.3.1.1)].

Proof: See the Appendix. ■

Lemma 4. *The n -th moment of the instantaneous SNR is given by*

$$\mathbb{E}[\Gamma^n] = \bar{\gamma}^n \frac{\lambda}{\zeta^\alpha} \mathfrak{B}\left(1 + \frac{n}{\alpha}, \lambda - \frac{n}{\alpha}\right), \quad (8)$$

where $\mathfrak{B}(\cdot, \cdot)$ denotes the Beta function [9, Eq. (8.384.1)].

Proof: See the Appendix. ■

III. PERFORMANCE ANALYSIS

A. Outage Probability Analysis

The outage probability (OP) can be defined as the probability of the data rate of a communication link falls below a specified rate R_0 [bps/Hz], i.e., $\mathbb{P}_{\text{out}} \triangleq \Pr(\gamma \leq \gamma_0) = F_\Gamma(\gamma_0)$, where $\Pr(\cdot)$ denotes probability and $\gamma_0 = 2^{R_0} - 1$. Using (6), the OP can be readily obtained as

$$\mathbb{P}_{\text{out}} = 1 - \left(1 + \frac{\zeta}{\bar{\gamma}^\alpha} \gamma_0^\alpha\right)^{-\lambda}. \quad (9)$$

At high SNR values, i.e., when $\bar{\gamma} \rightarrow \infty$, the OP has the form of $\mathbb{P}_{\text{out}} \approx (G_c \bar{\gamma})^{-G_d}$, where G_c and G_d are, respectively, the coding and diversity gains. Thus, using (9), a simple approximation for the OP can be obtained as

$$\mathbb{P}_{\text{out}}^\infty \approx \left(\frac{1}{\gamma_0 \zeta^\alpha \lambda^\alpha} \bar{\gamma}\right)^{-\lambda}. \quad (10)$$

Based on (10), $G_c = \frac{1}{\gamma_0 \zeta^\alpha \lambda^\alpha}$ and $G_d = \alpha$. Note that the system's diversity gain depends only on α , which means that increasing α will result in a significant change in performance.

B. Bit Error Rate Analysis

Assuming coherent binary modulations, the average BER \bar{P}_b , can be obtained using

$$\bar{P}_b = \frac{1}{\pi} \int_0^{\frac{\pi}{2}} \mathcal{M}_\Gamma\left(\frac{\varphi}{\sin^2 \theta}\right) d\theta, \quad (11)$$

where φ is modulation-dependent parameter. For coherent binary phase-shift keying (BPSK), $\varphi = 1$, whereas for coherent binary frequency shift keying (BFSK), $\varphi = 0.5$, and for coherent detection of minimum shift keying (MSK), also known as BFSK with minimum correlation, $\varphi = 0.715$. Setting $n = 0$ in (7) and substituting the result in (11), it yields

$$\bar{P}_b = \frac{\alpha}{\pi \Gamma(\lambda)} \int_0^{\frac{\pi}{2}} H_{2,1}^{1,2} \left[\frac{\zeta \sin^{2\alpha} \theta}{\bar{\gamma}^\alpha \varphi^\alpha} \middle| \begin{matrix} (1-\lambda, 1), (1, \alpha) \\ (1, 1) \end{matrix} \right] d\theta. \quad (12)$$

Using the change of variable $x = \sin^2 \theta$ and applying [10, Eq. (2.25.2.2)], a closed-form expression for the average BER can be derived as

$$\overline{P}_b = \frac{\alpha}{2\pi\Gamma(\lambda)} \mathbf{H}_{4,2}^{1,4} \left[\frac{\zeta}{\overline{\gamma}^\alpha \varphi^\alpha} \middle| \begin{matrix} (\frac{1}{2}, \alpha), (\frac{1}{2}, 0), (1-\lambda, 1), (1, \alpha) \\ (1, 1), (0, \alpha) \end{matrix} \right]. \quad (13)$$

At high SNR values, the average BER can be approximated by $\overline{P}_b \approx (G_c \overline{\gamma})^{-G_d}$. Thus, applying [11, Eq. (1.8.4)] to (13), the average BER can be simply approximated by

$$\overline{P}_b \approx \left(\left(\frac{2\varphi^\alpha \sqrt{\pi}}{\lambda \zeta \Gamma(\frac{1}{2} + \alpha)} \right)^{\frac{1}{\alpha}} \overline{\gamma} \right)^{-\alpha}. \quad (14)$$

Hence, $G_c = \left(\frac{2\varphi^\alpha \sqrt{\pi}}{\lambda \zeta \Gamma(\frac{1}{2} + \alpha)} \right)^{\frac{1}{\alpha}}$ and confirms that the system's diversity gain is $G_d = \alpha$, as obtained in the outage probability analysis.

C. Average Channel Capacity Analysis

The average channel capacity, in [bps/Hz], can be found using

$$\overline{C} = \frac{1}{\ln(2)} \int_0^\infty \ln(1 + \gamma) f_\Gamma(\gamma) d\gamma. \quad (15)$$

Substituting (5) into (15), applying respectively [10, Eq. (8.4.6.5)], [10, Eq. (8.4.2.5)], [10, Eq. (2.25.1.1)], and [10, Eq. (8.3.2.8)], the following expression is obtained for the average channel capacity

$$\overline{C} = \frac{\alpha}{\ln(2)\Gamma(\lambda)} \mathbf{H}_{3,3}^{3,2} \left[\frac{\zeta}{\overline{\gamma}^\alpha} \middle| \begin{matrix} (1-\lambda, 1), (0, \alpha), (1, \alpha) \\ (1, 1), (0, \alpha), (0, \alpha) \end{matrix} \right]. \quad (16)$$

When $\overline{\gamma} \rightarrow \infty$, the average channel capacity can be approximated by

$$\overline{C} \approx \frac{1}{\ln(2)} \int_0^\infty \ln(\gamma) f_\Gamma(\gamma) d\gamma. \quad (17)$$

Substituting (5) into (17) and using [12, Eq. (2.6.4.7)], the approximated average channel capacity can be expressed as

$$\overline{C} \approx \frac{1}{\alpha \ln(2)} \left[\ln \left(\frac{\overline{\gamma}^\alpha}{\zeta} \right) - \gamma_E - \Psi(\lambda) \right], \quad (18)$$

where γ_E [9, Eq. (8.367.1)] and $\Psi(\cdot)$ [9, Eq. (8.360.1)] are the Euler's constant and digamma function, respectively.

IV. SHORT-PACKET COMMUNICATIONS

Short-packet, i.e., finite block-length, can support ultra-reliable communications. For such communications, the BLER can be accurately approximated by

$$\text{BLER} \simeq \begin{cases} 1, & \gamma \leq \mu \\ \frac{1}{2} - \frac{\delta}{\sqrt{2\pi}}(\gamma - \eta), & \mu < \gamma < v \\ 0, & \gamma \geq v \end{cases} \quad (19)$$

where $\mu = \eta - \sqrt{\frac{\pi}{2\delta^2}}$, $v = \eta + \sqrt{\frac{\pi}{2\delta^2}}$, $\eta = 2^{\frac{K}{N}} - 1$, $\delta = \sqrt{\frac{N}{2\pi}} \left(2^{\frac{2K}{N}} - 1 \right)^{-\frac{1}{2}}$, N and K are respectively represent the

block-length and the number of information bits in each finite block-length. Therefore, over fading channels, the average BLER can be expressed as

$$\overline{\text{BLER}} \simeq \int_0^\mu f_\Gamma(\gamma) d\gamma - \frac{\delta}{\sqrt{2\pi}} \int_\mu^v \gamma f_\Gamma(\gamma) d\gamma + \left(\frac{1}{2} + \frac{\delta\eta}{\sqrt{2\pi}} \right) \int_\mu^v f_\Gamma(\gamma) d\gamma. \quad (20)$$

The first integral represents the CDF of Γ evaluated at μ . Now, when substituting (5) into (20), then an integral of the following form has to be solved. That is,

$$\mathcal{I} = \int_\mu^v \gamma^{p+\alpha-1} \left(1 + \frac{\zeta}{\overline{\gamma}^\alpha} \gamma^\alpha \right)^{-(\lambda+1)} d\gamma, \quad (21)$$

where $p \in \{0, 1\}$. To the best of authors' knowledge, no solution to this integral is available in the literature. To this end, we represent the quantity $\left(1 + \frac{\zeta}{\overline{\gamma}^\alpha} \gamma^\alpha \right)^{-(\lambda+1)}$ in terms of Meijer G-function using [10, Eq. (8.4.2.5)] and then applying the definition of the Meijer G-function [10, Eq. (8.2.1.1)]. Thus, (21) becomes

$$\mathcal{I} = \frac{1}{\Gamma(\lambda+1)} \frac{1}{\mathbb{J}2\pi} \oint_{\mathcal{L}} \left(\frac{\zeta}{\overline{\gamma}^\alpha} \right)^s \Gamma(-s) \Gamma(1+\lambda+s) \times \int_\mu^v \gamma^{p+\alpha+\alpha s-1} d\gamma ds. \quad (22)$$

The inner integral w.r.t. γ can be solved as

$$\int_\mu^v \gamma^{p+\alpha+\alpha s-1} d\gamma = \frac{\Gamma\left(\frac{p+\alpha}{\alpha} + s\right) (v^{p+\alpha+\alpha s} - \mu^{p+\alpha+\alpha s})}{\alpha \Gamma\left(1 + \frac{p+\alpha}{\alpha} + s\right)}. \quad (23)$$

Substituting (23) into (22), representing the result in terms of the Meijer G-function [10, Eq. (8.2.1.1)], and applying [10, Eq. (8.4.49.13)], the final expression for the average BLER can be obtained as

$$\overline{\text{BLER}} \simeq F_\Gamma(\mu) - c_1 \left\{ v^{\alpha+1} \Theta^{(1)} \left(\frac{\zeta v^\alpha}{\overline{\gamma}^\alpha} \right) - \mu^{\alpha+1} \Theta^{(1)} \left(\frac{\zeta \mu^\alpha}{\overline{\gamma}^\alpha} \right) \right\} - c_2 \left\{ v^\alpha \Theta^{(0)} \left(\frac{\zeta v^\alpha}{\overline{\gamma}^\alpha} \right) - \mu^\alpha \Theta^{(0)} \left(\frac{\zeta \mu^\alpha}{\overline{\gamma}^\alpha} \right) \right\}, \quad (24)$$

where $c_1 = \frac{\delta\alpha\lambda\zeta}{\sqrt{2\pi}(1+\alpha)\overline{\gamma}^\alpha}$, $c_2 = \left(\frac{1}{2} + \frac{\delta\eta}{\sqrt{2\pi}} \right) \frac{\lambda\zeta}{\overline{\gamma}^\alpha}$, and $\Theta^{(p)}(x) = {}_2F_1(1+\lambda; \frac{p+\alpha}{\alpha}; \frac{p+2\alpha}{\alpha}; -x)$, with ${}_2F_1(\cdot)$ being the hypergeometric function [9, Eq. (9.14.2)]. At high SNR values, the asymptotic average BLER can be accurately obtained in a simple form as

$$\overline{\text{BLER}} \approx \frac{\zeta\lambda\mu^\alpha}{\overline{\gamma}^\alpha} - c_1 \{v^{\alpha+1} - \mu^{\alpha+1}\} - c_2 \{v^\alpha - \mu^\alpha\}. \quad (25)$$

Clearly, the system diversity gain depends only on α .




Fig. 1. Outdoor NLoS empirical and theoretical PDFs fitted to D2D communication systems [14, Fig. 12].

V. RESULTS AND DISCUSSIONS

This section is dedicated to validating the mathematical derivations, specifically, the derived analytical expressions for the PDF of the instantaneous SNR, the outage probability, average BER, average channel capacity, and average BELR for short-packet communications. These expressions are evaluated and compared with Monte-Carlo simulations. Most importantly, the discussions in this section offer deeper insights into the obtained results.

As a practical application, the PDF of the α -Lomax is fitted to empirical data obtained from D2D communication systems, as shown in Fig. 1. Additionally, the PDF of the \mathcal{K} distribution [6, Eq. (43)] is also fitted. The \mathcal{K} distribution is chosen because it is a compound distribution, similar to the α -Lomax. To assess the quality of fit between the theoretical PDFs and the empirical PDF, we calculate the Resistor-Average Distance (RAD) [13]. The results show that the RAD values for the α -Lomax and \mathcal{K} distributions are respectively $\text{RAD} = 3.3 \times 10^{-3}$ and $\text{RAD} = 22.5 \times 10^{-3}$, indicating that the α -Lomax offers a better fit to the empirical data compared to the \mathcal{K} distribution.

The SNR PDF is plotted in Fig. 2 for different values of α , by setting $\lambda = 1.25$. Clearly, when $\alpha \leq 1$, the SNR PDF is a decreasing function, while for $\alpha > 1$, the SNR PDF is a unimodal function. Moreover, as α increases, the SNR PDF moves toward the right, indicating better fading conditions. Additionally, the analytical curves of the SNR PDF are in perfect agreement with Monte-Carlo simulation results, validating our analysis and the physical model of the α -Lomax relationship.

The impact of λ on the SNR PDF is depicted in Fig. 3. It can be observed that as λ increases, the SNR PDF slightly shifts to the right, compared to the effect of α , as shown earlier. This observation indicates a slight improvement in channel conditions. Next, we demonstrate that the impact of




Fig. 2. α -Lomax SNR PDF under varying α with $\lambda = 1.25$.




Fig. 3. α -Lomax SNR PDF under varying λ with $\alpha = 2$.

α on the system performance is more pronounced than that of λ . Fig. 4 illustrates the influence of both parameters, α and λ , on the outage probability. The results indicate that the outage performance improves as α and (or) λ increases. Furthermore, it is noteworthy that increasing α has a more pronounced impact when compared to λ , whereas the effect of λ becomes insignificant at higher values of α . Additionally, the asymptotic curves closely match the analytical curves, particularly at high SNR values. Moreover, the slope of the asymptotic curves changes only as α varies, remaining constant with λ , thus confirming our finding in Eq. (10).

Fig. 5 illustrates the average BER across different coherent binary modulation schemes. These findings confirm the accuracy of the derived analytical BER expression and the validity of the asymptotic analysis. Additionally, the results indicate that the diversity gain (i.e., the slope of the asymptotic curves) is independent of the type of modulation.

Fig. 6 illustrates the variation in the average channel ca-




Fig. 4. Outage performance for different values of α and λ . $R_0 = 1$ [bps/Hz].




Fig. 5. Average BER performance for various modulation schemes with $\alpha = 1.75$ and $\lambda = 1.25$.

capacity of the α -Lomax fading channel across different values of α . We also include the capacity of the AWGN channel as a reference point. Notably, as α grows, the average channel capacity experiences enhancement, eventually converging to that of the AWGN channel, particularly when α reaches a high value, such as $\alpha = 7$.

In Fig. 7, the average BLER performance for short-packet communications shows improvement as the block length increases, as expected. Furthermore, the results validate our analysis's accuracy.

VI. CONCLUSIONS

In this paper, we introduced a new compound fading channel model known as the α -Lomax. In this fading channel model, the reciprocal of the variance in the Rayleigh distribution is represented by a Gamma RV, and the resulting signal power is not simply obtained as the modulus of the




Fig. 6. Average channel capacity for different values of α .




Fig. 7. Average BLER in short-packet communications.

sum of the in-phase and quadrature components. Instead, it is obtained as the modulus raised to a certain given power, represented by the parameter α . The α -Lomax includes the Lomax fading channel model as a special case, offering more flexibility in modeling wireless fading channels.

APPENDIX

Proof of Lemma 1: First, let's derive the signal power PDF of the Lomax distribution². To this end, the PDF of (1) can be found using

$$f_P(p) = \int_0^\infty f_P(p | \tau) f_\tau(\tau) d\tau, \quad (26)$$

where $f_P(p | \tau) = \tau \exp(-p\tau)$ is the conditional signal power, which follows an exponential RV. Substituting this

²Alternatively, it can be generated when $\mathbb{E}[X^2] = \mathbb{E}[Y^2] = \tau/2$, τ follows the inverse Gamma; that is, $f_\tau(\tau) = \frac{\beta^\lambda}{\Gamma(\lambda)} \frac{1}{\tau^{\lambda+1}} \exp(-\frac{\beta}{\tau})$ and $f_P(p | \tau) = \frac{1}{\tau} \exp(-\frac{p}{\tau})$.

and (2) into (26), it yields

$$f_P(p) = \frac{\beta^\lambda}{\Gamma(\lambda)} \int_0^\infty \tau^\lambda \exp(-(\beta + p)\tau) d\tau \stackrel{(a)}{=} \frac{\lambda/\beta}{\left(1 + \frac{p}{\beta}\right)^{\lambda+1}}, \quad (27)$$

where (a) is obtained using [9, Eq. (3.381.4)].

The α -Lomax fading distribution is defined as $H \triangleq P^{\frac{1}{\alpha}}$. Thus, applying transformation of RVs to (27), the PDF of H can be found as

$$f_H(h) = \frac{\alpha\lambda}{\beta} h^{\alpha-1} \left(1 + \frac{h^\alpha}{\beta}\right)^{-(\lambda+1)}, \quad y > 0. \quad (28)$$

For the purpose of channel modeling, let's redefine the PDF in (28) as follows: Let $Z = \frac{H}{\Omega}$, where $\Omega = \mathbb{E}[H]$ denotes the statistical average of H , which can be obtained as

$$\mathbb{E}[H] = \frac{\beta^{\frac{1}{\alpha}} \Gamma(1 + \frac{1}{\alpha}) \Gamma(\lambda - \frac{1}{\alpha})}{\Gamma(\lambda)}. \quad (29)$$

Using the transformation of RVs and after algebraic manipulations, the PDF, $f_Z(z)$, in (3), can be readily obtained. Finally, the CDF in (4) can be directly obtained from (3) through proper integration. This completes the proof of Lemma 1.

Proof of Lemma 2: We define the instantaneous SNR as $\Gamma \triangleq \bar{\gamma} Z$. Thus, one can obtain the desired PDF of the instantaneous SNR, in (5), using $f_\Gamma(\gamma) = \frac{1}{\bar{\gamma}} f_Z\left(\frac{\gamma}{\bar{\gamma}}\right)$. While the CDF, in (6), can be obtained using $F_\Gamma(\gamma) = F_Z\left(\frac{\gamma}{\bar{\gamma}}\right)$, which ends the proof of Lemma 2.

Proof of Lemma 3: The generalized MGF can be found by substituting (5) into $M_\Gamma^n(s) = \int_0^\infty \gamma^n f_\Gamma(\gamma) \exp(-\gamma s) d\gamma$, and sequentially applying [10, Eq. (8.4.2.5)] and [10, Eq. (8.3.2.21)], and using [10, Eq. (2.25.2.3)].

Proof of Lemma 4: The n -th moment can be obtained by substituting (5) into $\mathbb{E}[\Gamma^n] = \int_0^\infty \gamma^n f_\Gamma(\gamma) d\gamma$, and using [9, Eq. (3.194.3)].

REFERENCES

- [1] I. Sanchez and F. J. Lopez-Martinez, "The Lomax distribution for wireless channel modeling: a preliminary study," in *Proc. IEEE ECTM*, Ambato, Ecuador, Oct. 2023, pp. 1–5.
- [2] —, "The Lomax distribution for wireless channel modeling: Theory and applications," *IEEE Open J. Veh. Technol.*, pp. 1–9, Dec. 2023.
- [3] S. K. Yoo, S. Cotton, P. Sofotasios, M. Matthaiou, M. Valkama, and G. Karagiannidis, "The Fisher-Snedecor \mathcal{F} distribution: A simple and accurate composite fading model," *IEEE Commun. Lett.*, vol. 21, no. 7, pp. 1661–1664, Jul. 2017.
- [4] M. D. Yacoub, "The α - μ distribution: a general fading distribution," in *Proc. IEEE PIMRC*, Sep. 15-18 2002, pp. 629–629.
- [5] F. Hansen and F. Meno, "Mobile fading—Rayleigh and lognormal superimposed," *IEEE Trans. Veh. Technol.*, vol. 26, no. 4, pp. 332–335, Nov. 1977.
- [6] A. Abraham, "Modeling non-Rayleigh reverberation," SR-266, SACLANT Undersea Research Center, La Spezia, Italy, Tech. Rep., 1997.
- [7] A. Abdi and M. Kaveh, "On the utility of gamma PDF in modeling shadow fading (slow fading)," in *Proc. IEEE VTC*, vol. 3, Houston, TX, USA, May 1999, pp. 2308–2312.
- [8] O. S. Badarneh, "The α - \mathcal{F} composite fading distribution: Statistical characterization and applications," *IEEE Trans. Veh. Technol.*, vol. 69, no. 8, pp. 8097–8106, Aug. 2020.
- [9] I. S. Gradshteyn and I. M. Ryzhik, *Table of Integrals, Series, and Products*, 7th ed. Academic Press, California, 2007.
- [10] A. P. Prudnikov, Y. A. Brychkov, and O. I. Marichev, *Integrals, and Series: More Special Functions*. Gordon & Breach Sci. Publ., New York, 1990, vol. 3.
- [11] A. Kilbas and M. Saigo, *H-Transforms: Theory and Applications (Analytical Method and Special Function)*, 1st ed. CRC Press, 2004.
- [12] A. P. Prudnikov, Y. A. Brychkov, and O. I. Marichev, *Integrals, and Series: More Special Functions*. Gordon & Breach Sci. Publ., New York, 1981, vol. 1.
- [13] D. Johnson and S. Sinanovic, "Symmetrizing the kullback-leibler distance," Rice University, Tech. Rep., 2001.
- [14] N. Bhargava *et al.*, "On the product of two κ - μ random variables and its application to double and composite fading channels," *IEEE Trans. Wirel. Commun.*, vol. 17, no. 4, pp. 2457–2470, Apr. 2018.