

# Reconfigurable Intelligent Surface Assisted VEC Based on Multi-Agent Reinforcement Learning

Kangwei Qi, Qiong Wu, *Senior Member, IEEE*, Pingyi Fan, *Senior Member, IEEE*,  
Nan Cheng, *Senior Member, IEEE*, Qiang Fan, Jiangzhou Wang, *Fellow, IEEE*

**Abstract**—Vehicular edge computing (VEC) is an emerging technology that enables vehicles to perform high-intensity tasks by executing tasks locally or offloading them to nearby edge devices. However, obstacles such as buildings may degrade the communications and incur communication interruptions, and thus the vehicle may not meet the requirement for task offloading. Reconfigurable intelligent surfaces (RIS) is introduced to support vehicle communication and provide an alternative communication path. The system performance can be improved by flexibly adjusting the phase-shift of the RIS. For RIS-assisted VEC system where tasks arrive randomly, we design a control scheme that considers offloading power, local power allocation and phase-shift optimization. To solve this non-convex problem, we propose a new deep reinforcement learning (DRL) framework that employs modified multi-agent deep deterministic policy gradient (MADDPG) approach to optimize the power allocation for vehicle users (VUs) and block coordinate descent (BCD) algorithm to optimize the phase-shift of the RIS. Simulation results show that our proposed scheme outperforms the centralized deep deterministic policy gradient (DDPG) scheme and random scheme.

**Index Terms**—Reconfigurable intelligent surface (RIS), vehicular edge computing (VEC), multi-agents deep reinforcement learning (MA-DRL).

## I. INTRODUCTION

VEHICLE edge computing (VEC) is considered to be a promising technology in supporting vehicle real-time computing. It can offload tasks to VEC servers with rich computation and storage resources when the local CPU capacity of the vehicle is limited [1], [2]. However, in some scenarios, the vehicle user (VU) is impacted by blocking obstacles such as buildings, making it unable to communicate with base station (BS) in a timely manner within a certain distance [3], so that it cannot offload tasks in time.

Recently, reconfigurable intelligent surface (RIS) technology has shown significant advantages in enhancing the com-

munication quality by provisioning an additional communication link to VU by adjusting phase-shifts [4]. Therefore, the VEC system with RIS deserves extensive research. However, due to limited hardware, the phase-shift of the RIS can only be selected from a limited number of values [5]. In addition, the vehicle mobility and uncertain environment pose significant challenges. Therefore, the joint RIS phase-shift and power allocation optimization is a difficult problem to handle. For the optimization problem of RIS phase-shift, in [6], He *et al.* employed algorithms such as block coordinate descent (BCD), alternating optimization (AO), and semi definite relaxation (SDR) to solve it. In addition, for the VEC power allocation problem, deep reinforcement learning (DRL) algorithms are considered as an effective solution. In [7], Zhu *et al.* used the deep deterministic policy gradient (DDPG) algorithm to allocate the offloading power and local power of a single VU, thereby achieving the minimal total power and buffer length. However, in scenarios with multiple vehicle users, the centralized algorithms do not have advantages any more [8].

In this letter, we investigate the RIS assisted VEC problem and propose a multi-agent DRL scheme with joint BCD<sup>1</sup>. To simplify the problem, we decompose it into two sub problems: VEC power allocation problem and RIS phase-shift matrix optimization problem. To address it, we first use the BCD algorithm to optimize the RIS phase-shift matrix, and then use the modified multi-agent DDPG (MADDPG) algorithm to solve the power allocation problem for vehicle offloading and local execution. The extensive simulations demonstrate that the proposed scheme is superior to the centralized DDPG algorithms in terms of rewards, convergence speed, stability, and other aspects.

## II. SYSTEM MODEL AND PROBLEM FORMULATION

### A. Scenario

As shown in Fig. 1, we consider a RIS-assisted VEC network with multiple users, where the BS has  $M$  antennas and is associated with a VEC server, and the VU has a single antenna. Since a VU has limited computational resources, it can offload some tasks to the VEC server for processing. When the VU's link is obstructed, it cannot communicate with the BS directly and efficiently, where a RIS with  $N$  reflective elements can assist the VU in offloading tasks to the edge devices (we only consider one link, the VU communicating with the BS via the RIS). Here, we consider an urban intersection scenario

This work was supported in part by the National Natural Science Foundation of China under Grant No. 61701197, in part by the National Key Research and Development Program of China under Grant No.2021YFA1000500(4), in part by the 111 Project under Grant No. B12018.

Kangwei Qi, Qiong Wu are with the School of Internet of Things Engineering, Jiangnan University, Wuxi 214122, China. (e-mail: kangweiqi@stu.jiangnan.edu.cn, qiongwu@jiangnan.edu.cn).

Pingyi Fan is with the Department of Electronic Engineering, Beijing National Research Center for Information Science and Technology, Tsinghua University, Beijing 100084, China (e-mail: fpy@tsinghua.edu.cn).

Nan Cheng is with the State Key Lab. of ISN and School of Telecommunications Engineering, Xidian University, Xi'an 710071, China (e-mail: dr.nan.cheng@ieee.org).

Qiang Fan is with Qualcomm, San Jose, CA 95110, USA (e-mail: qf9898@gmail.com).

Jiangzhou Wang is with the School of Engineering, University of Kent, CT2 7NT Canterbury, U.K. (email: j.z.wang@kent.ac.uk).

<sup>1</sup>The source code has been released at: <https://github.com/qiongwu86/RIS-VEC-MARL.git>




Fig. 1. RIS aided vehicular edge computing

where VUs are randomly distributed at the intersection, where there are  $K$  VUs, denoted by the set  $\mathcal{K} = \{1, 2, \dots, K\}$ . The VU has the flexibility to offload the tasks for processing and local execution, and additionally, we divide the task processing into  $T$  equally time slots  $\Delta t$  of discrete time, denoted by  $\mathcal{T} = \{1, 2, \dots, T\}$ . At each time slot  $t$ , the vehicle randomly generates a kind of tasks, where task arrivals follow a Poisson distribution with an arrival rate of  $\eta$ . Note that we consider quasi-static scenarios where the channel conditions keep constant within a time slot but may change between the different time slots.

### B. Queue Model

For VU  $k$ , we assume that its task arrival rate at time slot  $t$  is  $\eta_k(t)$ , which follows a Poisson distribution, so we can calculate the tasks of VU  $k$  during time slot  $t$  as

$$a_k(t) = \eta_k(t) \times \Delta t. \quad (1)$$

The arriving tasks will be saved in the buffer, and processed at time slot  $t + 1$ , thus we can get the buffer length of VU  $k$  at time slot  $t + 1$  is

$$q_k(t + 1) = [q_k(t) - q_{k,o}(t) - q_{k,l}(t)]^+ + a_k(t), \quad (2)$$

where  $q_{k,o}(t)$  and  $q_{k,l}(t)$  denote the amount of tasks processed by task offloading and locally, respectively. Note that  $[x]^+ = \max(0, x)$ .

### C. Offloading Model

In our proposed model, it is assumed that the location of the  $k$ th vehicle is  $(x_k^t, y_k^t, z_k^t)$  at time slot  $t$ , and the coordinates of the BS and the RIS are  $(BS_x, BS_y, BS_z)$  and  $(RIS_x, RIS_y, RIS_z)$ , respectively. While the link between BS and RIS is line-of-sight(LoS), the link between RIS and the vehicles is the same. Therefore, these communication links undergo small-scale fading, which is modeled as the Rician fading with the pure LoS component [26], [27]. Since both the RIS and the BS are deployed at a fixed location, the RIS-BS link will remain static. Therefore, we can obtain the channel gain  $\mathbf{h}_{r,b}$  between the RIS and BS as

$$\mathbf{h}_{r,b} = \sqrt{\rho(d_{r,b})^{-\alpha_{r,b}}} \sqrt{\frac{R}{1+R}} \mathbf{h}_{r,b}^{LoS}. \quad (3)$$

where  $\rho$  is the path loss at reference distance  $d_0 = 1m$ ,  $d_{r,b}$  is the geometric distance from the RIS to the BS,  $\alpha_{r,b}$  is the path loss exponent of the RIS-BS link, and  $R$  is the Rician coefficient associated with small-scale fading. LoS components  $\mathbf{h}_{r,b}^{LoS}$  is defined as follows:

$$\mathbf{h}_{r,b}^{LoS} = [1, e^{-j\frac{2\pi}{\lambda}d_r \sin(\theta_{r,b})}, \dots, e^{-j\frac{2\pi}{\lambda}(N-1)d_r \sin(\theta_{r,b})}]^T, \quad (4)$$

where  $\lambda$  is the carrier length,  $d_r$  is the interval between RIS elements, and  $\theta_{r,b}$  is the departure angle of the signal from the RIS to the BS. Similarly, the channel gain  $\mathbf{h}_{k,r}^t$  from the  $k$ th VU to the RIS at time slot  $t$  is defined as

$$\mathbf{h}_{k,r}^t = \sqrt{\rho(d_{k,r}^t)^{-\alpha_{k,r}}} \sqrt{\frac{R}{1+R}} \mathbf{h}_{k,r}^{LoS}, \forall k \in \mathcal{K}, \forall t \in \mathcal{T}. \quad (5)$$

Here,  $d_{k,r}^t$  is the geometric distance between the  $k$ th vehicle and the RIS at time slot  $t$ , and  $\alpha_{k,r}$  is the path loss exponent between the vehicle and the RIS. Note that  $\mathbf{h}_{k,r}^{LoS}$  is expressed as follows

$$\mathbf{h}_{k,r}^{LoS} = [1, e^{-j\frac{2\pi}{\lambda}d_r \sin(\theta_{k,r}^t)}, \dots, e^{-j\frac{2\pi}{\lambda}(N-1)d_r \sin(\theta_{k,r}^t)}]^T, \quad (6)$$

where  $\theta_{k,r}^t$  is the arrival angle of the signal from the  $k$ th vehicle to the RIS at time slot  $t$ .

In this letter, we consider that the communication link between the vehicle and the BS is completely blocked, and the VU can only communicate through the RIS. Thus, we can obtain the signal-to-noise ratio (SNR) between the  $k$ th VU and the BS through the RIS at time slot  $t$  as

$$\gamma_k(t) = \frac{P_{k,o}^t |(\mathbf{h}_{r,b})^H \Theta^t \mathbf{h}_{k,r}^t|^2}{\sigma^2}, \forall k \in \mathcal{K}, \forall t \in \mathcal{T}, \quad (7)$$

where  $P_{k,o}^t \in [0, P_{\max,o}]$  is the offloading power of  $k$ th VU at time slot  $t$ , and  $\sigma^2$  is thermal noise power. The diagonal phase-shift matrix of RIS is  $\Theta^t = \text{diag}[\beta_1 e^{j\theta_1^t}, \dots, \beta_n e^{j\theta_n^t}, \dots, \beta_N e^{j\theta_N^t}]$ ,  $\forall n \in [1, N]$ ,  $\beta_n \in [0, 1]$ . Due to hardware constraint, phase-shift can only be selected from a finite discrete value set  $\theta_n^t \in \Phi = \left\{0, \frac{2\pi}{2^b}, \dots, \frac{2\pi(2^b-1)}{2^b}\right\}$ , where  $b$  controls the degree of phase-shift discrete degree.

When VU  $k$  chooses to offload tasks to the VEC server associated with the BS, based on the formula (7), we can obtain the number of offloaded tasks processed by VU  $k$  at time slot  $t$  as

$$q_{k,o}(t) = \Delta t \times W \log_2(1 + \gamma_k(t)), \quad (8)$$

where  $W$  represents the channel bandwidth.

### D. Local Execution

When VU  $k$  selects to process tasks locally, we can obtain the size of tasks that can be processed locally at time slot  $t$  as

$$q_{k,l}(t) = \Delta t f_k(t) / L, \quad (9)$$

where  $L$  is denoted as the CPU frequency required to process one bit of task,  $f_k(t) \in [0, F_{\max}]$  is the CPU frequency

scheduled by utilizing DVFS technology to adjust the chip voltage, i.e.,

$$f_k(t) = \sqrt[3]{p_{k,l}(t)/c}, \quad (10)$$

where  $p_{k,l}(t) \in [0, P_{\max,l}]$  is the local execution power of VU  $k$  at time slot  $t$ , and  $c$  is the effective selection capacitance.

### E. Problem Formulation

The target is to minimize the power consumption of task offloading and local processing as well as buffer length. Therefore, the multi-objective optimization problem for each VU  $k$  can be formulated as follows:

$$P1: \quad \min_{\theta_n^t, p_{k,o}(t), p_{k,l}(t)} \left\{ \frac{1}{T} \sum_{t=1}^T (p_{k,o}(t) + p_{k,l}(t) + q_k(t)) \right\}, \quad (11a)$$

$$\text{s.t.} \quad 0 < p_{k,o}(t) < P_{\max,o}, \forall k \in \mathcal{K}, \forall t \in \mathcal{T}, \quad (11b)$$

$$0 < p_{k,l}(t) < P_{\max,l}, \forall k \in \mathcal{K}, \forall t \in \mathcal{T}, \quad (11c)$$

$$\theta_n^t \in \Phi, \forall n \in \mathcal{N}, \forall t \in \mathcal{T}, \quad (11d)$$

where (11b) and (11c) represent the power constraints for VU  $k$  when offloading tasks and processing tasks locally, respectively. Due to the limitation of RIS hardware, the size of RIS phase-shift can only be selected within a limited range constrained by (11d). Furthermore, the objective function is non-convex, so this optimization problem is difficult to be solved [9], [10], [11], [12], [13], [14], [15], [16], [17]. To better address this issue, we propose a Multi-agents deep reinforcement learning (MARL) scheme for joint BCD. Since the RIS phase-shift controller and VUs are not the same type of agents, their actions and reward are also different. Therefore, we will first use the BCD algorithm to obtain the optimal size of phase-shift, and then obtain the optimal power allocation scheme through the modified MADDPG algorithm.

## III. SOLUTION APPROACH

We will describe the proposed scheme in detail. Firstly, we compute the channel information of VU based on the relevant position of VU, BS and RIS, etc., where the RIS phase-shift is a variable, and we use the BCD algorithm to obtain the optimal phase-shift with the objective of maximizing  $\left| (\mathbf{h}_{r,b})^H \Theta^t \mathbf{h}_{k,r}^t \right|^2$ . Then, the power allocation problem of VU is solved according to the modified MADDPG algorithm. The detailed algorithms are introduced as below.

### A. BCD for RIS Phase-Shift Coefficients

In this subsection, to handle the RIS phase-shift optimization problem, the details related to the BCD algorithm can be referred to [6]. At time slot  $t$ , we use the BCD algorithm to maximize the instantaneous modulus sum of all VUs expressed as follows:

$$\sum_{k=1}^K \left| (h_{r,b})^H \Theta^t \mathbf{h}_{k,r}^t \right|^2. \quad (12)$$

In each training iteration, the BCD algorithm is called to optimize the phase-shift of the RIS. For  $M$  RIS elements, we select the optimal one among  $2^b$  values for each element. The optimization procedure is described in detail in Algorithm 1.

---

### Algorithm 1: BCD to Optimize Phase-Shift Matrix

---

**Inputs:**  $\Phi$

**Outputs:**  $\theta_n^t$

**for**  $n = 1, \dots, N$  **do**

Fix  $n', \forall n' \neq n, n' \in N$   
 Set  $\theta_n^t = \arg \max_{\Phi} (12)$

**Obtain** (12)

---

### B. DRL for Power Allocation

In this subsection, we use the MARL algorithm to solve the power allocation problem for VU. Here, each VU interacts with the environment as an agent and makes power allocation decisions through the corresponding strategies. At time slot  $t$ , the agent obtains the current state  $s_t$ , the corresponding action  $a_t$  and the corresponding reward  $r_t$ , and transitions to the next state  $s_{t+1}$ . This process can be formulated as  $e_t = (s_t, a_t, r_t, s_{t+1})$  [18], [19], [20], [21], [22], [23], [24], [25], and the relevant state space, action space, and reward function in this model are represented as follows:

**State space:** At time slot  $t$ , the state of each VU  $k$  (agent  $k$ ) consists of the following components: buffer length  $q_k(t)$ , the size of offloaded executed tasks  $q_{k,o}(t)$ , the size of locally executed tasks  $q_{k,l}(t)$ , and the offloaded and locally processed task overflows  $q_{k,o}(t) + q_{k,l}(t) - q_k(t)$ . In addition, through equation (7), the SNR of VU  $k$  at time slot  $t$ , i.e.  $\gamma_k(t-1)$ , depends on  $h_{r,b}$  and  $h_{k,r}^t$ , which reflects the channel uncertainty of the VU at time slot  $t$ . Therefore, the state space of the VU  $k$  at slot  $t$  can be formulated as  $\mathbf{s} = [q_k(t), q_{k,o}(t), q_{k,l}(t), q_{k,o}(t) + q_{k,l}(t) - q_k(t), \gamma_k(t-1)]$ .

**Action space:** as described above, agent  $k$  allocates the offloading power and the local power according to the corresponding policy, so that the action space of agent  $k$  at time slot  $t$  is defined as  $a_k(t) = [p_{k,o}(t), p_{k,l}(t)]$ .

**Reward function:** in our proposed scheme, there are two aspects of rewards for each agent, one is the global reward reflecting the cooperation among agents, and the other is the local reward that is to help each agent to explore to the optimal power allocation scheme. In DRL, rewards can be set flexibly, and a good reward can improve the performance of the system. Here, our goal is to optimize the agent  $k$ 's offloading and the local power level, as well as the corresponding buffer length. To address it, we add two penalties  $Pen1$  and  $Pen2$ , one for the buffer length of agent  $k$  being greater than a threshold at time slot  $t$ , and the other for the penalty incurred when agent  $k$  allocates a certain amount of power to offloading execution and local execution at time slot  $t$ , resulting in the total number of tasks processed being a certain value more than the buffer length. Thus the local and global rewards of VU  $k$  at time slot  $t$  are

$$r_{k,l} = - [w_1(p_{k,o}(t) + p_{k,l}(t)) + w_2q_k(t)] - Pen1 - Pen2, \quad (13)$$

and

$$r_g = \frac{1}{K} \sum_{k \in K} r_{k,l}. \quad (14)$$

---

**Algorithm 2:** Modified MADDPG Algorithm for Power Allocation
 

---

Start environment simulator, generate vehicles  
 Initialize global critic networks  $Q_{\psi_1}^{g1}$  and  $Q_{\psi_2}^{g2}$   
 Initialize target global critic networks  $Q_{\psi_1'}^{g1}$  and  $Q_{\psi_2'}^{g2}$   
 Initialize each agent's policy and critic networks  
**for each episode do**  
   Reset simulation parameters for the RIS-assisted VEC system **for each timestep  $t$  do**  
     **for each agent  $k$  do**  
       Observe  $s_k^t$  and select action  $a_k^t = \pi_\theta(s_k^t)$   
       Receive local reward  $r_{k,l}^t$   
      $\mathbf{s} = (s_1, s_2, \dots, s_K)$  and  $\mathbf{a} = (a_1, a_2, \dots, a_K)$   
     Receive global reward  $r_g^t$   
     Store  $(\mathbf{s}^t, \mathbf{s}^t, \mathbf{r}_l^t, r_g^t, \mathbf{s}^{t+1})$  in replay buffer  $\mathcal{D}$   
   **if the size of the replay buffer is larger than  $I$  then**  
     Randomly sample mini-batch of  $I$  transitions tuples from  $\mathcal{D}$   
     Update global critics by minimizing the loss according to Eq.(16)  
     Update global target networks parameters:  
        $\psi_j' \leftarrow \tau \psi_j + (1 - \tau) \psi_j', j = 1, 2$   
     **if episode mod  $d$  then**  
       Train local critics and actors  
       **for each agent  $k$  do**  
         Update local critics by minimizing the loss according to Eq.(18)  
         Update local actors according to Eq.(15)  
         Update local target networks parameters:  
            $\theta_k' \leftarrow \tau \theta_k + (1 - \tau) \theta_k'$ ,  
            $\phi_k' \leftarrow \tau \phi_k + (1 - \tau) \phi_k'$

---

We propose a MARL algorithm that learns how to maximize both global and local rewards. It contains two main critics, one is a global critic, which is shared among all the agents and inputs the states and actions of all the agents to maximize the global reward; the other is local critic, which receives the states and actions of the specific agents and evaluates the its rewards. In addition, we consider the impact of approximation errors in strategy and value updates on the global critic in MADDPG algorithm, according to [28], To improve the MADDPG algorithm, we employ twin-delay deterministic strategy gradient to replace the global critic.

Specifically, we consider a vehicular environment with  $K$  vehicles (agents) and the policies for all agents are  $\pi = \{\pi_1, \pi_2, \dots, \pi_K\}$ . The agent  $k$ 's strategy  $\pi_k$ , Q-functions  $Q_{\phi_k}^k$  and twin global critic Q-functions ( $Q_{\psi_1}^{g1}$ ,  $Q_{\psi_2}^{g2}$ ) are parameterized by  $\theta_k$ ,  $\phi_k$ ,  $\psi_1$  and  $\psi_2$ , respectively. For each agent, the modified policy gradient can be written as

$$\nabla J(\theta_k) = \underbrace{\mathbb{E}_{\mathbf{s}, \mathbf{a} \sim \mathcal{D}} \left[ \nabla_{\theta_k} \pi_k(a_k | s_k) \nabla_{a_k} Q_{\psi_j}^{g_j}(\mathbf{s}, \mathbf{a}) \right]}_{\text{Global Critic}} + \underbrace{\mathbb{E}_{s_k, a_k \sim \mathcal{D}} \left[ \nabla_{\theta_k} \pi_k(a_k | s_k) \nabla_{a_k} Q_{\phi_k}^k(s_k, a_k) \right]}_{\text{Local Critic}}, \quad (15)$$

TABLE I  
VALUES OF THE PARAMETERS IN THE EXPERIMENTS.

Parameters of System Model			
Parameter	Value	Parameter	Value
$K$	8	$\eta$	3 Mbps
$N$	40	$\sigma^2$	-110 dBm
$b$	3	$\alpha_{r,b}$	2.5
$\alpha_{k,r}$	2.2	$W$	1 MHz
$L$	500 cycles/bit	$c$	$10^{-28}$
$F_{max}$	2.15 GHz	$P_{max,o}, P_{max,l}$	1 W
Parameters of Modified MADDPG			
Parameter	Value	Parameter	Value
$\alpha_C$	0.001	$\alpha_A$	0.0001
$\omega_1$	1	$\omega_2$	0.6
$pen1, pen2$	2	$d$	2
$\gamma$	0.99	$\tau$	0.005
$I$	64	$\mathcal{D}$	$10^6$




Fig. 2. Reward function convergence

where  $\mathbf{s} = (s_1, s_2, \dots, s_K)$  and  $\mathbf{a} = (a_1, a_2, \dots, a_K)$  are the total state and action vectors,  $\mathcal{D}$  is the replay buffer, and  $a_k = \pi_k(s_k)$  is the action which is chosen for agent  $k$  according to its own policy  $\pi_k$ . Then the twin global critic  $Q_{\psi_j}^{g_j}$  is updated to

$$L(\psi_j) = \mathbb{E}_{\mathbf{s}, \mathbf{a}, r, s'} \left[ (Q_{\psi_j}^{g_j}(\mathbf{s}, \mathbf{a}) - y_g)^2 \right], j = 1, 2, \quad (16)$$

where

$$y_g = r_g + \gamma \min_{j=1,2} Q_{\psi_j}^{g_j}(s', \mathbf{a}') \Big|_{a'_k = \pi'_k(s'_k)}. \quad (17)$$

Here,  $\pi' = \{\pi'_1, \pi'_2, \dots, \pi'_K\}$  is the target policy with parameter  $\theta' = \{\theta'_1, \theta'_2, \dots, \theta'_K\}$ . Similarly, the local critic  $Q_{\phi_k}^k$  of agent  $k$  is updated to

$$L^k(\psi_k) = \mathbb{E}_{s_k, a_k, r_k, s'_k} \left[ (Q_{\phi_k}^k(s_k, a_k) - y_l^k)^2 \right], \quad (18)$$

where

$$y_l^k = r_l^k + \gamma Q_{\phi_k}^k(s'_k, a'_k) \Big|_{a'_k = \pi'_k(s'_k)}. \quad (19)$$

The detailed MARL algorithm is described in the table Algorithm 2.

#### IV. SIMULATION RESULTS

In this section, we perform simulation experiments to validate our proposed multi-agent DRL scheme with joint BCD. The simulation tool is Python 3.9. It is assumed that within some road segments, the vehicles cannot communicate directly with the BS (0, 0, 25) and thus need to rely on the assistance of RIS (220, 220, 25) to communicate indirectly with the BS. 8






Fig. 3. Performance: (a) Total power consumption; (b) Buffer length; (c) Total power consumption and buffer length

vehicles are involved in the experiment, each with a randomly chosen speed within 10 to 15 km/h. The numbers of hidden layers for actor and critic networks are 2 and 3, respectively. The learning rates of critic/actor networks learning rate are 0.001 and 0.0001, respectively. The key parameters are shown in Table I.

Fig. 2 presents the convergence performance of the proposed scheme and the DDPG scheme in terms of rewards. The proposed framework is very stable with less oscillations compared to DDPG. Since the DDPG is fully centralized, it must take the observations and actions of all agents as input, which cannot effectively address individual performance, leading to suboptimal reward situations. The proposed framework combines MARL with the BCD algorithm and shows excellent convergence performance. It can also simultaneously select the better result on maximizing the local and global rewards of all agents, and thus facilitate the cooperation among agents.

Figs. 3(a) and 3(b) show the changes in power consumption and buffer length for all VUs at different task arrival rates. In addition, we consider different effective selection capacity  $c$  and different training methods. It can be seen that the power consumption and buffer length increase with the increment of task arrival rate. The proposed algorithm has the lowest power consumption and relatively small buffer length at different capacitances. As the capacity increases, the power consumption and buffer length also increase. This is because, according to the Eq. (9) and Eq. (10),  $q_{k,l}(t)$  is related to the effective selection capacity  $c$ , the larger the capacity, the fewer local processing tasks, which increases the power consumption and buffer length. Due to the poor performance of the DDPG algorithm, it always spends some power to ensure that the buffer does not accumulate too many tasks. However, when the capacity and task arrival rate are both large, it cannot achieve a good power allocation strategy, resulting in a large amount of task accumulation.

Fig. 3(c) reflects the impact of the number of RIS elements on the network performance, where the total power consumption and buffer length decrease when the number of RIS elements increases. Our proposed scheme outperforms random RIS phase-shift because random RIS phase-shift reduces the data transmission rate during offloading, resulting in more power consumption to ensure data transmission and also

affecting the buffer length.

## V. CONCLUSION

In this letter, in order to optimize the power consumption, buffer length, and RIS phase-shift matrix in RIS assisted VEC network, we developed a new framework, i.e., the MARL scheme with joint BCD algorithm. Simulation results demonstrated the superiority of our scheme to the random RIS phase-shift and DDPG algorithms in terms of power consumption and buffer length.

## REFERENCES

- [1] Y. Liu, H. Yu, S. Xie and Y. Zhang, "Deep Reinforcement Learning for Offloading and Resource Allocation in Vehicle Edge Computing and Networks," *IEEE Trans. Veh. Technol.*, vol. 68, no. 11, pp. 11158-11168, Nov. 2019.
- [2] N. Cheng et al., "Space/Aerial-Assisted Computing Offloading for IoT Applications: A Learning-Based Approach," *IEEE J. Sel. Areas Commun.*, vol. 37, no. 5, pp. 1117-1129, May 2019.
- [3] A. Al-Hilo, M. Samir, M. Elhattab, C. Assi and S. Sharafeddine, "Reconfigurable Intelligent Surface Enabled Vehicular Communication: Joint User Scheduling and Passive Beamforming," *IEEE Trans. Veh. Technol.*, vol. 71, no. 3, pp. 2333-2345, March 2022.
- [4] M. Di Renzo, A. Zappone, M. Debbah, C. Yuen, J. de Rosny, S. Tretyakov, "Smart Radio Environments Empowered by Reconfigurable Intelligent Surfaces: How It Works, State of Research, and The Road Ahead," *IEEE J. Sel. Areas Commun.*, vol. 38, no. 11, pp. 2450-2525, Nov. 2020.
- [5] Y. Liu, X. Liu, X. Mu, T. Hou, J. Xu, M. D. Renzo, "Reconfigurable Intelligent Surfaces: Principles and Opportunities," *IEEE Commun. Surveys Tuts.*, vol. 23, no. 3, pp. 1546-1577, 3th Quarter 2021.
- [6] J. He, K. Yu, Y. Shi, Y. Zhou, W. Chen and K. B. Letaief, "Reconfigurable Intelligent Surface Assisted Massive MIMO With Antenna Selection," *IEEE Trans. Wireless Commun.*, vol. 21, no. 7, pp. 4769-4783, July 2022.
- [7] H. Zhu, Q. Wu, X. -J. Wu, Q. Fan, P. Fan and J. Wang, "Decentralized Power Allocation for MIMO-NOMA Vehicular Edge Computing Based on Deep Reinforcement Learning," *IEEE Internet of Things J.*, vol. 9, no. 14, pp. 12770-12782, July, 2022.
- [8] M. Parvini, M. R. Javan, N. Mokari, B. Abbasi and E. A. Jorswieck, "AoI-Aware Resource Allocation for Platoon-Based C-V2X Networks via Multi-Agent Multi-Task Reinforcement Learning," *IEEE Trans. Veh. Technol.*, vol. 72, no. 8, pp. 9880-9896, Aug. 2023.
- [9] J. Fan, Q. Wu and J. Hao, "Optimal Deployment of Wireless Mesh Sensor Networks based on Delaunay Triangulations," in *Proc. of IEEE International Conference on Information, Networking and Automation*, Kunming, China, Oct. 2010, pp. 1-5.
- [10] Q. Wu and J. Zheng, "Performance Modeling and Analysis of the ADHOC MAC Protocol for Vehicular Networks," *Wireless Networks*, Vol. 22, No. 3, Apr. 2016, pp. 799-812.
- [11] Q. Wu, S. Xia, Q. Fan and Z. Li, "Performance Analysis of IEEE 802.11p for Continuous Backoff Freezing in IoV," *Electronics*, Vol. 8, No. 1404, Dec. 2019.

- [12] W. Chen, L. Dai, K. B. Letaief and Z. Cao, "A Unified Cross-Layer Framework for Resource Allocation in Cooperative Networks," *IEEE Transactions on Wireless Communications*, vol. 7, no. 8, pp. 3000-3012, August 2008.
- [13] Y. Zhang and K. B. Letaief, "Adaptive resource allocation and scheduling for multiuser packet-based OFDM networks," 2004 *IEEE International Conference on Communications*, Paris, France, 2004, pp. 2949-2953 Vol.5.
- [14] K. Xiong, C. Chen, G. Qu, P. Fan and K. B. Letaief, "Group Cooperation With Optimal Resource Allocation in Wireless Powered Communication Networks," *IEEE Transactions on Wireless Communications*, vol. 16, no. 6, pp. 3840-3853, June 2017.
- [15] T. Li, P. Fan, Z. Chen and K. B. Letaief, "Optimum Transmission Policies for Energy Harvesting Sensor Networks Powered by a Mobile Control Center," *IEEE Transactions on Wireless Communications*, vol. 15, no. 9, pp. 6132-6145, Sept. 2016.
- [16] J. Zhang, P. Fan and K. B. Letaief, "Network Coding for Efficient Multicast Routing in Wireless Ad-hoc Networks," *IEEE Transactions on Communications*, vol. 56, no. 4, pp. 598-607, April 2008.
- [17] Z. Yao, J. Jiang, P. Fan, Z. Cao and V. O. K. Li, "A neighbor-table-based multipath routing in ad hoc networks," *The 57th IEEE Semiannual Vehicular Technology Conference*, 2003. VTC 2003-Spring., Jeju, Korea (South), pp. 1739-1743 vol.3, 2003.
- [18] Q. Wu, Y. Zhao, Q. Fan, P. Fan, J. Wang and C. Zhang, "Mobility-Aware Cooperative Caching in Vehicular Edge Computing Based on Asynchronous Federated and Deep Reinforcement Learning," *IEEE J. Sel. Topics Signal Process.*, vol. 17, no. 1, pp. 66-81, Jan. 2023.
- [19] S. Wang, Q. Wu, Q. Fan, P. Fan and J. Wang, "Mobility-Aware Asynchronous Federated Learning for Edge-Assisted Vehicular Networks," *IEEE International Conf. Commun.*, Rome, Italy, 2023, pp. 3621-3626.
- [20] Q. Wu, W. Wang, P. Fan, Q. Fan, J. Wang and K. B. Letaief, "URLLC-Aware Resource Allocation for Heterogeneous Vehicular Edge Computing," *IEEE Trans Veh. Technol.*, early access, February 2024, doi: 10.1109/TVT.2024.3370196.
- [21] Q. Wu, S. Wang, H. Ge, P. Fan, Q. Fan and K. B. Letaief, "Delay-sensitive Task Offloading in Vehicular Fog Computing-Assisted Platoons", *IEEE Trans. Netw. Ser. Manag.*, Vol. 21, No. 2, pp. 2012-2026, April 2024.
- [22] Q. Wu, X. Wang, Q. Fan, P. Fan, C. Zhang and Z. Li, "High Stable and Accurate Vehicle Selection Scheme based on Federated Edge Learning in Vehicular Networks", *China Communications*, Vol. 20, No. 3, pp. 1-17, Mar. 2023.
- [23] Q. Wu, S. Shi, Z. Wan, Q. Fan, P. Fan and C. Zhang, "Towards V2I Age-aware Fairness Access: A DQN Based Intelligent Vehicular Node Training and Test Method", *Chinese Journal of Electronics*, vol. 32, no. 6, pp. 1230-1244, 2023.
- [24] Q. Wu, W. Wang, P. Fan, Q. Fan, H. Zhu and K. B. Letaief, "Cooperative Edge Caching Based on Elastic Federated and Multi-Agent Deep Reinforcement Learning in Next-Generation Networks.", *IEEE Transactions on Network and Service Management*, 2024, doi: 10.1109/TNSM.2024.3403842.
- [25] D. Long, Q. Wu, Q. Fan, P. Fan, Z. Li and J. Fan, "A Power Allocation Scheme for MIMO-NOMA and D2D Vehicular Edge Computing Based on Decentralized DRL", *Sensors*, Vol. 23, No. 7, 2023, Art. no. 3449.
- [26] M. Samir, M. Elhattab, C. Assi, S. Sharafeddine and A. Ghayeb, "Optimizing Age of Information Through Aerial Reconfigurable Intelligent Surfaces: A Deep Reinforcement Learning Approach," *IEEE Trans. Veh. Technol.*, vol. 70, no. 4, pp. 3978-3983, April 2021.
- [27] Y. Chen, Y. Wang, J. Zhang and M. D. Renzo, "QoS-Driven Spectrum Sharing for Reconfigurable Intelligent Surfaces (RISs) Aided Vehicular Networks," *IEEE Trans. Wireless Commun.*, vol. 20, no. 9, pp. 5969-5985, Sept. 2021.
- [28] S. Fujimoto, H. van Hoof, and D. Meger, "Addressing function approximation error in actor-critic methods," in *Proceedings of the 35th International Conference on Machine Learning*, vol. 80, pp. 1587-1596, July 2018.