

Recognizing Small-Circuit Structure in Two-Qubit Operators and Timing Hamiltonians to Compute Controlled-Not Gates*

Vivek V. Shende¹, Stephen S. Bullock² and Igor L. Markov^{3†}

¹The University of Michigan, Department of Mathematics,

²National Institute of Standards and Technology, I.T.L.-M.C.S.D.

³The University of Michigan, Department of Electrical Engineering and Computer Science[‡]

This work proposes numerical tests which determine whether a two-qubit operator has an atypically simple quantum circuit. Specifically, we describe formulae, written in terms of matrix coefficients, characterizing operators implementable with exactly zero, one, or two controlled-not (CNOT) gates and all other gates being one-qubit. We give an algorithm for synthesizing two-qubit circuits with optimal number of CNOT gates, and illustrate it on operators appearing in quantum algorithms by Deutsch-Josza, Shor and Grover. In another application, our explicit numerical tests allow timing a given Hamiltonian to compute a CNOT modulo one-qubit gates, when this is possible.

PACS numbers: 03.67.Lx, 03.65.Fd 03.65.Ud

I. INTRODUCTION

Quantum circuits compactly represent unitary operators and find applications in quantum computing, communication and cryptography [1]. Such a representation can often be interpreted as a program (e.g., a sequence of RF pulses for NMR) whose execution on a quantum system of choice performs a requested unitary evolution. Simple steps in the program correspond to gates in the circuit, and smaller circuits lead to faster programs. In this work we discuss exact implementations of two-qubit operators because (i) such operators suffice to implement arbitrary operators [2], and (ii) a number of controllable two-qubit systems were recently reported.

The simulation of generic two-qubit operators via CNOT gates and one-qubit operators has been thoroughly investigated, resulting in several three-CNOT decompositions [3, 4, 5]. It is known that the swap gate requires three CNOTs [4], and also that an arbitrary n -qubit operator requires at least $\lceil \frac{1}{4}(4^n - 3n - 1) \rceil$. The proof of this latter result [5] holds for any controlled- u gate, where u is a given fixed one-qubit operator. For $n = 2$, it has been shown that an arbitrary controlled- u gate is generically worse than the CNOT [6].

The above-mentioned results motivate the focus on the *basic-gate* library [7], which consists of the CNOT gate and all one-qubit gates: it is powerful and well-understood. Yet, given the diversity of implementation technologies, it is not clear that the CNOT gate will be directly available in a given implementation. Nonetheless, we believe results expressed in the *basic-gate* library will be relevant. An analogous situation occurs in the design of (classical) integrated circuits. In this context, first *technology-independent synthesis* is performed in terms of abstract gates (AND, OR, NOT). Later, during *technology mapping*, circuits are converted to use gates that are specific to a given implementation technology (e.g., NOR, NAND and AOI gates, which require very few CMOS tran-

sistors). Work in the direction of quantum technology mapping includes techniques for expressing a CNOT gate in terms of a given entangling two-qubit gate and arbitrary one-qubit gates [8]. The simulation of CNOT gates with implementation-specific resources is the basis of a major physical implementation technology [9].

The analogy with classical logic synthesis provides the following additional intuition: operators useful in practice will not be the worst-case operators studied in the aforementioned works. This belief is confirmed by published quantum algorithms and communication protocols. It is therefore important for quantum logic synthesis techniques to detect when a given operator can be implemented using fewer gates than are necessary in the worst case. For some classes of operators, this is easy; e.g., the algorithm in [10] implements tensor-product operators without CNOTs. The matrix of a controlled- U operator can be recognized by its pattern of zeros and ones (either directly, or after pre- and post-multiplication by wire swaps). Song and Klappenecker [11] study optimal implementations of two-qubit controlled-unitary operators, known to require up to two CNOT gates. They contribute a catalog of numerical tests that detect when zero, one or two CNOT gates are required, and similar criteria for the number of basic one-qubit gates.

We address a related question for arbitrary two-qubit operators and contribute simple numerical tests to determine the minimal achievable number of CNOTs, including a novel one-CNOT test. We also generalize a two-CNOT test from [3] and make it easier to compute. Such explicit numerical tests facilitate a new application. A given two-qubit Hamiltonian H , if timed precisely, may allow one to implement a CNOT using e^{iHt} and one-qubit gates. We show how to compute correct durations.

II. BACKGROUND AND NOTATION

It is well known that an arbitrary one-qubit gate u can be written as $u = e^{i\Phi} R_z(\theta) R_y(\phi) R_z(\psi)$ [1]. Furthermore, the Bloch sphere isomorphism suggests that the choice of y, z is

*Electronic address: vshende@umich.edu

†Electronic address: stephen.bullock@nist.gov

‡Electronic address: imarkov@umich.edu

arbitrary in the sense that any pair of orthogonal vectors will do: in particular, we may write

$$u = e^{i\Phi} R_z(\theta) R_x(\phi) R_z(\psi) = e^{i\Phi} R_x(\alpha) R_z(\delta) R_x(\beta)$$

These decompositions are more convenient when working with CNOT gates because R_z gates commute through the control of the CNOT whereas R_x gates commute through the target. We will denote by C_j^k a CNOT with control on the j -th wire and target on the k -th. For convenience, we consider the CNOT gate to be normalized to have determinant 1.

Additional conventions are as follows. For g any complex matrix, g^t denotes the transpose and g^* denotes the adjoint, i.e. the complex-conjugate transpose. Additionally, $\chi(g) = p(x) = \det(xI - g)$ denotes the characteristic polynomial of g . We use axis-dependent phase operators [5] $S_* = R_*(\pi/2)$, $*$ = x, y, z . Finally, $SU(4)$ denotes the group of all *determinant one* unitary matrices, fixing the global phase of a two-qubit unitary operator up to $\pm 1, \pm i$.

We now consider when two-qubit operators u, v differ by pre- or post-composing with one-qubit operators and possibly by an irrelevant global phase. In this case, we write $u \equiv v$ and say that u and v are equivalent up to one-qubit gates. The following invariant characterizes when this occurs.

Proposition II.1 *Let $\gamma: U(4) \rightarrow U(4)$ be given by the formula $u \mapsto u(\sigma^y)^{\otimes 2} u^t (\sigma^y)^{\otimes 2}$. Then for $u, v \in SU(4)$, $u \equiv v \iff \chi[\gamma(u)] = \chi[\pm\gamma(v)]$.*

We defer the proof to the Appendix. However, note that this proof provides an explicit procedure for computing the one-qubit operators $a, b, c, d \in SU(2)$ such that $(a \otimes b)u(c \otimes d) = e^{i\phi}v$ in the event that $\chi[\gamma(u)] = \chi[\pm\gamma(v)]$. We discuss γ more fully in the context of minimal universal two-qubit circuits [5]. Related invariants are discussed in [12, 13], and generalizations in [14].

III. OPTIMIZING CNOT-COUNT

We now characterize which two-qubit operators admit a quantum circuit using only m CNOT gates. Since any two-qubit operator is implemented by some three CNOT circuit, the relevant cases are $m = 0, 1, 2$. We begin with case $m = 0$.

Proposition III.1 *An operator $u \in SU(4)$ can be simulated using no CNOT gates and arbitrary one-qubit gates from $SU(2)$ iff $\chi[\gamma(u)] = (x+1)^4$ or $(x-1)^4$.*

Proof: u can be simulated using no CNOT gates iff $u \equiv I$. Thus $\chi[\gamma(u)] = \chi[\pm\gamma(I)] = \chi[\pm I] = (x \pm 1)^4$. \square

The case $m = 1$ is similar. Note that this test *requires* normalizing the global phase so that $\det(v) = 1$, implicit in $v \in SU(4)$. Had we not normalized the CNOT gate, $\chi[\gamma(C_1^2)]$ would not be of the form described.

Proposition III.2 *An operator $u \in SU(4)$ can be simulated using one CNOT gate and arbitrary one-qubit gates from $SU(2)$ iff $\chi[\gamma(u)] = (x+i)^2(x-i)^2$.*

Proof: u is simulated using one CNOT gate iff $u \equiv C_1^2$ or $u \equiv C_2^1$. Now $\gamma(C_2^1) = -i\sigma^z \otimes \sigma^x$; also $\gamma(C_1^2) = -i\sigma^x \otimes \sigma^z$. Each has χ given by $(x+i)^2(x-i)^2$. \square

In particular, we see that $C_1^2 \equiv C_2^1$. This can also be seen from the well-known identity $(H \otimes H)C_1^2(H \otimes H) = C_2^1$. We will use this fact for the final case, $m = 2$.

Proposition III.3 *An operator $u \in SU(4)$ can be simulated using two CNOT gates and arbitrary one-qubit gates from $SU(2)$ iff $\chi[\gamma(u)]$ has all real coefficients, which occurs iff $\text{tr}[\gamma(u)]$ is real.*

Proof: Since $C_1^2 \equiv C_2^1$, it is clear that u can be simulated using two CNOT gates iff $u \equiv C_1^2(a \otimes b)C_1^2$. We decompose $a = R_x(\alpha)R_z(\delta)R_x(\beta)$ decomposition and $b = R_z(\theta)R_x(\phi)R_z(\psi)$, and pass R_x gates and R_z gates outward through the target and control of the CNOT gates. Thus we are left with $u \equiv C_1^2[R_z(\delta) \otimes R_x(\phi)]C_1^2$. Explicit computation yields $\chi[\gamma(C_1^2[R_z(\delta) \otimes R_x(\phi)]C_1^2)] = (x + e^{i(\delta+\phi)})(x + e^{-i(\delta+\phi)})(x + e^{i(\delta-\phi)})(x + e^{-i(\delta-\phi)})$. On the other hand, if $\chi[\gamma(u)]$ has all real coefficients, then the eigenvalues come in conjugate pairs; it follows from this and Proposition II.1 that $\chi[\gamma(u)]$ is as above for some δ, ϕ .

Finally, we note that for $u \in SU(N)$, and $\chi(u) = \prod(x - \lambda_i)$, we have $\prod \lambda_i = 1$. Thus $\chi(u) = \left(\prod \bar{\lambda}_i\right) \prod(x - \lambda_i) = \prod(\bar{\lambda}_i x - 1)$. It follows that the coefficient of x^k is the complex conjugate of the coefficient of x^{N-k} . In particular, for $N = 4$, the coefficient of x^2 is real and the coefficients of x^3, x are $\text{tr}(u)$ and its conjugate. Since the constant term and the x^4 coefficient are 1, we see $\chi(u)$ has all real coefficients iff $\text{tr}(u)$ is real. \square

IV. SYNTHESIS ALGORITHM AND ITS VALIDATION

The results of Section III can be combined with the techniques of Propositions III.3 and II.1 and the published literature to yield an explicit circuit synthesis algorithm:

- Given the matrix of a unitary operator $u \in U(4)$, divide it by $\sqrt[4]{\det(u)}$ to ensure $u \in SU(4)$.
- Compute $\chi[\gamma(u)]$ to determine whether u requires zero, one, two, or three CNOT gates.
- If u requires zero or one CNOT gates, use the techniques of the proof of Proposition VI.1 to determine which one-qubit operators are required.
- If u requires two CNOT gates, find the roots of $\chi[\gamma(u)]$ and determine the δ, ϕ of Proposition III.3. Then use the methods of Proposition VI.1 to determine what one-qubit gates are required at the ends of the circuit.
- Finally, if u requires three CNOT gates, apply the methods of the literature [5].

By construction, the algorithm produces CNOT-optimal circuits in all cases. It also outperforms those in [3, 4, 5, 10] in important special cases, as shown below.

Example IV.1 Many quantum algorithms, notably Grover's quantum search [15] and Shor's number factoring [16], use the operator $u = H \otimes H$ to create superpositions. Computing $\gamma(u)$ allows our synthesis algorithm to recognize that u admits a quantum circuit containing no CNOTs. \diamond

This example is less trivial than it seems: while writing $u = H \otimes H$ makes it obvious that u requires no CNOT gates, a synthesis procedure will not receive an input of $u = H \otimes H$ but rather of the 4×4 matrix corresponding to u . It is not *a priori* clear that any worst-case CNOT-optimal circuit decomposition will implement u without CNOT gates. However, several previously published algorithms do. For the next example, previous two-qubit synthesis techniques produce circuits with more CNOTs than necessary.


Example IV.2 The operator u that swaps $|00\rangle \leftrightarrow |01\rangle$ while fixing $|10\rangle$ and $|11\rangle$ plays a prominent role in the Deutsch-Jozsa algorithm [1, 17]. Note that $C_2^1(I \otimes \sigma_x)$ simulates u . Computing $\gamma(e^{i\pi/4}u)$ reveals that u requires only one CNOT. However, depending on certain algorithmic choices, anywhere from one to four one-qubit gates could appear. In any event, this compares favorably to previous work [5] which synthesizes a circuit with two CNOT and five one-qubit gates. \diamond

The algorithmic choices mentioned above come in two flavors. First, as the two CNOT gates C_1^2 and C_2^1 differ only by one-qubit gates, they are equivalent from the perspective of our methods. However, the number of one-qubit gates present in the resulting circuit depends on which of these is chosen. This is a finite problem: at most three CNOT gates appear and thus there are at most 8 possibilities, so we simply run through them all. Additional degrees of freedom arise in finding a circuit that computes a given v using a given u and one-qubit operators, when this is possible. The proof of Proposition VI.1 describes an algorithm for this, and requires picking a basis of eigenvectors for a certain matrix. If the eigenvalues are distinct, the only degree of freedom is the ordering of the basis of eigenvectors ($4! = 24$ possibilities). However, repeated eigenvalues allow more flexibility in choosing basis vectors, and potentially non-trivial circuit optimizations.

Example IV.3 At the heart of Shor's factoring algorithm [16] is the Quantum Fourier Transform [1]. On two qubits, it is given by the following matrix.

$$\mathcal{F} = \frac{1}{2} \begin{pmatrix} 1 & 1 & 1 & 1 \\ 1 & i & -1 & -i \\ 1 & -1 & 1 & -1 \\ 1 & -i & -1 & i \end{pmatrix}$$

Explicit computation of $\chi[\gamma(\mathcal{F})]$ reveals that two CNOT gates do not suffice to simulate \mathcal{F} . Thus, the following circuit to compute \mathcal{F} is CNOT-optimal:



Above, $T_z = e^{-i\sigma^z\pi/8}$ and $S_y = e^{-i\sigma^y\pi/4}$. Note that this circuit requires only three one-qubit gates, although two of these have been broken up for clarity. Finally, given that this circuit is CNOT-optimal, it is not difficult to check by hand that its basic-gate count cannot be improved. \diamond

V. TIMING A HAMILTONIAN TO COMPUTE CNOT

Our numerical tests facilitate a new application. Given a Hamiltonian that can be timed to compute a CNOT modulo one-qubit gates, we illustrate finding the correct duration. Our example is a perturbation of $\sigma^x \otimes \sigma^x$ by non-commutative one-qubit noise.

$$H_{42} = (0.42)I \otimes \sigma^z + \sigma^x \otimes \sigma^x$$

Recall that a CNOT can be constructed using one-qubit gates and some time-iterate of the Hamiltonian $\sigma^x \otimes \sigma^x$. However, to handle the noise term, existing techniques resort to Trotterization, which implements $\exp(A+B)$ by separately turning on A and B for short periods of time. Below we find a simpler, direct implementation of CNOT from H_{42} . It is especially interesting in light of concerns about the scalability of Trotterization [18].

We compute $\gamma(e^{iH_{42}t})$ for uniformly-spaced trial values of t and seek out those values at which the characteristic polynomial nears $p(x) = (x^2 + 1)^2 = x^4 + 2x^2 + 1$. Our implementation in C++ finds $t_{\text{CNOT}} = 0.80587$ in twenty seconds on a common workstation. Hence, we produce a CNOT from H_{42} and one-qubit gates without Trotterization. Specifically, since $e^{iH_{42}t_{\text{CNOT}}}$ implements C_2^1 up to one-qubit operators, we use the technique of Proposition VI.1 to compute the relevant one-qubit operators. We find that the matrices

$$a_2 = \frac{1}{2} \begin{pmatrix} 1-i & -1+i \\ 1+i & 1+i \end{pmatrix} \quad c_2 = 0.707107 \begin{pmatrix} -1 & -1 \\ 1 & -1 \end{pmatrix}$$

$$b_2 = \begin{pmatrix} -0.21503 - 0.976607i & 0 \\ 0 & -0.21503 + 0.976607i \end{pmatrix}$$

$$d_2 = \begin{pmatrix} 0.152049 + 0.690566i & 0.690566 - 0.152049i \\ -0.690566 - 0.152049i & 0.152049 - 0.690566i \end{pmatrix}$$

satisfy $C_2^1 = (a_2 \otimes b_2)e^{iH_{42}t_{\text{CNOT}}}(c_2 \otimes d_2)$ with numerical precision of 10^{-6} .

Further numerical experiments suggest that building a CNOT is possible whenever 0.42 is replaced by a weight w , $0 \leq w \leq 1$. However, we have no analytical proof of this. Numerical experiments also suggest the *impossibility* of timing the Hamiltonian $H_{XYZ} = \sigma^x \otimes \sigma^x + \sigma^y \otimes \sigma^y + \sigma^z \otimes \sigma^z$ so as to compute a CNOT. In other words, trying values of t in the range $-10 \leq t \leq 10$ as above produced no candidate durations.

VI. CONCLUSIONS AND FUTURE WORK

Our work addresses small-circuit structure in two-qubit unitary operators. In particular, we contribute tests for such structure, and our techniques can be viewed as algorithms for finding small circuits when they exist. We detail such an algorithm that produces the minimal possible number of CNOT gates (zero, one, two or three) *for each input*. It is illustrated on circuit examples derived from well-known applications.

The one-CNOT test has an additional use. It provides a numerical method for timing a given two-qubit Hamiltonian H so that e^{iH} realizes a CNOT gate up to local unitary operators (one-qubit gates,) given this is possible for H .

Acknowledgments. This work is supported by the DARPA QuIST program and an NSF grant. The views and conclusions contained herein are those of the authors and should not be interpreted as necessarily representing official policies or endorsements of employers and funding agencies.

Appendix

Proposition VI.1 *Let $\gamma: SU(4) \rightarrow SU(4)$ be given by the formula $u \mapsto u(\sigma^y)^{\otimes 2} u^t (\sigma^y)^{\otimes 2}$. Then for $u, v \in SU(4)$, $u \equiv v \iff \chi[\gamma(u)] = \chi[\pm\gamma(v)]$.*

Proof: By definition, $u \equiv v \iff u = (a \otimes b)\lambda v(a' \otimes b')$ for

some one-qubit operators a, b, a', b' and some scalar λ . Requiring $u, v \in SU(4)$ implies $\lambda = \pm 1, \pm i$. We show below that $u = (a \otimes b)v(a' \otimes b') \iff \chi[\gamma(u)] = \chi[\gamma(v)]$; the proposition then follows from the fact that $\gamma(iu) = -\gamma(u)$.

We recall that there exist $E \in SU(4)$ such that $E SO(4) E^* = SU(2)^{\otimes 2} = \{a \otimes b : a, b \in SU(2)\}$. Such matrices are characterized by the property that $EE^t = -\sigma^y \otimes \sigma^y$. This and related issues have been exhaustively dealt with in several papers [19, 20, 21, 22].

The property $\chi[\gamma(u)] = \chi[\gamma(v)]$ is not changed by replacing γ with $E^* \gamma E$. Using the fact $\sigma^y \otimes \sigma^y = EE^t = (EE^t)^*$, we compute: $E^* \gamma(u) E = E^* u E E^t u^t E^t E^* E = (E^* u E)(E^* u E)^t$

By making the substitution $u \mapsto EuE^*$; it suffices to prove: for $u, v \in SU(4)$, there exists $x, y \in SO(4)$ such that $xuy = v$ iff $\chi[uu^t] = \chi[vv^t]$. Here, $SO(4)$ is the real matrices within $SU(4)$.

Note that for P symmetric unitary, $P^{-1} = \bar{P}$, hence $[P + \bar{P}, P - \bar{P}] = 0$. It follows that the real and imaginary parts of P share an orthonormal basis of eigenvectors. As they are moreover real symmetric matrices, we know from the spectral theorem that their eigenvectors can be taken to be real. Thus there exists $q \in SO(4)$ such that $quu^t q^*$ is diagonal. By re-ordering (and negating) the columns of q , we can re-order the diagonal elements of $quu^t q^*$ as desired. Thus if $\chi[uu^t] = \chi[vv^t]$, we can find $q, r \in SO(4)$ such that $quu^t q^* = rvv^t r^t$ by diagonalizing both; then $(v^* r^t q u)(v^* r^t q u)^t = I$. Let $s = v^* r^t q u \in SO(4)$. We have $q^t r v s = u$, as desired. \square

-
- [1] M. Nielsen and I. Chuang, *Quantum Computation and Quantum Information*, Cambridge Univ. Press, 2000.
 - [2] D. P. DiVincenzo, "Two-bit gates are universal for quantum computation," *PRA* **51**, pp. 1015-1022, 1995, cond-mat/94.
 - [3] G. Vidal and C.M. Dawson, "A universal quantum circuit for two-qubit transformations with three CNOT gates," quant-ph/0307177.
 - [4] F. Vatan and C. Williams, "Optimal Realization of an Arbitrary Two-Qubit Quantum Gate", quant-ph/0308006.
 - [5] V.V. Shende, I.L. Markov and S.S. Bullock, "Minimal Universal Two-qubit Circuits," quant-ph/0308033.
 - [6] J. Zhang, J. Vala, Sh. Sastry, and K. B. Whaley, "Optimal Quantum Circuit Synthesis From Controlled-U Gates," quant-ph/0308167.
 - [7] A. Barenco et al., "Elementary Gates For Quantum Computation," *PRA* **52**, 3457-3467, 1995, quant-ph/9503016.
 - [8] M. J. Bremner, C. M. Dawson, J. L. Dodd, A. Gilchrist, A. W. Harrow, D. Mortimer, M. A. Nielsen and T. J. Osborne, "A Practical Scheme For Quantum Computation With Any Two-qubit Entangling Gate," *PRL* **89**, no. 24, 247902 (2002). quant-ph/0207072
 - [9] D. Wineland, C. Monroe, W. Itano, D. Leibfried, B. King, and D. Meekhof, "Experimental issues in coherent quantum manipulation of trapped atomic ions," *NIST J. of Research* **103**, p. 259 (1998).
 - [10] S. S. Bullock and I. L. Markov, "An Elementary Two-Qubit Quantum Computation In Twenty-Three Elementary Gates," *PRA* **68**, 012318-012325, 2003, quant-ph/0211002.
 - [11] G. Song and A. Klappenecker, "Optimal Realizations of Controlled Unitary Gates," *J. of Quantum Information and Computation*, **3**(2), pp. 139-155, 2003. quant-ph/0207157.
 - [12] J. Zhang et al., "A geometric theory of non-local two-qubit operations," 2003, quant-ph/0209120.
 - [13] Yu. Makhlin, "Nonlocal properties of two-qubit gates and mixed states and optimization of quantum computations," *Quant. Info. Proc.* **1**, 243-252, 2002, quant-ph/0002045.
 - [14] S. Bullock and G. Brennen, "Canonical Decompositions of n -qubit Quantum Computations and Concurrence," 2003, quant-ph/0309104.
 - [15] L. Grover, "Quantum Mechanics Helps In Searching For A Needle In A Haystack," *PRL* **79**, pp. 325-8, 1997.
 - [16] P. W. Shor, "Polynomial-time algorithms for prime factorization and discrete logarithms on a quantum computer," *SIAM J. of Computing*, Vol. 26, p. 1484, 1997.
 - [17] D. Deutsch and R. Josza, "Rapid Solution of Problems by Quantum Computation," *Proc. R. Soc. London A*, 439:553, 1992.
 - [18] A. M. Childs, H. L. Haselgrove, M. A. Nielsen, "Lower bounds on the complexity of simulating quantum gates," *PRA* **68**, 052311 (2003).
 - [19] C. Bennett et al., "Mixed State Entanglement and Quantum Error Correction," *PRA* **54**, 3824, 1996, quant-ph/9604024.
 - [20] S. Hill, K. Wothers, "Entanglement of a Pair of Quantum Bits," *PRL* **78**, 5022-5025, 1997, quant-ph/9703041.
 - [21] N. Khaneja, R. Brockett and S. J. Glaser, "Time Optimal Control In Spin Systems," 2001 quant-ph/0006114.
 - [22] M. Lewenstein et al., "Characterization of Separable States and Entanglement Witnesses," *PRA* **63**, pp. 044304-7, 2001, quant-ph/0011050.