

Canonical quantization of electromagnetic field in an anisotropic polarizable and magnetizable medium with spatial-temporal dispersion

M. Amooshahi¹ *

¹ Faculty of science, University of Isfahan ,Hezar Jarib Ave., Isfahan,Iran

March 11, 2019

Abstract

Modeling an anisotropic spatially and temporarily dispersive magnetodielectric medium by two independent collections of three dimensional vector fields, we demonstrate a fully canonical quantization of electromagnetic field in the presence of such a medium. Two tensor fields which couple the electromagnetic field with the medium and have an important role in this quantization method are introduced. The electric and magnetic polarization fields of the medium naturally are concluded in terms of the coupling tensors and the dynamical variables modeling the magnetodielectric medium. In Heisenberg picture, the constitutive equations of the medium together with the Maxwell laws are obtained as the equations of motion of the total system and the susceptibility tensors of the medium are calculated in terms of the coupling tensors. Following a perturbation method the Green function related to the total system is found and the time dependence of electromagnetic field operators is derived.

Key words: Canonical quantization, Magnetodielectric medium, Spatial-temporal dispersion, Susceptibility tensor, Coupling tensor, Constitutive equation

PACS No: 12.20.Ds, 42.50.Nn

*amooshahi@sci.ui.ac.ir

1 introduction

One of the important quantum dissipative systems is the quantized electromagnetic field in the presence of an absorbing polarizable medium. In this case there are mainly two quantization approaches, the phenomenological method [1]-[7] and the damped polarization model [8, 9]. The phenomenological scheme has been formulated on the basis of the fluctuation-dissipation theorem [1]. In this method by adding a fluctuating noise term, that is the noise polarization field, to the classical constitutive equation of the medium, this equation is taken as the definition of the electric polarization operator. Combination of the Maxwell equations and the constitutive equation in frequency domain, gives the electromagnetic field operators in terms of the noise polarization field and the classical Green tensor. By imposing suitable commutation relations on the bosonic operators associated with the noise, one arrives at a quantization procedure that has been quite successful in describing some electromagnetic phenomena in the presence of a lossy dielectric medium [10]-[14]. The phenomenological approach has been extended to a lossy magnetic or anisotropic medium [15]-[17]. This formalism also has been generalized to an arbitrary linearly responding medium based on a spatially nonlocal conductivity tensor [18].

The damped polarization model to quantize electromagnetic field in a dispersive dielectric medium [8, 9] is a canonical quantization in which the electric polarization field of the medium applies in the Lagrangian of the total system as a part of the degrees of freedom of the medium. The other parts of the degrees of freedom of the absorbing medium are related to the dynamical variables of a heat bath describing the absorptivity feature of the medium. In this method the dielectric function of the medium is found in terms of the coupling function of the heat bath and the polarization field, so that it satisfies the Kramers-Kronig relations [19]. This quantization method has been generalized to an inhomogeneous medium [20].

In the present work we generalize our previous model [21, 22] to an anisotropic spatially and temporarily dispersive magnetodielectric medium using a canonical approach. In this formalism we model the medium with two independent collections of vector fields. In opposite to Huttner-Barnett model [8], these collections solely constitute the degrees of freedom of the medium and it is not needed the electric and magnetic polarization fields to be included in the Lagrangian of the total system as a part of the degree of freedom of the medium. In fact the dynamical fields modeling the dispersive medium are

able to describe both polarizability and absorptivity features of the medium. In addition, this formalism takes spatial dispersion into account where can be regarded as a step toward the electrodynamics in the presence of moving media. Because a responding medium which is not spatially dispersive in its rest frame, may be in general appeared as nonlocally responding when it is in motion.

This paper is organized as follows. In Sec. 2, we propose a Lagrangian for the total system and classical electrodynamics in the presence of an anisotropic polarizable and magnetizable medium with spatial-temporal dispersion briefly is discussed . In Sec. 3, we apply the Lagrangian introduced in Sec. 2 to arrive at a canonical quantization of both electromagnetic field and the dynamical variable modeling the responding medium. Then in Sec. 4, the constitutive equations of the medium are obtained as the consequences of the Heisenberg equations of the total system and the electric and magnetic susceptibility tensors of the medium are calculated in terms of the parameters applied in the theory . Finally in Sec.5, it is shown the Green function of the total system in reciprocal space satisfies an algebraic equation and a perturbation method to obtain the Green function is introduced. this paper is closed with a summary and some concluding remarks in Sec.6 .

2 Classical electrodynamics in an anisotropic medium with spatial-temporal dispersion

In order to present a fully canonical quantization of electromagnetic field in the presence of an anisotropic polarizable and magnetizable medium, we model the medium by two independent reservoirs. Each reservoir contains a continuum of three dimensional harmonic oscillators labeled with a continuous parameter ω . We call these two continuous sets of oscillators " E field " and " M field". The E field and M field describe polarizability and magnetizability of the medium, respectively. This means that, in our approach we do not need the electric and magnetic polarization fields of the medium to be appeared explicitly in the Lagrangian of the total system as a part of the degrees of freedom of the medium , but the contribution of the medium in the Lagrangian of the total system is related only to the Lagrangian of the E and M fields and these fields completely describe the degrees of freedom of the medium. The presence of the " E field" in the total Lagrangian is sufficient

for a complete description of both polarizability and the absorption of the medium due to its electrically dispersive property. Also the "M field" solely is sufficient in order to description of both magnetizability and the absorption of the medium due to its magnetically dispersive property. Therefore, in order to have a classical treatment of electrodynamics in a magnetodielectric medium, we start with a Lagrangian for the total system (medium + electromagnetic field) which is the sum of three parts

$$L(t) = L_{res} + L_{em} + L_{int} \quad (1)$$

where L_{res} is the part related to the degrees of freedom of the medium and is the sum of the Lagrangians of the E and M fields

$$L_{res} = L_e + L_m \quad (2)$$

$$L_e = \int_0^\infty d\omega \int d^3r \left[\frac{1}{2} \dot{\vec{X}}_\omega \cdot \dot{\vec{X}}_\omega - \frac{1}{2} \omega^2 \vec{X}_\omega \cdot \vec{X}_\omega \right] \quad (3)$$

$$L_m = \int_0^\infty d\omega \int d^3r \left[\frac{1}{2} \dot{\vec{Y}}_\omega \cdot \dot{\vec{Y}}_\omega - \frac{1}{2} \omega^2 \vec{Y}_\omega \cdot \vec{Y}_\omega \right] \quad (4)$$

where \vec{X}_ω and \vec{Y}_ω are the dynamical variables of the E and M fields . L_{em} is the contribution of the electromagnetic field in the Lagrangian of the total system

$$L_{em} = \int d^3r \left[\frac{1}{2} \epsilon_0 \vec{E}^2 - \frac{\vec{B}^2}{2\mu_0} \right] \quad (5)$$

and L_{int} is the part describing the interaction of the electromagnetic field with the medium

$$L_{int} = \int_0^\infty d\omega \int d^3r \int d^3r' f_{ij}(\omega, \vec{r}, \vec{r}') E^i(\vec{r}, t) \vec{X}_\omega^j(\vec{r}', t) + \int_0^\infty d\omega \int d^3r \int d^3r' g_{ij}(\omega, \vec{r}, \vec{r}') B^i(\vec{r}, t) \vec{Y}_\omega^j(\vec{r}', t) \quad (6)$$

In equations (5) and (6) $\vec{E} = -\frac{\partial \vec{A}}{\partial t} - \nabla \varphi$ and $\vec{B} = \nabla \times \vec{A}$ are electric and magnetic fields respectively, where \vec{A} and φ are the vector and the scalar potentials. The tensors f and g in (6) are called the coupling tensors of the medium with electromagnetic field and for a medium with spatial dispersion are dependent on the both position vectors \vec{r} and \vec{r}' . The coupling tensors are

the key parameters of this theory. As was mentioned above, it is not needed the electric and magnetic polarization fields of the medium explicitly to be appeared in the total Lagrangian (1)-(6) as a part of degrees of freedom of the medium . As we will see, the electric polarization(magnetic polarization) of the medium is obtained in terms of the coupling tensor f (g) and the dynamical variables \vec{X}_ω (\vec{Y}_ω). Also the electric susceptibility tensor (magnetic susceptibility tensor) of the medium naturally will expressed in terms of the coupling tensor f (g). The coupling tensors f and g are appeared as common factors in both the noise polarization fields and the susceptibility tensors of the medium, so that for the free space the susceptibility tensors together with the noise polarizations become identically zero and this quantization scheme is reduced to the usual quantization of electromagnetic field quantization in free space. Furthermore when the medium tends to a non-absorbing one, the coupling tensors and the noise polarizations also tend to zero and this quantization method is reduced to the quantization in a non-absorbing medium [21, 23].

In order to prevent some difficulties with a non-local Lagrangian such as (6), it is the easiest way to work in the reciprocal space and write all the fields and the coupling tensors f , g in terms of their spatial Fourier transforms. For example the dynamical variable \vec{X}_ω can be written as

$$\vec{X}_\omega(\vec{r}, t) = \frac{1}{\sqrt{(2\pi)^3}} \int d^3k \vec{X}_\omega(\vec{k}, t) e^{i\vec{k}\cdot\vec{r}} \quad (7)$$

Since we are concerned with real valued fields in the total Lagrangian (1)-(6), we have $\vec{X}_\omega^*(\vec{k}, t) = \vec{X}_\omega(-\vec{k}, t)$ for the field $\vec{X}_\omega(\vec{r}, t)$ and the other dynamical fields in this Lagrangian. Similarly the real valued coupling tensors f and g can be expressed in reciprocal space as

$$\begin{aligned} f_{ij}(\omega, \vec{r}, \vec{r}') &= \frac{1}{(2\pi)^3} \int d^3k \int d^3k' \underline{f}_{ij}(\omega, \vec{k}, \vec{k}') e^{i\vec{k}\cdot\vec{r} - i\vec{k}'\cdot\vec{r}'} \\ g_{ij}(\omega, \vec{r}, \vec{r}') &= \frac{1}{(2\pi)^3} \int d^3k \int d^3k' \underline{g}_{ij}(\omega, \vec{k}, \vec{k}') e^{i\vec{k}\cdot\vec{r} - i\vec{k}'\cdot\vec{r}'} \end{aligned} \quad (8)$$

which obey the condition

$$\begin{aligned} \underline{f}_{ij}(\omega, \vec{k}, \vec{k}') &= \underline{f}_{ij}^*(\omega, -\vec{k}, -\vec{k}') \\ \underline{g}_{ij}(\omega, \vec{k}, \vec{k}') &= \underline{g}_{ij}^*(\omega, -\vec{k}, -\vec{k}') \end{aligned} \quad (9)$$

The number of independent variables can be recovered by restricting the integrations on the reciprocal space to the half space $k_z \geq 0$. The total Lagrangian (1)-(6) is then obtained as

$$\underline{L}(t) = \underline{L}_{res}(t) + \underline{L}_{em}(t) + \underline{L}_{int}(t) \quad (10)$$

$$\underline{L}_{res}(t) = \int_0^\infty d\omega \int' d^3k \left(|\dot{\underline{X}}_\omega|^2 - \omega^2 |\underline{X}_\omega|^2 \right) + \int_0^\infty d\omega \int' d^3k \left(|\dot{\underline{Y}}_\omega|^2 - \omega^2 |\underline{Y}_\omega|^2 \right) \quad (11)$$

$$\underline{L}_{em}(t) = \int' d^3k \left(\varepsilon_0 |\dot{\underline{A}}|^2 + \varepsilon_0 |\vec{k} \underline{\varphi}|^2 - \frac{|\vec{k} \times \underline{A}|^2}{\mu_0} \right) + \varepsilon_0 \int' d^3k \left(-i\vec{k} \cdot \underline{A} \underline{\varphi}^* + h.c \right) \quad (12)$$

$$\begin{aligned} \underline{L}_{int}(t) = & - \int_0^\infty d\omega \int' d^3q \int' d^3p \left[\left(\dot{\underline{A}}(\vec{q}, t) + i\vec{q} \underline{\varphi}(\vec{q}, t) \right) \cdot \underline{f}(\omega, -\vec{q}, \vec{p}) \cdot \underline{X}_\omega(\vec{p}, t) + h.c \right] \\ & - \int_0^\infty d\omega \int' d^3q \int' d^3p \left[\left(\dot{\underline{A}}^*(\vec{q}, t) - i\vec{q} \underline{\varphi}^*(\vec{q}, t) \right) \cdot \underline{f}(\omega, \vec{q}, \vec{p}) \cdot \underline{X}_\omega(\vec{p}, t) + h.c \right] \\ & + \int_0^\infty d\omega \int' d^3q \int' d^3p \left[(i\vec{q} \times \underline{A}(\vec{q}, t)) \cdot \underline{g}(\omega, -\vec{q}, \vec{p}) \cdot \underline{Y}_\omega(\vec{p}, t) + h.c \right] \\ & + \int_0^\infty d\omega \int' d^3q \int' d^3p \left[(-i\vec{q} \times \underline{A}^*(\vec{q}, t)) \cdot \underline{g}(\omega, \vec{q}, \vec{p}) \cdot \underline{Y}_\omega(\vec{p}, t) + h.c \right] \end{aligned} \quad (13)$$

where $\int' d^3k$ implies the integration over the half space $k_z \geq 0$ (hereafter , we apply the symbol $\int' d^3k$ for the integration on the half space $k_z \geq 0$ and $\int d^3k$ for the integration on the total space of the reciprocal space). In the reciprocal space the total Lagrangian (10)- (13) do not involve the space derivatives of the dynamical variables of the system and the classical equations of the motion of the system can be obtained using the principle of the Hamilton's least action, $\delta \int dt \underline{L}(t) = 0$. These equations are the Euler-Lagrange equations. For the vector potential $\underline{A}(\vec{k}, t)$ and the scalar potential $\underline{\varphi}(\vec{k}, t)$ for any wave vector \vec{k} in the half space $k_z \geq 0$ we find

$$\begin{aligned} & \frac{d}{dt} \left(\frac{\delta \underline{L}}{\delta \dot{\underline{A}}_i(\vec{k}, t)} \right) - \frac{\delta \underline{L}}{\delta \underline{A}_i(\vec{k}, t)} = 0 \quad i = 1, 2, 3 \\ \implies & \mu_0 \varepsilon_0 \ddot{\underline{A}}(\vec{k}, t) + \mu_0 \varepsilon_0 i\vec{k} \dot{\underline{\varphi}}(\vec{k}, t) - \vec{k} \times (\vec{k} \times \underline{A}(\vec{k}, t)) = \\ & \mu_0 \dot{\underline{P}}(\vec{k}, t) + i\mu_0 \vec{k} \times \underline{M}(\vec{k}, t) \end{aligned} \quad (14)$$

$$\begin{aligned} & \frac{d}{dt} \left(\frac{\delta \underline{L}}{\delta (\underline{\varphi}^*(\vec{k}, t))} \right) - \frac{\delta \underline{L}}{\delta (\underline{\varphi}^*(\vec{k}, t))} = 0 \\ \implies & -\varepsilon_0 \, i\vec{k} \cdot \dot{\underline{\underline{A}}}(\vec{k}, t) + \varepsilon_0 |\vec{k}|^2 \underline{\underline{\varphi}}(\vec{k}, t) = -i\vec{k} \cdot \underline{\underline{P}}(\vec{k}, t) \end{aligned} \quad (15)$$

where

$$\underline{\underline{P}}(\vec{k}, t) = \int_0^\infty d\omega \int d^3p \, \underline{f}(\omega, \vec{k}, \vec{p}) \cdot \underline{X}_\omega(\vec{p}, t) \quad (16)$$

$$\underline{\underline{M}}(\vec{k}, t) = \int_0^\infty d\omega \int d^3p \, \underline{g}(\omega, \vec{k}, \vec{p}) \cdot \underline{Y}_\omega(\vec{p}, t) \quad (17)$$

are respectively the spatial Fourier transforms of the electric and magnetic polarization densities of the medium and it has been used from the relations (9). Therefore in this method the polarization fields of the medium naturally are concluded in terms of the coupling tensors f, g and the dynamical variables of the E and M fields. In this way we do not need to arrive the polarizations fields directly in the total Lagrangian (1)-(6) as a part of the degrees of freedom of the medium. Similarly the Euler-Lagrange equations for the fields $\underline{\underline{X}}_\omega$ and $\underline{\underline{Y}}_\omega$ for any vector \vec{k} in the half space $k_z \geq 0$ easily are obtained as

$$\begin{aligned} & \frac{d}{dt} \left(\frac{\delta \underline{L}}{\delta (\underline{\dot{X}}_{\omega i}^*(\vec{k}, t))} \right) - \frac{\delta \underline{L}}{\delta (\underline{X}_{\omega i}^*(\vec{k}, t))} = 0 \quad i = 1, 2, 3 \\ \implies & \ddot{\underline{\underline{X}}}_\omega(\vec{k}, t) + \omega^2 \underline{\underline{X}}_\omega(\vec{k}, t) = - \int d^3q \, \underline{f}^\dagger(\omega, \vec{q}, \vec{k}) \cdot \left(\dot{\underline{\underline{A}}}(\vec{q}, t) + i\vec{q} \underline{\underline{\varphi}}(\vec{q}, t) \right) \end{aligned} \quad (18)$$

$$\begin{aligned} & \frac{d}{dt} \left(\frac{\delta \underline{L}}{\delta (\underline{\dot{Y}}_{\omega i}^*(\vec{k}, t))} \right) - \frac{\delta \underline{L}}{\delta (\underline{Y}_{\omega i}^*(\vec{k}, t))} = 0 \quad i = 1, 2, 3 \\ \implies & \ddot{\underline{\underline{Y}}}_\omega(\vec{k}, t) + \omega^2 \underline{\underline{Y}}_\omega(\vec{k}, t) = \int d^3q \, \underline{g}^\dagger(\omega, \vec{q}, \vec{k}) \cdot (i \vec{q} \times \underline{\underline{A}}(\vec{q}, t)) \end{aligned} \quad (19)$$

where we have introduced $\underline{f}_{ij}^\dagger(\omega, \vec{k}, \vec{q}) = \underline{f}_{ji}^*(\omega, \vec{k}, \vec{q})$ for the hermitian conjugate of the tensor \underline{f} and similar expression for the coupling tensor \underline{g} .

3 Canonical quantization

Following the standard approach, we choose the Coulomb gauge $\vec{k} \cdot \vec{A}(\vec{k}, t) = 0$ to quantize electromagnetic field. In this gauge the vector potential \vec{A} is a purely transverse field and can be decomposed along the unit polarization vectors $\vec{e}_{\lambda\vec{k}} \quad \lambda = 1, 2$ which are orthogonal to each other and to the wave vector \vec{k} .

$$\vec{A}(\vec{k}, t) = \sum_{\lambda=1}^2 \underline{A}_{\lambda}(\vec{k}, t) \vec{e}_{\lambda\vec{k}} \quad (20)$$

Although the vector potential is purely transverse, but the dynamical fields \vec{X}_{ω} and \vec{Y}_{ω} may have both transverse and longitudinal parts and can be expanded along the three mutually orthogonal unit vectors $\vec{e}_{\lambda\vec{k}} \quad \lambda = 1, 2$ and $\vec{e}_{3\vec{k}} = \hat{k} = \frac{\vec{k}}{|\vec{k}|}$ as

$$\begin{aligned} \vec{X}_{\omega}(\vec{k}, t) &= \sum_{\lambda=1}^3 \underline{X}_{\omega\lambda}(\vec{k}, t) \vec{e}_{\lambda\vec{k}} \\ \vec{Y}_{\omega}(\vec{k}, t) &= \sum_{\lambda=1}^3 \underline{Y}_{\omega\lambda}(\vec{k}, t) \vec{e}_{\lambda\vec{k}} \end{aligned} \quad (21)$$

Furthermore in Coulomb gauge the Euler- Lagrange equation (15) can be used to eliminate the extra degree of freedom $\underline{\varphi}(\vec{k}, t)$ from the Lagrangian of the system

$$\underline{\varphi}(\vec{k}, t) = -\frac{i\vec{k} \cdot \vec{P}(\vec{k}, t)}{\epsilon_0 |\vec{k}|^2} \quad (22)$$

The total Lagrangian (10)-(13) can now be rewritten in terms of the independent dynamical variables $\underline{A}_{\lambda} \quad \lambda = 1, 2$ and $\vec{X}_{\omega\lambda}, \vec{Y}_{\omega\lambda} \quad \lambda = 1, 2, 3$ which constitute completely the coordinates of the total system

$$\begin{aligned} \underline{L}(t) &= \int_0^{\infty} d\omega \int' d^3k \sum_{\lambda=1}^3 \left(|\dot{\vec{X}}_{\omega\lambda}|^2 - \omega^2 |\vec{X}_{\omega\lambda}|^2 + |\dot{\vec{Y}}_{\omega\lambda}|^2 - \omega^2 |\vec{Y}_{\omega\lambda}|^2 \right) \\ &+ \int' d^3k \sum_{\lambda=1}^2 \left(\epsilon_0 |\dot{\underline{A}}_{\lambda}|^2 - \frac{|\vec{k} \cdot \underline{A}_{\lambda}|^2}{\mu_0} \right) - \frac{1}{\epsilon_0} \int' d^3k \frac{|i\vec{k} \cdot \vec{P}|^2}{|\vec{k}|^2} \\ &+ \int' d^3k \left[\left(-\sum_{\lambda=1}^2 \dot{\underline{A}}_{\lambda} \vec{e}_{\lambda\vec{k}} \right) \cdot \vec{P}^* + \left(i\vec{k} \times \sum_{\lambda=1}^2 \underline{A}_{\lambda} \vec{e}_{\lambda\vec{k}} \right) \cdot \vec{M}^* + h.c \right] \end{aligned} \quad (23)$$

where the polarizations \vec{P} and \vec{M} have been defined previously in terms of the dynamical variables of the E and M fields in equations (16) and (17). The Lagrangian (23) can now be used to define the canonical conjugate momenta of the system. In any wave vector \vec{k} in half space $k_z \geq 0$ this momenta are defined as

$$\begin{aligned}
-\underline{D}_\lambda(\vec{k}, t) &= \frac{\delta \underline{L}}{\delta (\underline{A}_\lambda^*(\vec{k}, t))} = \varepsilon_0 \dot{A}_\lambda(\vec{k}, t) - \vec{e}_{\lambda\vec{k}} \cdot \vec{P}(\vec{k}, t) \\
\underline{Q}_{\omega\lambda}(\vec{k}, t) &= \frac{\delta \underline{L}}{\delta (\underline{X}_{\omega\lambda}^*(\vec{k}, t))} = \underline{X}_{\omega\lambda}(\vec{k}, t) \\
\underline{Y}_{\omega\lambda}(\vec{k}, t) &= \frac{\delta \underline{L}}{\delta (\underline{Y}_{\omega\lambda}^*(\vec{k}, t))} = \underline{Y}_{\omega\lambda}(\vec{k}, t)
\end{aligned} \tag{24}$$

The total system are quantized canonically in a standard method by imposing equal-time commutation relations between the coordinates of the system and their conjugates variables as follows

$$\begin{aligned}
[\underline{A}_\lambda^*(\vec{k}, t), -\underline{D}_{\lambda'}(\vec{k}', t)] &= i\hbar \delta_{\lambda\lambda'} \delta(\vec{k} - \vec{k}') \\
[\underline{X}_{\omega\lambda}^*(\vec{k}, t), \underline{Q}_{\omega'\lambda'}(\vec{k}', t)] &= i\hbar \delta_{\lambda\lambda'} \delta(\omega - \omega') \delta(\vec{k} - \vec{k}') \\
[\underline{Y}_{\omega\lambda}^*(\vec{k}, t), \underline{Y}_{\omega'\lambda'}(\vec{k}', t)] &= i\hbar \delta_{\lambda\lambda'} \delta(\omega - \omega') \delta(\vec{k} - \vec{k}')
\end{aligned} \tag{25}$$

Using the Lagrangian (23) and the conjugates momenta introduced in (24) the Hamiltonian of the total system can be written in the form

$$\begin{aligned}
H(t) &= \int' d^3k \sum_{\lambda=1}^2 \left(\frac{|\underline{D}_\lambda - \vec{e}_{\lambda\vec{k}} \cdot \vec{P}|^2}{\varepsilon_0} + \frac{|\vec{k} \underline{A}_\lambda|^2}{\mu_0} \right) + \int' d^3k \frac{|\vec{k} \cdot \vec{P}|^2}{\varepsilon_0 |\vec{k}|^2} \\
&- \int' d^3k \left[\left(i\vec{k} \times \sum_{\lambda=1}^2 \underline{A}_\lambda \vec{e}_{\lambda\vec{k}} \right) \cdot \vec{M}^* + h.c \right] \\
&+ \int_0^\infty d\omega \int' d^3k \sum_{\lambda=1}^3 (|\underline{Q}_{\omega\lambda}|^2 + \omega^2 |\underline{X}_{\omega\lambda}|^2 + |\underline{Y}_{\omega\lambda}|^2 + \omega^2 |\underline{Y}_{\omega\lambda}|^2)
\end{aligned} \tag{26}$$

3.1 Maxwell equations

Using Heisenberg equations for the operators \underline{D}_λ and \underline{A}_λ Maxwell equations can be obtained as is expected

$$\begin{aligned}\dot{\underline{A}}_\lambda(\vec{k}, t) &= \frac{i}{\hbar} [H, \underline{A}_\lambda(\vec{k}, t)] = - \frac{\underline{D}_\lambda(\vec{k}, t) - \vec{e}_{\lambda\vec{k}} \cdot \underline{\vec{P}}(\vec{k}, t)}{\varepsilon_0} \\ \dot{\underline{D}}_\lambda(\vec{k}, t) &= \frac{i}{\hbar} [H, \underline{D}_\lambda(\vec{k}, t)] = \frac{|\vec{k}|^2}{\mu_0} \underline{A}_\lambda(\vec{k}, t) - \vec{e}_{\lambda\vec{k}} \cdot (i\vec{k} \times \underline{\vec{M}}(\vec{k}, t))\end{aligned}\tag{27}$$

Multiplying both sides of these equations in the polarization unit vector $\vec{e}_{\lambda\vec{k}}$ and then summation on polarization index $\lambda = 1, 2$ and using (22) clearly give us

$$\underline{\vec{D}}(\vec{k}, t) = \varepsilon_0 \underline{\vec{E}}(\vec{k}, t) + \underline{\vec{P}}(\vec{k}, t)\tag{28}$$

$$\dot{\underline{\vec{D}}}(\vec{k}, t) = i\vec{k} \times \underline{\vec{H}}\tag{29}$$

where $\underline{D} = \sum_{\lambda=1}^2 \dot{\underline{D}}_\lambda \vec{e}_{\lambda\vec{k}}$ plays the role of the displacement field, $\underline{\vec{E}} = -\dot{\underline{\vec{A}}} - i\vec{k}\varphi = -\dot{\underline{\vec{A}}} - \frac{\hat{k}(\hat{k} \cdot \underline{\vec{P}})}{\varepsilon_0}$ is the electric field and $\underline{\vec{H}}(\vec{k}, t) = \frac{i\vec{k} \times \underline{\vec{A}}}{\mu_0} - \underline{\vec{M}}$ is the magnetic induction field.

4 The constitutive equations of the medium

It is well known that the constitutive equations of a polarizable and magnetizable medium relating the electric and magnetic polarization densities, respectively, to the electric and magnetic fields are the consequences of the interaction of the medium with electromagnetic field. Any quantization method such as this theory, in which the medium enter directly in the process of quantization and the interaction of the medium with the vacuum field explicitly is given, must be able to give the constitutive equations of the medium using the Heisenberg equations of the total system. Also the susceptibility tensors of the medium which are a measure for the polarizability of the medium should be specified in terms of the parameters describing the interaction of the medium with electromagnetic field. In this section, we find

the constitutive equations of the medium using the Heisenberg equations of the dynamical fields modeling the medium. As we do this, the electric and magnetic susceptibility tensors of the medium are naturally found in terms of the coupling tensors f and g . In the Heisenberg picture, using the commutation relations (25) and the total Hamiltonian (26), the equations of motion for the canonical variables $\underline{X}_{\omega\lambda}$, $\underline{Q}_{\omega\lambda}$ $\lambda = 1, 2, 3$ for each wave vector in the half space $k_z \geq 0$ follow as

$$\begin{aligned}\dot{\underline{X}}_{\omega\lambda}(\vec{k}, t) &= \frac{i}{\hbar}[H, \underline{X}_{\omega\lambda}(\vec{k}, t)] = \underline{Q}_{\omega\lambda}(\vec{k}, t) \\ \dot{\underline{Q}}_{\omega\lambda}(\vec{k}, t) &= [H, \underline{Q}_{\omega\lambda}(\vec{k}, t)] = -\omega^2 \underline{X}_{\omega\lambda}(\vec{k}, t) + \int d^3q \underline{f}_{ij}^*(\omega, \vec{q}, \vec{k}) \underline{E}^i(\vec{q}, t) e_{\lambda\vec{k}}^j\end{aligned}\quad (30)$$

where $\underline{E}(\vec{q}, t) = -\dot{\underline{A}}(\vec{q}, t) - \frac{\hat{q} \cdot \underline{P}(\vec{q}, t)}{\varepsilon_0}$ is the Fourier transform of the total electric field. Multiplying both sides of Eqs. (30) in the mutually orthogonal unit vectors $\vec{e}_{\lambda\vec{k}}$ and then summation on $\lambda = 1, 2, 3$ and using the completeness relations $\sum_{\lambda=1}^3 e_{\lambda\vec{k}}^i e_{\lambda\vec{k}}^j = \delta_{ij}$ we find

$$\ddot{\underline{X}}(\vec{k}, t) + \omega^2 \underline{X}(\vec{k}, t) = \int d^3q \underline{f}^\dagger(\omega, \vec{q}, \vec{k}) \cdot \underline{E}(\vec{q}, t) \quad (31)$$

This equation can be integrated formally as

$$\begin{aligned}\underline{X}_\omega(\vec{k}, t) &= \underline{Q}_\omega(\vec{k}, 0) \frac{\sin \omega t}{\omega} + \underline{X}_\omega(\vec{k}, 0) \cos \omega t \\ &+ \int_0^t dt' \frac{\sin \omega(t-t')}{\omega} \int d^3q \underline{f}^\dagger(\omega, \vec{q}, \vec{k}) \cdot \underline{E}(\vec{q}, t')\end{aligned}\quad (32)$$

Now, by substituting $\underline{X}_\omega(\vec{k}, t)$ from (32) in the definition of electric polarization density given by (16), we find the constitutive equation of the medium in reciprocal space relating the electric polarization to the electric field

$$\underline{P}(\vec{k}, t) = \underline{P}_N(\vec{k}, t) + \varepsilon_0 \int_0^{|t|} dt' \int d^3q \underline{\chi}^e(\vec{k}, \vec{q}, |t-t') \cdot \underline{E}(\vec{q}, \pm t') \quad (33)$$

where the upper (lower) sign corresponds to $t > 0$ ($t < 0$). Here the $\underline{\chi}^e$ is the spatial Fourier transform of the electric susceptibility tensor

$$\underline{\chi}^e(\vec{k}, \vec{q}, t) = \begin{cases} \frac{1}{\varepsilon_0} \int_0^\infty d\omega \frac{\sin \omega t}{\omega} \int d^3p \underline{f}(\omega, \vec{k}, \vec{p}) \cdot \underline{f}^\dagger(\omega, \vec{q}, \vec{p}) & t > 0 \\ 0 & t \leq 0 \end{cases} \quad (34)$$

and is guaranteed to possess solutions for the coupling tensor \underline{f} in terms of the temporal Fourier transform of $\underline{\chi}^e$ using a type of eigenvalue problem[18]. It must be pointed out that for a given $\underline{\chi}^e$ the coupling tensor \underline{f} satisfying the relation (34) is not unique. In fact if \underline{f} satisfy (34), for a given susceptibility tensor ,then

$$\underline{f}'(\omega, \vec{k}, \vec{q}) = \int d^3 p' \underline{f}(\omega, \vec{k}, \vec{p}') \cdot \underline{A}(\omega, \vec{q}, \vec{p}') \quad (35)$$

also satisfy the (34) where \underline{A} is a tensor with orthogonality condition

$$\int d^3 p \underline{A}(\omega, \vec{p}, \vec{p}') \cdot \underline{A}^\dagger(\omega, \vec{p}, \vec{p}'') = I \delta^3(\vec{p}' - \vec{p}'') \quad (36)$$

Although for a given $\underline{\chi}^e$ various choices of the tensor \underline{f} satisfying (34) affect the space-time dependence of electromagnetic field operators, but all of these choices are equivalent and the commutation relations between electromagnetic field operators remain unchanged [23]. That is, the commutation relations between electromagnetic operators and the physical observables finally are dependent only on the given susceptibility tensor not on the coupling functions $\underline{f}, \underline{g}$.

In (33), $\underline{\vec{P}}_N$ is the spatial Fourier transform of the noise electric polarization density which is expressed in terms of the dynamical variables of the "E field" at $t = 0$

$$\underline{\vec{P}}_N(\vec{k}, t) = \int_0^\infty d\omega \int d^3 p \underline{f}(\omega, \vec{k}, \vec{p}) \cdot \left(\underline{\vec{Q}}_\omega(\vec{p}, 0) \frac{\sin \omega t}{\omega} + \underline{\vec{X}}_\omega(\vec{p}, 0) \cos \omega t \right) \quad (37)$$

In a similar fashion the constitutive equation relating the magnetic polarization density of the medium to the magnetic field $\underline{B}(\vec{q}, t) = i\vec{q} \times \underline{A}(\vec{q}, t)$ can be obtained straightforwardly using the Heisenberg equations for the conjugate dynamical variables $\underline{Y}_{\omega\lambda}$ and $\underline{I}_{\omega\lambda}$ as the form

$$\underline{\vec{M}}(\vec{k}, t) = \underline{\vec{M}}_N(\vec{k}, t) + \frac{1}{\mu_0} \int_0^{|t|} dt' \int d^3 q \underline{\chi}^m(\vec{k}, \vec{q}, |t| - t') \cdot \underline{\vec{B}}(\vec{q}, \pm t') \quad (38)$$

where the $\underline{\chi}^m$ is the spatial Fourier transform of the magnetic susceptibility tensor which is written in terms the coupling tensor \underline{g} as

$$\underline{\chi}^m(\vec{k}, \vec{q}, t) = \begin{cases} \mu_0 \int_0^\infty d\omega \frac{\sin \omega t}{\omega} \int d^3 p \underline{g}(\omega, \vec{k}, \vec{p}) \cdot \underline{g}^\dagger(\omega, \vec{q}, \vec{p}) & t > 0 \\ 0 & t \leq 0 \end{cases} \quad (39)$$

and

$$\vec{M}_N(\vec{k}, t) = \int_0^\infty d\omega \int d^3p \underline{g}(\omega, \vec{k}, \vec{p}) \cdot \left(\vec{\Pi}_\omega(\vec{p}, 0) \frac{\sin \omega t}{\omega} + \vec{Y}_\omega(\vec{p}, 0) \cos \omega t \right) \quad (40)$$

is the noise magnetic polarization density.

Therefore modeling an anisotropic spatially and temporally dispersive magnetodielectric medium with two independent collections of harmonic oscillators, that is, the E and M field, we successfully have constructed a fully canonical quantization of electromagnetic field in the presence of such a medium, so that the Maxwell equations together with the constitutive equations of the medium have been obtained from the Heisenberg equations of the total system. In this method the susceptibility tensors of the medium are concluded in terms of the coupling tensors which are the key parameters of this theory and are describing the coupling of the electromagnetic field with the medium.

5 Space -time dependence of the electromagnetic field operators

Our goal for this section is to determine the complete expressions of the electromagnetic field operators for both negative and positive times. The Heisenberg equations of the total system, that is the Maxwell equation (29) together with the constitutive equations (28), (33) and (38), constitute a set of coupled linear equations which can be solved in terms of the initial conditions by the temporal Laplace transformation. This technique has been used previously in the damped polarization model[20]. For an arbitrary time-dependent operator $\Gamma(t)$ the backward and forward Laplace transformations, denoted respectively, by $\Gamma^b(s)$ and $\Gamma^f(\rho)$ are defined as

$$\begin{aligned} \Gamma^b(s) &= \int_0^\infty dt e^{-st} \Gamma(-t) \\ \Gamma^f(s) &= \int_0^\infty dt e^{-st} \Gamma(t) \end{aligned} \quad (41)$$

Carrying out the backward and forward Laplace transformations of Eqs.(28) , (29), (33) , (38) and $i\vec{k} \times \vec{E}(\vec{k}, t) = -\dot{\vec{B}}(\vec{k}, t)$ and then their combination,

for the electric field operator we find

$$\begin{aligned} \int d^3q \left[\vec{k} \times \underline{\tilde{\mu}}(\vec{k}, \vec{q}, s) \left(\vec{q} \times \underline{\vec{E}}^b(\vec{q}, s) \right) \right] - \frac{s^2}{c^2} \int d^3q \underline{\tilde{\epsilon}}(\vec{k}, \vec{q}, s) \underline{\vec{E}}^b(\vec{q}, s) &= \underline{\vec{J}}_N^b(\vec{k}, s) \\ \int d^3q \left[\vec{k} \times \underline{\tilde{\mu}}(\vec{k}, \vec{q}, s) \left(\vec{q} \times \underline{\vec{E}}^f(\vec{q}, s) \right) \right] - \frac{s^2}{c^2} \int d^3q \underline{\tilde{\epsilon}}(\vec{k}, \vec{q}, s) \underline{\vec{E}}^f(\vec{q}, s) &= \underline{\vec{J}}_N^f(\vec{k}, s) \end{aligned} \quad (42)$$

where

$$\begin{aligned} \underline{\tilde{\epsilon}}(\vec{k}, \vec{q}, s) &= \delta(\vec{k} - \vec{q})I + \underline{\tilde{\chi}}^e(\vec{k}, \vec{q}, s) \\ \underline{\tilde{\mu}}(\vec{k}, \vec{q}, s) &= \delta(\vec{k} - \vec{q})I - \underline{\tilde{\chi}}^m(\vec{k}, \vec{q}, s) \end{aligned} \quad (43)$$

are respectively the permittivity and permeability tensors of the medium in Laplace language. The source terms in the right hand of the inhomogeneous Eqs.(42) are the backward and forward Laplace transformations of the noise current density and are expressed in terms of initial conditions of the dynamical variables of the total system at $t = 0$ as

$$\begin{aligned} \underline{\vec{J}}_N^b(\vec{k}, s) &= \mu_0 s^2 \underline{\vec{P}}_N^b(\vec{k}, s) - \mu_0 s \, i\vec{k} \times \underline{M}_N^b(\vec{k}, s) + \\ &\quad i\vec{k} \times \int d^3q \underline{\tilde{\mu}}(\vec{k}, \vec{q}, s) \underline{\vec{B}}(\vec{q}, 0) - \mu_0 s \underline{\vec{D}}(\vec{k}, 0) \\ \underline{\vec{J}}_N^f(\vec{k}, s) &= \mu_0 s^2 \underline{\vec{P}}_N^f(\vec{k}, s) + \mu_0 s \, i\vec{k} \times \underline{M}_N^f(\vec{k}, s) \\ &\quad - i\vec{k} \times \int d^3q \underline{\tilde{\mu}}(\vec{k}, \vec{q}, s) \underline{\vec{B}}(\vec{q}, 0) - \mu_0 s \underline{\vec{D}}(\vec{k}, 0) \end{aligned} \quad (44)$$

Eqs. (42) can be rewritten in a compact form as

$$\begin{aligned} \int d^3q \underline{\Lambda}(\vec{k}, \vec{q}, s) \cdot \underline{\vec{E}}^b(\vec{q}, s) &= \underline{\vec{J}}_N^b(\vec{k}, s) \\ \int d^3q \underline{\Lambda}(\vec{k}, \vec{q}, s) \cdot \underline{\vec{E}}^f(\vec{q}, s) &= \underline{\vec{J}}_N^f(\vec{k}, s) \end{aligned} \quad (45)$$

with

$$\underline{\Lambda}_{ij}(\vec{k}, \vec{q}, s) = \varepsilon_{i\delta\gamma} \varepsilon_{\alpha\beta j} k^\delta q^\beta \underline{\tilde{\mu}}^{\gamma\alpha}(\vec{k}, \vec{q}, s) - \frac{s^2}{c^2} \underline{\tilde{\epsilon}}_{ij}(\vec{k}, \vec{q}, s) \quad (46)$$

From (45) we see that the backward and forward Laplace transformations of the electric field operator satisfy an inhomogeneous equation with a source term. To solve such equations it is common to use the Green function

method. The suitable Green function associated to the Eq. (45) is defined as the solution of an algebraic equation as follows

$$\int d^3q \underline{\Lambda}(\vec{k}, \vec{q}, s) \cdot \underline{G}(\vec{q}, \vec{p}, s) = I \delta(\vec{k} - \vec{p}) \quad (47)$$

Accordingly the solution of Eqs. (45) in terms of the Green function defined in (47) can be written as

$$\begin{aligned} \underline{E}^b(\vec{k}, s) &= \int d^3p \underline{G}(\vec{k}, \vec{p}, s) \cdot \underline{J}_N^b(\vec{p}, s) \\ \underline{E}^f(\vec{k}, s) &= \int d^3p \underline{G}(\vec{k}, \vec{p}, s) \cdot \underline{J}_N^f(\vec{p}, s) \end{aligned} \quad (48)$$

In the special case of a homogeneous medium for which the electric and magnetic susceptibility tensors are translationally invariant, that is when the tensors $\chi^e(\vec{r}, \vec{r}', t)$ and $\chi^m(\vec{r}, \vec{r}', t)$ are a function of the difference $\vec{r} - \vec{r}'$ and so is then, the permittivity and permeability tensors $\varepsilon(\vec{r}, \vec{r}', t)$ and $\mu(\vec{r}, \vec{r}', t)$, we deduce

$$\begin{aligned} \tilde{\underline{\varepsilon}}(\vec{k}, \vec{q}, s) &= \left(I + \tilde{\underline{\chi}}^e(\vec{k}, s) \right) \delta(\vec{k} - \vec{q}) \\ \tilde{\underline{\mu}}(\vec{k}, \vec{q}, s) &= \left(I - \tilde{\underline{\chi}}^m(\vec{k}, s) \right) \delta(\vec{k} - \vec{q}) \end{aligned} \quad (49)$$

and therefore from the Eqs. (46) and (47) we find

$$\begin{aligned} \underline{G}(\vec{k}, \vec{p}, s) &= \underline{T}^{-1}(\vec{k}, s) \delta(\vec{k} - \vec{p}) \\ \underline{T}_{ij} &= \left[\varepsilon_{i\delta\gamma} \varepsilon_{\alpha\beta j} k_\delta k_\beta \left(\delta_{\gamma\alpha} - \tilde{\chi}_{\gamma\alpha}^m(\vec{k}, s) \right) - \frac{s^2}{c^2} \left(\delta_{ij} + \tilde{\chi}_{ij}^e(\vec{k}, s) \right) \right] \end{aligned} \quad (50)$$

where it should be summed on the indices $\alpha, \beta, \gamma, \delta$ in the first term in the bracket. For a general medium it may be impossible to solve Eq.(47) exactly to obtain the Green function \underline{G} . However one can use a suitable iteration method and find the Green function up to an arbitrary accuracy which may be useful for media with considerably weak polarizability. Let us write the tensor $\underline{\Lambda}(\vec{k}, \vec{q}, s)$ as the sum of two parts

$$\underline{\Lambda}(\vec{k}, \vec{q}, s) = \underline{\Lambda}^{(0)}(\vec{k}, \vec{q}, s) + \underline{\Lambda}^{(1)}(\vec{k}, \vec{q}, s) \quad (51)$$

where

$$\underline{\Lambda}_{ij}^{(0)}(\vec{k}, \vec{q}, s) = \left(k_i k_j - \delta_{ij} k^2 - \frac{s^2}{c^2} \delta_{ij} \right) \delta(\vec{k} - \vec{q}) \equiv L(\vec{k}, s) \delta(\vec{k} - \vec{q}) \quad (52)$$

is the tensor $\underline{\Lambda}$ in free space, that is when there is no medium and

$$\underline{\Lambda}_{ij}^{(1)}(\vec{k}, \vec{q}, s) = -\varepsilon_{i\delta\gamma}\varepsilon_{\alpha\beta j}k_{\delta}q_{\beta}\tilde{\chi}_{\gamma\alpha}^m(\vec{k}, \vec{q}, s) - \frac{s^2}{c^2}\tilde{\chi}_{ij}^e(\vec{k}, \vec{q}, s) \quad (53)$$

is the part due to the presence of the medium, that is the effect of the medium in the total tensor $\underline{\Lambda}$. Then, Following a perturbation method the Green function \underline{G} can be expressed as a series

$$\underline{G}(\vec{k}, \vec{p}, s) = \underline{G}^{(0)}(\vec{k}, \vec{p}, s) + \underline{G}^{(1)}(\vec{k}, \vec{p}, s) + \underline{G}^{(2)}(\vec{k}, \vec{p}, s) + \dots \quad (54)$$

Here

$$\underline{G}^{(0)}(\vec{k}, \vec{p}, s) = L^{-1}(\vec{k}, s) \delta(\vec{k} - \vec{p}) \quad (55)$$

is the Green function for the free space and $\underline{G}^{(n)}(\vec{k}, \vec{p}, s) \quad n = 1, 2, 3 \dots$ are found from the following recurrence relation

$$\begin{aligned} \int d^3q \underline{\Lambda}^{(0)}(\vec{k}, \vec{q}, s) \cdot \underline{G}^{(n)}(\vec{q}, \vec{p}, s) &= - \int d^3q \underline{\Lambda}^{(1)}(\vec{k}, \vec{q}, s) \cdot \underline{G}^{(n-1)}(\vec{q}, \vec{p}, s) \\ \implies \underline{G}^{(n)}(\vec{k}, \vec{p}, s) &= -L^{(-1)}(\vec{k}, s) \int d^3q \underline{\Lambda}^{(1)}(\vec{k}, \vec{q}, s) \cdot \underline{G}^{(n-1)}(\vec{q}, \vec{p}, s) \end{aligned} \quad (56)$$

where we have used Eq.(52). Using the series (54) and the recurrence relation (56) one can obtain the Green function \underline{G} up to an arbitrary accuracy. In n'th order approximation it can be neglected from the terms $\underline{G}^{(j)} \quad j \geq n+1$ in the series (54) which may be useful for media with considerably weak polarizability.

Now, having the Green function \underline{G} , the time dependence of electric field operator for negative and positive times can be obtained by inverse Laplace transformations of $\underline{\vec{E}}^b$ and $\underline{\vec{E}}^f$, respectively. Carrying out the inverse Laplace transformation of Eq. (48) for $t < 0$ we deduce

$$\underline{\vec{E}}(\vec{k}, t) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} d\omega e^{-i\omega t} \int d^3p \underline{G}(\vec{k}, \vec{p}, i\omega + 0^+) \cdot \underline{\vec{J}}_N^b(\vec{p}, i\omega + 0^+) \quad (57)$$

where 0^+ is an arbitrarily small positive number. For $t > 0$ the inverse Laplace transformation of $\underline{\vec{E}}^f$ is

$$\underline{\vec{E}}(\vec{k}, t) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} d\omega e^{-i\omega t} \int d^3p \underline{G}(\vec{k}, \vec{p}, -i\omega + 0^+) \cdot \underline{\vec{J}}_N^f(\vec{p}, -i\omega + 0^+) \quad (58)$$

Because the Laplace transformations of the susceptibility tensors are analytic functions respect to the variable s in any point of the half-plane $Re[s] \geq 0$

then, clearly the ω -dependence integrand in Eq. (57) also is analytic in the half-plane $Im[\omega] \leq 0$. Accordingly, the integral over ω in (57) vanishes for the positive times. Likewise the integral in (58) is zero for $t < 0$. Therefore we can combine the two expressions (57) and (58) into a single one and write the full time-dependence of electric field for all times as

$$\begin{aligned} \underline{\vec{E}}(\vec{k}, t) &= \frac{1}{2\pi} \int_{-\infty}^{+\infty} d\omega e^{-i\omega t} \int d^3p \left[\underline{\mathcal{G}}(\vec{k}, \vec{p}, i\omega + 0^+) \cdot \underline{\vec{J}}_N^b(\vec{p}, i\omega + 0^+) \right. \\ &\quad \left. + \underline{\mathcal{G}}(\vec{k}, \vec{p}, -i\omega + 0^+) \cdot \underline{\vec{J}}_N^f(\vec{p}, -i\omega + 0^+) \right] \end{aligned} \quad (59)$$

It is remarkable that using the asymptotic behavior of the Green function $\underline{\mathcal{G}}$ and the susceptibility tensors for large $|\omega|$ it can be verified straightforwardly, the integral in (59) reduces to $\underline{\vec{E}}(\vec{k}, 0)$ at $t = 0$ and hence this equation give us correctly the time dependence of the electric field for all times. Finally having the electric field operator, we can obtain the magnetic field using $i\vec{k} \times \underline{\vec{E}}(\vec{k}, t) = \underline{\vec{B}}(\vec{k}, t)$ and then the polarization densities employing the constitutive Eqs.(33) and (38).

6 Summary and concluding remarks

By modeling an anisotropic polarizable and magnetizable medium with spatial-temporal dispersion phenomenologically with two continuous collections of three dimensional vector fields, we have presented a fully canonical quantization for electromagnetic field in the presence of such a medium. In this model the polarization fields of the medium did not enter directly in the Lagrangian of the total system as a part of the degrees of freedom of the medium, but the space-dependent oscillators modeling the medium solely was sufficient to describe both polarizability and the absorption of the medium. The interaction of the medium with the electromagnetic field explicitly was given and both the Maxwell's laws and the constitutive equations of the medium were obtained as the consequences of the Heisenberg equations of total system. The electric and magnetic polarization fields of the medium could be deduced naturally in terms of the dynamical fields modeling the medium. Some space dependent real valued tensor coupling the medium with electromagnetic field were introduced. The coupling tensor had an important role in this quantization scheme, so that the electric and magnetic susceptibility tensors of the

medium were determined in terms of the coupling tensor. Also the noise polarizations were expressed in terms of the coupling tensor and the dynamical variables describing the degrees of freedom of the medium at $t = 0$. In the free space and in the case of a non-absorbing medium the coupling tensor and the noise polarizations tend to zero and this quantization method is reduced to the usual quantization in these limiting cases. As a tool, we have used the reciprocal space to quantize the total system. It was shown the temporal backward and forward Laplace transforms of the electric field obey some algebraic equations with source terms that could be determined in terms of the dynamical variables of the system at $t = 0$. By introducing the Green function of these algebraic equations we were able to determine the Green function up to an arbitrary accuracy using a perturbation method which may be useful in some real cases with weak polarizability. The time-dependence of electric field was derived for both negative and positive times.

References

- [1] T. Gruner, D. G. Welsch, Phys. Rev. A 51, 3246 (1995).
- [2] R. Matloob, R. Loudon, S. M. Barnett, J. Jeffers, Phys. Rev. A 52, 4823 (1995).
- [3] T. Gruner, D. G. Welsch, Phys. Rev. A 53, 1818 (1996).
- [4] R. Matloob, R. Loudon, Phys. Rev. A 53, 4567 (1996).
- [5] T. Gruner, D. G. Welsch, Phys. Rev. A 54, 1661 (1996).
- [6] H. T. Dung, L. Knöll, D. G. Welsch, Phys. Rev. A 57, 3931(1998)
- [7] S. Scheel, L. Knöll, D. G. Welsch, Phys. Rev. A 58, 700(1998)
- [8] B. Huttner, S. M. Barnett, Phys. Rev. A 46, 4306 (1992).
- [9] B. Huttner, S. M. Barnett, Europhys. Lett. 18, 487 (1992).
- [10] S. M. Barnett, B. Huttner, R. Loudon, R. Matloob, J. Phys. B 29, 3763(1996)
- [11] S. Scheel, L. Knöll, D. G. Welsch, S. M. Barnett, Phys. Rev. A 60, 1590(1999).

- [12] S. Scheel, L. Knöll, D. G. Welsch, Phys. Rev. A 60, 4094 (1999).
- [13] H. T. Dung, L. Knöll, D. G. Welsch, Phys. Rev. A 62, 053804(2000)
- [14] H. T. Dung, L. Knöll, D. G. Welsch, Phys. Rev. A 66, 063810(2002)
- [15] L. Knöll, S. Scheel, D. G. Welsch, *in Coherence and Statistics of photons and atoms*, edited by J. Peřina (Wiley, Newyork, 2001).
- [16] A. Lukš, V. Peřinová, *in progress in optics*, Edited by E. Wolf (North-Holand, Amsterdam, 2002) Vol. 43, p. 295.
- [17] H. T. Dung, S. Y. Buhmann, L. Knöll, D. G. Welsch, Phys. Rev. A 68, 043816 (2003).
- [18] C. Raabe, S. Scheel, D. G. Welsch, Phys. Rev. A 75, 053813 (2007).
- [19] L. D. Landau, E. M. Lifshitz, *Electrodynamics of Continuous Media*(oxford: Pergamon, 1977).
- [20] L. G. Suttorp, M. Wubs, Phys. Rev. A 70, 013816 (2004)
- [21] F. Kheirandish, M. Amooshahi, Phys. Rev. A 74, 042102(2006).
- [22] M. Amooshahi, F. Kheirandish, Phys. Rev. A 76, 062103(2006).
- [23] M. Amooshahi, F. Kheirandish, Modd. Phys. Lett. A 23, No. 26 (2008)