

REALIZATION SCHEMES FOR QUANTUM INSTRUMENTS IN FINITE DIMENSIONS

GIULIO CHIRIBELLA, GIACOMO MAURO D'ARIANO, AND PAOLO PERINOTTI

ABSTRACT. We present a general dilation scheme for quantum instruments with continuous outcome space in finite dimensions, in terms of an indirect POVM measurement performed on a finite dimensional ancilla. The general result is then applied to a large class of instruments generated by operator frames, which contains group-covariant instruments as a particular case, and allows to construct dilation schemes based on a measurement on the ancilla followed by a conditional feed-forward operation on the output. In the case of tight operator frames our construction generalizes quantum teleportation and telecloning, producing a whole family of generalized teleportation schemes in which the instrument is realized via a joint POVM at the sender combined with a conditional feed-forward operation at the receiver.

1. INTRODUCTION

The theory of quantum measurements for discrete spectrum has been formulated by von Neumann in the pioneering work [1]. For continuous-outcome quantum measurements, however, a satisfactory theory has been lacking for another thirty years, when the problem was finally settled by Ozawa [2]. The main difficulties with the continuous-outcome measurements were *i)* the issue of repeatability, and *ii)* the compatibility between the statistics of the measurement and the dynamical evolution of the observed system and the measuring apparatus. In their pioneering work [3], Davies and Lewis introduced an operational framework for the statistical description based on the mathematical concept of "instrument"—i.e. of transformation-valued measure. In this framework they formulated a weak repeatability hypothesis, and conjectured that instruments for continuous-outcome measurements can never be repeatable, even in such weak sense. Davies and Lewis, however, overlooked the requirement of complete positivity of the state change in measurements, which was instead established by Kraus [4] in the particular case of yes-no measurements. Thirteen years later Ozawa [2] showed that the state change due to an arbitrary measuring process are described by completely positive (CP) instruments, and, viceversa, that any CP instrument can be dilated to an indirect measurement process, with the measured system unitarily interacting with an ancilla which then undergoes the measurement of a von Neumann observable with the same outcome space of the instrument. In the same paper, Ozawa finally proved the Davies and Lewis conjecture for CP instruments, showing that they cannot be weakly repeatable unless their outcome space is discrete.

A von Neumann observable with continuous outcome space is a projection valued measure (PVM), such as the spectral measure of a selfadjoint operator with continuous spectrum. Such a continuous-outcome observable can exist only for infinite

dimensional systems. It follows that the Ozawa dilations of quantum instruments with continuous outcome space, even for finite dimensional systems, require an infinite dimensional ancilla. A general positive operator valued measure (POVM), on the contrary, can have a continuous outcome space even for finite dimensions, e. g. for the measurement of the spin direction [5]. Recently, in Refs. [6, 7] it has been shown that in finite dimensions every continuous-outcome POVM can be achieved as the randomization of finite-outcome POVMs with no more than d^2 outcomes, d being the dimension of the system's Hilbert space. Exploiting Naimark dilation [8] of the finite-outcome POVMs involved in the randomization, this implies that for finite dimensions any continuous-outcome POVM can be realized as a randomized observable with dimensions no greater than d^2 . Therefore, realization of an instrument via indirect measurement of a POVM on a finite-dimensional ancilla allows one to achieve the instrument as the indirect measurement of a randomized observable in finite dimension.

The existence of the dilation for the continuous-outcome instrument to a POVM on a finite-dimensional ancilla has not been considered yet in the literature, and it is not a priori obvious, since the usual dilation procedure exploits the orthogonality of the PVM. Such an indirect-POVM realization of the instrument is the main result of the present paper, where we construct a general realization scheme for a quantum instrument with continuous outcome space in finite dimension, in terms of an indirect POVM measurement performed on an ancilla interacting with the system. In addition, in this paper we define the notion of instruments generated by operator frames and specialize our dilation theorem to this case, showing that any such instrument allows a realization in terms of an ancilla measurement followed by a conditional feed-forward operation. For tight operator frames, the feed-forward scheme becomes a generalized teleportation scheme, namely a scheme where a sender performs a joint POVM measurement on the input system and locally on another system of an entangled pair, and communicates the measurement outcome to the receiver, who then performs a suitable conditional quantum channel on the other system of the entangled pair.

The paper is organized as follows: in Sect. 2 we recall the preliminary notions used in the paper, also giving a new compact rule for expressing the minimal Stinespring dilation of a given CP map as a function of its Choi-Jamiołkowski operator. The general dilation theorem for quantum instruments in finite dimensions is then presented in Sect. 3, where we construct an indirect measuring process based on a POVM on a finite dimensional ancilla. In Sect. 4 we introduce a class of instruments generated by operator frames, which contains group-covariant instruments as a special case. The case of group-covariant instruments is then analyzed in detail in Sect. 5. In Sect. 6 we specialize to the case of instruments generated by tight operator frames, showing that any such instrument can be realized via generalized teleportation scheme, with a joint measurement at the sender and a conditional operation at the receiver. This construction generalizes quantum teleportation and provides the general framework for quantum tasks such as tele-cloning [9] and tele-UNOT [10], as shown in Sect. 7, where we provide generalized teleportation schemes for covariant channels.

2. GENERAL NOTIONS ON QUANTUM INSTRUMENTS AND CHANNELS

In the following we will denote by $\text{Lin}(\mathbb{H})$ the vector space of linear operators on the Hilbert space \mathbb{H} , and by $\text{Lin}(\mathbb{H}, \mathbb{K})$ the vector space of linear operators from \mathbb{H} to \mathbb{K} . We will exclusively consider finite dimensional Hilbert spaces. Moreover, we will denote by $\mathcal{S}(\mathbb{H})$ the convex set of density matrices on \mathbb{H} , and by $\text{CP}(\mathbb{H}, \mathbb{K})$ the convex cone of completely positive (CP) maps from $\text{Lin}(\mathbb{H})$ to $\text{Lin}(\mathbb{K})$.

2.1. Quantum Operations. In Quantum Mechanics the most general evolution of a system is described by a **quantum operation**[11]. We will consider generally different input and output systems in the evolution, and denote by \mathbb{H}_{in} and \mathbb{H}_{out} the corresponding Hilbert spaces. Then, a quantum operation with input space \mathbb{H}_{in} and output space \mathbb{H}_{out} is a CP-map $\mathcal{E} \in \text{CP}(\mathbb{H}_{\text{in}}, \mathbb{H}_{\text{out}})$ which is also trace-non-increasing. The operation \mathcal{E} transforms the input state $\rho_{\text{in}} \in \mathcal{S}(\mathbb{H}_{\text{in}})$ into the output state $\rho_{\text{out}} \in \mathcal{S}(\mathbb{H}_{\text{out}})$ as follows

$$(1) \quad \rho_{\text{out}} = \frac{\mathcal{E}(\rho_{\text{in}})}{\text{Tr}[\mathcal{E}(\rho_{\text{in}})]},$$

the transformation occurring with probability $p_{\mathcal{E}} := \text{Tr}[\mathcal{E}(\rho_{\text{in}})]$ among a set of possible transformations. In the deterministic case the map \mathcal{E} is trace preserving, and the quantum operation is usually called **quantum channel**.

2.2. Representations of operators and CP-maps. In finite dimensions it is convenient to exploit the isomorphism between $\text{Lin}(\mathbb{H}_{\text{in}}, \mathbb{H}_{\text{out}})$ and $\mathbb{H}_{\text{out}} \otimes \mathbb{H}_{\text{in}}$ induced by correspondence $F \in \text{Lin}(\mathbb{H}_{\text{in}}, \mathbb{H}_{\text{out}}) \mapsto |F\rangle\rangle \in \mathbb{H}_{\text{out}} \otimes \mathbb{H}_{\text{in}}$ given by

$$(2) \quad |F\rangle\rangle := (F \otimes \mathbb{1}_{\text{in}})|\mathbb{1}_{\text{in}}\rangle\rangle,$$

where $|\mathbb{1}_{\text{in}}\rangle\rangle \in \mathbb{H}_{\text{in}}^{\otimes 2}$ is the maximally entangled vector $|\mathbb{1}_{\text{in}}\rangle\rangle \doteq \sum_n |n\rangle|n\rangle$, $\{|n\rangle\}$ being a fixed orthonormal basis for \mathbb{H}_{in} . All throughout the paper we will make extensive use of the relation

$$(3) \quad A \otimes B |F\rangle\rangle = |AFB^{\tau}\rangle\rangle \quad \forall A \in \text{Lin}(\mathbb{H}_{\text{out}}), \forall B \in \text{Lin}(\mathbb{H}_{\text{in}}), \forall F \in \text{Lin}(\mathbb{H}_{\text{in}}, \mathbb{H}_{\text{out}}),$$

τ denoting transposition w.r.t. the fixed basis.

In finite dimensions it is convenient to represent linear maps \mathcal{M} from $\text{Lin}(\mathbb{H}_{\text{in}})$ to $\text{Lin}(\mathbb{H}_{\text{out}})$ as linear operators $R_{\mathcal{M}}$ on $\mathbb{H}_{\text{out}} \otimes \mathbb{H}_{\text{in}}$ via the so-called Choi-Jamiołkowski (CJ) isomorphism [12, 13]

$$(4) \quad R_{\mathcal{M}} = \mathcal{M} \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\rangle\langle\langle\mathbb{1}_{\text{in}}|), \quad \mathcal{M}(\rho) = \text{Tr}_{\text{in}}[(\mathbb{1}_{\text{out}} \otimes \rho^{\tau})R_{\mathcal{M}}],$$

where \mathcal{I} is the identity map and Tr_{in} denotes the partial trace on \mathbb{H}_{in} (see [14] for the second equality in Eq. (4)). It is easy to check that the linear map \mathcal{M} is CP if and only if the **CJ operator** $R_{\mathcal{M}}$ is positive, and the correspondence $\mathcal{M} \leftrightarrow R_{\mathcal{M}}$ is an isomorphism of positive cones. Moreover, \mathcal{M} is trace-non-increasing if and only if the following domination relation holds

$$(5) \quad \text{Tr}_{\text{out}}[R_{\mathcal{M}}] \leq \mathbb{1}_{\text{in}},$$

the equal sign corresponding to the trace-preserving case of the quantum channel.

Another convenient isomorphism is the one between linear maps \mathcal{M} from $\text{Lin}(\mathbb{H}_{\text{in}})$ to $\text{Lin}(\mathbb{H}_{\text{out}})$ and linear operators $\check{R}_{\mathcal{M}}$ from $\mathbb{H}_{\text{in}}^{\otimes 2}$ to $\mathbb{H}_{\text{out}}^{\otimes 2}$ given by

$$(6) \quad \check{R}_{\mathcal{M}}|X\rangle\rangle = |\mathcal{M}(X)\rangle\rangle \quad \forall X \in \text{Lin}(\mathbb{H}_{\text{in}}) \simeq \mathbb{H}_{\text{in}}^{\otimes 2}$$

In this case one has $\check{R}_{\mathcal{A}\mathcal{B}} = \check{R}_{\mathcal{A}}\check{R}_{\mathcal{B}}$, namely the correspondence $\mathcal{M} \leftrightarrow \check{R}_{\mathcal{M}}$ is an isomorphism of (finite dimensional) algebras. The correspondence $\mathcal{M} \leftrightarrow \check{R}_{\mathcal{M}}$ also induces a one-to-one correspondence between $R_{\mathcal{M}} \in \text{Lin}(\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\text{in}})$ and $\check{R}_{\mathcal{M}} \in \text{Lin}(\mathbf{H}_{\text{in}}^{\otimes 2}, \mathbf{H}_{\text{out}}^{\otimes 2})$:

$$(7) \quad \check{R}_{\mathcal{M}} = \mathbf{I}(R_{\mathcal{M}}),$$

Every quantum operation \mathcal{M} can be written in a (non-unique) **Kraus form**

$$(8) \quad \mathcal{M}(\rho) = \sum_i M_i \rho M_i^\dagger.$$

The Kraus form is equivalent to decomposing the CJ positive operator $R_{\mathcal{M}}$ into rank-one positive operators

$$(9) \quad R_{\mathcal{M}} = \sum_i |M_i\rangle\rangle\langle\langle M_i|.$$

In particular, diagonalization of $R_{\mathcal{M}}$ yields to the **canonical Kraus form** $\mathcal{M}(\rho) = \sum_i K_i \rho K_i^\dagger$, $\text{Tr}[K_i^\dagger K_j] = \delta_{ij} \|K_i\|_2^2$, where $\|X\|_2 := \text{Tr}[X^\dagger X]^{\frac{1}{2}}$ is the Hilbert-Schmidt norm. Moreover, using Eqs. (6) and (3) the operator $\check{R}_{\mathcal{M}} = \mathbf{I}(R_{\mathcal{M}})$ can be written in terms of any Kraus form as follows

$$(10) \quad \mathbf{I}(R_{\mathcal{M}}) = \sum_i M_i \otimes M_i^*.$$

Different Kraus decompositions are all connected to a minimal one—e. g. the canonical—by an isometric matrix W as follows

$$(11) \quad M_i = \sum_j W_{ij} K_j, \quad \sum_k W_{ki}^* W_{kj} = \delta_{ij}.$$

Therefore, the operator space $\text{Span}\{M_i\}$ is independent of the choice of the Kraus form, and is a function only of the map \mathcal{M} . In the following we will make use of the corresponding Hilbert space, which is spanned by the bipartite vectors $\{|M_i\rangle\rangle\}$

$$(12) \quad \mathbf{H}_{\mathcal{M}} = \text{Span}\{|M_i\rangle\rangle\} \equiv \text{Supp}(R_{\mathcal{M}}).$$

Note that generally $\mathbf{H}_{\mathcal{M}}$ can be a proper subspace of $\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\text{in}}$.

2.3. Operator frames. The Kraus operators $\{M_i\}$ are generally non orthogonal, and not even linearly independent. They are a so-called **operator frame** for the operator space $\text{Span}\{M_i\}$, namely a (possibly infinite) set of vectors such that the sum $\sum_i |M_i\rangle\rangle\langle\langle M_i|$ converges to an operator $M \in \text{Lin}(\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\text{in}})$, called the **frame operator**. For Kraus operators we have indeed

$$(13) \quad M := \sum_i |M_i\rangle\rangle\langle\langle M_i| = R_{\mathcal{M}}.$$

Any vector $|A\rangle\rangle$ in $\text{Supp}(R_{\mathcal{M}})$ can be expanded on the frame $\{|M_i\rangle\rangle\}$, and the expansion can be written in terms of another set of operators $\{N_i\}$ called **dual of the frame** $\{M_i\}$ as $|A\rangle\rangle = \sum_i |M_i\rangle\rangle\langle\langle N_i|A\rangle\rangle$. Equivalently, we have the completeness relation

$$(14) \quad \sum_i |M_i\rangle\rangle\langle\langle N_i| = \mathbb{1}_{\text{out}} \otimes \mathbb{1}_{\text{in}}.$$

A possible choice of dual, particularly relevant to our purposes, is the **canonical dual** given by

$$(15) \quad |\hat{M}_i\rangle\rangle = M^{-1}|M_i\rangle\rangle,$$

Notice that the inverse M^{-1} is actually defined on $H_{\mathcal{M}} = \text{Rng}(R_{\mathcal{M}}) \equiv \text{Supp}(R_{\mathcal{M}})$, and on $H_{\text{out}} \otimes H_{\text{in}}$ it must be regarded as the Moore-Penrose pseudoinverse with support on $H_{\mathcal{M}}$.

2.4. Minimal dilation of a quantum operation. For $\{M_i\}$ Kraus operators of the CP map \mathcal{M} , the frame operator M is just the CJ operator $R_{\mathcal{M}} \equiv M$ of the map \mathcal{M} , whence it is independent of the choice of the Kraus operators $\{M_i\}$. Consider now the following operator $V : H_{\text{in}} \rightarrow H_{\text{out}} \otimes H_{\mathcal{M}}$

$$(16) \quad V = \sum_i M_i \otimes (M^{-\frac{1}{2}} * |M_i^*\rangle\rangle)$$

where $*$ denotes complex conjugation componentwise w.r.t. the fixed tensor basis $\{|m\rangle \otimes |n\rangle\}$. Note that V is independent of the choice of the Kraus form: indeed, one has

$$(17) \quad V = \sum_{ijk} W_{ij} W_{ik}^* K_j \otimes (R_{\mathcal{M}}^{-\frac{1}{2}})^* |K_k^*\rangle\rangle = \sum_j K_j \otimes (R_{\mathcal{M}}^{-\frac{1}{2}})^* |K_j^*\rangle\rangle = \sum_j K_j \otimes \frac{|K_j^*\rangle\rangle}{\|K_j\|_2},$$

having used Eq. (11) and the fact that each canonical Kraus operator K_i is eigenvector of $R_{\mathcal{M}}$ with eigenvalue $\|K_i\|_2^2$. Clearly the operator V provides a dilation of the CP map \mathcal{M} , with $H_{\mathcal{M}}$ playing the role of ancillary Hilbert space:

$$(18) \quad \mathcal{M}(\rho) = \text{Tr}_{H_{\mathcal{M}}}[V\rho V^\dagger].$$

For quantum operations V is a contraction ($V^\dagger V \leq \mathbb{1}_{\text{in}}$), while for quantum channels V is an isometry ($V^\dagger V = \mathbb{1}_{\text{in}}$).

Among all possible dilations of \mathcal{M} , the one given by V in Eq. (18) has minimum ancilla dimension. Indeed, for any operator $V' : H_{\text{in}} \rightarrow H_{\text{out}} \otimes H_A$ such that $\mathcal{M}(\rho) = \text{Tr}_A[V'\rho V'^\dagger]$, the map $\mathcal{M}(\rho)$ has Kraus representation $\{M_i := {}_A\langle i|V'\rangle\rangle$ where $\{|i\rangle_A\}$ is an orthonormal basis for H_A . Then, according to Eq. (9) $\dim(H_A) \geq \text{rank}(R_{\mathcal{M}}) = \dim(H_{\mathcal{M}})$. In other words, V is the **minimal Stinespring dilation** of the CP map \mathcal{M} [15]. Any non-minimal dilation V' is connected to the minimal one via an isometry of ancillary spaces $Y : H_{\mathcal{M}} \rightarrow H_A$, $Y^\dagger Y = \mathbb{1}_{H_{\mathcal{M}}}$. Indeed, using Eq. (11) one has

$$(19) \quad V' = \sum_{ij} W_{ij} K_j \otimes |i\rangle = \sum_j K_j \otimes |\psi_j\rangle = (\mathbb{1}_{\text{out}} \otimes Y)V,$$

where $\{|\psi_j\rangle \in H_A\}$ are the orthonormal vectors $|\psi_j\rangle := \sum_i W_{ij}|i\rangle$ and Y is the isometry $Y := \frac{|\psi_j\rangle\langle\langle K_j^*|}{\|K_j\|_2}$. The minimal Stinespring dilation is unique up to local unitaries on the ancilla Hilbert space $H_{\mathcal{M}}$, namely if V' is also minimal, then Y is a unitary from $H_{\mathcal{M}}$ to H_A [15].

We now give a new compact formula for the minimal Stinespring dilation of a CP map in terms of the Choi-Jamiolkowski operator $R_{\mathcal{M}}$:

Proposition 1. *Let $R_{\mathcal{M}} \in \text{Lin}(\mathbf{H}_{\text{out}}, \mathbf{H}_{\text{in}})$ be the Choi-Jamiołkowski operator associated to the CP map $\mathcal{M} \in \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$. Then, a minimal dilation $V : \mathbf{H}_{\text{in}} \rightarrow \mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\mathcal{M}}$ is given by*

$$(20) \quad V = (\mathbb{1}_{\text{out}} \otimes R_{\mathcal{M}}^{*\frac{1}{2}})(|\mathbb{1}_{\text{out}}\rangle\rangle \otimes \mathbb{1}_{\text{in}}),$$

or, alternatively, by

$$(21) \quad V = (\mathbf{I}(R_{\mathcal{M}}^{\frac{1}{2}}) \otimes \mathbb{1}_{\text{in}})(\mathbb{1}_{\text{in}} \otimes |\mathbb{1}_{\text{in}}\rangle\rangle),$$

\mathbf{I} being the one-to-one correspondence defined in Eq. (7)

Proof. It is simple to check that Eq. (20) provides a dilation of \mathcal{M} , which is clearly minimal since the ancilla space is $\mathbf{H}_{\mathcal{M}} = \text{Supp}(R_{\mathcal{M}})$. Indeed, using the inclusion $\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\mathcal{M}} \subseteq \mathbf{H}_{\text{out}}^{\otimes 2} \otimes \mathbf{H}_{\text{in}}$ and Eqs. (3) and (4) one has for any $\rho \in \mathbf{S}(\mathbf{H}_{\text{in}})$

$$(22) \quad \begin{aligned} \text{Tr}_{\mathbf{H}_{\mathcal{M}}}[V\rho V^\dagger] &= \text{Tr}_{\text{out}_2} \text{Tr}_{\text{in}}[(\mathbb{1}_{\text{out}} \otimes R_{\mathcal{M}}^*)(|\mathbb{1}_{\text{out}}\rangle\rangle\langle\langle \mathbb{1}_{\text{out}}| \otimes \rho)] \\ &= \text{Tr}_{\text{out}_2}[(\mathbb{1}_{\text{out}} \otimes \mathcal{M}(\rho)^*)|\mathbb{1}_{\text{out}}\rangle\rangle\langle\langle \mathbb{1}_{\text{out}}|] \\ &= \mathcal{M}(\rho), \end{aligned}$$

Tr_{out_2} denoting partial trace over the second copy of \mathbf{H}_{out} in the tensor product $\mathbf{H}_{\text{out}}^{\otimes 2} \otimes \mathbf{H}_{\text{in}}$. On the other hand, using the relation $(R_{\mathcal{M}})^s = \sum_j \|K_j\|^{2(s-1)} |K_j\rangle\rangle\langle\langle K_j|$ along with Eq. (10) we get $\mathbf{I}(R_{\mathcal{M}}^{\frac{1}{2}}) = \sum_j \|K_j\|^{-\frac{1}{2}} K_j \otimes K_j^*$. Substituting $\mathbf{I}(R_{\mathcal{M}}^{\frac{1}{2}})$ into Eq. (21) and comparing with Eq. (17) we obtain that the definition of V in Eqs. (21) and (16) actually coincide. Finally, direct calculation shows the coincidence of definitions of V in (20) and (21). ■

2.5. POVMs and Quantum Instruments. The statistics of a quantum measurement is described by a **measurable space** Ω with a σ -**algebra** Σ_Ω of **events**, and a **probability measure** p on (Ω, Σ_Ω) . In Quantum Mechanics the probability measure in terms of the quantum state ρ is given by the **Born rule**

$$(23) \quad \forall B \in \Sigma_\Omega, \quad p(B) = \text{Tr}[\rho P_B],$$

where P is a **positive operator valued measure (POVM)**, namely a map from events $B \in \Sigma_\Omega$ to positive operators $P_B \geq 0$ on \mathbf{H} , satisfying the requirements

$$(24) \quad P_\Omega = \mathbb{1} \quad (\text{normalization})$$

$$(25) \quad P_{(\cup_{i=1}^{\infty} B_i)} = \sum_{i=1}^{\infty} P_{B_i} \quad \forall \{B_i\} : B_i \cap B_j = \emptyset \quad \forall i \neq j, \quad (\sigma\text{-additivity}),$$

where the series converges in the weak operator topology.

A complete description of a measurement in a cascade of different measurements performed on the same system must also provide the **conditional state** associated to any possible event. In Quantum Mechanics this is given by the notion of "quantum instrument" [2], in which each event $B \in \Sigma_\Omega$ corresponds to a quantum operation $\mathcal{Z}_B \in \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$. More precisely, we have

Definition 1. *A map $\mathcal{Z} : \Sigma_\Omega \rightarrow \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ is a quantum instrument if it satisfies the properties*

$$(26) \quad \text{Tr}[\mathcal{Z}_\Omega(\rho)] = \text{Tr}[\rho] \quad \forall \rho \in \mathbf{S}(\mathbf{H}_{\text{in}})$$

$$(27) \quad \mathcal{Z}_{(\cup_{i=1}^{\infty} B_i)} = \sum_{i=1}^{\infty} \mathcal{Z}_{B_i} \quad \forall \{B_i\} : B_i \cap B_j = \emptyset \quad \forall i \neq j.$$

Using the CJ isomorphism (4), any instrument \mathcal{I} can be associated in a one-to-one fashion with a positive operator valued measure Z , which we call **Choi-Jamiołkowski measure (CJM) of the instrument**, given by

$$(28) \quad Z_B := R_{\mathcal{I}_B} = \mathcal{L}_B \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\rangle\langle\langle\mathbb{1}_{\text{in}}|) \quad \forall B \in \Sigma_\Omega.$$

Differently from usual POVMs, for which the normalization is given by Eq. (24) the measure Z has the normalization condition

$$(29) \quad \text{Tr}_{\text{out}}[Z_\Omega] = \mathbb{1}_{\text{in}} ,$$

$\text{Tr}_{\text{out}}[\cdot]$ denoting partial trace over \mathbf{H}_{out} .

The POVM P giving the probability of the event $B \in \Sigma_\Omega$ for state $\rho \in \mathbf{S}(\mathbf{H}_{\text{in}})$ can be written in terms of the CJM Z using the isomorphism (4) as follows

$$(30) \quad \begin{aligned} \text{Tr}[P_B \rho] &= \text{Tr}[\mathcal{L}_B(\rho)] = \text{Tr}[(\mathbb{1}_{\text{out}} \otimes \rho^\tau) Z_B] = \text{Tr}[\rho \text{Tr}_{\text{out}}(Z_B)^\tau] \\ &= \text{Tr}[\rho \text{Tr}_{\text{out}}[Z_B^*]] , \end{aligned}$$

whence

$$(31) \quad P_B = \text{Tr}_{\text{out}}[Z_B^*] \quad \forall B \in \Sigma_\Omega.$$

In finite dimensions, the correspondence between instruments and CJMs allows one to simply prove the existence of an instrument density w.r.t. a suitable scalar measure [16, 17].

Proposition 2. *Any instrument $\mathcal{I} : \Sigma_\Omega \rightarrow \mathbf{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ in finite dimensions can be written as*

$$(32) \quad \mathcal{L}_B = \int_B \mu(d\omega) \mathcal{S}_\omega$$

where $\mu(d\omega)$ is the finite measure defined by $\mu(B) \doteq \text{Tr}[Z_B] \forall B \in \Sigma_\Omega$, and the density \mathcal{S}_ω is a CP-map valued function, uniquely defined μ -almost everywhere.

Proof. Let $\{|k\rangle\}$ be an orthonormal basis for $\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\text{in}}$ and define the complex measures μ_{kl} , $\mu_{kl}(B) := \langle k|Z_B|l\rangle$. Due to positivity, one has $|\mu_{kl}(B)| \leq \sqrt{\langle k|Z_B|k\rangle\langle l|Z_B|l\rangle} \leq \text{Tr}[Z_B] = \mu(B)$, i.e. all measures μ_{kl} are absolutely continuous w.r.t. μ . Therefore, any measure μ_{kl} admits a density $\sigma_{kl}(\omega)$ w.r.t. μ . We then have

$$(33) \quad Z_B = \sum_{k,l} \mu_{kl}(B) |k\rangle\langle l| = \sum_{k,l} \int_B \mu(d\omega) \sigma_{kl}(\omega) |k\rangle\langle l| = \int_B \mu(d\omega) S_\omega ,$$

having defined $S_\omega := \sum_{k,l} \sigma_{kl}(\omega) |k\rangle\langle l|$. Since S_ω is the density of the positive operator valued measure Z_B w.r.t. the scalar measure μ , it is positive and uniquely defined μ -a.e. The instrument density \mathcal{S}_ω is then obtained by the relation $\mathcal{S}_\omega(\rho) = \text{Tr}_{\text{in}}[(\mathbb{1}_{\text{out}} \otimes \rho^\tau) S_\omega]$. ■

3. DILATIONS OF QUANTUM INSTRUMENTS

We are now in position to prove a dilation theorem for instruments with generally continuous outcome space in finite dimensions. A **dilation of a quantum instrument** $\mathcal{I} : \Sigma_\Omega \rightarrow \mathbf{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ is a triple (\mathbf{H}_A, V, Q) , where \mathbf{H}_A is an ancillary Hilbert space, $V : \mathbf{H}_{\text{in}} \rightarrow \mathbf{H}_{\text{out}} \otimes \mathbf{H}_A$ is an isometry, and $Q : \Sigma_\Omega \rightarrow \mathbf{Lin}(\mathbf{H}_A)$ is a POVM on the ancilla, such that

$$(34) \quad \mathcal{L}_B(\rho) = \text{Tr}_{\mathbf{H}_A}[V \rho V^\dagger (\mathbb{1}_{\text{out}} \otimes Q_B)] \quad \forall B \in \Sigma_\Omega .$$

The triple (H_A, V, Q) represents an **indirect measurement scheme** where the input system H_{in} evolves through the isometry V , producing the output H_{out} and the ancilla H_A , which then undergoes a POVM measurement Q with the same outcome space as the instrument.

Theorem 1. *Let $\mathcal{I} : \Sigma_\Omega \rightarrow \text{CP}(H_{\text{in}}, H_{\text{out}})$ be an instrument with outcome space Ω , and $Z : \Sigma_\Omega \rightarrow \text{Lin}(H_{\text{out}} \otimes H_{\text{in}})$ be the associated CJM. A minimal dilation of the instrument is given by the triple (H_A, V, Q) where the ancillary Hilbert space H_A is isomorphic to $H_{\mathcal{I}} := \text{Supp}(Z_\Omega)$, $V : H_{\text{in}} \rightarrow H_{\text{out}} \otimes H_A$ is the isometry*

$$(35) \quad V := (\mathbb{1}_{\text{out}} \otimes Z_\Omega^{*\frac{1}{2}})(|\mathbb{1}_{\text{out}}\rangle \otimes \mathbb{1}_{\text{in}}) ,$$

and Q is the POVM on H_A given by

$$(36) \quad Q_B := (Z_\Omega^{-\frac{1}{2}} Z_B Z_\Omega^{-\frac{1}{2}})^* \quad \forall B \in \Sigma_\Omega .$$

Proof. According to Eq. (20), V is the minimal Stinespring isometry of the channel \mathcal{Z}_Ω . On the other hand, Q is clearly a POVM on H_A , since $Q_B \geq 0 \forall B \in \Sigma_\Omega$ and $Q_\Omega = \mathbb{1}_{H_A}$. Moreover, exploiting the inclusion $H_{\text{out}} \otimes H_A \subseteq H_{\text{out}}^{\otimes 2} \otimes H_{\text{in}}$ we have

$$(37) \quad \begin{aligned} \text{Tr}_{H_A}[V\rho V^\dagger(\mathbb{1}_{\text{out}} \otimes Q_B)] &= \text{Tr}_{\text{out}_2} \text{Tr}_{\text{in}}[(|\mathbb{1}_{\text{out}}\rangle\langle\mathbb{1}_{\text{out}}| \otimes \rho)(\mathbb{1}_{\text{out}} \otimes Z_B^*)] \\ &= \text{Tr}_{\text{out}_2} [(\mathbb{1}_{\text{out}} \otimes \mathcal{Z}_B(\rho)^* | \mathbb{1}_{\text{out}}\rangle\langle\mathbb{1}_{\text{out}}|] = \mathcal{Z}_B(\rho) , \end{aligned}$$

thus proving that (H_A, V, Q) is actually a dilation of the instrument \mathcal{I} . Finally, the dilation has minimal ancilla dimension. Indeed, for any dilation $(H_{A'}, V', Q')$ of the instrument \mathcal{I} , we have a dilation of the channel \mathcal{Z}_Ω , given by $\mathcal{Z}_\Omega(\rho) = \text{Tr}_{H_{A'}}[V'\rho V'^\dagger]$. Since V is the minimal Stinespring isometry of the channel \mathcal{Z}_Ω , one necessarily has $\dim(H_{A'}) \geq \dim(\text{Supp}(Z_\Omega)) \equiv \dim(H_{\mathcal{I}})$. ■

Any other dilation of the instrument \mathcal{I} arises from some non-minimal isometry $V' : H_{\text{in}} \rightarrow H_{\text{out}} \otimes H_A$, which is necessarily of the form $V' = (\mathbb{1}_{\text{out}} \otimes Y)V$, where $Y : H_{\mathcal{I}} \rightarrow H_A$ is an isometry of ancilla spaces. Substituting the form of V' in Eq. (34) we then obtain

$$(38) \quad Q_B = Y^\dagger Q'_B Y \quad \forall B \in \Sigma_\Omega .$$

Since Y can be viewed as an isometric embedding of $H_{\mathcal{I}}$ into H_A , the above equation means that Q is the projection of Q' on the support of Y . This is indeed the case of the non-minimal dilation provided by Ozawa's dilation theorem [2], where Q' is a projection valued measure (PVM) on the infinite dimensional ancilla space H_A . According to Eq. (38), Q' is then a Naimark dilation [8] of the minimal POVM Q provided in our theorem.

4. INSTRUMENTS GENERATED BY OPERATOR FRAMES

We now introduce the definition of **frame-orbit instruments**, which will play an important role in the construction of feed-forward realization schemes and generalized teleportation schemes.

Fix a finite measure $\mu(d\omega)$ on the outcome space Ω , a measurable family of quantum operations $\mathcal{A}_\Omega := \{\mathcal{A}_\omega\}_{\omega \in \Omega}$, and a measurable family of quantum channels $\mathcal{B}_\Omega := \{\mathcal{B}_\omega\}_{\omega \in \Omega}$. Then we have the following:

Definition 2 (Frame-orbit instruments). *An instrument $\mathcal{L} : \Sigma_\Omega \rightarrow \mathbf{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ is a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ if \mathcal{L} admits a density w.r.t. μ and the density has the form*

$$(39) \quad \mathcal{S}_\omega = \mathcal{B}_\omega \mathcal{S}_0 \mathcal{A}_\omega^\dagger \quad \mu - \forall \omega \in \Omega ,$$

where \mathcal{S}_0 is a fixed CP map. In the case $\mathcal{B}_\omega \equiv \mathcal{I}_{\text{out}} \forall \omega \in \Omega$ we say that \mathcal{L} is a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega)$.

According to proposition 2, any instrument \mathcal{L} can be trivially viewed as a frame-orbit instrument by taking $\mu(B) := \text{Tr}[Z_B]$, $\mathcal{A}_\omega \equiv \mathcal{S}_\omega$, $\mathcal{S}_0 \equiv \mathcal{I}$ and $\mathcal{B}_\omega \equiv \mathcal{I}$. However, a given instrument can be a frame-orbit instrument w.r.t. several different triples $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$, and, on the contrary, once a triple $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ has been fixed, not all instruments are frame-orbit instruments w.r.t. that triple.

From now on we will restrict our attention to the case where the elements of \mathcal{A}_Ω are **single-Kraus operations** $\mathcal{A}_\omega(\cdot) := A_\omega \cdot A_\omega^\dagger$. The generalization of all results to the case $\mathcal{A}_\omega(\cdot) = \sum_{k=1}^{d_{\text{in}}^2} A_{\omega,k} \cdot A_{\omega,k}^\dagger$ is straightforward, as it only consists in replacing the index ω by the couple (ω, k) , $\int_\Omega \mu(d\omega)$ by $\int_\Omega \mu(d\omega) \sum_{k=1}^{d_{\text{in}}^2}$ and taking $\mathcal{B}_{(\omega,k)} := \mathcal{B}_\omega$ and $\mathcal{S}_\omega := \sum_{k=1}^{d_{\text{in}}^2} \mathcal{S}_{(\omega,k)}$.

Lemma 1. *Let $\mathcal{L} : \Sigma_\Omega \rightarrow \mathbf{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ be a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ with density $\mathcal{S}_\omega = \mathcal{B}_\omega \mathcal{S}_0 \mathcal{A}_\omega^\dagger$, $\mathcal{S}_0(\cdot) = \sum_{i=1}^r S_i \cdot S_i^\dagger$ be a Kraus form for \mathcal{S}_0 , and $\xi := \sum_{i=0}^r S_i^\dagger S_i \in \text{Lin}(\mathbf{H}_{\text{in}})$. Then,*

$$(40) \quad \int_\Omega \mu(d\omega) A_\omega \xi A_\omega^\dagger = \text{Tr}_{\text{in}_2}[(\mathbb{1}_{\text{in}} \otimes \xi^T) A] = \mathbb{1}_{\text{in}} ,$$

where $A \in \text{Lin}(\mathbf{H}_{\text{in}}^{\otimes 2})$ is the frame operator

$$(41) \quad A = \int_\Omega \mu(d\omega) |A_\omega\rangle \langle A_\omega| ,$$

and Tr_{in_2} denotes partial trace over the second copy of \mathbf{H}_{in} in the tensor $\mathbf{H}_{\text{in}}^{\otimes 2}$. Viceversa, for any positive operator $\xi \in \text{Lin}(\mathbf{H}_{\text{in}})$ satisfying Eq. (40) there exists a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$.

Proof. For the normalization of the instrument \mathcal{L} , \mathcal{L}_Ω must be trace-preserving, and we have $\text{Tr}[\mathcal{L}_\Omega(\rho)] = \int_\Omega \mu(d\omega) \text{Tr}[A_\omega \xi A_\omega^\dagger \rho] = \text{Tr}[\rho] \forall \rho \in \mathcal{S}(\mathbf{H}_{\text{in}})$, whence Eq. (40). Viceversa, for any $\xi \geq 0$ satisfying Eq. (40) we can define $\mathcal{S}_0(\cdot) := \xi^{\frac{1}{2}} \cdot \xi^{\frac{1}{2}}$, so that $\mathcal{S}_\omega := \mathcal{B}_\omega \mathcal{S}_0 \mathcal{A}_\omega^\dagger$ is the density of a normalized frame-orbit instrument. ■

In particular, whenever the elements of \mathcal{A}_Ω are all proportional to unitary channels, the class of frame-orbit instruments w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ is nonempty, as one can choose e.g. $\xi = \kappa \mathbb{1}_{\text{in}}$ with suitable normalization constant $\kappa > 0$. As we will see in the following Section, this includes the case of group-covariant instruments. Similarly, if $\mathbf{A}_\Omega := \{A_\omega\}$ is a tight operator frame, namely $A = \mathbb{1}_{\text{in}}^{\otimes 2}$, by definition Eq. (40) holds for any $\xi \in \text{Lin}(\mathbf{H}_{\text{in}})$. Notice that, however, the operators in \mathbf{A}_Ω do not need to be unitary in general, nor \mathbf{A}_Ω needs to be a tight frame, since it is enough that Eq. (40) holds for a single operator $0 \leq \xi \in \text{Lin}(\mathbf{H}_{\text{in}})$.

4.1. Canonically associated POVMs and their densities. According to the previous section, there are two POVMs P and Q that are canonically associated to the instrument \mathcal{Z} . The POVM P gives the probability distribution of the instrument for each event and each state, whereas the POVM Q allows to express the minimal dilation of the instrument via the minimal isometry $V = (\mathbb{1}_{\text{out}} \otimes Z_\Omega^{*\frac{1}{2}})(|\mathbb{1}_{\text{out}}\rangle \otimes \mathbb{1}_{\text{in}})$. Both P and Q can be written in terms of the CJM $Z_B = \mathcal{Z}_B \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\langle\mathbb{1}_{\text{in}}|)$ of the instrument (see Eq. (28)) as

$$(42) \quad P_B = \text{Tr}_{\text{out}}(Z_B)^*, \quad Q_B = (Z_\Omega^{-\frac{1}{2}} Z_B Z_\Omega^{-\frac{1}{2}})^*.$$

Obviously, since the instrument \mathcal{Z} admits a density w.r.t. μ , also the CJM Z will admit a density w.r.t. μ , given by

$$(43) \quad S_\omega := \mathcal{S}_\omega \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\langle\mathbb{1}_{\text{in}}|),$$

which is positive and uniquely defined μ -almost everywhere. From Eq. (39) it is also clear that the density S_ω has the form

$$(44) \quad S_\omega = (\mathcal{B}_\omega \otimes \mathcal{A}_\omega^*)(S_0),$$

having defined $S_0 := \mathcal{S}_0 \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\langle\mathbb{1}_{\text{in}}|) = \sum_{i=1}^r |S_i\rangle\langle S_i|$ and $\mathcal{A}_\omega^*(\cdot) := A_\omega^* \cdot A_\omega^\tau$. Finally, from Eq. (42) it follows that the POVMs P and Q admit densities w.r.t. μ , ξ_ω and ζ_ω , respectively, given by

$$(45) \quad \begin{aligned} \xi_\omega &= A_\omega \xi A_\omega^\dagger & \xi &:= \text{Tr}_{\text{out}}[S_0^*] = \sum_{i=1}^r S_i^\dagger S_i \\ \zeta_\omega &= \left(Z_\Omega^{-\frac{1}{2}} S_\omega Z_\Omega^{-\frac{1}{2}} \right)^* . \end{aligned}$$

4.2. Feed-forward realization of frame-orbit instruments. The realization of frame-orbit instruments w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ can be always reduced to the realization of frame-orbit instruments w.r.t. $(\mu, \mathcal{A}_\Omega)$, combined with a feed-forward classical communication to implement the conditional channel \mathcal{B}_ω . Indeed, according to Eq. (39), every frame-orbit instrument \mathcal{Z} w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ is equivalent to the frame-orbit instrument \mathcal{T} w.r.t. $(\mu, \mathcal{A}_\Omega)$ given by

$$(46) \quad \mathcal{T}_B = \int_B \mu(d\omega) \mathcal{S}_0 \mathcal{A}_\omega^\dagger$$

followed by the channel \mathcal{B}_ω depending on the outcome ω . Notice that \mathcal{T} is a normalized instrument, since \mathcal{T} and \mathcal{Z} have the same normalization in Eq. (40).

According to Eq. (44) the CJ operator $T_\Omega = \mathcal{T}_\Omega \otimes \mathcal{I}(|\mathbb{1}_{\text{in}}\rangle\langle\mathbb{1}_{\text{in}}|)$ is then given by

$$(47) \quad \begin{aligned} T_\Omega &= \int_\Omega \mu(d\omega) (\mathbb{1}_{\text{out}} \otimes A_\omega^*) S_0 (\mathbb{1}_{\text{out}} \otimes A_\omega^\tau) \\ &= (\mathcal{S}_0 \otimes \mathcal{I})(EA^*E) \end{aligned}$$

with $\mathcal{S}_0 \in \text{CP}(\mathbf{H}_{\text{in}_1}, \mathbf{H}_{\text{out}})$, and $A \in \text{Lin}(\mathbf{H}_{\text{in}}^{\otimes 2})$ being the frame operator in Eq. (41), and E denoting the unitary swap between the two copies of \mathbf{H}_{in} in the tensor $\mathbf{H}_{\text{in}}^{\otimes 2}$. Combining the feed-forward scheme with the minimal dilation of the instrument \mathcal{T} we obtain the following

Corollary 1. *Let $\mathcal{L} \in \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ be a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ with density $\mathcal{S}_\omega = \mathcal{B}_\omega \mathcal{S}_0 \mathcal{A}_\omega^\dagger$, and let $T_\Omega \in \text{Lin}(\mathbf{H}_{\text{out}} \otimes \mathbf{H}_{\text{in}})$ be the CJ operator defined in Eq. (47). Then, the instrument \mathcal{L} has the minimal feed-forward realization*

$$(48) \quad \mathcal{S}_\omega(\rho) = \mathcal{B}_\omega \left(\text{Tr}_{\mathbf{H}_A} \left[V \rho V^\dagger (\mathbb{1}_{\text{out}} \otimes \zeta_\omega) \right] \right) ,$$

where V is the isometry $V := (\mathbb{1}_{\text{out}} \otimes T_\Omega^{*\frac{1}{2}}) | \mathbb{1}_{\text{out}} \rangle \rangle \otimes \mathbb{1}_{\text{in}}$, and ζ_ω is the POVM density $\zeta_\omega := \left(T_\Omega^{-\frac{1}{2}} (\mathbb{1}_{\text{out}} \otimes A_\omega^*) S_0 (\mathbb{1}_{\text{out}} \otimes A_\omega^\tau) T_\Omega^{-\frac{1}{2}} \right)^*$.

5. GROUP-COINVARIANT INSTRUMENTS WITH TRANSITIVE OUTCOME SPACE

A particular case of frame-orbit instruments is that of covariant instruments whose outcome space Ω is a transitive \mathbf{G} -space. Given a group \mathbf{G} , we will denote by $\mathbf{U}_\mathbf{G} := \{U_g \in \text{Lin}(\mathbf{H}_{\text{in}})\}_{g \in \mathbf{G}}$ by $\mathbf{V}_\mathbf{G} := \{V_g \in \text{Lin}(\mathbf{H}_{\text{out}})\}_{g \in \mathbf{G}}$ two unitary representations of \mathbf{G} , and by $\mathcal{U}_\mathbf{G} := \{U_g \in \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{in}})\}_{g \in \mathbf{G}}$, $\mathcal{V}_\mathbf{G} := \{V_g \in \text{CP}(\mathbf{H}_{\text{out}}, \mathbf{H}_{\text{out}})\}_{g \in \mathbf{G}}$ the corresponding sets of automorphisms $\mathcal{U}_g(\cdot) := U_g \cdot U_g^\dagger$, $\mathcal{V}_g(\cdot) := V_g \cdot V_g^\dagger$.

Definition 3 (Group-covariant instruments). *Given a topological group \mathbf{G} acting on Ω , and two continuous unitary (generally projective) representations $\mathbf{U}_\mathbf{G}$ and $\mathbf{V}_\mathbf{G}$ on the Hilbert spaces \mathbf{H}_{in} and \mathbf{H}_{out} , respectively, we say that the instrument $\mathcal{L} : \Sigma_\Omega \rightarrow \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ is group-covariant w.r.t. $(\mathbf{G}, \mathcal{U}_\mathbf{G}, \mathcal{V}_\mathbf{G})$ when one has*

$$(49) \quad \mathcal{L}_B \circ \mathcal{U}_g(\rho) = \mathcal{V}_g \circ \mathcal{L}_{g^{-1}(B)}(\rho) \quad \forall \rho \in \mathbf{S}(\mathbf{H}_{\text{in}}), \forall B \in \Sigma_\Omega, \forall g \in \mathbf{G} ,$$

with $g^{-1}(B) := \{\omega \in \Omega \mid g\omega \in B\}$.

In the case of transitive group action on the outcome space Ω , for any point $\omega_0 \in \Omega$ one has $\Omega = \mathbf{G}\omega_0$, and the outcome space Ω can be identified with the space of left-cosets $\Omega \equiv \mathbf{G}/\mathbf{G}_0$ with respect to the stability group $\mathbf{G}_0 := \{h \in \mathbf{G} \mid h\omega_0 = \omega_0\}$. Denote by π the projection map $\pi : \mathbf{G} \rightarrow \Omega, g \mapsto \pi(g) = g\omega_0$ and by μ the invariant measure on Ω given by $\mu(B) = \int_{\pi^{-1}(B)} dg$, where dg is the normalized Haar measure over \mathbf{G} . Under this hypothesis and notation the following structure theorem holds [18, 19]:

Theorem 2. *Let \mathbf{G} be a compact group, \mathbf{G}_0 be a closed subgroup, and $\mathcal{L} : \Sigma_\Omega \rightarrow \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ be a covariant instrument w.r.t. $(\mathbf{G}, \mathcal{U}_\mathbf{G}, \mathcal{V}_\mathbf{G})$ with outcome space $\Omega = \mathbf{G}/\mathbf{G}_0$. Then \mathcal{L} admits a density w.r.t. μ of the form*

$$(50) \quad \mathcal{S}_{\pi(g)} = \mathcal{V}_g \mathcal{S}_0 \mathcal{U}_g^\dagger \quad \forall g \in \mathbf{G} ,$$

where \mathcal{S}_0 is a CP map, $\mathcal{V}_g(\cdot) := V_g \cdot V_g^\dagger$, and $\mathcal{U}_g^\dagger(\cdot) := U_g^\dagger \cdot U_g$.

Since the group-action is transitive, Eq. (50) defines the density \mathcal{S}_ω for any $\omega \in \Omega$. Indeed one can take any measurable section $\sigma : \Omega \rightarrow \mathbf{G}, \omega \mapsto \sigma(\omega), \pi(\sigma(\omega)) = \omega$ and declare

$$(51) \quad \mathcal{S}_\omega = \mathcal{V}_{\sigma(\omega)} \mathcal{S}_0 \mathcal{U}_{\sigma(\omega)}^\dagger .$$

The above equation clearly characterizes any covariant instrument with $\Omega = \mathbf{G}/\mathbf{G}_0$ as a frame-orbit instrument w.r.t. $(\mu, \mathcal{U}_{\sigma(\Omega)}, \mathcal{V}_{\sigma(\Omega)})$. In addition, Eq. (50) implies the invariance condition

$$(52) \quad \mathcal{S}_0 = \mathcal{V}_h \mathcal{S}_0 \mathcal{U}_h^\dagger \quad \forall h \in \mathbf{G}_0 ,$$

which in terms of CJ operators becomes the commutation relation

$$(53) \quad [S_0, V_h \otimes U_h^*] = 0 \quad h \in \mathbf{G}_0 .$$

5.1. Covariant POVMs and dilation of covariant instruments.

5.1.1. *Minimal dilation.* Let \mathcal{I} be an instrument with outcome space $\Omega = \mathbf{G}/\mathbf{G}_0$ covariant w.r.t. $(\mathbf{G}, \mathcal{U}_{\mathbf{G}}, \mathcal{V}_{\mathbf{G}})$. From Eqs. (44) and (51), the CJM density is

$$(54) \quad S_\omega = (\mathcal{V}_{\sigma(\omega)} \otimes \mathcal{U}_{\sigma(\omega)}^*)(S_0) .$$

Exploiting the Mackey-Bruhat identity, which sets up an isomorphism between \mathbf{G} equipped with the Haar measure dg and $\Omega \times \mathbf{G}_0$ equipped with the product measure $\mu(d\omega) \times \nu(dh)$, $\nu(dh)$ normalized Haar measure over \mathbf{G}_0 (see e.g. [20]), we obtain

$$(55) \quad \begin{aligned} Z_\Omega &= \int_\Omega \mu(d\omega) S_\omega = \int_{\Omega \times \mathbf{G}_0} \mu(d\omega) \nu(dh) (\mathcal{V}_{\sigma(\omega)} \otimes \mathcal{U}_{\sigma(\omega)}^*)(S_0) = \\ &= \int_{\mathbf{G}} dg (\mathcal{V}_g \otimes \mathcal{U}_g^*)(S_0) . \end{aligned}$$

As a consequence, we have $[Z_\Omega, V_g \otimes U_g^*] = 0 \forall g \in \mathbf{G}$ and the density ζ_ω in Eq. (45) is given by

$$(56) \quad \zeta_\omega = \left(V_{\sigma(\omega)}^* \otimes U_{\sigma(\omega)} \right) \Xi \left(V_{\sigma(\omega)}^* \otimes U_{\sigma(\omega)} \right)^\dagger \quad \Xi := \left(Z_\Omega^{-\frac{1}{2}} S_0 Z_\Omega^{-\frac{1}{2}} \right)^* ,$$

with Ξ satisfying the commutation relation

$$(57) \quad [\Xi, V_h^* \otimes U_h] = 0 \quad \forall h \in \mathbf{G}_0 .$$

This shows that POVM $Q_B = \int_B \mu(d\omega) \zeta_\omega$ used in the minimal dilation of Theorem 1 is a **covariant POVM** with outcome space Ω [19], i.e.

$$(58) \quad Q_{g(B)} = (\mathcal{V}_g^* \otimes \mathcal{U}_g)(Q_B) \quad \forall B \in \Sigma_\Omega .$$

Furthermore, using the relation $[Z_\Omega^*, V_g^* \otimes U_g] = 0 \forall g \in \mathbf{G}$, it is immediate to see that the minimal isometry $V = (\mathbb{1}_{\text{out}} \otimes Z_\Omega^{\frac{1}{2}}) |\mathbb{1}_{\text{out}}\rangle \otimes \mathbb{1}_{\text{in}}$ intertwines the two representations $\mathbf{V}_{\mathbf{G}} \otimes \mathbf{V}_{\mathbf{G}}^* \otimes \mathbf{U}_{\mathbf{G}}$ and $\mathbf{U}_{\mathbf{G}}$, namely

$$(59) \quad (V_g \otimes V_g^* \otimes U_g) V = V U_g \quad \forall g \in \mathbf{G} .$$

5.1.2. *Minimal feed-forward realization and generalized teleportation schemes.* A minimal feed-forward realization can be obtained by using Corollary 1, in terms of the instrument $\mathcal{T}_B := \int_B \mu(d\omega) \mathcal{S}_0 \mathcal{U}_{\sigma(\omega)}^\dagger$. In this case we have

$$(60) \quad T_\Omega = \int_{\mathbf{G}} dg (\mathcal{I}_{\text{out}} \otimes \mathcal{U}_g^*)(S_0)$$

whence $[T_\Omega, \mathbb{1}_{\text{out}} \otimes U_g^*] = 0 \forall g \in \mathbf{G}$. As a consequence, the POVM density ζ_ω is now given by

$$(61) \quad \zeta_\omega = (I \otimes U_{\sigma(\omega)}) \Xi (I \otimes U_{\sigma(\omega)})^\dagger \quad \Xi := \left(T_\Omega^{-\frac{1}{2}} S_0 T_\Omega^{-\frac{1}{2}} \right)^* .$$

Notice that in this case ζ_ω is not a covariant POVM density, since the relation $[\Xi, \mathbb{1}_{\text{out}} \otimes U_h] = 0 \forall h \in \mathbf{G}_0$ does not necessarily hold. The minimal isometry V is now given by $V = (\mathbb{1}_{\text{out}} \otimes T_\Omega^{\frac{1}{2}}) |\mathbb{1}_{\text{out}}\rangle \otimes \mathbb{1}_{\text{in}}$ and enjoys the property

$$(62) \quad (\mathbb{1}_{\text{out}}^{\otimes 2} \otimes U_g) V = V U_g \quad \forall g \in \mathbf{G} .$$

For irreducible $U_{\mathbf{G}}$ the above equation gives $V = |\Psi\rangle\rangle \otimes \mathbb{1}_{\text{in}}$ for some $|\Psi\rangle\rangle \in H_{\text{out}}^{\otimes 2}$, $\|\Psi\|_2 = 1$, namely the isometry V is just the extension with some pure state. Precisely, computing the average in Eq. (60) we have $T_{\Omega} = d_{\text{in}}^{-1} \text{Tr}_{\text{in}}[S_0] \otimes \mathbb{1}_{\text{in}}$, whence

$$(63) \quad V = |\sigma^{\frac{1}{2}}\rangle\rangle \otimes \mathbb{1}_{\text{in}} \quad \sigma := d_{\text{in}}^{-1} \text{Tr}_{\text{in}}[S_0] = d_{\text{in}}^{-1} \sum_{i=1}^r S_i S_i^{\dagger}.$$

The feed-forward realization then becomes a **generalized teleportation scheme** where $|\sigma^{\frac{1}{2}}\rangle\rangle$ plays the role of entangled resource, the joint measurement ζ_{ω} is performed by the sender on the input system and on half of the entangled state, the outcome ω is classically transmitted, and the conditional operation $\mathcal{V}_{\sigma(\omega)}$ is performed at the receiver's end. The discussion on generalized teleportation schemes will be extended in Section 6 to the case of frame-orbit instruments generated by tight operator frames.

5.1.3. *Non minimal feed-forward dilations.* Using group theory it is easy to construct non-minimal dilations of group-covariant instruments. Let us decompose H_{in} and $U_{\mathbf{G}}$ as

$$(64) \quad H_{\text{in}} = \bigoplus_{\mu \in \mathbf{S}} H_{\mu} \otimes \mathbb{C}^{m_{\mu}}, \quad U_g = \bigoplus_{\mu \in \mathbf{S}} U_g^{\mu} \otimes \mathbb{1}_{m_{\mu}}$$

the sum running over the set \mathbf{S} of inequivalent irreducible representations (**irreps**) of \mathbf{G} contained in the decomposition of $U_{\mathbf{G}}$, $H_{\mu}(\mathbb{C}^{m_{\mu}})$ being the representation (multiplicity) space of the irrep μ , of dimension $\dim(H_{\mu}) = d_{\mu}$ ($\dim \mathbb{C}^{m_{\mu}} = m_{\mu}$). The **group average** of an operator $O \in \text{Lin}(H_{\text{in}})$ is then given by

$$(65) \quad \langle O \rangle_{U_{\mathbf{G}}} := \int_{\mathbf{G}} dg U_g O U_g^{\dagger} = \bigoplus_{\mu \in \mathbf{S}} d_{\mu}^{-1} (\mathbb{1}_{d_{\mu}} \otimes \text{Tr}_{H_{\mu}}[\Pi_{\mu} O \Pi_{\mu}]),$$

Π_{μ} denoting the projector onto $H_{\mu} \otimes \mathbb{C}^{m_{\mu}}$. For the dilation we introduce now two ancillary spaces $H_0 \simeq \mathbb{C}^r$ where $r = \text{rank}(S_0)$, and \tilde{H} , which is given by

$$(66) \quad \tilde{H} := \bigoplus_{\mu \in \mathbf{S}} H_{\mu} \otimes \mathbb{C}^{d_{\mu}},$$

and carries the representation $\tilde{U}_{\mathbf{G}} := \{\tilde{U}_g = \bigoplus_{\mu \in \mathbf{S}} U_g^{\mu} \otimes \mathbb{1}_{d_{\mu}}\}$.

Proposition 3. *Let \mathcal{Z} be an instrument with outcome space $\Omega = \mathbf{G}/\mathbf{G}_0$, covariant w.r.t. $\{\mathbf{G}, U_{\mathbf{G}}, \mathcal{V}_{\mathbf{G}}\}$, and with density \mathcal{S}_{ω} . A dilation of \mathcal{Z} can be achieved as follows*

$$(67) \quad \mathcal{S}_{\pi(g)}(\rho) = V_g \left(\text{Tr}_{H_0} \text{Tr}_{\tilde{H}} [(\mathbb{1}_{H_0} \otimes \mathbb{1}_{\text{out}} \otimes \zeta'_g) V' \rho V'^{\dagger}] \right) V_g^{\dagger},$$

where $\pi : g \mapsto \pi(g) \in \mathbf{G}/\mathbf{G}_0$ projects group elements to the corresponding left coset, ζ'_g is the POVM density on \tilde{H} given by

$$(68) \quad \zeta'_g = |\eta_g\rangle\langle\eta_g| \quad |\eta_g\rangle = \bigoplus_{\mu \in \mathbf{S}} \sqrt{d_{\mu}} |U_g^{\mu}\rangle\rangle \in \tilde{H},$$

and $V' : H_{\text{in}} \rightarrow H_0 \otimes H_{\text{out}} \otimes \tilde{H}$ is the isometry

$$(69) \quad V' = \sum_{i=1}^r |i\rangle \otimes \int_{\mathbf{G}} dg S_i U_g^{\dagger} \otimes |\eta_g\rangle,$$

$\{|i\rangle\}_{i=1}^r$ being an orthonormal basis for \mathbf{H}_0 .

Proof. As an immediate consequence of Eq. (65), the vectors $|\eta_g\rangle = \tilde{U}_g|\eta\rangle$ provide a resolution of the identity in $\tilde{\mathbf{H}}$, namely

$$(70) \quad \int_{\mathbf{G}} dg |\eta_g\rangle\langle\eta_g| = \mathbb{1}_{\tilde{\mathbf{H}}},$$

whence ζ'_g is the density of a normalized POVM. Moreover, it is easy to verify that V' is an isometry. First, we have $\langle\eta_g|\eta_h\rangle = \sum_{\mu \in \mathcal{S}} d_\mu \chi_\mu(g^{-1}h)$, where $\chi_\mu(g) \doteq \text{Tr}[U_g^\mu]$ is the character of the irrep μ . Then, as a consequence of the orthogonality of irreducible matrix elements, we have the relation

$$(71) \quad \int_{\mathbf{G}} dg \left(\sum_{\mu} d_\mu \chi_\mu^*(g) \right) U_g = \mathbb{1}_{\text{in}},$$

whence

$$(72) \quad \begin{aligned} V'^{\dagger}V' &= \sum_i \int_{\mathbf{G}} dg \int_{\mathbf{G}} dh U_g S_i^{\dagger} S_i U_h^{\dagger} \langle\eta_g|\eta_h\rangle \\ &= \int_{\mathbf{G}} dg \int_{\mathbf{G}} dh U_g \xi U_h^{\dagger} \left(\sum_{\mu} d_\mu \chi_\mu(g^{-1}h) \right) \\ &= \int_{\mathbf{G}} dg \int_{\mathbf{G}} dk U_g \xi U_k U_g^{\dagger} \left(\sum_{\mu} d_\mu \chi_\mu^*(k) \right) = \int_{\mathbf{G}} dg U_g \xi U_g^{\dagger} = \mathbb{1}_{\text{in}}, \end{aligned}$$

having used Eq. (40) with $\mathbf{A}_\Omega \equiv \mathbf{U}_{\mathbf{G}}$. Finally, identity (67) holds, namely

$$(73) \quad \begin{aligned} &V_g \left(\text{Tr}_{\mathbf{H}_0} \text{Tr}_{\tilde{\mathbf{H}}} [V' \rho V'^{\dagger} (\mathbb{1}_A \otimes \mathbb{1}_{\mathbf{H}} \otimes \zeta'_g)] \right) V_g^{\dagger} = \\ &= V_g \left(\sum_{i=1}^r \int_{\mathbf{G}} dh \int_{\mathbf{G}} dk S_i U_h^{\dagger} \rho U_k S_i^{\dagger} \langle\eta_g|\eta_h\rangle \langle\eta_k|\eta_g\rangle \right) V_g^{\dagger} \\ &= V_g \left(\sum_{i=1}^r \int_{\mathbf{G}} dh \int_{\mathbf{G}} dk S_i U_h U_g^{\dagger} \rho U_g U_k S_i^{\dagger} \left(\sum_{\mu \in \mathcal{S}} d_\mu \chi_\mu^*(h) \right) \left(\sum_{\nu \in \mathcal{S}} d_\nu \chi_\nu^*(k) \right) \right) V_g^{\dagger} \\ &= V_g \left(\sum_{i=1}^r S_i U_g^{\dagger} \rho U_g S_i^{\dagger} \right) V_g^{\dagger} = \mathcal{V}_g \cdot \mathcal{S}_0 \mathcal{W}_g^{\dagger}(\rho) = \mathcal{S}_{\pi(g)}(\rho), \end{aligned}$$

having used Eqs. (71) and (50). ■

The above proposition shows that in order to realize the instrument \mathcal{I} it is enough to perform the indirect measurement ζ_g —whose outcome space is the whole group \mathbf{G} —and subsequently to use the classical data-processing $g \mapsto \pi(g)$, that projects the g onto the final outcome space $\Omega = \mathbf{G}/\mathbf{G}_0$. In this way, both the statistics and the state reduction associated to the operational scheme of measurement and feed-forward are exactly the same as for the instrument \mathcal{I} .

5.1.4. Naimark dilation. Consider the Hilbert space $\bigoplus_{\mu \in \hat{\mathbf{G}}} \mathbf{H}_\mu \otimes \mathbb{C}^{d_\mu}$ where $\hat{\mathbf{G}}$ denotes the set of all possible unitary irreps of \mathbf{G} . According to Fourier-Plancherel

theory [20], any vector $|f\rangle \in \bigoplus_{\mu \in \tilde{\mathbf{G}}} \mathbf{H}_\mu \otimes \mathbb{C}^{d_\mu}$ is associated with a square-summable function $f(g)$ as follows

$$(74) \quad |f\rangle \mapsto f(g) = \sum_{\mu \in \tilde{\mathbf{G}}} \sqrt{d_\mu} \langle U_g | \Pi_\mu | f \rangle .$$

In this way, one has $\langle f|h\rangle = \int_{\mathbf{G}} d g f^*(g) h(g)$, and correspondence $|f\rangle \mapsto f(g)$ sets up a unitary equivalence between the Hilbert spaces $\bigoplus_{\mu \in \tilde{\mathbf{G}}} \mathbf{H}_\mu \otimes \mathbb{C}^{d_\mu}$ and $L^2(\mathbf{G}, d g)$.

Therefore, we can identify the ancilla space $\tilde{\mathbf{H}}$ in proposition 3 with a subspace of $L^2(\mathbf{G}, d g)$, the projector on $\tilde{\mathbf{H}}$ being $Y = \bigoplus_{\mu \in \mathcal{S}} \Pi_\mu$. Hence the POVM Q' defined by the density ζ'_g in Eq. (68) has the following Naimark dilation

$$(75) \quad \begin{aligned} \langle f|Q'_B|h\rangle &= \int_B d g \sum_{\mu, \nu \in \mathcal{S}} \sqrt{d_\mu d_\nu} \langle f|\Pi_\mu|U_g^\mu\rangle \langle U_g^\nu|\Pi_\nu|h\rangle \\ &= \int_B d g (Y f)^*(g) (Y h)(g) \\ &= \langle f|Y^\dagger E_B Y|h\rangle \quad \forall |f\rangle, |h\rangle \in L^2(\mathbf{G}, d g) , \end{aligned}$$

where E is the PVM on $L^2(\mathbf{G}, d g)$ defined by

$$(76) \quad \langle f|E_B|h\rangle := \int_B d g f^*(g) h(g) \quad \forall |f\rangle, |h\rangle \in L^2(\mathbf{G}, d g) .$$

The relation $Q_B = Y^\dagger E_B Y$ shows that the POVM Q' is simply the projection of the PVM E on the subspace $\tilde{\mathbf{H}} \subset L^2(\mathbf{G}, d g)$. It is worth noting that the POVM Q' is also the optimal POVM for the estimation of an unknown unitary transformation \tilde{U}_g acting on the finite dimensional Hilbert space $\tilde{\mathbf{H}}$ [21].

6. TIGHT OPERATOR FRAMES: TELE-INSTRUMENTS AND TELE-CHANNELS

Let μ be a finite measure on Ω and A_Ω a measurable family of operators. A_Ω is a tight operator frame if the frame operator A is the identity on $\mathbf{H}^{\otimes 2}$, i.e.

$$(77) \quad A = \int_{\Omega} \mu(d\omega) |A_\omega\rangle \langle A_\omega| = \mathbb{1} \otimes \mathbb{1}$$

A special case of tight unitary frame is that of irreducible unitary representation of a compact group \mathbf{G} , namely $\Omega = \mathbf{G}$, $A_\Omega = \mathbf{U}_\mathbf{G}$ and $\mu(d\omega) = \dim \mathbf{H} \times d g$.

Generalizing the notion of tight frame to the case where the frame operator is the identity only on the first copy we have the following

Definition 4. Let μ be a measure on Ω and A_Ω be a measurable family of operators. We say that A_Ω is a **left-tight operator frame** if

$$(78) \quad \int_{\Omega} \mu(d\omega) |A_\omega\rangle \langle A_\omega| = \mathbb{1} \otimes K .$$

Note that identity (78) is equivalent to the following ones

$$(79) \quad \begin{aligned} \int_{\Omega} \mu(d\omega) A_\omega X A_\omega^\dagger &= \text{Tr}[X K^*] \mathbb{1}, \quad \forall X \in \text{Lin}(H) \\ \int_{\Omega} \mu(d\omega) A_\omega \otimes A_\omega^* &= |\mathbb{1}\rangle \langle K^*| . \end{aligned}$$

We will see in the following that operator-frame instruments generated by operations $\mathcal{A}_\omega(\cdot) = A_\omega \cdot A_\omega^\dagger$ corresponding to left-tight frames \mathbf{A}_Ω can be realized by **generalized teleportation schemes**, in which two parties (conventionally named Alice and Bob) exploit an entangled resource to achieve the instrument via local operations and one-way classical communication: a suitable joint POVM ζ_ω is measured by Alice on the input and on one side of the entangled state, the measurement outcome ω is announced to Bob, who performs a conditional feed-forward operation \mathcal{B}_ω on the other side. We will also use the term **tele-instruments** to denote instruments that admit such a realization. In addition, we will show that frame-orbit instruments generated by tight unitary frames are useful for the realization of covariant channels. In this case, which covers in particular the case of unitary irreducible group representations, a covariant channel can be realized by a generalized teleportation scheme, hence becoming a **tele-channel**. In particular, we will provide also the realization of covariant channels such as universal cloning [22] and universal NOT [23].

6.1. Minimal tele-instruments. Let $\mathcal{I} : \Sigma_\Omega \rightarrow \mathcal{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ be a frame-orbit instrument w.r.t. $(\mu, \mathcal{A}_\Omega, \mathcal{B}_\Omega)$ with \mathcal{A}_Ω left-tight operator frame, and let \mathcal{S}_ω be the instrument density of \mathcal{I} . We consider now the minimal feed-forward realization of Corollary 1. Using Eq. (79), the CJ operator of the instrument channel \mathcal{T}_Ω is given by

$$(80) \quad \begin{aligned} T_\Omega &= (\mathcal{T}_\Omega \otimes \mathcal{I})(|\mathbb{1}_{\text{in}}\rangle\langle\mathbb{1}_{\text{in}}|) = \int_\Omega \mu(d\omega) (\mathbb{1}_{\text{out}} \otimes A_\omega^*) S_0(\mathbb{1}_{\text{out}} \otimes A_\omega^\dagger) \\ &= \text{Tr}_{\text{in}}[S_0(\mathbb{1}_{\text{out}} \otimes K)] \otimes \mathbb{1}_{\text{in}} = \sigma \otimes \mathbb{1}_{\text{in}} , \end{aligned}$$

having defined the state

$$(81) \quad \sigma := \text{Tr}_{\text{in}}[S_0(\mathbb{1}_{\text{out}} \otimes K)] = \mathcal{S}_0(K^*) \quad \text{Tr}[\sigma] = 1 .$$

The minimal isometry $V = (\mathbb{1}_{\text{out}} \otimes T_\Omega^{\frac{1}{2}})|\mathbb{1}_{\text{out}}\rangle \otimes \mathbb{1}_{\text{in}}$ is then given by:

$$(82) \quad V = |\sigma^{\frac{1}{2}}\rangle \otimes \mathbb{1}_{\text{in}}$$

and Corollary 1 yields the following generalized teleportation scheme for the instrument \mathcal{I} :

$$(83) \quad \mathcal{S}_\omega(\rho) = \mathcal{B}_\omega \left(\text{Tr}_{2,3}[(|\sigma^{\frac{1}{2}}\rangle\langle\sigma^{\frac{1}{2}}| \otimes \rho)(\mathbb{1}_{\text{out}} \otimes \zeta_\omega)] \right)$$

where the POVM density ζ_ω is given by $\zeta_\omega = (\sigma^{-\frac{1}{2}} * \otimes A_\omega) S_0^*(\sigma^{-\frac{1}{2}} * \otimes A_\omega^\dagger)$.

In conclusion, in the minimal feed-forward realization the frame-orbit instrument \mathcal{I} can be implemented by two parties that share the pure entangled state $|\sigma^{\frac{1}{2}}\rangle$ by using only local operations and one-way classical communication: it is enough for Alice to perform the joint POVM $\zeta_\omega = (\sigma^{-\frac{1}{2}} * \otimes A_\omega) S_0^*(\sigma^{-\frac{1}{2}} * \otimes A_\omega^\dagger)$ on the input state and on one side of the entangled resource, and to announce the measurement outcome ω to Bob, who implements the conditional channel \mathcal{B}_ω .

6.2. Non-minimal tele-instruments. Starting from the minimal dilation it is simple to obtain other generalized teleportation realization schemes. In particular,

from Eq. (83) we obtain

$$\begin{aligned}
 (84) \quad \mathcal{S}_\omega &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left(|\sigma^{\frac{1}{2}}\rangle\langle\sigma^{\frac{1}{2}}| \otimes \rho \right) \left(\mathbb{1}_{\text{out}} \otimes (\sigma^{-\frac{1}{2}} * \otimes A_\omega) S_0^* (\sigma^{-\frac{1}{2}} * \otimes A_\omega^\dagger) \right) \right] \right) \\
 &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left(|\mathbb{1}_{\text{out}}\rangle\langle\mathbb{1}_{\text{out}}| \otimes \rho \right) \left(\mathbb{1}_{\text{out}} \otimes (\mathcal{S}_0^* \otimes \mathcal{S}) (|A^\tau_\omega\rangle\langle A^\tau_\omega|) \right) \right] \right) \\
 &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left((\mathcal{S} \otimes \mathcal{S}^\tau_0) (|\mathbb{1}_{\text{out}}\rangle\langle\mathbb{1}_{\text{out}}|) \otimes \rho \right) \left(\mathbb{1}_{\text{out}} \otimes |A^\tau_\omega\rangle\langle A^\tau_\omega| \right) \right] \right) \\
 &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left((\mathcal{S}_0 \otimes \mathcal{S}) (|\mathbb{1}_{\text{out}}\rangle\langle\mathbb{1}_{\text{out}}|) \otimes \rho \right) \left(\mathbb{1}_{\text{out}} \otimes |A^\tau_\omega\rangle\langle A^\tau_\omega| \right) \right] \right) \\
 &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left((\mathcal{S}_0 \otimes \mathcal{S}) (|K^{*\frac{1}{2}}\rangle\langle K^{*\frac{1}{2}}|) \otimes \rho \right) \left(\mathbb{1}_{\text{out}} \otimes |K^{-\frac{1}{2}} A^\tau_\omega\rangle\langle K^{-\frac{1}{2}} A^\tau_\omega| \right) \right] \right) \\
 &= \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[(\sigma' \otimes \rho) (\mathbb{1}_{\text{out}} \otimes \zeta'_\omega) \right] \right)
 \end{aligned}$$

having defined the state

$$(85) \quad \sigma' := (\mathcal{S}_0 \otimes \mathcal{S}) (|K^{*\frac{1}{2}}\rangle\langle K^{*\frac{1}{2}}|)$$

and the POVM density

$$(86) \quad \zeta'_\omega := |K^{-\frac{1}{2}} A^\tau_\omega\rangle\langle K^{-\frac{1}{2}} A^\tau_\omega|.$$

The normalization of σ' is given by $\text{Tr}[\sigma'] = \text{Tr}[\mathcal{S}_0(K^*)] = \text{Tr}[\sigma] = 1$ (having used Eq. (81)), while the normalization of the POVM ζ'_ω follows directly from Eq. (78).

Also the above feed-forward realization is a generalized teleportation scheme, which allows Alice and Bob to implement the instrument \mathcal{Z} as a tele-instrument. Notice that now the entangled resource $\sigma' = (\mathcal{S}_0 \otimes \mathcal{S}) (|K^{*\frac{1}{2}}\rangle\langle K^{*\frac{1}{2}}|)$ is a generally *mixed* state, whereas the joint POVM performed by Alice has now the *rank-one* density $\zeta'_\omega = |K^{-\frac{1}{2}} A^\tau_\omega\rangle\langle K^{-\frac{1}{2}} A^\tau_\omega|$.

6.3. Tight unitary frames and Bell measurements. A particularly interesting generalized teleportation scheme arises when the left-tight frame \mathbf{A}_Ω consists of unitary operators, namely $\mathbf{A}_\Omega \equiv \mathbf{U}_\Omega$. This is the case, for instance, when \mathbf{A}_ω is a unitary irreducible representation of some compact group \mathbf{G} .

It is immediate to see that a unitary left-tight frame \mathbf{A}_Ω is necessarily tight, since Eq. (78) implies $K = \mathbb{1}_{\text{in}}/d_{\text{in}}$. For unitary tight frames the non-minimal realization of Eq.(84) becomes

$$(87) \quad \mathcal{S}_\omega = \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[\left(\frac{S_0}{d_{\text{in}}} \otimes \rho \right) (\mathbb{1}_{\text{out}} \otimes \zeta'_\omega) \right] \right) \quad \zeta'_\omega = d_{\text{in}} |U_\omega^\tau\rangle\langle U_\omega^\tau|,$$

and the joint POVM used by Alice is a Bell measurement, i.e. ζ'_ω are proportional to rank-one projectors on maximally entangled states. On the other hand, the minimal realization of Eq. (83) gives

$$(88) \quad \mathcal{S}_\omega(\rho) = \mathcal{B}_\omega \left(\text{Tr}_{2,3} \left[(|\sigma^{\frac{1}{2}}\rangle\langle\sigma^{\frac{1}{2}}| \otimes \rho) (\mathbb{1}_{\text{out}} \otimes \zeta_\omega) \right] \right)$$

with $\sigma = \mathcal{S}_0(\mathbb{1}_{\text{in}})/d_{\text{in}}$, and POVM density $\zeta_\omega = (\sigma^{-\frac{1}{2}} * \otimes U_\omega) S_0^* (\sigma^{-\frac{1}{2}} * \otimes U_\omega^\dagger)$. Note that typically the POVM ζ_ω in the minimal realization is not a Bell POVM.

7. REALIZATION OF COVARIANT CHANNELS

The realization of a covariant instrument \mathcal{Z} also allows one to achieve the corresponding channel \mathcal{X}_Ω by simply averaging over the instrument outcomes. Therefore, the general realization schemes presented in Theorem 1 and Corollary 1 for

instruments can be directly transferred to the corresponding channels. In particular, for any tele-instrument \mathcal{I} in subsections 6.2 and 6.1 we have a corresponding tele-channel \mathcal{I}_Ω achieved by the same generalized teleportation scheme.

A particularly interesting case is that of **covariant channels**, which we intend here in a very broad sense, according to the following:

Definition 5. *Let \mathcal{A}_Ω be a family of quantum channels on \mathbf{H}_{in} and \mathcal{B}_Ω a family of quantum channels on \mathbf{H}_{out} . A channel $\mathcal{C} \in \text{CP}(\mathbf{H}_{\text{in}}, \mathbf{H}_{\text{out}})$ is covariant w.r.t. $(\mathcal{A}_\Omega, \mathcal{B}_\Omega)$ if*

$$(89) \quad \mathcal{C}\mathcal{A}_\omega = \mathcal{B}_\omega\mathcal{C} \quad \forall \omega \in \Omega .$$

In particular we consider the case where all channels in \mathcal{A}_Ω are unitary, namely $\mathcal{A}_\omega(\cdot) \equiv \mathcal{U}_\omega(\cdot) = U_\omega \cdot U_\omega^\dagger$, for some unitary operator $U_\omega \in \text{Lin}(\mathbf{H}_{\text{in}})$. Since for a covariant channel one has $\mathcal{C} = \mathcal{B}_\omega\mathcal{C}\mathcal{U}_\omega^\dagger \forall \omega \in \Omega$, any covariant channel is trivially the channel corresponding to a frame-orbit instrument, namely $\mathcal{C} \equiv \mathcal{I}_\Omega$ with $\mathcal{I}_B := \int_B \mu(d\omega)\mathcal{I}_\omega$, $\mathcal{I}_\omega := \mathcal{B}_\omega\mathcal{C}\mathcal{U}_\omega^\dagger$. In fact, the covariant channel \mathcal{C} coincides with the instrument density \mathcal{I}_ω for any outcome ω . In particular, when \mathbf{U}_Ω is a tight unitary frame, \mathcal{C} becomes a tele-channel, and the non-minimal dilation of Eq. (87) yields a generalized teleportation scheme with Bell measurement:

$$(90) \quad \mathcal{C}(\rho) \equiv \mathcal{I}_\omega(\rho) = \mathcal{B}_\omega \left(\text{Tr}_{2,3} [(C/d_{\text{in}} \otimes \rho) (\mathbb{1}_{\text{out}} \otimes d_{\text{in}} |U_\omega^\tau\rangle\langle\langle U_\omega^\tau|)] \right) ,$$

with $C = (\mathcal{C} \otimes \mathcal{I})(|\mathbb{1}_{\text{in}}\rangle\langle\langle \mathbb{1}_{\text{in}}|) \equiv (\mathcal{I}_0 \otimes \mathcal{I})(|\mathbb{1}_{\text{in}}\rangle\langle\langle \mathbb{1}_{\text{in}}|) = S_0$.

The minimal dilation of Eq. (83) gives instead

$$(91) \quad \mathcal{C}(\rho) \equiv \mathcal{I}_\omega(\rho) = \mathcal{B}_\omega \left(\text{Tr}_{2,3} [(|\sigma^{\frac{1}{2}}\rangle\langle\langle \sigma^{\frac{1}{2}}| \otimes \rho) (\mathbb{1}_{\text{out}} \otimes \zeta_\omega)] \right)$$

where $\sigma = \mathcal{C}(\mathbb{1}_{\text{in}})/d_{\text{in}}$ according to Eq. (81), and POVM density given by $\zeta_\omega = (\sigma^{-\frac{1}{2}} * \otimes U_\omega) C^* (\sigma^{-\frac{1}{2}} * \otimes U_\omega^\dagger)$.

Notice that the non-minimal realization uses the Choi-Jamiołkowski state $\sigma_{CJ} = C/d_{\text{in}}$ as entangled resource, while the minimal realization uses a purification of the local state $\sigma = \text{Tr}_{\text{in}}[\sigma_{CJ}]$. The two realizations coincide (up to local unitaries on \mathbf{H}_{in}) when the CJ-operator C is rank-one, corresponding to unitary channels.

We conclude with the following examples of application:

7.0.1. Ideal teleportation. Ideal teleportation from Alice's to Bob's site is described by the identity channel $\mathcal{C} = \mathcal{I}$, which is a covariant channel w.r.t. $(\mathcal{U}_\Omega, \mathcal{U}_\Omega)$ for any unitary frame \mathbf{U}_Ω , since trivially $\mathcal{C}\mathcal{U}_\omega = \mathcal{U}_\omega\mathcal{C} \forall \omega \in \Omega$. For tight unitary frames, Eqs. (91) and (90) coincide and give the realization

$$(92) \quad \mathcal{C}(\rho) = \mathcal{U}_\omega \left(\text{Tr}_{2,3} \left[\left(\frac{|\mathbb{1}\rangle\langle\langle \mathbb{1}|}{d} \otimes \rho \right) (\mathbb{1}_{\text{out}} \otimes d |U_\omega^\tau\rangle\langle\langle U_\omega^\tau|) \right] \right) .$$

In other words, our general scheme retrieves all possible schemes to achieve ideal teleportation with Bell observables [24, 25], and, more generally, with Bell POVMs [26].

7.0.2. Universal tele-cloning. The optimal quantum cloning of pure states from N input copies to M output copies is given by a channel $\mathcal{C}_{N,M} \in \text{CP}(\mathbf{H}_N^+, \mathbf{H}_M^+)$, where \mathbf{H}_k^+ denotes the totally symmetric subspace of the tensor product $\mathbf{H}^{\otimes k}$. The

channel is covariant w.r.t. the irreducible representations $(\mathcal{U}_{\mathbf{G}}^{\otimes N}, \mathcal{U}_{\mathbf{G}}^{\otimes M})$ of the group $\mathbf{G} = \text{SU}(d)$, namely $\mathcal{C}_{N,M} \mathcal{U}_g^{\otimes N} = \mathcal{U}_g^{\otimes M} \mathcal{C}_{N,M} \forall g \in \text{SU}(d)$, and is given by [27, 28]

$$(93) \quad \mathcal{C}_{N,M}(\rho) = \frac{d_N^+}{d_M^+} P_M^+(\rho \otimes \mathbb{1}^{\otimes(M-N)}) P_M^+ \quad \rho \in \mathcal{S}(\mathbf{H}_N^+),$$

where $d_k^+ := \dim \mathbf{H}_k^+$, and P_k^+ is the projector on \mathbf{H}_k^+ . The realization of Eq. (90) then yields a generalized teleportation scheme with covariant Bell POVM:

$$(94) \quad \mathcal{C}_{N,M}(\rho) = \mathcal{U}_g^{\otimes M} \left(\text{Tr}_{2,3} \left[\left(\frac{C_{N,M}}{d_N^+} \otimes \rho \right) (\mathbb{1}_{\text{out}} \otimes d_N^+ |U_g^{\tau \otimes N}\rangle\rangle \langle\langle U_g^{\tau \otimes N}|) \right] \right),$$

with $C_{N,M} = (\mathcal{C}_{N,M} \otimes \mathcal{I})(|\mathbb{1}_{\mathbf{H}_N^+}\rangle\rangle \langle\langle \mathbb{1}_{\mathbf{H}_N^+}|)$. On the other hand, the feed-forward scheme of Eq. (91) gives

$$(95) \quad \mathcal{C}_{N,M}(\rho) = \mathcal{U}_g^{\otimes M} \left(\text{Tr}_{2,3} \left[\left(\frac{|P_M^+\rangle\rangle \langle\langle P_M^+|}{d_M^+} \otimes \rho \right) (\mathbb{1}_{\text{out}} \otimes \zeta_g) \right] \right)$$

where ζ_g is the covariant POVM given by

$$(96) \quad \zeta_g = d_M^+ (\mathbb{1}_{\text{out}} \otimes U_g^{\otimes N}) C_{N,M}^* (\mathbb{1}_{\text{out}} \otimes U_g^{\dagger \otimes N})$$

7.0.3. Optimal universal NOT gate. The optimal universal NOT is the channel from \mathbf{H}_N^+ to \mathbf{H}_M^+ with $\mathbf{H} = \text{Span}\{|0\rangle, |1\rangle\} \simeq \mathbb{C}^2$ which transforms N copies of a pure state into one approximate copy of its orthogonal complement. The channel \mathcal{N} is given by the measure-and-reprepare scheme [29]

$$(97) \quad \mathcal{N}(\rho) = \int_{\text{SU}(d)} dg \text{Tr}[\rho \zeta_g] U_g |1\rangle \langle 1| U_g^\dagger.$$

where ζ_g is the covariant POVM $\zeta_g = d_N^+ (U_g |0\rangle \langle 0| U_g^\dagger)^{\otimes N}$. By definition, $\mathcal{N} \equiv \mathcal{Z}_\Omega$, where \mathcal{Z} the covariant channel with density $\mathcal{S}_g(\rho) = \text{Tr}[\rho \zeta_g] U_g |1\rangle \langle 1| U_g^\dagger = \mathcal{U}_g \mathcal{S}_0 \mathcal{U}_g^{\dagger \otimes N}$, $\mathcal{S}_0(\rho) = \text{Tr}[\rho(|0\rangle \langle 0|)^{\otimes N}] |1\rangle \langle 1|$. In this case, it easy to see that the minimal generalized teleportation scheme given by Eq. (83) coincides with the definition of the channel: indeed \mathcal{N} is of the measure-and-reprepare form, and by definition it can be achieved via a measurement at Alice's site combined with a conditional state preparation at Bob's site. On the other hand, the non-minimal scheme of Eq. (84) gives

$$(98) \quad \mathcal{N}(\rho) = \int_{\text{SU}(d)} dg \mathcal{U}_g (\text{Tr}_{2,3} [(|1\rangle \langle 1| \otimes |0\rangle \langle 0|^{\otimes N} \otimes \rho) (\mathbb{1}_{\text{out}} \otimes d_N^+ |U_g^{\tau \otimes N}\rangle\rangle \langle\langle U_g^{\tau \otimes N}|)]).$$

REFERENCES

- [1] J. von Neumann. *Mathematical Foundations of Quantum Mechanics*. Princeton UP, Princeton, NJ, 1955.
- [2] M. Ozawa. Quantum measuring processes of continuous observables. *J. Math. Phys.*, 25:79, 1984.
- [3] E. B. Davies and J. T. Lewis. An operational approach to quantum probability. *Comm. Math. Phys.*, 17:239, 1970.
- [4] K. Kraus. General state changes in quantum theory. *Ann. Phys.*, 64:311–335, 1971.
- [5] G. M. D'Ariano, P. Lo Presti, and M. F. Sacchi. A quantum measurement of the spin direction. *Phys. Lett. A*, 292:233, 2002.
- [6] G. Chiribella, G. M. D'Ariano, and D. M. Schlingemann. How continuous quantum measurements in finite dimensions are actually discrete. *Phys. Rev. Lett.*, 98:190403, 2007.

- [7] G. Chiribella, G. M. D'Ariano, and D. M. Schlingemann. Barycentric decomposition of quantum measurements in finite dimensions. *LANL arXive eprint*, quant-ph/08???.???:1–11, 2008.
- [8] M. A. Naimark. Spectral functions of a symmetric operator. *Iza. Akad. Nauk USSR, Ser. Mat.*, 4:277–318, 1940.
- [9] M Murao, D Jonathan, M. B Plenio, and V Vedral. Quantum teleportation and multiparticle entanglement. *Physical Review A (Atomic)*, 59:156, Jan 1999.
- [10] V Buž Ek, M Hillery, and R. F Werner. Optimal manipulations with qubits: Universal-not gate. *Physical Review A (Atomic)*, 60:2626, Oct 1999.
- [11] K. Kraus. *States, Effects, and Operations*. Springer, Berlin, 1983.
- [12] M.-D. Choi. Completely positive linear maps on complex matrices. *Linear Algebra Appl.*, 10:285–290, 1975.
- [13] A. Jamiolkowski. Linear transformations which preserve trace and positive semidefiniteness of operators. *Rep. Math. Phys.*, 3:275, 1972.
- [14] G. M. D'Ariano and P. Lo Presti. Optimal non-universally covariant cloning. *Phys. Rev. A*, 64:042308, 2001.
- [15] W. F. Stinespring. Positive functions on C^* -algebras. *Proc. Amer. Math. Soc.*, 6:211–216, 1955.
- [16] A. S Holevo. Radon-nikodym derivatives of quantum instruments. *Journal of Mathematical Physics*, 39:1373, Mar 1998.
- [17] Masanao Ozawa. Concepts of conditional expectations in quantum theory. *Journal of Mathematical Physics*, 26:1948, Aug 1985.
- [18] E. B. Davies. Quantum dynamical semigroups and the neutron diffusion equation. *Rep. Math. Phys.*, 11:169, 1977.
- [19] A. S. Holevo. *Probabilistic and statistical aspects of quantum theory*, volume 1 of *Series in Statistics and Probability*. North-Holland, Amsterdam, New York, Oxford, 1982.
- [20] Gerald B. Folland, editor. *A course in abstract harmonic analysis*. Studies in Advanced Mathematics. CRC Press, Boca Raton, FL, 1995.
- [21] G Chiribella, G. M D'ariano, and M. F Sacchi. Optimal estimation of group transformations using entanglement. *Phys. Rev. A*, 72(4):10, Oct 2005.
- [22] R. Werner. Optimal cloning of pure states. *Phys. Rev. A*, 58:1827, 1998.
- [23] F. Buscemi, G. M. D'Ariano, P. Perinotti, and M. F. Sacchi. Optimal realization of the transposition maps. *Phys. Lett. A*, 314:374, 2003.
- [24] Charles H Bennett, Gilles Brassard, Claude Crepeau, Richard Jozsa, Asher Peres, and William K Wootters. Teleporting an unknown quantum state via dual classical and einstein-podolsky-rosen channels. *Physical Review Letters (ISSN 0031-9007)*, 70:1895, Mar 1993.
- [25] R. F Werner. All teleportation and dense coding schemes. *Journal of Physics A: Mathematical and General*, 34:7081, Sep 2001.
- [26] Samuel L Braunstein, Giacomo M D'Ariano, G. J Milburn, and Massimiliano F Sacchi. Universal teleportation with a twist. *Phys. Rev. Lett.*, 84:3486, Apr 2000.
- [27] RF Werner. Optimal cloning of pure states. *Phys. Rev. A*, 58(3):1827–1832, Jan 1998.
- [28] M Keyl and R. F Werner. Optimal cloning of pure states, testing single clones. *Journal of Mathematical Physics*, 40:3283, Jul 1999.
- [29] M Ricci, F Sciarrino, C Sias, and F De Martini. Teleportation scheme implementing the universal optimal quantum cloning machine and the universal *Phys. Rev. Lett.*, Jan 2004.

GIULIO CHIRIBELLA, *QUIT* GROUP, DIPARTIMENTO DI FISICA “A. VOLTA”, VIA BASSI 6, I-27100 PAVIA, ITALY, [HTTP://WWW.QUBIT.IT](http://www.qubit.it)
E-mail address: chiribella@unipv.it

GIACOMO MAURO D'ARIANO, *QUIT* GROUP, DIPARTIMENTO DI FISICA “A. VOLTA”, VIA BASSI 6, I-27100 PAVIA, ITALY, [HTTP://WWW.QUBIT.IT](http://www.qubit.it), ISTITUTO NAZIONALE DI FISICA NUCLEARE, SEZIONE DI PAVIA., CENTER FOR PHOTONIC COMMUNICATION AND COMPUTING, DEPARTMENT OF ELECTRICAL AND COMPUTER ENGINEERING, NORTHWESTERN UNIVERSITY, EVANSTON, IL 60208
E-mail address: dariano@unipv.it

PAOLO PERINOTTI, *QUIT* GROUP, DIPARTIMENTO DI FISICA “A. VOLTA”, VIA BASSI 6, I-27100 PAVIA, ITALY, [HTTP://WWW.QUBIT.IT](http://www.qubit.it), ISTITUTO NAZIONALE DI FISICA NUCLEARE, SEZIONE DI PAVIA
E-mail address: perinotti@unipv.it