## Comment on Local Unitary equivalence of multipartite pure qubits states

Ana M. Martins

Instituto Superior Técnico-IST, Universidade de Lisboa-UL, 1049-001 Lisboa, Portugal

April 12, 2021

## Abstract

A Comment on the Letter by B. Kraus Phys. Rev. Lett. 104, 020504 (2010).

## Comment on "Local Unitary equivalence of multipartite pure qubits states"

Kraus [\[1\]](#page-3-0) derives necessary and sufficient conditions for the equivalence of arbitrary, n-qbit pure states under Local Unitary (LU) operations. Theorem 1, stating that any two pure *n*-qubit states, with  $\rho_i \neq \frac{1}{2}$  $\frac{1}{2}$ , are LU-equivalent iff their standard forms are equal, can be formulated using simply the trace decomposition form of a state instead of its standard form, as proposed in the letter. By one side, it is simpler to work with the trace decomposition form of a state then with its *sorted trace decomposition*, that precedes its standard form. By another side we show that this new formulation is equally applicable to pure and mixed states. The proof goes like this.

A pure or mixed state  $\rho'$  is LU-equivalent to  $\rho$  when there exist Local Unitary operators  $U_i, ..., U_n$  such that  $\rho' = U_1 \otimes ... \otimes U_n$   $\rho$   $U_n^{\dagger} \otimes ... \otimes U_1^{\dagger}$  $i$ <sup>1</sup>. Then

<span id="page-1-0"></span>
$$
\rho_i' = U_i \rho_i, U_i^{\dagger} \tag{1}
$$

where  $\rho'_{i}$  $\varphi$  and  $\rho_i$  are the reduced states of qubit i associated to the global states  $\rho'$  and  $\rho$ .

Let  $V_i$  be the unitary operator that diagonalizes  $\rho_i$ , i.e.,  $\rho_i = V_i D_i V_i^{\dagger}$  where  $D_i$  is a diagonal matrix. Introducing this equality in eq.[\(1\)](#page-1-0) we conclude that  $V'_i = U_i V_i$  is the unitary operator that diagonalizes  $\rho'_i$  $\mu'_{i}$ , i.e.  $\rho'_{i} = V'_{i} D_{i} V'^{\dagger}_{i}$  $\frac{r}{i}$ , therefore the local unitary  $U_i$  is uniquely determined (up to a global phase) by  $U_i = V_i' V_i^{\dagger}$ <sup>r</sup><sup>t</sup>. When  $\rho'_i = \rho_i$ , then  $V'_i = V_i$  and  $U_i = 1$ , is the trivial identity operator. However, there are LU-operators, beside the trivial one  $U_i = 1$ , named cyclic local unitary operators [\[2,](#page-3-1) [3\]](#page-3-2), that leave a state,  $\rho_i \neq \frac{1}{2}$  $\frac{1}{2}$ , invariant. Such LU operators obey the following commutation relation

<span id="page-1-1"></span>
$$
[\rho_i, U_i] = 0 \tag{2}
$$

The set of local unitary operators  $U_i \in SU(2)$  obeying the cyclic condition [\(2\)](#page-1-1) is the stabilizer subgroup of  $\rho_i$ . The general form of the non trivial unitary cyclic operators  $U_j$ , that comute with the 1-qubit density matrix  $\rho_j=\frac{1}{2}$  $\frac{1}{2}(\mathbf{1}_j + \vec{r}(j) \cdot \vec{\sigma}(j))$ , where  $\vec{r}(j) \neq 0$  is the 3-dimensional Bloch vector,  $\vec{\sigma}(j) = (\sigma_1(j), \sigma_2(j), \sigma_3(j))$ , and where  $\sigma_i(j)$  (i = 1, 2, 3) are the Pauli matrices, was derived in Ref.[\[4\]](#page-3-3). There it was shown that  $U_j = e^{i\xi_j \vec{n}_j \cdot \vec{\sigma}(j)}$ , where  $\vec{n}_j =$  $\vec{r}(j)/||\vec{r}(j)||$  and  $\xi_j$  is a real continuous parameter such that  $0 \leq \xi_j \leq \pi/2$ .

The *trace decomposition*  $\rho_t$  and  $\rho'_t$  $t<sub>t</sub>$  of any two LU-equivalent states  $\rho$  and  $\rho^{'}$  is

<span id="page-1-2"></span>
$$
\rho_t^{'} = V_1^{'\dagger} \otimes \dots \otimes V_n^{'\dagger} \rho^{'} V_n^{'} \otimes \dots \otimes V_1^{'}
$$
 (3)

<span id="page-2-0"></span>
$$
\rho_t = V_1^{\dagger} \otimes \dots \otimes V_n^{\dagger} \; \rho \; V_n \otimes \dots \otimes V_1 \tag{4}
$$

From where we easily obtain the relation between the two trace decomposition forms

$$
\rho'_{t} = (V'^{\dagger}_{1} U_{1} V_{1}) \otimes ... \otimes (V'^{\dagger}_{n} U_{n} V_{n}) \rho_{t} (V'^{\dagger}_{n} U_{n} V_{n})^{\dagger} \otimes ... \otimes (V'^{\dagger}_{1} U_{1} V_{1})^{\dagger} (5)
$$

When  $\rho'_i \neq \rho_i$  and  $\rho_i \neq \frac{1}{2}$  $\frac{1}{2}$ , for all  $i = 1, ..., n$ , then,  $U_i = V_i' V_i^{\dagger} \Leftrightarrow V_i'^{\dagger} U_i V_i = \mathbf{1}_i$ , and the two *trace decomposition* forms are equal, i.e.,  $\rho'_{t} = \rho_{t}$ . Given two arbitrary *n*-qubit states  $\rho$  and  $\rho'$  we can check if they are LU-equivalent with the following protocol. After verifying that none of the LU operators is cyclic, we express the density operators  $\rho$  and  $\rho'$  in the generalized Pauli basis [\[4\]](#page-3-3), and compute separately  $\rho_t$  and  $\rho'_t$  using [\(3\)](#page-1-2) and [\(4\)](#page-2-0). Then we take the difference  $(\rho'_t - \rho_t)$ . It will be null iff  $\rho'$  and  $\rho$  are LU-equivalent.

When there is at least one k such that  $\rho'_k = \rho_k \neq \frac{1}{2}$  $\frac{1}{2}$ , then  $\bar{U}_k = V_k^{\dagger} U_k V_k$ is given by

<span id="page-2-2"></span>
$$
\bar{U}_k = \begin{pmatrix} e^{i\omega_k} & 0\\ 0 & e^{-i\omega_k} \end{pmatrix}
$$
 (6)

where  $\omega_k = \xi_k ||\vec{r}(k)||$ . Assuming that there is only one  $U_k$  obeying condition [\(2\)](#page-1-1) the *trace decomposition forms*,  $\rho'_t$  and  $\rho_t$ , are related by

<span id="page-2-1"></span>
$$
\rho_t^{'} = \mathbf{1}_1 \otimes \ldots \otimes \bar{U}_k \otimes \ldots \otimes \mathbf{1}_n \ \rho_t \ \mathbf{1}_1 \otimes \ldots \otimes \bar{U}_k^{\dagger} \otimes \ldots \otimes \mathbf{1}_n \tag{7}
$$

To check for the LU-equivalence we compute  $\rho'_{t}$  using eq.[\(3\)](#page-1-2) with  $V'_{k} = V_{k}$ , and the right side of  $(7)$  using  $(4)$  and  $(6)$ . Then we compute the difference,

$$
\rho'_{t} - (\mathbf{1}_{1} \otimes \ldots \otimes \bar{U}_{k} \otimes \ldots \otimes \mathbf{1}_{n} \rho_{t} \mathbf{1}_{1} \otimes \ldots \otimes \bar{U}_{k}^{\dagger} \otimes \ldots \otimes \mathbf{1}_{n})
$$
(8)

It will be null iff  $\rho'$  and  $\rho$  are LU-equivalent. This procedure is easily generalized when there are more than one local unitary operador obeying condition [\(2\)](#page-1-1).

In conclusion, there are two advantages of using the *trace decomposition* form and density matrix representation of a state instead of the standard form and the wave function representation of a state, as is done in the letter [\[1\]](#page-3-0): 1) It can be equally applied to pure and mixed states, 2) It is more straighforward to compute the trace decomposition form of a state than its standard form as it is proposed in the Letter.

## <span id="page-3-0"></span>References

- <span id="page-3-1"></span>[1] B. Kraus, *Phys. Rev. Lett.*, **104**, 020504 (2010).
- <span id="page-3-2"></span>[2] L. B. Fu., Europhys. Lett., 75, 1 (2006).
- [3] S. Gharibian, H. Kampermann, and D. Bruß, Quantum Information and Computation, 9, 1013 (2009).
- <span id="page-3-3"></span>[4] A. Martins, arXiv:quant-ph/1307.0948v2 (2014).