

# Scattering approach to Anderson localisation

A. Ossipov\*

*School of Mathematical Sciences, University of Nottingham, Nottingham NG7 2RD, United Kingdom*  
(Dated: June 3, 2019)

We develop a novel approach to the Anderson localisation problem in a  $d$ -dimensional disordered sample of dimension  $L \times M^{d-1}$ . Attaching a perfect lead with the cross-section  $M^{d-1}$  to one side of the sample, we derive evolution equations for the scattering matrix and the Wigner-Smith time delay matrix as a function of  $L$ . Using them one obtains the Fokker-Planck equation for the distribution of the proper delay times and the evolution equation for their density at weak disorder. The latter can be mapped onto a non-linear partial differential equation of the Burgers type, for which a complete analytical solution for arbitrary  $L$  is constructed. Analysing the solution for a cubic sample with  $M = L$  in the limit  $L \rightarrow \infty$ , we find that for  $d < 2$  the solution tends to the localised fixed point, while for  $d > 2$  to the metallic fixed point and provide explicit results for the density of the delay times in these two limits.

PACS numbers:

*Introduction*– Sixty years ago Anderson discovered that the classical diffusion in a random potential can be totally suppressed by quantum interference effects [1]. Since that time the problem of Anderson localisation has remained in the focus of very active research and recently it has received a lot of attention in the context of topological insulators and many-body localisation [2].

Apart from the strictly one-dimensional case, the most developed non-perturbative theory of Anderson localisation is available for disordered wires. The only important parameters of such a system are the length  $L$ , the mean free path  $l$ , the number of the propagating modes  $N$  at the Fermi energy  $E$  and the localisation length  $\xi = Nl$ . The disorder is usually assumed to be weak, so that  $L, l \gg \lambda_F$ , where  $\lambda_F$  is the Fermi wave length. There are two powerful analytical approaches, which can solve the problem of Anderson localisation in a wire for an arbitrary ratio  $L/\xi$ : the Dorokhov, Mello, Pereyra and Kumar (DMPK) equation [3, 4] and the supersymmetric nonlinear  $\sigma$ -model [5, 6]. Both solutions are restricted to the quasi-one-dimensional geometry of a wire, for which the transverse dimension  $M$  is much smaller than  $L$ . Despite a lot of efforts, a similar theory for higher dimensional systems has not been developed so far and it is the purpose of this Letter to take the first step towards this long-standing goal.

We consider a  $d$ -dimensional weakly disordered sample of the length  $L$  in the  $x$ -direction and the width  $M$  in all other transverse directions. A perfect lead is attached to one side of the sample along the  $x$ -direction, which has the same cross section  $M^{d-1}$  as the sample. The scattering setup allows one to introduce the scattering matrix  $S$  and the Wigner-Smith time-delay matrix  $Q = -i\hbar S^{-1/2} \frac{\partial S}{\partial E} S^{-1/2}$ , whose eigenvalues  $\tilde{\tau}_i$  are referred to as the proper delay times (see Ref.[7] for a recent review). Generalising the approach developed for the one-dimensional systems [8, 9] we derive the Fokker-Planck equation for the evolution of the distribution function  $P(\{\tilde{\tau}_i\}, r)$  in fictitious time  $r \propto L/l$ , provided that

$L, M, l \gg \lambda_F$ . Then we focus on the time-dependent equation for the density  $\rho(\tilde{\tau}, r)$  of the delay times, which contains important information about localisation in the corresponding closed system. Mapping this equation onto a non-linear partial differential equation of the Burgers type, we construct its complete analytical solution for arbitrary  $L$ ,  $M$  and  $l$ .

Our general solution, which is valid for any dimensionality  $d$ , allows us in particular to consider a  $d$ -dimensional cubic sample with  $M = L$ . Analysing such a system in the limit  $L/\lambda_F \rightarrow \infty$ , we find that for  $d < 2$  the solution tends to the localised fixed point, while for  $d > 2$  to the metallic (diffusive) fixed point and derive explicit analytical results for the density of the delay times in these two limits. Thus our approach provides a solid non-perturbative foundation for the arguments of the scaling theory of Anderson localisation [10].

As the derivation of our results involves a lot of technical steps, in this Letter we only outline its main points and leave the technical details for a more specialised publication [11].

*Model*– We consider the Hamiltonian for a particle moving in the  $d$ -dimensional  $\delta$ -correlated disordered potential:

$$H = - \sum_{i=0}^{d-1} \frac{\partial^2}{\partial x_i^2} + V(\mathbf{r}), \quad \mathbf{r} = (x, \boldsymbol{\rho}),$$

$$\langle V(\mathbf{r})V(\mathbf{r}') \rangle = \sigma \delta(\mathbf{r} - \mathbf{r}'), \quad \sigma = \frac{1}{2\pi\nu\tau_s}, \quad (1)$$

where  $x \equiv x_0$ ,  $\boldsymbol{\rho} \equiv (x_1, \dots, x_{d-1})$ ,  $\nu$  is the density of states,  $\tau_s$  is the scattering mean free time and we set  $\hbar = 2m = 1$ . A sample is assumed to be finite with  $-L \leq x \leq 0$  and  $0 \leq x_i \leq M$  for  $i = 1, \dots, d-1$ , and the Dirichlet boundary condition is imposed in all directions.

By attaching a perfect lead to one side of the sample at  $x = 0$ , we obtain a scattering system characterised by the  $N \times N$   $S$ -matrix, which is unitary  $S^\dagger = S^{-1}$  and symmetric  $S^T = S$  due to the time reversal

symmetry. The eigenfunctions in the transverse directions  $u_{\mathbf{n}}(\boldsymbol{\rho}) = \left(\frac{2}{M}\right)^{\frac{d-1}{2}} \prod_{i=1}^{d-1} \sin \frac{\pi n_i x_i}{M}$ ,  $n_i \in \mathbb{N}$ , correspond to the eigenenergies  $E_{\mathbf{n}} = \left(\frac{\pi \mathbf{n}}{M}\right)^2$ . The number of open channels at the energy  $E$  is equal to  $N = \gamma_{d-1}(M\sqrt{E}/\pi)^{d-1}$ , where  $\gamma_d = \frac{\pi^{\frac{d}{2}}}{2^d \Gamma(\frac{d}{2}+1)}$ .

*Recursion relations for  $S$  and  $Q$  matrices*– In order to derive an equation for the evolution of  $S$  by increasing  $L$  to  $L + \delta L$ , we first consider the scattering matrix of a thin slice of the length  $\delta L \ll \lambda_F$ . Using the Lippmann-Schwinger equation, one can show that the reflection and the transmission matrices from the left and from the right coincide respectively,  $r' = r$ ,  $t' = t$ , and to the leading order in  $\delta L/\lambda_F$  are given by

$$r = -B(I + B)^{-1}, \quad t = I + r, \quad B \equiv \frac{i}{2} \hat{q}^{-1/2} \bar{V}(0) \hat{q}^{-1/2}, \quad (2)$$

where  $\hat{q}$  is the diagonal matrix, whose elements are the quantised longitudinal momenta  $q_{\mathbf{n}} = \sqrt{E - E_{\mathbf{n}}}$  and  $\bar{V}_{nm}(x) \equiv \int_x^{x+\delta L} dx' \int d\rho V(x', \boldsymbol{\rho}) u_{\mathbf{n}}(\boldsymbol{\rho}) u_{\mathbf{m}}(\boldsymbol{\rho})$ .

Applying the standard formula for the composition of the scattering matrices and using the fact that  $r = t - I$  we derive the relation between  $S_{n+1} \equiv S(L + \delta L)$  and  $S_n \equiv S(L)$ , the scattering matrices corresponding to the system of the length  $L = n\delta L$  and  $L + \delta L = (n + 1)\delta L$ :

$$f(S_{n+1}) = f(e^{i\hat{q}\delta L} S_n e^{i\hat{q}\delta L}) + A_{n+1}, \quad (3)$$

where  $A_{n+1} \equiv \hat{q}^{-1/2} \bar{V}(L) \hat{q}^{-1/2}$ , and  $f(S) \equiv i \frac{(S-I)}{(S+I)}$ . The above equation is a direct generalisation of the one-dimensional relation [8]. Differentiating it w.r.t.  $E$  one obtains the recursion relation for  $Q$ :

$$W_n Q_{n+1} W_n^T = C_n (J_n Q_n J_n^T + K_n) C_n + H_n. \quad (4)$$

All the matrices involved in this equation can be expressed through  $S_n$ ,  $A_{n+1}$  and  $\hat{q}$  and their definitions are given in the Supplemental Material [12]. Both relations preserve the symmetries of the scattering and Wigner-Smith matrices respectively:  $S^\dagger = S^{-1}$ ,  $S^T = S$ ,  $Q^\dagger = Q$ ,  $Q^T = Q$ . They hold for any strength of disorder  $\sigma$  and are very convenient for numerical simulations, as they deal with the matrices corresponding to  $d-1$  rather than  $d$ -dimensional systems.

Now we assume that disorder is weak, i.e.  $l \gg \lambda_F$ . Then an analysis of the relations (3) and (4) suggests that the change of  $S$  and the eigenvectors of  $Q$  at each step of the recursion is governed by the parameter  $\delta L/\lambda_F$ , while the change of the eigenvalues of  $Q$  by the parameter  $\delta L/l$  [12]. As  $\delta L/\lambda_F \gg \delta L/l$ , this implies that  $S$  and the matrix of the eigenvectors of  $Q$ ,  $O$ , represent fast variables, while  $\tilde{\tau}_i$  are slow variables. Therefore in the following we assume that for  $L \gg \lambda_F$ ,  $S$  is distributed uniformly, i.e.  $S$  is an element of the Circular Orthogonal Ensemble (COE),  $O$  is distributed uniformly over the orthogonal group  $O(N)$ , and  $S$  and  $O$  are statistically independent.

In fact such properties of  $S$  and  $Q$  were proved for chaotic scattering in Ref. [13] using the so called Wigner conjecture, which is very general and can be formulated for a system of an arbitrary dimensionality.

*Fokker-Planck equation and the evolution equation for the density* – The recursion relation (4) can be transformed into the Fokker-Planck equation for the joint probability distribution function  $P(\{\tilde{\tau}_i\})$  in the continuum limit  $\delta L \rightarrow 0$ . To this end, we first use the general relation between  $P(\{\tilde{\tau}_i\})$  calculated at two consequent steps:

$$P_{n+1}(\{\tilde{\tau}_i\}) = P_n(\{\tilde{\tau}_i\}) + \left[ -\sum_i \frac{\partial}{\partial \tilde{\tau}_i} \langle \delta \tilde{\tau}_i \rangle + \frac{1}{2} \sum_{ik} \frac{\partial^2}{\partial \tilde{\tau}_i \partial \tilde{\tau}_k} \langle \delta \tilde{\tau}_i \delta \tilde{\tau}_k \rangle \right] P_n(\{\tilde{\tau}_i\}), \quad (5)$$

where  $\langle \dots \rangle$  stands for the averaging over  $S$ ,  $O$  and  $V(\mathbf{r})$  and only the terms up to the first order in  $\delta L$  must be retained on the r.h.s. The averages  $\langle \delta \tilde{\tau}_i \rangle$  and  $\langle \delta \tilde{\tau}_i \delta \tilde{\tau}_k \rangle$  can be computed with the help of the perturbation theory:

$$\delta \tilde{\tau}_i = \langle i | O^T \delta Q O | i \rangle + \sum_{k \neq i} \frac{|\langle k | O^T \delta Q O | i \rangle|^2}{\tilde{\tau}_i - \tilde{\tau}_k}, \quad (6)$$

where  $\{|i\rangle\}$  is the standard basis in  $\mathbb{R}^N$  and we omit the index  $n$  for all variables to lighten the notation. The matrix  $\delta Q \equiv Q_{n+1} - Q_n$  can be found from Eq.(4).

Introducing the scaled variables  $\tau = \frac{\tilde{\tau}}{\tau_s}$  and  $r = A_d \frac{L}{l}$ , with  $A_d \equiv \frac{\sqrt{\pi} \Gamma(\frac{d+1}{2})}{\Gamma(\frac{d}{2})}$ , and taking the limit  $\delta L \rightarrow 0$ , we derive (see the Supplemental Material [12] for details) the Fokker-Planck equation for the distribution function  $P(\{\tau_i\}, r)$

$$\frac{\partial P}{\partial r} = \frac{1}{N} \sum_i \frac{\partial}{\partial \tau_i} \left[ (N-1)\tau_i - 2N \left( -\sum_{k \neq i} \frac{\tau_i^2}{\tau_i - \tau_k} + \sum_k \frac{\partial}{\partial \tau_k} \left( \tau_i^2 \delta_{ik} + \frac{\tau_i \tau_k}{N} \right) \right) \right] P. \quad (7)$$

The distribution function  $P(\{\tau_i\}, r)$  contains the full information about the delay times, however in order to distinguish between the localised and delocalised phases of the closed system, it is sufficient to study a simpler quantity – the density of the delay times  $\rho(\tau, r) = \frac{1}{N} \sum_i \langle \delta(\tau - \tau_i) \rangle$ , which can be obtained from  $P(\{\tau_i\}, r)$  by integrating out all but one variables  $\tau_i$ .

The evolution equation for  $\rho(\tau, r)$ , which can be derived from (7) in the standard way [14], reads

$$\frac{\partial \rho}{\partial r} = \frac{\partial}{\partial \tau} \left[ \rho \left( \tau - 2 - \tau^2 \int d\tau' \frac{\rho(\tau', t)}{\tau - \tau'} \right) + \frac{\partial}{\partial \tau} \frac{\tau^2 \rho}{2N} \right]. \quad (8)$$

*Burgers equation and the stationary solution* – The integro-differential equation for the density can be mapped onto a non-linear partial differential equation

employing the method used in Ref.[15]. We introduce the Stieltjes transform of  $\rho(\tau, r)$  defined as

$$F(z, r) = \int_0^\infty d\tau' \frac{\rho(\tau', r)}{z - \tau'}. \quad (9)$$

The function  $F(z, r)$  is analytic in the complex plane for all  $z$  except the positive real axis, where it is discontinuous:

$$F_\pm \equiv \lim_{\epsilon \rightarrow 0^+} F(\tau \pm i\epsilon) = \pm \frac{\pi}{i} \rho(\tau, r) + \int_0^\infty d\tau' \frac{\rho(\tau', r)}{\tau - \tau'}. \quad (10)$$

Using this formula, the analyticity of  $F$  and Eq.(8) one can show that  $F$  satisfies the non-linear differential equation of the Burgers type

$$\frac{\partial F}{\partial r} = \frac{1}{2N} \frac{\partial}{\partial z} \left[ N(2(z-2)F - z^2 F^2) + \frac{\partial}{\partial z} z^2 F \right], \quad (11)$$

whose solution allows us to find  $\rho$  through the relation  $\rho(\tau, r) = \frac{i}{2\pi}(F_+ - F_-)$ . Eq.(11) enables one to determine easily the stationary solution for  $r \rightarrow \infty$  and  $\tau \sim N^0$ . Indeed in this case one can set  $\frac{\partial F}{\partial r} = 0$  and neglect the last term on the r.h.s.

$$\frac{d}{dz} [N(2(z-2)F_{st} - z^2 F_{st}^2)] = 0. \quad (12)$$

The solution of the above equation satisfying the condition  $F(z, r) \approx \frac{1}{z}$ ,  $|z| \rightarrow \infty$  (which follows from the definition of  $F$ ), is given by

$$F_{st}(z) = \frac{z - 2 - 2\sqrt{1-z}}{z^2} \quad (13)$$

and corresponds to the density

$$\rho_{st}(\tau) = \frac{2}{\pi} \frac{\sqrt{\tau-1}}{\tau^2}, \quad \tau \geq 1. \quad (14)$$

*Hopf-Cole transformation and the non-stationary solution* – In order to find a solution of Eq.(11) at finite  $r$  we employ a variant of the Hopf-Cole transformation:

$$F(z, r) = \frac{z-2}{z^2} - \frac{4}{z^2} \frac{u'_s(s, r)}{u(s, r)}, \quad s = -\frac{4N}{z} \quad (15)$$

which maps the equation for  $F$  onto the generalised diffusion equation:

$$8N \frac{\partial u}{\partial r} = 4s^2 u''_{ss} - s(s+4N)u. \quad (16)$$

One can look for the general solution of this equation as a linear combination of the eigenfunctions  $e^{-\frac{\lambda}{2}r} u_\lambda(s)$ . It turns out that the spectrum is continuous for  $\lambda = \frac{4\mu^2+1}{4N}$ , and the corresponding orthogonal eigenfunctions are given by the Whittaker functions  $W_{-N, i\mu}(s)$  with  $\mu > 0$  [16]. Additionally to this set of the eigenstates there is another eigenfunction  $W_{-N, \frac{1}{2}}(s)$  for  $\lambda = 0$  corresponding

to the stationary state [17]. Thus the solution of Eq.(16) can be written as

$$u(s, r) = c_0 W_{-N, \frac{1}{2}}(s) + \int_0^\infty d\mu c(\mu) e^{-\frac{(4\mu^2+1)r}{8N}} W_{-N, i\mu}(s), \quad (17)$$

where the coefficients  $c_0 = \Gamma(N+1)$  and  $c(\mu) = \frac{8\mu \sinh(\pi\mu) \Gamma(N+\frac{1}{2}+i\mu) \Gamma(N+\frac{1}{2}-i\mu)}{\pi(1+4\mu^2) \Gamma(N)}$  are determined from the initial condition  $u(s, 0) = e^{-\frac{s}{2}}$ . This formula along with Eq.(15) and the relation  $\rho(\tau, r) = \frac{i}{2\pi}(F_+ - F_-)$  provides the general solution for  $\rho(\tau, r)$ , which is valid for any  $L/\lambda_F \gg 1$ ,  $N \propto (M/\lambda_F)^{d-1} \gg 1$  and  $l/\lambda_F \gg 1$ .

*The density of delay times for a cubic sample in the thermodynamic limit* – For a cubic sample  $M = L$  and it follows from Eq.(17) that the  $r$ -dependence of the solution is governed by the parameter  $r/N \propto (\lambda_F/l)(L/\lambda_F)^{2-d}$ , which has a meaning of the inverse dimensionless conductance  $g^{-1}$ . One can see that in the thermodynamic limit ( $L/\lambda_F \rightarrow \infty$ ),  $r/N \rightarrow \infty$  for  $d < 2$  and  $r/N \rightarrow 0$  for  $d > 2$ . In the former case, the solution tends to its localised fix point given by  $W_{-N, \frac{1}{2}}(s)$ , whereas in the latter case it tends to the metallic (diffusive) fixed point, where the contribution from all  $W_{-N, i\mu}(s)$  is important. The  $d = 2$  case is a marginal one and requires more careful treatment [11].

*Localised regime* – In the localised regime, where the solution is determined by the stationary state, the density can be found from the asymptotics of  $W_{-N, \frac{1}{2}}(s)$  at  $N \rightarrow \infty$ . In this way, for  $\tau \sim N^0$ , one can reproduce Eq.(14), while for  $\tau \sim N^2$  one obtains a different asymptotic behaviour of  $W_{-N, \frac{1}{2}}(s)$  and hence a different result for the density:

$$\rho_{st}(\tau) = \begin{cases} \frac{2}{\pi} \frac{\sqrt{\tau-1}}{\tau^2} & , \quad \tau \sim N^0, \tau \geq 1 \\ \frac{4N}{\tau^2} & , \quad \tau \gtrsim N^2. \end{cases} \quad (18)$$

A long  $\tau^{-2}$  tail in the distribution of the delay times in the localised regime was previously found analytically for  $1d$  and quasi- $1d$  systems [7, 18]. In the numerical simulations for the  $2d$  Anderson model both power-laws  $\tau^{-\frac{3}{2}}$  and  $\tau^{-2}$ , which follow from our result, were identified [19].

*Diffusive and ballistic regimes* – In the metallic regime, where  $r/N \ll 1$ , a direct analysis of Eq.(17) is complicated, so it is more convenient to derive the limiting solution in a different way. For  $r/N \ll 1$  the last term in Eq.(11) is small and hence can be neglected, then introducing the new function  $\psi(\xi, r)$ , such that  $F = \frac{z-2}{z^2} + z^{-1}\psi(\ln z, r)$ , one can map Eq.(11) onto the inviscid forced Burgers equation

$$\frac{\partial \psi}{\partial r} + \psi \frac{\partial \psi}{\partial \xi} = 2e^{-\xi} - 4e^{-2\xi}, \quad (19)$$

which can be solved by the method of characteristics:

$$F(z, r) = \frac{z - 2 + 2\sqrt{1 - z + \frac{z^2}{z_0^2}}}{z^2}, \quad (20)$$

where  $z_0 = z_0(z, r)$  is determined implicitly by the equation  $f(z_0, r) = z$  with  $f(x, r) \equiv \frac{x}{2} \left( x \left( 1 + \cosh \frac{2r}{x} \right) + 2 \sinh \frac{2r}{x} \right)$ . This formula gives a solution at an arbitrary value of  $r \propto L/l$  in the metallic regime. Now we can analyse it in detail in the ballistic ( $L/l \ll 1$ ) and the diffusive ( $L/l \gg 1$ ) limits.

In the ballistic regime,  $r \ll 1$ , one can expand  $f(x, r)$  in the power-series in  $r/x$  and find  $z_0$  approximately. The leading order result reads:

$$F(z, r) \approx \frac{1}{z - 2r}, \Rightarrow \rho(\tau, r) = \delta(\tau - 2r), \quad (21)$$

which describes a ballistic motion with the Fermi velocity,  $L \propto v_F \tilde{\tau}$ , as expected.

In the diffusive regime ( $r \gg 1$ ), the solution can be found by scaling  $z_0 = yr$ ,  $z = wr^2$  and  $F(z, r) = \frac{1}{r^2} \tilde{F}(\frac{z}{r^2}, r)$  and keeping only the leading order terms in  $r$ . The appearance of such a scaling implies that a typical delay time  $\tilde{\tau} \propto L^2/D$  ( $D$  is the classical diffusion constant), which is very natural in the diffusive regime. The function  $\tilde{F}(w, r)$  is then given by

$$\tilde{F}(w, r) = \frac{1}{w} + \frac{2}{rw^{\frac{3}{2}}} \sqrt{\frac{w}{y^2} - 1}, \quad (22)$$

where  $y = y(w)$  satisfies the equation  $y \cosh y^{-1} = \sqrt{w}$ . This result implies that  $\rho(\tau, r) \approx \tilde{\rho}(w)/r^3 \neq 0$  only for  $w \in [w_{min}, w_{max}]$ , where  $w_{min} \approx \frac{\pi^2}{16r^2}$  and  $w_{max} \approx 2.28$ . The behaviour of  $\tilde{\rho}(w)$  can be found analytically at  $w \rightarrow w_{min}$ , where  $\tilde{\rho}(w) \approx \frac{2}{\pi w^{\frac{3}{2}}}$ , and at  $w \rightarrow w_{max}$ , where  $\tilde{\rho}(w) \approx \frac{2\sqrt{(w_{max}+1)(w_{max}-w)}}{\pi w_{max}^2}$ . For intermediate values of  $w$ ,  $\tilde{\rho}(w)$  can be determined numerically from Eq.(22).

The appearance of the power-law  $\tau^{-\frac{3}{2}}$  tail in the metallic regime can be related to the classical diffusion [20].

*Comparison with the DMPK equation* – Since our method works also for a quasi-1d geometry, it makes sense to compare it with the DMPK equation. In Refs. [21, 22] the DMPK equation for the reflection eigenvalues in the presence of absorption was derived. As the proper delay times can be extracted from the reflection eigenvalues in the limit of weak absorption [23], one can obtain the DMPK equation for proper delay times and compare it with our Eq.(7). It turns out that the last term in Eq.(7) is absent in the DMPK equation. At the same time, the equation for the density  $\rho(\tau, r)$ , which can be derived from the DMPK equation, coincides with our Eq.(8).

We stress that the scattering isotropy assumption for a thin slice, which is crucial for the derivation of the DMPK

equation [14], is not used in our approach, in which the scattering properties of a slice are treated microscopically.

*Conclusions*– We have developed a new approach to the  $d$ -dimensional Anderson localisation problem, which enabled us to obtain in a non-perturbative way the statistics of the delay times in the ballistic, diffusive and localised regimes at weak disorder. Our work paves the way for studying analytically Anderson localisation in higher dimensional systems.

I acknowledge useful discussions with Y. V. Fyodorov.

- 
- \* Electronic address: alexander.ossipov@nottingham.ac.uk
- [1] P. W. Anderson, Phys. Rev. **109**, 1492 (1958).
  - [2] *50 Years of Anderson Localization*, ed E. Abrahams (World Scientific Publishing, 2010).
  - [3] O. N. Dorokhov, Pis'ma Zh. Eksp. Teor. Fiz. **36**, 259 (1982) [JETP Lett. **36**, 318 (1982)].
  - [4] P. A. Mello, P. Pereyra, and N. Kumar, 1988, Ann. Phys. (N.Y.) **181**, 290 (1988).
  - [5] K. B. Efetov and A. I. Larkin, Zh. Eksp. Teor. Fiz. **85**, 764 (1983) [Sov. Phys. JETP **58**, 444 (1983)].
  - [6] Y. V. Fyodorov and A. D. Mirlin, Phys. Rev. Lett. **69**, 1093 (1992).
  - [7] C. Texier, Physica E **82**, 16 (2016).
  - [8] A. Ossipov, T. Kottos, and T. Geisel, Phys. Rev. B **61**, 11411 (2000).
  - [9] A. Comtet and C. Texier, J Phys. A. **30**, 8017 (1997).
  - [10] E. Abrahams, P. W. Anderson, D. C. Licciardello, and T. V. Ramakrishnan, Phys. Rev. Lett. **42**, 673 (1979).
  - [11] A. Ossipov, in preparation.
  - [12] See Supplemental Material [url].
  - [13] P. W. Brouwer, K. M. Frahm and C. W. J. Beenakker, Waves in Random Media **9**, 91 (1999).
  - [14] C. W. J. Beenakker, Rev. Mod. Phys. **69**, 731 (1997).
  - [15] C. W. J. Beenakker, B. Rejaei, and J. A. Melsen, Phys. Rev. Lett. **72**, 2470 (1994).
  - [16] R. Sznmytkowski and S. Bielski, Integral Transforms and Special Functions **21**, 739 (2010).
  - [17] We note that a similar coexistence of a continuous spectrum and an isolated discrete eigenvalue corresponding to the stationary solution was previously found in the  $\sigma$ -model solution of the quasi-1d problem [6].
  - [18] Y. V. Fyodorov, JETP Lett. **78**, 250 (2003).
  - [19] F. Xu and J. Wang, Phys. Rev. B **84**, 024205 (2011).
  - [20] A. Ossipov, T. Kottos, and T. Geisel, Europhys. Lett. **62**, 719 (2003).
  - [21] C. W. J. Beenakker, J. C. J. Paasschens, and P. W. Brouwer, Phys. Rev. Lett. **76**, 1368 (1996).
  - [22] N. A. Bruce and J. T. Chalker, J. Phys. A **29**, 3761 (1996).
  - [23] C. W. J. Beenakker, *Photonic Crystals and Light Localization in the 21st Century*, edited by C.M. Soukoulis, NATO Science Series C563 (Kluwer, Dordrecht, 2001): pp. 489-508

## Supplemental Material: Scattering approach to Anderson localisation

### RECURSION RELATION FOR $Q$ MATRICES

The recursion relation for the  $S$ -matrix reads

$$f(S_{n+1}) = f(e^{i\hat{q}\delta L} S_n e^{i\hat{q}\delta L}) + A_{n+1}, \quad (\text{S1})$$

where  $\hat{q}$  is the diagonal matrix, whose elements are the longitudinal momenta  $q_n = \sqrt{E - E_n}$ ,  $A_{n+1} \equiv \hat{q}^{-1/2} \overline{V}(L) \hat{q}^{-1/2}$  and  $f(S) \equiv i \frac{(S-I)}{(S+I)}$ . In order to derive the recursion relation for  $Q_n$ , it is convenient first to introduce the following notation

$$S_n \equiv e^{2i\Theta_n}, \quad T_n \equiv e^{i\hat{q}\delta L} S_n e^{i\hat{q}\delta L} \equiv e^{2i\Phi_n}. \quad (\text{S2})$$

Then the recursion relation can be written as

$$\tan \Theta_{n+1} = \tan \Phi_n - A_{n+1}. \quad (\text{S3})$$

Using that  $f(S) = iI - 2i(S+I)^{-1}$  and differentiating Eq.(S1) w.r.t.  $E$  one obtains

$$\begin{aligned} S_{n+1}^{-1/2} \frac{dS_{n+1}}{dE} S_{n+1}^{-1/2} &= \Gamma_n^{-1} T_n^{-1/2} \frac{dT_n}{dE} T_n^{-1/2} (\Gamma_n^T)^{-1} \\ -2i \cos \Theta_{n+1} \frac{dA_{n+1}}{dE} \cos \Theta_{n+1}, \end{aligned} \quad (\text{S4})$$

where  $\Gamma_n = \cos \Phi_n (\cos \Theta_{n+1})^{-1}$ . From Eq.(S2) we find that

$$\frac{dT_n}{dE} = e^{i\hat{q}\delta L} \left( i \frac{d\hat{q}}{dE} S_n \delta L + i S_n \frac{d\hat{q}}{dE} \delta L + \frac{dS_n}{dE} \right) e^{i\hat{q}\delta L}. \quad (\text{S5})$$

Using this result and the fact that  $\frac{d\hat{q}}{dE} = (2\hat{q})^{-1}$  we can rewrite the term  $T_n^{-1/2} \frac{dT_n}{dE} T_n^{-1/2}$  in Eq.(S4) as

$$\begin{aligned} \frac{i}{2} T_n^{-1/2} e^{i\hat{q}\delta L} (\hat{q}^{-1} S_n + S_n \hat{q}^{-1}) e^{i\hat{q}\delta L} T_n^{-1/2} \delta L \\ + i T_n^{-1/2} e^{i\hat{q}\delta L} S_n^{1/2} Q_n S_n^{1/2} e^{i\hat{q}\delta L} T_n^{-1/2}, \end{aligned} \quad (\text{S6})$$

where we introduced the Wigner-Smith time delay matrix  $Q$  defined as

$$Q = -i S^{-1/2} \frac{dS}{dE} S^{-1/2}. \quad (\text{S7})$$

Now we can rewrite Eq.(S4) as a recursion relation for the  $Q$ -matrices:

$$Q_{n+1} = \Gamma_n^{-1} (J_n Q_n J_n^T + K_n) (\Gamma_n^T)^{-1} + R_n, \quad (\text{S8})$$

where the following matrices were introduced

$$\begin{aligned} J_n &= T_n^{-1/2} e^{i\hat{q}\delta L} S_n^{1/2}, \quad J_n J_n^T = I, \quad J_n^* = J_n, \\ K_n &= \frac{1}{2} T_n^{-1/2} e^{i\hat{q}\delta L} (\hat{q}^{-1} S_n + S_n \hat{q}^{-1}) e^{i\hat{q}\delta L} T_n^{-1/2} \delta L, \\ K_n^* &= K_n, \quad K_n^T = K_n \\ R_n &= -2 \cos \Theta_{n+1} \frac{dA_{n+1}}{dE} \cos \Theta_{n+1}, \\ R_n^* &= R_n, \quad R_n^T = R_n. \end{aligned}$$

It follows from the two symmetries of the scattering matrix  $S^T = S$  and  $S^\dagger = S^{-1}$ , that  $\Phi = \Phi^\dagger = \Phi^T$  and  $\Theta = \Theta^\dagger = \Theta^T$ , which implies that  $\Gamma^T = \Gamma^\dagger$ . Thus the transformation (S8) preserves both symmetries of the  $Q$ -matrix  $Q = Q^T$  and  $Q = Q^\dagger$ , as expected.

From Eq.(S3) one can find a useful representation for  $\Gamma_n$ .

$$\begin{aligned} \Gamma_n &= (I + \Delta_n)^{1/2} W_n, \quad (\text{S9}) \\ \Delta_n &\equiv -\sin \Phi_n A_{n+1} \cos \Phi_n - \cos \Phi_n A_{n+1} \sin \Phi_n \\ &\quad + \cos \Phi_n A_{n+1}^2 \cos \Phi_n, \quad \Delta_n^T = \Delta_n, \quad \Delta_n^* = \Delta_n \\ W_n &\equiv (I + \Delta_n)^{-1/2} \cos \Phi_n \\ &\quad \times \left( (\cos \Phi_n)^{-1} (I + \Delta_n) (\cos \Phi_n)^{-1} \right)^{1/2}, \\ W_n W_n^T &= I, \quad W_n^* = W_n. \end{aligned}$$

One can use this expression for  $\Gamma_n$  in Eq.(S8) in order to rewrite it as

$$W_n Q_{n+1} W_n^T = C_n (J_n Q_n J_n^T + K_n) C_n + H_n, \quad (\text{S10})$$

where  $C_n \equiv (I + \Delta_n)^{-1/2}$  and  $H_n \equiv W_n R_n W_n^T$ .

For the derivation of the Fokker-Planck equation, it is useful to introduce the rotated time delay matrix  $Z_n \equiv J_n Q_n J_n^T$ , for which the recursion relation takes the form

$$\begin{aligned} U_n Z_{n+1} U_n^T &= C_n (Z_n + K_n) C_n + W_n R_n W_n^T, \\ U_n &\equiv W_n J_n^T, \quad U_n U_n^T = I. \end{aligned} \quad (\text{S11})$$

We note that the matrices  $Z_n$  and  $Q_n$  have the same eigenvalues. Since  $K_n \sim \delta L$  and one should keep only the terms up to the first order in  $\delta L$ , we can rewrite the above equation as

$$U_n Z_{n+1} U_n^T = C_n (Z_n + \Gamma_n R_n \Gamma_n^T) C_n + K_n. \quad (\text{S12})$$

### DERIVATION OF THE FOKKER-PLANCK EQUATION

The evolution equation for the joint probability distribution function  $P_n(\{\tilde{\tau}_i\})$  of the eigenvalues  $\{\tilde{\tau}_i\}$  of the matrix  $Z_n$  can be derived from the recursion relation for  $Z_n$  using the second order perturbation theory.

According to Eq.(S12)

$$\begin{aligned} U_n Z_{n+1} U_n^T &= Z_n + \delta Z_n, \quad \delta Z_n = \delta Z_n^{(1)} + \delta Z_n^{(2)}, \\ \delta Z_n^{(1)} &\equiv C_n Z_n C_n - Z_n + K_n \\ \delta Z_n^{(2)} &\equiv C_n \Gamma_n R_n \Gamma_n^T C_n. \end{aligned} \quad (\text{S13})$$

One can show that the contribution from  $\delta Z_n^{(2)}$  has an extra factor of  $(\lambda_F/l)$  compared to the contribution from

$\delta Z_n^{(1)}$  and hence can be neglected for weak disorder. The contribution from  $\delta Z_n \equiv \delta Z_n^{(1)}$  must be expanded up to the linear term in  $\delta L$ . Recalling that  $C_n \equiv (I + \Delta_n)^{-1/2}$  and  $\Delta_n$  is defined in Eq.(S9), we notice that  $A \sim \overline{V}$  and  $\langle \overline{V} \rangle = 0$ ,  $\langle \overline{V}\overline{V}^T \rangle \sim \delta L$ , so that we should keep only the terms up to the second order in  $A$ . Thus we obtain

$$\delta Z_n = -\frac{1}{2}(\Delta_n Z_n + Z_n \Delta_n) + \frac{1}{4}(\Delta_n Z_n \Delta_n) + \frac{3}{8}(\Delta_n^2 Z_n + Z_n \Delta_n^2) + K_n + O(\delta L^2). \quad (\text{S14})$$

The eigenvalues  $\{\tilde{\tau}_i\}$  of  $Z_{n+1}$  are the same as the eigenvalues of  $Z_n + \delta Z_n$ .

$$Z_n = O_n D_n O_n^T, \quad D_n = \text{diag}(\{\tilde{\tau}_i^{(n)}\}), \quad (\text{S15})$$

$$Z_n + \delta Z_n = O_n (D_n + O_n^T \delta Z_n O_n) O_n^T, \quad (\text{S16})$$

$$\tilde{\tau}_i^{(n+1)} = \tilde{\tau}_i^{(n)} + \delta \tilde{\tau}_i, \quad (\text{S17})$$

where  $\tilde{\tau}_i^{(n)}$  are eigenvalues of  $Z_n$  and  $O_n$  is the matrix of its eigenvectors.

The joint probability distribution function  $P_{n+1}(\{\tilde{\tau}_i\})$  can be calculated as

$$P_{n+1} = \left\langle \prod_i \delta(\tilde{\tau}_i - \tilde{\tau}_i^{(n+1)}) \right\rangle = P_n - \left[ \sum_i \frac{\partial}{\partial \tilde{\tau}_i} \langle \delta \tilde{\tau}_i \rangle - \sum_{ik} \frac{\partial^2}{\partial \tilde{\tau}_i \partial \tilde{\tau}_k} \frac{\langle \delta \tilde{\tau}_i \delta \tilde{\tau}_k \rangle}{2} \right] P_n. \quad (\text{S18})$$

The averages  $\langle \delta \tilde{\tau}_i \rangle$  and  $\langle \delta \tilde{\tau}_i \delta \tilde{\tau}_k \rangle$  can be computed with the help of the perturbation theory. The first and second order results for the eigenvalues of  $D_n$  with the perturbation  $O_n^T \delta Z_n O_n$  are given by

$$\delta \tilde{\tau}_i = \langle i | O^T \delta Z O | i \rangle + \sum_{k \neq i} \frac{|\langle k | O^T \delta Z O | i \rangle|^2}{\tilde{\tau}_i - \tilde{\tau}_k}, \quad (\text{S19})$$

where  $\{|i\rangle\}$  is the standard basis in  $\mathbb{R}^N$  and we omit the index  $n$  for all variables.

Next the following steps should be taken. One substitutes  $Z = O D O^T$  and  $\delta Z$  from Eq.(S14) into Eq.(S18) and performs first averaging over the orthogonal matrix  $O$  and the COE matrix  $T = e^{2i\Phi}$ . For the latter averaging one uses the exact relations [1]

$$\langle \text{Tr} X T Y T^{-1} \rangle_T = \frac{1}{N+1} (\text{Tr} X \text{Tr} Y + \text{Tr} X Y^T), \quad (\text{S20})$$

$$\langle \text{Tr} X T \rangle_T = 0,$$

which hold for any matrices  $X$  and  $Y$ . For the averaging over the orthogonal group one has also the exact relation

$$\langle \text{Tr} X O Y O^T \rangle_O = \frac{1}{N} \text{Tr} X \text{Tr} Y. \quad (\text{S21})$$

Expressions involving four matrices  $O$  are calculated approximately for  $N \gg 1$  using the Gaussian approximation (the Wick's theorem) [2].

After the first step we are left only with the terms containing the eigenvalues  $\tilde{\tau}_i$  and two more terms  $\langle \text{Tr} A^2 \rangle$  and  $\text{Tr} \hat{q}^{-1}$  coming from the averaging of the terms involving  $\Delta$  and  $K$  respectively. For the former one we first average over the disordered potential  $V(\mathbf{r})$  and then calculate a sum over transverse momenta  $q_n$ . For the latter one we just calculate a sum over  $q_n$ . In the leading order in  $N$  the results are given by

$$\langle \text{Tr} A^2 \rangle = \frac{2N A_d \delta L}{l}, \quad \text{Tr} \hat{q}^{-1} = \frac{N A_d}{\sqrt{E}}, \quad (\text{S22})$$

where  $A_d \equiv \frac{\sqrt{\pi} \Gamma(\frac{d+1}{2})}{\Gamma(\frac{d}{2})}$ .

Finally, scaling the variables  $\tau = \frac{\tilde{\tau}}{\tau_s}$  and  $r = A_d \frac{l}{\tau}$  and taking the limit  $\delta L \rightarrow 0$ , one obtains the Fokker-Planck equation for the distribution function  $P(\{\tau_i\}, r)$

$$\frac{\partial P}{\partial r} = \frac{1}{N} \sum_i \frac{\partial}{\partial \tau_i} [(N-1)\tau_i - 2N - \sum_{k \neq i} \frac{\tau_i^2}{\tau_i - \tau_k} + \sum_k \frac{\partial}{\partial \tau_k} \left( \tau_i^2 \delta_{ik} + \frac{\tau_i \tau_k}{N} \right)] P. \quad (\text{S23})$$

Although  $1/N$  corrections were discarded in the derivation of this equation, we include such a correction to the first term on the r.h.s. for the following reason. Studying the moments  $\langle \tau^q \rangle$  directly from the recursion relation (S10), one can show that the relative values of the  $1/N$  corrections to the first and the third terms are constrained. By writing  $N-1$  instead of  $N$  in the first term one makes sure that this constraint is satisfied. In particular, it guarantees that there are no  $1/N$  corrections to the evolution of  $\langle \tau \rangle$ , as one expects from Eq.(S10).

## FAST AND SLOW VARIABLES

It is clear from the structure of Eq.(S1) that the main change of the  $S$ -matrix at each step of the recursion occurs due to the term  $e^{i\hat{q}\delta L}$ , describing the evolution of the  $S$ -matrix in the absence of disorder. Therefore a typical change of the  $S$ -matrix is governed by the parameter  $k_F \delta L = \frac{\delta L}{\lambda_F}$ . At the same time, Eq.(S10) suggests that there are two sources for the change of  $\tilde{\tau}$ : the additive one due to the  $K$  matrix and the multiplicative one due to the  $A^2$  matrix. Using the fact that  $\langle \text{Tr} K \rangle = \text{Tr} \hat{q}^{-1} \delta L$  and Eq.(S22) one can see that a typical change of  $\tilde{\tau}$  can be estimated as

$$\delta \tilde{\tau} \sim \frac{\delta L}{\sqrt{E}} + \frac{\delta L}{l} \tilde{\tau} \sim \frac{\delta L}{l} (\tilde{\tau} + \tau_s). \quad (\text{S24})$$

Since  $\frac{\delta L}{l} \ll \frac{\delta L}{\lambda_F}$  for weak disorder, we conclude that  $S$  is a fast variable, while  $\tilde{\tau}$  is a slow variable. The eigenvectors of  $Q$  are changed primarily due to the  $W$  and  $J$  matrices, whose definitions involve the  $S$ -matrix, and thus they

also should be considered as fast variables. The compact nature of the fast variables leads to their complete randomisation after their total change becomes of the order of unity, implying that the corresponding length scale is of the order of  $\lambda_F$ .

- [1] P. W. Brouwer and C. W. J. Beenakker, *J. Math. Phys.* **37**, 4904 (1996).
- [2] It should be possible to calculate such averages exactly using the method of Ref.[3].
- [3] T. Prosen, T.H. Seligman and H. A. Weidenmüller, *Europhys. Lett.* **55**, 12 (2001).

---

\* Electronic address: alexander.ossipov@nottingham.ac.uk