Generation of Single-mode Narrow-band Photons Resonant to Atomic Transitions

Amir Moqanaki,¹ Francesco Massa,¹ and Philip Walther¹

¹Vienna Center for Quantum Science and Technology (VCQ), Faculty of Physics,

and Research Platform TURIS, University of Vienna, Vienna, Austria

Hybrid quantum systems of photons and atoms are promising architectures with the immediate application for realizing two-qubit gates for quantum computations. Tailoring the spectral properties of photonic states is essential for realizing such systems. For this purpose, cavity-enhanced spontaneous parametric down-conversion (SPDC) is proven to be a successful technique. Here we demonstrate a bright source of narrow-band single photons employing a novel mode-selection technique, which allows for single-mode operation with very high spectral purity. We generate single-frequency-mode photons at 852 nm, resonant to Cs D2 line, with the bandwidth of 16 MHz and a spectral brightness of $257 \text{ s}^{-1}\text{mW}^{-1}\text{MHz}^{-1}$. Additionally, the lack of mode filters enables us to directly access double-pair emission for multi-photon generation. We observe a four-photon rate of 37 Hz at 20 mW of pump power. Our source realizes an important tool for applications involving hybrid light-matter quantum systems.

I. INTRODUCTION

Single photons are intriguing quantum systems. Their mobility, efficient detection, and ease of manipulation are very desirable features. These features make them the system of choice for observing many quantum phenomena^{1,2} and ideally suited for quantum information processing applications³⁻⁸. However, the lack of photon-photon interactions raises the challenge for implementing two-qubit gates⁹. On the other hand, interfacing single photons with the strong optical non-linearities provided in the matter-based quantum systems can effectively resolve this issue^{10,11}. Such rich hybrid quantum systems with the combined benefits of both photons and matter can realize sough-after quantum devices such as two-qubit gates¹², quantum memories¹³, quantum repeaters¹⁴, and eventually a full-scale quantum network 15 .

Spontaneous Parametric Down-Conversion (SPDC) has been widely used to generate high-purity single photons^{16,17} at broad range of frequencies with relatively easy experimental effort. In contrast to the other photon generation techniques^{18,19}, SPDC also allows for efficient heralding of the photons²⁰. Recent developments in periodic poling and laser-written waveguides have triggered the realization of bright, robust and tunable photon sources^{21,22}. The typical SPDC bandwidth ranges from hundreds of GHz to THz^{23,24}, but interfacing single photons with atoms demands a specific bandwidth in the order of MHz or less, thus making passive spectral filtering very inefficient.

It has been shown that an optical parametric oscillator (OPO) pumped well below threshold can emit single photons within the bandwidth of its cavity and greatly enhance the spectral brightness^{25,26}. Since the SPDC bandwidth is typically larger than the free-spectral range (FSR) of the enhancement cavity, the resulting source has a multi-mode spectral characteristic. Additional filters such as filter cavities^{27–30} and atomic line filters³¹ have been employed to suppress these unwanted modes. But this additional filtering stages come at the cost of photon loss and increased complexity of the setup.

There is another promising route: when signal and idler are simultaneously resonant in an OPO, and the two FSRs are not equal, the number of longitudinal modes is reduced. This effect is known as *clustering*^{32–35}. Exploiting this feature has recently gained attention and enabled narrow-band photon sources to eliminate unwanted modes^{36–38}.

In this work, we report a novel approach to reach doubly resonant condition by tuning the birefringence of the enhancement cavity. This is achieved by inserting an additional birefringent crystal in a type-II OPO. The measured number of longitudinal modes from our source is to our knowledge the lowest ever reported. Additionally, the cluster effect is tunable in a broad range of signal and idler frequencies, including the degenerate case. Our mode-selection scheme avoids photon losses due to additional filtering and this results into an enhanced detection rate, which even allows us to directly measure multi-photon emission from our source.

II. SINGLE-MODE OPERATION

From the theory of the SPDC process in periodicallypoled crystals, assuming a monochromatic pump, we can approximate the full-width at full-maximum of the emitted spectrum to^{23,24}:

$$\Delta \nu_{SPDC} \approx \frac{2c}{|n_s - n_i|L} \tag{1}$$

In which, c is the speed of light, L the crystal length, and n_s and n_i are the group indices for the signal and the idler photons. In the resonant case, the enhancement cavity only allows the crystal to emit photons at the resonant frequencies of the cavity. In type-II phase-matching or non-degenerate SPDC the two group indices are not equal, consequently signal and idler photons travel different optical paths inside the cavity. This results in two



FIG. 1. Cluster effect. Frequency modes for signal and idler allowed by the cavity $(FSR_s \neq FSR_i)$ in a comb-like structure are shown. The SPDC emission occurs only when both signal and idler are resonant (cluster effect). If the neighboring side modes partially overlap, each cluster will contain more than one mode. These additional modes can be suppressed in a sufficiently highfinesse cavity.

sets of resonance modes, one for the signal and one for the idler, separated by different FSRs. There is double resonant condition when two modes from the different sets overlap. The resulting spectrum consists of *clusters* of modes instead of a comb-like pattern. The condition of full overlap is periodically repeated over the set of modes with a frequency period of $\Delta \nu_c$ (See Fig. 1). $\Delta \nu_c$ is greater than both FSR_s and FSR_i and is given by³²:

$$\Delta \nu_c = \frac{FSR_s \cdot FSR_i}{|FSR_s - FSR_i|} \tag{2}$$

If $\Delta \nu_c < \frac{1}{2} \Delta \nu_{SPDC}$ there is only one cluster in the SPDC spectrum. This can happen at specific frequencies of signal and idler, according to the considered parametric process³⁸. Changing the cluster separation independent of the phase-matching condition allows for single-longitudinal-mode operation at the desired frequencies. Adding another degree of freedom dedicated to tune $\Delta \nu_c$ can address this problem. This has already been partially investigated, by angle tuning of the SPDC crystal or exploiting the electro-optical effect³³. Yet these efforts have not been sufficient to fully suppress the unwanted longitudinal modes.

Now, assume we have a linear enhancement cavity with length d, containing an SPDC crystal with length L, a birefringent crystal -which we call *tunning crystal*-, with length L' and n'_s , n'_i group indices for signal and idler, and some air gap $(L_{gap} = d - L - L')$. By using Eq. 2, we obtain for the cluster separation in this arrangement:

$$\Delta\nu_c = \frac{c}{2|n_{s,i}L + n'_{s,i}L' + d - L - L'|}$$
(3)



FIG. 2. Narrowband single photon source. BS (beam splitter), PBS (polarizing beam splitter), HWP (half-wave plate), QWP (quarter-wave plate), DM (dichroic mirror), PD (photo diode), APD (avalanche photo diode), PPKTP (periodically-poled potassium titanyl phosphate), BBO (barium borate), SM Fiber (singlemode fiber), TTM (time-tagging module)

The additional degrees of freedom of the tuning crystal give us the possibility to achieve the cluster effect independent of the phase-matching condition. At the same time, this allows us to reach single-cluster operation. In order to obtain this, the parameters should satisfy the following condition:

$$\frac{1}{2} \frac{|n_s - n_i|}{|n'_s - n'_i|} \le \frac{L'}{L} < \frac{|n_s - n_i|}{|n'_s - n'_i|} \tag{4}$$

This procedure effectively reduces the number of clusters to one, but the central cluster can still contain more than one mode depending on the finesse of the cavity, as explained in Fig. 1. We can estimate a threshold for the average finesse, F, in order to ensure single-mode emission³⁸:

$$F > \frac{1}{2} \frac{FSR_i + FSR_s}{|FSR_i - FSR_s|} \tag{5}$$

III. EXPERIMENTAL REALIZATION

We show a schematic of the experimental realization of the source in Fig.2. The probe laser is stabilized to the Cs D2 line by polarization spectroscopy³⁹ and acts as the frequency reference. The pump laser is locked to the probe laser by frequency-offset locking technique⁴⁰. We have built our OPO in a linear, semi-hemispherical configuration. The out-coupling mirror is reflective for the pump beam (R ≈ 0.97 at 426 nm, T ≈ 0.03 at 852 nm). The in-coupler has a high reflection for the probe (R > 0.999 at 852 nm, $R \approx 0.57$ at 426 nm). The mirror reflectivities allow the pump to pass the crystal more than once. This effectively increases the crystal length.

The SPDC crystal is a 30-mm-long, type-II PPKTP crystal. The tuning crystal is a 15-mm-long BBO crystal. Both crystals are anti-reflection coated for 426 nm and 852 nm and are temperature-controlled with a precision better than 2 mK.

The cavity is about 60 mm long. We estimate $FSR_s \approx 1.56$ GHz and $FSR_i \approx 1.58$ GHz. According to Eq. 5, the minimum finesse to achieve single-mode operation is 81.

The cavity is locked to the probe laser by side-ofthe-fringe lock on transmission. We use two optical shutters to block the probe beam for 600 ms during the measurement cycles and prevent it from reaching the detectors. After separating signal and idler by a PBS, we couple the photons into single-mode fibers with 53 percent average coupling efficiency, and send them to the single-photon counting modules for detection and analysis. Our detectors have a typical full width at half maximum (FWHM) jitter of 350 ps and a combined jitter of 495 ps. The detectors read-out is recorded by a time-tagging module (TTM).

IV. CHARACTERIZATION AND RESULTS

Temporal correlations are powerful tools to characterize narrow-band photon sources and infer their spectral properties^{38,41-43}. The cross-correlation function $G^{(1,1)}(\tau)$ is proportional to the probability of detecting a signal photon at time t and an idler photon at time $t+\tau$. The FWHM of the cross-correlation temporal profile is defined as cross-correlation time and is inversely proportional to the bandwidth of the emitted photons. In case of a type-II SPDC resonant process we have³⁸:

$$G^{(1,1)}(\tau) = H(\tau)e^{-2\gamma_s\tau} + H(\tau)e^{2\gamma_i\tau}$$
(6)

where $H(\tau)$ is the Heaviside step function and $\gamma_{s,i}$ are the signal and idler decay rates in the cavity. We plot the measured cross-correlation in Fig. 3, together with a fit from Eq. 6. The results from the fit are shown in Table I. The decay rates are not equal because of the birefringence in the OPO, which is not fully compensated by the tuning crystal, as explained in the previous section.

From the decay times we can also estimate the finesse of the cavity 38

$$F_{s,i} = \frac{\pi}{1 - e^{-L_{s,i}/ct_{s,i}}}$$
(7)

In which $L_{s,i}$ are the single-trip optical paths of the signal and the idler photon in the cavity, and c is the

TABLE I. Experimental temporal correlations. Parameters are extracted from the experimental correlation measurements. The errors are estimated by simulating Poisson statistics of the detection counts. γ_s and γ_i (signal and idler decay rates) are the fit parameters for the cross-correlation function, marked by \star . $\gamma_s + \gamma_i$ (the auto-correlation decay rate) and N (number of modes) are the fit parameters for the auto-correlation function, marked by \circ . t_s and t_i (signal and idler decay times), τ_c (cross-correlation time), τ_{ac} (auto-correlation time), $\Delta\nu$ (bandwidth).

Parameter	Definition	Value
$g^{(2)}(0)$	0	2.0 ± 0.3
N	0	1.0 ± 0.3
$\Delta \nu$	$\sqrt{2}/2\pi\tau_c$	$16\pm6~\mathrm{MHz}$
γ_s	*	$0.06\pm0.02~{\rm ns}^{\text{-}1}$
γ_i	*	$0.05\pm0.02~{\rm ns}^{\text{-}1}$
$\gamma_s + \gamma_i$	0	$0.10\pm0.02~{\rm ns}^{\text{-}1}$
t_s	$1/2\gamma_s$	9 ± 4 ns
t_i	$1/2\gamma_i$	10 ± 4 ns
$ au_c$	$^{2}/e(t_{s}+t_{i})$	$14 \pm 5 \text{ ns}$
$ au_{ac}$	$4/\gamma_s + \gamma_i \approx \ln(2)/2\tau_c$	$39\pm10~\mathrm{ns}$



FIG. 3. Experimental cross-correlation. The delays are calculated from the coincidence time-tags recorded by the TTM. We normalize the counts to the maximum and correct for the accidentals and the dark counts. Each time bin has a width of 2.97 ns, which corresponds to six times the combined jitter of the detectors. The errorbars are calculated from the Poisson statistics of the photon counting. The fit function is an exponential (See Eq. 6) and the decay rates γ_s and γ_i are the fit parameters. The cross-correlation time is 14 ns, corresponding to the bandwidth of 16 MHz.

speed of light. Using the above expression, we obtain 86 and 102, as the finesse for the signal and the idler, respectively, which are both above the threshold for single-mode operation (See Eq. 5).

The auto-correlation function, $g^{(2)}(\tau)$ provides information about the statistics of the single SPDC fields. We measure it by splitting the signal arm with a 50:50 fiber beam splitter and recording the coincidences at the output port at the time delay τ , thus realizing an Hanbury Brown-Twiss interferometer.

Ideally, the auto-correlation function measured by a detection system with no jitter would always peak at 2, revealing the thermal statistics of the SPDC fields⁴⁴. However, given the jitter in the detectors, this holds true only for a single-frequency-mode photon source. In the multimode case $g^{(2)}(0) < 2$. It has been shown that the value of auto-correlation function at 0 delay gives the effective number of modes present in the cavity^{38,43}, N:

$$g^{(2)}(0) = 1 + \frac{1}{N} \tag{8}$$

The general expression for the auto-correlation when $\gamma_s \neq \gamma_i$ is given by³⁸:

$$g^{(2)}(\tau) = 1 + \frac{1}{N} \left[\frac{1}{\gamma_i - \gamma_s} e^{-\frac{\gamma_s + \gamma_i}{2} |\tau|} \times \left(\gamma_i e^{\frac{\gamma_i - \gamma_s}{2} |\tau|} - \gamma_s e^{\frac{\gamma_i - \gamma_s}{2} |\tau|} \right) \right]^2$$
(9)

We plot the measured auto-correlation in Fig. 4, together with a fit from Eq. 9. The results from the fit are shown in Table I. The auto-correlation function is expected to be symmetric and broader than the crosscorrelation function by a factor of 2.88 and our measurements result in 2.8, which is in good agreement with the expectation³⁸. From these results we conclude that we have single-frequency-mode operation^{38,43}.

Another important figure of merit is the value of heralded auto-correlation function at 0 delay, $G^{(2)}(0)$. This is a parameter quantifying the multi-photon emission from an SPDC source. It is measured in the same way as the auto-correlation, with the only difference that the detection of the first signal photon is heralded by a corresponding detection of an idler photon. It should be close to 0 for an ideal single-photon source without higher order emissions. We calculate $G^{(2)}(0)$ as¹⁶:

$$G^{(2)}(0) = \frac{2 \times C_{\rm H} \times CC_{\rm HAB}}{(CC_{\rm HA} + CC_{\rm HB})^2},\tag{10}$$

where $C_{\rm H}$ is the rate of single counts for the heralding photons, $CC_{\rm HAB}$ is the 3-fold coincidence between the heralding photon and the arms of the Hanbury Brown-Twiss interferometer, and $CC_{\rm HA}$, $CC_{\rm HB}$ are the 2-fold coincidences between the heralding photon and each of the arms of the the Hanbury Brown-Twiss interferometer independently. We measure the heralded auto-correlation at 1 mW of pump power to be 0.041 \pm 0.008. The error is calculated by averaging the count rates per second over 433 s.

Our mode selection technique allows for direct singlemode emission, and therefore does not require any additional filtering stage. This drastically reduces the losses and gives us the possibility to operate the source for



FIG. 4. Experimental auto-correlation. The delays are calculated from the coincidence time-tags recorded by the TTM. We normalize the counts to the value at far delays. The time bin size is 4.95 ns, which corresponds to ten times the combined jitter of our detectors. The errorbars are calculated from the Poisson statistics of the photon counting. The fit function is that of Eq. 9 and the fit parameters are $\gamma_s + \gamma_i$, and $\gamma_s - \gamma_i$ the sum and the difference of the decay rates of signal and idler, and N, the effective mode number. The auto-correlation is symmetric and visibly broader than the cross-correlation. The auto-correlation time is calculated from the fit to be 39 ns, 2.8 times larger than the cross-correlation time, close to the ideal value. The peak value at 0 delay is 2.0, corresponding to the single-frequency-mode operation of our source.



FIG. 5. Set-up for the measurement of the 4-fold coincidences. For the 4-fold coincidence measurement the pump power is increased and the double pairs are spatially separated by two 50:50 fiber beam splitters. The 4-fold coincidences are post-selected by the TTM.

multi-photon generation. In order to demonstrate this, we have inserted two 50:50 fiber BS in the signal and idler arm (See Fig. 5) and measured the 4-fold coincidence rate from our source, after post-selection. By increasing the pump power to 20 mW, we can directly observe a 4-fold coincidence rate of 0.28 Hz, after correcting for the accidentals (0.002 Hz). By taking into account the coupling and detection loss, and the transmission losses of the dichroic filters, we obtain a double-pair generation rate of 37 Hz. The recorded 2-fold coincidence rate at

this pump power is 7.1 KHz corrected for the accidentals. Factoring in the losses and normalizing the brightness, we reach a spectral brightness of $257 \text{ s}^{-1}\text{mW}^{-1}\text{MHz}^{-1}$.

V. CONCLUSIONS

Here we experimentally demonstrate a novel technique to efficiently generate narrow-bandwidth singlefrequency-mode photons, tuned to Cs atoms D2 line. We characterize the photon emission by analyzing the temporal correlations of the emitted photons, and verify their spectral properties. Furthermore, we show that our mode selection approach reduces the losses to the level that makes multi-photon generation accessible to experimental investigation. Our work sets a milestone for hybrid quantum systems of light and matter, which can unveil new prospects both in fundamental and applied quantum science. Furthermore, our results break the ground for

- ¹ M. Giustina, M. A. M. Versteegh, S. Wengerowsky, J. Handsteiner, A. Hochrainer, K. Phelan, F. Steinlechner, J. Kofler, J.-A. Larsson, C. Abellán, W. Amaya, V. Pruneri, M. W. Mitchell, J. Beyer, T. Gerrits, A. E. Lita, L. K. Shalm, S. W. Nam, T. Scheidl, R. Ursin, B. Wittmann, and A. Zeilinger, Phys. Rev. Lett. **115**, 250401 (2015).
- ² D. Bouwmeester, J.-W. Pan, K. Mattle, M. Eibl, H. Weinfurter, and A. Zeilinger, Nature **390**, 575 (1997).
- ³ A. Crespi, R. Osellame, R. Ramponi, D. J. Brod, E. F. Galvao, N. Spagnolo, C. Vitelli, E. Maiorino, P. Mataloni, and F. Sciarrino, Nature Photonics 7, 545 (2013).
- ⁴ M. A. Broome, A. Fedrizzi, S. Rahimi-Keshari, J. Dove, S. Aaronson, T. C. Ralph, and A. G. White, Science **339**, 794 (2013).
- ⁵ J. B. Spring, B. J. Metcalf, P. C. Humphreys, W. S. Kolthammer, X.-M. Jin, M. Barbieri, A. Datta, N. Thomas-Peter, N. K. Langford, D. Kundys, J. C. Gates, B. J. Smith, P. G. R. Smith, and I. A. Walmsley, Science (2012).
- ⁶ M. Tillmann, B. Dakić, R. Heilmann, S. Nolte, A. Szameit, and P. Walther, Nature Photonics **7**, 540 (2013).
- ⁷ P. Walther, K. J. Resch, T. Rudolph, E. Schenck, H. Weinfurter, V. Vedral, M. Aspelmeyer, and A. Zeilinger, Nature 434, 169 (2005).
- ⁸ S. Barz, E. Kashefi, A. Broadbent, J. F. Fitzsimons, A. Zeilinger, and P. Walther, Science **335**, 303 (2012).
- ⁹ E. Knill, R. Laflamme, and G. J. Milburn, nature **409**, 46 (2001).
- ¹⁰ Q. A. Turchette, C. J. Hood, W. Lange, H. Mabuchi, and H. J. Kimble, Physical Review Letters **75**, 4710 (1995).
- ¹¹ H. Schmidt and A. Imamoglu, Optics letters **21**, 1936 (1996).
- ¹² C. Hamsen, K. N. Tolazzi, T. Wilk, and G. Rempe, Physical review letters **118**, 133604 (2017).
- ¹³ B. Julsgaard, J. Sherson, J. I. Cirac, J. Fiurášek, and E. S. Polzik, Nature **432**, 482 (2004).
- ¹⁴ Z.-S. Yuan, Y.-A. Chen, B. Zhao, S. Chen, J. Schmiedmayer, and J.-W. Pan, Nature **454**, 1098 (2008).

future exploit of narrow-band multi-photon states.

VI. ACKNOWLEDGEMENTS

We would like to thank Kai-Hong Luo, Andreas Ahlrichs, Oliver Benson, and Morgan Mitchell for the useful discussions. We thank Fabian Laudenbach and the Austrian Institute of Technology (AIT) GmbH for kindly lending us their TTMs. We would like to thank European Commission under the project ErBeStA (No. 800942), Austrian Research Promotion Agency (FFG) through the QuantERA ERA-NET Cofund project HiPhoP, Austrian Science Fund (FWF) through the doctoral programme CoQuS (W1210), NaMuG (P30067-N36), and GRIPS (P30817-N36), University of Vienna via the Research Platform TURIS, and Red Bull GmbH for their generous support.

- ¹⁵ H. J. Kimble, Nature **453**, 1023 (2008).
- ¹⁶ R.-B. Jin, R. Shimizu, K. Wakui, H. Benichi, and M. Sasaki, Optics express **21**, 10659 (2013).
- ¹⁷ P. J. Mosley, J. S. Lundeen, B. J. Smith, P. Wasylczyk, A. B. URen, C. Silberhorn, and I. A. Walmsley, Physical Review Letters **100**, 133601 (2008).
- ¹⁸ P. Senellart, G. Solomon, and A. White, Nature nanotechnology **12**, 1026 (2017).
- ¹⁹ B. Rodiek, M. Lopez, H. Hofer, G. Porrovecchio, M. Smid, X.-L. Chu, S. Gotzinger, V. Sandoghdar, S. Lindner, C. Becher, et al., Optica 4, 71 (2017).
- ²⁰ M. D. Eisaman, J. Fan, A. Migdall, and S. V. Polyakov, Review of Scientific Instruments 82, 071101 (2011).
- ²¹ T. Zhong, F. N. Wong, T. D. Roberts, and P. Battle, Optics express **17**, 12019 (2009).
- ²² X.-C. Yao, T.-X. Wang, P. Xu, H. Lu, G.-S. Pan, X.-H. Bao, C.-Z. Peng, C.-Y. Lu, Y.-A. Chen, and J.-W. Pan, Nature photonics **6**, 225 (2012).
- ²³ B. E. Saleh, M. C. Teich, and B. E. Saleh, Fundamentals of photonics (Wiley New York, 2007).
- ²⁴ M. H. Rubin, D. N. Klyshko, Y. Shih, and A. Sergienko, Physical Review A 50, 5122 (1994).
- ²⁵ Z. Y. Ou and Y. J. Lu, Phys. Rev. Lett. 83, 2556 (1999).
- ²⁶ Y. J. Lu and Z. Y. Ou, Phys. Rev. A **62**, 033804 (2000).
- ²⁷ J. S. Neergaard-Nielsen, B. M. Nielsen, H. Takahashi, A. I. Vistnes, and E. S. Polzik, Opt. Express **15**, 7940 (2007).
- ²⁸ M. Scholz, F. Wolfgramm, U. Herzog, and O. Benson, Applied Physics Letters **91**, 191104 (2007).
- ²⁹ X.-H. Bao, Y. Qian, J. Yang, H. Zhang, Z.-B. Chen, T. Yang, and J.-W. Pan, Phys. Rev. Lett. **101**, 190501 (2008).
- ³⁰ A. Ahlrichs, C. Berkemeier, B. Sprenger, and O. Benson, Applied Physics Letters **103**, 241110 (2013).
- ³¹ F. Wolfgramm, Y. A. de Icaza Astiz, F. A. Beduini, A. Cerè, and M. W. Mitchell, Phys. Rev. Lett. **106**, 053602 (2011).
- ³² M. Ebrahim-Zadeh, Handbook of Optics 4 (2010).
- ³³ R. C. Eckardt, C. Nabors, W. J. Kozlovsky, and R. L. Byer, JOSA B 8, 646 (1991).

- ³⁴ A. Henderson, M. Padgett, F. Colville, J. Zhang, and M. Dunn, Optics communications **119**, 256 (1995).
- ³⁵ C. Nabors, S. Yang, T. Day, and R. Byer, JOSA B 7, 815 (1990).
- ³⁶ C.-S. Chuu, G. Yin, and S. Harris, Applied Physics Letters 101, 051108 (2012).
- ³⁷ M. Förtsch, G. Schunk, J. U. Fürst, D. Strekalov, T. Gerrits, M. J. Stevens, F. Sedlmeir, H. G. L. Schwefel, S. W. Nam, G. Leuchs, and C. Marquardt, Phys. Rev. A **91**, 023812 (2015).
- ³⁸ K.-H. Luo, H. Herrmann, S. Krapick, B. Brecht, R. Ricken, V. Quiring, H. Suche, W. Sohler, and C. Silberhorn, New Journal of Physics **17**, 073039 (2015).
- ³⁹ C. Pearman, C. Adams, S. Cox, P. Griffin, D. Smith, and I. Hughes, Journal of Physics B: Atomic, Molecular and Optical Physics **35**, 5141 (2002).
- ⁴⁰ U. Schünemann, H. Engler, R. Grimm, M. Weidemüller, and M. Zielonkowski, Review of Scientific Instruments **70**, 242 (1999).
- ⁴¹ M. Scholz, L. Koch, and O. Benson, Optics Communications 282, 3518 (2009).
- ⁴² M. Scholz, L. Koch, and O. Benson, Physical review letters 102, 063603 (2009).
- ⁴³ C. Clausen, F. Bussieres, A. Tiranov, H. Herrmann, C. Silberhorn, W. Sohler, M. Afzelius, and N. Gisin, New Journal of Physics **16**, 093058 (2014).
- ⁴⁴ Z.-Y. J. Ou, Multi-photon quantum interference, Vol. 43 (Springer, 2007).