

EM algorithm for stochastic hybrid systems

Masaaki Fukasawa

Graduate School of Engineering Science
Osaka University

560-8531, Osaka, Japan
fukasawa@sigmath.es.osaka-u.ac.jp

Abstract

A stochastic hybrid system, also known as a switching diffusion, is a continuous-time Markov process with state space consisting of discrete and continuous parts. We consider parametric estimation of the Q matrix for the discrete state transitions and of the drift coefficient for the diffusion part. First, we derive the likelihood function under the complete observation of a sample path in continuous-time. Then, extending a finite-dimensional filter for hidden Markov models developed by Elliott et al. (*Hidden Markov Models*, Springer, 1995) to stochastic hybrid systems, we derive the likelihood function and the EM algorithm under a partial observation where the continuous state is monitored continuously in time, while the discrete state is unobserved.

Keywords: partial observation; filtering; stochastic hybrid system.

1 Introduction

A stochastic hybrid system (SHS, hereafter), also known as a switching diffusion [5], is a continuous-time Markov process Z with state space $S = \{e_1, \dots, e_k\} \times \mathbb{R}^d$ consisting of both discrete and continuous parts, namely, $\{e_1, \dots, e_k\}$ and \mathbb{R}^d respectively. The elements $\{e_i\}$ are, without loss of generality, specified as the standard basis of \mathbb{R}^k in this article. Denoting by $\langle \cdot, \cdot \rangle$ the inner product of \mathbb{R}^k or \mathbb{R}^d , $\langle e_i, e_j \rangle = \delta_{ij}$, where δ_{ij} is Kronecker's delta. The discrete part of Z , denoted by X , is a step process with state space $\{e_1, \dots, e_k\}$ and "Q matrix" of the form $Q(Y_t) = [q_{ij}(Y_t)]$, where Y is the continuous part of Z . In other words,

$$P(X_{t+h} = e_j | X_t = e_i, Y_t = y) = (\delta_{ji} + q_{ji}(y))h + o(h) \quad (1)$$

as $h \rightarrow 0$. Here, $Q(y) = [q_{ij}(y)]$ is a Q matrix for each y , that is, $q_{ji}(y) \geq 0$ for $j \neq i$ and $\sum_{j \neq i} q_{ji}(y) = -q_{ii}(y)$ for all $y \in \mathbb{R}^d$. The continuous part Y is defined as the

solution of a stochastic differential equation

$$\dot{Y} = \mu(X, Y) + \epsilon \dot{W}$$

on \mathbb{R}^d for some \mathbb{R}^d -valued function μ , where $\epsilon > 0$ and \dot{W} is a d dimensional Gaussian white noise. The generator \mathcal{L} of the Markov process $Z = (X, Y)$ is given by

$$\mathcal{L}f(e_i, y) = \langle \mu, \nabla_y f \rangle(e_i, y) + \frac{1}{2} \epsilon^2 \Delta_y f(e_i, y) + \sum_{j=1}^k (f(e_j, y) - f(e_i, y)) \langle e_j, Q(y) e_i \rangle, \quad (2)$$

where ∇_y and Δ_y refer to the gradient and Laplacian operators respectively with respect to the variable y .

There is a huge amount of literature on the analysis and applications of SHS. See e.g., [5, 6, 14, 10, 9, 17] and the references therein. The author's motivation to study the SHS is its potential application to the analysis of certain single-molecule dynamics which have several hidden states with the switching rates depending on the (observable) position of the molecule [4]. In this article, our aim is to construct an estimation algorithm for the Q matrix $Q(y) = Q^\theta(y)$ and of the drift coefficient $\mu(z) = \mu^\theta(z)$ based on a continuous path of Y with X unobserved.

Our problem is closely related to filtering. Indeed, when Q does not depend on y , the system is a hidden Markov model, for which finite dimensional filters are given by Wonham [15] and Elliott et al. [3]. Dembo and Zeitouni [2] combined the filtering and the EM algorithm for parametric estimation under partial observations. Although the general case of our interest is beyond the framework of [2, 3], we observe in this article that the arguments in [2, 3] can be extended.

A general theory of filtering, estimation and related stochastic analysis is available in Liptser and Shiryaev [11, 12]. In general, an optimal filtering equation is infinite dimensional, which hampers its direct use in practice. Finite dimensional filters have been obtained in some cases (see Bain and Crisan [1]) including the hidden Markov model as mentioned above, of which the essential property is that the state space of the hidden process is finite. The literature of filtering is huge. Nevertheless, a filtering problem considers a signal (hidden) process of which the law is determined irrespectively of an observable process. On the other hand, our interest is in the case where a hidden process and an observable process are coupled.

In Section 2, we describe the basic properties of SHS as the solution of a martingale problem. In Section 3, we derive the likelihood function under complete observations of both X and Y on a time interval $[0, T]$. In Section 4, we consider the case where the discrete part X is unobservable, and construct a finite dimensional filter extending [3]. In Section 5, using the finite dimensional filter, we derive the likelihood function under the partial observation. In Section 6, extending [2, 3], we construct the EM algorithm for an exponential family under the partial observation.

2 A construction as a weak solution

Here we construct a SHS as a weak solution, that is, we construct a distribution on the path space $D([0, T]; S)$ which is a solution of the martingale problem with the generator (2).

A direct application of Theorem (5.2) of Stroock [13] provides the following.

Theorem 2.1 *Let μ be a bounded Borel function and q_{ij} , $1 \leq i, j \leq k$ be bounded continuous functions. Then, for any $z \in S$, there exists a unique probability measure P_z on $D([0, T]; S)$ such that $Z_0 = z$ and*

$$f(Z_t) - \int_0^t \mathcal{L}f(Z_s) ds$$

is a martingale under P_z for any $f \in C_0^{0,\infty}(\{e_1, \dots, e_k\} \times \mathbb{R}^d)$, where $Z : t \mapsto Z_t$ is the canonical map on $D([0, T]; S)$. Moreover, Z is a strong Markov process with $\{P_z\}_{z \in S}$.

The uniqueness part of Theorem 2.1 is important in this article. For the existence, we give below an explicit construction, which plays a key role to solve a filtering problem later.

First, we construct a SHS with $\mu = 0$ in a pathwise manner. Without loss of generality, assume $\epsilon = 1$. Note that Y is then a d dimensional Brownian motion. Let $(\Omega, \mathcal{F}, P^0)$ be a probability space on which a d dimensional Brownian motion Y and an i.i.d. sequence of exponential random variables $\{E_n\}$ that is independent of Y are defined. Conditionally on $Y = \{Y_t\}_{t \geq 0}$, a time-inhomogeneous continuous-time Markov chain X with (1) is defined using the exponential variables. More specifically, given $X_0 = e_i$, let

$$\tau_1 = \min_{1 \leq j \leq k} \tau_1^j, \quad \tau_1^j = \inf \left\{ t > 0; \int_0^t q_{ji}(Y_s) ds > E_j \right\}$$

and $X_t = X_0$ for $0 \leq t < \tau_1$, $X_{\tau_1} = e_j$ with $J = \operatorname{argmin} \tau_1^j$. The construction goes in a recursive manner; given $X_{\tau_n} = e_i$, let

$$\tau_{n+1} = \min_{1 \leq j \leq k} \tau_{n+1}^j, \quad \tau_{n+1}^j = \inf \left\{ t > \tau_n; \int_{\tau_n}^t q_{ji}(Y_s) ds > E_{nk+j} \right\}$$

and $X_t = X_{\tau_n}$ for $\tau_n \leq t < \tau_{n+1}$, $X_{\tau_{n+1}} = e_j$ with $J = \operatorname{argmin} \tau_{n+1}^j$. Properties of the exponential distribution verifies the following lemma.

Lemma 2.1 *Assume $q_{ij}(y)$ is bounded and continuous in $y \in \mathbb{R}^d$ for each (i, j) . Then,*

$$P^0(X_{t+h} = e_j | X_t = e_i, Y) = (\delta_{ji} + q_{ji}(Y_t))h + o(h) \quad (3)$$

and (1) with $P = P^0$.

By Itô's formula, for any $f \in C_b^{0,2}(\{e_1, \dots, e_k\} \times \mathbb{R}^d)$, we have

$$f(X_{t+h}, Y_{t+h}) = f(X_t, Y_t) + \int_t^{t+h} \langle \nabla_y f(X_s, Y_s), dY_s \rangle + \frac{1}{2} \epsilon^2 \int_t^{t+h} \Delta_y f(X_s, Y_s) ds + \sum_{t < s \leq t+h} (f(X_s, Y_s) - f(X_{s-}, Y_s)),$$

from which together with (1) it follows

$$\lim_{h \rightarrow 0} \frac{E^0[f(X_{t+h}, Y_{t+h}) | X_t = e_i, Y_t = y] - f(e_i, y)}{h} = \mathcal{L}^0 f(e_i, y),$$

where E^0 is the expectation under P^0 and $\mathcal{L}^0 f = \mathcal{L}f$ with $\mu = 0$ in (2). Note only this, we have also that

$$U_t^{0,f} := f(X_t, Y_t) - \int_0^t \mathcal{L}^0 f(X_s, Y_s) ds$$

is a martingale with respect to the filtration $\{\mathcal{F}_t\}$ generated by $Z = (X, Y)$. Even more importantly, Lemma 2.1 implies the following.

Lemma 2.2 *Under the same conditions of Lemma 2.1, for any function g on $\{e_1, \dots, e_k\}$,*

$$V_t^{0,g} := g(X_t) - \int_0^t \mathcal{L}^0 g(X_s) ds$$

is a martingale with respect to the natural filtration of X under the conditional probability measure given Y , where $\mathcal{L}^0 g = \mathcal{L}^0 f$ with $f(x, y) = g(x)$. In particular,

$$X_t - \int_0^t Q(Y_s) X_s ds$$

is a martingale under the conditional probability measure $P^0(\cdot | Y)$.

Remark 2.1 Lemma 2.2 will be the key to extend a finite dimensional filter developed in Chapter 8 of Elliott et al. [3]. The measure P^0 corresponds to \bar{P} in Chapter 8 of [3], under which X and Y are independent. In our framework, when Q depends on y , they are not independent anymore but still, Y is a Brownian motion. This, together with the martingale property in Lemma 2.2, enables us to compute conditional expectations in Theorem 4.1 below.

Now we construct a SHS for a general bounded Borel function μ . Let

$$\Lambda_T = \exp \left\{ \frac{1}{\epsilon^2} \int_0^T \langle \mu(X_t, Y_t), dY_t \rangle - \frac{1}{2\epsilon^2} \int_0^T |\mu(X_t, Y_t)|^2 dt \right\}. \quad (4)$$

By the boundedness of μ , Novikov's conditions is satisfied and so, Λ is an $\{\mathcal{F}_t\}$ -martingale under P^0 . Therefore,

$$\frac{dP}{dP^0} = \Lambda_T$$

defines a probability space $(\Omega, \mathcal{F}_T, P)$.

Theorem 2.2 Let $Q = [q_{ij}]$ be a Q matrix-valued bounded continuous function and μ be an \mathbb{R}^d -valued bounded Borel function. Under P , $Z = (X, Y)$ is a Markov process with generator (2). Further for any $f \in C_b^{0,2}(\{e_1, \dots, e_k\} \times \mathbb{R}^d)$,

$$U_t^f := f(Z_t) - \int_0^t \mathcal{L}f(Z_s) ds$$

is an $\{\mathcal{F}_t\}$ martingale.

Proof: By the Bayes formula,

$$E[f(Z_{t+h})|\mathcal{F}_t] = \frac{E^0[\Lambda_T f(Z_{t+h})|\mathcal{F}_t]}{E^0[\Lambda_T|\mathcal{F}_t]} = E^0 \left[\frac{\Lambda_{t+h}}{\Lambda_t} f(Z_{t+h})|\mathcal{F}_t \right].$$

Since

$$\frac{\Lambda_{t+h}}{\Lambda_t} = \exp \left\{ \frac{1}{\epsilon^2} \int_t^{t+h} \langle \mu(Z_s), dY_s \rangle - \frac{1}{2\epsilon^2} \int_t^{t+h} |\mu(Z_s)|^2 ds \right\}$$

and Z is Markov under P^0 , $E[f(Z_{t+h})|\mathcal{F}_t] = E[f(Z_{t+h})|Z_t]$, meaning that it is Markov under P as well. By Itô's formula,

$$d\Lambda_t = \frac{1}{\epsilon^2} \Lambda_t \mu(Z_t) dY_t$$

and

$$\begin{aligned} \Lambda_{t+h} f(Z_{t+h}) &= \Lambda_t f(Z_t) + \int_t^{t+h} f(Z_s) d\Lambda_s + \int_t^{t+h} \Lambda_s - dU_s^{0,f} \\ &\quad + \int_t^{t+h} \Lambda_s \mathcal{L}^0 f(Z_s) ds + \int_t^{t+h} \Lambda_s \langle \mu, \nabla_y f \rangle(Z_s) ds. \end{aligned}$$

Therefore,

$$\Lambda_{t+h} U_{t+h}^f = \Lambda_t U_t^f + \int_t^{t+h} U_s^f d\Lambda_s + \int_t^{t+h} \Lambda_s - dU_s^{0,f},$$

meaning that ΛU^f is a martingale under P^0 . The Bayes formula then implies that U^f is a martingale under P . In particular, the generator is given by \mathcal{L} . $////$

Corollary 2.1 Under the same condition of Theorem 2.2,

$$V_t := X_t - \int_0^t Q(Y_s) X_s ds$$

is an $\{\mathcal{F}_t\}$ -martingale.

By the uniqueness result of Theorem 2.1, the law of Z under P coincides with P_z with $z = Z_0$.

Remark 2.2 An extension to the case where ϵ depends on Y is straightforward under the nondegeneracy of ϵ and the well-posedness of the SDE

$$dY_t = \epsilon(Y, t)dW_t$$

(but with more tedious expressions). The key of our framework is the existence of an equivalent measure under which the law of Y is uniquely determined irrespectively of X . This property admits not only (1) but also (3), which as we will see is sufficient to follow the arguments in Elliott et al. [3] to derive a finite dimensional filter. Therefore the case where ϵ depends on X is fundamentally different.

3 The likelihood under complete observations

Here we consider a statistical model $\{P^\theta\}_{\theta \in \Theta}$ and derive the likelihood under complete observation of a sample path $Z = (X, Y)$ on a time interval $[0, T]$. For each $\theta \in \Theta$, P^θ denotes the distribution on $D([0, T]; S)$ induced by a Markov process Z with generator

$$\mathcal{L}^\theta f(e_i, y) = \langle \mu^\theta, \nabla_y f \rangle(e_i, y) + \frac{1}{2} \epsilon^2 \Delta_y f(e_i, y) + \sum_{j=1}^k (f(e_j, y) - f(e_i, y)) \langle e_j, Q^\theta(y) e_i \rangle,$$

where μ^θ is a family of \mathbb{R}^d -valued bounded Borel functions and $Q^\theta = [q_{ij}^\theta]$ is a family of Q matrix-valued bounded continuous functions. Note that $\epsilon > 0$ is almost surely identified from a path of Y by computing its quadratic variation. It is therefore assumed to be known hereafter. With a slight abuse of notation, we will use P^θ also to mean P (that is, the probability measure on Ω , not on $D([0, T]; S)$) when the true parameter is θ (that is, when $P^\theta = P \circ Z^{-1}$ with $\mu = \mu^\theta$ and $Q = Q^\theta$). We assume that the initial distribution $P^\theta \circ Z_0^{-1}$ is known and does not depend on θ .

Theorem 3.1 *Let $\theta, \theta_0 \in \Theta$ and assume that*

$$y \mapsto \frac{q_{ij}^\theta(y)}{q_{ij}^{\theta_0}(y)}, \quad y \mapsto \frac{q_{ij}^{\theta_0}(y)}{q_{ij}^\theta(y)}$$

are bounded for each (i, j) , where $0/0 = 1$. Then, P^θ is equivalent to P^{θ_0} , and the log likelihood

$$L_T(\theta, \theta_0) := \log \frac{dP^\theta}{dP^{\theta_0}}(\{Z_t\}_{t \in [0, T]})$$

is given by

$$\begin{aligned} L_T(\theta, \theta_0) = & \sum_{i \neq j} \left\{ \int_0^T \log \frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} dN_t^{ji} - \int_0^T (q_{ji}^\theta(Y_t) - q_{ji}^{\theta_0}(Y_t)) \langle X_t, e_i \rangle dt \right\} \\ & + \frac{1}{\epsilon^2} \int_0^T \langle \mu^\theta(Z_t) - \mu^{\theta_0}(Z_t), dY_t \rangle - \frac{1}{2\epsilon^2} \int_0^T (|\mu^\theta(Z_t)|^2 - |\mu^{\theta_0}(Z_t)|^2) dt, \end{aligned}$$

where N_t^{ji} is the counting process of the transition from e_i to e_j :

$$N_t^{ji} = \int_0^t \langle X_{s-}, e_i \rangle \langle e_j, dX_s \rangle. \quad (5)$$

Proof: A general representation of the density process can be found in Theorem III.5.19 of Jacod and Shiryaev [8]. For such a specific model as ours, a direct derivation is more elementary. It is standard but here given for the readers' convenience. Let

$$L_\tau^{ji} = \int_0^\tau \log \frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} dN_t^{ji} - \int_0^\tau (q_{ji}^\theta(Y_t) - q_{ji}^{\theta_0}(Y_t)) \langle X_t, e_i \rangle dt$$

and

$$\begin{aligned} L_\tau^0 &= \frac{1}{\epsilon^2} \int_0^\tau \langle \mu^\theta(Z_t) - \mu^{\theta_0}(Z_t), dY_t \rangle - \frac{1}{2\epsilon^2} \int_0^\tau (|\mu^\theta(Z_t)|^2 - |\mu^{\theta_0}(Z_t)|^2) dt \\ &= \frac{1}{\epsilon^2} \int_0^\tau \langle \mu^\theta(Z_t) - \mu^{\theta_0}(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle - \frac{1}{2\epsilon^2} \int_0^\tau |\mu^\theta(Z_t) - \mu^{\theta_0}(Z_t)|^2 dt. \end{aligned}$$

By Itô's formula,

$$\begin{aligned} \exp\{L_\tau^{ji}\} &= 1 - \int_0^\tau \exp\{L_t^{ji}\} (q_{ji}^\theta(Y_t) - q_{ji}^{\theta_0}(Y_t)) \langle X_t, e_i \rangle dt + \sum_{0 < t \leq \tau} (\exp\{L_t^{ji}\} - \exp\{L_{t-}^{ji}\}) \\ &= 1 + \int_0^\tau \exp\{L_{t-}^{ji}\} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) [dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt] \end{aligned}$$

and by (5),

$$dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt = \langle X_{t-}, e_i \rangle \langle e_j, dX_t - Q^{\theta_0}(Y_t) X_t dt \rangle. \quad (6)$$

Therefore, by Corollary 2.1, $\exp\{L^{ji}\}$ and $\exp\{L^0\}$ are orthogonal local martingales under P^{θ_0} . The assumed boundedness further implies that they are martingales. This implies that $\mathcal{E}_t := \exp\{L_t(\theta, \theta_0)\}$ is a martingale under P^{θ_0} .

Define $U^{\theta,f}$ by

$$U_t^{\theta,f} = f(Z_t) - f(Z_0) - \int_0^t \mathcal{L}^\theta f(Z_s) ds$$

for $f \in C_b^{0,2}$. If $\mathcal{E}U^{\theta,f}$ is a martingale under P^{θ_0} , it means that $U^{\theta,f}$ is a martingale under the probability measure P' defined by

$$\frac{dQ}{dP^{\theta_0}} = \mathcal{E}_T.$$

If this is true for any f , P' is the solution of the martingale problem with respect to the generator \mathcal{L}^θ and so, by Theorem 2.1, $P' = P^\theta$ and we get the result.

Therefore it only remains to show that $\mathcal{E}U^{\theta,f}$ is a martingale under P^{θ_0} for any $f \in C_b^{0,2}$. By Itô's formula,

$$\mathcal{E}_\tau U_\tau^{\theta,f} = \int_0^\tau \mathcal{E}_t dU_t^{\theta,f} + \int_0^\tau U_t^{\theta,f} d\mathcal{E}_t + \int_0^\tau \mathcal{E}_t \langle \mu^\theta - \mu^{\theta_0}, \nabla_y f \rangle (Z_t) dt + \sum_{0 < t \leq \tau} \Delta \mathcal{E}_t \Delta U_t^{\theta,f}$$

and

$$\Delta \mathcal{E}_t = \mathcal{E}_{t-} \sum_{i \neq j} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) (N_t^{ji} - N_{t-}^{ji}), \quad \Delta U_t^{\theta,f} = f(X_t, Y_t) - f(X_{t-}, Y_t).$$

Since

$$\Delta \mathcal{E}_t \Delta U_t^{\theta,f} = \mathcal{E}_{t-} \sum_{i \neq j} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) (N_t^{ji} - N_{t-}^{ji}) (f(e_j, Y_t) - f(e_i, Y_t)),$$

we have

$$\begin{aligned} & \sum_{0 < t \leq \tau} \Delta \mathcal{E}_t \Delta U_t^{\theta,f} \\ &= \int_0^\tau \mathcal{E}_{t-} \sum_{i \neq j} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) (f(e_j, Y_t) - f(e_i, Y_t)) dN_t^{ji} \\ &= \int_0^\tau \mathcal{E}_{t-} \sum_{i \neq j} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) (f(e_j, Y_t) - f(e_i, Y_t)) [dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt] \\ & \quad + \int_0^\tau \mathcal{E}_t \sum_{i \neq j} (q_{ji}^\theta(Y_t) - q_{ji}^{\theta_0}(Y_t)) (f(e_j, Y_t) - f(e_i, Y_t)) \langle X_t, e_i \rangle dt. \end{aligned}$$

Consequently, we have

$$\begin{aligned} \mathcal{E}_\tau U_\tau^{\theta,f} &= \int_0^\tau \mathcal{E}_t dU_t^{\theta,f} + \int_0^\tau U_t^{\theta,f} d\mathcal{E}_t \\ & \quad + \int_0^\tau \mathcal{E}_{t-} \sum_{i \neq j} \left(\frac{q_{ji}^\theta(Y_t)}{q_{ji}^{\theta_0}(Y_t)} - 1 \right) (f(e_j, Y_t) - f(e_i, Y_t)) [dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt], \end{aligned}$$

which is a martingale under P^{θ_0} by (6). ////

Theorem 3.1 provides a starting point of asymptotic theories. Let us discuss briefly the large sample asymptotics $T \rightarrow \infty$ as an example. Assume $\Theta \subset \mathbb{R}^n$ and the maps $\theta \mapsto \mu^\theta$ and $\theta \mapsto Q^\theta = [q_{ij}^\theta]$ are regular enough. Denote by $\dot{\mu}^\theta$ and \dot{q}_{ij}^θ their derivatives in θ . For $\theta_T = \theta_0 + uT^{-1/2}$, $u \in \mathbb{R}^n$, by the Taylor expansion,

we have

$$\begin{aligned}
& \int_0^T \log \frac{q_{ji}^{\theta_T}(Y_t)}{q_{ji}^{\theta_0}(Y_t)} dN_t^{ji} - \int_0^T (q_{ji}^{\theta_T}(Y_t) - q_{ji}^{\theta_0}(Y_t)) \langle X_t, e_i \rangle dt \\
& \approx \int_0^T \log \frac{q_{ji}^{\theta_T}(Y_t)}{q_{ji}^{\theta_0}(Y_t)} [dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt] - \frac{1}{2} \int_0^T \left| \log \frac{q_{ji}^{\theta_T}(Y_t)}{q_{ji}^{\theta_0}(Y_t)} \right|^2 q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt \\
& \approx \frac{1}{\sqrt{T}} \int_0^T \frac{\langle u, \dot{q}_{ji}^{\theta_0} \rangle}{q_{ji}^{\theta_0}}(Y_t) [dN_t^{ji} - q_{ji}^{\theta_0}(Y_t) \langle X_t, e_i \rangle dt] - \frac{1}{2T} \int_0^T \frac{|\langle u, \dot{q}_{ji}^{\theta_0} \rangle|^2}{q_{ji}^{\theta_0}}(Y_t) \langle X_t, e_i \rangle dt
\end{aligned}$$

and

$$\begin{aligned}
& \frac{1}{\epsilon^2} \int_0^T \langle \mu^{\theta_T}(Z_t) - \mu^{\theta_0}(Z_t), dY_t \rangle - \frac{1}{2\epsilon^2} \int_0^T (|\mu^{\theta_T}(Z_t)|^2 - |\mu^{\theta_0}(Z_t)|^2) dt \\
& = \frac{1}{\epsilon^2} \int_0^T \langle \mu^{\theta_T}(Z_t) - \mu^{\theta_0}(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle - \frac{1}{2\epsilon^2} \int_0^T |\mu^{\theta_T}(Z_t) - \mu^{\theta_0}(Z_t)|^2 dt \\
& \approx \frac{1}{\epsilon \sqrt{T}} \int_0^T \left\langle \langle u, \dot{\mu}^{\theta_0}(Z_t) \rangle, \frac{dY_t - \mu^{\theta_0}(Z_t) dt}{\epsilon} \right\rangle - \frac{1}{2\epsilon^2 T} \int_0^T |\langle u, \dot{\mu}^{\theta_0}(Z_t) \rangle|^2 dt.
\end{aligned}$$

Therefore, under the ergodic property (see Yin and Zhu [17]):

$$\begin{aligned}
& \frac{1}{T} \int_0^T \frac{|\langle u, \dot{q}_{ji}^{\theta_0} \rangle|^2}{q_{ji}^{\theta_0}}(Y_t) \langle X_t, e_i \rangle dt \rightarrow \int \frac{|\langle u, \dot{q}_{ji}^{\theta_0} \rangle|^2}{q_{ji}^{\theta_0}}(y) \langle x, e_i \rangle \pi(dx, dy), \\
& \frac{1}{T} \int_0^T |\langle u, \dot{\mu}^{\theta_0}(Z_t) \rangle|^2 dt \rightarrow \int |\langle u, \dot{\mu}^{\theta_0} \rangle|^2(x, y) \pi(dx, dy),
\end{aligned}$$

the martingale central limit theorem implies the Local Asymptotic Normality (LAN) property:

$$L_T(\theta_T, \theta_0) \rightarrow \langle u, N \rangle - \frac{1}{2} \langle u, I(\theta_0)u \rangle, \quad N \sim \mathcal{N}(0, I(\theta_0)),$$

where

$$I(\theta_0) = \int \sum_{i \neq j} \frac{\dot{q}_{ji}^{\theta_0} (\dot{q}_{ji}^{\theta_0})^\perp}{q_{ji}^{\theta_0}}(y) \langle x, e_i \rangle + \frac{1}{\epsilon^2} \dot{\mu}^{\theta_0} (\dot{\mu}^{\theta_0})^\perp(x, y) \pi(dx, dy)$$

and π is the ergodic distribution. Under the non-degeneracy of $I(\theta_0)$, the LAN implies the asymptotic efficiency of a Maximum Likelihood Estimator (MLE), with asymptotic variance $I(\theta_0)^{-1}$; see Ibragimov and Has'minskii [7] for the detail.

4 A finite-dimensional filter

Here we extend the filtering theory of hidden Markov models developed in Chapter 8 of Elliott et al. [3] to the SHS

$$\begin{aligned} dX_t &= Q(Y_t)X_t dt + dV_t, \\ dY_t &= \mu(X_t, Y_t)dt + \epsilon dW_t, \end{aligned}$$

where V is an $\{\mathcal{F}_t\}$ -martingale (recall Corollary 2.1). Denoting $\langle e_i, \mu(e_j, y) \rangle = c_{ij}(y)$, $C(y) = [c_{ij}(y)]$, we can write $\mu(X_s, Y_s) = C(Y_s)X_s$. In this section we assume we observe only a continuous sample path Y on a time interval $[0, T]$ while X is hidden. The system is a hidden Markov model in [3] when both Q and μ do not depend on Y . By the dependence, V is not independent of W and so, it is beyond the framework of [3]. We however show in this and the next sections that the results in Chapter 8 of [3] remain valid. Namely, a finite-dimensional filter and the EM algorithm can be constructed for the SHS. A key for this is Lemma 2.2.

Denote by \mathcal{F}^Y the natural filtration of Y . The filtering problem is to infer X from the observation of Y , that is, to compute $E[X_t | \mathcal{F}_t^Y]$. The smoothing problem is to compute $E[X_t | \mathcal{F}_T^Y]$ for $t \leq T$. Denote $E_t^0[H] = E^0[H | \mathcal{F}_t^Y]$ for a given integrable random variable H , where E^0 is the expectation under P^0 in Section 2. For a given process H , the Bayes formula gives

$$E[H_t | \mathcal{F}_t^Y] = \frac{E_t^0[\Lambda_t H_t]}{E_t^0[\Lambda_t]}, \quad (7)$$

where Λ is defined by (4). Theorem 4.2 below shows that both the numerator and denominator of (7) for $H_t = X_t$ can be computed by solving a linear equation.

Theorem 4.1 *Under the same conditions of Theorem 2.2, if H is of the form*

$$dH_t = \alpha_t dt + \langle \beta_t, dX_t \rangle + \langle \delta_t, dY_t \rangle, \quad (8)$$

where α, β, δ are bounded predictable processes, then

$$\begin{aligned} E_t^0[\Lambda_t H_t] &= H_0 + \frac{1}{\epsilon^2} \int_0^t \langle C(Y_s) E_s^0[\Lambda_s H_s X_s] + \epsilon^2 E_s^0[\Lambda_s \delta_s], dY_s \rangle \\ &+ \int_0^t E_s^0[\Lambda_s \alpha_s] + E_s^0[\Lambda_s \langle \beta_s, Q(Y_s) X_{s-} \rangle] + E_s^0[\Lambda_s \langle \delta_s, C(Y_s) X_s \rangle] ds. \end{aligned} \quad (9)$$

Proof: Itô's formula gives

$$\Lambda_t H_t = H_0 + \int_0^t H_{s-} d\Lambda_s + \int_0^t \Lambda_s dH_s + \int_0^t \Lambda_s \langle \delta_s, \mu(Z_s) \rangle ds.$$

Take the conditional expectation under P^0 given \mathcal{F}_t^Y to get (9). Here, we have used the fact that Y/ϵ is a d dimensional Brownian motion under P^0 as well as Lemma 2.2. ////

Theorem 4.2 Under the same conditions of Theorem 2.2,

$$E_t^0[\Lambda_t X_t] = X_0 + \frac{1}{\epsilon^2} \int_0^t \text{diag}(E_s^0[\Lambda_s X_s]) C(Y_s)^\perp dY_s + \int_0^t Q(Y_s) E_s^0[\Lambda_s X_s] ds \quad (10)$$

and

$$E_t^0[\Lambda_t] = \langle \mathbf{1}, E_t^0[\Lambda_t X_t] \rangle = 1 + \frac{1}{\epsilon^2} \int_0^t \langle C(Y_s) E_s^0[\Lambda_s X_s], dY_s \rangle. \quad (11)$$

Proof: For each $i = 1, \dots, k$, let $H_t = \langle e_i, X_t \rangle$ in (9) to get

$$\begin{aligned} & \langle e_i, E_t^0[\Lambda_t X_t] \rangle \\ &= \langle e_i, X_0 \rangle + \frac{1}{\epsilon^2} \int_0^t \langle e_i, E_s^0[\Lambda_s X_s] \rangle \langle C(Y_s) e_i, dY_s \rangle + \int_0^t \langle e_i, Q(Y_s) E_s^0[\Lambda_s X_s] \rangle ds, \end{aligned}$$

which is equivalent to (10). Here we have used that $\langle e_i, X_s \rangle X_s = \langle e_i, X_s \rangle e_i$. The first identity of (11) is by $\langle \mathbf{1}, X_t \rangle = 1$. To get the second identity, use the first and (10), or alternatively, let $H_t = 1$ in (9). ////

The smoothing problem is also solved as follows.

Theorem 4.3 Under the same conditions of Theorem 2.2, for $t \geq \tau$,

$$E_t^0[\Lambda_t X_t] = E_\tau^0[\Lambda_\tau X_\tau] + \frac{1}{\epsilon^2} \int_\tau^t \text{diag}(E_s^0[\Lambda_s X_s]) C(Y_s)^\perp dY_s.$$

Proof: Let $H_t = \langle e_i, X_{t \wedge \tau} \rangle$ in (9) to get

$$\langle e_i, E_t^0[\Lambda_t X_t] \rangle = \langle e_i, E_\tau^0[\Lambda_\tau X_\tau] \rangle + \frac{1}{\epsilon^2} \int_\tau^t \langle e_i, E_s^0[\Lambda_s X_s] \rangle \langle C(Y_s) e_i, dY_s \rangle$$

for $t \geq \tau$. ////

5 The likelihood under partial observations

Here we consider again the parametric family $\{P^\theta\}$ introduced in Section 3. We assume that a continuous sample path Y is observed on a time interval $[0, T]$ while X is hidden. Under the same assumptions as in Theorem 3.1, the law of Y under P^θ is equivalent to that under P^{θ_0} and the log likelihood function is given by

$$L^Y(\theta, \theta_0) = \log E^{\theta_0} \left[\frac{dP^\theta}{dP^{\theta_0}} \Big| \mathcal{F}_T^Y \right]. \quad (12)$$

A MLE is therefore given by

$$\hat{\theta} = \operatorname{argmax}_{\theta \in \Theta} L^Y(\theta, \theta_0).$$

Note that $\hat{\theta}$ does not depend on the choice of θ_0 because by the Bayes formula,

$$\begin{aligned} L^Y(\theta, \theta_0) &= \log E^{\theta_1} \left[\frac{dP^{\theta_0}}{dP^{\theta_1}} \frac{dP^\theta}{dP^{\theta_0}} \middle| \mathcal{F}_T^Y \right] - \log E^{\theta_1} \left[\frac{dP^{\theta_0}}{dP^{\theta_1}} \middle| \mathcal{F}_T^Y \right] \\ &= L^Y(\theta, \theta_1) - L^Y(\theta_0, \theta_1) \end{aligned} \quad (13)$$

for any $\theta_1 \in \Theta$.

Here we show that the likelihood function can be obtained as a solution of a linear filtering equation. Let

$$H_t = \frac{dP^\theta}{dP^{\theta_0}} \Big|_{\mathcal{F}_t} = \exp(L_t(\theta, \theta_0)).$$

By Theorem 3.1, we have

$$\begin{aligned} dH_t &= H_{t-} \left\{ \langle R^{\theta, \theta_0}(Y_t) X_{t-}, dX_t - Q^{\theta_0}(Y_t) X_t dt \rangle \right. \\ &\quad \left. + \frac{1}{\epsilon^2} \langle (C^\theta(Y_t) - C^{\theta_0}(Y_t)) X_t, dY_t - C^{\theta_0}(Y_t) X_t dt \rangle \right\}, \end{aligned}$$

where

$$R^{\theta, \theta_0}(Y_t) = [r_{ij}^{\theta, \theta_0}(Y_t)], \quad r_{ij}^{\theta, \theta_0}(Y_t) = \begin{cases} \frac{q_{ij}^\theta}{q_{ij}^{\theta_0}}(Y_t) - 1, & i \neq j \\ 0, & i = j. \end{cases}$$

The likelihood function under the partial observation of $\{Y_t\}_{t \in [0, T]}$ is given by

$$\exp(L^Y(\theta, \theta_0)) = E^{\theta_0} [H_T | \mathcal{F}_T^Y] = \frac{E_T^0[\Lambda_T H_T]}{E_T^0[\Lambda_T]}. \quad (14)$$

Both the numerator and denominator are computed as follows.

Theorem 5.1 *Under the same conditions of Theorem 3.1, for $t \in [0, T]$,*

$$E_t^0[\Lambda_t H_t] = \langle \mathbf{1}, E_t^0[\Lambda_t H_t X_t] \rangle = 1 + \frac{1}{\epsilon^2} \int_0^t \langle C^\theta(Y_s) E_s^0[\Lambda_s H_s X_s], dY_s \rangle \quad (15)$$

and

$$\begin{aligned} E_t^0[\Lambda_t H_t X_t] &= X_0 + \frac{1}{\epsilon^2} \int_0^t \text{diag}(E_s^0[\Lambda_s H_s X_s]) C^\theta(Y_s)^\perp dY_s + \int_0^t Q^\theta(Y_s) E_s^0[\Lambda_s H_s X_s] ds. \end{aligned} \quad (16)$$

Proof: Since

$$\begin{aligned} \Delta H_t \langle e_i, \Delta X_t \rangle &= H_{t-} \sum_{j,l=1}^k \langle X_{t-}, e_l \rangle r_{jl}^{\theta, \theta_0}(Y_t) \langle e_j, \Delta X_t \rangle \langle e_i, \Delta X_t \rangle \\ &= H_{t-} \left\{ - \sum_{j=1}^k \langle X_{t-}, e_j \rangle r_{jj}^{\theta, \theta_0}(Y_t) \langle e_j, \Delta X_t \rangle + \sum_{l=1}^k \langle X_{t-}, e_l \rangle r_{ll}^{\theta, \theta_0}(Y_t) \langle e_i, \Delta X_t \rangle \right\} \\ &= H_{t-} \left\{ - \langle X_{t-}, e_i \rangle \langle R^{\theta, \theta_0} X_{t-}, \Delta X_t \rangle + \langle e_i, R^{\theta, \theta_0}(Y_t) X_{t-} \rangle \langle e_i, \Delta X_t \rangle \right\}, \end{aligned}$$

applying Theorem 4.1 with

$$\begin{aligned}\alpha_t &= -\langle e_i, X_t \rangle H_t \left\{ \langle R^{\theta, \theta_0}(Y_t) X_t, Q^{\theta_0}(Y_t) X_t \rangle + \frac{1}{\epsilon^2} \langle (C^\theta(Y_t) - C^{\theta_0}(Y_t)) X_t, C^{\theta_0}(Y_t) X_t \rangle \right\}, \\ \beta_t &= H_{t-} e_i + H_{t-} \langle e_i, R^{\theta, \theta_0}(Y_t) X_{t-} \rangle e_i, \\ \delta_t &= \frac{1}{\epsilon^2} \langle e_i, X_t \rangle H_t (C^\theta(Y_t) - C^{\theta_0}(Y_t)) X_t,\end{aligned}$$

we obtain, using $\langle e_i, X_s \rangle X_s = \langle e_i, X_s \rangle e_i$ again and again,

$$\begin{aligned}\langle e_i, E_t^0[\Lambda_t H_t X_t] \rangle &= \langle e_i, X_0 \rangle + \frac{1}{\epsilon^2} \int_0^t \langle e_i, E_s^0[\Lambda_s H_s X_s] \rangle \langle C^\theta(Y_s) e_i, dY_s \rangle \\ &\quad + \int_0^t E_s^0[\Lambda_s \alpha_s] + E_s^0[\Lambda_s \langle \beta_s, Q^{\theta_0}(Y_s) X_{s-} \rangle] + E_s^0[\Lambda_s \langle \delta_s, C^{\theta_0}(Y_s) X_s \rangle] ds \\ &= \langle e_i, X_0 \rangle + \frac{1}{\epsilon^2} \int_0^t \langle e_i, E_s^0[\Lambda_s H_s X_s] \rangle \langle C^\theta(Y_s) e_i, dY_s \rangle \\ &\quad - \int_0^t \langle R^{\theta, \theta_0}(Y_s) e_i, Q^{\theta_0}(Y_s) e_i \rangle \langle e_i, E_s^0[\Lambda_s H_s X_s] \rangle ds \\ &\quad + \int_0^t E_s^0[\Lambda_s H_s (\langle e_i, Q^{\theta_0}(Y_s) X_s \rangle + \langle e_i, R^{\theta, \theta_0}(Y_s) X_s \rangle \langle e_i, Q^{\theta_0}(Y_s) X_s \rangle)] ds.\end{aligned}$$

Since

$$\langle R^{\theta, \theta_0}(Y_s) e_i, Q^{\theta_0}(Y_s) e_i \rangle = \sum_{j=1} r_{ji}^{\theta, \theta_0}(Y_s) q_{ji}^{\theta_0}(Y_s) = \sum_{j \neq i} (q_{ji}^\theta - q_{ji}^{\theta_0})(Y_s) = -(q_{ii}^\theta - q_{ii}^{\theta_0})(Y_s)$$

and

$$\begin{aligned}\langle e_i, R^{\theta, \theta_0}(Y_s) X_s \rangle \langle e_i, Q^{\theta_0}(Y_s) X_s \rangle &= \sum_{j=1}^k \langle e_i, R^{\theta, \theta_0}(Y_s) e_j \rangle \langle e_i, Q^{\theta_0}(Y_s) e_j \rangle \langle e_j, X_s \rangle \\ &= \sum_{j \neq i} \langle e_i, (Q^\theta(Y_t) - Q^{\theta_0}(Y_s)) e_j \rangle \langle e_j, X_s \rangle \\ &= \langle e_i, (Q^\theta(Y_t) - Q^{\theta_0}(Y_s)) X_s \rangle - (q_{ii}^\theta(Y_t) - q_{ii}^{\theta_0}(Y_s)) \langle e_i, X_s \rangle,\end{aligned}$$

we conclude the linear equation

$$\begin{aligned}\langle e_i, E_t^0[\Lambda_t H_t X_t] \rangle &= \langle e_i, X_0 \rangle + \frac{1}{\epsilon^2} \int_0^t \langle e_i, E_s^0[\Lambda_s H_s X_s] \rangle \langle C^\theta(Y_s) e_i, dY_s \rangle \\ &\quad + \int_0^t \langle e_i, Q^\theta(Y_s) E_s^0[\Lambda_s H_s X_s] \rangle ds,\end{aligned}$$

which is equivalent to (16). Then, (15) follows from $\langle \mathbf{1}, X_t \rangle = 1$.

////

Corollary 5.1 Let $L^Y(\theta, \theta_0)$ be the log likelihood function defined by (12), and

$$\hat{\mu}_t^\theta = E^\theta[\mu^\theta(Z_t)|\mathcal{F}_t^Y].$$

Then,

$$\begin{aligned} L^Y(\theta, \theta_0) &= \frac{1}{\epsilon^2} \int_0^T \langle \hat{\mu}_t^\theta - \hat{\mu}_t^{\theta_0}, dY_t \rangle - \frac{1}{2\epsilon^2} \int_0^T |\hat{\mu}_t^\theta|^2 - |\hat{\mu}_t^{\theta_0}|^2 dt \\ &= \frac{1}{\epsilon^2} \int_0^T \langle \hat{\mu}_t^\theta - \hat{\mu}_t^{\theta_0}, dY_t - \hat{\mu}_t^{\theta_0} dt \rangle - \frac{1}{2\epsilon^2} \int_0^T |\hat{\mu}_t^\theta - \hat{\mu}_t^{\theta_0}|^2 dt. \end{aligned}$$

Proof: First we should note that this representation is valid in a more general framework than the stochastic hybrid system. Indeed, by Theorem 7.12 of Liptser and Shiryaev [11],

$$\hat{W}_t = \frac{1}{\epsilon} \left\{ Y_t - \int_0^t \hat{\mu}_s^\theta ds \right\}$$

is an $\{\mathcal{F}_t^Y\}$ -Brownian motion under P^θ . Since

$$dY_t = \hat{\mu}_t^\theta dt + \epsilon d\hat{W}_t, \quad (17)$$

the result follows from the Girsanov-Maruyama theorem. Here we derive it as a corollary of Theorem 5.1. By (14), we have

$$L^Y(\theta, \theta_0) = \log E_T^0[\Lambda_T H_T] - \log E_T^0[\Lambda_T],$$

and by Itô's formula and (15),

$$\begin{aligned} d \log E_t^0[\Lambda_t H_t] &= \frac{1}{\epsilon^2} \left\langle C^\theta(Y) \frac{E_t^0[\Lambda_t H_t X_t]}{E_t^0[\Lambda_t H_t]}, dY_t \right\rangle - \frac{1}{2\epsilon^2} \left| C^\theta(Y) \frac{E_t^0[\Lambda_t H_t X_t]}{E_t^0[\Lambda_t H_t]} \right|^2 dt \\ &= \frac{1}{\epsilon^2} \langle C^\theta(Y) E^\theta[X_t | \mathcal{F}_t^Y], dY_t \rangle - \frac{1}{2\epsilon^2} |C^\theta(Y) E^\theta[X_t | \mathcal{F}_t^Y]|^2 dt. \end{aligned}$$

Similarly, we obtain

$$d \log E_t^0[\Lambda_t] = \frac{1}{\epsilon^2} \langle C^{\theta_0}(Y) E^{\theta_0}[X_t | \mathcal{F}_t^Y], dY_t \rangle - \frac{1}{2\epsilon^2} |C^{\theta_0}(Y) E^{\theta_0}[X_t | \mathcal{F}_t^Y]|^2 dt$$

and conclude the result. ////

By (15), (16), (17), and

$$\hat{\mu}_t^\theta = C^\theta(Y_t) E^\theta[X_t | \mathcal{F}_t^Y] = C^\theta(Y_t) \frac{\bar{X}_t^\theta}{\langle \mathbf{1}, \bar{X}_t^\theta \rangle}, \quad \bar{X}_t^\theta = E_t^0[\Lambda_t H_t X_t],$$

we observe that our model is translated to a path-dependent diffusion model

$$\begin{aligned} dY_t &= C^\theta(Y_t) \frac{\bar{X}_t^\theta}{\langle \mathbf{1}, \bar{X}_t^\theta \rangle} dt + \epsilon d\hat{W}_t, \\ d\bar{X}_t^\theta &= Q^\theta(Y_t) \bar{X}_t^\theta dt + \frac{1}{\epsilon^2} \text{diag}(\bar{X}_t^\theta) C^\theta(Y_t)^\perp dY_t. \end{aligned}$$

This representation would serve as a starting point of a theory of asymptotic statistics, which however remains for future research. In particular, specifications of an appropriate ergodicity condition, an identifiability condition, and the asymptotic variance of a MLE remain open. Nevertheless, having the complete observation counterpart in our mind (see Section 3), it would be natural to expect a MLE to work reasonably well also under the partial observation. In the sequel, we focus on a computational issue of a MLE.

An apparent computational problem to obtain a MLE:

$$\hat{\theta} = \operatorname{argmax}_{\theta \in \Theta} L^Y(\theta, \theta_0) = \operatorname{argmax}_{\theta \in \Theta} \langle \mathbf{1}, \bar{X}_T^\theta \rangle$$

is that the associated numerical maximization is time-consuming, due to that the evaluation of the objective function requires to solve a different filtering equation for each θ . For some cases however an efficient algorithm is available as will be seen in the next section.

6 The EM algorithm

The EM algorithm is a well-known technique which is often useful when a likelihood function is not easily computable. Let us recall the idea of the EM algorithm. Let

$$Q(\theta^*, \theta) = E^\theta \left[\log \frac{dP^{\theta^*}}{dP^\theta} \middle| \mathcal{F}_T^Y \right].$$

By Jensen's inequality and (13),

$$Q(\theta^*, \theta) \leq \log E^\theta \left[\frac{dP^{\theta^*}}{dP^\theta} \middle| \mathcal{F}_T^Y \right] = L^Y(\theta^*, \theta) = L^Y(\theta^*, \theta_0) - L^Y(\theta, \theta_0), \quad (18)$$

which means that the sequence defined by

$$\theta_{n+1} = \operatorname{argmax}_{\theta \in \Theta} Q(\theta, \theta_n)$$

makes $L^Y(\theta_n, \theta_0)$ increasing. Under an appropriate condition the sequence $\{\theta_n\}$ converges to a MLE $\hat{\theta}$, for which we refer to Wu [16]. See also Dembo and Zeitouni [2]. As easily seen from (18), a MLE is a stationary point of the EM algorithm in general. However in general, there might be many stationary points other than a MLE and so, as in many other optimization problems, one would need to examine results with various initial parameters θ_0 .

The EM algorithm is particularly effective when the statistical model in question is an exponential family under complete observations. Let us consider the case where $Q^\theta(y) = [q_{ji}^\theta(y)]$ and $C^\theta(y)$ are of the form

$$q_{ji}^\theta(y) = \varphi_{ji}(\theta)q_{ji}^0(y), \quad \mu^\theta(z) = \sum_{l=1}^L \psi_l(\theta)\mu^l(z)$$

for some functions $\varphi_{ji}, \psi_l : \Theta \rightarrow \mathbb{R}$ and $k \times k$ Q-matrix $Q^0(y) = [q_{ji}^0(y)]$ and $\mu^l : S \mapsto \mathbb{R}^d, l = 1, \dots, L$. The log likelihood under the complete observation (see Theorem 3.1) is then

$$\begin{aligned} L_T(\theta, \theta_0) &= \sum_{i \neq j} \left\{ N_T^{ji} \log \frac{\varphi_{ji}(\theta)}{\varphi_{ji}(\theta_0)} - \left(\frac{\varphi_{ji}(\theta)}{\varphi_{ji}(\theta_0)} - 1 \right) \int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt \right\} \\ &\quad + \frac{1}{\epsilon^2} \sum_{l=1}^L (\psi_l(\theta) - \psi_l(\theta_0)) \int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle \\ &\quad - \frac{1}{2\epsilon^2} \sum_{l,m=1}^L (\psi_l(\theta) - \psi_l(\theta_0)) (\psi_m(\theta) - \psi_m(\theta_0)) \int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt. \end{aligned}$$

The statistical model under the complete observation is then an exponential family with sufficient statistics

$$N_T^{ji}, \int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt, \int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle, \int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt.$$

Under the partial observation, in terms of the EM algorithm, the Expectation step amounts to filtering the sufficient statistics under P^{θ_0} :

$$\begin{aligned} Q(\theta, \theta_0) &= \sum_{i \neq j} \left\{ E^{\theta_0} [N_T^{ji} | \mathcal{F}_T^Y] \log \frac{\varphi_{ji}(\theta)}{\varphi_{ji}(\theta_0)} - \left(\frac{\varphi_{ji}(\theta)}{\varphi_{ji}(\theta_0)} - 1 \right) E^{\theta_0} \left[\int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt | \mathcal{F}_T^Y \right] \right\} \\ &\quad + \frac{1}{\epsilon^2} \sum_{l=1}^L (\psi_l(\theta) - \psi_l(\theta_0)) E^{\theta_0} \left[\int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle | \mathcal{F}_T^Y \right] \\ &\quad - \frac{1}{2\epsilon^2} \sum_{l,m=1}^L (\psi_l(\theta) - \psi_l(\theta_0)) (\psi_m(\theta) - \psi_m(\theta_0)) E^{\theta_0} \left[\int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt | \mathcal{F}_T^Y \right], \end{aligned}$$

and the Maximization step is the same exercise as finding a MLE for an exponential family. The filtering equations to solve are as follows.

Theorem 6.1 *Under the same condition of Theorem 3.1, for each $i, j = 1, \dots, k$ and $l, m = 1, \dots, L$,*

1.

$$E^{\theta_0}[N_T^{ji}|\mathcal{F}_T^Y] = \frac{E^0[\Lambda_T N_T^{ji}]}{E^0[\Lambda_T]}, \quad E_T^0[\Lambda_T N_T^{ji}] = \langle \mathbf{1}, E_T^0[\Lambda_T N_T^{ji} X_T] \rangle$$

and $F_t := E_t^0[\Lambda_t N_t^{ji} X_t]$ is the solution of

$$\begin{aligned} F_t &= \frac{1}{\epsilon^2} \int_0^t \text{diag}(F_s) C^{\theta_0}(Y_s)^\perp dY_s + \int_0^t Q^{\theta_0}(Y_s) F_s ds \\ &\quad + e_j \int_0^t q_{ji}^{\theta_0}(Y_s) \langle e_i, E_s^0[\Lambda_s X_s] \rangle ds. \end{aligned} \quad (19)$$

2.

$$E^{\theta_0} \left[\int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt \middle| \mathcal{F}_T^Y \right] = \frac{1}{E_T^0[\Lambda_T]} E_T^0[\Lambda_T \int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt],$$

$$E_T^0[\Lambda_T \int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt] = \langle \mathbf{1}, E_T^0[\Lambda_T X_T \int_0^T q_{ji}^{\theta_0}(Y_t) \langle e_i, X_t \rangle dt] \rangle$$

and

$$F_t := E_t^0[\Lambda_t X_t \int_0^t q_{ji}^{\theta_0}(Y_s) \langle e_i, X_s \rangle ds]$$

is the solution of

$$\begin{aligned} F_t &= \frac{1}{\epsilon^2} \int_0^t \text{diag}(F_s) C^{\theta_0}(Y_s)^\perp dY_s + \int_0^t Q^{\theta_0}(Y_s) F_s ds \\ &\quad + e_i \int_0^t q_{ji}^{\theta_0}(Y_s) \langle e_i, E_s^0[\Lambda_s X_s] \rangle ds. \end{aligned}$$

3.

$$\begin{aligned} &E^{\theta_0} \left[\int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle \middle| \mathcal{F}_T^Y \right] \\ &= \frac{1}{E_T^0[\Lambda_T]} E_T^0[\Lambda_T \int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle], \\ &E_T^0[\Lambda_T \int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle] \\ &= \langle \mathbf{1}, E_T^0[\Lambda_T X_T \int_0^T \langle \mu^l(Z_t), dY_t - \mu^{\theta_0}(Z_t) dt \rangle] \rangle \end{aligned}$$

and

$$F_t := E_t^0[\Lambda_t X_t \int_0^t \langle \mu^l(Z_s), dY_s - \mu^{\theta_0}(Z_s) ds \rangle]$$

is the solution of

$$F_t = \frac{1}{\epsilon^2} \int_0^t \text{diag}(F_s) C^{\theta_0}(Y_s)^\perp dY_s + \int_0^t Q^{\theta_0}(Y_s) F_s ds \\ + \int_0^t \text{diag}(E_s^0[\Lambda_s X_s]) C^l(Y_s)^\perp dY_s,$$

where $C^l(y) = [c_{ij}^l]$, $c_{ij}^l(y) = \langle e_i, \mu^l(y, e_j) \rangle$.

4.

$$E^{\theta_0} \left[\int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt \middle| \mathcal{F}_T^{-Y} \right] = \frac{1}{E_T^0[\Lambda_T]} E_T^0[\Lambda_T \int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt],$$

$$E_T^0[\Lambda_T \int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt] = \langle \mathbf{1}, E_T^0[\Lambda_T X_T \int_0^T \langle \mu^l(Z_t), \mu^m(Z_t) \rangle dt] \rangle$$

and

$$F_t := E_t^0[\Lambda_t X_t \int_0^t \langle \mu^l(Z_s), \mu^m(Z_s) \rangle ds]$$

is the solution of

$$F_t = \frac{1}{\epsilon^2} \int_0^t \text{diag}(F_s) C^{\theta_0}(Y_s)^\perp dY_s + \int_0^t Q^{\theta_0}(Y_s) F_s ds \\ + \int_0^t \text{diag}(E_s^0[\Lambda_s X_s]) D^{l,m}(Y_s) ds,$$

where $D^{l,m}(y) = \text{diag}(\langle \mu^l(e_1, y), \mu^m(e_1, y) \rangle, \dots, \langle \mu^l(e_k, y), \mu^m(e_k, y) \rangle)$.

Proof: For 1., let $H_t = \langle e_a, X_t \rangle N_t^{ji}$ and apply Theorem 4.1 with $\alpha = \delta = 0$ and $\beta_t = \delta_{aj} \langle e_i, X_{t-} \rangle e_j + N_{t-}^{ji} e_a$ to obtain

$$\langle e_a, E_t^0[\Lambda_t N_t^{ji} X_t] \rangle = \frac{1}{\epsilon^2} \int_0^t \langle e_a, E_s^0[\Lambda_s N_s^{ji} X_s] \rangle \langle C^{\theta_0}(Y_s) e_a, dY_s \rangle \\ + \int_0^t \langle e_a, Q^{\theta_0}(Y_s) E_s^0[\Lambda_s N_s^{ji} X_s] \rangle ds + \delta_{aj} \int_0^t q_{ji}^{\theta_0}(Y_s) \langle e_i, E_s^0[\Lambda_s X_s] \rangle ds,$$

which is equivalent to (19). Here, we have used that

$$dH_t = \langle e_a, X_{t-} \rangle dN_t^{ji} + N_{t-}^{ji} \langle e_a, dX_t \rangle + \langle e_a, \Delta X_t \rangle \Delta N_t^{ji} \\ = N_{t-}^{ji} \langle e_a, dX_t \rangle + \delta_{aj} \langle e_i, X_{t-} \rangle \langle e_j, dX_t \rangle.$$

The rest is similar and so omitted. ////

Conflict of Interest : The author states that there is no conflict of interest.

References

- [1] A. Bain and D. Crisan, *Fundamentals of Stochastic Filtering*, Springer, 2009.
- [2] A. Dembo and O. Zeitouni, Parametric estimation of partially observed continuous time stochastic processes via the EM algorithm, *Stoch. Process. Appl.* 23,91-113 (1986).
- [3] R. J. Elliott, L. Aggoun and J.B. Moore, *Hidden Markov Models*, Springer, 1995.
- [4] K. Fujita, M. Ohmachi, K. Ikezaki, T. Yanagida and M. Iwaki, Direct visualization of human myosin II force generation using DNA origami-based thick filaments, *Communications Biology*, doi: 10.1038/s42003-019-0683-0.
- [5] M. Ghosh, A. Arapostathis and S. Marcus, Ergodic control of switching diffusions, *SIAM J. Control Optim.* 35, 1952-1988 (1997).
- [6] J.P. Hespanha, A model for stochastic hybrid systems with application to communication networks, *Nonlinear Analysis* 62, 1353-1383 (2005).
- [7] I.A. Ibragimov and R.Z. Has'minskii, *Statistical Estimation, Asymptotic Theory*, Springer-Verlag New York (1981).
- [8] J. Jacod and A. Shiryaev, *Limit theorems for stochastic processes*, 2nd Ed. Springer Verlag Berlin (2003).
- [9] R.S. Mamon and R.j. Elliott, *Hidden Markov Models in Finance*, Springer, 2014.
- [10] X. Ki, O. Omotere, L. Qian and E.R. Dougherty, Review of stochastic hybrid systems with applications in biological systems modeling and analysis, *EURASIM J. Bioinform. Syst. Biol.* doi: 10.1186/s13637-017-0061-5.
- [11] R.S. Liptser and A.N Shiryaev, *Statistics of Random Processes. I General Theory*, 2nd Ed. Springer-Verlag Berlin (2001).
- [12] R.S. Liptser and A.N Shiryaev, *Statistics of Random Processes. II Applications*, 2nd Ed. Springer-Verlag Berlin (2001).
- [13] D. Stroock, Diffusion Processes Associated with Lévy Generators, *Z. Wahrscheinlichkeitstheorie verw. Gebiete* 32, 209-244 (1975).
- [14] A.R. Teel, A. Subbaraman and A. Sferlazza, Stability analysis for stochastic hybrid systems: A survey, *Automatica* 50, 2435-2456 (2014).
- [15] W.M. Wonham, Some Applications of Stochastic Differential Equations to Optimal Nonlinear Filtering, *Journal of the Society for Industrial and Applied Mathematics Series A Control*, Vol. 2, No. 3, 347-369 (1964).
- [16] C.F.J. Wu, On the convergence properties of the EM algorithm, *Ann. Statist.* 11, 95-103 (1983).

[17] G.G. Yin and C. Zhu, *Hybrid Switching Diffusions*, Springer (2010).