

Codes for the Z-channel

Nikita Polyanskii ^{*} Yihan Zhang [†]

Abstract

This paper is a collection of results on combinatorial properties of codes for the *Z-channel*. A Z-channel with error fraction τ takes as input a length- n binary codeword and injects in an adversarial manner $n\tau$ *asymmetric* errors, i.e., errors that only zero out bits but do not flip 0's to 1's. It is known that the largest $(L - 1)$ -list-decodable code for the Z-channel with error fraction τ has exponential (in n) size if τ is less than a critical value that we call the *Plotkin point* and has constant size if τ is larger than the threshold. The $(L - 1)$ -list-decoding Plotkin point is known to be $L^{-\frac{1}{L-1}} - L^{-\frac{L}{L-1}}$, which equals $1/4$ for unique-decoding with $L - 1 = 1$. In this paper, we derive various results for the size of the largest codes above and below the list-decoding Plotkin point. In particular, we show that the largest $(L - 1)$ -list-decodable code ε -above the Plotkin point has size $\Theta_L(\varepsilon^{-3/2})$ for any $L - 1 \geq 1$. We also devise upper and lower bounds on the exponential size of codes below the list-decoding Plotkin point.

^{*}Nikita Polyanskii is with the Technical University of Munich. Email: nikita.polyanskii@tum.de. Supported by the German Research Foundation (Deutsche Forschungsgemeinschaft, DFG) under Grant No. WA3907/1-1.

[†]Yihan Zhang is with the Technion – Israel Institute of Technology. Email: yihanz@campus.technion.ac.il. Supported by funding from the European Union's Horizon 2020 research and innovation programme under grant agreement No 682203-ERC-[Inf-Speed-Tradeoff].

Contents

1	Introduction	3
2	Overview of our results and techniques	3
3	Preliminaries	5
4	Uniquely-decodable codes	6
4.1	Upper bound	6
4.2	Construction	7
5	List-decodable codes	10
5.1	List-decoding radius	10
5.2	List-decoding Plotkin point	11
5.3	Upper bound for constant-weight codes	12
5.4	Construction of constant-weight codes	12
5.5	Upper bound for approximate constant-weight codes	13
5.6	Upper bound for general codes	15
5.7	Construction of general codes	17
5.8	Upper bound on $(L - 1)$ -list-decoding capacity	18
5.9	Lower bound on $(L - 1)$ -list-decoding capacity	21
5.10	List-decoding capacity	22
6	Capacity of stochastic Z-channels	24
7	Open problems	24

1 Introduction

In coding theory, the Z-channel is used to model some asymmetric data storage and transmission systems. In this binary-input binary-output channel, the symbol 0 is always transmitted correctly, whereas the transmitted symbol 1 can be received as 0.

In this paper, we consider the combinatorial setting where the encoder transmits n symbols, and the maximum number of errors inflicted by an adversary is proportional to n . For a given word $\mathbf{x} \in \{0, 1\}^n$, we define the Z-ball centered at \mathbf{x} with radius τn as a set of all possible words that can be transmitted over the Z-channel with at most τn errors such that \mathbf{x} is received. Given τ and n , the main goal for $(L - 1)$ -list-decoding is to construct a code $\mathcal{C} \subseteq \{0, 1\}^n$ such that for any $\mathbf{x} \in \{0, 1\}^n$, the Z-ball centered at \mathbf{x} contains at most $L - 1$ codewords from \mathcal{C} . For $L = 2$, we say that \mathcal{C} is a uniquely-decodable code tolerating a fraction τ of (asymmetric) errors. For $L \geq 3$, \mathcal{C} is referred to as an $(L - 1)$ -list-decodable code for the Z-channel with list-decoding radius τ . Finding fundamental limits of error-correcting codes is one of the major problems in coding theory. Uniquely-decodable codes for asymmetric errors have been a subject for extensive studies in the numerous papers [1–9]. Up to our best knowledge, there are only two papers [10, 11] in the literature that discuss properties of list-decodable codes for the Z-channel.

First, we recall some results concerning the unique-decoding case. It is known [1, 2] that the rate of optimal codes tolerating a fraction τ of asymmetric errors is asymptotically equal to the rate of optimal codes correcting a fraction τ of symmetric errors¹. Hence there exist exponential-sized uniquely-decodable codes for any fraction of errors $\tau < 1/4$. The Plotkin bound [12] says that the size of a code capable of correcting a fraction $\tau = 1/4 + \varepsilon$ of symmetric errors is bounded above by $1 + 1/(4\varepsilon)$. One might ask a similar question for asymmetric errors. Specifically, can we bound the size of a code $\mathcal{C} \subseteq \{0, 1\}^n$ tolerating a fraction $\tau = 1/4 + \varepsilon$ of asymmetric errors using a function that depends only on ε ? The paper [2] claims that such a bound exists only for $\varepsilon > 1/12$. We disprove this statement and provide an order-optimal uniquely-decodable code of size $\Theta(\varepsilon^{-3/2})$ as $\varepsilon \rightarrow 0$. From the results of [12–14], it follows that the maximal size of a code tolerating a fraction $1/4 + \varepsilon$ of symmetric errors is $(4\varepsilon)^{-1}(1 + o(1))$ as $\varepsilon \rightarrow 0$.

Much less is known about list-decodable codes for the Z-channel. By [10, 11], exponential-sized (or positive-rate) $(L - 1)$ -list-decodable codes with list-decoding radius τ exist only for $\tau < \tau_L$, where $\tau_L = w_{\max} - w_{\max}^L$ and w_{\max} equals $L^{-\frac{1}{L-1}}$. We call τ_L the $(L - 1)$ -list-decoding Plotkin point. We extend the above results from unique-decoding to list-decoding and obtain the same characterization $\Theta_L(\varepsilon^{-3/2})$ for list-decodable codes with arbitrary list size $L - 1$ correcting $\tau_L + \varepsilon$ fraction of asymmetric errors. The same question for symmetric errors was also studied before. In a recent work [14], the results in [12, 13] for unique-decoding were generalized to list-decoding with any *odd* list size that is at least one and the optimal code size was shown to be $\Theta_L(\varepsilon^{-1})$. For *even* list size, the problem seems significantly more difficult and [14] showed that the optimal code size is $\Theta_L(\varepsilon^{-3/2})$ for list size three.

2 Overview of our results and techniques

This paper is a collection of results on combinatorial properties of codes for the Z-channel with adversarial errors. The most technically challenging part of our results has to do with obtaining order-optimal size of codes that correct a fraction of asymmetric errors ε -above the Plotkin point. We start with the unique-decoding case and show in Sec. 4 that the optimal size of codes which correct $1/4 + \varepsilon$ fraction of asymmetric errors is exactly $\Theta(\varepsilon^{-3/2})$. This follows from an upper bound (Theorem 5 in Sec. 4.1) and a matching construction (Theorem 6 in Sec. 4.2). We then generalize these results to list-decoding for any list size at least one. We show in Sec. 5.3–5.7

¹Hereafter, errors are called symmetric if any transmitted symbol from the alphabet $\{0, 1\}$ can be bit-flipped.

that the same bound $\Theta_L(\varepsilon^{-3/2})$ is also optimal for list-decodable codes which correct $\tau_L + \varepsilon$ fraction of asymmetric errors, where τ_L is the list-decoding Plotkin point. See Sec. 5.1 and 5.2 for definitions and properties of the list-decoding radius and list-decoding Plotkin point.

We briefly explain below the ideas behind our results on “post-Plotkin” codes.

1. (Upper bound for (approximate) constant-weight codes.) For *constant-weight* codes (i.e., a code in which all codewords have the same Hamming weight), it follows from a standard double-counting argument that the size of any code ε -above the Plotkin point (i.e., $1/4$) is at most $O_L(\varepsilon^{-1})$. For unique-decoding, this is known by [12]; for list-decoding, this follows from [10] (see Theorem 7 in Sec. 5.3). Furthermore, these results can be extended to *approximate constant-weight* codes (i.e., a code in which all codewords have *approximately* the same Hamming weight). This can be done by either repeating the double-counting argument with additional care of the deviation in weights or carefully augmenting the codewords in such a way that the augmented codewords all have the same weight. See Theorem 9 and 10 in Sec. 5.5 for detail.
2. (Upper bound for general codes.) For *general* codes in which codewords can have any weight between 0 and n , given the above results, it is tempting to partition $\{0, 1\}^n$ into ε^{-1} slices each of weight between nw and $n(w + \varepsilon)$ for some $w \in [0, 1]$. The subcode in each slice is therefore approximate constant-weight and has size at most $O_L(\varepsilon^{-1})$. In total, we get an upper bound $O_L(\varepsilon^{-2})$ on the size of the whole code. However, this bound turns out to be suboptimal! We improve it by partitioning the space in a more delicate way. The width of the slice is wider for weights far from the critical weight $w_{\max} = L^{-\frac{1}{L-1}}$ and is thinner for weights close to w_{\max} . In particular, we choose the width to be $\varepsilon^{1/2}$ on average for $w \in [0, w_{\max} - \Omega_L(\varepsilon^{1/2})] \cup [w_{\max} + \Omega_L(\varepsilon^{1/2}), 1]$ and we choose it to be ε for $w \in [w_{\max} - O_L(\varepsilon^{1/2}), w_{\max} + O_L(\varepsilon^{1/2})]$, while keeping the subcode in each slice having size $O_L(\varepsilon^{-1})$. In total, there are at most $O_L(1/\varepsilon^{1/2}) = O_L(\varepsilon^{-1/2})$ slices for small and large weights (i.e., weights far from w_{\max}) and at most $O_L(\varepsilon^{1/2}/\varepsilon) = O_L(\varepsilon^{-1/2})$ slices for moderate weights (i.e., weights close to w_{\max}). This gives an improved upper bound $O_L(\varepsilon^{-1/2}\varepsilon^{-1}) = O_L(\varepsilon^{-3/2})$ on the size of the whole code. The rigorous analysis for $L = 2$ and $L > 2$ is presented in the proof of Theorem 5 in Sec. 4.1 and Theorem 11 in Sec. 5.6, respectively.
3. (Construction of constant-weight codes.) In Sec. 5.4, we analyze a code formed by rows of a matrix whose columns are all possible constant-weight words. In Theorem 8, such a balanced code is shown to be ε -above the list-decoding Plotkin point and have order-optimal size $\Omega_L(\varepsilon^{-1})$. This code generalizes a construction proposed in [14] in the context of list-decodable codes for symmetric errors and has a similar flavour as weak-flip codes discussed in [15].
4. (Construction of general codes.) We note that purely random post-Plotkin code constructions do not have large size. However, we show how to use randomness in order to build a code ε -above the Plotkin point of size $\Omega_L(\varepsilon^{-3/2})$. The non-uniform partition used in the proof of the converse bound suggests a matching construction. We reuse the constant-weight construction in Theorem 8 in a consistent way with the non-uniform partition. Specifically, we first build $\Theta_L(\varepsilon^{-1/2})$ constant-weight codes such that the i th code has size $\Theta_L(\varepsilon^{-1})$ and contains codewords with relative weight $w_{\max} - i\varepsilon$. The asymmetry property of the Z-channel comes to play when we apply $\Theta_L(\varepsilon^{-1/2})$ independent random permutations on the set of coordinates within each code and consider the union of all these codes. For $L = 2$, we carefully analyze the unique-decoding radius of the resulting construction in the proof of Theorem 6 in Sec. 4.2. For $L > 2$, we investigate the list-decoding radius of our construction in the proof of Theorem 12.

In Sec. 5.8 and 5.9, we study codes for the Z-channel *below* the list-decoding Plotkin point and obtain upper and lower bounds on the list-decoding capacity. The upper bound in Theorem 14 follows the classical idea of Elias and Bassalygo [1]. Specifically, the space is multicovered by special balls and the size of all balls is carefully adjusted such that each of them contains a constant number of codewords only. The lower bound in Theorem 16 uses the standard random coding with expurgation technique. The question of obtaining the exact list-decoding capacity for arbitrary list sizes is difficult and our upper and lower bounds do not match. However, we manage to derive the list-decoding capacity for asymptotically large list sizes in Theorem 19 in Sec. 5.10.

Sec. 6 contains discussion on the capacity of Z-channels with *stochastic* errors. This is a direct consequence of the seminal channel coding theorem by Shannon [16].

We end the paper with open questions in Sec. 7.

3 Preliminaries

The set $\{i, i+1, \dots, j\}$ for some integers i and j with $i \leq j$ will be denoted as $[i, j]$. The set $[1, j]$ is shortly denoted as $[j]$. By slight abuse of notation, we write $[w_1, w_2]$ to denote the interval of real numbers between w_1 and w_2 . A vector of length n is denoted by bold lowercase letters, such as \mathbf{x} , and the i th entry of the vector \mathbf{x} is referred to as x_i . The all-zero vector, which length will be clear from the context, is written as $\mathbf{0}$. Define the asymmetric function $\Delta(\mathbf{x}, \mathbf{y})$ to be the number of positions $i \in [n]$ such that $x_i = 1$ and $y_i = 0$. The Hamming distance between $\mathbf{x}, \mathbf{y} \in \{0, 1\}^n$ is then $d_H(\mathbf{x}, \mathbf{y}) := \Delta(\mathbf{x}, \mathbf{y}) + \Delta(\mathbf{y}, \mathbf{x})$. The (Hamming) weight of $\mathbf{x} \in \{0, 1\}^n$ is $\text{wt}(\mathbf{x}) := d_H(\mathbf{x}, \mathbf{0})$; the relative weight is $\text{wt}(\mathbf{x})/n$. The *Z-distance* between $\mathbf{x}, \mathbf{y} \in \{0, 1\}^n$ is defined as $d_Z(\mathbf{x}, \mathbf{y}) := \max(\Delta(\mathbf{x}, \mathbf{y}), \Delta(\mathbf{y}, \mathbf{x}))$. Note that the Hamming distance and the Z-distance are related by the following identity: $d_Z(\mathbf{x}, \mathbf{y}) = \frac{1}{2}(d_H(\mathbf{x}, \mathbf{y}) + |\text{wt}(\mathbf{x}) - \text{wt}(\mathbf{y})|)$. By this relation, we see that $d_Z(\cdot, \cdot)$ is indeed a distance, and it equals $d_H(\cdot, \cdot)/2$ if the Hamming weights of \mathbf{x} and \mathbf{y} are the same. Define the *Z-ball* and the *H-ball* centered at $\mathbf{x} \in \{0, 1\}^n$ with radius t as follows

$$\begin{aligned} B_t^Z(\mathbf{x}) &:= \{\mathbf{y} \in \{0, 1\}^n : \Delta(\mathbf{x}, \mathbf{y}) = 0, \Delta(\mathbf{y}, \mathbf{x}) \leq t\}, \\ B_t^H(\mathbf{x}) &:= \{\mathbf{y} \in \{0, 1\}^n : d_H(\mathbf{x}, \mathbf{y}) \leq t\}. \end{aligned}$$

Similarly, define the *Z-sphere* and the *H-sphere* centered at $\mathbf{x} \in \{0, 1\}^n$ with radius t as follows

$$\begin{aligned} S_t^Z(\mathbf{x}) &:= \{\mathbf{y} \in \{0, 1\}^n : \Delta(\mathbf{x}, \mathbf{y}) = 0, \Delta(\mathbf{y}, \mathbf{x}) = t\}, \\ S_t^H(\mathbf{x}) &:= \{\mathbf{y} \in \{0, 1\}^n : d_H(\mathbf{x}, \mathbf{y}) = t\}. \end{aligned}$$

A code $\mathcal{C} \subseteq \{0, 1\}^n$ is an arbitrary subset of binary vector of the same length n . The *size* of a code \mathcal{C} is denoted as $|\mathcal{C}|$. The *rate* of \mathcal{C} is defined as $R(\mathcal{C}) := \frac{1}{n} \log |\mathcal{C}|$. A code $\mathcal{C} \subseteq \{0, 1\}^n$ is called *w-constant-weight* if the weight of all codewords $\mathbf{x} \in \mathcal{C}$ is $\text{wt}(\mathbf{x}) = nw$.

Definition 1 (Uniquely-decodable code). We say that a code $\mathcal{C} \subseteq \{0, 1\}^n$ *corrects* t asymmetric (symmetric) errors if for any $\mathbf{x} \in \{0, 1\}^n$ the respected Z-ball (H-ball) centered at \mathbf{x} with radius t contains at most one codeword from \mathcal{C} , i.e., it holds that $|B_t^Z(\mathbf{x}) \cap \mathcal{C}| \leq 1$ ($|B_t^H(\mathbf{x}) \cap \mathcal{C}| \leq 1$).

Note that a code \mathcal{C} corrects t asymmetric errors if and only if for any two distinct codewords $\mathbf{x}, \mathbf{y} \in \mathcal{C}$, it holds that $d_Z(\mathbf{x}, \mathbf{y}) > t$. A code $\mathcal{C} \subseteq \{0, 1\}^n$ is said to correct a *fraction* τ of asymmetric (symmetric) errors if it corrects t asymmetric (symmetric) errors for $t = \lceil \tau n \rceil$.

In the following statement, we first recall a (trivial) observation from [4].

Lemma 1. *Let a code $\mathcal{C} \subseteq \{0, 1\}^n$ be w-constant-weight. Then \mathcal{C} corrects t asymmetric errors if and only if it corrects t symmetric errors.*

We state two classical coding theory results, which were proved in [12] and [1] respectively.

Lemma 2. *Let a code $\mathcal{C} \subseteq \{0, 1\}^n$ corrects t , $t > n/4$, symmetric errors. Then its size is bounded above as follows*

$$|\mathcal{C}| \leq 2 \left\lfloor \frac{2t + 2}{4t + 3 - n} \right\rfloor.$$

Lemma 3. *Let a code $\mathcal{C} \subseteq \{0, 1\}^n$ be w -constant-weight and correct t symmetric errors. If the inequality $t + 1 \leq w \leq (n - \sqrt{n^2 - 4tn})/2$ is fulfilled, then the size of \mathcal{C} is bounded above as follows*

$$|\mathcal{C}| \leq \left\lfloor \frac{tn}{w^2 - (w - t)n} \right\rfloor.$$

At last we introduce the concept of list-decodable codes.

Definition 2 (List-decodable code). Let L be a positive integer at least 2. A code $\mathcal{C} \subseteq \{0, 1\}^n$ is said to be $(L - 1)$ -list-decodable with list-decoding radius τ if for any $\mathbf{x} \in \{0, 1\}^n$ the respected Z -ball (H-ball) centered at \mathbf{x} with radius $t := \lceil \tau n \rceil$ contains at most $L - 1$ codewords from \mathcal{C} , i.e., it holds that $|B_t^Z(\mathbf{x}) \cap \mathcal{C}| \leq L - 1$ ($|B_t^H(\mathbf{x}) \cap \mathcal{C}| \leq L - 1$).

Let $\mathcal{P}(\Sigma)$ denote the set of distributions supported on a finite set Σ .

Definition 3 (Type). Let $\Sigma_1, \dots, \Sigma_k$ be finite alphabets. Let $(\mathbf{x}_1, \dots, \mathbf{x}_k) \in \Sigma_1^n \times \dots \times \Sigma_k^n$. The *joint type* $T_{\mathbf{x}_1, \dots, \mathbf{x}_k} \in \mathbb{R}^{|\Sigma_1| \times \dots \times |\Sigma_k|}$ of $\mathbf{x}_1, \dots, \mathbf{x}_k$ is defined as their empirical distribution (a.k.a. histogram), i.e., for any $(x_1, \dots, x_k) \in \Sigma_1 \times \dots \times \Sigma_k$,

$$T_{\mathbf{x}_1, \dots, \mathbf{x}_k}(x_1, \dots, x_k) := \frac{1}{n} |\{i \in [n] : \mathbf{x}_{1,i} = x_1, \dots, \mathbf{x}_{k,i} = x_k\}|.$$

Theorem 4 (Sanov [17]). *Let $\mathcal{Q} \subset \mathcal{P}(\Sigma)$ be a subset of distributions on a finite set Σ such that it is equal to the closure of its interior. Let $\mathbf{x} \in \Sigma^n$ be distributed according to $P^{\otimes n}$ for some $P \in \mathcal{P}(\Sigma)$. Then*

$$\lim_{n \rightarrow \infty} \frac{1}{n} \log \Pr\{T_{\mathbf{x}} \in \mathcal{Q}\} = - \inf_{Q \in \mathcal{Q}} D(Q \| P).$$

4 Uniquely-decodable codes

In this section, we obtain upper and lower bounds on the size of an optimal code capable of correcting a fraction $\tau = \frac{1}{4} + \varepsilon$ of asymmetric errors.

4.1 Upper bound

In the following statement, we derive an upper bound on the size of a code capable of correcting a large fraction of asymmetric errors. The idea of the proof is to partition a code into $O(\varepsilon^{-1/2})$ subcodes with approximate constant weight. By extending codewords within each subcode, we obtain constant-weight codes correcting a large fraction of symmetric errors and show that their size can be bounded by $O(\varepsilon^{-1})$.

Theorem 5. *Let $n > 36$ be an integer and $\mathcal{C} \subseteq \{0, 1\}^n$ be a code correcting a fraction $\tau = \frac{1}{4} + \varepsilon$ of asymmetric errors for some real number $0 < \varepsilon < 1/12 - 3/n$. Then the size of the code can be bounded as follows*

$$|\mathcal{C}| \leq \frac{1 + 7/n + 2\sqrt{\varepsilon} + 4\varepsilon + 16\sqrt{\varepsilon}/n}{\varepsilon^{3/2}} + 10.$$

Proof. Without loss of generality, we assume that the number of codewords of weight at most $n/2$ is at least as the number of codewords of weight at least $n/2$. Otherwise, we can consider the code that is obtained by replacing 0 by 1 and 1 by 0 in all codewords of the original code. For a non-negative integer i , define $\rho_i := \frac{i}{2i+1}$. Define the subcode

$$\mathcal{A}_i := \{\mathbf{x} \in \mathcal{C} : \lfloor \rho_i n \rfloor < \text{wt}(\mathbf{x}) \leq \lfloor \rho_{i+1} n \rfloor\}.$$

Extend all codewords of \mathcal{A}_i by adding $\lfloor \rho_{i+1} n \rfloor - \lfloor \rho_i n \rfloor - 1$ extra positions such that all codewords have weight $\lfloor \rho_{i+1} n \rfloor$. Note that this can be done in different ways. From Lemma 1 it follows that the obtained code $\mathcal{A}'_i \subseteq \{0, 1\}^{n + \lfloor \rho_{i+1} n \rfloor - \lfloor \rho_i n \rfloor - 1}$ contains codewords of weight $\lfloor \rho_{i+1} n \rfloor$ and correct $\lceil (1/4 + \varepsilon)n \rceil$ symmetric errors. For $\varepsilon < 1/12 - 3/n$, the condition of Lemma 3 is fulfilled. Thus, we obtain that

$$\begin{aligned} |\mathcal{A}_i| = |\mathcal{A}'_i| &\leq \frac{\lceil (1/4 + \varepsilon)n \rceil (n + \lfloor \rho_{i+1} n \rfloor - \lfloor \rho_i n \rfloor - 1)}{\lfloor \rho_{i+1} n \rfloor^2 - (\lfloor \rho_{i+1} n \rfloor - \lceil (1/4 + \varepsilon)n \rceil)(n + \lfloor \rho_{i+1} n \rfloor - \lfloor \rho_i n \rfloor - 1)} \\ &\leq \frac{(1/4 + \varepsilon + 1/n)(1 + \rho_{i+1} - \rho_i)}{\rho_{i+1}^2 - (\rho_{i+1} - 1/4 - \varepsilon)(1 + \rho_{i+1} - \rho_i)}. \end{aligned}$$

In the last inequality, we make use of the fact that $w^2 - (w - t)n$ is a monotonically decreasing function in w for $w \leq (n - \sqrt{n^2 - 4tn})/2$. Observe that $\rho_{i+1}^2 - (\rho_{i+1} - 1/4 - \varepsilon)(1 + \rho_{i+1} - \rho_i) = 0$ since $\rho_i = \frac{i}{2i+1}$. Thus, $|\mathcal{A}'_i| \leq 1 + (1/4 + 1/n)\varepsilon^{-1}$.

Let $i_0 := \lfloor 1/(2\sqrt{\varepsilon}) \rfloor$ and, thus, $\rho_{i_0} \geq \frac{1-2\sqrt{\varepsilon}}{2+2\sqrt{\varepsilon}}$. For a non-negative integer j , consider the subcode

$$\mathcal{B}_j := \{\mathbf{x} \in \mathcal{C} : \lfloor \rho_{i_0} n \rfloor + j \lceil 2\varepsilon n \rceil < \text{wt}(\mathbf{x}) \leq \lfloor \rho_{i_0} n \rfloor + (j+1) \lceil 2\varepsilon n \rceil\}.$$

We extend all codewords of \mathcal{B}_j by adding $\lceil 2\varepsilon n \rceil$ extra positions such that all obtained codewords have the same weight. We get the code $\mathcal{B}'_j \subseteq \{0, 1\}^{n + \lceil 2\varepsilon n \rceil}$ which contains codewords of weight $\lfloor \rho_{i_0} n \rfloor + (j+1) \lceil 2\varepsilon n \rceil$ and corrects $\lceil (1/4 + \varepsilon)n \rceil$ symmetric errors. By Lemma 2, we estimate

$$|\mathcal{B}_j| = |\mathcal{B}'_j| \leq \frac{n + 4\varepsilon n + 8}{n + 4\varepsilon n + 3 - n - 2\varepsilon n - 1} \leq (1/2 + 4/n + 2\varepsilon)\varepsilon^{-1}.$$

Each codeword of \mathcal{C} , having weight within the interval $[1, n/2]$, is included in \mathcal{A}_i with some $i \in [0, i_0 - 1]$ or \mathcal{B}_j with some $j \in [0, j_0 - 1]$ if $j_0 := \lfloor 3/(4\sqrt{\varepsilon}) + 2 \rfloor$. Indeed,

$$\frac{n/2 - \lfloor \rho_{i_0} n \rfloor}{\lceil 2\varepsilon n \rceil} \leq \frac{n/2 - \frac{1-2\sqrt{\varepsilon}}{2+2\sqrt{\varepsilon}}n}{2\varepsilon n} + 1 \leq \left\lfloor \frac{3}{4\sqrt{\varepsilon}} + 2 \right\rfloor.$$

Since the number of codewords with weight from the interval $[1, n/2]$ is not less than the number of codewords of weight from the interval $[n/2, n - 1]$, it holds

$$\begin{aligned} |\mathcal{C}| &\leq 2 \left(\sum_{i=0}^{i_0-1} |\mathcal{A}_i| + \sum_{j=0}^{j_0-1} |\mathcal{B}_j| \right) + 2 \\ &\leq \frac{1}{\varepsilon^{3/2}} (\varepsilon + 1/4 + 1/n + 3/4 + 6/n + 3\varepsilon + 2\sqrt{\varepsilon} + 16\sqrt{\varepsilon}/n + 8\varepsilon^{3/2}) + 2 \\ &= \frac{1 + 7/n + 4\varepsilon + 2\sqrt{\varepsilon} + 16\sqrt{\varepsilon}/n}{\varepsilon^{3/2}} + 10. \quad \square \end{aligned}$$

4.2 Construction

In the following statement, we prove that there exists a code of size $\Omega(\varepsilon^{-3/2})$ and length $\exp(\Theta(\varepsilon^{-3/2}))$ capable of correcting a fraction $1/4 + \varepsilon$ of asymmetric errors. We use the intuition from the proof of Theorem 5. First, we build $O(\varepsilon^{-1/2})$ codes such that the j th code is a

uniquely-decodable code containing codewords with the relative weight $\frac{1}{2} - j\varepsilon$. We borrow an idea for such code with $j = 0$ from [14], where the authors constructed list-decodable codes for symmetric errors. By performing simple repetition, we construct longer codes of the same size while the error-correction capability of all those codes remains unchanged. Applying a random permutation on the set of coordinates within each code, we guarantee that two codewords from different codes have a large asymmetric distance with overwhelming probability.

Theorem 6. *There exists a code of length $\exp(O(\varepsilon^{-3/2}))$, capable of correcting a fraction $\tau = \frac{1}{4} + \varepsilon$ of asymmetric errors. Furthermore, its size is at least $\frac{3\sqrt{3}}{128}\varepsilon^{-3/2}(1 + o(1))$ as $\varepsilon \rightarrow 0$.*

Proof. Consider the positive integer $m := \lfloor 3/(32\varepsilon) \rfloor$ and define the real number $c := 2^{-3/2}$. For every $j \in \{-\lfloor c\sqrt{m} \rfloor, \dots, \lfloor c\sqrt{m} \rfloor\}$, denote $n_j := \binom{2m}{m-j}$. Consider a binary matrix A_j of size $2m \times n_j$, whose columns are all possible binary vectors of length $2m$ and weight $m - j$. For two distinct rows \mathbf{x} and \mathbf{y} of matrix A_j , we compute the number of position in which the rows are different:

$$\Delta(\mathbf{x}, \mathbf{y}) = \Delta(\mathbf{y}, \mathbf{x}) = \binom{2m-2}{m-j-1}.$$

This means that a code, whose codewords are rows of A_j , corrects a fraction τ_j of asymmetric errors, where

$$\tau_j := \frac{\binom{2m-2}{m-j-1} - 1}{\binom{2m}{m-j}} = \frac{(m-j)(m+j)}{2m(2m-1)} - \frac{1}{\binom{2m}{m-j}} = \frac{1}{4} + \frac{m/2 - j^2}{4m^2 - 2m} - \frac{1}{\binom{2m}{m-j}}.$$

Let us show that for small enough ε , it holds that $\tau_j \geq \frac{1}{4} + \varepsilon$. We have

$$\begin{aligned} \frac{m/2 - j^2}{4m^2 - 2m} - \frac{1}{\binom{2m}{m-j}} &\geq \frac{m/2 - c^2m}{4m^2 - 2m} - \frac{1}{\binom{2m}{m-\lfloor c\sqrt{m} \rfloor}} \\ &= \frac{3}{32m - 16} - \frac{1}{\binom{2m}{m-\lfloor c\sqrt{m} \rfloor}} \\ &= \frac{3}{32m} + \frac{3}{2m(32m - 16)} - \frac{1}{\binom{2m}{m-\lfloor c\sqrt{m} \rfloor}} \\ &\geq \varepsilon. \end{aligned}$$

To show the last inequality, we used that $m = \lfloor 3/(32\varepsilon) \rfloor$, $c = 2^{-3/2}$ and the fact that for sufficiently large m (small ε), it holds

$$\frac{3}{64m^2} > \frac{1}{\binom{2m}{m-\lfloor c\sqrt{m} \rfloor}}.$$

For a positive integer z , consider a matrix $A_j^{(z)}$ of size $2m \times zn_j$ which is composed of z copies of the matrix A_j . We write copies of A_j to the right, i.e., $A_j^{(z)} = (A_j, A_j, \dots, A_j)$. By $\tilde{A}_j^{(z)}$ denote a matrix obtained from $A_j^{(z)}$ by a random permutation of its columns. This permutation is taken uniformly at random from the set of all permutations. Note that a code whose codewords are rows of $\tilde{A}_j^{(z)}$ corrects the same fraction of errors as the original code obtained from A_j . Define integers

$$z_j := \prod_{\substack{i=-\lfloor c\sqrt{m} \rfloor \\ i \neq j}}^{\lfloor c\sqrt{m} \rfloor} \binom{2m}{m-i}, \quad N := \prod_{i=-\lfloor c\sqrt{m} \rfloor}^{\lfloor c\sqrt{m} \rfloor} \binom{2m}{m-i}, \quad M := 2m(2\lfloor c\sqrt{m} \rfloor + 1).$$

Consider a matrix A of size $M \times N$ containing $\tilde{A}_j^{(z_j)}$ as a submatrix for all $j \in \{-\lfloor c\sqrt{m} \rfloor, \dots, \lfloor c\sqrt{m} \rfloor\}$. We assume that matrices $\tilde{A}_j^{(z_j)}$ are written one below the other using the ascending order of parameter j . For $\varepsilon \rightarrow 0$, we estimate the number of rows M and the number of columns N in A as follows

$$M = \frac{3\sqrt{3}}{128\varepsilon\sqrt{\varepsilon}}(1 + o(1)), \quad N = \exp(\Theta(\varepsilon^{-3/2})).$$

Let us show that for two distinct rows $\tilde{\mathbf{x}}$ and $\tilde{\mathbf{y}}$ in A , the value $d_Z(\tilde{\mathbf{x}}, \tilde{\mathbf{y}})$ is large enough with overwhelming probability. The latter ensures that the code obtained from A can correct the required fraction of asymmetric errors. More formally, let $\tilde{\mathbf{x}}$ and $\tilde{\mathbf{y}}$ be rows from $\tilde{A}_j^{(z_j)}$ and $\tilde{A}_i^{(z_i)}$, where $j < i$. Clearly, $\text{wt}(\tilde{\mathbf{x}}) = \frac{m-j}{2m}N > \frac{m-i}{2m}N = \text{wt}(\tilde{\mathbf{y}})$ and $d_Z(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) = \Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}})$. The probability distribution for the random variable $\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}})$ is given by

$$\Pr\{\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) = t\} = \begin{cases} \frac{\binom{\text{wt}(\tilde{\mathbf{x}})}{t} \binom{N - \text{wt}(\tilde{\mathbf{x}})}{\text{wt}(\tilde{\mathbf{y}}) - \text{wt}(\tilde{\mathbf{x}}) + t}}{\binom{N}{\text{wt}(\tilde{\mathbf{y}})}}, & \text{for } t \in \{\text{wt}(\tilde{\mathbf{x}}) - \text{wt}(\tilde{\mathbf{y}}), \dots, \min(\text{wt}(\tilde{\mathbf{x}}), N - \text{wt}(\tilde{\mathbf{y}}))\}, \\ 0, & \text{otherwise.} \end{cases}$$

We estimate the probability of the event that $\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}})$ is small

$$\Pr\left\{\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) \leq N\left(\frac{1}{4} + \varepsilon\right)\right\} \leq N \max_{t \in [0, \lfloor N(\frac{1}{4} + \varepsilon) \rfloor]} \Pr\{\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) = t\}. \quad (1)$$

Let an integer t be equal to αN for some real number $\alpha \in \left[\frac{i-j}{2m}, \min\left(\frac{m-j}{2m}, \frac{m+i}{2m}\right)\right]$. Note that N and m are functions of ε . Define the function

$$g_{i,j}(\alpha, \varepsilon) := \frac{1}{N} \log(\Pr\{\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) = t\}).$$

For arbitrary integers u and v so that $u > v \geq 1$, the binomial coefficient $\binom{u}{v}$ satisfies

$$\sqrt{\frac{u}{8v(u-v)}} 2^{uh(v/u)} \leq \binom{u}{v} \leq 2^{uh(v/u)},$$

where $h(x) := -x \log x - (1-x) \log(1-x)$. Thus, for $\alpha \in \left(\frac{i-j}{2m}, \min\left(\frac{m-j}{2m}, \frac{m+i}{2m}\right)\right)$, it holds that

$$\begin{aligned} g_{i,j}(\alpha, \varepsilon) &\leq \frac{m-j}{2m} h\left(\frac{2\alpha m}{m-j}\right) + \frac{m+j}{2m} h\left(\frac{j-i+2\alpha m}{m+j}\right) - h\left(\frac{m-i}{2m}\right) - \frac{\log\left(\frac{m^2}{2(m-i)(m+i)N}\right)}{2N} \\ &\leq r_{i,j}(\alpha, \varepsilon) + \delta(\varepsilon), \end{aligned}$$

where functions $r_{i,j}(\alpha, \varepsilon)$ and $\delta_{i,j}(\varepsilon)$ are defined as follows

$$r_{i,j}(\alpha, \varepsilon) := \frac{m-j}{2m} h\left(\frac{2\alpha m}{m-j}\right) + \frac{m+j}{2m} h\left(\frac{j-i+2\alpha m}{m+j}\right) - h\left(\frac{m-i}{2m}\right), \quad \delta(\varepsilon) := \frac{\log(2N)}{2N}.$$

Using the relation $\frac{\partial h(x)}{\partial x} = \log\left(\frac{1-x}{x}\right)$, we compute the derivative of $r_{i,j}(\alpha, \varepsilon)$:

$$q_{i,j}(\alpha, \varepsilon) := \frac{\partial r_{i,j}(\alpha, \varepsilon)}{\partial \alpha} = \log\left(\frac{m-j-2\alpha m}{2\alpha m}\right) + \log\left(\frac{m+i-2\alpha m}{j-i+2\alpha m}\right).$$

Let $\alpha_{i,j} = \alpha_{i,j}(\varepsilon) := \frac{(m-j)(m+i)}{4m^2}$. Clearly, the function $q_{i,j}(\alpha, \varepsilon)$ is positive for $\alpha < \alpha_{i,j}$, and the function $r_{i,j}(\alpha, \varepsilon) \leq 0$ for all required α . Furthermore, $r_{i,j}(\alpha_{i,j}, \varepsilon) = 0$. Since $m = \lfloor 3/(32\varepsilon) \rfloor$ and $-\lfloor c\sqrt{m} \rfloor \leq j < i \leq \lfloor c\sqrt{m} \rfloor$, we obtain that $\alpha_{i,j}(\varepsilon) - \left(\frac{1}{4} + \varepsilon\right) > 0$ and

$$\alpha_{i,j}(\varepsilon) - \left(\frac{1}{4} + \varepsilon\right) = \frac{(m-j)(m+i)}{4m^2} - \left(\frac{1}{4} + \varepsilon\right) = \frac{(i-j)m - ij - 4\varepsilon m^2}{4m^2}.$$

Since the derivative of $r_{i,j}(\alpha, \varepsilon)$ is positive for $\alpha \leq 1/4 + \varepsilon$, we get that

$$\sup_{\frac{i-j}{2m} < \alpha \leq \frac{1}{4} + \varepsilon} g_{i,j}(\alpha, \varepsilon) \leq r_{i,j}(1/4 + \varepsilon, \varepsilon) + \delta(\varepsilon). \quad (2)$$

Observe that we have the partial sum of the Taylor series with the remainder in Lagrange's form

$$r_{i,j}(\alpha_{i,j}, \varepsilon) = r_{i,j}(1/4 + \varepsilon, \varepsilon) + (\alpha_{i,j} - 1/4 - \varepsilon)q_{i,j}(1/4 + \varepsilon, \varepsilon) + (\alpha_{i,j} - 1/4 - \varepsilon)^2 \frac{\sigma_{i,j}(\theta, \varepsilon)}{2}, \quad (3)$$

where $\sigma_{i,j}(\alpha, \varepsilon) := \frac{\partial q_{i,j}(\alpha, \varepsilon)}{\partial \alpha}$ and θ is some point within the interval $[1/4 + \varepsilon, \alpha_{i,j}]$. Let us show that the function $\sigma_{i,j}(\alpha, \varepsilon)$ in the interval $(1/4 + \varepsilon, \alpha_{i,j})$ can be bounded below

$$\frac{\sigma_{i,j}(\alpha, \varepsilon)}{\log e} = \frac{j - m}{\alpha(m - j - 2\alpha m)} - \frac{2m(m + j)}{(j - i + 2\alpha m)(m + i - 2\alpha m)}.$$

For $\varepsilon \rightarrow 0$, $m = \Theta(\varepsilon^{-1})$. Thus, $\sigma_{i,j}(\theta, \varepsilon) = -16 \log e(1 + o(1))$ as $\varepsilon \rightarrow 0$. Indeed, it holds that

$$\lim_{\varepsilon \rightarrow 0} \sup_{1/4 + \varepsilon < \alpha < \alpha_{i,j}} \sigma_{i,j}(\alpha, \varepsilon) = -16 \log e, \quad \lim_{\varepsilon \rightarrow 0} \inf_{1/4 + \varepsilon < \alpha < \alpha_{i,j}} \sigma_{i,j}(\alpha, \varepsilon) = -16 \log e.$$

Now we estimate $q_{i,j}(1/4 + \varepsilon, \varepsilon)$ as $\varepsilon \rightarrow 0$

$$\begin{aligned} q_{i,j}(1/4 + \varepsilon, \varepsilon) &= \log \left(1 + \frac{mi - 4\varepsilon m^2 - jm - ji}{(m/2 + 2\varepsilon m)(m/2 + j - i + 2\varepsilon m)} \right) \\ &= 4 \log e \frac{m(i - j) - 4\varepsilon m^2 - ji}{m^2} (1 + o(1)). \end{aligned}$$

Recall that $r_{i,j}(\alpha_{i,j}, \varepsilon) = 0$. Combining the above bounds with (3), we get

$$\begin{aligned} r_{i,j}(1/4 + \varepsilon, \varepsilon) &= - \left(\alpha_{i,j} - \frac{1}{4} - \varepsilon \right) \left(\frac{m(i - j) - 4\varepsilon m^2 - ji}{m^2} (4 \log e - 2 \log e) \right) (1 + o(1)) \\ &\leq -\lambda \varepsilon^2 + o(\varepsilon^2) \end{aligned}$$

for some constant $\lambda > 0$ and $\varepsilon \rightarrow 0$. Using this inequality, the bound $\delta(\varepsilon) = o(\varepsilon^2)$ and the inequality (2), we estimate the LHS of (1) as follows

$$\Pr \left\{ \Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}) \leq N \left(\frac{1}{4} + \varepsilon \right) \right\} \leq N 2^{-\lambda \varepsilon^2 N + o(\varepsilon^2 N)} = o(1),$$

since $\varepsilon^2 N = \exp(\Omega(\varepsilon^{-3/2}))$. The probability of the event that $\max(\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}), \Delta(\tilde{\mathbf{y}}, \tilde{\mathbf{x}})) \leq N(\frac{1}{4} + \varepsilon)$ for some distinct rows $\tilde{\mathbf{x}}, \tilde{\mathbf{y}}$ in matrix A can be bounded above as follows

$$\binom{M}{2} \max_{\substack{\tilde{\mathbf{x}}, \tilde{\mathbf{y}} \in A \\ \tilde{\mathbf{x}} \neq \tilde{\mathbf{y}}}} \Pr \left\{ \max(\Delta(\tilde{\mathbf{x}}, \tilde{\mathbf{y}}), \Delta(\tilde{\mathbf{y}}, \tilde{\mathbf{x}})) \leq N \left(\frac{1}{4} + \varepsilon \right) \right\} = o(1).$$

It follows that for $\varepsilon \rightarrow 0$, with overwhelming probability, the code composed of rows of matrix A can correct a fraction $\tau = \frac{1}{4} + \varepsilon$ of asymmetric errors. \square

5 List-decodable codes

5.1 List-decoding radius

Fix $L \in \mathbb{Z}_{\geq 2}$. For an L -list $\mathcal{L} := \{\mathbf{x}_1, \dots, \mathbf{x}_L\} \in \binom{\{0,1\}^n}{L}$ of distinct vectors, define its *Chebyshev radius* w.r.t. Z -distance as

$$\text{rad}(\mathcal{L}) := \min_{\mathbf{y} \in \{0,1\}^n} \max_{i \in [L]} d_Z(\mathbf{x}_i, \mathbf{y}).$$

Let $\mathcal{C} \subseteq \{0, 1\}^n$ be an arbitrary code for the Z-channel. The $(L - 1)$ -list-decoding radius $\tau_L(\mathcal{C})$ of \mathcal{C} is defined as

$$\tau_L(\mathcal{C}) := \min_{\mathcal{L} \in \binom{\mathcal{C}}{L}} \text{rad}(\mathcal{L}).$$

It is easy to see that the minimum in the definition of $\text{rad}(\mathcal{L})$ can be achieved by the following vector $\mathbf{y}_{\mathcal{L}} = (y_1, \dots, y_n) \in \{0, 1\}^n$:

$$y_i = \begin{cases} 1, & x_{1,i} = \dots = x_{L,i} = 1 \\ 0, & \text{otherwise} \end{cases}, \quad (4)$$

for each $i \in [n]$. Here $x_{j,i}$ denotes the i th entry of \mathbf{x}_j . Observe that since $\text{supp}(\mathbf{y}_{\mathcal{L}}) \subseteq \text{supp}(\mathbf{x}_i)$ for all $i \in [L]$, we have $d_Z(\mathbf{x}_i, \mathbf{y}_{\mathcal{L}}) = |\text{supp}(\mathbf{x}_i)| - |\text{supp}(\mathbf{y}_{\mathcal{L}})| = \text{wt}(\mathbf{x}_i) - \text{wt}(\mathbf{y}_{\mathcal{L}})$. Therefore

$$\text{rad}(\mathcal{L}) := \max_{i \in [L]} \text{wt}(\mathbf{x}_i) - \text{wt}(\mathbf{y}_{\mathcal{L}}) = \max_{i \in [L]} \text{wt}(\mathbf{x}_i) - \left| \bigcap_{i \in [L]} \text{supp}(\mathbf{x}_i) \right|.$$

Furthermore, if all \mathbf{x}_i 's have the same weight w , then

$$\text{rad}(\mathcal{L}) = nw - \left| \bigcap_{i \in [L]} \text{supp}(\mathbf{x}_i) \right|. \quad (5)$$

For a constant-weight code \mathcal{C} of weight w , we have

$$\tau_L(\mathcal{C}) = nw - \max_{\mathcal{L} \in \binom{\mathcal{C}}{L}} \left| \bigcap_{\mathbf{x} \in \mathcal{L}} \text{supp}(\mathbf{x}) \right|.$$

It is not hard to see that $\mathcal{C} \subseteq \{0, 1\}^n$ is $(L - 1)$ -list-decodable with list-decoding radius τ if and only if $\tau_L(\mathcal{C}) > n\tau$. The $(L - 1)$ -list-decoding capacity of a Z-channel with input weight w and fraction of asymmetric errors τ is defined as

$$C_{L-1}(w, \tau) := \limsup_{n \rightarrow \infty} \max_{\substack{\mathcal{C}_n \subset B_{nw}^Z(\mathbf{0}) \\ \tau_L(\mathcal{C}_n) > n\tau}} R(\mathcal{C}_n).$$

The $(L - 1)$ -list-decoding radius of a Z-channel with input weight w and fraction of asymmetric errors τ is defined as

$$\tau_L(w, R) := \limsup_{n \rightarrow \infty} \max_{\substack{\mathcal{C}_n \subset B_{nw}^Z(\mathbf{0}) \\ R(\mathcal{C}_n) \geq R}} \tau_L(\mathcal{C}_n).$$

5.2 List-decoding Plotkin point

Let $\tau_L(w) := w - w^L$ and $\tau_L := \max_{0 \leq w \leq 1} \tau_L(w)$. With slight abuse of notation, we write w_{\max} to denote the argument of w that attains the maximum of $\tau_L(w)$. It is not hard to check that $\tau_L(w)$ is concave in w and the maximizer w_{\max} equals $L^{-\frac{1}{L-1}}$. Note that w_{\max} is increasing in L . The minimum value of w_{\max} over all $L \in \mathbb{Z}_{\geq 2}$ is $1/2$ when $L = 2$ and $w_{\max} \xrightarrow{L \rightarrow \infty} 1$. Therefore $\tau_L = L^{-\frac{1}{L-1}} - L^{-\frac{L}{L-1}} = (1 - L^{-1})L^{-\frac{1}{L-1}} = (L - 1)L^{-\frac{L}{L-1}}$. Note that τ_L is increasing in L and attains its minimum value $1/4$ at $L = 2$. Furthermore, $\tau_L \xrightarrow{L \rightarrow \infty} 1$.

5.3 Upper bound for constant-weight codes

Fix $w \in (0, 1)$. Consider an arbitrary code \mathcal{C} of constant-weight w for the Z-channel with noise level $\tau = \tau_L(w) + \varepsilon$. Let $M := |\mathcal{C}|$. It was shown in [10] via a double-counting argument that

$$\frac{M^L}{M(M-1)\cdots(M-L+1)} \geq \frac{\tau}{\tau_L(w)}. \quad (6)$$

Rearranging terms, we get

$$\begin{aligned} & (M(M-1)\cdots(M-L+1))(\tau_L(w) + \varepsilon) \leq M^L \tau_L(w) \\ \implies & (M(M-1)\cdots(M-L+1))\varepsilon \leq (M^L - M(M-1)\cdots(M-L+1))\tau_L(w) \\ \implies & \frac{M(M-1)\cdots(M-L+1)}{M^L - M(M-1)\cdots(M-L+1)} \leq \frac{\tau_L(w)}{\varepsilon}. \end{aligned}$$

Applying Taylor expansion to the LHS of the above inequality, we get

$$\begin{aligned} \frac{M}{\binom{L}{2}} - O_L(1) &\leq \frac{\tau_L(w)}{\varepsilon} \\ \implies & M \leq \frac{C_{L,w}}{\varepsilon} + O_L(1), \end{aligned}$$

where $C_{L,w} := \tau_L(w) \binom{L}{2} = (w - w^L) \binom{L}{2}$.

We have therefore proved the following theorem.

Theorem 7. *Any w -constant-weight list-decodable code \mathcal{C} for the Z-channel with list-decoding radius $w - w^L + \varepsilon$ has size at most $\frac{C_{L,w}}{\varepsilon} + O_L(1)$ where $C_{L,w} := (w - w^L) \binom{L}{2}$.*

5.4 Construction of constant-weight codes

In this section, we construct codes of constant-weight w whose list-decoding radius is ε -above the list-decoding Plotkin point $\tau_L(w)$ for Z-channels. The code we construct has size $\Theta(1/\varepsilon)$, which is optimal by the upper bound in the preceding section. Our construction is inspired by [14].

We prove the following theorem.

Theorem 8. *There exists an $(L-1)$ -list-decodable code \mathcal{C} for the Z-channel with list-decoding radius $w - w^L - \varepsilon$ of size at least $\frac{c_{L,w}}{\varepsilon} + o_{L,w}(1)$ where $c_{L,w} = (1-w)w^{L-1} \binom{L}{2}$.*

Proof. Fix the weight w . Let m be a sufficiently large integer. For simplicity, assume that m/w is an integer. Let $M := m/w$ and $n := \binom{m/w}{m}$. Our construction of \mathcal{C} can be viewed as an $M \times n$ matrix, each row of which is a codeword denoted by \mathbf{x}_i ($1 \leq i \leq M$). The code \mathcal{C} consists of all possible length- (m/w) vectors of Hamming weight m as its *columns*.²

To examine $(L-1)$ -list-decodability of \mathcal{C} , we compute the $(L-1)$ -list-decoding radius $\tau_L(\mathcal{C})$ of \mathcal{C} . By symmetry, the Chebyshev radius $\text{rad}(\mathcal{L})$ of any L -list $\mathcal{L} \in \binom{\mathcal{C}}{L}$ of codewords does not depend on the choice of \mathcal{L} . Therefore, $\tau_L(\mathcal{C}) = \mathbf{E}_{\mathcal{L}}\{\text{rad}(\mathcal{L})\}$ where the expectation is over \mathcal{L} uniformly chosen from $\binom{\mathcal{C}}{L}$. We now compute the latter quantity.

$$\begin{aligned} \mathbf{E}_{\mathcal{L}}\{\text{rad}(\mathcal{L})\} &= nw - \mathbf{E}_{\mathcal{L}} \left\{ \left| \bigcap_{\mathbf{x} \in \mathcal{L}} \text{supp}(\mathbf{x}) \right| \right\} \\ &= nw - \mathbf{E}_{\mathcal{L}} \left\{ \sum_{i \in [n]} \mathbf{1}\{\forall \mathbf{x} \in \mathcal{L}, x_i = 1\} \right\} \end{aligned}$$

²Note that there are $\binom{m/w}{m} = n$ such columns in total.

$$\begin{aligned}
&= nw - \sum_{i \in [n]} \Pr_{\mathcal{L}}\{\forall \mathbf{x} \in \mathcal{L}, x_i = 1\} \\
&= nw - n \frac{\binom{m}{L}}{\binom{m/w}{L}}.
\end{aligned}$$

The last equality follows since the probability in the summation can be viewed as the probability that one gets L ones when sampling without replacement L bits from a length- (m/w) vector of weight m .

Taking the Taylor expansion of the above expression at $m \rightarrow \infty$, we get

$$\tau_L(\mathcal{C}) = \mathbf{E}_{\mathcal{L}}\{\text{rad}(\mathcal{L})\} = n \left(w - w^L + (1-w)w^L \binom{L}{2} m^{-1} + O_{L,w}(m^{-2}) \right).$$

Recall that we want \mathcal{C} to be ε -above the Plotkin point, i.e., $\tau_L(\mathcal{C}) \geq n(\tau_L(w) + \varepsilon) = n(w - w^L + \varepsilon)$. This is satisfied as long as

$$\begin{aligned}
&\varepsilon \leq (1-w)w^L \binom{L}{2} m^{-1} + O_{L,w}(m^{-2}) \\
\iff &\varepsilon \leq (1-w)w^{L-1} \binom{L}{2} M^{-1} + O_{L,w}(M^{-2}) \\
\iff &M \leq \frac{c_{L,w}}{\varepsilon} + o_{L,w}(1),
\end{aligned}$$

where $c_{L,w} := (1-w)w^{L-1} \binom{L}{2}$. This finishes the proof. \square

5.5 Upper bound for approximate constant-weight codes

The proof in Sec. 5.3 can be modified to work for *approximate* constant-weight codes.

Theorem 9. *Let \mathcal{C} be an arbitrary $(L-1)$ -list-decodable code for the Z-channel with list-decoding radius $\tau = w - w^L + \varepsilon$. Suppose that every codeword in \mathcal{C} has weight in $[nw(1-\delta), nw(1+\delta)]$ for some $\delta \in [0, \tau/(2w)]$. Then $M := |\mathcal{C}|$ satisfies the following relation:*

$$\frac{M^L}{M(M-1) \cdots (M-L+1)} \geq \frac{\tau - 2w\delta}{w(1+\delta) - (w(1-\delta))^L}.$$

Remark 1. *If $\delta = 0$, the above theorem recovers Theorem 7.*

Proof. To derive an upper bound on M , we follow a double-counting argument commonly used in coding theory. We bound from both sides the following quantity:

$$\sum_{\mathcal{L} \in [M]^L} \sum_{j \in \mathcal{L}} d_Z(\mathbf{x}_j, \mathbf{y}_{\mathcal{L}}), \tag{7}$$

where $\mathbf{y}_{\mathcal{L}}$ is defined in Eqn. (4).

We first give a lower bound on Eqn. (7). We drop all terms in Eqn. (7) with an \mathcal{L} whose elements are not all distinct. For any \mathcal{L} whose elements are all distinct, by list-decodability,

$$\max_{j \in \mathcal{L}} d_Z(\mathbf{x}_j, \mathbf{y}_{\mathcal{L}}) = \max_{j \in \mathcal{L}} \text{wt}(\mathbf{x}_j) - \text{wt}(\mathbf{y}_{\mathcal{L}}) > n\tau.$$

Since \mathcal{C} is approximate constant-weight, we have $|\text{wt}(\mathbf{x}_i) - \text{wt}(\mathbf{x}_j)| \leq 2nw\delta$ for any $i \neq j$. Therefore, Eqn. (7) is at least $M(M-1) \cdots (M-L+1)(n\tau + (L-1)(n\tau - 2nw\delta))$.

We then give an upper bound on Eqn (7).

$$\sum_{(i_1, \dots, i_L) \in [M]^L} \sum_{j \in [L]} d_Z(\mathbf{x}_{i_j}, \mathbf{y}_{\mathcal{L}}) = \sum_{(i_1, \dots, i_L) \in [M]^L} \sum_{j \in [L]} (\text{wt}(\mathbf{x}_{i_j}) - \text{wt}(\mathbf{y}_{\mathcal{L}}))$$

$$\begin{aligned}
&= \sum_{(i_1, \dots, i_L) \in [M]^L} \sum_{j \in [L]} \left(\text{wt}(\mathbf{x}_{i_j}) - \sum_{k \in [n]} \mathbb{1}\{x_{i_1, k} = 1\} \cdots \mathbb{1}\{x_{i_L, k} = 1\} \right) \\
&\leq M^L L n w (1 + \delta) - \sum_{j \in [L]} \sum_{k \in [n]} \prod_{\ell \in [L]} \left(\sum_{i_\ell \in [M]} \mathbb{1}\{x_{i_\ell, k} = 1\} \right) \\
&= M^L L n w (1 + \delta) - L \sum_{k \in [n]} S_k^L,
\end{aligned}$$

where $S_k := \sum_{i \in [M]} \mathbb{1}\{x_{i, k} = 1\}$ denotes the weight of the k th column of $\mathcal{C} \in \{0, 1\}^{M \times n}$. By the norm comparison inequality $\|\mathbf{x}\|_p \leq n^{1/p-1/q} \|\mathbf{x}\|_q$ for any $\mathbf{x} \in \mathbb{R}^n$ and $0 < p < q$, we have

$$\sum_{k \in [n]} S_k^L \geq n^{1-L} \left(\sum_{k \in [n]} S_k \right)^L \geq n^{1-L} (M n w (1 - \delta))^L = n (M w (1 - \delta))^L.$$

Therefore, Eqn. (7) is upper bounded by $M^L L n w (1 + \delta) - n L (M w (1 - \delta))^L$.

Finally, putting the lower and upper bounds together, we get

$$\begin{aligned}
&M(M-1) \cdots (M-L+1) (n\tau + (L-1)(n\tau - 2nw\delta)) \leq M^L L n w (1 + \delta) - n L (M w (1 - \delta))^L \\
\implies &M(M-1) \cdots (M-L+1) (L\tau - L \cdot 2w\delta) \leq M^L L w (1 + \delta) - L M^L (w(1 - \delta))^L \\
\implies &M(M-1) \cdots (M-L+1) (\tau - 2w\delta) \leq M^L (w(1 + \delta) - (w(1 - \delta))^L) \\
\implies &\frac{M^L}{M(M-1) \cdots (M-L+1)} \geq \frac{\tau - 2w\delta}{w(1 + \delta) - (w(1 - \delta))^L}. \quad \square
\end{aligned}$$

In fact, one can apply a similar trick as that used in the proof of Theorem 5 and obtain a cheaper version of Theorem 9.

Theorem 10. *Let \mathcal{C} be an $(L-1)$ -list-decodable code for the Z-channel with list-decoding radius $\tau > \tau_L$. Suppose that every codeword in \mathcal{C} has weight between nw_1 and nw_2 for some $0 \leq w_1 \leq w_2 \leq 1$. Then*

$$|\mathcal{C}| \leq \frac{L-1}{1 - \left(\frac{w_2/(1+w_2-w_1) - w_2^L/(1+w_2-w_1)^L}{\tau/(1+w_2-w_1)} \right)^{\frac{1}{L-1}}}.$$

Proof. The proof follows by augmenting the code \mathcal{C} to reduce it from approximate constant-weight to exact constant-weight.

Let \mathcal{C} be as described in the theorem statement. One can append $(w_2 - w_1)n$ coordinates to each codeword in \mathcal{C} in such a way that all codewords of length $(1 + w_2 - w_1)n$ have weight exactly $w_2 n$. Note that the relative weight of each codeword is now $\frac{w_2}{1+w_2-w_1}$. Moreover, the augmented code is $(L-1)$ -list-decodable with relative list-decoding radius $\frac{\tau}{1+w_2-w_1}$.

We now recall the upper bound for w -constant-weight code given by Eqn. (6):

$$\begin{aligned}
&\frac{M^L}{M(M-1) \cdots (M-L+1)} \geq \frac{\tau}{w - w^L} \\
\implies &(M-L+1)^{L-1} \tau \leq M^{L-1} (w - w^L) \\
\implies &M \leq \frac{L-1}{1 - \left(\frac{w - w^L}{\tau} \right)^{\frac{1}{L-1}}}.
\end{aligned}$$

Normalizing the parameters by $\frac{1}{1+w_2-w_1}$, we get the desired bound. \square

In the following statement, we estimate the size of a code ε -above the list-decoding Plotkin point if all codewords are of weight ε -close to each other.

Corollary 1. *Let \mathcal{C} be an $(L-1)$ -list-decodable code for the Z-channel with list-decoding radius $\tau = \tau_L + \varepsilon$. Suppose that the relative weight of all codewords is in the range $[w_1, w_2]$, where $w_2 - w_1 \leq \phi_L \varepsilon$ with ϕ_L being a positive real number so that $\phi_L \leq \frac{1-\tau_L}{2\tau_L}$. Then $|\mathcal{C}| \leq \frac{(L-1)^2}{\varepsilon}$ for small enough ε .*

Proof. By Theorem 10 we get that

$$|\mathcal{C}| \leq \frac{L-1}{1 - \left(\frac{w_2/(1+w_2-w_1) - w_2^L/(1+w_2-w_1)^L}{\tau/(1+w_2-w_1)} \right)^{\frac{1}{L-1}}}.$$

After simple manipulation, it remains to show that

$$w_2 - \frac{w_2^L}{(1 + \varepsilon \phi_L)^{L-1}} \leq \left(1 - \frac{\varepsilon}{L-1} \right)^{L-1} (\tau_L + \varepsilon).$$

The LHS of the above inequality achieves its maximum at $w_2 = \frac{1+\varepsilon\phi_L}{L^{1/(L-1)}}$. Thus, after simplification, we get a stronger sufficient condition

$$(1 + \varepsilon \phi_L) \tau_L \leq (1 - \varepsilon) (\tau_L + \varepsilon)$$

or

$$\phi_L \leq \frac{(1 - \tau_L) \varepsilon - \varepsilon^2}{\varepsilon \tau_L}.$$

The latter holds for sufficiently small ε , and the corollary follows. \square

5.6 Upper bound for general codes

For $L \geq 2$ and $\varepsilon > 0$, denote the maximal size of a list-decodable code for the Z-channel with $(L-1)$ -list-decoding radius $\tau_L + \varepsilon$ by $M_L(\varepsilon)$. From Corollary 1 one can immediately see that $M_L(\varepsilon) = O_L(\varepsilon^{-2})$. However, it is possible to improve this bound. In principle, we will follow the same approach as in the proof of Theorem 5. For simplicity of arguments, we assume that some numbers that are introduced in the discussion in this and next subsections are integers since this will not affect the main conclusion.

Theorem 11. *For $L \geq 2$, it holds that $M_L(\varepsilon) = O_L(\varepsilon^{-3/2})$ as $\varepsilon \rightarrow 0$.*

Proof. Let \mathcal{C} be an $(L-1)$ -list-decodable code of length n with $(L-1)$ -list-decoding radius $\tau(\mathcal{C}) = \tau_L + \varepsilon$ for some $\varepsilon > 0$. Recall that w_{\max} is the argument achieving the maximum of the function $w - w^L$ and $\tau_L = w_{\max} - w_{\max}^L$. Consider all codewords whose Hamming weight is between $w_1 n$ and $w_2 n$ with $w_1 < w_2$.

Small weight $w_1 = w_{\max} - \Omega_L(\sqrt{\varepsilon})$: In the following, we analyze the case when $w_1 = w_{\max} - \Omega_L(\varepsilon)$, where w_{\max} is the maximizer of $w - w^L$, i.e. w_{\max} satisfies $1 - Lw_{\max}^{L-1} = 0$. In our analysis, we assume that w_1 is fixed and $\Delta := w_2 - w_1 > 0$ is to be specified. By Theorem 10, the number of codewords of these weights is at most

$$\frac{L-1}{1 - \left(\frac{w_2/(1+w_2-w_1) - w_2^L/(1+w_2-w_1)^L}{\tau(\mathcal{C})/(1+w_2-w_1)} \right)^{\frac{1}{L-1}}}.$$

This quantity is at most $\frac{L-1}{\varepsilon}$ if $\Delta = \Delta(w_1)$ satisfies

$$w_2 - w_2(w_2/(1 + \Delta))^{L-1} \leq \tau(\mathcal{C})(1 - \varepsilon)^{L-1}. \quad (8)$$

Recall that $\tau(\mathcal{C}) = \tau_L + \varepsilon = w_{\max} - w_{\max}^L + \varepsilon$. For any $\gamma > 0$, there exists a sufficiently small $\varepsilon > 0$ such that the RHS of inequality (8) is lower bounded as follows

$$\begin{aligned} \tau(\mathcal{C})(1 - \varepsilon)^{L-1} &\geq (w_{\max} - w_{\max}^L + \varepsilon)(1 - (L-1)\varepsilon) \\ &\geq w_{\max} - w_{\max}^L + \varepsilon(1 - \gamma - (L-1)(w_{\max} - w_{\max}^L)). \end{aligned} \quad (9)$$

Define C_L to be $1 - \gamma - (L-1)(w_{\max} - w_{\max}^L)$. Clearly, for $2 \leq L \leq 3$ and sufficiently small γ , $C_L > 0$, whereas for $L > 3$, $C_L < 0$. Note that $(w_1 + \Delta)(1 + \Delta)^{-1} \geq w_1$. Now we elaborate the LHS of (8):

$$\begin{aligned} w_2 - w_2(w_2/(1 + \Delta))^{L-1} &\leq w_2 - w_1((w_1 + \Delta)(1 + \Delta)^{-1})^{L-1} \\ &\leq w_2 - w_1^L. \end{aligned} \quad (10)$$

Given (8)-(10), we conclude that it is sufficient to take w_2 such that it satisfies

$$w_2 \leq w_{\max} - w_{\max}^L + w_1^L + C_L \varepsilon. \quad (11)$$

Consider the iterative process

$$x_i := w_{\max} - w_{\max}^L + x_{i-1}^L + C_L \varepsilon$$

with starting point $x_1 = 0$. We shall prove by induction that $x_i \geq w_{\max} - \frac{D_L}{i}$ for all $i \in [1, \varepsilon^{-1/2}]$ and some absolute constant $D_L \geq 0$. The base case $i = 1$ holds true if $D_L \geq w_{\max}$. Now assume that the inductive hypothesis is true for some $i > 1$. Recall the Bernoulli inequality $(1 - y)^s \geq 1 - sy$ for any real $y \leq 1$ and $s \geq 1$. Then we obtain

$$\begin{aligned} x_{i+1} &\geq w_{\max} - w_{\max}^L + w_{\max}^L \left(1 - \frac{D_L}{i w_{\max}}\right)^L + C_L \varepsilon \\ &\geq w_{\max} - w_{\max}^L + w_{\max}^L \left(1 - \frac{2D_L}{i w_{\max}} + \frac{D_L^2}{i^2 w_{\max}^2}\right)^{L/2} + C_L \varepsilon \\ &\geq w_{\max} - w_{\max}^L + w_{\max}^L \left(1 - \frac{LD_L}{i w_{\max}} + \frac{LD_L^2}{2i^2 w_{\max}^2}\right) + C_L \varepsilon \\ &\geq w_{\max} - \frac{D_L}{i+1} - \frac{D_L}{i(i+1)} + \frac{D_L^2}{2w_{\max} i^2} + C_L \varepsilon. \end{aligned}$$

Note that for $D_L \geq \max(4w_{\max}, |C_L|)$ and $i \leq \varepsilon^{-1/2}$, the sum of the last three terms is non-negative and the inductive hypothesis follows.

Define the subcode $\mathcal{C}' \subseteq \mathcal{C}$ that includes all codewords of \mathcal{C} with the Hamming weight within the range $[0, n(w_{\max} - D_L \varepsilon^{1/2})]$. The above arguments imply that the size of \mathcal{C}' is $O_L(\varepsilon^{-3/2})$.

Large weight $w_1 = w_{\max} + \Omega_L(\sqrt{\varepsilon})$: Consider the iterative process

$$x_i := w_{\max} - w_{\max}^L + x_{i+1}^L + C_L \varepsilon$$

with starting point $x_1 = w_{\max} + E_L \varepsilon^{1/2}$, where an absolute constant E_L is to be specified. We shall prove by induction that $x_i \geq w_{\max} + \frac{E_L}{\varepsilon^{-1/2} + 1 - i}$ for all $i \in [1, \varepsilon^{-1/2}]$. The base case $i = 1$ holds true. Assume the hypothesis is true for some $i > 1$. Then we obtain

$$\begin{aligned} x_{i+1} &\geq w_{\max} - w_{\max}^L + \left(w_{\max} + \frac{E_L}{\varepsilon^{-1/2} + 1 - i}\right)^L + C_L \varepsilon \\ &= w_{\max} - w_{\max}^L + w_{\max}^L \left(1 + \frac{2E_L}{w_{\max}(\varepsilon^{-1/2} + 1 - i)} + \frac{E_L^2}{w_{\max}^2(\varepsilon^{-1/2} + 1 - i)^2}\right)^{L/2} + C_L \varepsilon \\ &\geq w_{\max} + \frac{E_L}{\varepsilon^{-1/2} + 1 - i} + \frac{E_L^2}{2w_{\max}(\varepsilon^{-1/2} + 1 - i)^2} + C_L \varepsilon \end{aligned}$$

$$= w_{\max} + \frac{E_L}{\varepsilon^{-1/2} - i} + \frac{E_L}{(\varepsilon^{-1/2} + 1 - i)(\varepsilon^{-1/2} - i)} + \frac{E_L^2}{2w_{\max}(\varepsilon^{-1/2} + 1 - i)^2} + C_L \varepsilon.$$

Observe that the sum of the last three terms is non-negative for $E_L \geq \max\{8w_{\max}, |C_L|/2\}$.

Define the subcode $\mathcal{C}'' \subseteq \mathcal{C}$ that includes all codewords of \mathcal{C} with the Hamming weight within the range $[n(w_{\max} + D_L \varepsilon^{1/2}), n]$. The above arguments imply that the size of \mathcal{C}'' is $O_L(\varepsilon^{-3/2})$.

Moderate weight $|w_1 - w_{\max}| = O_L(\sqrt{\varepsilon})$: By Corollary 1 we can partition the set of codewords with weight $[n(w_{\max} - D_L \varepsilon^{1/2}), n(w_{\max} + E_L \varepsilon^{1/2})]$ into $O_L(\varepsilon^{-1/2})$ subcodes such that each of them has size $O_L(\varepsilon^{-1})$.

Summing up the above discussion, we conclude that the size of \mathcal{C} can be bounded as $O_L(\varepsilon^{-3/2})$ as $\varepsilon \rightarrow 0$. \square

5.7 Construction of general codes

In this section we construct $(L-1)$ -list-decodable codes of size $\Omega_L(\varepsilon^{-3/2})$ and length $\exp(\Theta(\varepsilon^{-3/2}))$ whose list-decoding radius is $\tau_L + \varepsilon$. For this purpose, we follow the arguments as used in the case of uniquely-decodable codes. This construction is order-optimal by the upper bound for general codes.

Theorem 12. *There exists an $(L-1)$ -list-decodable code of length $\exp(O_L(\varepsilon^{-3/2}))$ whose list-decoding radius is $\tau_L + \varepsilon$. Furthermore, its size is $\Omega_L(\varepsilon^{-3/2})$ as $\varepsilon \rightarrow 0$.*

Proof. Recall that w_{\max} is the argument attaining the maximum of the function $\tau_L(w)$. Consider the positive integer $m := 1/\varepsilon$. Let $J := \{-\sqrt{(w_{\max} - w_{\max}^2)m/2}, \dots, \sqrt{(w_{\max} - w_{\max}^2)m/2}\}$. For every $j \in J$, denote $n_j := \binom{m}{w_{\max}m - j}$. Consider a binary matrix A_j of size $m \times n_j$, whose columns are all possible binary vectors of length m and weight $w_{\max}m - j$. By Theorem 8, we get that the code formed by rows of matrix A_j is an $(L-1)$ -list-decodable with the list-decoding radius τ_j , where

$$\tau_j := w'_j - w_j^{L-1} + (1 - w'_j)w_j^{L-1} \binom{L}{2} m^{-1} + O_L(m^{-2}), \quad w'_j := \frac{mw_{\max} - j}{m}.$$

Clearly, we have

$$\begin{aligned} \min_{j \in J} \tau_j &= w_{\max} - w_{\max}^L + \min_{j \in J} \left(\frac{jLw_{\max}^{L-1}}{m} - \frac{j}{m} - \frac{j^2 \binom{L}{2} w_{\max}^{L-2}}{m^2} \right) + (1 - w_{\max})w_{\max}^{L-1} \binom{L}{2} m^{-1} + o_L(m^{-1}) \\ &= w_{\max} - w_{\max}^L + (1 - w_{\max}) \frac{L-1}{4m} + o_L(m^{-1}) \\ &= \tau_L + \Omega_L(\varepsilon). \end{aligned} \tag{12}$$

For a positive integer z , consider a matrix $A_j^{(z)}$ of size $2m \times zn_j$ which is composed of z copies of the matrix A_j . We write copies of A_j to the right, i.e., $A_j^{(z)} = (A_j, A_j, \dots, A_j)$. By $\tilde{A}_j^{(z)}$ denote a matrix obtained from $A_j^{(z)}$ by a random permutation of its columns. This permutation is taken uniformly at random from the set of all permutations. Note that the list-decoding radius of the code formed by $\tilde{A}_j^{(z)}$ is the same as for the code given by A_j . Define integers

$$z_j := \prod_{i \in J \setminus \{j\}} \binom{m}{w_{\max}m - i}, \quad N := \prod_{i \in J} \binom{m}{w_{\max}m - i}, \quad M := m|J|.$$

Consider a random matrix A of size $M \times N$ containing $\tilde{A}_j^{(z_j)}$ as a submatrix for all $j \in J$. We assume that matrices $\tilde{A}_j^{(z_j)}$ are written one below the other using the ascending order of

parameter j . For $\varepsilon \rightarrow 0$, we estimate the number of rows M and the number of columns N in A as follows

$$M = \Omega_L(\varepsilon^{-3/2}), \quad N = \exp(\Theta_L(\varepsilon^{-3/2})).$$

We claim that with high probability, rows of matrix A form an $(L-1)$ -list-decodable code with the list-decoding radius $\tau_L + \Omega_L(\varepsilon)$. Let us take L random codewords $\mathbf{x}_1, \dots, \mathbf{x}_L$ from different subcodes induced by $\tilde{A}_{j_1}^{(z_{j_1})}, \dots, \tilde{A}_{j_L}^{(z_{j_L})}$ with $j_1 < j_2 < \dots < j_L$. For this purpose, we compute the expectation of the Chebyshev radius for this given L -list $\mathcal{L} = \{\mathbf{x}_1, \dots, \mathbf{x}_L\}$ of codewords. Before proceeding with the latter we recall that the Hamming weight of \mathbf{x}_k is $N \frac{w_{\max} m - j_k}{m}$. Thus, we have

$$\begin{aligned} \mathbf{E}\{\text{rad}(\mathcal{L})\} &= N \frac{w_{\max} m - j_1}{m} - N \prod_{k=1}^L \frac{w_{\max} m - j_k}{m} \\ &= N \left(w_{\max} - w_{\max}^L + \frac{w_{\max}^{L-1} \sum_{k=1}^L j_k - j_1}{m} + o_L(m^{-1}) \right) \\ &= N \left(w_{\max} - w_{\max}^L + \frac{\frac{1}{L} \sum_{k=1}^L j_k - j_1}{m} + o_L(m^{-1}) \right). \end{aligned}$$

This means that for any list of L codewords from different subcodes, their relative Chebyshev radius is concentrated above

$$\tau_L + \min_{\substack{j_1, \dots, j_L \in J \\ j_1 < \dots < j_L}} \frac{\frac{1}{L} \sum_{k=1}^L j_k - j_1}{m} + o_L(m^{-1}) = \tau_L + \Omega_L(m^{-1}) = \tau_L + \Omega_L(\varepsilon). \quad (13)$$

Now consider a more general case, when some codewords of $\mathcal{L} = \{\mathbf{x}_1, \dots, \mathbf{x}_L\}$ could be from the same subcode, i.e., it holds that \mathbf{x}_k is a row from $\tilde{A}_{j_k}^{(z_{j_k})}$ for all $k \in [L]$ and $j_1 \leq j_2 \leq \dots \leq j_L$. If the whole list is from the same subcode, then their list-decoding radius is at least $\tau_L + \Omega_L(\varepsilon)$ by Eqn. (12). If not, then one can argue that the list-decoding radius is again at least (13). \square

5.8 Upper bound on $(L-1)$ -list-decoding capacity

In this and the next sections, we will bound $C_{L-1}(w, \tau)$ for $\tau < w - w^L$. We note that for such a purpose, it suffices to consider constant-weight codes. This is because for any general code \mathcal{C} of size M , one can find a constant-weight subcode $\mathcal{C}' \subseteq \mathcal{C}$ of size at least $M/(n+1)$. The rate of \mathcal{C} and \mathcal{C}' is asymptotically (in n) the same.

In this section, we derive an upper bound on the size of any list-decodable code for the Z-channel. At a high level, the proof follows the idea of Elias and Bassalygo [1]. The idea is to *cover* the space where the code is living using Hamming balls³. The radius of the balls is carefully chosen so that there can only be a *constant* number of codewords in the each ball satisfying the list-decodability condition. Then the total number of codewords is bounded by the covering number times a constant. We flesh out the detail below.

We first present a covering lemma that will be useful in the proof of the upper bound.

Lemma 13. *Let $w, v \in (0, 1)$ and $\max(0, w + v - 1) \leq a \leq \min(w, v)$. Define*

$$I(w, v, a) := (1 - w - v + a) \log \frac{1 - w - v + a}{(1 - w)(1 - v)} + (v - a) \log \frac{v - a}{(1 - w)v} + (w - a) \log \frac{w - a}{w(1 - v)} + a \log \frac{a}{wv}.$$

³In fact, it is more convenient for us to consider sets that are slightly more structured than Hamming balls which will be specified in the proceeding proof.

to be the mutual information of the joint distribution $P_{U,X} := \begin{bmatrix} 1-w-v+a & v-a \\ w-a & a \end{bmatrix}$.⁴ Then for any $\varepsilon > 0$, there exists a covering $\mathcal{D} \subset S_{nw}^H(\mathbf{0})$ of $S_{nw}^H(\mathbf{0})$ satisfying: for any $\mathbf{x} \in S_{nw}^H(\mathbf{0})$, there is a $\mathbf{u} \in \mathcal{D}$ such that $T_{\mathbf{u},\mathbf{x}} = P_{U,X}$. Furthermore, the size of \mathcal{D} is at most $2^{n(I(w,v,a)+\varepsilon)}$.

Proof. We will show that with high probability a random subset \mathcal{D} of $S_{nw}^H(\mathbf{0})$ is a covering of $S_{nw}^H(\mathbf{0})$. Indeed, we sample $M := 2^{n(I(w,v,a)+\varepsilon)}$ vectors uniformly at random from all weight- nv vectors and call such a set \mathcal{D} . The probability that some sequence \mathbf{x} in $S_{nw}^H(\mathbf{0})$ is not covered by any vector in \mathcal{D} can be bounded as follows:

$$\begin{aligned}
& \Pr\{\exists \mathbf{x} \in S_{nw}^H(\mathbf{0}), \forall \mathbf{u} \in \mathcal{D}, T_{\mathbf{u},\mathbf{x}} \neq P_{U,X}\} \\
& \leq \sum_{\mathbf{x} \in S_{nw}^H(\mathbf{0})} \prod_{\mathbf{u} \in \mathcal{D}} (1 - \Pr\{T_{\mathbf{u},\mathbf{x}} = P_{U,X}\}) \\
& = \sum_{\mathbf{x} \in S_{nw}^H(\mathbf{0})} \prod_{\mathbf{u} \in \mathcal{D}} \left(1 - \frac{\binom{n(1-w)}{n(v-a)} \binom{nw}{na}}{\binom{n}{nv}}\right) \\
& = \binom{n}{nw} \left(1 - 2^{n(1-w)H\left(\frac{v-a}{1-w}\right) + nwH\left(\frac{a}{w}\right) - nH(v) + o(n)}\right)^M \\
& \leq 2^{nH(w)} \left(1 - 2^{nI(w,v,a) + o(n)}\right)^{2^{nI(w,v,a)} 2^{n\varepsilon}} \\
& \xrightarrow{n \rightarrow \infty} 2^{nH(w)} e^{-2^{n\varepsilon}} \\
& = e^{-2^{n\varepsilon} + O_L(n)}.
\end{aligned} \tag{14}$$

In Eqn. (14), we used the fact $\lim_{n \rightarrow \infty} (1 - 1/n)^n = 1/e$. Therefore, with probability at least $1 - e^{-2^{\Omega(n)}}$, \mathcal{D} is a covering of $S_{nw}^H(\mathbf{0})$ w.r.t. $P_{U,X}$. This finishes the proof of the lemma. \square

We are now ready to prove the upper bound which reads as follows.

Theorem 14. Fix $0 < w < 1$. Let \mathcal{C} be a w -constant-weight list-decodable code for the Z-channel of length n with list-decoding radius τ . Then for $n \rightarrow \infty$

$$R(\mathcal{C}) \leq \min_{\substack{0 \leq v \leq 1, \max(0, w+v-1) \leq a \leq \min(w, v) \\ (1-v) \left[\frac{w-a}{1-v} - \left(\frac{w-a}{1-v}\right)^L \right] + v \left[\frac{a}{v} - \left(\frac{a}{v}\right)^L \right] \leq \tau}} I(w, v, a) + o(1),$$

where $I(w, v, a)$ was defined in Lemma 13.

Proof. By Lemma 13, for any list-decodable code \mathcal{C} with constant-weight nw , one can find a weight- nv covering \mathcal{D} w.r.t. a joint distribution $P_{U,X}$ as specified in Lemma 13, where the parameters v and a are to be optimized later and \mathcal{D} satisfies the properties given by the lemma.

For each $\mathbf{u} \in S_{nv}^H(\mathbf{0})$, define the following *jointly typical set* $A(\mathbf{u}, P_{U,X})$ w.r.t. the joint distribution $P_{U,X}$:

$$A(\mathbf{u}, P_{U,X}) := \{\mathbf{x} \in S_{nw}^H(\mathbf{0}) : T_{\mathbf{u},\mathbf{x}} = P_{U,X}\}. \tag{15}$$

By the covering property of \mathcal{D} , we have

$$\begin{aligned}
& S_{nw}^H(\mathbf{0}) = \bigcup_{\mathbf{u} \in \mathcal{D}} A(\mathbf{u}, P_{U,X}) \\
\Rightarrow & S_{nw}^H(\mathbf{0}) \cap \mathcal{C} = \left(\bigcup_{\mathbf{u} \in \mathcal{D}} A(\mathbf{u}, P_{U,X}) \right) \cap \mathcal{C}
\end{aligned}$$

⁴Note that the marginal P_X of $P_{U,X}$ is $\text{Bern}(w)$ and the marginal P_U of $P_{U,X}$ is $\text{Bern}(v)$.

$$\begin{aligned} \Rightarrow & \mathcal{C} = \bigcup_{\mathbf{u} \in \mathcal{D}} (A(\mathbf{u}, P_{U,X}) \cap \mathcal{C}) \\ \Rightarrow & |\mathcal{C}| \leq \sum_{\mathbf{u} \in \mathcal{D}} |A(\mathbf{u}, P_{U,X}) \cap \mathcal{C}|. \end{aligned}$$

For each $\mathbf{u} \in \mathcal{D}$, define $\mathcal{C}_{\mathbf{u}} := A(\mathbf{u}, P_{U,X}) \cap \mathcal{C}$. By Markov's inequality, there must be a $\mathbf{u}^* \in \mathcal{D}$ such that $|\mathcal{C}_{\mathbf{u}^*}| \geq |\mathcal{C}|/|\mathcal{D}|$. We further define the punctured subcodes of $\mathcal{C}_{\mathbf{u}^*}$ w.r.t. \mathbf{u}^* . For $u \in \{0, 1\}$, let $\mathcal{C}_{\mathbf{u}^*, u} := \{(x_i)_{i \in [n]}, u_i^* = u : \mathbf{x} \in \mathcal{C}\}$ be the subcode obtained by restricting codewords in \mathcal{C} to the coordinates i 's where $u_i^* = u$. Note that $\mathcal{C}_{\mathbf{u}^*, 1} \in \{0, 1\}^{nv}$ and $\mathcal{C}_{\mathbf{u}^*, 0} \in \{0, 1\}^{n(1-v)}$.

The punctured subcodes $\mathcal{C}_{\mathbf{u}^*, 0}$ and $\mathcal{C}_{\mathbf{u}^*, 1}$ enjoy the following property. For $u \in \{0, 1\}$, all codewords in $\mathcal{C}_{\mathbf{u}^*, u}$ have the same type $P_{X|U=u}$. That is, every codeword in $\mathcal{C}_{\mathbf{u}^*, 0}$ has weight $w - a$ and every codeword in $\mathcal{C}_{\mathbf{u}^*, 1}$ has weight a . Clearly, $|\mathcal{C}_{\mathbf{u}^*}| \leq |\mathcal{C}_{\mathbf{u}^*, 0}| \cdot |\mathcal{C}_{\mathbf{u}^*, 1}|$.

Suppose that there are $n\tau_0$ errors in the locations i 's such that $u_i^* = 0$ and there are $n\tau_1$ errors in the locations j 's such that $u_j^* = 1$. The parameters τ_0 and τ_1 satisfy $\tau_0 + \tau_1 \leq \tau$. As long as the following two conditions are satisfied,

$$\frac{\tau_0}{1-v} > \frac{w-a}{1-v} - \left(\frac{w-a}{1-v}\right)^L, \quad \frac{\tau_1}{v} > \frac{a}{v} - \left(\frac{a}{v}\right)^L,$$

both $|\mathcal{C}_{\mathbf{u}^*, 0}|$ and $|\mathcal{C}_{\mathbf{u}^*, 1}|$ are at most a constant (independent of n) by Theorem 7. Specifically, if

$$\frac{\tau_0}{1-v} = \frac{w-a}{1-v} - \left(\frac{w-a}{1-v}\right)^L + \varepsilon, \quad \frac{\tau_1}{v} = \frac{a}{v} - \left(\frac{a}{v}\right)^L + \varepsilon,$$

then

$$|\mathcal{C}_{\mathbf{u}^*, 0}| \leq \frac{C_0}{\varepsilon} + O_L(1), \quad |\mathcal{C}_{\mathbf{u}^*, 1}| \leq \frac{C_1}{\varepsilon} + O_L(1),$$

where

$$C_0 := \left[\frac{w-a}{1-v} - \left(\frac{w-a}{1-v}\right)^L \right] \binom{L}{2}, \quad C_1 := \left[\frac{a}{v} - \left(\frac{a}{v}\right)^L \right] \binom{L}{2}.$$

Therefore

$$|\mathcal{C}| \leq |\mathcal{C}_{\mathbf{u}^*}| \cdot |\mathcal{D}| \leq |\mathcal{C}_{\mathbf{u}^*, 0}| \cdot |\mathcal{C}_{\mathbf{u}^*, 1}| \cdot |\mathcal{D}| \leq \left(\frac{C_0}{\varepsilon} + O_L(1)\right) \cdot \left(\frac{C_1}{\varepsilon} + O_L(1)\right) \cdot 2^{n(I(w,v,a)+\varepsilon)},$$

and $R(\mathcal{C}) \leq I(w, v, a) + \varepsilon + o(1)$. Taking $\varepsilon \rightarrow 0$ finishes the proof. \square

Though not used in the proof of Theorem 14, the upper bound on the size of a covering given in Lemma 13 is actually tight (on the exponential scale). Such a converse follows from a simple sphere-covering-type argument as below.

Lemma 15. *Let $I(w, v, a)$ and $P_{U,X}$ be as defined in Lemma 13. Then any covering $\mathcal{D} \subset S_{nv}^H(\mathbf{0})$ of $S_{nw}^H(\mathbf{0})$ satisfying the property in Lemma 13 has size at least $2^{nI(w,v,a)-o(n)}$.*

Proof. For any $\mathbf{u} \in S_{nv}^H(\mathbf{0})$, we first compute the size of $A(\mathbf{u}, P_{U,X})$ defined in Eqn. (15).

$$|A(\mathbf{u}, P_{U,X})| = \binom{n(1-v)}{n(w-a)} \binom{nv}{na} \leq 2^{n[(1-v)H(\frac{w-a}{1-v}) + vH(\frac{a}{v})]}.$$

Now, by the covering property of \mathcal{D} , we have

$$\begin{aligned} S_{nw}^H(\mathbf{0}) &= \bigcup_{\mathbf{u} \in \mathcal{D}} A(\mathbf{u}, P_{U,X}) \\ \Rightarrow & |S_{nw}^H(\mathbf{0})| \leq \sum_{\mathbf{u} \in \mathcal{D}} |A(\mathbf{u}, P_{U,X})| \\ \Rightarrow & 2^{nH(w)-o(n)} \leq |\mathcal{D}| 2^{n[(1-v)H(\frac{w-a}{1-v}) + vH(\frac{a}{v})]} \\ \Rightarrow & |\mathcal{D}| \geq 2^{n[H(w)-(1-v)H(\frac{w-a}{1-v}) - vH(\frac{a}{v})] - o(n)} = 2^{nI(w,v,a)-o(n)}. \quad \square \end{aligned}$$

5.9 Lower bound on $(L - 1)$ -list-decoding capacity

In this section, our goal is to construct an $(L - 1)$ -list-decodable code $\mathcal{C} \subset \{0, 1\}^n$ for a Z-channel with noise level τ . We would like to obtain a lower bound on the rate $R(\mathcal{C})$ that can be achieved by such a \mathcal{C} .

Before deriving the bound, we first introduce a set of distributions that will play an important role in the proceeding analysis. For any $w \in [0, 1]$ and $\tau \in [0, w]$, define the following set of distributions:

$$\mathcal{K}(w, \tau) := \left\{ P_{X_1, \dots, X_L} \in \mathcal{P}(\{0, 1\}^L) : \begin{array}{l} \forall i \in [L], P_{X_i}(1) = w \\ w - P_{X_1, \dots, X_L}(1, \dots, 1) \leq \tau \end{array} \right\}. \quad (16)$$

In words, $\mathcal{K}(w, \tau)$ is the collection of distributions P_{X_1, \dots, X_L} on length- L binary strings satisfying: (i) each of its marginal P_{X_i} (for $1 \leq i \leq L$) is $\text{Bern}(w)$; (ii) the probability mass $P_{X_1, \dots, X_L}(1, \dots, 1)$ on the all-one string is at least $w - \tau$.

We now describe our construction and analyze it. Our approach follows the standard random coding with expurgation technique. We sample a codebook $\mathcal{C} \subset \{0, 1\}^{M \times n}$ each entry of which is i.i.d. according to $\text{Bern}(w)$.

First, we claim that in expectation a $1/\text{poly}(n)$ fraction of the codewords have weight exactly nw . To see this, note that for any $\mathbf{x} \in \mathcal{C}$,

$$\begin{aligned} \Pr\{\text{wt}(\mathbf{x}) = nw\} &= \binom{n}{nw} w^{nw} (1-w)^{n(1-w)} \\ &= \frac{\sqrt{2\pi n} (n/e)^n}{\sqrt{2\pi n w (nw/e)^{nw}} \sqrt{2\pi (1-w)} (n(1-w)/e)^{n(1-w)}} (1 - O_L(n^{-1})) w^{nw} (1-w)^{n(1-w)} \\ &= \frac{1}{\sqrt{2\pi n w (1-w)}} (1 - O_L(n^{-1})), \end{aligned}$$

where the second step is by Stirling's approximation $n! = \sqrt{2\pi n} (n/e)^n (1 + O_L(n^{-1}))$. Therefore,

$$\mathbf{E}|\{\mathbf{x} \in \mathcal{C} : \text{wt}(\mathbf{x}) = nw\}| = \frac{M}{\sqrt{2\pi n w (1-w)}} (1 - O_L(n^{-1})).$$

Second, we compute the expected number of *bad* L -lists, i.e., those L -lists whose list-decoding radius is at most $n\tau$. For any list $\mathcal{L} \in \binom{\mathcal{C}}{L}$ of codewords all of weight nw , it is clear that $\text{rad}(\mathcal{L}) \leq n\tau$ (where $\text{rad}(\mathcal{L})$ was defined in Eqn. (5)) if and only if the joint type $T_{\mathcal{L}}$ of \mathcal{L} is in $\mathcal{K}(w, \tau)$. By Sanov's theorem (Theorem 4),

$$\begin{aligned} -\frac{1}{n} \log \Pr\{\text{rad}(\mathcal{L}) \leq n\tau\} &= -\frac{1}{n} \log \Pr\{T_{\mathcal{L}} \in \mathcal{K}(w, \tau)\} \\ &\xrightarrow{n \rightarrow \infty} \min_{P_{X_1, \dots, X_L} \in \mathcal{K}(w, \tau)} D(P_{X_1, \dots, X_L} \| \text{Bern}^{\otimes L}(w)) =: E(w, \tau). \end{aligned}$$

Therefore, for sufficiently large n , we have

$$\mathbf{E} \left| \left\{ \mathcal{L} \in \binom{\mathcal{C}}{L} : \text{rad}(\mathcal{L}) \leq n\tau \right\} \right| = \binom{M}{L} 2^{-nE(w, \tau)(1-o(1))}.$$

Finally, we expurgate all codewords whose weights are not exactly nw ; we also expurgate one codeword from each of the *bad* L -lists \mathcal{L} , i.e., those \mathcal{L} such that $\text{rad}(\mathcal{L}) \leq n\tau$. If

$$\begin{aligned} \binom{M}{L} 2^{-nE(w, \tau)(1-o(1))} &\leq \frac{M}{2\sqrt{2\pi n w (1-w)}} (1 - O_L(n^{-1})) \\ \Leftarrow M^L 2^{-nE(w, \tau)(1-o(1))} &\leq \frac{M}{2\sqrt{2\pi n w (1-w)}} (1 - O_L(n^{-1})) \end{aligned}$$

$$\begin{aligned} \Leftarrow & \quad RL - E(w, \tau)(1 - o(1)) \leq R(1 - o(1)) \\ \Leftarrow & \quad R \leq \frac{E(w, \tau)}{L - 1}(1 - o(1)), \end{aligned}$$

then after expurgation, we are left with at least $\frac{M}{2\sqrt{2\pi n w(1-w)}}(1 - O(n^{-1}))$ codewords which form an $(L - 1)$ -list-decodable code $\mathcal{C}' \subset \mathcal{C}$. Note that the rate $R(\mathcal{C}')$ is asymptotically equal to $R(\mathcal{C})$.

Therefore, we have proved the following theorem.

Theorem 16. *There exist w -constant-weight $(L - 1)$ -list-decodable codes for the Z-channel with list-decoding radius $\tau < \tau_L(w)$ of rate at least*

$$\frac{1}{L - 1} \min_{P_{X_1, \dots, X_L} \in \mathcal{K}(w, \tau)} D(P_{X_1, \dots, X_L} \parallel \text{Bern}^{\otimes L}(w)),$$

where $\mathcal{K}(w, \tau)$ was defined in Eqn. 16.

5.10 List-decoding capacity

Obtaining the exact $(L - 1)$ -list-decoding capacity for the Z-channel is a difficult question and we are only able to derive nonmatching upper and lower bounds in Sec. 5.8 and 5.9 respectively. Nevertheless, we can compute the list-decoding capacity $C_{L-1}(w, \tau)$ when L is sufficiently large. Specifically, we determine the limit $\lim_{L \rightarrow \infty} C_{L-1}(w, \tau)$ using the following two lemmas.

Define

$$C_{\text{LD}}(w, \tau) := -(1 - w + \tau) \log(1 - w + \tau) + \tau \log \tau - w \log w. \quad (17)$$

Note that for any fixed w , $C_{\text{LD}}(w, \tau)$ is convex and decreasing in τ . It attains its maximum value $H(w)$ at $\tau = 0$ and attains its minimum value 0 at $\tau = w$. Furthermore, $C_{\text{LD}}(w, \tau)$ is concave in w and attains its maximum value at $w = \frac{1+\tau}{2}$ for any fixed τ . The corresponding maximum value is $C_{\text{LD}}(\tau) := -(1 + \tau) \log \frac{1+\tau}{2} + \tau \log \tau$ which is in turn convex and decreasing with maximum value 1 at $\tau = 0$ and minimum value 0 at $\tau = 1$.

Lemma 17 (Upper bound). *For any $\delta \in (0, 1)$, any w -constant-weight code of rate $C_{\text{LD}}(w, \tau) + \delta$ for the Z-channel with error fraction τ is not $(L - 1)$ -list-decodable for any $L < 2^{n\delta + o(n)}$.*

Proof. Let \mathcal{C} be any w -constant-weight code of rate $C_{\text{LD}}(w, \tau) + \delta$. To show non-list-decodability, we need to exhibit a *bad* center \mathbf{y} such that the Z-ball around \mathbf{y} of radius $n\tau$ contains at least $2^{n\delta + o(n)}$ codewords from \mathcal{C} . Indeed, we will show that a random \mathbf{y} has such a property. Specifically, let \mathbf{y} be uniformly distributed among all vectors of weight $n(w - p)$. We compute the expected number of codewords in $B_{n\tau}^Z(\mathbf{y})$.

$$\begin{aligned} \mathbf{E}|B_{n\tau}^Z(\mathbf{y}) \cap \mathcal{C}| &= \sum_{\mathbf{x} \in \mathcal{C}} \Pr\{B_{n\tau}^Z(\mathbf{y}) \ni \mathbf{x}\} \\ &= \sum_{\mathbf{x} \in \mathcal{C}} \Pr\{\text{supp}(\mathbf{y}) \subseteq \text{supp}(\mathbf{x})\} \\ &= \sum_{\mathbf{x} \in \mathcal{C}} \frac{\binom{nw}{n(w-p)}}{\binom{n}{n(w-p)}} \\ &= 2^{nC_{\text{LD}}(w, \tau) + n\delta} 2^{n(wH(\frac{w-p}{w}) - H(w-p)) + o(n)} \\ &= 2^{n\delta + o(n)}. \end{aligned}$$

This finishes the proof. □

Lemma 18 (Construction). *For any $\delta \in (0, 1)$ and any $L > 1/\delta$, there exist $(L-1)$ -list-decodable codes for the Z-channel with error fraction τ of rate $C_{\text{LD}}(w, \tau) - \delta$.*

Proof. First note that if $\tau \geq w$, the capacity is trivially zero under any constant list size since the channel can zero out all bits in any codeword and the list size has to be as large as the code size. In the proof we therefore assume $\tau < w$.

Let $\mathcal{C} \subset \{0, 1\}^n$ be a collection of $M := 2^{nR}$ (where $R = C_{\text{LD}}(w, \tau) - \delta$) random vectors $\mathbf{x}_1, \dots, \mathbf{x}_M$ each of which is i.i.d. chosen from the set of all weight- nw binary vectors. If a codeword $\mathbf{x} \in \mathcal{C}$ is input to the channel, the weight of the output vector $\mathbf{y} \in \{0, 1\}^n$ is in the range $[n(w - \tau), nw]$. A vector $\mathbf{y} \in \{0, 1\}^n$ of weight in $[n(w - \tau), nw]$ can result from $\mathbf{x} \in \mathcal{C}$ through the channel if and only if $\text{supp}(\mathbf{y}) \subseteq \text{supp}(\mathbf{x})$. We compute the probability that this happens to a random codeword $\mathbf{x} \in \mathcal{C}$. For any fixed $\mathbf{y} \in \{0, 1\}^n$ of weight nu where $u \in [w - \tau, w]$, we have

$$\Pr\{\text{supp}(\mathbf{y}) \subseteq \text{supp}(\mathbf{x})\} = \frac{\binom{n(1-u)}{n(w-u)}}{\binom{n}{nw}} \leq 2^{n(1-u)H\left(\frac{w-u}{1-u}\right) - nH(w) + o(n)}.$$

Therefore, the probability that such a random code \mathcal{C} is not $(L-1)$ -list-decodable is:

$$\begin{aligned} & \Pr\{\mathcal{C} \text{ is not } (L-1)\text{-list-decodable}\} \\ & \leq \Pr\left\{\exists\{i_1, \dots, i_L\} \in \binom{[M]}{L}, \exists \mathbf{y} \in \{0, 1\}^n, \text{ s.t. } \text{wt}(\mathbf{y}) \in [n(w - \tau), nw]; \forall j \in [L], \text{supp}(\mathbf{y}) \subseteq \text{supp}(\mathbf{x}_{i_j})\right\} \\ & \leq \binom{M}{L} 2^n \max_{w-\tau \leq u \leq w} \left(2^{n(1-u)H\left(\frac{w-u}{1-u}\right) - nH(w) + o(n)}\right)^L \\ & \leq \max_{w-\tau \leq u \leq w} 2^{nRL + n + nL[(1-u)H\left(\frac{w-u}{1-u}\right) - H(w) + o(1)]} \\ & \leq 2^{n[RL + 1 + L((1-w+\tau)H\left(\frac{\tau}{1-w+\tau}\right) - H(w) + o(1))]} \end{aligned} \tag{18}$$

The last inequality follows since the function $f_w(u) := (1-u)H\left(\frac{w-u}{1-u}\right)$ has the following property. For any fixed w , $f_w(u)$ is concave and decreasing in $u \in [0, w]$, and therefore in the domain $u \in [w - \tau, w]$ it attains its maximum at $u = w - \tau$.

By elementary algebraic manipulation, we have

$$(1 - w + \tau)H\left(\frac{\tau}{1 - w + \tau}\right) - H(w) = -C_{\text{LD}}(w, \tau).$$

Recall $R = C_{\text{LD}}(w, \tau) - \delta$. Then the exponent (normalized by n^{-1}) of the RHS of the inequality (18) equals

$$(C_{\text{LD}}(w, \tau) - \delta)L + 1 - C_{\text{LD}}(w, \tau)L + o(1) = -\delta L + 1 + o(1),$$

which is negative if $L > 1/\delta + o(1)$. That is, the probability that \mathcal{C} is $(L-1)$ -list-decodable is at least $1 - 2^{-\Omega(n)}$ for any $L > 1/\delta + o(1)$. \square

Lemma 17 and 18 imply the following characterization.

Theorem 19 (List-decoding capacity). *The $(L-1)$ -list-decoding capacity of the Z-channel with error fraction τ under input constraint w is given by $\lim_{L \rightarrow \infty} C_{L-1}(w, \tau) = C_{\text{LD}}(w, \tau)$ as defined in Eqn. (5.10).*

6 Capacity of stochastic Z-channels

In all other sections of this paper, we considered Z-channels with *adversarial* errors. In this section, we derive the capacity of *stochastic* Z-channels from Shannon’s seminal channel coding theorem.

To this end, we first state Shannon’s theorem for general discrete memoryless channels (DMCs). Let \mathcal{X} and \mathcal{Y} be two finite sets denoting the input and output alphabets of the channel. A DMC is a stochastic matrix $W_{Y|X}$ that maps a distribution over \mathcal{X} to a distribution over \mathcal{Y} . When the channel is used n times with an input sequence $\mathbf{x} \in \mathcal{X}^n$, the output sequence $\mathbf{y} \in \mathcal{Y}^n$ follows a product law:

$$\Pr\{\mathbf{y} = (b_1, \dots, b_n) | \mathbf{x} = (a_1, \dots, a_n)\} = \prod_{i=1}^n W_{Y|X}(b_i | a_i),$$

for any $(a_1, \dots, a_n) \in \mathcal{X}^n$ and $(b_1, \dots, b_n) \in \mathcal{Y}^n$.

The DMC is said to be equipped with input constraints $\mathcal{Q} \subset \mathcal{P}(\mathcal{X})$ if the type $T_{\mathbf{x}}$ of any input sequence $\mathbf{x} \in \mathcal{C}$ is required to belong to \mathcal{Q} .

Theorem 20 (Channel coding theorem [16]). *The capacity $C(W_{Y|X})$ of a DMC $W_{Y|X} \in \mathcal{P}(\mathcal{Y}|\mathcal{X})$ with input constraints \mathcal{Q} is given by*

$$C(W_{Y|X}) = \max_{P_X \in \mathcal{Q}} I(X; Y), \quad (19)$$

where the mutual information is evaluated w.r.t. the joint law $P_X W_{Y|X}$.

A discrete memoryless Z-channel is defined as follows. Both the input and output alphabets are binary: $\mathcal{X} = \mathcal{Y} = \{0, 1\}$. The channel transition law is parameterized by the zeroing-out probability τ , i.e., $W_{Y|X}^Z(0|0) = 1$, $W_{Y|X}^Z(0|1) = \tau$. The input constraint is such that all input sequences should have Hamming weight at most nw for some $w \in [0, 1]$. It is easy to evaluate Eqn. (19) which yields $C(W_{Y|X}^Z) = C(w, \tau) = H(w(1 - \tau)) - wH(\tau)$.

We note that for any fixed $w \in [0, 1]$, $C(w, \tau)$ is convex and decreasing in τ . It attains its maximum value $H(w)$ at $\tau = 0$ and attains its minimum value 0 at $\tau = 1$.

We also note that $C(w, \tau)$ is concave in w for any fixed τ . The maximizing w is given by

$$w_{\max} := \left(1 - \tau + \tau^{-\frac{\tau}{1-\tau}}\right)^{-1},$$

and the corresponding capacity $C(\tau) := H(w_{\max}(1 - \tau)) - w_{\max}H(\tau)$ is convex and decreasing with maximum value 1 at $\tau = 0$ and minimum value 0 at $\tau = 1$.

For symmetric (a.k.a. bitflip) errors and erasures, it happens that the capacity of binary symmetric channels and binary erasure channels coincide with the respective list-decoding capacity (under adversarial errors). Comparing the expressions of $C(w, \tau)$ and $C_{LD}(w, \tau)$, we see that this is no longer true for Z-channels.

7 Open problems

1. For codes correcting symmetric (a.k.a. bitflip) errors, the Elias–Bassalygo bound can be improved using Delsarte’s linear program [18]. We do not know how to derive a linear programming-type bound for Z-channels. As far as we know, the linear programming framework, in its most general form, assumes that the ambient space that the code lives in (which is $\{0, 1\}^n$ for general codes and $S_{nw}^H(\mathbf{0})$ for w -constant-weight codes) can be defined as an *association scheme*. We do not see how to do so under the Z-metric $d_Z(\cdot, \cdot)$ since the volume of the intersection of two Z-spheres is not invariant under shifts.

2. The largest code size is exponential in n if the fraction of asymmetric errors the list-decodable code can correct is less than the Plotkin point τ_L and we gave bounds on the exponent in Sec. 5.8 and 5.9; whereas it is $\Theta_L(\varepsilon^{-3/2})$ if the fraction of errors is ε -above τ_L . There is one missing case which we did not solve, that is, what is the largest code size with error fraction being *exactly* τ_L ? We conjecture that in this case the answer is $\Theta_L(n^{3/2})$. Note that the answer to the same question for symmetric errors is $2n$ proved by a geometric argument.

References

- [1] L. A. Bassalygo, “New upper bounds for error correcting codes,” *Problemy Peredachi Informatsii*, vol. 1, no. 4, pp. 41–44, 1965.
- [2] J. Borden, “A low-rate bound for asymmetric error-correcting codes (corresp.),” *IEEE Transactions on Information Theory*, vol. 29, no. 4, pp. 600–602, 1983.
- [3] W. Kim and C. Freiman, “Single error-correcting codes for asymmetric binary channels,” *IRE Transactions on Information Theory*, vol. 5, no. 2, pp. 62–66, 1959.
- [4] R. R. Varshamov, “On the theory of asymmetric codes,” in *Doklady Akademii Nauk*, vol. 164, no. 4. Russian Academy of Sciences, 1965, pp. 757–760.
- [5] T. Kløve, “Upper bounds on codes correcting asymmetric errors (corresp.),” *IEEE Transactions on Information Theory*, vol. 27, no. 1, pp. 128–131, 1981.
- [6] T. Kløve, *Error correcting codes for the asymmetric channel*. Department of Pure Mathematics, University of Bergen, 1981.
- [7] F.-W. Fu, S. Ling, and C. Xing, “New lower bounds and constructions for binary codes correcting asymmetric errors,” *IEEE Transactions on Information Theory*, vol. 49, no. 12, pp. 3294–3299, 2003.
- [8] B. Bose and S. Cunningham, “Asymmetric error correcting codes,” in *Sequences II*. Springer, 1993, pp. 24–35.
- [9] J. Zhang and F.-W. Fu, “A construction of vh-sequences and its application to binary asymmetric error-correcting codes,” *Finite Fields and Their Applications*, vol. 55, pp. 216–230, 2019.
- [10] A. Lebedev, V. Lebedev, and N. Polyanskiy, “Two-stage coding over the z-channel,” *arXiv*, 2020.
- [11] Y. Zhang, A. J. Budkuley, and S. Jaggi, “Generalized list decoding,” in *11th Innovations in Theoretical Computer Science Conference (ITCS 2020)*. Schloss Dagstuhl-Leibniz-Zentrum für Informatik, 2020.
- [12] M. Plotkin, “Binary codes with specified minimum distance,” *IRE Transactions on Information Theory*, vol. 6, no. 4, pp. 445–450, 1960.
- [13] V. Levenshtein, “Application of hadamard matrices on coding problem,” *Problems of Cybernetica*, vol. 5, pp. 123–136, 1961.
- [14] N. Alon, B. Bukh, and Y. Polyanskiy, “List-decodable zero-rate codes,” *IEEE Transactions on Information Theory*, vol. 65, no. 3, pp. 1657–1667, 2018.

- [15] H.-Y. Lin, S. M. Moser, and P.-N. Chen, “Weak flip codes and their optimality on the binary erasure channel,” *IEEE Transactions on Information Theory*, vol. 64, no. 7, pp. 5191–5218, 2018.
- [16] C. E. Shannon, “A mathematical theory of communication,” *The Bell system technical journal*, vol. 27, no. 3, pp. 379–423, 1948.
- [17] I. N. Sanov, *On the probability of large deviations of random variables*. United States Air Force, Office of Scientific Research, 1958.
- [18] R. McEliece, E. Rodemich, H. Rumsey, and L. Welch, “New upper bounds on the rate of a code via the delserte-macwilliams inequalities,” *IEEE Transactions on Information Theory*, vol. 23, no. 2, pp. 157–166, 1977.