

# ADDITIVE POLYCYCLIC CODES OVER $\mathbb{F}_4$ INDUCED BY BINARY VECTORS AND SOME OPTIMAL CODES

AREZOO SOUFI KARBASKI, TAHER ABUALRUB, NUH AYDIN, AND PEIHAN LIU

ABSTRACT. In this paper we study the structure and properties of additive right and left polycyclic codes induced by a binary vector  $a$  in  $\mathbb{F}_2^n$ . We find the generator polynomials and the cardinality of these codes. We also study different duals for these codes. In particular, we show that if  $C$  is a right polycyclic code induced by a vector  $a \in \mathbb{F}_2^n$ , then the Hermitian dual of  $C$  is a sequential code induced by  $a$ . As an application of these codes, we present examples of additive right polycyclic codes over  $\mathbb{F}_4$  with more codewords than comparable optimal linear codes as well as optimal binary linear codes and optimal quantum codes obtained from additive right polycyclic codes over  $\mathbb{F}_4$ .

## 1. PRELIMINARIES

A linear code of length  $n$  over a finite field  $\mathbb{F}$  is a subspace of  $\mathbb{F}^n$ . An Additive code of length  $n$  over a finite field  $\mathbb{F}$  is a subgroup of  $\mathbb{F}^n$ . Additive codes over the finite field  $\mathbb{F}_4 = \{0, 1, \alpha, \alpha^2\}$  where  $\alpha^2 + \alpha + 1 = 0$  were introduced in [3] because of their applications in quantum computing. Define the mapping  $T : \mathbb{F}_4^n \rightarrow \mathbb{F}_4^n$  by  $T((c_0, c_1, \dots, c_{n-1})) = (c_{n-1}, c_0, c_1, \dots, c_{n-2})$ . Cyclic additive codes over  $\mathbb{F}_4^n$  are additive codes over  $\mathbb{F}_4^n$  such that if  $c = (c_0, c_1, \dots, c_{n-1}) \in C$ , then  $T(c) \in C$ .

Let  $C$  be a linear code over a finite field  $\mathbb{F}$ . Right and left linear polycyclic codes over finite fields were introduced in [7]. These codes are generalization of cyclic codes over finite fields. Their properties and structures are studied in details in ([7],[6],[2],[5]).

In this paper, we are interested in studying the structure and the properties of additive right and left polycyclic codes induced by a binary vector  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ . In this work, we consider the important special case where the vector  $a$  has all binary entries. Useful results are obtained in this special case both in terms of the structure of the codes and obtaining codes with good parameters. We give the definition of these codes, study their properties and find their generator polynomials and their cardinality. We also study different duals of these codes and show that if  $C$  is a right polycyclic code induced by a vector  $a \in \mathbb{F}_2^n$ , then the Hermitian dual of  $C$  is a sequential code induced by  $a$ . As an application of our study, we present examples of codes with good parameters. We have three sets of examples. One is a set of additive polycyclic codes that contain more codewords (twice as many) than

---

DEPARTMENT OF MATHEMATICS, BU ALI SINA UNIVERSITY, HAMEDAN, IRAN

DEPARTMENT OF MATHEMATICS & STATISTICS, AMERICAN UNIVERSITY OF SHARJAH, SHARJAH, UAE

DEPARTMENT OF MATHEMATICS & STATISTICS, KENYON COLLEGE, GAMBIER, OH, USA

DEPARTMENT OF MATHEMATICS, UNIVERSITY OF MICHIGAN, ANN ARBOR, MI, USA

*E-mail addresses:* arezoo.sufi@basu.ac.ir, abualrub@aus.edu, aydinn@kenyon.edu, paulliu@umich.edu.

comparable optimal linear codes over  $\mathbb{F}_4$  with the same length and the minimum distance. Another one is a set of best known binary linear codes, most of which are also optimal, that are obtained from additive right polycyclic codes over  $\mathbb{F}_4$  via certain maps. And the third is a set of optimal quantum codes according to the database [4] obtained from additive polycyclic codes.

## 2. INTRODUCTION

Consider the finite field  $\mathbb{F}_4 = \{0, 1, \alpha, \alpha^2\}$  where  $\alpha^2 + \alpha + 1 = 0$ . An additive code  $C$  of length  $n$  over  $\mathbb{F}_4$  is a subgroup of  $(\mathbb{F}_4^n, +)$ .

**Definition 2.1.** Let  $C$  be an additive code over  $\mathbb{F}_4$  and let  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ .  $C$  is called an additive right polycyclic code induced by  $a$ , if for any  $c = (c_0, c_1, \dots, c_{n-1}) \in C$ , we have

$$(0, c_0, c_1, \dots, c_{n-2}) + c_{n-1} (a_0, a_1, \dots, a_{n-1}) \in C.$$

**Definition 2.2.** Let  $C$  be an additive code over  $\mathbb{F}_4$  and let  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ .  $C$  is called an additive left polycyclic code induced by  $a$ , if for any  $c = (c_0, c_1, \dots, c_{n-1}) \in C$ , we have

$$(c_1, c_2, \dots, c_{n-1}, 0) + c_0 (a_0, a_1, \dots, a_{n-1}) \in C.$$

Notice that if  $a = (1, 0, 0, \dots, 0)$ , then right polycyclic codes induced by  $a$  are just the familiar cyclic codes.

Suppose that  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ . As in the case of additive cyclic codes over finite fields, it is useful to have polynomial representations of additive (right or left) polycyclic codes.

Let  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ . The vector  $a$  can be represented as  $a(x) = a_0 + a_1x + \dots + a_{n-1}x^{n-1} \in \mathbb{F}_2[x]$ . Consider the ring  $R_n = \mathbb{F}_4[x] / \langle x^n - a(x) \rangle$ , which is an  $\mathbb{F}_2[x]$ -module. Let  $c(x) = c_0 + c_1x + \dots + c_{n-1}x^{n-1} \in \mathbb{F}_4[x] / \langle x^n - a(x) \rangle$ . Then,

$$\begin{aligned} xc(x) &= c_0x + c_1x^2 + \dots + c_{n-2}x^{n-1} + c_{n-1}x^n \\ &= c_0x + c_1x^2 + \dots + c_{n-2}x^{n-1} + c_{n-1}(a_0 + a_1x + \dots + a_{n-1}x^{n-1}) \\ &= c_{n-1}a_0 + x(c_0 + c_{n-1}a_1) + \dots + x^{n-1}(c_{n-2} + c_{n-1}a_{n-1}). \end{aligned}$$

The polynomial representation of  $xc(x)$  is  $(c_{n-1}a_0, c_0 + c_{n-1}a_1, \dots, c_{n-2} + c_{n-1}a_{n-1}) = (0, c_0, c_1, \dots, c_{n-2}) + c_{n-1}(a_0, a_1, \dots, a_{n-1})$ .

Similarly, let  $c = (c_0, c_1, \dots, c_{n-1}) \in \mathbb{F}_4^n$  be represented by the polynomial  $c(x) = c_{n-1} + c_{n-2}x + \dots + c_0x^{n-1} \in \mathbb{F}_4[x] / \langle x^n - a(x) \rangle$ , where  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$  and  $a(x) = a_{n-1} + a_{n-2}x + \dots + a_0x^{n-1} \in \mathbb{F}_2[x]$ . Then,

$$\begin{aligned} xc(x) &= c_{n-1}x + c_{n-2}x^2 + \dots + c_1x^{n-1} + c_0x^n \\ &= c_{n-1}x + c_{n-2}x^2 + \dots + c_1x^{n-1} + c_0(a_{n-1} + a_{n-2}x + \dots + a_0x^{n-1}) \\ &= c_0a_{n-1} + x(c_{n-1} + c_0a_{n-2}) + \dots + x^{n-1}(c_1 + c_0a_0). \end{aligned}$$

The polynomial representation of  $xc(x)$  is  $(c_1 + c_0a_0, \dots, c_{n-1} + c_0a_{n-2}, c_0a_{n-1}) = (c_1, c_2, \dots, c_{n-1}, 0) + c_0(a_0, a_1, \dots, a_{n-1})$ . Hence, we get the following lemmas.

**Lemma 2.1.**  $C$  is an additive right polycyclic code induced by  $a$  if and only if  $C$  is an  $\mathbb{F}_2[x]$ -submodule of  $R_n$ .

**Lemma 2.2.**  $C$  is an additive left polycyclic code induced by  $a$  if and only if  $C$  is an  $\mathbb{F}_2[x]$ -submodule of  $R_n$ .

Let  $C$  be an additive right polycyclic code induced by  $\mathbf{a}$ . Then  $C$  is invariant under right multiplication by the square matrix

$$D = \begin{bmatrix} 0 & 1 & 0 & 0 & \dots \\ 0 & 0 & 1 & 0 & \dots \\ \vdots & & & \ddots & \\ 0 & 0 & \dots & 0 & 1 \\ a_0 & a_1 & a_2 & \dots & a_{n-1} \end{bmatrix}.$$

Similarly, an additive left polycyclic code induced by  $\mathbf{d} = (d_0, d_1, \dots, d_{n-1})$  is invariant under right multiplication by the square matrix

$$E = \begin{bmatrix} d_0 & d_1 & d_2 & \dots & d_{n-1} \\ 1 & 0 & 0 & \dots & 0 \\ 0 & 1 & 0 & \dots & 0 \\ \vdots & & \ddots & 0 & 1 \\ 0 & 0 & \dots & 1 & 0 \end{bmatrix}.$$

**Theorem 2.3.** Let  $C$  be an additive right polycyclic code induced by  $\mathbf{a} = (a_0, a_1, \dots, a_{n-1})$  with  $a_0 \neq 0$ . Then  $C$  is an additive left polycyclic code induced by  $\mathbf{d} = (d_0, d_1, \dots, d_{n-1})$  where  $d_j = \frac{-a_{j+1}}{a_0}$  for  $j < n-1$  and  $d_{n-1} = \frac{1}{a_0}$ .

*Proof.* It is obvious that the matrix  $D$  above is invertible and

$$D^{-1} = \begin{bmatrix} d_0 & d_1 & d_2 & \dots & d_{n-1} \\ 1 & 0 & 0 & \dots & 0 \\ 0 & 1 & 0 & \dots & 0 \\ \vdots & & \ddots & 0 & \\ 0 & 0 & \dots & 1 & 0 \end{bmatrix},$$

where  $d_j = \frac{-a_{j+1}}{a_0}$  for  $j < n-1$  and  $d_{n-1} = \frac{1}{a_0}$ . Since  $CD = C$ , then  $C = CDD^{-1} = CD^{-1}$  and hence  $C$  is a left polycyclic code induced by  $\mathbf{d} = (d_0, d_1, \dots, d_{n-1})$ .  $\square$

Note that if  $C$  is both additive right and left polycyclic code induced by the same  $\mathbf{a}$ , it is an additive right-left polycyclic code.

**Theorem 2.4.** Let  $C$  be an additive right-left polycyclic code induced by  $a(x) = a_0 + a_1x + \dots + a_{n-1}x^{n-1}$ . Then  $a(x) = \frac{x^n + a_0}{1 + a_0x}$ , where  $a_0^{n+1} = (-1)^{n+1}$ .

*Proof.* Since  $C$  be an additive right-left polycyclic code induced by  $a(x) = a_0 + a_1x + \dots + a_{n-1}x^{n-1}$ , then  $a(x) = d(x)$ , where

$$\begin{aligned} d(x) &= \frac{-a_1}{a_0} + \frac{-a_2}{a_0}x + \frac{-a_3}{a_0}x^2 + \dots + \frac{-a_{n-1}}{a_0}x^{n-2} + \frac{1}{a_0}x^{n-1} \\ &= -\frac{a_0 + a_1x + \dots + a_{n-1}x^{n-1} - a_0}{a_0x} + \frac{1}{a_0}x^{n-1} \\ &= -\frac{a(x) - a_0}{a_0x} + \frac{1}{a_0}x^{n-1}. \end{aligned}$$

Since  $a(x) = d(x)$ , then  $a(x) = -\frac{a(x) - a_0}{a_0x} + \frac{1}{a_0}x^{n-1} = \frac{-a(x) + a_0 + x^n}{a_0x}$ . This implies that  $a_0xa(x) = -a(x) + a_0 + x^n$  and  $a(x) = \frac{x^n + a_0}{1 + a_0x}$ . Since  $a(x) = a_0 + a_1x + \dots + a_{n-1}x^{n-1}$ , then the root of  $1 + a_0x$  must be also the root of  $x^n + a_0$ . Therefore,  $a_0^{n+1} = (-1)^{n+1}$ .  $\square$

3. THE GENERATORS OF ADDITIVE RIGHT AND LEFT POLYCYCLIC CODES

In this section, we will focus on finding the structure of additive right polycyclic codes over  $\mathbb{F}_4$  induced by a binary vector  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ . The structure of additive left polycyclic codes over  $\mathbb{F}_4$  is obtained in the same way.

Suppose that  $C$  is an additive right polycyclic code over  $\mathbb{F}_4$  induced by  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$ . From Lemma 2.1,  $C$  is an  $\mathbb{F}_2[x]$ -submodule of  $R_n$ . For the rest of the paper, we will simply write  $f$  for the polynomial  $f(x)$ .

Let  $\alpha g_1 + g_2, b$  be two polynomials in  $C$  with the following properties:

**Condition 1.** The polynomial  $b$  is a binary polynomial of degree less than  $n$  in  $C$  and of minimal degree. If  $C$  has no binary polynomials, then  $b = 0$

**Condition 2.** The polynomial  $\alpha g_1 + g_2$  is a nonbinary polynomial of degree less than  $n$  in  $C$  in which  $g_1$  and  $g_2$  are binary polynomials and  $g_1$  is of minimal degree. If  $C$  has only binary polynomials, then  $\alpha g_1 + g_2 = 0$ .

Suppose that  $c \in C$ . If  $c$  is a binary polynomial in  $C$ , then by the division algorithm we get that

$$\begin{aligned} c &= qb + r, \text{ or} \\ r &= c - qb \end{aligned}$$

where  $q$  and  $r$  are binary polynomials and  $\deg r < \deg c$  or  $r = 0$ . Hence,  $r = c - qb \in C$  and  $r = 0$ . Therefore,  $c = qb$ . Now suppose that  $c = \alpha c_1 + c_2$  is a nonbinary polynomial in  $C$ . Then,

$$c_1 = q_1 g_1 + r_1,$$

where  $q_1$  and  $r_1$  are binary polynomials and  $\deg r_1 < \deg g_1$ . Hence,

$$\begin{aligned} \alpha c_1 &= q_1 \alpha g_1 + \alpha r_1. \\ &= q_1 (\alpha g_1 + g_2) + q_1 g_2 + \alpha r_1 \end{aligned}$$

Also,

$$c_2 = q_2 b + r_2$$

where  $q_2, r_2$  are binary polynomials with  $\deg r_2 < \deg b$ . Hence,

$$\begin{aligned} \alpha c_1 + c_2 &= q_1 (\alpha g_1 + g_2) + q_1 g_2 + \alpha r_1 + q_2 b + r_2 \\ &= q_1 (\alpha g_1 + g_2) + q_2 b + (\alpha r_1 + q_1 g_2 + r_2). \end{aligned}$$

This implies that  $(\alpha r_1 + q_1 g_2 + r_2) \in C$ . Since  $q_1 g_2 + r_2$  is a binary polynomial and  $\deg r_1 < \deg g_1$ , we conclude that  $r_1 = 0$ . Thus,  $(q_1 g_2 + r_2)$  is a binary polynomial in  $C$ . Hence,  $q_1 g_2 + r_2 = q_3 b$  and

$$\begin{aligned} \alpha c_1 + c_2 &= q_1 (\alpha g_1 + g_2) + q_2 b + q_3 b \\ &= q_1 (\alpha g_1 + g_2) + (q_2 + q_3) b \end{aligned}$$

where  $q_1, q_2, q_3$  are all binary polynomials. This proves the following Theorem that classifies all right polycyclic codes.

**Theorem 3.1.** Let  $C$  be an additive right polycyclic code induced by  $a$ . Then,  $C = \langle \alpha g_1 + g_2, b \rangle$  where  $\alpha g_1 + g_2, b$  satisfy conditions 1 and 2 and  $\deg g_2 < \deg b$ .

*Proof.* We only need to prove that  $\deg g_2 < \deg b$ . Suppose that  $\deg g_2 \geq \deg b$ . Since  $g_2$  and  $b$  are binary polynomials, by the division algorithm we have  $g_2 = qb + r$ , where  $r = 0$  or  $\deg r < \deg b$ . Consider the additive right polycyclic code  $D = \langle \alpha g_1 + r, b \rangle$  induced by  $a$ . Then  $\alpha g_1 + r = \alpha g_1 + g_2 - qb \in C$ . Hence,  $D \subseteq C$ . On the other hand, we have  $\alpha g_1 + g_2 = \alpha g_1 + r + qb \in D$ . Thus,  $C \subseteq D$  and therefore  $C = D$ .  $\square$

**Lemma 3.2.** Suppose that  $C = \langle \alpha g_1 + g_2, b \rangle$  is an additive right polycyclic code induced by  $a$ , with the generators satisfy the conditions in Theorem 3.1. Then  $g_1, g_2$  and  $b$  are unique.

*Proof.* Suppose that  $C = \langle \alpha g_1 + g_2, b_1 \rangle = \langle \alpha g_3 + g_4, b_2 \rangle$ . Since  $b_1$  is a binary polynomial of minimal degree and  $b_2$  is binary polynomials of minimal degree in  $C$ , then  $\deg b_1 = \deg b_2$ . If  $b_1 \neq b_2$ , then  $b_3 = (b_1 - b_2)$  is a binary polynomial in  $C$  of degree less than the degree of  $b_1$ . Hence,  $b_1 - b_2 = 0$  and  $b_1 = b_2$ . Since  $g_1$  and  $g_3$  are of minimal degree in  $C$ , then  $\deg g_1 = \deg g_3$ . If  $g_1 \neq g_3$ , then  $\alpha(g_1 - g_3) + (g_2 - g_4) \in C$ , and  $\deg(g_1 - g_3) < \deg g_1$ . A contradiction unless  $g_1 = g_3$ . If  $g_2 \neq g_4$ , then  $(\alpha g_1 + g_2) - (\alpha g_3 + g_4) = g_2 - g_4$  is a binary polynomial in  $C$  of degree less than the degree of  $b$ . A contradiction. Hence  $g_2 = g_4$  and the generators are unique.  $\square$

**Theorem 3.3.** Let  $C$  be an additive right polycyclic code induced by a binary vector  $a$ . Then the code  $C$  is given by

- (1)  $C = \langle b \rangle$ , where  $b$  is a binary polynomial of minimal degree in  $C$  and  $b \mid (x^n - a)$ . Or
- (2)  $C = \langle \alpha g_1 + g_2 \rangle$  where  $g_1, g_2$  satisfy condition 2. Moreover,  $g_1 \mid (x^n - a)$ , and  $(x^n - a) \mid \left( \frac{x^n - a}{g_1} g_2 \right)$ . Or
- (3)  $C = \langle \alpha g_1 + g_2, b \rangle$ , where  $g_1, g_2$  and  $b$  are polynomials satisfy conditions 1 and 2. Moreover,  $b \mid (x^n - a)$ ,  $g_1 \mid (x^n - a)$ ,  $\deg g_2 < \deg b$  and  $b \mid \left( \frac{x^n - a}{g_1} g_2 \right)$

*Proof.* From Theorem 3.1, we know that  $C = \langle \alpha g_1 + g_2, b \rangle$ , where  $\alpha g_1 + g_2, b$  satisfy conditions 1 and 2 and  $\deg g_2 < \deg b$ .

- (1) If  $C$  has only binary polynomials, then  $\alpha g_1 + g_2 = 0$  and  $C = \langle b \rangle$ . Since  $a$  is a binary polynomial, by the division algorithm we have

$$x^n - a = Q_1 b + R_1.$$

where  $Q_1$  and  $R_1$  are binary polynomials with  $\deg R_1 < \deg b$  or  $R_1 = 0$ . Hence,  $R_1 = Q_1 b \in C$ . Therefore,  $R_1 = 0$  and  $b \mid (x^n - a)$ .

- (2) Suppose that  $C$  has no binary polynomials. Then  $b = 0$  and  $C = \langle \alpha g_1 + g_2 \rangle$  where  $g_1, g_2$  satisfy condition 2. We also have

$$x^n - a = Q_2 g_1 + R_2,$$

where  $Q_2, R_2$  are binary polynomials and  $\deg R_2 < \deg g_1$ . Hence,

$$\alpha(x^n - a) = Q_2(\alpha g_1 + g_2) + \alpha R_2 + Q_2 g_2.$$

This implies that  $(\alpha R_2 + Q_2 g_2) \in C$ . Since  $Q_2 g_2$  is a binary polynomial and  $\deg R_2 < \deg g_1$ ,  $\alpha R_2 = 0$  and  $g_1 \mid (x^n - a)$ . Notice that  $\frac{x^n - a}{g_1}(\alpha g_1 + g_2) =$

$\frac{x^n - a}{g_1}g_2$  is a binary polynomial in  $C$ . Since  $C$  has no binary polynomials,  $(x^n - a) \mid \left(\frac{x^n - a}{g_1}g_2\right)$ .

- (3) If  $C$  has binary and nonbinary polynomials, then  $C = \langle \alpha g_1 + g_2, b \rangle$ , where  $g_1, g_2$  and  $b$  are polynomials satisfy conditions 1, 2 and  $\deg g_2 < \deg b$ . From (1) and (2) we get that  $b \mid (x^n - a)$ ,  $g_1 \mid (x^n - a)$ . Since  $\frac{x^n - a}{g_1}(\alpha g_1 + g_2) = \frac{x^n - a}{g_1}g_2$  is a binary polynomial in  $C$ , then  $b \mid \left(\frac{x^n - a}{g_1}g_2\right)$ .  $\square$

**Corollary 3.3.1.** If  $a(x)$  is a binary polynomial and  $\gcd\left(b, \frac{x^n - a}{g_1}\right) = 1$ , then  $g_2 = 0$ .

*Proof.* Since  $b \mid \left(\frac{x^n - a}{g_1}g_2\right)$  and  $\gcd\left(b, \frac{x^n - a}{g_1}\right) = 1$ , then  $b \mid g_2$ . But  $\deg g_2 < \deg b$ . Hence,  $g_2 = 0$ .  $\square$

**Corollary 3.3.2.** Let  $C$  be an additive left polycyclic code induced by a binary vector  $a$ . Then the code  $C$  is given by

- (1)  $C = \langle b \rangle$ , where  $b$  is a binary polynomial of minimal degree in  $C$  and  $b \mid (x^n - a)$ . Or
- (2)  $C = \langle \alpha g_1 + g_2 \rangle$  where  $g_1, g_2$  satisfy condition 2. Moreover,  $g_1 \mid (x^n - a)$ , and  $(x^n - a) \mid \left(\frac{x^n - a}{g_1}g_2\right)$ . Or
- (3)  $C = \langle \alpha g_1 + g_2, b \rangle$ , where  $g_1, g_2$  and  $b$  are polynomials satisfy conditions 1 and 2. Moreover,  $b \mid (x^n - a)$ ,  $g_1 \mid (x^n - a)$ ,  $\deg g_2 < \deg b$  and  $b \mid \left(\frac{x^n - a}{g_1}g_2\right)$

*Proof.* The proof is similar to the proof in Theorem 3.1, Lemma 3.2 and Theorem 3.3.  $\square$

**Theorem 3.4.** Let  $C$  be an additive right polycyclic code induced by a binary vector  $a$ .

- (1) If  $C = \langle b \rangle$ , where  $b$  is a binary polynomial with  $\deg b = t_1$ , then  $|C| = 2^{n-t_1}$ .
- (2) If  $C = \langle \alpha g_1 + g_2 \rangle$ , where  $\deg g_1 = t_2$  and  $(x^n - a) \mid \left(\frac{x^n - a}{g_1}g_2\right)$ , then  $|C| = 2^{n-\deg t_2}$ .
- (3) If  $C = \langle \alpha g_1 + g_2, b \rangle$ , where  $\deg b = t_1$  and  $\deg g_1 = t_2$ , then  $|C| = 2^{n-t_1}2^{n-t_2}$

*Proof.* We will prove (3). The proof of (1) and (2) is similar to the proof of (3).

Suppose that  $C = \langle \alpha g_1 + g_2, b \rangle$  where  $g_1, g_2$ , and  $b$  satisfy the conditions in Theorem 3.3. Let  $c(x) \in C$ . Then  $c = f_1(\alpha g_1 + g_2) + f_2b$ . Using the division algorithm, we get

$$f_2 = q_2 \frac{x^n - a}{b} + r_2,$$

where  $r_2$  is a binary polynomial satisfying  $\deg r_2 < n - t_1$ . Hence,

$$f_2b = q_2 \frac{x^n - a}{b}b + r_2b = r_2b,$$

where  $\deg r_2 < n - t_1$ . Again using the division algorithm, we get

$$f_1 = q_1 \frac{x^n - a}{g_1} + r_1,$$

where  $r_1$  is a binary polynomial satisfying  $\deg r_1 < n - t_2$ . Hence,

$$\begin{aligned} f_1(\alpha g_1 + g_2) &= q_1 \frac{x^n - a}{g_1} (\alpha g_1 + g_2) + r_1 (\alpha g_1 + g_2) \\ &= r_1 (\alpha g_1 + g_2) + q_1 \frac{x^n - a}{g_1} g_2. \end{aligned}$$

Since  $q_1 \frac{x^n - a}{g_1} g_2$  is a binary polynomial,  $q_1 \frac{x^n - a}{g_1} g_2 = r_3 b$ . We have

$$r_3 = q_3 \frac{x^n - a}{b} + r_4,$$

where  $\deg r_4 < n - t_1$ . Hence,

$$\begin{aligned} r_3 b &= q_3 \frac{x^n - a}{b} b + r_4 b \\ &= r_4 b. \end{aligned}$$

Therefore,

$$\begin{aligned} c &= f_1(\alpha g_1 + g_2) + f_2 b \\ &= r_1(\alpha g_1 + g_2) + (r_2 + r_4) b, \end{aligned}$$

where  $\deg r_1 < n - t_2$  and  $\deg(r_2 + r_3) < n - t_1$ . Hence,  $|C| = 2^{n-t_1} 2^{n-t_2}$ .  $\square$

#### 4. DUALS AND ADDITIVE SEQUENTIAL CODES

**Definition 4.1.** Let  $C$  be an additive code over  $\mathbb{F}_4$  and let  $c = (c_0, c_1, \dots, c_{n-1}) \in C$ .  $C$  is called an additive right sequential code induced by  $a$  if there exists a vector  $a = (a_0, a_1, \dots, a_{n-1}) \in \mathbb{F}_2^n$  such that

$$(c_1, c_2, \dots, c_{n-1}, c_0 a_0 + c_1 a_1 + \dots + c_{n-1} a_{n-1}) \in C.$$

The trace map  $Tr_2 : \mathbb{F}_4 \rightarrow \mathbb{F}_2$  is defined by  $Tr_2(a) = a + a^2$ . Thus,  $Tr_2(0) = Tr_2(1) = 0$ , and  $Tr_2(\alpha) = Tr_2(\alpha^2) = 1$ . Moreover, For any  $\mathbf{x}, \mathbf{y} \in \mathbb{F}_4^n$ , the trace inner product  $\langle \cdot, \cdot \rangle_T$  on  $\mathbb{F}_4$  is defined by

$$\langle \mathbf{x}, \mathbf{y} \rangle_T = Tr_2(\langle \mathbf{x}, \mathbf{y} \rangle),$$

where  $\langle \mathbf{x}, \mathbf{y} \rangle$  is the Hermitian inner product.

**Definition 4.2.** Let  $C$  be an additive polycyclic code over  $\mathbb{F}_4$ . We consider three different dual codes for  $C$

- (1) Define the Hermitian dual of  $C$  by

$$C^\perp = \{\mathbf{y} \in \mathbb{F}_4^n : \langle \mathbf{x}, \mathbf{y} \rangle_T = 0 \forall \mathbf{x} \in C\}.$$

- (2) Define the annihilator dual of  $C$  by  $Ann(C) = \{g \in R_n : g(x) f(x) = 0 \forall f(x) \in C\}$ .

- (3) Define the 0-dual of  $C$  by

$$C^0 = \{g \in R_n : gf(0) = 0 \forall f(x) \in C\}.$$

Since the set  $R_n$  is an  $\mathbb{F}_4[x]$ -submodule and  $C$  is a subset of  $R_n$ , the sets  $Ann(C)$  and  $C^0$  above are well-defined. In [2], the authors proved that if  $C$  is a linear polycyclic code, then  $Ann(C) = C^0$ .

**Lemma 4.1.** Let  $C$  be an additive right polycyclic code over  $\mathbb{F}_4$ . Then  $\text{Ann}(C)$  and  $C^0$  are linear right polycyclic codes over  $\mathbb{F}_4$ .

*Proof.* We will prove that  $\text{Ann}(C)$  is an ideal in  $R_n$ . The same proof applies to  $C^0$  as well. Suppose that  $s_1, s_2 \in \text{Ann}(C)$ ,  $f \in C$  and  $r \in R_n$ . Then,  $(s_1 + s_2)f = s_1f + s_2f = 0$  and  $r(x)s_1(x)f(x) = r(x)(s_1(x)f(x)) = 0$ . Hence,  $s_1 + s_2$  and  $rs_1 \in \text{Ann}(C)$ . Therefore  $\text{Ann}(C)$  and  $C^0$  are ideals in  $R_n$  and hence they are linear right polycyclic codes over  $\mathbb{F}_4$ .  $\square$

**Theorem 4.2.**  $C$  is an additive right polycyclic code induced by  $a$  if and only if the dual code  $C^\perp$  is an additive  $(n, 2^{2n-k})$  sequential code induced by  $a$ .

*Proof.* Suppose that  $C$  is an additive right polycyclic code induced by  $a$ . Then  $C$  is invariant under right multiplication by the square matrix

$$G = \begin{bmatrix} 0 & 1 & 0 & 0 & \dots \\ 0 & 0 & 1 & 0 & \dots \\ \vdots & & & \ddots & \\ 0 & 0 & \dots & 0 & 1 \\ a_0 & a_1 & a_2 & \dots & a_{n-1} \end{bmatrix}.$$

If  $H$  is a check matrix for  $C$ , then  $\overline{C}H^T + C\overline{H}^T = C * H^T = 0$ , where  $*$  means the trace inner product. Hence,  $CD * H^T = \overline{C}D\overline{H}^T + CD\overline{H}^T = C \left( \overline{H}D^T \right)^T + C \left( \overline{H}D^T \right)^T = C * \left( HD^T \right)^T = 0$ . This implies that  $C^\perp$  is invariant under right multiplication by  $D^T$ . Thus  $C^\perp$  is an additive sequential code induced by  $a$ .  $\square$

## 5. APPLICATIONS AND EXAMPLES

**5.1. Additive Codes with More Codewords than Optimal Linear Codes over  $\text{GF}(4)$ .** Based on Theorem 3.3 and Theorem 3.4, we conducted computer searches to find additive codes with good parameters. We took binary  $g_1|x^n - a$  and binary  $b|x^n - a$  that are relatively prime, and binary  $g_2$  to be a random polynomial of degree less than the degree of  $b$ . Then, it automatically follows that  $b|\frac{x^n - a}{g_1}g_2$ . As a result of our search we found 13 additive polycyclic codes over  $\mathbb{F}_4$  that contain more codewords than the comparable optimal linear codes  $\mathbb{F}_4$ .

Table 1 below shows these codes with their generators  $\langle \alpha g_1 + g_2, b \rangle$ . We use the notation  $[n, \frac{2k+1}{2}, d]_4$  to denote the parameters of a polycyclic code which means its size is  $2 \cdot 4^k$ . On the other hand, the comparable optimal linear code with the same length and minimum distance  $d$  has  $4^k$  codewords and the best linear code of dimension  $k + 1$  has minimum distance  $d - 1$ . In other words, these additive polycyclic codes contain twice as many codewords as the optimal linear codes with the same length and minimum distance. Note that the multinomials below refer to  $x^n - a$ .

TABLE 1. Additive codes  $[n, k, d]_4$  v.s. BKLC  $[n, k, d]_4$  with smaller dimension

$[n, \frac{2k+1}{2}, d]_4$	$[n, k, d]_4$	$[n, k+1, d-1]_4$	$\langle \alpha g_1 + g_2, b \rangle$	Multinomial
$[7, 9/2, 3]_4$	$[7, 4, 3]_4$	$[7, 5, 2]_4$	$\langle \alpha(x^2 + x + 1) + x, x^3 + x^2 + 1 \rangle$	$x^7 + x^6 + x^5 + x^3 + 1$
$[7, 7/2, 4]_4$	$[7, 3, 4]_4$	$[7, 4, 3]_4$	$\langle \alpha(x+1) + x^4 + x^3 + x^2 + x, x^6 + x^5 + x^4 + x^3 + x^2 + x + 1 \rangle$	$x^7 + 1$
$[22, 37/2, 3]_4$	$[22, 18, 3]_4$	$[22, 19, 2]_4$	$\langle \alpha(x+1) + x^3 + x, x^6 + x^4 + x^3 + x + 1 \rangle$	$x^{22} + x^{19} + x^{15} + x^{14} + x^{13} + x^8 + x^7 + x^6 + x^4 + x^2 + x + 1$
$[23, 39/2, 3]_4$	$[23, 19, 3]_4$	$[23, 20, 2]_4$	$\langle \alpha(x+1) + x^4 + x^2, x^6 + x^5 + 1 \rangle$	$x^{23} + x^{22} + x^{21} + x^{15} + x^{13} + x^{11} + x^{10} + x^9 + x^8 + x^7 + x^3 + x^2 + x + 1$
$[24, 41/2, 3]_4$	$[24, 20, 3]_4$	$[24, 21, 2]_4$	$\langle \alpha(x^2 + x + 1) + x^2 + x, x^5 + x^4 + x^3 + x + 1 \rangle$	$x^{24} + x^{21} + x^{20} + x^{19} + x^{18} + x^{16} + x^{14} + x^8 + x^5 + x^4 + x^3 + x^2 + 1$
$[25, 43/2, 4]_4$	$[25, 21, 3]_4$	$[25, 22, 2]_4$	$\langle \alpha(x+1) + x^4 + x^2, x^6 + x^5 + 1 \rangle$	$x^{25} + x^{24} + x^{22} + x^{21} + x^{19} + x^{18} + x^{15} + x^{13} + x^{12} + x^{11} + x^{10} + x^9 + x^8 + x^7 + x^6 + x^5 + x^4 + x^3 + x^2 + 1$
$[26, 45/2, 3]_4$	$[26, 22, 3]_4$	$[26, 23, 2]_4$	$\langle \alpha(x+1) + x^4 + x^3 + x, x^6 + x^5 + x^3 + x^2 + 1 \rangle$	$x^{26} + x^{24} + x^{21} + x^{16} + x^{15} + x^{13} + x^{12} + x^{11} + x^{10} + x^9 + x^7 + x^3 + x^2 + 1$
$[27, 47/2, 3]_4$	$[27, 23, 3]_4$	$[27, 24, 2]_4$	$\langle \alpha(x^2 + x + 1) + x^2 + x, x^5 + x^4 + x^3 + x + 1 \rangle$	$x^{27} + x^{26} + x^{23} + x^{21} + x^{19} + x^{18} + x^{17} + x^{14} + x^{13} + x^{11} + x^{10} + x^7 + x^3 + x + 1$
$[27, 47/2, 3]_4$	$[27, 23, 3]_4$	$[27, 24, 2]_4$	$\langle \alpha(x^2 + x + 1) + x^2 + x, x^5 + x^4 + x^3 + x + 1 \rangle$	$x^{27} + x^{26} + x^{23} + x^{21} + x^{19} + x^{18} + x^{17} + x^{14} + x^{13} + x^{11} + x^{10} + x^7 + x^3 + x + 1$
$[28, 49/2, 3, 1]_4$	$[28, 24, 3]_4$	$[28, 25, 2]_4$	$\langle \alpha(x^2 + x + 1) + x^3 + x^2 + x, x^5 + x^3 + x^2 + x + 1 \rangle$	$x^{28} + x^{27} + x^{24} + x^{23} + x^{22} + x^{20} + x^{17} + x^{16} + x^{15} + x^{14} + x^{13} + x^{11} + x^{10} + x^8 + x^7 + x^5 + x^3 + x + 1$
$[29, 51/2, 3]_4$	$[29, 25, 3]_4$	$[29, 26, 2]_4$	$\langle \alpha(x+1) + x^2 + x + 1, x^6 + x^5 + x^4 + x + 1 \rangle$	$x^{29} + x^{25} + x^{22} + x^{21} + x^{19} + x^{15} + x^{14} + x^{13} + x^{11} + x^{10} + x^6 + x^3 + x + 1$
$[30, 53/2, 3]_4$	$[30, 26, 3]_4$	$[30, 27, 2]_4$	$\langle \alpha(x+1) + x^3 + x^2 + 1, x^6 + x^5 + x^3 + x^2 + 1 \rangle$	$x^{30} + x^{27} + x^{26} + x^{25} + x^{24} + x^{20} + x^{19} + x^{18} + x^{16} + x^{11} + x^{10} + x^9 + x^8 + x^7 + x^2 + 1$
$[31, 55/2, 3]_4$	$[31, 27, 3]_4$	$[31, 28, 2]_4$	$\langle \alpha(x+1) + x^4 + x + 1, x^6 + x^5 + x^3 + x^2 + 1 \rangle$	$x^{31} + x^{25} + x^{23} + x^{22} + x^{20} + x^{18} + x^{17} + x^{16} + x^{15} + x^{14} + x^{13} + x^{12} + x^{10} + x^9 + x^8 + x^7 + x^6 + x^4 + x^3 + 1$

## 5.2. Best Known Linear Codes over GF(2) Obtained from Additive Codes over GF(4).

We can define the following maps,  $W$ ,  $T$ , and  $L$ : [1]

$$\begin{aligned}
 W &: \mathbb{F}_4^n \rightarrow \mathbb{F}_2^{2n} \\
 &W(x_1, x_2, \dots, x_n) \\
 &= W((a_1 + b_1\alpha), (a_2 + b_2\alpha), \dots, (a_n + b_n\alpha)) \\
 &= ((a_1 + b_1), (a_2 + b_2), \dots, (a_n + b_n), b_1, b_2, \dots, b_n) \\
 \text{(trace map)} \quad T &: \mathbb{F}_4^n \rightarrow \mathbb{F}_2^n \\
 &T(x_1, x_2, \dots, x_n) \\
 &= ((x_1 + x_1^2), (x_2 + x_2^2), \dots, (x_n + x_n^2)) \\
 L &: \mathbb{F}_4^n \rightarrow \mathbb{F}_2^n \\
 &L(x_1, x_2, \dots, x_n) \\
 &= ((x_1\alpha + x_1^2\alpha^2), (x_2\alpha + x_2^2\alpha^2), \dots, (x_n\alpha + x_n^2\alpha^2))
 \end{aligned}$$

Using these map, we can construct binary linear codes from quaternary additive codes. Namely, by  $W$ , we can construct an  $[2n, 2k, d']_2$  linear code from an  $[n, k, d]_4$  additive code; and by  $T$  and  $L$ , we can construct  $[n, k', d']_2$  linear codes from  $[n, k, d]_4$  additive codes. We present some optimal codes in Table 2 where  $[n, k, d]_2$  is the binary optimal linear codes we obtained, and  $\langle \alpha g_1 + g_2, b \rangle$  refers to the generators as in Theorem 3.3, multinomial denotes  $x^n - a$ , where  $a$  is the associated vector;  $*$  and  $\circ$  delineates reversible and self-orthogonal codes respectively.

TABLE 2. Optimal binary linear codes  $[n, k, d]_2$  obtained from quaternary additive codes based on  $W$ ,  $T$ , and  $L$ 

$[n, k, d]_2$	Map	$\langle \alpha g_1 + g_2, b \rangle$	Multinomial
$[7, 2, 4]_2^{*o}$	L	$\langle \alpha(x^5 + x^4 + x + 1) + 1, x^2 + x + 1 \rangle$	$x^7 + x^4 + x^3 + 1$
$[10, 4, 4]_2$	L	$\langle \alpha(x + 1) + x + 1, x^6 + x^5 + x^4 + x + 1 \rangle$	$x^{10} + x^9 + x^8 + x^6 + x + 1$
$[12, 5, 4]_2$	L	$\langle \alpha(x^2 + x + 1) + x^2 + x + 1, x^7 + x^3 + x^2 + x + 1 \rangle$	$x^{12} + x^6 + x^5 + x^4 + 1$
$[16, 9, 4]_2^*$	T	$\langle \alpha(x^7 + x^3 + x^2 + x + 1) + x^4 + x^3 + x^2 + x + 1, x^9 + x + 1 \rangle$	$x^{16} + x^{12} + x^{11} + x^{10} + x^9 + x^8 + x^7 + x^4 + 1$
$[17, 9, 5]_2$	T	$\langle \alpha(x^8 + x^5 + x^4 + x^3 + 1) + x^7 + x^6 + x^4 + x^3 + x, x^9 + x^8 + x^6 + x^5 + x^4 + x^3 + x^2 + x + 1 \rangle$	$x^{17} + x^{16} + x^{13} + x^{12} + x^{11} + x^{10} + x^9 + x^8 + x^7 + x^4 + x^2 + x + 1$
$[20, 11, 5]_2$	W	$\langle \alpha(x + 1) + x^6 + x^4 + x^2 + x, x^8 + x^6 + x^5 + x^4 + x^2 + x + 1 \rangle$	$x^{10} + x^7 + x^5 + x^3 + x + 1$
$[26, 17, 4]_2$	W	$\langle \alpha(x + 1) + x^4 + x^3 + x^2, x^8 + x^5 + x^3 + x + 1 \rangle$	$x^{13} + x^{10} + x^6 + x^3 + x + 1$
$[35, 24, 5]_2^*$	T	$\langle \alpha(x^{11} + x^9 + x^8 + x^6 + x^4 + x^3 + x^2 + x + 1) + x^{22} + x^{16} + x^{15} + x^{14} + x^{13} + x^{10} + x^9 + x^8 + x^7 + x^5 + x + 1, x^{24} + x^{21} + x^{19} + x^{16} + x^{13} + x^{12} + x^{10} + x^8 + x^7 + x^6 + x^2 + x + 1 \rangle$	$x^{35} + x^{33} + x^{30} + x^{29} + x^{26} + x^{23} + x^{21} + x^{20} + x^{19} + x^{14} + x^{13} + x^{12} + x^{11} + x^9 + x^8 + x^7 + x^6 + x^4 + x^3 + x^2 + 1$
$[49, 39, 4]_2^*$	T	$\langle \alpha(x^{10} + x^8 + x^6 + x^4 + x^2 + x + 1) + x, x^5 + x^4 + x^3 + x^2 + 1 \rangle$	$x^{49} + x^{46} + x^{45} + x^{44} + x^{40} + x^{39} + x^{38} + x^{36} + x^{35} + x^{31} + x^{30} + x^{29} + x^{28} + x^{27} + x^{24} + x^{23} + x^{20} + x^{19} + x^{17} + x^{15} + x^{12} + x^{11} + x^9 + x^8 + x^4 + x + 1$
$[62, 51, 4]_2$	W	$\langle \alpha(x + 1) + x^8 + x^4 + x + 1, x^{10} + x^9 + x^8 + x^4 + 1 \rangle$	$x^{31} + x^{29} + x^{28} + x^{27} + x^{26} + x^{25} + x^{23} + x^{15} + x^{14} + x^{13} + x^{12} + x^9 + x^8 + x^7 + x^3 + x^2 + x + 1$
$[98, 86, 4]_2$	W	$\langle \alpha(x^2 + x + 1) + x^8 + x^7 + x^6 + x^3 + 1, x^{10} + x^8 + x^6 + x^4 + x^2 + x + 1 \rangle$	$x^{49} + x^{48} + x^{46} + x^{45} + x^{43} + x^{39} + x^{36} + x^{31} + x^{27} + x^{25} + x^{24} + x^{22} + x^{21} + x^{20} + x^{19} + x^{18} + x^{17} + x^{14} + x^7 + x^6 + x^3 + x + 1$

**5.3. Quantum Codes with Good Parameters from Additive Polycyclic Codes.** Quantum error correcting codes are an increasingly important part of quantum information theory. Many researchers have used classical block codes to construct quantum codes. One of the most commonly used methods is the CSS construction [3]. The CSS construction requires two linear codes  $C_1$  and  $C_2$  such that  $C_2^\perp \subseteq C_1$ . Hence, if  $C_1$  is a self-dual code, then we can construct a CSS quantum code using  $C_1$  alone since  $C_1^\perp \subseteq C_1$ . If  $C_1$  is self-orthogonal or dual-containing, then we can construct a CSS quantum code with  $C_1^\perp$  and  $C_1$  with the similar reason.

In this section, we present some optimal quantum codes derived from additive polycyclic codes. After constructing additive polycyclic codes by theorem 12, we used maps W, T, and L to construct self-dual, self-orthogonal, or dual-containing binary codes. Then, we used binary codes and their duals to construct CSS codes. Here are some example of optimal codes we found using this method. The optimality of these codes can be confirmed via the online table [4].

TABLE 3. Optimal quantum codes  $[[n, k, d]]_4$  from self-dual/self-orthogonal/dual-containing binary linear codes obtained from quaternary additive codes

$[[n, k, d]]_4$	Map	$\langle \alpha g_1 + g_2, b \rangle$	Multinomial
$[[7, 1, 3]]_4$	T	$\langle \alpha(x^3 + x^2 + 1) + x, x^4 + x^3 + x^2 + x + 1 \rangle$	$x^7 + x^4 + x^3 + x + 1$
$[[10, 8, 2]]_4$	T	$\langle \alpha(x + 1) + 1, x^2 + x + 1 \rangle$	$x^{10} + x^9 + x^7 + x^5 + x^4 + x^2 + x + 1$
$[[15, 7, 3]]_4$	T	$\langle \alpha(x^4 + x + 1) + x^2 + x + 1, x^4 + x^3 + 1 \rangle$	$x^{15} + x^{10} + x^9 + x^7 + x^6 + x^5 + x^3 + x^2 + 1$
$[[30, 26, 2]]_4$	T	$\langle \alpha(x^2 + x + 1) + x^8 + x^6 + 1, x^{12} + x^{11} + x^8 + x^7 + x^5 + x^4 + x^2 + x + 1 \rangle$	$x^{30} + x^{29} + x^{27} + x^{25} + x^{24} + x^{23} + x^{22} + x^{21} + x^{20} + x^{17} + x^{13} + x^{11} + x^{10} + x^9 + x^6 + x^5 + x^2 + x + 1$
$[[35, 29, 2]]_4$	L	$\langle \alpha(x + 1) + x + 1, x^3 + x + 1 \rangle$	$x^{35} + x^{34} + x^{33} + x^{31} + x^{27} + x^{25} + x^{24} + x^{22} + x^{20} + x^{18} + x^{17} + x^{16} + x^{15} + x^{11} + x^5 + x^4 + x + 1$
$[[36, 30, 2]]_4$	W	$\langle \alpha(x + 1) + 1, x^2 + x + 1 \rangle$	$x^{18} + x^{16} + x^{13} + x^{11} + x^9 + x^8 + x^7 + x^4 + x^3 + 1$
$[[48, 42, 2]]_4$	W	$\langle \alpha(x + 1) + 1, x^2 + x + 1 \rangle$	$x^{24} + x^{22} + x^{16} + x^{15} + x^{14} + x^{13} + x^{11} + x^{10} + x^7 + x^6 + x^4 + 1$
$[[56, 50, 2]]_4$	L	$\langle \alpha(x + 1) + 1, x^3 + x + 1 \rangle$	$x^{56} + x^{51} + x^{49} + x^{48} + x^{47} + x^{41} + x^{38} + x^{36} + x^{31} + x^{30} + x^{29} + x^{28} + x^{26} + x^{18} + x^{16} + x^{15} + x^{14} + x^{12} + x^{10} + x^9 + x^5 + x^2 + x + 1$
$[[72, 66, 2]]_4$	W	$\langle \alpha(x + 1) + 1, x^2 + x + 1 \rangle$	$x^{36} + x^{35} + x^{32} + x^{31} + x^{30} + x^{29} + x^{26} + x^{22} + x^{21} + x^{20} + x^{18} + x^{16} + x^{13} + x^{10} + x^9 + x^2 + x + 1$
$[[84, 76, 2]]_4$	W	$\langle \alpha(x + 1) + 1, x^3 + x + 1 \rangle$	$x^{42} + x^{41} + x^{40} + x^{39} + x^{37} + x^{35} + x^{33} + x^{30} + x^{29} + x^{28} + x^{27} + x^{25} + x^{21} + x^{15} + x^{14} + x^{13} + x^{11} + x^{10} + x^9 + x^6 + x^5 + x^2 + x + 1$

## 6. CONCLUSION AND FUTURE WORKS

In this paper, we have studied the structure and properties of additive right and left polycyclic codes induced by a binary vector  $a \in \mathbb{F}_2^n$ . We have also studied different duals of these codes and showed that  $C$  is an additive right polycyclic code induced by  $a$  if and only if the Hermitian dual code  $C^\perp$  is an additive  $(n, 2^{2n-k})$  sequential code induced by  $a$ . Finally, we have shown that it is possible to obtain both classical and quantum codes with good parameters from these codes.

Our work in this paper is on additive right and left polycyclic codes induced by a binary vector  $a \in \mathbb{F}_2^n$ . A generalization of this work to non-binary vectors  $a \in \mathbb{F}_4^n$  would be interesting. It is known that ([3]) constacyclic additive codes that are not cyclic over  $\mathbb{F}_4$  are just linear constacyclic codes. Hence, it will be interesting to study the relationship between additive right and left polycyclic codes over  $\mathbb{F}_4$  induced by a nonbinary vector  $a \in \mathbb{F}_4^n$  and linear polycyclic codes over  $\mathbb{F}_4$  induced by the vector  $a$ . We have few results on this relationship but the work is still in progress.

## REFERENCES

- [1] T. Abualrub, N. Aydin, I. Aydogdu, "Optimal binary codes derived from  $\mathbb{F}_2\mathbb{F}_4$ -additive cyclic codes," *Journal of Applied Mathematics and Computing*, vol. 64, 2020, pp. 71-87.
- [2] A. Alahmadi, A. Dougherty, A. Leroy, P. Solé, "On the duality and direction of polycyclic codes," *Advances in Mathematics of Communications*, vol. 10, 2016, pp. 921-929.
- [3] A. R. Calderbank, E. M. Rains, P. W. Shor and N. J. A. Sloane, "Quantum error correction via codes  $\mathbb{F}_4$ ," *IEEE Transaction on Information Theory*, vol. 44, 1998, pp. 1369-1387.
- [4] M. Grassl, *Code Tables: Bounds on the parameters of codes*. Online available at <http://www.codetables.de/>
- [5] W.C. Huffman, "Additive codes over  $\mathbb{F}_4$ ," *Advances in Mathematics of Communications*, vol. 2, 2008, pp. 309-343.

- [6] M. Matsuoka, "Polynomial realization of sequential codes over finite fields," SUT Journal of Mathematics, vol. 48, 2012, pp. 47–53.
- [7] S. R. López-Permouth, B. R. Parra-Avila, S. Szabo, "Dual generalizations of the concept of cyclicity of codes," Advances in Mathematics of Communications, vol. 3, 2009, pp. 227–234.