

Convergence of a robust deep FBSDE method for stochastic control

Kristoffer Andersson*

Adam Andersson†‡

Cornelis W. Oosterlee*§

January 19, 2022

Abstract

In this paper we propose a deep learning based numerical scheme for strongly coupled FBSDE, stemming from stochastic control. It is a modification of the deep BSDE method in which the initial value to the backward equation is not a free parameter, and with a new loss function being the weighted sum of the cost of the control problem, and a variance term which coincides with the means square error in the terminal condition. We show by a numerical example that a direct extension of the classical deep BSDE method to FBSDE, fails for a simple linear-quadratic control problem, and motivate why the new method works. Under regularity and boundedness assumptions on the exact controls of time continuous and time discrete control problems we provide an error analysis for our method. We show empirically that the method converges for three different problems, one being the one that failed for a direct extension of the deep BSDE method.

Contents

1	Introduction	1
2	The deep FBSDE method and an improved family of methods	3
2.1	Stochastic control and FBSDE	3
2.2	Alternative formulations of FBSDE	4
2.3	A direct extension of the deep BSDE method and why it fails	5
2.4	A robust deep FBSDE method	8
2.5	Decoupled BSDE and why coupled FBSDE are important	8
3	Fully implementable scheme and neural network regression	8
3.1	Fully implementable algorithms	9
3.2	Specification of the neural networks	9
4	Convergence analysis	9
4.1	Notation and spaces	11
4.2	Setting and spaces of Markov maps	11
4.3	Auxiliary lemmata on strong convergence for SDE	11
4.4	Time discretization error of the initial and terminal values	14
4.5	Time discretization error of the FBSDE	16
4.6	A discussion on the full error analysis of the robust deep FBSDE method	17
5	Numerical experiments	17
5.1	Linear quadratic control problems	18
5.1.1	Example with state and control of the same dimension	18
5.1.2	Example with control in lower dimensions than the state	20
5.2	Non-linear control problems	20

1 Introduction

The concept of forward backward stochastic differential equations (FBSDE) has become an important modelling tool with many applications in a wide variety of fields such as finance, physics, chemistry and stochastic control. As the name suggests, an FBSDE consists of two stochastic differential equations (SDE) one forward SDE and

*Research Group of Scientific Computing, Centrum Wiskunde & Informatica

†Research Group of Computational Mathematics, Chalmers University of Technology & the University of Gothenburg

‡Saab Surveillance, Gothenburg, Sweden

§Mathematical Institute, Utrecht University

one backward SDE, commonly referred to as the forward equation and the backward equation, respectively. The forward equation is a classical SDE with a given, possibly stochastic, initial value, while the backward equation has a given stochastic terminal value and the initial value is part of the solution. In this paper we are concerned with stochastic control problems, which typically lead to coupled FBSDE, meaning that the primary stochastic variables in the backward SDE impact the forward SDE and vice versa. Since closed form solutions to FBSDE are rare one often has to rely on numerical approximations. These approximation schemes can be categorized into *backward* and *forward* numerical methods, referring to the order in time in which the methods operate.

A backward numerical method usually relies on an initialization of the backward equation at the known terminal value (or an approximation of the terminal value). The solution is then approximated recursively, backwards in time, by approximating conditional expectations. There are several different methods to approximate these conditional expectations and we give a few examples below. A fast and accurate class of algorithms are the tree based methods, see *e.g.*, [2, 3]. These algorithms do usually not require strict assumptions on the coefficients, but are very sensitive to the dimensionality of the problem, *i.e.*, they suffer from the curse of dimensionality, meaning that the time complexity and the memory requirements increase exponentially with the dimensions of the problem. A second approach, which also provides highly accurate approximations fast is the class of Fourier based methods, see *e.g.*, [4, 5, 6, 7]. A drawback of these methods is that they require access to the characteristic functions of the transition densities and it is non-trivial to approximate high-dimensional problems. A methodology which can overcome the curse of dimensionality is the least-squares Monte Carlo methodology (LSMC), see *e.g.*, [14, 15, 16, 17, 18, 19]. LSMC relies on a projection of the solution onto a lower-dimensional subspace spanned by a set of orthogonal basis functions, such as *e.g.*, Laguerre or Hermite polynomials. Even though these methods overcome the curse of dimensionality, it is nontrivial to find suitable basis functions for the approximation of complicated function surfaces in high dimensions. Other notable methods are algorithms, or reformulations, based on Malliavin calculus or branching diffusion systems. A general property of backward methods is that the terminal condition of the backward equation depends on the realization of the forward equation. This is not a problem for *decoupled* FBSDE, but for coupled FBSDE the method becomes implicit and iterative schemes which may not always converge need to be employed.

A second class of algorithms, which is better suitable for coupled FBSDE is the class of forward methods. One such approach is based on the connection between FBSDE and parabolic PDE. If the PDE can be approximated (and in general, also its gradient) on a computational grid, then an approximation of the FBSDE solution can also be obtained by pathwise evaluation of the PDE solution and its gradient, see *e.g.*, [8, 9, 10]. However, since these methods are based on a discrete mesh, they also suffer from the curse of dimensionality. We also mention the Picard linearization scheme, which relies on a contraction mapping. When this method converges, it is suitable for the approximation of high-dimensional FBSDE, see *e.g.*, [11, 12, 13]. See [20] for a summary on forward and backward numerical methods for FBSDE.

In addition to the classical methods described above, a new branch of algorithms based on neural networks has appeared in recent years. In [22, 23], the authors present a method called the *Deep BSDE solver*, which relies on a neural network parametrization of the control process and the initial condition of the backward equation. Both the forward and the backward equations are then treated as forward equations and approximated with the Euler–Maruyama scheme. To achieve an accurate approximation, the parameters of the neural networks are optimized such that the terminal condition on the backward equation is (approximately) satisfied in mean-squared sense. The method has proven to be able to approximate a wide class of equations in very high dimensions (at least 100). Since the original Deep BSDE solver publication, several papers with adjustments of the algorithm as in *e.g.*, [33, 34, 36, 38, 39, 24, 50, 51] and others with convergence analysis in *e.g.*, [25, 27, 28, 29, 30, 31, 32], have been published. In addition to being forward methods, these algorithms are *global* in their approximation, meaning that the optimization of all involved neural networks is carried out simultaneously. This implies that they are optimized subject to one single objective function, also called *loss function*, as it is usually referred to in the machine learning literature. There also exists a branch of neural network based algorithms relying on *local* optimization techniques. Typically, these methods are of backward type and of similar nature as the LSMC algorithms, but instead of polynomials as their basis functions, neural networks are used. As for the LSMC method, these kinds of algorithms are not easily applied to coupled FBSDE. Algorithms of this type can be found in *e.g.*, [42, 41, 43] and with error analysis [44]. For an overview of machine learning algorithms for approximation of PDE we refer to [45].

In this paper we are interested in problems from stochastic control, which implies that the FBSDE are coupled by nature. Therefore, the focus is on global algorithms operating forward in time, with a structure similar to the Deep BSDE solver. There are several attempts to use the deep BSDE solver for stochastic control problem, see *e.g.*, [47, 48, 49, 39, 40], where the deep BSDE solver is applied to the FBSDE associated with the stochastic control problem. We demonstrate in this paper, that this approach is problematic since even though an accurate approximation of the control problem can be achieved, this does not imply an approximation of the FBSDE in general. Moreover, it is observed that the deep BSDE solver does not converge for certain problems and, as we show in the present paper, the convergence problem is prominent for the strongly coupled FBSDE. In [25] an a posteriori error bound for the deep BSDE solver was established for weakly coupled FBSDE which

was later extended to non-Lipschitz coefficients (but for less general diffusion coefficients) in [26]. However, these results are difficult to extend to strongly coupled FBSDE and we observe several examples in which the discrete terminal condition converges while the FBSDE approximation does not. This indicates that the convergence results from [25] cannot be extended to this class of equations. For this reason, we exploit the known structure of the problem which comes from the connection to the original stochastic control problem, to introduce an extension to the deep BSDE solver which can overcome this problem. Moreover, under regularity assumptions similar to those in [25], we show several different convergence concepts for the proposed algorithm such as convergence of the initial and terminal conditions of the BSDE. Finally, under some restrictions on the terminal time, we show strong convergence of order α to the full FBSDE, where $\alpha \in (0, 1]$ depends on the regularity of the FBSDE coefficients.

This paper is structured as follows: In Section 2, we present the stochastic control problem and explain the reformulations to a PDE as well as an FBSDE. Moreover, we introduce reformulations of the FBSDE to different variational problems which are used for the algorithms in later sections. The section concludes by introducing the time discrete counterparts of the reformulations as well as a discussion on when and why the deep BSDE solver fails to converge. In Section 3 the fully implementable algorithms are presented together with details on the neural networks used. Section 4 is devoted to error analysis of the proposed algorithm. Both classical Euler–Maruyama type discretization errors and errors stemming from differences between time discrete and time continuous stochastic control are discussed. Finally, in Section 5 numerical approximations are compared with their analytic counterparts when we have such available. We also give convergence plots for different problems and discuss the connection to the theoretical analysis in Section 4.

2 The deep FBSDE method and an improved family of methods

This section contains a formal introduction to our method and the context of FBSDE and stochastic control. Section 2.1 introduces the stochastic control problem, the related Hamilton–Jacobi–Bellman equation and FBSDE. Alternative formulations of the FBSDE are presented in Section 2.2. In Section 2.3 we motivate by numerical examples why a direct extension of the deep BSDE method to FBSDE, as in [47, 48, 49], fails for many problems. Finally, in Section 2.4 we present the proposed robust deep FBSDE method. As rigour is not the purpose of this section the assumptions that guarantee that our claims are true are not yet given.

2.1 Stochastic control and FBSDE

Our starting point is a controlled SDE and its associated cost functional

$$\begin{cases} X_t^u = x_0 + \int_0^t \bar{b}(t, X_t^u, u_t) dt + \int_0^t \sigma(t, X_t^u) dW_t, & (1) \\ J(t, x; u) = \mathbb{E} \left[\int_t^T \bar{f}(t, X_t^u, u_t) dt + g(X_T^u) \mid X_t^u = x \right]. & (2) \end{cases}$$

Here $T \in (0, \infty)$, $d, k, \ell \in \mathbb{N}$, $(W_t)_{t \in [0, T]}$ is a k -dimensional standard Brownian motion, the coefficients $\bar{b}: [0, T] \times \mathbb{R}^d \times \mathbb{R}^\ell \rightarrow \mathbb{R}^d$, $\sigma: [0, T] \times \mathbb{R}^d \times \mathbb{R}^\ell \rightarrow \mathbb{R}^{d \times k}$, $\bar{f}: [0, T] \times \mathbb{R}^d \times \mathbb{R}^\ell \rightarrow \mathbb{R}$ and $g: \mathbb{R}^d \rightarrow \mathbb{R}$ satisfy some extra regularity conditions, and the control process $u = (u_t)_{t \in [0, T]}$ belongs to a set \mathcal{U} of admissible controls, taking values in a set $U \subset \mathbb{R}^\ell$. The aim is to find a control process $u^* \in \mathcal{U}$ that minimizes $J(0, x_0; u)$.

Assuming the cost to be bounded from below, the *value function* of the control problem is given by

$$V(t, x) = \inf_{u \in \mathcal{U}} J^u(t, x). \quad (3)$$

For the presentation, we assume uniqueness of the infimum. Under appropriate conditions, the value function satisfies a *Hamilton–Jacobi–Bellman* (HJB) equation, which is a non-linear parabolic PDE given by

$$\begin{cases} \frac{\partial V}{\partial t}(t, x) + \frac{1}{2} \text{Tr}(\sigma \sigma^\top D_x^2 V)(t, x) + \mathcal{H}(t, x, D_x V(t, x)) = 0, & (t, x) \in [0, T] \times \mathbb{R}^d, \\ V(t, x) = g(x), & (t, x) \in \{T\} \times \mathbb{R}^d. \end{cases} \quad (4)$$

Here Tr denotes the trace of a matrix and for $(t, x) \in [0, T] \times \mathbb{R}^d$, $p \in \mathbb{R}^d$ the *Hamiltonian*, \mathcal{H} , is given by

$$\mathcal{H}(t, x, p) = \inf_{v \in U} [\bar{b}(t, x, v)^\top p + \bar{f}(t, x, v)]. \quad (5)$$

Under conditions that guarantee (4) to have a sufficiently regular solution, and the infimum in the Hamiltonian to be attained at $v^* = v^*(t, x, p)$, the optimal control is of the feedback form $u^*(t, X_t) = v^*(t, X_t, D_x V(t, X_t))$,

where we have written $X := X^{u^*}$ for the optimally controlled X^u . The feedback map v^* is for many interesting problems easy to derive. Again, under sufficient regularity, Itô's formula applied to $V(t, X_t)$ yields

$$\begin{cases} X_t = x_0 + \int_0^t b(s, X_s, Z_s) ds + \int_0^t \sigma(s, X_s) dW_s, \\ Y_t = g(X_T) + \int_t^T f(s, X_s, Z_s) ds - \int_t^T \langle Z_s, dW_s \rangle, \end{cases} \quad (6)$$

where $Y_t = V(t, X_t)$, $Z_t = \sigma^T(t, X_t) D_x V(t, X_t)$ and for $\theta \in \{b, f\}$ we have

$$\theta(t, X_t, Z_t) := \bar{\theta}(t, X_t, v^*(t, X_t, (\sigma(t, X_t) \sigma^T(t, X_t))^{-1} \sigma(t, X_t) Z_t)).$$

In the rest of this section we assume the existence of a unique solution (X, Y, Z) of (6) in appropriate spaces. Given Z or equivalently $D_x V$ we thus have an optimal control $u_t^* = v^*(t, X_t, (\sigma(t, X_t) \sigma^T(t, X_t))^{-1} \sigma(t, X_t) Z_t)$. This would make efficient numerical FBSDE schemes very useful for solving the control problem. In the other direction, if we have an optimal control u^* , then in general this does not give us Z , unless $p \mapsto v^*(t, x, p)$ is invertible, and only in this case the control problem naturally suggests numerical schemes for FBSDE. Below, we introduce a family of numerical schemes for FBSDE that works regardless of invertibility of the feedback map, but reduces to the control problem in the case of invertibility.

2.2 Alternative formulations of FBSDE

The Deep BSDE solver proposed in [22], relies on a reformulation of the FBSDE (6) into two forward SDE, one with apriori unknown initial value. It relies moreover on the Markov property of the FBSDE, which guarantees that $Z_t = \zeta^*(t, X_t)$ for some function $\zeta^*: [0, T] \times \mathbb{R}^d \rightarrow \mathbb{R}^k$, that we refer to as Markov map, and optimization is done with respect to such functions and initial values y_0 . More precisely, the FBSDE (6) is reformulated into the following variational problem

$$\begin{cases} \text{minimize}_{y_0, \zeta} \mathbb{E} |Y_T^\zeta - g(X_T^\zeta)|^2, \quad \text{where} \\ X_t^\zeta = x_0 + \int_0^t b(s, X_s^\zeta, Z_s^\zeta) ds + \int_0^t \sigma(s, X_s^\zeta) dW_s, \\ Y_t^\zeta = y_0 - \int_0^t f(s, X_s^\zeta, Z_s^\zeta) ds + \int_0^t \langle Z_s^\zeta, dW_s \rangle, \\ Z_s^\zeta = \zeta(s, X_s^\zeta), \end{cases} \quad (7)$$

where y_0 and ζ are sought in appropriate spaces. From the theory outlined in Section 2.1, under well-posedness and sufficient regularity of (6), it holds that $Y_0 = V(0, x_0)$ and $\zeta^* = \sigma^\top D_x V$, and thus we have well-posedness of (7). While it seems natural to propose a numerical algorithm based on a discrete version of (7), we demonstrate below that for such a scheme, a good approximation of Y_0 is not found in neither a local nor global minimum.

In order to introduce numerical schemes that do not suffer under the above problem, we use the following two properties of the initial value Y_0 of (6):

- (i) Y_0 coincides with the value function of the control problem (property from the control problem);
- (ii) Y_0 is \mathcal{F}_0 -measurable and therefore has zero variance (property from the FBSDE).

The two properties are both captured in the following variational problem:

$$\begin{cases} \text{minimize}_{\zeta} \Phi_\lambda(\zeta) = \mathbb{E}[\mathcal{Y}_0^\zeta] + \lambda \text{Var}[\mathcal{Y}_0^\zeta], \quad \text{where} \\ \mathcal{Y}_0^\zeta = g(X_T^\zeta) + \int_0^T f(t, X_t^\zeta, Z_t^\zeta) dt - \int_0^T \langle Z_t^\zeta, dW_t \rangle, \\ X_t^\zeta = x_0 + \int_0^t b(s, X_s^\zeta, Z_s^\zeta) ds + \int_0^t \sigma(s, X_s^\zeta) dW_s, \\ Y_t^\zeta = \mathbb{E}[\mathcal{Y}_0^\zeta] - \int_0^t f(s, X_s^\zeta, Z_s^\zeta) ds + \int_0^t \langle Z_s^\zeta, dW_s \rangle, \\ Z_t^\zeta = \zeta(t, X_t^\zeta). \end{cases} \quad (8)$$

We refer to \mathcal{Y}_0^ζ as the *stochastic cost* and notice that $\mathbb{E}[\mathcal{Y}_0^\zeta] = J^\zeta(0, x_0)$, where $u = u(\zeta) \in \mathcal{U}$ is the control generated by ζ . Thus the first term of the objective function Φ_λ is the cost function of the control problem. In

the case of $\alpha \mapsto v^*(t, x, \alpha)$ being invertible, this term alone, i.e., for $\lambda = 0$, offers an equivalent formulation to (7). In other cases uniqueness of minimizers of $\zeta \mapsto \mathbb{E}[y_0^\zeta]$ cannot be guaranteed. But among the minimizers, there is only one ζ^* with the property that the variance of the stochastic cost \mathcal{Y}_0^ζ equals zero. The second term of Φ_λ is introduced to penalize non-zero variance and the minimizer for $\lambda > 0$ is unique. Another important feature of the formulation (8) is that Y_0^ζ is determined by ζ alone and (8) has thus one degree of freedom less than (7). A final observation is that

$$\text{Var}[\mathcal{Y}_0^\zeta] = \mathbb{E}[|\mathbb{E}[\mathcal{Y}_0^\zeta] - \mathcal{Y}_0^\zeta|^2] = \mathbb{E}\left[\left|Y_0^\zeta - \int_0^t f(s, X_s^\zeta, Z_s^\zeta)ds + \int_0^t Z_s^\zeta dW_s - g(X_T^\zeta)\right|^2\right] = \mathbb{E}[|Y_T^\zeta - g(X_T^\zeta)|^2]. \quad (9)$$

This implies that the second term of Φ is, up to the factor λ , the same as that of (7), but with Y_0^ζ not being a variable to optimize. Thus there are strong similarities between (7) and (8), but in the time discrete setting the latter formulation is shown to be advantageous sections below.

2.3 A direct extension of the deep BSDE method and why it fails

In this section, we present the time discrete counterpart of (7). We assume an equidistant time grid $0 = t_0 < t_1 < \dots < t_N = T$, with $h = t_{n+1} - t_n$ and denote the Brownian increment $\Delta W_n = W_{n+1} - W_n$. Throughout the paper we parameterize discretizations by $h \in (0, 1)$ and by this we mean all $h \in (0, 1) \cap \{T/N : N \geq 1\}$.

The time discrete version of (7) is given by

$$\begin{cases} \underset{y_0, \zeta}{\text{minimize}} & \mathbb{E}\left[|Y_N^{h, y_0, \zeta} - g(X_N^{h, y_0, \zeta})|^2\right], \quad \text{where} \\ X_n^{h, y_0, \zeta} &= x_0 + \sum_{k=0}^{n-1} b(t_k, X_k^{h, y_0, \zeta}, Z_k^{h, y_0, \zeta})h + \sum_{k=0}^{n-1} \sigma(t_k, X_k^{h, y_0, \zeta})\Delta W_k, \\ Y_n^{h, \zeta} &= y_0 - \sum_{k=0}^{n-1} f(t_k, X_k^{h, y_0, \zeta}, Z_k^{h, y_0, \zeta})h + \sum_{k=0}^{n-1} \langle Z_k^{h, y_0, \zeta}, \Delta W_k \rangle, \\ Z_k^{h, y_0, \zeta} &= \zeta_k(X_k^{h, y_0, \zeta}). \end{cases} \quad (10)$$

It is a direct extension of the deep BSDE method from [22, 23]. In the literature it was first applied experimentally to FBSDE in the master thesis [47] and thereafter in [48], both for inverted pendulums, in [49] for an application to attitude control of hypersonic unmanned aerial vehicles. More examples of deep FBSDE are found in [39, 40].

In [25], the authors consider FBSDE with coefficients b, σ and f that may take the Y -component, but not the Z -component, as arguments. Under the relatively strict assumption of weak coupling (also called monotonicity condition, see *e.g.*, [54]), it is shown that for h small enough there is a constant C , independent of h , such that

$$\sup_{t \in [0, T]} \left(\mathbb{E}\left[|X_t - \hat{X}_t^{h, y_0, \zeta}|^2\right] + \mathbb{E}\left[|Y_t - \hat{Y}_t^{h, y_0, \zeta}|^2\right] \right) + \int_0^T \mathbb{E}\left[|Z_t - \hat{Z}_t^{h, y_0, \zeta}|^2\right] dt \leq C \left(h + \mathbb{E}\left[|Y_N^{h, y_0, \zeta} - g(X_N^{h, y_0, \zeta})|^2\right] \right), \quad (11)$$

where for $t \in [t_k, t_{k+1})$, $\hat{X}_t^{h, y_0, \zeta} := X_k^{h, y_0, \zeta}$, $\hat{Y}_t^{h, y_0, \zeta} := Y_k^{h, y_0, \zeta}$ and $\hat{Z}_t^{h, y_0, \zeta} = \zeta_k(X_k^{h, y_0, \zeta})$. Under some additional assumptions on the coefficients b, f, σ and g , (additional smoothness and boundedness of the coefficients to guarantee a bounded and smooth solution of the associated HJB equation) the results in [25] can be extended to the framework of interest in this paper, *i.e.*, coefficients taking the Z -component as an argument. On the other hand, the weak coupling condition is rarely satisfied for FBSDE stemming from stochastic control problems, and to the best of our knowledge, there is no known way to relax this condition.

To investigate convergence of (10) empirically, we first note that if we would know Y_0 a priori, then the variational problem (7) would be reduced to finding $\zeta := \{\zeta_0, \zeta_1, \dots, \zeta_{N-1}\}$. We also know that $D_x V^\top \sigma$ is the minimizer, which would make the objective function identical to zero. In the discrete counterpart, we would expect that, if (10) converges to (7), then for sufficiently small h , the objective function would be close to zero if optimizing only ζ and setting $y_0 = Y_0$. Moreover, for a robust algorithm to emerge from (10) it is important that $y_0 \neq Y_0$ results in a larger value of the optimal objective function, at least when y_0 and the true initial value, Y_0 are "far away" from each other. To formalize this, we introduce the formulation

$$\text{MSE}(y_0) := \inf_{\zeta} \mathbb{E}\left[|Y_N^{h, y_0, \zeta} - g(X_N^{h, y_0, \zeta})|^2\right]. \quad (12)$$

The aim is to investigate whether or not MSE is minimized at, or close to, the true initial condition Y_0 . Moreover, for each y_0 , we want to investigate the ζ^{y_0} that minimizes $\zeta \mapsto \mathbb{E}[|Y_N^{h, y_0, \zeta} - g(X_N^{h, y_0, \zeta})|^2]$. The discrete costs, associated with (y_0, ζ^{y_0}) and (y_0, ζ) , are given by

$$J_0^{h, y_0} = J_0^{h, y_0, \zeta^{y_0}} \quad \text{and} \quad J_0^{h, y_0, \zeta} = \mathbb{E}[\mathcal{Y}_0^{h, y_0, \zeta}].$$

Here, the *discrete stochastic cost* is given by

$$\mathcal{J}_0^{h,y_0,\zeta} = g(X_N^{h,y_0,\zeta}) + \sum_{k=0}^{N-1} f(t_k, X_k^{h,y_0,\zeta}, Z_k^{h,y_0,\zeta})h - \sum_{k=0}^{N-1} \langle Z_k^{h,y_0,\zeta}, \Delta W_k \rangle. \quad (13)$$

Using the stochastic cost we have by a substitution that

$$\text{MSE}(y_0) = \inf_{\zeta} \mathbb{E}[|\mathcal{J}_0^{h,y_0,\zeta} - y_0|^2]. \quad (14)$$

Figure 1 shows $y_0 \mapsto \text{MSE}(y_0)$ and $y_0 \mapsto J_0^{h,y_0}$ for two different Linear-Quadratic (LQ) control problems, a one-dimensional and a two-dimensional. The left figure shows that there is a minimum of MSE at the correct Y_0 and for this problem the method converges. For the right figure it is clear that there is no minimum of MSE around Y_0 , or anywhere in the range. When y_0 and ζ are jointly optimized the method has no chance to converge for this problem. When searching for example problems we have found no multi-dimensional LQ-problem that converges.

Both problems considered in this section are of the form (5.1) with parameters as in Section 5.1.1 for the two-dimensional problem and $A = B = C = R_x = R_u = G = 1$ and $\sigma = 0.5$ for the one-dimensional problem.




Figure 1: Demonstration of the performance of the direct extension of the deep BSDE solver to FBSDE corresponding to two LQ control problems. **Left:** A one-dimensional problem with $N = 10$ time steps. **Right:** A two-dimensional problem with $N = 100$ time steps.

We identify three distinct cases from Figure 1:

- $y_0 \approx Y_0$: In this case MSE is the mean square error of the discretized FBSDE and it is most reasonable that an approximation of (X, Y, Z) can be generated by optimizing over ζ .
- $y_0 > Y_0$: Under this assumption, any ζ attaining the infimum in (14) satisfies $\mathbb{E}[\mathcal{J}_0^{h,y_0,\zeta}] = J_0^{h,y_0} = y_0$. Thus minimizing (14), or equivalently (12), is the same as finding the ζ that generates cost $J_0^{h,y_0,\zeta} = y_0$ and that at the same time minimizes the mean square error in the terminal condition. A ζ with cost $y_0 > Y_0$ has the possibility to generate a lower $\text{MSE}(y_0) < \text{MSE}(Y_0)$, depending on y_0 and the problem at hand. This is only possible if the coupling of Z in b is strong enough, so that $g(X_T)$ can be efficiently controlled by Z . In the case with no coupling, i.e., for BSDE, $y_0 > Y_0$ leads to MSE of the magnitude $y_0 - Y_0$, and thus MSE is increasing in this regime. This is the reason why non-coupled BSDE as in [22, 23], or weakly coupled FBSDE as in [25] can be approximated with the deep BSDE method. The left plot of Figure 1 shows this favorable behaviour, while the right plot has a decreasing MSE and has no chance to converge. We also see that the cost increases linearly for $y_0 > Y_0$ according to $J_0^{h,y_0} = y_0$.
- $y_0 < Y_0$: Since Y_0 is (approximately) a lower bound of $(y_0, \zeta) \mapsto J_0^{h,y_0,\zeta}$, it holds that any ζ attaining the infimum in $\zeta \mapsto \mathbb{E}[|\mathcal{J}_0^{h,y_0,\zeta} - y_0|^2]$ also minimizes the cost functional $\zeta \mapsto J_0^{h,y_0,\zeta}$. But y_0 does not enter $\mathcal{J}_0^{h,y_0,\zeta}$ explicitly. Therefore, the minimizer of $\zeta \mapsto \mathbb{E}[\mathcal{J}_0^{h,y_0,\zeta}]$ does not depend on y_0 . Thus fixing $y_0 < Y_0$ and optimizing ζ approximates a solution to the control problem but not to the FBSDE. This can clearly be seen in Figure 1 from the cost being constant for $y_0 < Y_0$ in both plots. It is also clear that the MSE increases for decreasing $y_0 < Y_0$.

To further visualize the three cases, Figure 2 shows the empirical means and 90% confidence regions (defined as the area between the 5 :th and the 95 :th empirical percentiles at each time point) for the true and approximated

Y and Z processes of the two dimensional LQ-problem discussed above. In the top row we see that, in the case $y_0 \approx Y_0$, the two components of the Z -process are very well approximated, but the time discretization error of Y is visible. In the middle row, for $y_0 > Y_0$ we see what is expected based on the discussion above. The Y process satisfies the terminal value but are otherwise fundamentally distinct from the true Y . Since by setting $y_0 > Y_0$ we have asked for a control with cost y_0 , the two components of Z have oscillations to increase the cost to this level. Thus in this case neither Y nor Z are approximated. In the bottom row, the case $y_0 < Y_0$ is shown. Just as explained above, the control problem is solved and therefore the Z process is well approximated. It should though be noted that this is only true since the map $\alpha \mapsto v^*(t, x, \alpha)$, for this specific problem, is invertible. Otherwise, one optimal ζ , in a set of many optimal Markov maps, is approximated. Thus, the control problem is approximately solved, however Z -component of the FBSDE is unlikely to be accurate. The Y process is shifted by $y_0 - Y_0$ and the terminal value is naturally not satisfied.




Figure 2: Demonstration of the performance of the Deep FBSDE solver with fixed initial condition for $N = 100$ time steps. The shaded areas represent the domain in which 90% of all trajectories lie (the area is bounded by the 5:th and the 95:th empirical percentiles). **Left to right:** Sample means of the approximate and the semi-analytic (Riccati solutions) Y -process and the first and second components of the Z -process (C1 and C2). **Top to bottom:** Initial conditions $\hat{y}_0 = 0.0 < Y_0$, $\hat{y}_0 = 0.612 = Y_0$ and $\hat{y}_0 = 1.5 > Y_0$.

In the work with [47] it was noted that the deep FBSDE method, applied to inverted pendulum problems, was sensitive to the choice of model and penalty parameters. For many physically sensible parameters the method did not work. Our own search for interesting LQ-problems in this work, taught us that it is much easier to find problems that do not converge than finding problems that do converge. Therefore, it is our assumption that the problems of consideration in the literature were carefully chosen to demonstrate a successful training, or a family of problems was of interest that was not sensitive to parameter choices. In the case of non-unique feedback control it is also highly likely that by using the deep FBSDE method, the control problems were approximately solved but not the FBSDE.

2.4 A robust deep FBSDE method

Having observed the problems with the direct extension of the deep BSDE method to FBSDE, we here discretize the alternative formulation (8) of the FBSDE to obtain an alternative family of deep FBSDE methods. It reads:

$$\left\{ \begin{array}{l} \underset{\zeta}{\text{minimize}} \Phi_{\lambda,h}(\zeta) = \mathbb{E}[\mathcal{Y}_0^{h,\zeta}] + \lambda \text{Var}[\mathcal{Y}_0^{h,\zeta}], \quad \text{where,} \\ \mathcal{Y}_0^{h,\zeta} := g(X_N^{h,\zeta}) + \sum_{k=0}^{N-1} f(t_k, X_k^{h,\zeta}, Z_k^{h,\zeta})h - \sum_{k=0}^{N-1} \langle Z_k^{h,\zeta}, \Delta W_k \rangle, \\ X_n^{h,\zeta} = x_0 + \sum_{k=0}^{n-1} b(t_k, X_k^{h,\zeta}, Z_k^{h,\zeta})h + \sum_{k=0}^{n-1} \sigma(t_k, X_k^{h,\zeta})\Delta W_k, \\ Y_n^{h,\zeta} = \mathbb{E}[\mathcal{Y}_0^{h,\zeta}] - \sum_{k=0}^{n-1} f(t_k, X_k^{h,\zeta}, Z_k^{h,\zeta})h + \sum_{k=0}^{n-1} \langle Z_k^{h,\zeta}, \Delta W_k \rangle, Z_k^{h,\zeta} = \zeta_k(X_k^{h,\zeta}). \end{array} \right. \quad (15)$$

The main purpose and results of the current paper is the theoretical and numerical error analysis of (15).

In [52] the case $\lambda = 0$ was considered in the context of discrete time stochastic control, without explicit connections to FBSDE, or even to stochastic control in continuous time. The stochastic sum in $\mathcal{Y}_0^{h,\zeta}$ was not considered. More precisely, the discrete cost functional was used as loss function to train neural network approximations of feedback maps for the control. This is different from our method since we approximate the Markov maps for Z instead, but for σ with full rank it is equivalent, at least theoretically. Another method which also makes use of the connection to stochastic control, when approximating an FBSDE, was proposed in [50]. In this paper, the stochastic maximum principle approach to stochastic control is used, and this results in a different type of FBSDE, compared to the one obtained with the dynamic programming principle, that we consider in this paper. A similarity is that in both papers the algorithms use a method similar to that in [52], to include the cost in the objective function. The recent paper [51] is, to the best of our knowledge, the first to introduce the variance penalty term in (15) for an FBSDE obtained from the dynamic programming principle. They do not have the cost penalty and they approach the problem differently in that they have one network for the Markov map for Z and one for the feedback map for the control.

2.5 Decoupled BSDE and why coupled FBSDE are important

It is claimed in the literature that since coupled FBSDE can be transformed into decoupled BSDE, it is sufficient to have schemes for the latter, see *e.g.*, [25]. Here we explain this claim and why we, from a practical and applied viewpoint, do not agree. If $\psi: [0, T] \times \mathbb{R}^d \times \mathbb{R}^\ell \rightarrow \mathbb{R}^d$ is sufficiently regular, then it holds by the Itô formula for $Y_t^\psi = V(t, X_t^\psi)$ and $Z_t^\psi = \sigma^T(t, X_t^\psi)D_x V(t, X_t^\psi)$ that

$$\left\{ \begin{array}{l} X_t^\psi = x_0 + \int_0^t (b(s, X_s^\psi, Z_s^\psi) - \psi(s, X_s^\psi, Z_s^\psi))ds + \int_0^t \sigma(s, X_s^\psi)dW_s, \\ Y_t^\psi = g(X_T^\psi) + \int_t^T (f(s, X_s^\psi, Z_s^\psi) - \langle (\sigma(s, X_s^\psi)\sigma^T(s, X_s^\psi))^{-1}\sigma(s, X_s^\psi)Z_s^\psi, \psi(s, X_s^\psi, Z_s^\psi) \rangle)ds - \int_t^T \langle Z_s^\psi, dW_s \rangle. \end{array} \right.$$

Thus taking ψ so that $b - \psi$ does not depend on Z , decouples the FBSDE into a BSDE, where the forward equation has no coupling with the backward equation. From this observation it might be tempting to approximate the optimal Markov map $\sigma^T(t, x)D_x V(t, x)$ with the deep BSDE method. The problem with this approach is that the deep BSDE method will learn $\sigma^T(t, x)D_x V(t, x)$ well only around typical trajectories of X^ψ but not of X . While there is empirical evidence that the deep BSDE method overcomes the curse of dimensionality, it does not at all approximate the solution everywhere, but only around the typical solution trajectories of the forward equation. Since X is controlled, it is expected for most problems to have quite a different dynamics than X^ψ and this ruins the applicability of the deep BSDE method for control problems, if the feedback control is desired. In the original deep BSDE paper [22], the solution to an HJB equation is approximated at the initial time. For such applications a decoupled BSDE can be used as the Markov map is not the primary focus.

3 Fully implementable scheme and neural network regression

In this section, we describe how the discrete variational problem (15) is approximated with the help of neural network regression. In principle, other function approximators could be used, but neural network regression is arguably one of the most suitable choices due to the ability to approximate complicated high-dimensional functions. Although neural networks have shown empirically high quality results in many different fields, there are still many open convergence questions related to the optimization procedure of the loss function. On the

other hand, the Universal Approximation Theorem (UAT) [61] guarantees that under certain conditions, there is a neural network, sufficiently deep and wide, such that it is possible to approximate a large class of continuous functions to any, pre-specified degree of accuracy.

3.1 Fully implementable algorithms

Without further specifications, (15) assumes exact optimization over an unspecified set of functions ζ and the exact computation of expectations. To define a fully implementable scheme, the Markov maps $\zeta_0, \dots, \zeta_{N-1}$ are approximated with neural networks $\phi_0^{\theta_0}, \dots, \phi_{N-1}^{\theta_{N-1}}$ with parameters $\theta = (\theta_0, \dots, \theta_{N-1})$ in some parameter space Θ . We specify them in further detail below. Moreover, expectations are approximated with batch Monte-Carlo simulation. Let $K_{\text{epochs}} \geq 1, K_{\text{batch}} \geq 1$ be the number of epochs and the number of batches per epoch. Let further $M_{\text{train}}, M_{\text{batch}} \geq 1$ be the size of the training data set and batch, respectively. We assume that $M_{\text{train}}/(2M_{\text{batch}}) = K_{\text{batch}} \in \mathbb{N}$. Training data are M_{train} independent realizations of the Wiener increments $\Delta W_0, \dots, \Delta W_{N-1} \sim \mathcal{N}(0, h)$ and the training data are reused in K_{epoch} epochs. The training is initialized by random sampling of $\theta^0 \in \Theta$. For each update step in an epoch of the training algorithm we take $2M_{\text{batch}}$ Wiener increments $\Delta W_0(m), \dots, \Delta W_{N-1}(m)$, $m = 1, 2, \dots, 2M_{\text{batch}}$ from the training data set that were not previously used during the epoch and update θ by approximate optimization of the following problem:

$$\left\{ \begin{array}{l} \text{minimize}_{\theta \in \Theta} \mathcal{L}_{\lambda, h}(\theta) = \frac{1}{M_{\text{batch}}} \left(\sum_{m=1}^{M_{\text{batch}}} \mathcal{Y}_0^{h, \theta}(m) + \lambda \cdot \sum_{m=M_{\text{batch}}+1}^{2M_{\text{batch}}} |g(X_N^{h, \theta}(m)) - Y_N^{h, \theta}(m)|^2 \right), \quad \text{where,} \\ \mathcal{Y}_0^{h, \theta}(m) := g(X_N^{h, \theta}(m)) + \sum_{k=0}^{N-1} f(t_k, X_k^{h, \theta}(m), Z_k^{h, \theta}(m))h - \sum_{k=0}^{N-1} \langle Z_k^{h, \theta}(m), \Delta W_k(m) \rangle, \\ X_n^{h, \theta}(m) = x_0 + \sum_{k=0}^{n-1} b(t_k, X_k^{h, \theta}(m), Z_k^{h, \theta}(m))h + \sum_{k=0}^{n-1} \sigma(t_k, X_k^{h, \theta}(m))\Delta W_k(m), \\ Y_n^{h, \theta}(m) = \frac{1}{M_{\text{batch}}} \sum_{m=1}^{M_{\text{batch}}} \mathcal{Y}_0^{h, \theta}(m) - \sum_{k=0}^{n-1} f(t_k, X_k^{h, \theta}(m), Z_k^{h, \theta}(m))h + \sum_{k=0}^{n-1} \langle Z_k^{h, \theta}(m), \Delta W_k(m) \rangle, \\ Z_k^{h, \theta}(m) = \phi_k^{\theta_k}(X_k^{h, \theta}(m)). \end{array} \right. \quad (16)$$

When all training data was used we start a new epoch and when the K_{epoch} :th epoch is finished we terminate. The neural network parameters at termination are θ^* . It is an approximation of the parameters θ^{**} that optimize (16) in the limit $M_{\text{batch}} \rightarrow \infty$. To complement (16), Algorithm 1 details the training procedure.

It should be noted that the expected value of the stochastic sum in $\mathcal{Y}_0^{h, \theta}$ equals zero. Therefore, the algorithm would also work without it, but a practical reason to keep it is that it decreases the variance of $\mathcal{Y}_0^{h, \theta}$ significantly, and this requires fewer Monte-Carlo samples to achieve the same accuracy.

3.2 Specification of the neural networks

Here we introduce the neural networks that we use in our implementations in Section 5. The generality is kept to a minimum and more general architectures are of cause possible. For each $\phi_k^{\theta_k} : \mathbb{R}^d \rightarrow \mathbb{R}^\ell$ a fully connected neural network with two hidden layers with 20 nodes in each layer and ReLU activation function $\mathfrak{R}(x) = \max(0, x)$ acting elementwise. More precisely, the $\phi_k^{\theta_k}$ is of the form

$$\phi_k^{\theta_k}(x) = W_k^3 \mathfrak{R}(W_k^2 \mathfrak{R}(W_k^1 x + b_k^1) + b_k^2) + b_k^3,$$

with weight matrices $W_k^1 \in \mathbb{R}^{20 \times d}$, $W_k^2 \in \mathbb{R}^{20 \times 20}$, $W_k^3 \in \mathbb{R}^{\ell \times 20}$ and bias vectors $b_k^1, b_k^2 \in \mathbb{R}^{20}$, $b_k^3 \in \mathbb{R}^\ell$, and $\theta_k = (W_k^1, W_k^2, W_k^3, b_k^1, b_k^2, b_k^3)$, where the matrices are considered vectorized before concatenation.

4 Convergence analysis

In this section we primarily provide an error analysis for (15), i.e., for semidiscretization in time. In Section 4.1 we introduce notation and spaces, and in Section 4.2 we present the setting and some further notation. Two technical results on strong and weak convergence are stated and proved in Section 4.3. These two results are used in Section 4.4 to prove the error in the objective function, in the initial and terminal value of Y and for the variance of the stochastic control. The results hold under an assumption on the regularity of the exact continuous and discrete Markov maps. Convergence of the latter to the former is not assumed. Section 4.5 contains strong convergence of the FBSDE under either the stronger assumption of small time T or convergence of the discrete Markov maps. A discussion about a full error analysis for the fully implementable scheme (16) is presented in Section 4.6.

Input: Initialization of neural network parameters, $\{\theta_0(1), \dots, \theta_{N-1}(1)\}$ and for $0 \leq k \leq 2M_{\text{train}}$ and $0 \leq n \leq N - 1$ Wiener increments $\Delta W_n(k)$.

Output: Approximation of the Markov map for $(Z_t)_{t \in [0, T]}$ at the time discrete mesh points.

for $k = 1, 2, \dots, K_{\text{batch}}$ ($K_{\text{batch}} = \frac{M_{\text{train}}}{2M_{\text{batch}}}$ is the number of batches.) (Should be carried out sequentially) **do**

for $1 \leq m \leq M_{\text{batch}}$ (May be carried out in parallel) **do**

 Set $X_0^{h, \theta}(m) = x_0$

for $n = 0, \dots, N - 1$ (Should be done sequentially) **do**

$Z_n^{h, \theta}(m) = \phi_n(X_n^{h, \theta}(m) | \theta_n(k))$

$X_{n+1}^{h, \theta}(m) = X_n^{h, \theta}(m) + b(t_n, X_n^{h, \theta}(m), Z_n^{h, \theta}(m))h + \sigma(t_n, X_n^{h, \theta}(m))\Delta W_n(m)$

end

end

for $m \in \{M_{\text{batch}} + 1, \dots, 2M_{\text{batch}}\}$ (May be carried out in parallel) **do**

 Set $X_0^{h, \theta}(m) = x_0$ and $Y_0^{h, \theta}(m) =$

$\frac{1}{M_{\text{batch}}} \sum_{m=M_{\text{batch}}+1}^{2M_{\text{batch}}} g(X_N^{h, \theta}(m)) + \sum_{n=0}^{N-1} f(t_n, X_n^{h, \theta}(m), Z_n^{h, \theta}(m))h - \sum_{n=0}^{N-1} \langle Z_n^{h, \theta}(m), \Delta W_n(m) \rangle$

for $n = 0, \dots, N - 1$ (Should be carried out sequentially) **do**

$Z_{n+1}^{h, \theta}(m) = \phi_n(X_n^{h, \theta}(m) | \theta_n(k))$

$X_{n+1}^{h, \theta}(m) = X_n^{h, \theta}(m) + b(t_n, X_n^{h, \theta}(m), Z_n^{h, \theta}(m))h + \sigma(t_n, X_n^{h, \theta}(m))\Delta W_n(m)$

$Y_{n+1}^{h, \theta}(m) = Y_n^{h, \theta}(m) - f(t_n, X_n^{h, \theta}(m), Z_n^{h, \theta}(m))h + \langle Z_n^{h, \theta}(m), \Delta W_n(m) \rangle$

end

end

$\Theta = \{\theta_0, \theta_1, \dots, \theta_{N-1}\}$ (trainable parameters)

$\mathcal{L}(\Theta) = \frac{1}{M_{\text{batch}}} \left(\sum_{m=1}^{M_{\text{batch}}} Y_0^\theta(m) + \lambda \sum_{m=M_{\text{batch}}+1}^{2M_{\text{batch}}} |g(X_N^{h, \theta}(m)) - Y_N^{h, \theta}(m)|^2 \right)$ (Loss-function)

$\Theta(k+1) \leftarrow \arg \min_{\Theta} \mathcal{L}(\Theta)$ (some optimization algorithm, usually of gradient decent type)

end

Algorithm 1: Pseudo-code of neural network based algorithm

4.1 Notation and spaces

For Euclidean spaces \mathbb{R}^k , $k \geq 1$ we denote by $\|\cdot\|$ the 2-norm without specifying the dimension. Let $\mathcal{S}^2(\mathbb{R}^k)$ and $\mathcal{H}^2(\mathbb{R}^k)$ be the spaces of all progressively measurable stochastic processes $y, z: [0, T] \times \Omega \rightarrow \mathbb{R}^k$ for which

$$\|y\|_{\mathcal{S}^2(\mathbb{R}^k)} = \sup_{t \in [0, T]} \left(\mathbb{E}[\|y_t\|^2] \right)^{\frac{1}{2}} < \infty, \quad \text{and} \quad \|z\|_{\mathcal{H}^2(\mathbb{R}^k)} = \left(\mathbb{E} \left[\int_0^T \|z_t\|^2 dt \right] \right)^{\frac{1}{2}} < \infty,$$

respectively. For a discretization $0 = t_0 < t_1 < \dots < t_N = T$ with $t_{n+1} - t_n = h$ for all n , the space $\mathcal{S}_h(\mathbb{R}^d)$ is the space of all \mathcal{F}^h -adapted, square integrable and discrete stochastic processes $y: \{0, 1, \dots, N\} \times \Omega \rightarrow \mathbb{R}^d$, where $\mathcal{F}_n^h = \sigma(\Delta W_m, m = 0, \dots, n-1)$. For $k_1, k_2, k_3, k_4 \geq 1$, $\ell_1, \ell_2, \ell_3 \geq 0$ and regular $S_i \subseteq \mathbb{R}^{k_i}$, $i = 1, 2, 3, 4$, by $C_b^{\ell_1, \ell_2, \ell_3}(S_1 \times S_2 \times S_3; S_4)$ we denote the space of all functions $\phi: S_1 \times S_2 \times S_3 \rightarrow S_4$, whose derivatives up to orders ℓ_1, ℓ_2, ℓ_3 exist, are continuous and bounded. We equip it with the semi-norms

$$|\phi|_\gamma = \sup_{x \in S_1 \times S_2 \times S_3} \|\partial^\gamma \phi(x)\|, \quad i \in \{1, \dots, \ell\},$$

where $\gamma = \{(i_1, i_2, i_3) : i_j \in \{0, \dots, \ell_j\}, j = 1, 2, 3\}$ are multi-indices and $\partial^\gamma = \partial_1^{i_1} \partial_2^{i_2} \partial_3^{i_3}$ with $\partial_j^{i_j}$ denoting i_j -th derivative in variable j . The set $B(\ell_1, \ell_2, \ell_3)$ denotes all multi-indices of length 3 that have exactly one non-zero index. We only use multi-indices in $B(\ell_1, \ell_2, \ell_3)$ and do therefore not impose restrictions on the cross derivatives, as is otherwise common. For functions with fewer than three variables, we reduce the number of indices accordingly and in the semi-norms we write $|\phi|_{i_1, i_2, i_3} = |\phi|_{(i_1, i_2, i_3)}$. For $\alpha \in (0, 1]$, $k_1, k_2, k_3 \geq 1$, $\ell_1, \ell_2 \geq 0$ and regular $S_i \subseteq \mathbb{R}^{k_i}$, $i = 1, 2, 3$, by $C_{\text{H,b}}^{\alpha, \ell_1, \ell_2}([0, T] \times S_1 \times S_2; S_3)$ we denote the space of all functions $\phi: [0, T] \times S_1 \times S_2 \rightarrow S_3$ that are α -Hölder continuous in time and whose derivatives of order ℓ_1, ℓ_2 exist, are continuous and bounded and satisfy the property

$$\begin{aligned} \|\phi\|_{\alpha, \ell_1, \ell_2} &= \sup_{t \in [0, T]} \|\phi(t, 0, 0)\| + \sum_{\gamma \in B} \sup_{t \in [0, T]} |\phi(t, \cdot, \cdot)|_\gamma \\ &+ \sup_{(x_1, x_2) \in S_1 \times S_2} \sup_{t_1, t_2 \in [0, T], t_1 \neq t_2} \frac{\mathbf{1}_{(0,1]}(\alpha) \|\phi(t_1, x_1, x_2) - \phi(t_2, x_1, x_2)\|}{(1 + \|x_1\| + \|x_2\|) |t_2 - t_1|^\alpha} < \infty. \end{aligned}$$

Again, when there is only one space variable we reduce the number of indices. When there is no risk of confusion we write $|\cdot|_{\alpha, 0, 0}$ to denote the second term defining the $\|\cdot\|_{\alpha, \ell_1, \ell_2}$ -norm, and let $|\cdot|_{0, i, 0}$ and $|\cdot|_{0, 0, i}$ coincide with the semi-norms on $C_b^{\alpha, \ell_1, \ell_2}([0, T] \times S_1 \times S_2; S_3)$ with the same notation. For $\alpha = 0$ we write for convenience $C_{\text{H,b}}^{0, \ell_1, \ell_2}([0, T] \times S_1 \times S_2; S_3) = C_b^{0, \ell_1, \ell_2}([0, T] \times S_1 \times S_2; S_3)$.

For any function or process R defined on $[0, T]$, we denote by \check{R} the discrete time function or process defined by $\check{R}_n = R_{t_n}$, $n = 0, \dots, N$. For any discrete function or process R_h defined on $0, \dots, N$, we write \hat{R}_h for the continuous time function or process defined by the piecewise constant interpolation $\hat{R}_{h,t} = R_{h,n}$ for $t \in [t_n, t_{n+1})$ and $\hat{R}_{h,T} = R_{h,N}$.

4.2 Setting and spaces of Markov maps

Let $(W_t)_{t \in [0, T]}$ be a k -dimensional Brownian motion on a filtered probability space $(\Omega, \mathcal{F}, (\mathcal{F}_t)_{t \in [0, T]}, \mathbb{P})$, and $(\alpha, \beta) \in [0, \frac{1}{2}] \times \{1\}$ or $(\alpha, \beta) = (1, 2)$. The coefficients $b: [0, T] \times \mathbb{R}^d \times U \rightarrow \mathbb{R}^d$, $\sigma: [0, T] \times \mathbb{R}^d \rightarrow \mathbb{R}^{d \times k}$, $f: [0, T] \times \mathbb{R}^d \times U \rightarrow \mathbb{R}$ and $g: \mathbb{R}^d \rightarrow \mathbb{R}$ satisfy $b \in C_{\text{H,b}}^{\alpha, \beta, \beta}([0, T] \times \mathbb{R}^d \times U; \mathbb{R}^d)$, $\sigma \in C_{\text{H,b}}^{\alpha, \beta}([0, T] \times \mathbb{R}^d; \mathbb{R}^{d \times k})$, $f \in C_{\text{H,b}}^{\alpha, \beta, \beta}([0, T] \times \mathbb{R}^d \times U; \mathbb{R})$, $g \in C_{\text{H}}^\alpha(\mathbb{R}^d; \mathbb{R})$. In the case $\alpha = 1$ we assume that $D_x \sigma = 0$.

For the analysis we introduce auxiliary families of stochastic processes. Let $\mathcal{Z} = \mathcal{Z}(b, \sigma, f, g)$ be the collection of all measurable functions $\zeta: [0, T] \times \mathbb{R}^d \rightarrow \mathbb{R}^\ell$ with the property that the stochastic processes $(X^\zeta, Y^\zeta, Z^\zeta)_{\zeta \in \mathcal{Z}} \subset \mathcal{S}^2(\mathbb{R}^d) \times \mathcal{S}^2(\mathbb{R}) \times \mathcal{H}^2(\mathbb{R}^d)$ satisfying for all $t \in [0, T]$, \mathbb{P} -almost surely (8), are well defined. We write $\mathcal{Z}^{\alpha, \beta} = \mathcal{Z} \cap C_{\text{H,b}}^{\alpha, \beta}([0, T] \times \mathbb{R}^d; \mathbb{R}^\ell)$. For the discrete equations, we introduce for every $h \in (0, 1)$ analogously $\mathcal{Z}_h = \mathcal{Z}_h(b, \sigma, f, g)$ to be the collection of all measurable functions $\zeta: \{0, \dots, N_h - 1\} \times \mathbb{R}^d \rightarrow \mathbb{R}^\ell$, with the property that $(X^{h, \zeta}, Y^{h, \zeta}, Z^{h, \zeta})_{\zeta \in \mathcal{Z}_h} \subset \mathcal{S}_h^2(\mathbb{R}^d) \times \mathcal{S}_h^2(\mathbb{R}) \times \mathcal{S}_h^2(\mathbb{R}^d)$ satisfying for all $n \in \{0, \dots, N_h\}$, \mathbb{P} -almost surely (15) are well-defined. We write $\mathcal{Z}_h^\beta = \mathcal{Z}_h \cap (C_b^\beta(\mathbb{R}^d; \mathbb{R}^\ell))^{N+1}$.

4.3 Auxiliary lemmata on strong convergence for SDE

In the proof of convergence of the optimal objectives in Subsection 4.4, we rely on the strong convergence result, stated next. It contains both classical strong convergence of the Euler-Maruyama scheme for Hölder continuous coefficients, including strong order 1 for additive noise, but also a non-standard type of strong convergence result for processes that have drift coefficients that for each step size, agree between the grid points, but whose coefficients do not necessarily converge as the step size tends to zero.

Lemma 4.1. *Suppose the setting of Subsection 4.2 holds. Let $a \in C_{H,b}^{\alpha,\beta}([0, T] \times \mathbb{R}^d; \mathbb{R}^d)$ and $a_h : [0, T] \times \mathbb{R}^d \rightarrow \mathbb{R}$, $h \in (0, 1)$ be a family of functions that are constant on each interval $[t_n, t_{n+1})$, satisfy $a_h([0, T], \cdot) \subset C^\beta(\mathbb{R}^d; \mathbb{R}^d)$ and $\sup_{h \in (0,1)} \|a_h\|_{0,\beta} < \infty$, let $\mathcal{X}, \mathcal{X}^{1,h} \in \mathcal{S}^2(\mathbb{R}^d)$, $h \in (0, 1)$ be the unique solutions to*

$$\begin{aligned} d\mathcal{X}_t &= a(t, \mathcal{X}_t)dt + \sigma(t, \mathcal{X}_t)dW_t, \quad t \in (0, T]; \quad \mathcal{X}_0 = x_0, \\ d\mathcal{X}_t^{1,h} &= a_h(t, \mathcal{X}_t^{1,h})dt + \sigma(t, \mathcal{X}_t^{1,h})dW_t, \quad t \in (0, T]; \quad \mathcal{X}_0^{1,h} = x_0, \quad h \in (0, 1), \end{aligned}$$

and $\mathcal{X}^{2,h}, \mathcal{X}^{3,h} \in \mathcal{S}_h^2(\mathbb{R}^d)$, $h \in (0, 1)$ be the unique solutions to

$$\begin{aligned} \mathcal{X}_{n+1}^{2,h} &= \mathcal{X}_n^{2,h} + a(t_n, \mathcal{X}_n^{2,h})h + \sigma(t_n, \mathcal{X}_n^{2,h})\Delta W_n, \quad n \in \{0, \dots, N-1\}; \quad \mathcal{X}_0^{2,h} = x_0, \quad h \in (0, 1), \\ \mathcal{X}_{n+1}^{3,h} &= \mathcal{X}_n^{3,h} + a_h(t_n, \mathcal{X}_n^{3,h})h + \sigma(t_n, \mathcal{X}_n^{3,h})\Delta W_n, \quad n \in \{0, \dots, N-1\}; \quad \mathcal{X}_0^{3,h} = x_0, \quad h \in (0, 1). \end{aligned}$$

It holds that

$$\sup_{h \in (0,1)} \|\mathcal{X}^{1,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \sup_{h \in (0,1)} \|\hat{\mathcal{X}}^{2,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \sup_{h \in (0,1)} \|\hat{\mathcal{X}}^{3,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} < \infty, \quad (17)$$

and there exists a constant C , such that

$$\lim_{h \rightarrow 0} h^{-\alpha} \left(\|\mathcal{X} - \hat{\mathcal{X}}^{2,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|\mathcal{X}^{1,h} - \hat{\mathcal{X}}^{3,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} \right) = \begin{cases} 0 & \text{if } \alpha = 0, \\ C & \text{otherwise.} \end{cases}$$

Proof. Due to the assumption on a_h there exists a finite constant C such that

$$\|a_h(t, x)\| \leq \sup_{h \in (0,1)} \sup_{t \in [0, T]} (\|a_h(t, 0)\| + |a_h(t, \cdot)|_1) \|x\| \leq C \|x\|.$$

This is enough to show the first assertion, the stability estimate, using a Gronwall argument. For the convergence we rely on [56], which covers both the cases $\alpha \in [0, \frac{1}{2}]$ and $\alpha = 1$. It is based on the fact that bistability and consistency of order α , in the sense of [56], imply convergence of order α . We start with $\mathcal{X}^{1,h} \rightarrow \mathcal{X}^{3,h}$ and the convergence $\mathcal{X}^{2,h} \rightarrow \mathcal{X}$ is immediate afterwards. Since the drift coefficients of $\mathcal{X}^{1,h}$ and $\mathcal{X}^{3,h}$ are both h -dependent, are not assumed to converge, what we want to prove, i.e., $\lim_{h \rightarrow 0} \|\mathcal{X}_t^{1,h} - \hat{\mathcal{X}}_t^{3,h}\|_{\mathcal{S}^2(\mathbb{R}^d)} = 0$ does not say anything about convergence of $\mathcal{X}^{3,h}$ and $\mathcal{X}^{1,h}$. In particular, $\mathcal{X}_t^{1,h_1} - \hat{\mathcal{X}}_t^{3,h_2}$ is in general not small for $h_1 \neq h_2$. Due to this special setting we have to verify that the proofs of [56] are still valid.

We start with proving bistability. First, in [56, Lemma 4.1] it is proven that for small enough h the numerical scheme is bijective. For our proof it is important that the upper bound for this property does not depend on h . From the proof it is clear that this bound depends on the reciprocal of $\sup_{h \in (0,1)} \sup_{t \in [0, T]} |a_h(t, \cdot)|_1$ and is therefore bounded away from zero by assumption. By following the proof of [56, Lemma 4.2] line by line, the bistability constants are bounded by $\sup_{h \in (0,1)} \sup_{t \in [0, T]} |a_h(t, \cdot)|_1$ and its reciprocal when Assumptions (S1) and (S2) in [56] hold. It remains to prove (S1) and (S2) with uniform constants. First, (S1) is trivially satisfied with $L = 0$ for any explicit scheme. By inspection of the proof of [56, Theorem 3.3] we see that, for $\alpha \in [0, \frac{1}{2}]$, corresponding to the stochastic θ -method with $\theta = 0$, (S2) is satisfied for all h with $L = 3T \sup_{h \in (0,1)} \sup_{t \in [0, T]} |a_h(t, \cdot)|_1^2 + 12d|\sigma|_1^2$. For $\alpha = 1$, (S2) holds for the same L as the schemes are the same. This concludes the proof of bistability.

Consistency for $\alpha \in [0, \frac{1}{2}]$ is obtained by observing that the proof in [56], referring for details to [57], only relies on (17) and the $\frac{1}{2}$ -Hölder continuity of a_h between the grid points, and this is clearly satisfied since a_h is constant on $[t_n, t_{n+1})$. For consistency in case $\alpha = 1$, we rely on the proof of consistency for the Itô-Taylor scheme of order one, i.e., the Milstein scheme, coinciding with our scheme under the assumption of additive noise. It suffices to note that the analysis is conducted per interval, and to check that f_α is globally Lipschitz continuous for $\alpha \in \mathcal{B}(\mathcal{A}_1)$, in the notation of [56]. For this to hold it suffices that $\sup_{h \in (0,1)} \sup_{t \in [0, T]} |a_h(t, \cdot)|_2 < \infty$. By assumption this completes the proof for $\mathcal{X}^{1,h}$ and $\mathcal{X}^{3,h}$. For $\mathcal{X}^{2,h}$ and \mathcal{X} the convergence is included in [56] up to the order of consistency, which in our setting is lower when $\alpha \in [0, \frac{1}{2})$. It is straight forward to use α -Hölder continuity for $\alpha \in (0, \frac{1}{2})$, exactly as in the case $\alpha = \frac{1}{2}$, and this way get consistency of order α . For $\alpha = 0$ one uses dominated convergence instead to obtain the convergence without order. This is valid under our assumptions. \square

Our next Lemma is a weak convergence type result. With our assumption of low regularity on the FBSDE coefficients, the weak rate does not exceed the strong rate and therefore the proof relies on the strong convergence results of Lemma 4.1. Obtaining weak convergence order $\alpha \in (\frac{1}{2}, 1)$ for multiplicative noise would otherwise require a Hölder condition on the third derivative of b, σ, f, g and the case $\alpha = 1$ requires four derivatives [58, 59].

Lemma 4.2. *Suppose the setting of Subsection 4.2 holds. For all functions $\zeta \in \mathcal{Z}^{\alpha,\beta}$, collection of functions $\zeta_h \in \mathcal{Z}_h^\beta$, $h \in (0, 1)$, satisfying $\sup_{h \in (0,1)} \|\hat{\zeta}_h\|_{0,\beta} < \infty$, and $\lambda \geq 0$, there exists a constant C , such that*

$$\lim_{h \rightarrow 0} h^{-\alpha} \left(|\Phi_\lambda(\zeta) - \Phi_{\lambda,h}(\check{\zeta})| + |\Phi_\lambda(\hat{\zeta}_h) - \Phi_{\lambda,h}(\zeta_h)| \right) = \begin{cases} 0 & \text{if } \alpha = 0, \\ C & \text{otherwise.} \end{cases}$$

Proof. We start with the first term and observe that

$$|\Phi_\lambda(\zeta) - \Phi_{\lambda,h}(\check{\zeta})| \leq |\mathbb{E}[\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\check{\zeta}}]| + \lambda |\text{Var}(\mathcal{Y}_0^\zeta) - \text{Var}(\mathcal{Y}_0^{h,\check{\zeta}})|. \quad (18)$$

For the proof of both terms of (18), we rely on convergence of $(\mathbb{E}[(\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\check{\zeta}})^2])^{\frac{1}{2}}$, which we next prove, beginning with $\alpha > 0$. For $t \in [t_n, t_{n+1})$, denote $\bar{t} = t_n$. We start by observing that by the definition,

$$\begin{aligned} \mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\check{\zeta}} &= g(X_T^\zeta) - g(X_T^{h,\check{\zeta}}) + \int_0^T (f(t, X_t^\zeta, \zeta(t, X_t^\zeta)) - f(\bar{t}, \hat{X}_t^{h,\check{\zeta}}, \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}}))) dt \\ &\quad + \int_0^T \langle \zeta(t, X_t^\zeta) - \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}}), dW_t \rangle \\ &= g(X_T^\zeta) - g(X_T^{h,\check{\zeta}}) + \int_0^T (f(t, X_t^\zeta, \zeta(t, X_t^\zeta)) - f(t, \hat{X}_t^{h,\check{\zeta}}, \zeta(t, \hat{X}_t^{h,\check{\zeta}}))) dt \\ &\quad + \int_0^T (f(t, \hat{X}_t^{h,\check{\zeta}}, \zeta(t, \hat{X}_t^{h,\check{\zeta}})) - f(\bar{t}, \hat{X}_t^{h,\check{\zeta}}, \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}}))) dt + \int_0^T \langle \zeta(t, X_t^\zeta) - \zeta(t, \hat{X}_t^{h,\check{\zeta}}), dW_t \rangle + \\ &\quad + \int_0^T \langle \zeta(t, X_t^\zeta) - \zeta(t, \hat{X}_t^{h,\check{\zeta}}), dW_t \rangle + \int_0^T \langle \zeta(t, \hat{X}_t^{h,\check{\zeta}}) - \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}}), dW_t \rangle \end{aligned}$$

From the Itô Isometry and the triangle inequality, we have

$$\begin{aligned} (\mathbb{E}[(\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\check{\zeta}})^2])^{\frac{1}{2}} &\leq (\mathbb{E}[(g(X_T^\zeta) - g(X_T^{h,\check{\zeta}}))^2])^{\frac{1}{2}} + \int_0^T (\mathbb{E}[(f(t, X_t^\zeta, \zeta(t, X_t^\zeta)) - f(t, \hat{X}_t^{h,\check{\zeta}}, \zeta(t, \hat{X}_t^{h,\check{\zeta}}))]^2)^{\frac{1}{2}} dt \\ &\quad + \int_0^T \mathbb{E}[(f(t, \hat{X}_t^{h,\check{\zeta}}, \zeta(t, \hat{X}_t^{h,\check{\zeta}})) - f(\bar{t}, \hat{X}_t^{h,\check{\zeta}}, \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}}))]^2)^{\frac{1}{2}} dt \\ &\quad + \left(\int_0^T \mathbb{E}[\|\zeta(t, X_t^\zeta) - \zeta(t, \hat{X}_t^{h,\check{\zeta}})\|^2] dt \right)^{\frac{1}{2}} + \left(\int_0^T \mathbb{E}[\|\zeta(t, \hat{X}_t^{h,\check{\zeta}}) - \zeta(\bar{t}, \hat{X}_t^{h,\check{\zeta}})\|^2] dt \right)^{\frac{1}{2}} \\ &= I_1 + I_2 + I_3 + I_4 + I_5. \end{aligned}$$

For I_1 , we use Lipschitz continuity of g and Cauchy-Schwarz inequality to get

$$I_1 \leq |g|_1 \mathbb{E}[\|X_T^\zeta - X_T^{h,\check{\zeta}}\|] \leq |g|_1 (\mathbb{E}[\|X_T^\zeta - X_T^{h,\check{\zeta}}\|^2])^{\frac{1}{2}} \leq |g|_1 \|X^\zeta - \hat{X}^{h,\check{\zeta}}\|_{\mathcal{S}^2(\mathbb{R}^d)}. \quad (19)$$

The function $\phi(t, x) = f(t, x, \zeta(t, x))$ is uniformly Lipschitz continuous in x with Lipschitz constant $C_\phi = |f|_{0,1,0} + |f|_{0,0,1} |\zeta|_{0,1}$. This implies together with the Cauchy-Schwarz inequality

$$I_2 \leq C_\phi \int_0^T (\mathbb{E}[\|X_t^\zeta - \hat{X}_t^{h,\check{\zeta}}\|^2])^{\frac{1}{2}} dt \leq C_\phi T \|X^\zeta - \hat{X}^{h,\check{\zeta}}\|_{\mathcal{S}^2(\mathbb{R}^d)}. \quad (20)$$

Using the assumptions of b and ζ , it is easily verified that ϕ belongs to $C_{H,b}^{\alpha,\beta}([0, T] \times \mathbb{R}^d; \mathbb{R}^d)$ and therefore, by (19), (20) and Lemma 4.1, we have $I_1 + I_2 \leq Ch^\alpha$. For the term I_3 , we see that

$$\begin{aligned} I_3 &\leq \left(|f|_{\alpha,0,0} + |f|_{0,0,1} |\zeta|_{\alpha,0} \right) \left(1 + \sup_{h \in (0,1)} \|\hat{X}^{h,\check{\zeta}}\|_{\mathcal{S}^2(\mathbb{R}^d)} \right) \sum_{n=0}^{N-1} \int_{t_n}^{t_{n+1}} (t - t_n)^\alpha dt \\ &= \frac{|f|_{\alpha,0,0} + |f|_{0,0,1} |\zeta|_{\alpha,0}}{1 + \alpha} \left(1 + \sup_{h \in (0,1)} \|\hat{X}^{h,\check{\zeta}}\|_{\mathcal{S}^2(\mathbb{R}^d)} \right) N h^{1+\alpha} \leq Ch^\alpha. \end{aligned}$$

Similarly, for I_4 and I_5 we have

$$I_4 \leq |\zeta|_{0,1} \left(\int_0^T \mathbb{E}[\|X_t^\zeta - \hat{X}_t^{h,\check{\zeta}}\|^2] dt \right)^{\frac{1}{2}} \leq |\zeta|_{0,1} T^{\frac{1}{2}} \|X^\zeta - \hat{X}^{h,\check{\zeta}}\|_{\mathcal{S}^2(\mathbb{R}^d)} \leq Ch^\alpha,$$

and

$$\begin{aligned} I_5 &\leq |\zeta|_{\alpha,0} \left(1 + \sup_{h \in (0,1)} \|\hat{X}^{h,\zeta}\|_{\mathcal{S}^2(\mathbb{R}^d)}\right) \left(\sum_{n=0}^{N-1} \int_{t_n}^{t_{n+1}} |t - t_n|^{2\alpha} dt\right)^{\frac{1}{2}} \\ &= \frac{|\zeta|_{\alpha,0}}{1+2\alpha} \left(1 + \sup_{h \in (0,1)} \|\hat{X}^{h,\zeta}\|_{\mathcal{S}^2(\mathbb{R}^d)}\right) (Nh^{1+2\alpha})^{\frac{1}{2}} \leq Ch^\alpha. \end{aligned}$$

For $\alpha = 0$, the terms I_1, I_2, I_4 need no special treatment. For I_3 , we notice that the function ϕ is only continuous in t and convergence without rate holds by the Dominated Convergence Theorem. This is verified by noting that

$$\begin{aligned} &\sup_{t \in [0,T]} \left(\mathbb{E}\left[\left(f(t, \hat{X}_t^{h,\zeta}, \zeta(t, \hat{X}_t^{h,\zeta})) - f(\bar{t}, \hat{X}_t^{h,\zeta}, \zeta(\bar{t}, \hat{X}_t^{h,\zeta}))\right)^2\right]\right)^{\frac{1}{2}} \leq 2 \sup_{t \in [0,T]} \left(\mathbb{E}\left[\left(f(t, \hat{X}_t^{h,\zeta}, \zeta(t, \hat{X}_t^{h,\zeta}))\right)^2\right]\right)^{\frac{1}{2}} \\ &\leq 2 \sup_{t \in [0,T]} \left(\mathbb{E}\left[\left(f(t, \hat{X}_t^{h,\zeta}, \zeta(t, \hat{X}_t^{h,\zeta}) - f(t, 0, 0)\right)^2\right]\right)^{\frac{1}{2}} + 2 \sup_{t \in [0,T]} |f(t, 0, 0)| \\ &\leq 2 \sup_{t \in [0,T]} (|f(t, \cdot, \cdot)|_{1,0} + |f(t, \cdot, \cdot)|_{0,1} (|\zeta(t, \cdot)|_1 + \|\zeta(t, 0)\|)) \sup_{h \in (0,1)} \|\hat{X}^{h,\zeta}\|_{\mathcal{S}^2(\mathbb{R}^d)} + 2 \sup_{t \in [0,T]} |\mathbb{E}[f(t, 0, 0)]|. \end{aligned}$$

Due to the assumptions, the right-hand side is finite. The term I_5 admits a similar treatment and we refrain from giving details. This proves that

$$\lim_{h \rightarrow 0} (\mathbb{E}[(\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\zeta})^2])^{\frac{1}{2}} = \begin{cases} 0 & \text{if } \alpha = 0, \\ C & \text{otherwise.} \end{cases} \quad (21)$$

For the first term in (18), this and the fact that $|\mathbb{E}[\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\zeta}]| \leq (\mathbb{E}[(\mathcal{Y}_0^\zeta - \mathcal{Y}_0^{h,\zeta})^2])^{\frac{1}{2}}$ prove the convergence.

For the second term in (18), we use the conjugate rule, Cauchy-Schwarz' inequality, the triangle inequality, to get

$$\begin{aligned} |\text{Var}(\mathcal{Y}_0^\gamma) - \text{Var}(\mathcal{Y}_0^{h,\tilde{\gamma}})| &= \left| \mathbb{E}\left[|\mathbb{E}[\mathcal{Y}_0^\gamma] - \mathcal{Y}_0^\gamma|^2\right] - \mathbb{E}\left[|\mathbb{E}[\mathcal{Y}_0^{h,\tilde{\gamma}}] - \mathcal{Y}_0^{h,\tilde{\gamma}}|^2\right] \right| \\ &= \left| \mathbb{E}\left[\left(\mathbb{E}[\mathcal{Y}_0^\gamma - \mathcal{Y}_0^{h,\tilde{\gamma}}] + \mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma\right) \left(\mathbb{E}[\mathcal{Y}_0^\gamma + \mathcal{Y}_0^{h,\tilde{\gamma}}] - \mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma\right)\right] \right| \\ &\leq \left(\mathbb{E}\left[\left(\mathbb{E}[\mathcal{Y}_0^\gamma - \mathcal{Y}_0^{h,\tilde{\gamma}}] + \mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma\right)^2\right]\right)^{\frac{1}{2}} \left(\mathbb{E}\left[\left(\mathbb{E}[\mathcal{Y}_0^\gamma + \mathcal{Y}_0^{h,\tilde{\gamma}}] - \mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma\right)^2\right]\right)^{\frac{1}{2}} \\ &\leq \left(|\mathbb{E}[\mathcal{Y}_0^\gamma - \mathcal{Y}_0^{h,\tilde{\gamma}}]| + (\mathbb{E}[(\mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma)^2])^{\frac{1}{2}}\right) \left(|\mathbb{E}[\mathcal{Y}_0^\gamma + \mathcal{Y}_0^{h,\tilde{\gamma}}]| + (\mathbb{E}[(\mathcal{Y}_0^{h,\tilde{\gamma}} + \mathcal{Y}_0^\gamma)^2])^{\frac{1}{2}}\right) \\ &\leq 4 \left((\mathbb{E}[(\mathcal{Y}_0^\zeta)^2])^{\frac{1}{2}} + \sup_{h \in (0,1)} (\mathbb{E}[(\mathcal{Y}_0^{h,\zeta})^2])^{\frac{1}{2}}\right) (\mathbb{E}[(\mathcal{Y}_0^{h,\tilde{\gamma}} - \mathcal{Y}_0^\gamma)^2])^{\frac{1}{2}}. \end{aligned}$$

Together with (21), this completes the proof for the term $|\Phi_\lambda(\zeta) - \Phi_{\lambda,h}(\zeta)|$.

For the second term $|\Phi_\lambda(\hat{\zeta}_h) - \Phi_{\lambda,h}(\zeta_h)|$, we define the functions $a_h: [0, T] \times \mathbb{R}^d \rightarrow \mathbb{R}^d$, $h \in (0, 1)$, by $a_h = \hat{c}_h$, where $c_h: \{0, \dots, N\} \times \mathbb{R}^d \rightarrow \mathbb{R}^d$ are given by $c_{h,n}(x) = b(t_n, x, \zeta_{h,n}(x))$. By the assumptions on b and ζ_h , we have that a_h satisfy the assumption of Lemma 4.1. This implies that $\lim_{h \rightarrow 0} \|X^{\zeta_h} - \hat{X}^{h,\zeta_h}\|_{\mathcal{S}^2(\mathbb{R}^d)} = 0$ and $\|X^{\zeta_h} - \hat{X}^{h,\zeta_h}\|_{\mathcal{S}^2(\mathbb{R}^d)} \leq Ch^\alpha$ for $\alpha > 0$. This fact, together with the same calculations as for I_1, I_2, I_4, I_5 , and noting that the analogous for I_3 is zero, completes the proof. \square

4.4 Time discretization error of the initial and terminal values

This and the next section contain our main results. The results are based on an assumption of regularity of the Markov maps $\zeta^* \in \mathcal{Z}$ and $\zeta_{h,\lambda}^* \in \mathcal{Z}_h$, $h \in (0, 1)$, $\lambda \geq 0$, of the FBSDE and its discretizations, respectively. The regularity has to be verified for specific problems and this, in particular for the discrete problem, is a non-trivial and also not well studied problem, see [63, 64, 65]. For the continuous problem, it breaks down into regularity analysis of the solution to the HJB equation. In this paper, we provide only the abstract error analysis. Our assumption is next stated.

Assumption 4.3. *There exists a unique minimizer $\zeta^* \in \mathcal{Z}$ of $\zeta \mapsto \Phi_0(\zeta)$, it belongs to $\mathcal{Z}^{\alpha,\beta}$ and satisfies $\text{Var}(\mathcal{Y}_0^{\zeta^*}) = 0$. Moreover, for all $\lambda \geq 0$, there exists a collection of minimizers $\zeta_{\lambda,h}^* \in \mathcal{Z}_h$, $h \in (0, 1)$, of $\zeta \mapsto \Phi_{\lambda,h}(\zeta)$ that for each h belongs to \mathcal{Z}_h^β and satisfies $\sup_{h \in (0,1)} \|\hat{\zeta}_{\lambda,h}^*\|_{0,\beta} < \infty$.*

Our first result concerns the convergence of the objective function. The proof relies on a split of the error into two error terms, one containing only ζ^* and one containing only $\zeta_{h,\lambda}^*$. This way we avoid getting an error bound containing the error between the continuous and discrete Markov maps. The result is used throughout our proofs except in Proposition 4.4 where we have the error of the Markov map in the bound.

Theorem 4.1. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold and $\lambda \geq 0$. Then, $|\Phi^* - \Phi_{\lambda,h}^*| \rightarrow 0$ as $h \rightarrow 0$, and if $\alpha > 0$, then there exists a constant C , independent of h , such that*

$$|\Phi^* - \Phi_{\lambda,h}^*| \leq Ch^\alpha.$$

Proof. Because of optimality of $\zeta^* \in \mathcal{Z}$ and since $\hat{\zeta}_h^* \in \mathcal{Z}$, it holds that $\Phi^* \leq \Phi_\lambda(\hat{\zeta}_h^*)$. This implies

$$\Phi^* \leq \Phi_\lambda(\hat{\zeta}_{\lambda,h}^*) = \Phi_{\lambda,h}^* + \Phi_\lambda(\hat{\zeta}_{\lambda,h}^*) - \Phi_{\lambda,h}^* \leq \Phi_{\lambda,h}^* + |\Phi_\lambda(\hat{\zeta}_{\lambda,h}^*) - \Phi_{\lambda,h}^*|.$$

Similarly, from the optimality of $\check{\zeta}_{\lambda,h}^* \in \mathcal{Z}_h$ and since $\check{\zeta}^* \in \mathcal{Z}_h$, it holds $\Phi_{\lambda,h}^* \leq \Phi_{\lambda,h}(\check{\zeta}^*)$. We have

$$\Phi_{\lambda,h}^* \leq \Phi_{\lambda,h}(\check{\zeta}^*) = \Phi^* + \Phi_{\lambda,h}(\check{\zeta}^*) - \Phi^* \leq \Phi^* + |\Phi_{\lambda,h}(\check{\zeta}^*) - \Phi^*|.$$

The two inequalities equivalently read $\Phi^* - \Phi_{\lambda,h}^* \leq |\Phi(\hat{\zeta}_{\lambda,h}^*) - \Phi_{\lambda,h}^*|$ and $\Phi_{\lambda,h}^* - \Phi^* \leq |\Phi_{\lambda,h}(\check{\zeta}^*) - \Phi^*|$, and thus

$$|\Phi^* - \Phi_{\lambda,h}^*| \leq \max(|\Phi(\hat{\zeta}_{\lambda,h}^*) - \Phi_{\lambda,h}^*|, |\Phi_{\lambda,h}(\check{\zeta}^*) - \Phi^*|) \leq |\Phi(\hat{\zeta}_{\lambda,h}^*) - \Phi_{\lambda,h}^*| + |\Phi_{\lambda,h}(\check{\zeta}^*) - \Phi^*|.$$

The convergence is given by our assumption and Lemma 4.2. This completes the proof. \square

A consequence of the convergence of the objective function, is the convergence of the two components of the objective. This is stated in our next theorem.

Theorem 4.2. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold, $\lambda > 0$, $\mathcal{Y}_0^{h,\lambda} := \mathcal{Y}_0^{h,\zeta_{\lambda,h}^*}$ and $Y_0^{h,\lambda} := \mathbb{E}[\mathcal{Y}_0^{h,\lambda}]$. Then, $|Y_0 - Y_0^{h,\lambda}| + \text{Var}(\mathcal{Y}_0^{h,\lambda}) \rightarrow 0$ as $h \rightarrow 0$, and if $\alpha > 0$, then there exists a constant C , independent of h , such that*

$$|Y_0 - Y_0^{h,\lambda}| + \text{Var}(\mathcal{Y}_0^{h,\lambda}) \leq Ch^\alpha.$$

Proof. We start with the proof for the variance and use both the sequences $(\zeta_{0,h}^*)_{h \in (0,1)}$ and $(\zeta_{\lambda,h})_{h \in (0,1)}$. The proof relies on a squeezing argument. Adding and subtracting terms and using the triangle inequality, yields

$$\lambda \text{Var}(\mathcal{Y}_0^{h,\lambda}) \leq |Y_0 - Y_0^{h,\lambda} - \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda})| + |Y_0 - Y_0^{h,0}| + |Y_0^{h,0} - Y_0^{h,\lambda}|. \quad (22)$$

From the assumption $\text{Var}(\mathcal{Y}_0) = 0$, it holds that $\Phi^* = Y_0$ and Theorem 4.1 gives

$$|Y_0 - Y_0^{h,\lambda} - \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda})| + |Y_0 - Y_0^{h,0}| = |\Phi^* - \Phi_{h,\lambda}^*| + |\Phi^* - \Phi_{0,h}^*| \leq Ch^\alpha. \quad (23)$$

For the third term on the right-hand side of (22), we first notice that, since $\zeta_{0,h}$ is a minimizer of $\zeta \mapsto Y_0^{h,0}$, it holds that $Y_0^{h,\lambda} - Y_0^{h,0} \geq 0$. This fact, adding $\lambda \text{Var}(\mathcal{Y}_0^{h,\lambda})$, adding and subtracting Y_0 , using the triangle inequality and using (23), gives us

$$\begin{aligned} |Y_0^{h,0} - Y_0^{h,\lambda}| &= Y_0^{h,\lambda} - Y_0^{h,0} \leq Y_0^{h,\lambda} + \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda}) - Y_0 - Y_0^{h,0} + Y_0 \\ &\leq |Y_0 - Y_0^{h,\lambda} - \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda})| + |Y_0 - Y_0^{h,\lambda}| \leq Ch^\alpha. \end{aligned} \quad (24)$$

Now, (22)–(24) together complete the proof for the variance. For the convergence of $Y_0^{h,\lambda}$, we simply conclude

$$|Y_0 - Y_0^{h,\lambda}| \leq |Y_0 - Y_0^{h,\lambda} - \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda})| + \lambda \text{Var}(\mathcal{Y}_0^{h,\lambda}) \leq Ch^\alpha. \quad \square$$

From (9) and Theorem 4.2, we directly get convergence in the terminal value and we can also conclude strong convergence of $y_0^{h,\lambda}$. This is stated in the following two corollaries.

Corollary 4.1. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold and $\lambda > 0$. Then, $\mathbb{E}[(g(X_N^{h,\lambda}) - Y_N^{h,\lambda})^2] \rightarrow 0$ as $h \rightarrow 0$, and if $\alpha > 0$, then there exists a constant C , independent of h , such that*

$$\left(\mathbb{E} \left[(g(X_N^{h,\lambda}) - Y_N^{h,\lambda})^2 \right] \right)^{\frac{1}{2}} \leq Ch^{\frac{\alpha}{2}}.$$

Corollary 4.2. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold and $\lambda > 0$. Then, $\mathbb{E}[(\mathcal{Y}_0 - \mathcal{Y}_0^{h,\lambda})^2]^{\frac{1}{2}} \rightarrow 0$ as $h \rightarrow 0$, and if $\alpha > 0$, then there exists a constant C , independent of h , such that*

$$\left(\mathbb{E} \left[(\mathcal{Y}_0 - \mathcal{Y}_0^{h,\lambda})^2 \right] \right)^{\frac{1}{2}} \leq Ch^{\frac{\alpha}{2}}.$$

Proof. From Theorem 4.2 and the triangle inequality, it holds

$$\left(\mathbb{E} \left[(\mathcal{Y}_0 - \mathcal{Y}_0^{h,\lambda})^2 \right] \right)^{\frac{1}{2}} \leq \left(\mathbb{E} \left[(Y_0 - Y_0^{h,\lambda} + \mathcal{Y}_0 - \mathcal{Y}_0^{h,\lambda})^2 \right] \right)^{\frac{1}{2}} + |Y_0 - Y_0^{h,\lambda}| = \left(\text{Var}(\mathcal{Y}_0^{h,\lambda}) \right)^{\frac{1}{2}} + |Y_0 - Y_0^{h,\lambda}| \leq Ch^{\frac{\alpha}{2}}.$$

This proves the corollary. \square

4.5 Time discretization error of the FBSDE

While the error analysis for the initial and terminal values in the previous subsection required only Assumption 4.3, the strong error analysis of (X, Y, Z) requires more. In Theorem 4.3, we prove strong convergence for small horizon T . This should be compared with the convergence result in [25], that also has a very restrictive assumption on T . Compared to [25], whose bound contains the error in the terminal value, we have no such term. In Proposition 4.4, we prove the strong convergence without a restriction on T with the cost of having a bound containing the error between the Markov maps ζ^* and $\zeta_{h,\lambda}^*$.

Theorem 4.3. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold, $\alpha, \lambda > 0$, and*

$$\max \left(T^{\frac{1}{2}} |f|_{0,0,1}, \frac{6T(T|f|_{0,1,0} + |g|_1) |b|_{0,0,1}^2 \exp(6T(|b|_{0,1,0}T + |\sigma|_{0,1}))}{1 - T^{\frac{1}{2}} |f|_{0,0,1}} \right) < 1.$$

Then, there exists a constant C , independent of h , such that

$$\|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|Y - \hat{Y}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)} \leq Ch^{\frac{\alpha}{2}}.$$

Proof. We start by noting that for $t \in [0, T]$, it holds

$$Y_t - Y_t^{h,\lambda} = Y_0 - Y_0^{h,\lambda} - \int_0^t (f(s, X_s, Z_s) - f(\bar{s}, \hat{X}_s^{h,\lambda}, \hat{Z}_s^{h,\lambda})) ds + \int_0^t (Z_s - \hat{Z}_s^{h,\lambda}) dW_s. \quad (25)$$

By the Itô Isometry, substitution of (25) with $t = T$, and the triangle inequalities, we have

$$\begin{aligned} \|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)} &= \left(\mathbb{E} \left[\int_0^T \|Z_t - \hat{Z}_t^{h,\lambda}\|^2 dt \right] \right)^{\frac{1}{2}} = \left(\mathbb{E} \left[\left(\int_0^T (Z_t - \hat{Z}_t^{h,\lambda}) dW_t \right)^2 \right] \right)^{\frac{1}{2}} \\ &= \left(\mathbb{E} \left[\left(Y_0 - Y_0^{h,\lambda} + g(X_T) - Y_N^{h,\lambda} - \int_0^T (f(t, X_t, Z_t) - f(\bar{t}, \hat{X}_t^{h,\lambda}, \hat{Z}_t^{h,\lambda})) dt \right)^2 \right] \right)^{\frac{1}{2}} \\ &\leq |Y_0 - Y_0^{h,\lambda}| + \left(\mathbb{E} [(g(X_T) - g(X_N^{h,\lambda}))^2] \right)^{\frac{1}{2}} + \left(\mathbb{E} [(g(X_N^{h,\lambda}) - Y_N^{h,\lambda})^2] \right)^{\frac{1}{2}} \\ &\quad + \left(\mathbb{E} \left[\left(\int_0^T (f(t, X_t, Z_t) - f(\bar{t}, \hat{X}_t^{h,\lambda}, \hat{Z}_t^{h,\lambda})) dt \right)^2 \right] \right)^{\frac{1}{2}}. \end{aligned}$$

The first three terms are by Theorem 4.2 and Corollary 4.1, bounded from below by $Ch^{\frac{\alpha}{2}} + |g|_1 \|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}$. By similar arguments as those for I_2, I_3 in the proof of Lemma 4.2, it holds

$$\begin{aligned} &\left(\mathbb{E} \left[\left(\int_0^T (f(t, X_t, Z_t) - f(\bar{t}, \hat{X}_t^{h,\lambda}, \hat{Z}_t^{h,\lambda})) dt \right)^2 \right] \right)^{\frac{1}{2}} \\ &\leq T |f|_{\alpha,0,0} (1 + \alpha)^{-1} h^\alpha + T |f|_{0,1,0} \|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + T^{\frac{1}{2}} |f|_{0,0,1} \|\hat{Z}^{h,\lambda} - Z\|_{\mathcal{H}^2(\mathbb{R}^\ell)}. \end{aligned} \quad (26)$$

By a kickback argument and by assumption, it holds

$$\|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)} \leq Ch^\alpha + \frac{T |f|_{0,1,0} + |g|_1}{1 - T^{\frac{1}{2}} |f|_{0,0,1}} \|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}. \quad (27)$$

We next approach the error $\|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}$. Let $\Xi^{h,\lambda} \in \mathcal{S}^2(\mathbb{R}^d)$, $h \in (0, 1)$ be the family of stochastic processes that for all $t \in [0, T]$, \mathbb{P} -a.s. satisfy

$$\Xi_t^{h,\lambda} = x_0 + \int_0^t b(\bar{s}, \Xi_s^{h,\lambda}, Z_s^{h,\lambda}) ds + \int_0^t \sigma(\bar{s}, \Xi_s^{h,\lambda}) dW_s.$$

Using the triangle inequality, we get

$$\|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} \leq \|X - \Xi^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|\Xi^{h,\lambda} - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}.$$

By the arguments used repeatedly in the proof of Lemma 4.1 and by assumptions, it holds

$$\mathbb{E} [\|X_t - \Xi_t^{h,\lambda}\|^2] \leq Ch^\alpha + 6|b|_{0,0,1}^2 T \|Z - Z^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)}^2 + 6(|b|_{0,1,0}T + |\sigma|_{0,1}) \int_0^t \mathbb{E} [\|X_s - \Xi_s^{h,\lambda}\|^2] ds.$$

From this, it follows by the Gronwall lemma that

$$\mathbb{E} [\|X_t - \Xi_t^{h,\lambda}\|^2] \leq \exp \left(6T(|b|_{0,1,0}T + |\sigma|_{0,1}) \right) \left(Ch^\alpha + 6|b|_{0,0,1}^2 T \|Z - Z^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)}^2 \right)$$

A use of Lemma 4.1 yields $\|\Xi^{h,\lambda} - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} \leq Ch^\alpha$. We conclude that

$$\|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} \leq Ch^\alpha + 6T|b|_{0,0,1}^2 \exp(6T(|b|_{0,1,0}T + |\sigma|_{0,1})) \|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)}. \quad (28)$$

Using (28) in (27) gives, after a kickback argument, the desired bound $\|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)} \leq Ch^\alpha$.

For the $\|Y - \hat{Y}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}$, we use (25) and the standard arguments to get

$$\left(\mathbb{E}[\|Y_t - Y_t^{h,\lambda}\|^2]\right)^{\frac{1}{2}} \leq |Y_0 - Y_0^{h,\lambda}| + \left(\int_0^T \mathbb{E}\left[\|f(s, X_s, Z_s) - f(\bar{s}, \hat{X}_s^{h,\lambda}, \hat{Z}_s^{h,\lambda})\|^2\right] ds\right)^{\frac{1}{2}} + \|Z_s - \hat{Z}_s^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)}.$$

Applying Theorem 4.1, (26) and the obtained results for $\|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)}$ and $\|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)}$ complete the proof. \square

Proposition 4.4. *Suppose the setting of Subsection 4.2, let Assumption 4.3 hold, $\alpha, \lambda > 0$. Then, there exists a constant C , independent of h , such that*

$$\begin{aligned} & \|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|Y - \hat{Y}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \|Z - \hat{Z}^{h,\lambda}\|_{\mathcal{H}^2(\mathbb{R}^\ell)} \\ & \leq C \left(h^\alpha + \max_{0, \dots, N_h} \left(\mathbb{E} \left[\|\zeta^*(t_n, X_n^{\lambda, h}) - \hat{\zeta}_{h,\lambda}^*(t_n, X_n^{\lambda, h})\|^2 \right] \right)^{\frac{1}{2}} \right). \end{aligned}$$

Proof. This is proved similarly to Theorem 4.3 without the kick-back argument and instead of (26), using

$$\begin{aligned} & \left(\mathbb{E} \left[\left(\int_0^T (f(t, X_t, Z_t) - f(\bar{t}, \hat{X}_t^h, \hat{Z}_t^h)) dt \right)^2 \right] \right)^{\frac{1}{2}} \\ & \leq C \left(h^\alpha + \|X - \hat{X}^{h,\lambda}\|_{\mathcal{S}^2(\mathbb{R}^d)} + \max_{0, \dots, N_h} \left(\mathbb{E} \left[\|\zeta^*(t_n, X_n^{\lambda, h}) - \hat{\zeta}_{h,\lambda}^*(t_n, X_n^{\lambda, h})\|^2 \right] \right)^{\frac{1}{2}} \right). \quad \square \end{aligned}$$

4.6 A discussion on the full error analysis of the robust deep FBSDE method

In Subsections 4.4 and 4.5, only the time discretization error is considered, i.e., the error between (8) and (15). For a full error analysis, the error between the fully implementable scheme (15) and (8) must be considered. Besides the time discretization error, there are three other sources of errors: The first is the error induced by optimizing over the parameters of a neural network, instead of over the vast set \mathcal{Z}_h . By the Universal Approximation Theorem [61] this error can be made arbitrarily small, but this theorem gives no help with suggesting the network architecture that can guarantee a maximal error of desired size. Therefore, a careful error analysis for this error might fail to have a meaning. The second error is the Monte-Carlo error induced from approximating the expectation in Y_0 by a sample mean. This error allows for a simple error analysis and the Monte Carlo error is of the order $\mathcal{O}(M_{\text{batch}}^{-1/2})$. The final error is the error induced from the inexact optimization procedure of (16).

5 Numerical experiments

In this section, we evaluate our algorithm on three different problems. The first two are of LQ type, for which we have access to a semi-analytic solution for comparison. The third example uses nonlinear terms both in the drift and diffusion coefficients in the forward equation, and we no longer have access to a reference solution. In the first example, there is a one-to-one map between the feedback control and the Z -process, and we can set $\lambda = 0$ in the loss function. In the second and third examples, this is not the case, and $\lambda > 0$ is necessary for uniqueness of the minimizer to our discrete problem, and in turn convergence to the continuous FBSDE.

In the experimental convergence studies, we approximate $\|\cdot\|_{\mathcal{S}(\mathbb{R}^q)}$ and $\|\cdot\|_{\mathcal{H}(\mathbb{R}^q)}$ with

$$\|A\|_{\mathcal{S}_{h,M}^2(\mathbb{R}^q)} = \max_{n \in \{0,1,\dots,N\}} \left(\frac{1}{M} \sum_{m=1}^M \|A_n(m)\|^2 \right)^{\frac{1}{2}}, \quad \|A\|_{\mathcal{H}_{h,M}^2(\mathbb{R}^q)} = \frac{1}{N} \sum_{N=0}^{N-1} \left(\frac{1}{M} \sum_{m=1}^M \|A_n(m)\|^2 \right)^{\frac{1}{2}}.$$

Here, $A(m) = \{A_1(m), A_2(m), \dots, A_N(m)\}$, $m = 1, 2, \dots, M$, are *i.i.d.* realizations of some adapted stochastic processes A on the grid. The norm $\|\cdot\|_{L^2(\Omega; \mathbb{R}^q)}$ is approximated with a sample mean denoted $\|\cdot\|_{L_{h,M}^2(\mathbb{R}^q)}$. For the convergence study, the Experimental Order of Convergence (EOC) is used. It is defined as

$$\text{EOC}(h_i) = \frac{\log(\text{error}(h_{i+1})) - \log(\text{error}(h_i))}{\log(h_{i+1}) - \log(h_i)}.$$

In all examples, we use the neural network structure in Section 3.2. We use $M_{\text{train}} = 2^{20}$ training data points and batch size $M_{\text{batch}} = 2^9$ with $K_{\text{epoch}} = 15$ epochs. This gives $K_{\text{batch}} = 2^{10} = 1024$ updates per epoch. For the optimization, the Adam optimizer [66] is used with learning rate 0.1 for the first three epochs, which, after that, is multiplied by a factor of $e^{-0.5}$ for each new epoch. For our use, it was important to choose M_{train} large since in our empirical convergence results we want to isolate the time discretization error. In practice, the method generates acceptable solutions with significantly smaller M_{train} .

5.1 Linear quadratic control problems

Among all stochastic control problems, the LQ-problem is most studied and the problem with the most structure, see *e.g.*, [60]. For our purposes, it has a closed-form analytic solution with which we can compare our numerical approximations.

Let $x_0 \in \mathbb{R}^d$, $A, \sigma, \in \mathbb{R}^{d \times d}$, $R_x, G \in \mathbb{S}_+^d$, $R_u \in \mathbb{S}_+^\ell$ and $B \in \mathbb{R}^{d \times \ell}$ be of full rank and $C \in \mathbb{R}^d$. The state equation and cost functional of a linear-quadratic-Gaussian control problem are given by

$$\begin{cases} X_t = x_0 + \int_0^t (A(C - X_s) + Bu_s) ds + \int_0^t \sigma dW_s, \\ J^u(t, x) = \mathbb{E}^{t,x} \left[\int_t^T (\langle R_x X_s, X_s \rangle + \langle R_u u_s, u_s \rangle) ds + \langle GX_T, X_T \rangle \right]. \end{cases}$$

With the minimizer v^* of the corresponding Hamiltonian, $\inf_{u \in U} \{ \langle D_x V, Bu \rangle + \langle R_u u, u \rangle \}$, we have the optimal feedback control

$$u_t^* = -\frac{1}{2} R_u^{-1} B^T D_x V(t, X_t). \quad (29)$$

Here, we recall that V is the solution to the associated HJB-equation. Its solution is given by

$$V(t, x) = x^T P(t)x + x^T Q(t) + R(t),$$

where (P, Q, R) solves the system of ordinary differential equations,

$$\begin{cases} \dot{P}(t) - AP(t)P(t)A^T - P(t)BR_u^{-1}B^T P(t) + R_x^T R_x = \mathbf{0}_{d \times d}, \\ \dot{Q}(t) + 2P(t)AC - A^T Q(t) - P(t)BR_u^{-1}B^T Q(t) = \mathbf{0}_d, \\ \dot{R}(t) + 2\text{Tr}\{\sigma\sigma^T P(t)\} + Q(t)^T AC - \frac{1}{4}Q(t)^T BR_u^{-1}B^T Q(t) = 0, \\ P(T) = G; \quad Q(T) = \mathbf{0}_d; \quad R(T) = 0. \end{cases}$$

The first equation is a matrix Riccati equation, and we refer to the whole system, slightly inaccurately, as the Riccati equation. The gradient of V satisfies $D_x V(t, x) = 2P(t)x + Q(t)$. The related FBSDE reads:

$$\begin{cases} X_t = x_0 + \int_0^t [A(C - X_s) - \frac{1}{2}BR_u^{-1}(B^T Z_s + Q(t))] ds + \int_0^t \sigma dW_s, \\ Y_t = \langle GX_T, X_T \rangle - \int_t^T (\langle R_x X_s, X_s \rangle - \frac{1}{4}\langle R_u^{-1}B^T Z_s, B^T Z_s \rangle) ds + \int_t^T \langle Z_s, \sigma dW_s \rangle. \end{cases} \quad (30)$$

The solution to (30) is then given by

$$Y_t = X_t^T P(t)X_t + X_t^T Q(t) + R(t); \quad Z_t = 2P(t)X_t + Q(t). \quad (31)$$

The Riccati equation has an analytic solution in closed form only in one dimension. As benchmark solution in our experiments we use the Euler approximation of the Riccati equation with 80×2^8 time steps and with 160 time steps for for X . The processes (Y, Z) are approximated by (31).

5.1.1 Example with state and control of the same dimension

Our first example concerns a two-dimensional LQ-problem with two-dimensional control. The matrices for the forward equation are given by

$$A = \begin{pmatrix} 1 & 0 \\ 0 & 2 \end{pmatrix}, \quad B = \begin{pmatrix} 1 & 0.5 \\ -0.5 & 1 \end{pmatrix}, \quad C = \begin{pmatrix} 0.1 \\ 0.2 \end{pmatrix}, \quad \sigma = \begin{pmatrix} 0.05 & 0.25 \\ 0.05 & 0.25 \end{pmatrix}, \quad x_0 = \begin{pmatrix} 0.1 \\ 0.1 \end{pmatrix}, \quad T = 0.5,$$

and the penalty matrices for the control problem by

$$R_x = \begin{pmatrix} 100 & 0 \\ 0 & 1 \end{pmatrix}, \quad R_u = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}, \quad G = \begin{pmatrix} 1 & 0 \\ 0 & 100 \end{pmatrix}.$$

	$\ X - X^h\ _{\mathcal{S}_h^2(\mathbb{R}^6)}$		$\ Y - Y^h\ _{\mathcal{S}_h(\mathbb{R})^2}$		$\ Z - Z^h\ _{\mathcal{H}_h^2(\mathbb{R}^6)}$		$\ Y_N^h - g(X_N^h)\ _{L^2(\Omega)}$		$ Y_0 - Y_0^h $		Y_0^h
N	Error	EOC	Error	EOC	Error	EOC	Error	EOC	Error	EOC	Value
5	8.23e-2	0.81	1.22	1.02	3.71e-1	0.79	9.91e-1	0.97	7.10e-1	1.12	1.32
10	4.68e-2	0.89	6.02e-1	0.97	2.15e-1	0.69	5.07e-1	0.92	3.26e-1	1.15	0.938
20	2.53e-2	1.02	3.07e-1	0.87	1.33e-1	0.70	2.69e-1	0.81	1.47e-1	1.07	0.759
40	1.24e-2	1.22	1.68e-1	0.73	8.22e-2	0.91	1.53e-1	0.69	7.01e-2	1.01	0.682
80	5.31e-3		1.01e-1		4.35e-2		9.49e-3		3.47e-2		0.647

Table 1: Errors and experimental order of convergence for LQ-problem with $d = 6$ and $\ell = 2$ with analytic initial value $Y_0 = 0.6122$.

In Figure 3, the approximation of (X, Y, Z) is compared to the analytic solution in mean, an empirical credibility interval (again, defined as the area between the 5:th and 95:th percentiles at each time point) as well as for a single path. We see that the largest error comes from the approximation of Y . The reason for this is the error accumulation stemming from our time-discretization. Thus, it is not due to the neural network approximation. This can be verified by using the baseline for Z , from the Riccati equation, and use an Euler-Maruyama scheme to generate the same error. This suggests that a more suitable choice of numerical schemes for Y should be used.

In Table 1 we see the convergence rates from the experiment. The regime of the LQ-problem, with, e.g., quadratic dependence in f does not satisfy the assumptions made in Section 4 and a direct comparison cannot be made. Still, we see, for instance, that Y_0^h converges empirically with order 1 while the error in the terminal condition approaches the order $\frac{1}{2}$. The factor two in the comparison between these error is consistent with Theorem 4.2 and Corollary 4.1.




Figure 3: Average of solutions and a single solution path compared to their analytic counterparts for the LQ control problem from Section 5.1.1. The shaded areas represent empirical credibility intervals, defined as the areas between the 5:th and the 95:th percentiles at each time point.

	$\ X - X^h\ _{\mathcal{S}_h^2(\mathbb{R}^6)}$	$\ Y - Y^h\ _{\mathcal{S}_h^2(\mathbb{R})}$	$\ Z - Z^h\ _{\mathcal{H}_h^2(\mathbb{R}^6)}$	$\ Y_N^h - g(X_N^h)\ _{L^2(\Omega)}$	$ Y_0 - Y_0^h $	Y_0^h					
5	7.25e-2	1.23	5.65e-1	0.90	1.20	0.90	4.43e-1	0.80	3.51e-1	1.10	1.80
10	3.10e-2	1.10	3.02e-1	0.76	7.41e-1	0.49	2.54e-1	0.69	1.63e-1	0.94	1.55
20	1.45e-2	0.87	1.79e-1	0.63	5.26e-1	0.28	1.57e-1	0.60	8.51e-2	0.82	1.55
40	7.96e-3	0.35	1.15e-1	0.53	4.34e-1	0.18	1.04e-1	0.54	4.81e-2	0.69	1.51
80	6.24e-3		7.96e-2		3.84e-1		7.15e-2		3.00e-2		1.49

Table 2: Errors and experimental order of convergence for LQ-problem with $d = 6$ and $\ell = 2$ with analytic initial value $Y_0 = 1.4599$

5.1.2 Example with control in lower dimensions than the state

Our second example concerns a six-dimensional problem with a two-dimensional control. The matrices used for the state equation are

$$A = \text{diag}([1, 2, 3, 1, 2, 3]), \quad B = \begin{pmatrix} 1 & -1 \\ 1 & 1 \\ 0.5 & 1 \\ 1 & -1 \\ 0 & -1 \\ 0 & 1 \end{pmatrix}, \quad C = \text{diag}([-0.2, -0.1, 0, 0, 0.1, 0.2]),$$

$$\sigma = \text{diag}([0.05, 0.25, 0.05, 0.25, 0.05, 0.25]), \quad x_0 = (0.1, 0.1, 0.1, 0.1, 0.1, 0.1)^\top, \quad T = 0.5.$$

The penalty matrices of the control problem are given by

$$R_x = \text{diag}([25, 1, 25, 1, 25, 1]), \quad R_u = \text{diag}([1, 1]), \quad G = \text{diag}([1, 25, 1, 25, 1, 25]).$$

Before we discuss our results, recall that the optimal feedback control at time t is given by $u_t^* = -\frac{1}{2}R_u^{-1}B^T Z_t$. Since u_t^* takes on values in \mathbb{R}^ℓ and $R_u^{-1}B^T$ is of rank $\ell < d$ at most, we can conclude that there exists infinitely many processes ζ_t such that $u_t^* = -\frac{1}{2}R_u^{-1}B^T \zeta_t$. To obtain uniqueness of the control component, we set $\lambda = 1 > 0$.

In Figure 4, the approximations are compared with semi-analytic solutions in empirical mean, credibility interval and for a representative path realization of X, Y and Z . Visually, the approximations capture (X, Y, Z) well. The convergence is shown in Table 2. The experimental orders decrease below the orders in Table 1 of the previous example. To investigate whether this is the true convergence order, or if other errors are dominating for small time steps, we have done some manual hyper parameter optimization with different training data and batch sizes, learning rates and neural network architectures, without being able to improve the rates.

5.2 Non-linear control problems

Here, we consider a non-linear control problem with interesting dynamics. It has unstable equilibrium points at the even integers and stable equilibrium points at the odd integers. The problem has been chosen to mimic the unstable problems that are commonly considered in control, such as with inverted pendulums.

Let $x_0 \in \mathbb{R}^d$, $A, \Sigma \in \mathbb{R}^{d \times d}$, $R_x, G \in \mathbb{S}_+^d$, $R_u \in \mathbb{S}_+^\ell$ and $B \in \mathbb{R}^{d \times \ell}$ be of full rank and $C \in \mathbb{R}^d$. The state equation and cost functional of a linear-quadratic-Gaussian control problem are given by

$$\begin{cases} X_t = x_0 + \int_0^t (A \sin(\pi C X_s) + B u_s) ds + \int_0^t \Sigma(1_d + X_s X_s^\top) dW_s, \\ J^u(t, x) = \mathbb{E}^{t, x} \left[\int_t^T (\langle R_x X_s, X_s \rangle + \langle R_u u_s, u_s \rangle) ds + \langle G X_T, X_T \rangle \right]. \end{cases} \quad (32)$$

Due to the linear dependence of the control and the quadratic cost functional, the optimal feedback control is again given by

$$u_t^* = -\frac{1}{2}R_u^{-1}B^T D_x V(t, X_t). \quad (33)$$

Similar to above, V is the solution to the associated HJB-equation. Again, by setting $Y_t = V(t, X_t)$ and $Z_t = D_x V(t, X_t)$, we obtain the FBSDE

$$\begin{cases} X_t = x_0 + \int_0^t [A \sin(\pi C X_s) - \frac{1}{2}B R_u^{-1} R_u^{-1} B^\top Z_s] ds + \int_0^t \Sigma(1_d + X_s X_s^\top) dW_s, \\ Y_t = g(X_T) - \int_t^T (\langle R_x X_s, X_s \rangle - \frac{1}{4} \langle R_u^{-1} B^\top Z_s, B^\top Z_s \rangle) ds + \int_0^t Z_s^\top \Sigma(1_d + X_s X_s^\top) dW_s. \end{cases} \quad (34)$$




Figure 4: Average of solutions and a single solution path compared to their analytic counterparts for the LQ control problem from Section 5.1.2. The shaded area represents an empirical credibility interval for Y , defined as the area between the 5:th and the 95:th percentiles at each time point. We do not include credibility intervals for X and Z in this figure to facilitate visualization. For X and Z , we see one realization of each of the six components.

N	$\ Y_N^h - g(X_N^h)\ _{L^2(\Omega)}$		$ Y_0 - Y_0^h $		Y_0^h
	Error	EOC	Error	EOC	Value
5	2.697e-2	0.59	4.04e-2	0.99	0.2297
10	1.790e-2	0.53	2.26e-2	0.87	0.2241
20	1.240e-2	0.50	1.40e-2	0.99	0.2219
40	8.763e-3	0.48	9.24e-3	1.12	0.2207
80	6.281e-3		3.99e-3		0.2200

Table 3: Errors and experimental order of convergence for the nonlinear control problem in Section 5.2. A reference solution of $Y_0 = 0.2194$ is computed on fine grid.

Particularly, we consider a three-dimensional problem with control in two dimensions, *i.e.*, $d = 3$ and $\ell = 2$ and use the following matrices for the state

$$A = \text{diag}([1, 1, 1]), \quad B = \begin{pmatrix} 1 & 0 \\ 0 & 1 \\ 1 & 1 \end{pmatrix}, \quad C = \text{diag}([1, 1, 1]),$$

$$\Sigma = \text{diag}([0.1, 0.1, 0.1]), \quad x_0 = (0.1, 0.1, 0.1)^\top, \quad T = 0.25.$$

For the cost functional we have the matrices

$$R_x = \text{diag}([5, 1, 1]), \quad R_u = \text{diag}([1, 1]), \quad G = \text{diag}([1, 5, 1]).$$

Table 5.2 shows the experimental order of convergence of the terminal condition and the initial value of the BSDE. The factor two between them is again consistent with Theorem 4.2 and Corollary 4.1 even though the problem does not fall under the assumptions of these results.

Acknowledgments

We very much thank Boualem Djehiche for his kindness in bringing some very useful references to our knowledge. K.A. and C.W.O. acknowledge the funding of their research by the European Union, under the H2020-EU.1.3.1. MSCA-ITN-2018 scheme, Grant 813261.

References

- [1] W. H. Fleming, and H. M. Soner (2006). *Controlled Markov processes and viscosity solutions* (Vol. 25). Springer Science & Business Media.
- [2] L. Teng. *A review of tree-based approaches to solve forward-backward stochastic differential equations*. The Journal of Computational Finance, 2021.
- [3] J. Ma, P. Protter, J. Martín, and S. Torres. *Numerical method for backward stochastic differential equations*. The Annals of Applied Probability, 12(1):302–316, 2002.
- [4] M. J. Ruijter, and C. W. Oosterlee A Fourier cosine method for an efficient computation of solutions to BSDEs. SIAM Journal on Scientific Computing, 37(2), A859-A889, 2015.
- [5] T. P. Huijskens, M. J. Ruijter, and C. W. Oosterlee. *Efficient numerical Fourier methods for coupled forward-backward SDEs*. Journal of Computational and Applied Mathematics 296 (2016): 593-612.
- [6] M. J. Ruijter, and C. W. Oosterlee. *Numerical Fourier method and second-order Taylor scheme for backward SDEs in finance*. Applied Numerical Mathematics 103 (2016): 1-26.
- [7] T. P. Huijskens, M. J. Ruijter, C. W. Oosterlee. *Efficient numerical Fourier methods for coupled forward-backward SDE's* Journal of Computational and Applied Mathematics, 296, 593 - 612. ISSN 0377-0427.
- [8] M. Jin, P. Protter, and J. Yong. *Solving forward-backward stochastic differential equations explicitly — a four step scheme*. Probability theory and related fields 98.3 (1994): 339-359.
- [9] J. Ma, P. Protter, J. Martín, and S. Torres. *Numerical method for backward stochastic differential equations*. The Annals of Applied Probability 12.1 (2002): 302-316.
- [10] E. Gobet and C. Labart. *Error expansion for the discretization of backward stochastic differential equations*. Stochastic Processes and their Applications, 117(7):803–829, 2007.

- [11] E. Gobet and C. Labart. *Solving BSDE with adaptive control variate*. SIAM Journal on Numerical Analysis, 48(1):257–277, 2010.
- [12] W. E, M. Hutzenthaler, A. Jentzen, and T. Kruse, T. *On multilevel Picard numerical approximations for high-dimensional nonlinear parabolic partial differential equations and high-dimensional nonlinear backward stochastic differential equations*. Journal of Scientific Computing, 79(3), 1534-1571, 2019.
- [13] C. Bender and R. Denk. *A forward scheme for backward SDEs*. Stochastic Processes and their Applications, 117:1793–1812, 2007.
- [14] B. Bouchard, and N. Touzi. *Discrete-time approximation and Monte-Carlo simulation of backward stochastic differential equations*. Stochastic Processes and their applications 111.2 (2004): 175-206.
- [15] K. W. Chau, and C. W. Oosterlee. *Stochastic grid bundling method for backward stochastic differential equations*. International Journal of Computer Mathematics, 96(11), 2272-2301, 2019.
- [16] A. Fahim, N. Touzi, and X. Warin. *A probabilistic numerical method for fully nonlinear parabolic PDEs*. In: Ann. Appl. Probab. 21.4, 2011, pp. 1322–1364.
- [17] C. Bender and J. Steiner, *Least-squares Monte Carlo for backward SDEs* Numerical Methods in Finance. Springer, Berlin, Heidelberg, 2012, pp. 257–289
- [18] D. Crisan, K. Manolarakis, and N. Touzi. *On the Monte Carlo simulation of BSDEs: An improvement on the Malliavin weights*. Stochastic Processes and their Applications, 120(7), 1133-1158, 2010.
- [19] E. Gobet, J. G. López-Salas, P. Turkedjiev, C. Vasquez *Stratified regression Monte-Carlo scheme for semilinear PDEs and BSDEs with large scale parallelization on GPUs*. SIAM Journal on Scientific Computing, 38(6), C652-C677, 2016.
- [20] J. Chessari, and K. Reiichiro. *Numerical Methods for Backward Stochastic Differential Equations: A Survey*. arXiv preprint arXiv:2101.08936, 2021.
- [21] C. Huré, H. Pham, and X. Warin. *Deep backward schemes for high-dimensional nonlinear PDEs*. Mathematics of Computation 89.324 (2020): 1547-1579.
- [22] J. Han, A. Jentzen, and W. E. *Solving high-dimensional partial differential equations using deep learning*. Proceedings of the National Academy of Sciences 115.34 (2018): 8505-8510.
- [23] J. Han, A. Jentzen, and W. E. *Overcoming the curse of dimensionality: Solving high-dimensional partial differential equations using deep learning*. Proceedings of the National Academy of Sciences 115.34 (2018): 8505-8510.
- [24] G. Alessandro, C. Reisinger, and A. Picarelli. *Deep xVA Solver—A neural network based counterparty credit risk management framework*. Available at SSRN 3594076 (2020).
- [25] J. Han, and J. Long. *Convergence of the deep BSDE method for coupled FBSDEs*. Probability, Uncertainty and Quantitative Risk 5.1 (2020): 1-33.
- [26] J. Yifan, and J. Li. *Convergence of the Deep BSDE method for FBSDEs with non-Lipschitz coefficients*. arXiv preprint arXiv:2101.01869 (2021).
- [27] M. Hutzenthaler, F. Hornung, A. Jentzen, and P. von Wurstemberger, *A proof that rectified deep neural networks overcome the curse of dimensionality in the numerical approximation of semilinear heat equations*. SN partial differential equations and applications 1.2 (2020): 1-34.
- [28] J. Berner, P. Grohs, and A. Jentzen. *Analysis of the Generalization Error: Empirical Risk Minimization over Deep Artificial Neural Networks Overcomes the Curse of Dimensionality in the Numerical Approximation of Black–Scholes Partial Differential Equations*. SIAM Journal on Mathematics of Data Science 2.3 (2020): 631-657.
- [29] D. Elbrächter, P. Grohs, A. Jentzen, and C. Schwab. *DNN expression rate analysis of high-dimensional PDEs: Application to option pricing*. Constructive Approximation (2021): 1-69.
- [30] M. Hutzenthaler, A. Jentzen, T. Kruse, and T. A. Nguyen, *A proof that rectified deep neural networks overcome the curse of dimensionality in the numerical approximation of semilinear heat equations*, Partial Differ. Equ. Appl., 1 (2020), pp. 1-34.

- [31] A. Jentzen, D. Salimova, and T. Welti, *Proof that deep artificial neural networks overcome the curse of dimensionality in the numerical approximation of Kolmogorov partial differential equations with constant diffusion and nonlinear drift coefficients*, Commun. Math. Sci., 19 (2021), pp. 1167–1205.
- [32] J. Yifan, and J. Li. *Convergence of the Deep BSDE method for FBSDEs with non-Lipschitz coefficients*. arXiv preprint arXiv:2101.01869 (2021). APA
- [33] C. Beck, S. Becker, P. Grohs, N. Jaafari, and A. Jentzen, *Solving the Kolmogorov PDE by means of deep learning*, J. Sci. Comput., 88 (2021), 73.
- [34] C. Beck, W. E, and A. Jentzen, *Machine learning approximation algorithms for highdimensional fully nonlinear partial differential equations and second-order backward stochastic differential equations*, J. Nonlinear Sci., 29 (2019), pp. 1563–1619.
- [35] C. Beck, S. Becker, P. Cheridito, A. Jentzen, and A Neufeld. *Deep splitting method for parabolic PDEs*. SIAM Journal on Scientific Computing 43.5 (2021): A3135-A3154.
- [36] M. Fujii, A. Takahashi, and M. Takahashi, *Asymptotic expansion as prior knowledge in deep learning method for high dimensional BSDEs*, Asia-Pac., 26 (2019), pp. 391–408.
- [37] P. H. Labordere. *Deep Primal-Dual Algorithm for BSDEs: Applications of Machine Learning to CVA and IM*, ERN: Other Econometric Modeling: Capital Markets - Risk (Topic), 2017.
- [38] M. Raissi. *Forward-backward stochastic neural networks: Deep learning of high-dimensional partial differential equations*. arXiv preprint arXiv:1804.07010 (2018).
- [39] S. Ji, S. Peng, Y. Peng, and X. Zhang *Three algorithms for solving high-dimensional fully coupled FBSDEs through deep learning*. IEEE Intelligent Systems 35.3 (2020): 71-84.
- [40] B. Dai, V.R. Surabhi, P. Krishnamurthy *Learning Locomotion Controllers for Walking Using Deep FBSDE*. arXiv preprint arXiv:2107.07931 (2021).
- [41] Q. Chan-Wai-Nam, J. Mikael, and X. Warin, *Machine learning for semi linear PDEs*, J. Sci. Comput., 79 (2019), pp. 1667–1712.
- [42] C. Hüre, H. Pham, and X. Warin. *Some machine learning schemes for high-dimensional nonlinear PDEs*, Math. Comput., 2020, 89, p. 1547-1579.
- [43] B. Negyesi, Balint, K. Andersson, and C. W. Oosterlee. *The One Step Malliavin scheme: new discretization of BSDEs implemented with deep learning regressions*. arXiv preprint arXiv:2110.05421 (2021).
- [44] M. Germain, H. Pham, and X. Warin. *Approximation error analysis of some deep backward schemes for nonlinear PDEs*. SIAM Journal on Scientific Computing 44.1 (2022): A28-A56.
- [45] C. Beck, M. Hutzenthaler, and A Jentzen *An overview on deep learning-based approximation methods for partial differential equations*. arXiv preprint arXiv:2012.12348 (2020).
- [46] G. Tang. *Martingale Decomposition and BSDE on Time Scales*. arXiv preprint arXiv:2012.11200 (2020).
- [47] K. Andersson. *Approximate stochastic control based on deep learning and forward backward stochastic differential equations*. MS thesis, Chalmers University of Technology, (2018).
- [48] M. Pereira, Z. Wang, I. Exarchos *Learning deep stochastic optimal control policies using forward-backward sdes*. arXiv preprint arXiv:1902.03986 (2019).
- [49] Y. Liu, Y. Wang, Z. Zhuang and X. Guo *Deep FBSDE Controller for Attitude Control of Hypersonic Aircraft*. 2021 6th IEEE International Conference on Advanced Robotics and Mechatronics (ICARM). IEEE, 2021.
- [50] S. Ji, S. Peng, Y. Peng and X. Zhang *A control method for solving high-dimensional Hamiltonian systems through deep neural networks*. arXiv preprint arXiv:2111.02636 (2021).
- [51] Y. Wang, and Y.H. Ni *Deep BSDE-ML Learning and Its Application to Model-Free Optimal Control*. arXiv preprint arXiv:2201.01318 (2022).
- [52] J. Han, W. E. *Deep learning approximation for stochastic control problems*, Deep Reinforcement Learning Workshop, NIPS (2016).

- [53] J. Zhang. *Backward stochastic differential equations. In Backward Stochastic Differential Equations* (pp. 79-99). Springer, New York, NY, 2017.
- [54] F. Antonelli *Backward forward stochastic differential equations*. Diss. Purdue University, 1993.
- [55] P.E. Kloeden, and E. Platen. *Numerical Solution of Stochastic Differential Equations*. Springer, Berlin, Heidelberg, 1992.
- [56] R. Kruse. *Characterization of bistability for stochastic multistep methods*. BIT. (2012): 109–140.
- [57] R. Kruse and W.-J. Beyn. *Two-sided error estimates for the stochastic theta method*. Discrete Contin. Dyn. Syst. Ser. B. (2010): 389–407.
- [58] R. Mikulevičius, and E. Platen. *Rate of convergence of the Euler approximation for diffusion processes* Math. Nachr. (1991): 233–239.
- [59] K. Higa. *Weak rate of convergence of the Euler–Maruyama scheme for stochastic differential equations with non-regular drift* Comput. Appl. (2017): 138-158.
- [60] K. Åström. *Introduction to stochastic control theory* Courier Corporation, 2012.
- [61] G. Cybenko. *Approximation by superpositions of a sigmoidal function*. Mathematics of control, signals and systems 2.4 (1989): 303-314.
- [62] C. Nwankpa, W. Ijomah, A. Gachagan, and S. Marshall *Activation functions: Comparison of trends in practice and research for deep learning*. arXiv preprint arXiv:1811.03378, (2018).
- [63] G. Buttazzo, and G. Dal Maso (1982). Γ -convergence and optimal control problems. Journal of optimization theory and applications, 38(3), 385-407.
- [64] R. T. Rockafellar, and R. J. B. Wets (2009). *Variational analysis* (Vol. 317). Springer Science & Business Media.
- [65] J. F. Bonnans, J. Gianatti, and F. J. Silva (2019). *On the time discretization of stochastic optimal control problems: the dynamic programming approach*. ESAIM: Control, Optimisation and Calculus of Variations, 25, 63.
- [66] D. P. Kingma, and J. Ba *Adam: A method for stochastic optimization*. arXiv preprint arXiv:1412.6980. ISO 690. Comment: Published as a conference paper at the 3rd International Conference for Learning Representations, San Diego, (2015).