

DECOHERENCE QUANTIFICATION THROUGH COMMUTATION RELATIONS DECAY FOR OPEN QUANTUM HARMONIC OSCILLATORS

IGOR G. VLADIMIROV, IAN R. PETERSEN

ABSTRACT. This paper is concerned with multimode open quantum harmonic oscillators (OQHOs), described by linear quantum stochastic differential equations with multichannel external bosonic fields. We consider the exponentially fast decay in the two-point commutator matrix of the system variables as a manifestation of quantum decoherence. Such dissipative effects are caused by the interaction of the system with its environment and lead to a loss of specific features of the unitary evolution which the system would have in the case of isolated dynamics. These features are exploited as nonclassical resources in quantum computation and quantum information processing technologies. A system-theoretic definition of decoherence time in terms of the commutator matrix decay is discussed, and an upper bound for it is provided using algebraic Lyapunov inequalities. Employing spectrum perturbation techniques, we investigate the asymptotic behaviour of a related Lyapunov exponent for the oscillator when the system-field coupling is specified by a small coupling strength parameter and a given coupling shape matrix. The invariant quantum state of the system, driven by vacuum fields, in the weak-coupling limit is also studied. We illustrate the results for one- and two-mode oscillators with multichannel external fields and outline their application to a decoherence control problem for a feedback interconnection of OQHOs.

1. INTRODUCTION

In contrast to classical deterministic and stochastic systems, the evolution of quantum mechanical objects is described in terms of operator-valued variables on a Hilbert space, and their statistical properties are formulated using quantum probability [7, 23]. The quantum dynamic variables are usually noncommuting operators, which, unlike classical variables, are not accessible to simultaneous observation because quantum measurements, accompanied by interaction of quantum systems with classical measuring devices and resulting in real-valued quantities, modify the quantum states. The latter, represented by density operators on the same Hilbert space, are quantum counterparts of classical scalar-valued probability distributions.

The more complicated nature of quantum observables and quantum states and the subtle interplay between the noncommutativity and measurements are specific features of quantum mechanics. These features are closely related to the model of unitary, and hence reversible, dynamics of an isolated quantum system, whose initial conditions have a non-vanishing effect on the subsequent evolution of the system. The reversibility of the isolated quantum dynamics and its consequences (such as conservation laws) play an important role in quantum computation and quantum information processing which exploit quantum mechanical resources [15].

The dynamics of an open quantum system [1, 3], which interacts with its environment (such as other quantum or classical systems and external fields), are qualitatively different from the unitary evolution. In this case, the internal dynamics, which the system would

2010 *Mathematics Subject Classification.* 81S22, 81S25, 81P16, 81S05, 81Q93, 93E15, 81R15, 81Q10, 81Q15, 37L40, 81P40, 60G15.

Key words and phrases. Open quantum harmonic oscillator, quantum decoherence, two-point commutator matrix, exponential decay, Lyapunov exponent, algebraic Lyapunov inequality, spectrum perturbation.

This work is supported by the Australian Research Council grant DP210101938.

have in isolation from the surroundings, is “diluted” with the contribution from the other systems whose variables (as operators on different spaces) commute with (and hence, are classical with respect to) those of the underlying quantum system. This makes the open system gradually lose, over the course of time, its original quantum features in terms of the commutation structure and statistical properties, which is interpreted as quantum decoherence.

The decoherence effects, coming from the dissipative interaction with the environment, are particularly apparent in open quantum harmonic oscillators (OQHOs) which play the role of building blocks in linear quantum systems theory [17, 22] aiming to engineer quantum system interconnections with desired dynamic properties, including stability, robustness and optimality. Such systems are endowed with conjugate position-momentum pairs [23] (or their linear combinations) as dynamic variables and, in the framework of the Hudson-Parthasarathy calculus [9, 18], are described by linear quantum stochastic differential equations (QSDEs). These equations are driven by noncommutative quantum Wiener processes on a symmetric Fock space [20] which model bosonic fields. Similarly to classical linear systems [12], the solution of the linear QSDE consists of the system response to the initial system variables and the forced response to the external field, with both responses commuting with each other. For a dissipative OQHO, with a Hurwitz dynamics matrix, the forced response becomes dominant over the response to the initial condition which fades away exponentially fast, thus giving rise to meaningful time scales for the quantum decoherence in the system. On the other hand, the same mechanism underlies the convergence of the stable OQHO to its invariant zero-mean Gaussian quantum state in the case of vacuum fields, and this is employed for the generation of such states through dissipation [30].

The present paper is concerned with a particular way to quantify decoherence for multimode dissipative OQHOs, which defines the decoherence time in terms of the exponentially fast decay in the two-point canonical commutation relations (CCRs) for the system variables. We provide a system-theoretic upper bound for the decoherence time using algebraic Lyapunov inequalities. We also investigate the related asymptotic behaviour of the leading Lyapunov exponent for the dynamics matrix of the oscillator with a small coupling strength parameter and a given coupling shape matrix. This analysis employs spectrum perturbation techniques [14] and is carried out for a class of dissipative OQHOs with a positive definite energy matrix, a nonsingular one-point CCR matrix and pairwise different eigenfrequencies for the uncoupled version of the system. The weak-coupling formulation allows a low decoherence criterion for the OQHO to be obtained in the form of the asymptotic decoherence time significantly exceeding the largest period of uncoupled oscillatory modes. Since lowering the decoherence towards isolating the system from its environment is in conflict with increasing the dissipation for accelerated convergence to the invariant zero-mean Gaussian quantum state mentioned above, we also discuss the weak-coupling limit for the invariant covariance matrix which completely specifies such a state. These asymptotic results are compared with exact computations for one- and two-mode oscillators driven by multichannel fields. We also apply them to a decoherence control setting which is outlined for a coherent (measurement-free) feedback interconnection of two OQHOs (playing the role of a quantum plant and a quantum controller) with direct and indirect coupling.

Note that the type of decoherence discussed in this paper corresponds to vacuum decoherence in [1, Section 4.4.1], while there also are other scenarios of decoherence, involving, for example, thermal quantum noise [3, Section 3.3.3], quantum measurements and different classes of quantum systems, such as those with finite-level dynamic variables (see also [1, Section 4.4.1] and references therein, including [2, 25]). Although, in the context of quantum computing and quantum information, the study of decoherence phenomena is particularly relevant for finite-level (multiqubit) systems [15, Chapter III, Section 8] which

employ the Pauli matrices [23] and their extensions, OQHOs are tractable as the closest quantum-mechanical counterparts of classical linear stochastic systems, and the results for OQHOs can serve as prototypes for a more complicated decoherence analysis in the finite-level case.

The paper is organised as follows. Section 2 describes the class of OQHOs under consideration, including the isolated dynamics case in the absence of coupling. Section 3 discusses the exponential decay in the two-point CCRs for the system variables and the corresponding decoherence time. Section 4 obtains asymptotic estimates for the Lyapunov exponents and decoherence time in the presence of a small coupling strength parameter. Section 5 establishes a weak-coupling limit for the invariant covariance matrix. Section 6 shows that the decoherence time estimates are exact for one-mode oscillators. Section 7 provides a numerical illustration of the results for a two-mode oscillator. Section 8 outlines an application of the results to a decoherence control setting for interconnected OQHOs. Section 9 makes concluding remarks.

2. OPEN QUANTUM HARMONIC OSCILLATORS

We consider an $\frac{n}{2}$ -mode open quantum harmonic oscillator (OQHO) with an even number n of dynamic variables X_1, \dots, X_n . In accordance with the Heisenberg picture of quantum dynamics [23], they are time-varying self-adjoint operators on a complex separable Hilbert space \mathfrak{H} , satisfying at every moment of time the canonical commutation relations (CCRs)

$$[X, X^T] = 2i\Theta, \quad X := \begin{bmatrix} X_1 \\ \vdots \\ X_n \end{bmatrix} \quad (2.1)$$

with a constant matrix $\Theta = -\Theta^T \in \mathbb{R}^{n \times n}$. Here, the matrix transpose $(\cdot)^T$ applies to vectors of operators as if they consisted of scalars (with vectors being organised as columns unless indicated otherwise), and the commutator $[\alpha, \beta] := \alpha\beta - \beta\alpha$ of linear operators extends to the commutator matrix $[\xi, \eta^T] := ([\xi_j, \eta_k])_{1 \leq j \leq a, 1 \leq k \leq b}$ for vectors $\xi := (\xi_j)_{1 \leq j \leq a}$ and $\eta := (\eta_k)_{1 \leq k \leq b}$ of operators. The internal energy of the oscillator is described by the Hamiltonian

$$H := \frac{1}{2}X^T R X, \quad (2.2)$$

which is a self-adjoint operator on \mathfrak{H} , whose quadratic dependence on the system variables is parameterised by an energy matrix $R = R^T \in \mathbb{R}^{n \times n}$. As an open system, the OQHO interacts with its environment which is modelled by an $\frac{m}{2}$ -channel external bosonic field in the form of an even number m of self-adjoint quantum Wiener processes W_1, \dots, W_m on a symmetric Fock space \mathfrak{F} [18] with the Ito table

$$dW dW^T = \Omega dt, \quad W := \begin{bmatrix} W_1 \\ \vdots \\ W_m \end{bmatrix}, \quad \Omega := I_m + iJ, \quad (2.3)$$

where

$$J := \mathbf{J} \otimes I_{m/2} = \begin{bmatrix} 0 & I_{m/2} \\ -I_{m/2} & 0 \end{bmatrix}. \quad (2.4)$$

Here, \otimes is the Kronecker product of matrices, I_r is the identity matrix of order r , and the matrix

$$\mathbf{J} := \begin{bmatrix} 0 & 1 \\ -1 & 0 \end{bmatrix} \quad (2.5)$$

spans the one-dimensional subspace of antisymmetric matrices of order 2. In accordance with (2.3) and the commutativity $[W, dW^T] = 0$ between W (or any other adapted process)

and the future-pointing Ito increments dW , the matrix J in (2.4) specifies the commutation structure of W as

$$[W(s), W(t)^T] = 2i \min(s, t) J, \quad s, t \geq 0.$$

The internal dynamics of the system and its interaction with the external field lead to a quantum stochastic differential equation (QSDE) [17, 22] for the time evolution of the system variables:

$$dX = AXdt + BdW, \quad (2.6)$$

which is understood in the sense of the Hudson-Parthasarathy calculus [9, 18]. Here, $A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times m}$ are constant matrices which are specified by the CCR matrices Θ , J from (2.1), (2.4), the energy matrix R from (2.2), and a system-field coupling matrix $M \in \mathbb{R}^{m \times n}$ as

$$A = 2\Theta(R + M^T J M), \quad B = 2\Theta M^T. \quad (2.7)$$

The matrix M parameterises a vector MX of m self-adjoint coupling operators, which pertain to the energy exchange between the OQHO and the external quantum field. In the absence of coupling between the system and the environment, when $M = 0$, the matrix A takes the form

$$A_0 := 2\Theta R, \quad (2.8)$$

and the dispersion matrix B in (2.7) vanishes, so that the QSDE (2.6) loses its diffusion term BdW and reduces to an ODE

$$\dot{X} = i[H, X] = A_0 X, \quad (2.9)$$

where $(\dot{\cdot}) := \partial_t(\cdot)$ is the time derivative. In this isolated dynamics case, where $X(t) = U(t)^\dagger X(0)U(t)$, with $U(t) := e^{-itH(0)}$ a unitary operator and $(\cdot)^\dagger$ the operator adjoint, the Hamiltonian $H(t) = U(t)^\dagger H(0)U(t) = H(0)U(t)^\dagger U(t) = H(0)$ is preserved in time. This can also be seen from (2.2), (2.9) as

$$\dot{H} = \frac{1}{2}(\dot{X}^T R X + X^T R \dot{X}) = \frac{1}{2}X^T (A_0^T R + R A_0) X = 0$$

since, in view of (2.8),

$$\frac{1}{2}(A_0^T R + R A_0) = (\Theta R)^T R + R \Theta R = 0 \quad (2.10)$$

due to the antisymmetry of the CCR matrix Θ and the symmetry of the energy matrix R . For the general QSDE (2.6), the Hamiltonian H is no longer a constant operator. More precisely, by applying the quantum Ito lemma [9, 18] along with (2.3) to (2.2), it follows that

$$\begin{aligned} dH &= \frac{1}{2}((dX)^T R X + X^T R dX + (dX)^T R dX) \\ &= \frac{1}{2}(X^T (A^T R + R A) X dt + 2X^T R B dW + (dW)^T B^T R B dW) \\ &= \frac{1}{2}X^T (\tilde{A}^T R + R \tilde{A}) X dt + X^T R B dW + \frac{1}{2}\langle B^T R B, \Omega \rangle_F dt \\ &= \frac{1}{2}(X^T (\tilde{A}^T R + R \tilde{A}) X + \langle R, B B^T \rangle_F) dt + X^T R B dW, \end{aligned} \quad (2.11)$$

where

$$\tilde{A} := A - A_0 = 2\Theta M^T J M, \quad B B^T = -4\Theta M^T M \Theta, \quad (2.12)$$

in accordance with (2.7), (2.8). Here, $\langle \cdot, \cdot \rangle_F$ is the Frobenius inner product of matrices [8], and use is also made of the commutativity $[X, dW^T] = 0$ together with the special structure of the quantum Ito matrix Ω from (2.3) and the matrix A in (2.7), with the latter implying that

$$A^T R + R A = \tilde{A}^T R + R \tilde{A} \quad (2.13)$$

in view of (2.10), (2.12). In what follows, the expectation

$$\mathbf{E}\zeta := \text{Tr}(\rho\zeta) \quad (2.14)$$

of a quantum variable ζ on the system-field space $\mathfrak{H} := \mathfrak{H}_0 \otimes \mathfrak{F}$ is over the tensor-product state

$$\rho = \rho_0 \otimes \nu,$$

where ρ_0 is the initial quantum state of the system on the initial system space \mathfrak{H}_0 (for the action of $X_1(0), \dots, X_n(0)$), and ν is the vacuum state [18] for the quantum Wiener process W on \mathfrak{F} . In the case of vacuum fields, the averaging of both sides of (2.11) according to (2.14) yields

$$\begin{aligned} (\mathbf{E}H)' &= \frac{1}{2}(\mathbf{E}(X^T(\tilde{A}^T R + R\tilde{A})X) + \langle R, BB^T \rangle_{\mathbb{F}}) \\ &= \frac{1}{2}(\langle \tilde{A}^T R + R\tilde{A}, P \rangle_{\mathbb{F}} + \langle R, BB^T \rangle_{\mathbb{F}}), \end{aligned} \quad (2.15)$$

where the martingale part $X^T R B dW$ of (2.11) does not contribute to the expectation, and use is made of the real covariances

$$P := \text{Re}\mathbf{E}(XX^T)$$

of the system variables. The time-varying matrix $P = P^T \in \mathbb{R}^{n \times n}$ satisfies

$$P + i\Theta = \mathbf{E}(XX^T) \succcurlyeq 0 \quad (2.16)$$

due to the generalised Heisenberg uncertainty principle [7] and is governed by the Lyapunov ODE

$$\dot{P} = AP + PA^T + BB^T. \quad (2.17)$$

The latter provides an alternative way to arrive at (2.15) through the relation $\mathbf{E}H = \frac{1}{2}\langle R, P \rangle_{\mathbb{F}}$ as

$$\begin{aligned} (\mathbf{E}H)' &= \frac{1}{2}\langle R, \dot{P} \rangle_{\mathbb{F}} \\ &= \frac{1}{2}\langle R, AP + PA^T + BB^T \rangle_{\mathbb{F}} \\ &= \frac{1}{2}(\langle \tilde{A}^T R + R\tilde{A}, P \rangle_{\mathbb{F}} + \langle R, BB^T \rangle_{\mathbb{F}}) \\ &= \frac{1}{2}(\langle \tilde{A}^T R + R\tilde{A}, P \rangle_{\mathbb{F}} + \langle R, BB^T \rangle_{\mathbb{F}}), \end{aligned} \quad (2.18)$$

where (2.17) is used along with (2.13) and the second equality from (2.12). As seen from the right-hand side of (2.15), for a given matrix P , the quantity $(\mathbf{E}H)'$, which pertains to the rate of work of the external field on the system, depends on the coupling matrix M in a quadratic fashion through the matrices (2.12). In the steady-state regime, when the matrix A is Hurwitz and P is the unique solution

$$P = \int_{\mathbb{R}_+} e^{tA} BB^T e^{tA^T} dt \quad (2.19)$$

of the algebraic Lyapunov equation (ALE)

$$AP + PA^T + BB^T = 0, \quad (2.20)$$

it follows from (2.18) that $(\mathbf{E}H)' = 0$, and hence, the Hamiltonian H , despite not being preserved, has a constant mean value $\mathbf{E}H$. In this case (when A is Hurwitz), $P + i\Theta = \mathbf{E}(XX^T)$ is the quantum covariance matrix of the invariant zero mean Gaussian quantum state [19] of the system. This property of OQHOs underlies the generation of Gaussian states through a sufficiently long run of the system [30]. The dissipation, which is exploited in this state generation procedure, comes with decoherence. The latter results from the system-environment interaction and leads to a ‘‘loss of quantumness’’ over time in comparison with the isolated dynamics.

3. EXPONENTIAL DECAY IN TWO-POINT CCRs

The Hurwitz property of the matrix A , which secures the steady-state regime discussed above, gives rise to an exponentially fast decay in the two-point CCRs [27] for the system variables described by

$$[X(s), X(t)^T] = 2i\Upsilon(s-t), \quad s, t \geq 0, \quad (3.1)$$

with

$$\Upsilon(\tau) := \begin{cases} e^{\tau A} \Theta & \text{if } \tau \geq 0 \\ \Theta e^{-\tau A^T} & \text{if } \tau < 0 \end{cases}, \quad \tau \in \mathbb{R}, \quad (3.2)$$

from which the one-point CCRs (2.1) are obtained as a particular case at $s = t$ (that is, $\tau = 0$) due to

$$\Upsilon(0) = \Theta. \quad (3.3)$$

The CCRs (3.1), which are a consequence of the joint commutation structure of the system variables and the external fields, hold regardless of a particular quantum state and regardless of A being Hurwitz. The limit relation

$$\lim_{\tau \rightarrow \infty} \Upsilon(\tau) = 0 \quad (3.4)$$

(when A is Hurwitz) means that for any $j, k = 1, \dots, n$, the system variables $X_j(s)$ become “asymptotically commuting” with (and hence, classical with respect to) $X_k(t)$ at distant moments of time s, t (as $|s-t| \rightarrow +\infty$). The decay (3.4) in the two-point CCR matrix can be regarded as a manifestation of quantum decoherence in the system caused by its coupling to the environment. Indeed, the forced response term $\int_0^t e^{(t-s)A} B dW(s)$, contributed by the external field W to the system variables

$$X(t) = e^{tA} X(0) + \int_0^t e^{(t-s)A} B dW(s) \quad (3.5)$$

over time $t \geq 0$, and the response $e^{tA} X(0)$ of the system to the initial condition commute with each other:

$$\left[\int_0^t e^{(t-s)A} B dW(s), (e^{tA} X(0))^T \right] = \int_0^t e^{(t-s)A} B [dW(s), X(0)^T] e^{tA^T} = 0 \quad (3.6)$$

since $X(0)$ and W consist of operators acting on different Hilbert spaces \mathfrak{H}_0 and \mathfrak{F} , whereby $[W(t), X(0)^T] = 0$ for all $t \geq 0$. In fact, (3.1), (3.2) follow from a combination of (3.5), (3.6) with (2.1). Therefore, if A is Hurwitz, $X(0)$ has an exponentially decaying effect on $X(t)$, and the forced term in (3.5) becomes dominant over the course of time. This dissipative behaviour is qualitatively different from the isolated dynamics in the absence of coupling ($M = 0$), when the matrix A in (2.7) reduces to A_0 in (2.8), which has a purely imaginary spectrum $\{i\omega_k : k = 1, \dots, n\}$ in the case of a nonsingular CCR matrix Θ and positive definite energy matrix R :

$$\det \Theta \neq 0, \quad R \succ 0. \quad (3.7)$$

The eigenfrequencies $\omega_1, \dots, \omega_n \in \mathbb{R}$ (which should not be confused with the spectrum of the Hamiltonian H in (2.2) as a self-adjoint operator on the infinite dimensional system-field Hilbert space \mathfrak{H}) are all nonzero and symmetric about the origin, so that, without loss of generality,

$$\omega_k = -\omega_{k+\frac{n}{2}} > 0, \quad k = 1, \dots, \frac{n}{2}. \quad (3.8)$$

Indeed, under the conditions (3.7), the matrix A_0 in (2.8) is isospectral to the nonsingular real antisymmetric matrix $2\sqrt{R}\Theta\sqrt{R}$ whose eigenvalues are purely imaginary and symmetric about the origin [8]. This isospectrality follows from the similarity transformation

$$A_0 = R^{-1/2} (2\sqrt{R}\Theta\sqrt{R}) \sqrt{R} \quad (3.9)$$

(which is used, for example, in [21]; see also the proof of Williamson's symplectic diagonalization theorem [28, 29] in [5, pp. 244–245]). Moreover, (3.9) implies that the matrix A_0 is diagonalisable as

$$A_0 = iS\bar{U}S^{-1}, \quad S := R^{-1/2}V, \quad \bar{U} := \text{diag}(\omega_k)_{1 \leq k \leq n}. \quad (3.10)$$

Here, $S^{-1} = V^*\sqrt{R}$, with $(\cdot)^* := \overline{(\cdot)}^T$ the complex conjugate transpose of a matrix, and

$$V := [v_1 \ \dots \ v_n] \in \mathbb{C}^{n \times n} \quad (3.11)$$

is a unitary matrix whose columns $v_1, \dots, v_n \in \mathbb{C}^n$ are the eigenvectors of the Hermitian matrix

$$-2i\sqrt{R}\Theta\sqrt{R} = V\bar{U}V^* \quad (3.12)$$

with the eigenvalues $\omega_1, \dots, \omega_n$,

$$-2i\sqrt{R}\Theta\sqrt{R}v_k = \omega_k v_k, \quad k = 1, \dots, n, \quad (3.13)$$

satisfying

$$v_{k+\frac{n}{2}} = \bar{v}_k, \quad 1 \leq k \leq \frac{n}{2}, \quad (3.14)$$

in accordance with (3.8). The corresponding matrix exponentials

$$e^{\tau A_0} = S e^{i\tau \bar{U}} S^{-1}, \quad e^{-\tau A_0^T} = S^{-T} e^{-i\tau \bar{U}} S^T$$

(with $(\cdot)^{-T} := ((\cdot)^{-1})^T$) in (3.2), associated with (3.10), are oscillatory functions of time τ , with

$$T := \frac{2\pi}{\min_{1 \leq k \leq \frac{n}{2}} \omega_k} > 0 \quad (3.15)$$

being the largest period of the oscillatory modes, since $e^{i\tau \bar{U}} = \text{diag}_{1 \leq k \leq n}(e^{i\omega_k \tau})$. Therefore, in the case of (3.7), only a nonzero coupling matrix M can make the matrix $A = A_0 + \tilde{A}$ in (2.7) Hurwitz (thus leading to (3.4)) through the matrix \tilde{A} in (2.12) in view of (2.8). If the matrix A is Hurwitz, a ‘‘typical’’ time constant of the exponential decay in the two-point CCR matrix (3.2) provides a measure of quantum decoherence in the system and can be defined, for example, as

$$\tau_* := \inf \left\{ \tau > 0 : \|e^{\tau A} \Theta\|_F \leq \frac{1}{e} \|\Theta\|_F \right\}. \quad (3.16)$$

Here, use is made of the Frobenius norm $\|\Theta\|_F = \sqrt{-\text{Tr}(\Theta^2)}$ of the one-point antisymmetric CCR matrix Θ from (3.3), although a different matrix norm can also be used for this purpose.

An upper bound for the decoherence time (3.16) can be obtained through algebraic Lyapunov inequalities. More precisely, for any

$$0 < \lambda < -\ln \mathbf{r}(e^A) = -\max_{1 \leq k \leq n} \text{Re} \lambda_k \quad (3.17)$$

(with $\mathbf{r}(\cdot)$ the spectral radius, and $\lambda_1, \dots, \lambda_n$ the eigenvalues of A), there exists a positive definite matrix $\Gamma = \Gamma^T \in \mathbb{R}^{n \times n}$ such that

$$A\Gamma + \Gamma A^T + 2\lambda\Gamma \prec 0. \quad (3.18)$$

Since the second inequality in (3.17) is equivalent to $A + \lambda I_n$ being Hurwitz, all the matrices Γ , satisfying (3.18), can be represented as the solutions

$$\Gamma = \int_{\mathbb{R}_+} e^{2\lambda t} e^{tA} N e^{tA^T} dt \quad (3.19)$$

of the ALEs

$$(A + \lambda I_n)\Gamma + \Gamma(A + \lambda I_n)^T + N = 0$$

(by analogy with (2.19), (2.20)), involving arbitrary positive definite matrices $N = N^T \in \mathbb{R}^{n \times n}$. Similarly to [27, Proof of Theorem 6 on p. 122], (3.18) implies the contraction property

$$\|G_\tau\| \leq e^{-\lambda\tau}, \quad \tau > 0$$

for the matrix

$$G_\tau := \Gamma^{-1/2} e^{\tau A} \sqrt{\Gamma}$$

in the sense of the operator matrix norm $\|\cdot\|$. Hence,

$$\begin{aligned} \|e^{\tau A} \Theta\|_{\mathbb{F}}^2 &= \|\sqrt{\Gamma} G_\tau \Gamma^{-1/2} \Theta\|_{\mathbb{F}}^2 \\ &= \text{Tr}((\Gamma^{-1/2} \Theta)^T G_\tau^T \Gamma G_\tau \Gamma^{-1/2} \Theta) \\ &\leq \lambda_{\max}(\Gamma) \text{Tr}((\Gamma^{-1/2} \Theta)^T G_\tau^T G_\tau \Gamma^{-1/2} \Theta) \\ &\leq \|\Gamma\| \|G_\tau\|^2 \text{Tr}((\Gamma^{-1/2} \Theta)^T \Gamma^{-1/2} \Theta) \\ &\leq e^{-2\lambda\tau} \|\Gamma\| \|\Gamma^{-1/2} \Theta\|_{\mathbb{F}}^2 \end{aligned}$$

(where $\lambda_{\max}(\cdot)$ is the largest eigenvalue of a matrix with a real spectrum), so that $\|e^{\tau A} \Theta\|_{\mathbb{F}} \leq e^{-\lambda\tau} \sqrt{\|\Gamma\|} \|\Gamma^{-1/2} \Theta\|_{\mathbb{F}}$, and the decoherence time (3.16) admits an upper bound

$$\tau_* \leq \frac{1}{\lambda} \left(1 + \ln \left(\frac{1}{\|\Theta\|_{\mathbb{F}}} \sqrt{\|\Gamma\|} \|\Gamma^{-1/2} \Theta\|_{\mathbb{F}} \right) \right). \quad (3.20)$$

In view of the parameterisation (3.19) for the matrix Γ , the bound (3.20) can be tightened by minimising its right-hand side over the pairs (λ, N) such that λ satisfies (3.17) and $N \succ 0$ is normalised, for example, as $\text{Tr} N = 1$. The normalisation does not affect the resulting minimum value due to the linearity of the map $N \mapsto \Gamma$ and the invariance of the quantity $\sqrt{\|\Gamma\|} \|\Gamma^{-1/2} \Theta\|_{\mathbb{F}}$ in (3.20) with respect to the scaling transformation $\Gamma \mapsto \sigma \Gamma$ for any $\sigma > 0$.

4. ASYMPTOTIC WEAK-COUPLING DECOHERENCE ESTIMATES

With the decoherence part \tilde{A} of the matrix A in (2.12) depending on M in a quadratic fashion, this homogeneity can be taken into account by considering a weak-coupling formulation

$$M_\varepsilon := \varepsilon M, \quad (4.1)$$

where $\varepsilon \geq 0$ is a small scaling factor which quantifies the coupling strength, while $M \in \mathbb{R}^{m \times n}$ specifies the coupling ‘‘shape’’. Accordingly, the matrices (2.7) acquire dependence on ε as

$$A_\varepsilon = A_0 + \tilde{A}_\varepsilon, \quad \tilde{A}_\varepsilon = \varepsilon^2 \tilde{A}_1, \quad \tilde{A}_1 := 2\Theta M^T J M, \quad B_\varepsilon = \varepsilon B, \quad B := 2\Theta M^T, \quad (4.2)$$

where A_0 is given by (2.8). The following theorem is concerned with the asymptotic behaviour of the spectrum of the dynamics matrix A_ε .

Theorem 1. *Suppose the CCR matrix Θ and the energy matrix R of the OQHO satisfy (3.7). Also, suppose the eigenfrequencies of the matrix A_0 from (2.8) are pairwise different:*

$$\omega_j \neq \omega_k, \quad 1 \leq j \neq k \leq n. \quad (4.3)$$

Then for all sufficiently small values of the coupling strength parameter ε , the matrix A_ε in (4.2) has different eigenvalues $\lambda_1(\varepsilon), \dots, \lambda_n(\varepsilon)$ which, appropriately numbered, behave asymptotically as

$$\lambda_k(\varepsilon) = \omega_k(i - \varepsilon^2 \mu_k) + o(\varepsilon^2), \quad \text{as } \varepsilon \rightarrow 0+. \quad (4.4)$$

Here,

$$\mu_k := -iv_k^* R^{-1/2} M^T J M R^{-1/2} v_k, \quad k = 1, \dots, n, \quad (4.5)$$

are real-valued quantities involving the orthonormal eigenvectors v_k from (3.13) and the coupling shape matrix M in (4.1). \square

Proof. The property that the eigenvalues $\lambda_1(\varepsilon), \dots, \lambda_n(\varepsilon)$ of the matrix A_ε are pairwise different for all sufficiently small ε (that is, $\varepsilon \in [0, \delta)$ for some $\delta > 0$) follows from (4.3) and the Gershgorin localisation theorem [6, 8]. This also allows them to be numbered in such a way that each eigenvalue $\lambda_k(\varepsilon)$ inherits the infinite differentiability from A_ε in (4.2) over $\varepsilon \in [0, \delta)$. In view of the similarity transformation in (3.10), the matrix A_ε is isospectral to

$$\begin{aligned} S^{-1}A_\varepsilon S &= i\mathcal{U} + 2\varepsilon^2 S^{-1}\Theta M^T J M S \\ &= i\mathcal{U} + 2\varepsilon^2 V^* \sqrt{R} \Theta M^T J M R^{-1/2} V \\ &= i\mathcal{U} + 2\varepsilon^2 V^* \sqrt{R} \Theta \sqrt{R} R^{-1/2} M^T J M R^{-1/2} V \\ &= i\mathcal{U} + i\varepsilon^2 V^* V \mathcal{U} V^* R^{-1/2} M^T J M R^{-1/2} V \\ &= i\mathcal{U} + i\varepsilon^2 \mathcal{U} V^* R^{-1/2} M^T J M R^{-1/2} V, \end{aligned} \quad (4.6)$$

where use is also made of (3.11), (3.12). Since the matrix \mathcal{U} in (3.10) is diagonal, and its diagonal entries ω_k are pairwise different in view of (4.3), then by applying the spectrum perturbation results (see, for example, [14] and references therein), it follows from (4.6) that the diagonal entries

$$(i\mathcal{U} V^* R^{-1/2} M^T J M R^{-1/2} V)_{kk} = i\omega_k v_k^* R^{-1/2} M^T J M R^{-1/2} v_k = -\omega_k \mu_k \quad (4.7)$$

specify the coefficients of the linear terms in the asymptotic expansions of $\lambda_k(\varepsilon)$ over the powers of ε^2 as described in (4.4). Here, the matrix $iV^* R^{-1/2} M^T J M R^{-1/2} V$ is Hermitian, and hence, its diagonal entries $i v_k^* R^{-1/2} M^T J M R^{-1/2} v_k$ are real, and so also are the quantities μ_k in (4.5). ■

The following theorem is a corollary of Theorem 1 and provides stability conditions for the weakly coupled system.

Theorem 2. *Suppose the assumptions of Theorem 1 are satisfied and the eigenfrequencies ω_k of the matrix A_0 in (2.8) are arranged according to (3.8). Then the fulfillment of the inequalities*

$$\mu_k > 0, \quad k = 1, \dots, \frac{n}{2}, \quad (4.8)$$

is sufficient (and in nonstrict form, necessary) for the matrix A_ε in (4.2) to be Hurwitz for all $\varepsilon > 0$ small enough. □

Proof. From (4.4), it follows that

$$\operatorname{Re} \lambda_k(\varepsilon) = -\omega_k \mu_k \varepsilon^2 + o(\varepsilon^2), \quad \text{as } \varepsilon \rightarrow 0+. \quad (4.9)$$

Hence, the fulfillment of the inequalities

$$\omega_k \mu_k > 0, \quad k = 1, \dots, n, \quad (4.10)$$

is sufficient for A_ε to be Hurwitz for all $\varepsilon > 0$ small enough, while the nonstrict inequalities

$$\omega_k \mu_k = -\lim_{\varepsilon \rightarrow 0} \frac{\operatorname{Re} \lambda_k(\varepsilon)}{\varepsilon^2} \geq 0, \quad k = 1, \dots, n, \quad (4.11)$$

provide a necessary condition for the Hurwitz property. With the eigenvectors v_k of the matrix (3.12) satisfying (3.14) due to the convention (3.8), it follows for the quantities (4.5) that

$$\begin{aligned} \mu_{k+\frac{n}{2}} &= -i(\overline{v_k})^* R^{-1/2} M^T J M R^{-1/2} \overline{v_k} \\ &= \overline{i v_k^* R^{-1/2} M^T J M R^{-1/2} v_k} = -\mu_k, \end{aligned}$$

whereby

$$\omega_{k+\frac{n}{2}} \mu_{k+\frac{n}{2}} = \omega_k \mu_k, \quad k = 1, \dots, \frac{n}{2}. \quad (4.12)$$

Since $\text{sgn}(\omega_k \mu_k) = \text{sgn} \mu_k$ for all $k = 1, \dots, \frac{n}{2}$ in view of (3.8), then (4.12) reduces the inequalities (4.10) to (4.8), and a similar reduction holds for their nonstrict versions in (4.11). \blacksquare

Under the conditions of Theorem 2, it follows from a combination of (4.9) with (4.12) that

$$\ln \mathbf{r}(e^{A_\varepsilon}) = \max_{1 \leq k \leq n} \text{Re} \lambda_k(\varepsilon) = -\varepsilon^2 \min_{1 \leq k \leq \frac{n}{2}} (\omega_k \mu_k) + o(\varepsilon^2), \quad \text{as } \varepsilon \rightarrow 0+. \quad (4.13)$$

The leading Lyapunov exponent term $\varepsilon^2 \min_{1 \leq k \leq \frac{n}{2}} (\omega_k \mu_k)$ (taken with the opposite sign) provides an asymptotically accurate approximation for the right-hand side of (3.17) and also an estimate

$$\widehat{\tau} := \frac{\varepsilon^{-2}}{\min_{1 \leq k \leq \frac{n}{2}} (\omega_k \mu_k)} \quad (4.14)$$

for a decay time, which is different from yet related to (3.16). The decoherence time estimate (4.14) allows the coupling strength parameter ε to be chosen so as to enable all the oscillatory modes (of the uncoupled oscillator) to manifest themselves in a large number of cycles before the decay sets in. This requirement takes the form $\widehat{\tau} \gg T$ in terms of the period (3.15) and leads to

$$\varepsilon \ll \sqrt{\frac{\min_{1 \leq k \leq \frac{n}{2}} \omega_k}{2\pi \min_{1 \leq k \leq \frac{n}{2}} (\omega_k \mu_k)}} =: \widehat{\varepsilon} \quad (4.15)$$

as an asymptotic threshold on the coupling strength for the OQHO to preserve the quantum dynamic features of its isolated counterpart. Since

$$\widehat{\varepsilon} \geq \frac{1}{\sqrt{2\pi \max_{1 \leq k \leq \frac{n}{2}} \mu_k}} =: \widetilde{\varepsilon}, \quad (4.16)$$

in view of

$$\min_{1 \leq k \leq \frac{n}{2}} (\omega_k \mu_k) \leq \min_{1 \leq k \leq \frac{n}{2}} \omega_k \max_{1 \leq k \leq \frac{n}{2}} \mu_k,$$

the right-hand side of (4.16) provides a more stringent threshold on ε . For a one-mode oscillator ($n = 2$) with $\mu_1 > 0$, the eigenfrequency $\omega_1 > 0$ cancels out in (4.15), so that both thresholds are the same and reduce to

$$\varepsilon \ll \frac{1}{\sqrt{2\pi \mu_1}}. \quad (4.17)$$

These asymptotic estimates will be compared with exact results for one- and two-mode oscillators in Sections 6, 7.

5. ASYMPTOTIC BEHAVIOUR OF THE INVARIANT COVARIANCES

Whereas low decoherence is important for isolating the oscillator from the environment, this requirement conflicts with accelerating the convergence to the invariant quantum state through enhanced dissipation, which, as mentioned at the end of Section 2, underlies the Gaussian state generation. The system-field coupling influences not only the convergence rate (4.13), but also the Gaussian invariant state itself. To this end, of interest is the asymptotic behaviour of the real part of the invariant covariance matrix in (2.19),

$$P_\varepsilon = \int_{\mathbb{R}_+} e^{tA_\varepsilon} B_\varepsilon B_\varepsilon^T e^{tA_\varepsilon^T} dt = \varepsilon^2 \int_{\mathbb{R}_+} e^{tA_\varepsilon} B B^T e^{tA_\varepsilon^T} dt \quad (5.1)$$

as $\varepsilon \rightarrow 0+$, where the matrices $A_\varepsilon, B_\varepsilon$ are given by (4.2), with the ALE (2.20) taking the form

$$A_\varepsilon P_\varepsilon + P_\varepsilon A_\varepsilon^T + \varepsilon^2 B B^T = 0. \quad (5.2)$$

Theorem 3. *Suppose the assumptions of Theorems 1, 2, are satisfied along with the condition (4.8). Then the matrix P_ε in (5.1) has the limit*

$$\Pi := \lim_{\varepsilon \rightarrow 0^+} P_\varepsilon = R^{-1/2} \sum_{k=1}^{n/2} \frac{1}{\omega_k \mu_k} |\mathbf{B}^T \sqrt{R} v_k|^2 \operatorname{Re}(v_k v_k^*) R^{-1/2}, \quad (5.3)$$

computed in terms of the energy matrix R , the eigendata from (3.11)–(3.14), the matrix \mathbf{B} from (4.2) and the quantities μ_k defined in (4.5). \square

Proof. Under the conditions of Theorems 1, 2, there exists a $\delta > 0$ such that for all $\varepsilon \in [0, \delta)$, the matrix A_ε has pairwise different eigenvalues $\lambda_1(\varepsilon), \dots, \lambda_n(\varepsilon)$ in (4.4) and is diagonalisable as

$$A_\varepsilon = S_\varepsilon \Lambda_\varepsilon S_\varepsilon^{-1}, \quad (5.4)$$

where $S_\varepsilon \in \mathbb{C}^{n \times n}$ is a nonsingular matrix whose columns are the corresponding eigenvectors, and

$$\Lambda_\varepsilon := \operatorname{diag}(\lambda_k(\varepsilon))_{1 \leq k \leq n}. \quad (5.5)$$

The matrix S_ε (which is defined up to an arbitrary nonsingular diagonal right factor) can be chosen so as to inherit from A_ε the infinite differentiability over $\varepsilon \in [0, \delta)$ and to have the matrix S from (3.10) as the limit:

$$S_0 = \lim_{\varepsilon \rightarrow 0^+} S_\varepsilon = S. \quad (5.6)$$

Since $A_\varepsilon^T = A_\varepsilon^* = S_\varepsilon^{-*} \overline{\Lambda_\varepsilon} S_\varepsilon^*$ in view of (5.4), with $(\cdot)^{-*} := ((\cdot)^{-1})^*$, the ALE (5.2) can be represented as

$$\Lambda_\varepsilon Q_\varepsilon + Q_\varepsilon \overline{\Lambda_\varepsilon} + \varepsilon^2 S_\varepsilon^{-1} \mathbf{B} \mathbf{B}^T S_\varepsilon^{-*} = 0, \quad (5.7)$$

where

$$Q_\varepsilon := (q_{jk}(\varepsilon))_{1 \leq j, k \leq n} := S_\varepsilon^{-1} P_\varepsilon S_\varepsilon^{-*} = Q_\varepsilon^* \succcurlyeq 0 \quad (5.8)$$

is an auxiliary matrix. The diagonal structure of the matrix Λ_ε in (5.5) allows the ALE (5.7) to be solved entrywise:

$$q_{jk}(\varepsilon) = -\frac{\varepsilon^2}{\lambda_j(\varepsilon) + \overline{\lambda_k(\varepsilon)}} (S_\varepsilon^{-1} \mathbf{B} \mathbf{B}^T S_\varepsilon^{-*})_{jk}, \quad j, k = 1, \dots, n. \quad (5.9)$$

Now, (4.4) implies that

$$\lambda_j(\varepsilon) + \overline{\lambda_k(\varepsilon)} = i(\omega_j - \omega_k) - \varepsilon^2(\omega_j \mu_j + \omega_k \mu_k) + o(\varepsilon^2), \quad \text{as } \varepsilon \rightarrow 0^+, \quad (5.10)$$

and hence,

$$\begin{aligned} \lambda_j(0) + \overline{\lambda_k(0)} &= \lim_{\varepsilon \rightarrow 0^+} (\lambda_j(\varepsilon) + \overline{\lambda_k(\varepsilon)}) \\ &= i(\omega_j - \omega_k) \neq 0, \quad 1 \leq j \neq k \leq n, \end{aligned} \quad (5.11)$$

in view of (4.3), while

$$\lambda_k(\varepsilon) + \overline{\lambda_k(\varepsilon)} = 2\operatorname{Re}\lambda_k(\varepsilon) \sim -2\omega_k \mu_k \varepsilon^2, \quad \text{as } \varepsilon \rightarrow 0^+. \quad (5.12)$$

By combining (5.9) with (5.11), (5.12), (5.6), it follows that

$$\lim_{\varepsilon \rightarrow 0^+} q_{jk}(\varepsilon) = \frac{\delta_{jk}}{2\omega_k \mu_k} (S^{-1} \mathbf{B} \mathbf{B}^T S^{-*})_{jk}, \quad j, k = 1, \dots, n, \quad (5.13)$$

where δ_{jk} is the Kronecker delta. Since the matrix P_ε can be recovered from (5.8) as

$$P_\varepsilon = S_\varepsilon Q_\varepsilon S_\varepsilon^*, \quad (5.14)$$

then, in view of (5.6), (5.13), it has the following limit

$$\begin{aligned}
\lim_{\varepsilon \rightarrow 0^+} P_\varepsilon &= \frac{1}{2} S \operatorname{diag} \left(\frac{1}{\omega_k \mu_k} (S^{-1} B B^T S^{-*})_{kk} \right) S^* \\
&= \frac{1}{2} R^{-1/2} V \operatorname{diag} \left(\frac{1}{\omega_k \mu_k} (V^* \sqrt{R} B B^T \sqrt{R} V)_{kk} \right) V^* R^{-1/2} \\
&= \frac{1}{2} R^{-1/2} V \operatorname{diag} \left(\frac{1}{\omega_k \mu_k} |B^T \sqrt{R} v_k|^2 \right) V^* R^{-1/2} \\
&= \frac{1}{2} R^{-1/2} \sum_{k=1}^n \frac{1}{\omega_k \mu_k} |B^T \sqrt{R} v_k|^2 v_k v_k^* R^{-1/2},
\end{aligned}$$

which uses the structure of the matrices S, V from (3.10), (3.11) and yields (5.3) due to the symmetries (3.14), (4.12). \blacksquare

The limit (5.3) depends on the coupling shape matrix M only through the matrix B in (4.2) and the quantities (4.5) and is invariant under the scaling transformation $M \mapsto \sigma M$ for any $\sigma \in \mathbb{R} \setminus \{0\}$. Also,

$$\Pi + i\Theta \succ 0,$$

which is inherited from the positive semi-definiteness of the quantum covariance matrices (2.16).

6. ASYMPTOTIC ESTIMATES AND EXACT RESULTS FOR A ONE-MODE OSCILLATOR

In the one-mode case, the results of Section 4 hold not only in the asymptotic sense, but also beyond the weak-coupling assumption. More precisely, if $n = 2$, the real antisymmetric (2×2) -matrices Θ and $M^T J M$ can be represented as

$$\Theta = \theta \mathbf{J}, \quad M^T J M = \gamma \mathbf{J} \quad (6.1)$$

in terms of $\theta, \gamma \in \mathbb{R}$ and the matrix \mathbf{J} from (2.5). In particular, if the system variables of the OQHO are the conjugate position and momentum operators q and $p := -i\partial_q$ on the Schwartz space, then

$$\theta = \frac{1}{2} \quad (6.2)$$

(see, for example, [23]). Since the matrix Θ in (6.1) satisfies $\det \Theta = \theta^2$ and hence, $\theta \neq 0$ in view of the condition $\det \Theta \neq 0$ in (3.7), then the relation (6.2) can be achieved by rescaling one of the system variables (for example, X_1) as $X_1 \mapsto \frac{1}{2\theta} X_1$ while leaving the other unchanged ($X_2 \mapsto X_2$). This allows (6.1) to be assumed to hold along with (6.2) in what follows, without loss of generality. Therefore, since $\mathbf{J}^2 = -I_2$, the matrix A_ε in (4.2) takes the form

$$A_\varepsilon = A_0 + 2\varepsilon^2 \theta \gamma \mathbf{J}^2 = A_0 - \varepsilon^2 \gamma I_2, \quad (6.3)$$

where

$$\begin{aligned}
A_0 &= 2\theta \mathbf{J} R \\
&= R^{-1/2} \sqrt{R} \mathbf{J} \sqrt{R} \sqrt{R} \\
&= \sqrt{\det R} R^{-1/2} \mathbf{J} \sqrt{R}
\end{aligned} \quad (6.4)$$

in view of the condition $R \succ 0$ in (3.7) and the identity $N \mathbf{J} N^T = (\det N) \mathbf{J}$ for any $N \in \mathbb{C}^{2 \times 2}$. With the matrix $R^{-1/2} \mathbf{J} \sqrt{R}$ being isospectral to \mathbf{J} , it follows from (2.5), (6.4) that the eigenfrequencies of A_0 are specified by

$$\omega_{1,2} = \pm \omega, \quad \omega := \sqrt{\det R} > 0. \quad (6.5)$$

Therefore, the spectrum of the matrix A_ε in (6.3) is given by

$$\lambda_{1,2}(\varepsilon) = -\varepsilon^2 \gamma \pm i\omega = \omega(-\mu \varepsilon^2 \pm i), \quad (6.6)$$

and its quadratic dependence on ε is valid not only asymptotically as in (4.4) of Theorem 1, with

$$\mu_{1,2} = \pm\mu, \quad \mu := \frac{\gamma}{\omega}, \quad (6.7)$$

but for any coupling strength ε . In view of (6.6), (6.7), the condition $\mu > 0$, which secures the Hurwitz property of A_ε for all $\varepsilon > 0$, is equivalent to

$$\gamma > 0. \quad (6.8)$$

The relations (6.3), (6.4) allow the corresponding matrix exponential in (3.16) to be represented as

$$e^{\tau A_\varepsilon} = e^{-\varepsilon^2 \gamma \tau} e^{\tau A_0}, \quad (6.9)$$

where

$$e^{\tau A_0} = R^{-1/2} e^{\tau \sqrt{\det R} \mathbf{J}} \sqrt{R} = R^{-1/2} \Sigma(\omega \tau) \sqrt{R} \quad (6.10)$$

is a T -periodic function of time τ , with the period

$$T = \frac{2\pi}{\omega} \quad (6.11)$$

expressed in terms of the eigenfrequency ω from (6.5) in accordance with (3.15). Here, we have used the property that \mathbf{J} in (2.5) is an infinitesimal generator of the group of planar rotation matrices:

$$e^{\phi \mathbf{J}} = \begin{bmatrix} \cos \phi & \sin \phi \\ -\sin \phi & \cos \phi \end{bmatrix} =: \Sigma(\phi), \quad \phi \in \mathbb{R}. \quad (6.12)$$

In (6.10), use is also made of the relation $f(SNS^{-1}) = Sf(N)S^{-1}$ for equally dimensioned complex matrices N, S , with $\det S \neq 0$ and any function f , holomorphic in a neighbourhood of the spectrum of N ; see, for example, [6]. The T -periodicity of $e^{\tau A_0}$ with respect to τ in (6.10) implies that $e^{TA_0} = I_2$, and hence,

$$\|e^{TA_\varepsilon} \Theta\|_F = e^{-\varepsilon^2 \gamma T} \|\Theta\|_F = e^{-2\pi\mu\varepsilon^2} \|\Theta\|_F \quad (6.13)$$

in view of (6.7), (6.9), (6.11), where $\|\Theta\|_F = \frac{1}{2} \|\mathbf{J}\|_F = \frac{1}{\sqrt{2}}$ (although the latter is irrelevant for quantifying the decay). Therefore, the condition

$$\varepsilon < \frac{1}{\sqrt{2\pi\mu}} \quad (6.14)$$

is necessary for the decoherence time τ_* in (3.16) to satisfy $\tau_* > T$. Indeed, if $\varepsilon \geq \frac{1}{\sqrt{2\pi\mu}}$, then (6.13) yields $\|e^{TA_\varepsilon} \Theta\|_F \leq \frac{1}{e} \|\Theta\|_F$ and hence, $\tau_* \leq T$ in view of (3.16). This implication establishes the necessity of (6.14) for $\tau_* > T$. Furthermore, the condition (6.14) becomes necessary and sufficient if the standard Frobenius norm $\|\cdot\|_F$ in (3.16) is replaced with its weighted version

$$\|N\|_R := \|\sqrt{R}N\|_F = \sqrt{\text{Tr}(N^T R N)},$$

associated with the energy matrix $R \succ 0$ of the OQHO. Indeed, in application of this norm to the CCR matrices, it follows from (6.9), (6.10) and the orthogonality of the rotation matrix (6.12) that

$$\begin{aligned} \|e^{\tau A_\varepsilon} \Theta\|_R &= e^{-\varepsilon^2 \gamma \tau} \|e^{\tau A_0} \Theta\|_R \\ &= e^{-\varepsilon^2 \gamma \tau} \|R^{-1/2} \Sigma(\omega \tau) \sqrt{R} \Theta\|_R \\ &= e^{-\varepsilon^2 \gamma \tau} \|\Sigma(\omega \tau) \sqrt{R} \Theta\|_F \\ &= e^{-\varepsilon^2 \gamma \tau} \|\sqrt{R} \Theta\|_F = e^{-\varepsilon^2 \gamma \tau} \|\Theta\|_R. \end{aligned} \quad (6.15)$$

Due to the factor $e^{-\varepsilon^2\gamma\tau}$ on the right-hand side of (6.15), which decays under the condition (6.8), an appropriately modified decoherence time τ_R (with the weighted norm $\|\cdot\|_R$ instead of $\|\cdot\|_F$ in (3.16)) takes the form

$$\tau_R = \frac{\varepsilon^{-2}}{\gamma}$$

and coincides with (4.14) since $\omega\mu = \gamma$ in view of (6.7). Accordingly, the low decoherence requirement $\tau_R \gg T$ for the one-mode oscillator on the time scale of (6.11) becomes (4.17) as a strong version of (6.14).

For completeness, we will also discuss the behaviour of the invariant real covariance matrix P_ε from (5.1). In view of (6.3) in the one-mode case being considered, the diagonalising matrix S_ε in (5.4) does not depend on ε and coincides with the matrix S from (3.10), where

$$V = [v_1 \quad v_2], \quad v_{1,2} := \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ \pm i \end{bmatrix} \quad (6.16)$$

is formed from the orthonormal eigenvectors of the matrix \mathbf{J} from (2.5), in accordance with (3.11)–(3.14) and the relations

$$2\sqrt{R}\Theta\sqrt{R} = \sqrt{R}\mathbf{J}\sqrt{R} = \omega\mathbf{J},$$

where ω is the eigenfrequency given by (6.5). Hence, the representation (5.14) takes the form

$$P_\varepsilon = SQ_\varepsilon S^* = R^{-1/2} \sum_{j,k=1}^2 q_{jk}(\varepsilon) v_j v_k^* R^{-1/2}, \quad (6.17)$$

where the matrix $Q_\varepsilon := (q_{jk}(\varepsilon))_{1 \leq j,k \leq 2}$ in (5.8) is computed by combining (5.9) and (6.6) as

$$q_{jk}(\varepsilon) = -\frac{\varepsilon^2}{\lambda_j(\varepsilon) + \lambda_k(\varepsilon)} v_j^* \sqrt{R} B B^T \sqrt{R} v_k, \quad j, k = 1, 2, \quad (6.18)$$

with

$$\lambda_k(\varepsilon) + \overline{\lambda_k(\varepsilon)} = 2\operatorname{Re}\lambda_k(\varepsilon) = -2\varepsilon^2\gamma, \quad (6.19)$$

$$\lambda_k(\varepsilon) + \overline{\lambda_{3-k}(\varepsilon)} = 2(-\varepsilon^2\gamma \pm i\omega), \quad k = 1, 2, \quad (6.20)$$

so that the asymptotic relations (5.10), (5.12) are exact in the one-mode case. Substitution of (6.18)–(6.20) into (6.17) leads to

$$P_\varepsilon = \underbrace{\frac{1}{2\gamma} |\mathbf{B}^T \sqrt{R} v_1|^2 R^{-1}}_{\Pi} + \underbrace{\varepsilon^2 R^{-1/2} \operatorname{Re} \left(\frac{1}{\varepsilon^2 \gamma - i\omega} (v_1^* \sqrt{R} B B^T \sqrt{R} v_2) v_1 v_2^* \right) R^{-1/2}}_{O(\varepsilon^2)}. \quad (6.21)$$

Here, the first term uses the property $\operatorname{Re}(v_k v_k^*) = \frac{1}{2} I_2$ of the eigenvectors in (6.16) and describes the weak-coupling limit (5.3) for the invariant covariance matrix, while the second term in (6.21) calculates the remainder in closed form.

7. A NUMERICAL EXAMPLE WITH A TWO-MODE OSCILLATOR

For a numerical illustration, consider a two-mode ($n = 4$) OQHO with a three-channel ($m = 6$) external field. The system variables are two conjugate position-momentum pairs $(q_1, p_1), (q_2, p_2)$ which are assembled into the vector $X := [q_1, q_2, p_1, p_2]^T$ in (2.1) with the CCR matrix

$$\Theta = \frac{1}{2} \mathbf{J} \otimes I_2, \quad (7.1)$$

where \mathbf{J} is given by (2.5). The energy and coupling shape matrices are generated randomly (subject to the conditions of Theorem 2):

$$R := \begin{bmatrix} 1.3522 & 1.2976 & -0.5225 & -2.7819 \\ 1.2976 & 6.0400 & 1.1741 & -1.4901 \\ -0.5225 & 1.1741 & 2.2582 & 1.5566 \\ -2.7819 & -1.4901 & 1.5566 & 6.7739 \end{bmatrix}, \quad M := \begin{bmatrix} -1.7423 & -1.6364 & -0.3020 & -0.3483 \\ 0.2053 & 0.0173 & 1.8136 & 1.4126 \\ 1.1929 & 0.8284 & 0.9149 & 1.5024 \\ -0.8028 & 0.2177 & -0.0571 & 0.7304 \\ -1.2656 & -1.9092 & 1.3094 & 0.4908 \\ -0.1493 & -0.5368 & -1.0447 & -0.5861 \end{bmatrix}. \quad (7.2)$$

The positive eigenfrequencies (3.8) of the matrix A_0 for the uncoupled oscillator in (2.8) are

$$\omega_1 = 7.2046, \quad \omega_2 = 0.3729,$$

and the corresponding orthonormal eigenvectors from (3.13) are

$$v_1 = \begin{bmatrix} 0.1046 - 0.2450i \\ 0.6592 + 0.0000i \\ 0.2323 + 0.1748i \\ -0.0234 + 0.6399i \end{bmatrix}, \quad v_2 = \begin{bmatrix} 0.6550 + 0.0000i \\ -0.1053 - 0.2332i \\ 0.0283 + 0.6440i \\ 0.2431 - 0.1759i \end{bmatrix}.$$

The calculation of the quantities (4.5), associated with these eigenvectors, yields

$$\mu_1 = 0.1765, \quad \mu_2 = 5.2214,$$

and the leading coefficient of the asymptotic approximation on the right-hand side of (4.13) takes the value

$$\min_{k=1,2} (\omega_k \mu_k) = 1.2714.$$

A comparison of the exact value of the leading Lyapunov exponent with its approximation is provided by Fig. 1. The resulting thresholds for the coupling strength parameter in




FIGURE 1. The exact value $\ln \mathbf{r}(e^{A_\varepsilon})$ of the leading Lyapunov exponent for the matrix A_ε of the OQHO in (4.2) as a function of the coupling strength parameter ε (dashed line) in comparison with its asymptotic approximation $-\varepsilon^2 \min_{k=1,2} (\omega_k \mu_k)$ from (4.13) (solid line) for the two-mode OQHO example (7.1), (7.2).

(4.15), (4.16) are

$$\hat{\varepsilon} = 0.2161, \quad \tilde{\varepsilon} = 0.1746.$$

As Fig. 1 shows, the requirement $\varepsilon \ll \hat{\varepsilon}$ (or $\varepsilon \ll \tilde{\varepsilon}$) for securing a low decoherence level for the OQHO, obtained in the weak-coupling limit, is consistent with the validity range of this approximation in this example.

8. DECOHERENCE CONTROL BY INTERCONNECTION

We will now apply the results of the previous sections to a decoherence control setting for two OQHOs (interpreted, for example, as a quantum plant and a quantum controller) which, in addition to their interaction with external bosonic fields, are coupled to each other in a coherent (measurement-free) fashion. The latter involves a direct energy coupling and an indirect field-mediated coupling [31] as shown in Fig. 2. In this fully quantum feedback




FIGURE 2. An interconnection of two OQHOs, which have external input quantum Wiener processes w_1 , w_2 and interact with each other both directly (through the energy coupling shown as a double arrow) and indirectly in a field-mediated fashion through quantum Ito processes y_1 , y_2 at their corresponding outputs.

interconnection, the external fields are modelled by $\frac{m_1}{2}$ - and $\frac{m_2}{2}$ -channel quantum Wiener processes w_1 , w_2 (with even m_1, m_2) on symmetric Fock spaces $\mathfrak{F}_1, \mathfrak{F}_2$, respectively. These processes form an augmented quantum Wiener process

$$W := \begin{bmatrix} w_1 \\ w_2 \end{bmatrix} \quad (8.1)$$

on the composite Fock space $\mathfrak{F} := \mathfrak{F}_1 \otimes \mathfrak{F}_2$ and, similarly to (2.3), have the following Ito tables

$$dw_k dw_k^T = \Omega_k dt, \quad dW dW^T = \Omega dt, \quad k = 1, 2, \quad (8.2)$$

with the quantum Ito matrices $\Omega_1, \Omega_2, \Omega$ given by

$$\begin{aligned} \Omega_k &:= I_{m_k} + iJ_k, & J_k &:= \mathbf{J} \otimes I_{m_k/2}, \\ \Omega &:= \text{blockdiag}(\Omega_k)_{k=1,2} = I_m + iJ, & J &:= \text{blockdiag}(J_k)_{k=1,2}, & m &:= m_1 + m_2, \end{aligned} \quad (8.3)$$

where \mathbf{J} is the matrix from (2.5). The constituent OQHOs are endowed with initial spaces $\mathfrak{H}_1, \mathfrak{H}_2$ and even numbers n_1, n_2 of dynamic variables, acting on the space $\mathfrak{H} := \mathfrak{H}_0 \otimes \mathfrak{F}$ (with $\mathfrak{H}_0 := \mathfrak{H}_1 \otimes \mathfrak{H}_2$ the initial space of the composite system) and assembled into vectors x_1, x_2 which form the augmented vector

$$X := \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}. \quad (8.4)$$

In accordance with (2.1), the one-point CCR matrices $\Theta_k = -\Theta_k^T \in \mathbb{R}^{n_k \times n_k}$ of the OQHOs specify the relations

$$[x_k, x_k^T] = 2i\Theta_k, \quad [X, X^T] = 2i\Theta, \quad \Theta := \text{blockdiag}(\Theta_k)_{k=1,2}, \quad k = 1, 2. \quad (8.5)$$

Here, the block-diagonal structure of the augmented CCR matrix Θ comes from the commutativity

$$[x_1, x_2^T] = 0 \quad (8.6)$$

of the dynamic variables of the constituent OQHOs as operators acting initially (at time $t = 0$) on different spaces $\mathfrak{H}_1, \mathfrak{H}_2$ and since the system-field evolution preserves the CCRs. The direct coupling of the OQHOs is modelled by complementing the individual Hamiltonians

$\frac{1}{2}x_k^T R_k x_k$ of the OQHOs, specified by their energy matrices $R_k = R_k^T \in \mathbb{R}^{n_k \times n_k}$ for $k = 1, 2$, with an additional term

$$x_1^T R_{12} x_2 = x_2^T R_{21} x_1 \quad (8.7)$$

parameterised by $R_{12} = R_{21}^T \in \mathbb{R}^{n_1 \times n_2}$. The equality (8.7) uses the commutativity (8.6). The indirect coupling of the OQHOs in Fig. 2 is mediated by their $\frac{p_1}{2}$ - and $\frac{p_2}{2}$ -channel output fields y_1, y_2 (with p_1, p_2 even) which are quantum Ito processes whose Heisenberg dynamics are governed by the linear QSDEs

$$dx_k = (A_k x_k + F_k x_{3-k}) dt + B_k dw_k + E_k dy_{3-k}, \quad (8.8)$$

$$dy_k = C_k x_k dt + D_k dw_k, \quad k = 1, 2. \quad (8.9)$$

The matrices

$$A_k \in \mathbb{R}^{n_k \times n_k}, B_k \in \mathbb{R}^{n_k \times m_k}, C_k \in \mathbb{R}^{p_k \times n_k}, D_k \in \mathbb{R}^{p_k \times m_k}, E_k \in \mathbb{R}^{n_k \times p_{3-k}}, F_k \in \mathbb{R}^{n_k \times n_{3-k}}$$

are parameterised as

$$A_k = 2\Theta_k(R_k + M_k^T J_k M_k + L_k^T \tilde{J}_{3-k} L_k), \quad (8.10)$$

$$B_k = 2\Theta_k M_k^T, \quad (8.11)$$

$$C_k = 2D_k J_k M_k, \quad (8.12)$$

$$E_k = 2\Theta_k L_k^T, \quad (8.13)$$

$$F_k = 2\Theta_k R_{k,3-k}, \quad (8.14)$$

where

$$\tilde{J}_k := D_k J_k D_k^T, \quad k = 1, 2, \quad (8.15)$$

which can be obtained by using the quantum feedback network formalism [4, 10]. Here, $M_k \in \mathbb{R}^{m_k \times n_k}$, $L_k \in \mathbb{R}^{p_{3-k} \times n_k}$ are the matrices of coupling of the k th OQHO to the corresponding external input field w_k and the output y_{3-k} of the other OQHO, respectively. Also, each of the feedthrough matrices D_k in (8.9) is associated with a particular selection of the component output fields and is formed from conjugate pairs of rows of a permutation matrix of order m_k , so that $p_k \leq m_k$, with

$$D_k D_k^T = I_{p_k}, \quad k = 1, 2.$$

The combined QSDEs (8.8), (8.9) describe an augmented OQHO with $n := n_1 + n_2$ dynamic variables in (8.4), which have the one-point CCR matrix Θ in (8.5) and are driven by the $\frac{m}{2}$ -channel quantum Wiener process W in (8.1)–(8.3) according to the QSDE (2.6) with the matrices

$$A = \begin{bmatrix} A_1 & F_1 + E_1 C_2 \\ F_2 + E_2 C_1 & A_2 \end{bmatrix}, \quad B = \begin{bmatrix} B_1 & E_1 D_2 \\ E_2 D_1 & B_2 \end{bmatrix}. \quad (8.16)$$

The energy and coupling matrices of the resulting closed-loop OQHO in Fig. 2 are computed by substituting (8.10)–(8.15) into (8.16) and comparing the result with (2.7) in combination with (8.3), (8.5):

$$R = \begin{bmatrix} R_1 & R_{12} + \frac{1}{2}(L_1^T C_2 + C_1^T L_2) \\ R_{21} + \frac{1}{2}(C_2^T L_1 + L_2^T C_1) & R_2 \end{bmatrix} = R_0 + \tilde{R}, \quad (8.17)$$

$$M = \begin{bmatrix} M_1 & D_1^T L_2 \\ D_2^T L_1 & M_2 \end{bmatrix}. \quad (8.18)$$

Here,

$$R_0 := \begin{bmatrix} R_1 & R_{12} \\ R_{21} & R_2 \end{bmatrix} \quad (8.19)$$

is the energy matrix which the closed-loop system would have if the indirect field-mediated coupling between the constituent OQHOs were removed (that is, in the case when $L_1 = 0$, $L_2 = 0$). Accordingly, the additional term

$$\tilde{R} := R - R_0 = \begin{bmatrix} 0 & L_1^T D_2 J_2 M_2 - M_1^T J_1 D_1^T L_2 \\ L_2^T D_1 J_1 M_1 - M_2^T J_2 D_2^T L_1 & 0 \end{bmatrix} \quad (8.20)$$

in (8.17) originates from the field-mediated coupling between the OQHOs. With the feedthrough matrices D_1 , D_2 being fixed, the closed-loop coupling matrix M in (8.18) is a linear function of the coupling matrices M_1 , L_1 , M_2 , L_2 , while \tilde{R} in (8.20) depends on them in a quadratic fashion. The role of the matrix (2.8) for the composite system will now be played by

$$A_0 := 2\Theta R_0 = 2 \begin{bmatrix} \Theta_1 R_{11} & \Theta_1 R_{12} \\ \Theta_2 R_{21} & \Theta_2 R_{22} \end{bmatrix}. \quad (8.21)$$

In application to the block-diagonal matrix Θ in (8.5) and the matrix R_0 in (8.19), the condition (3.7) is equivalent to

$$R_0 \succ 0, \quad \det \Theta_k \neq 0, \quad k = 1, 2, \quad (8.22)$$

and guarantees that the spectrum of the matrix A_0 in (8.21) is purely imaginary and specified by the eigenfrequencies $\omega_1, \dots, \omega_n \in \mathbb{R}$ as before. The relations (3.10) are modified as

$$A_0 = iS\tilde{U}S^{-1}, \quad S := R_0^{-1/2}V, \quad \tilde{U} := \text{diag}(\omega_k)_{1 \leq k \leq n}, \quad (8.23)$$

where, this time, the unitary matrix V in (3.11) consists of the eigenvectors v_1, \dots, v_n of the Hermitian matrix

$$-2i\sqrt{R_0}\Theta\sqrt{R_0} = V\tilde{U}V^*. \quad (8.24)$$

In accordance with the weak-coupling framework of Section 4, suppose the coupling matrices

$$M_k := \varepsilon M_k, \quad L_k := \varepsilon L_k, \quad k = 1, 2, \quad (8.25)$$

are specified by a coupling strength parameter $\varepsilon \geq 0$ and appropriately dimensioned coupling shape matrices M_k , L_k . Then (8.18), (8.20) are represented as $M = \varepsilon M$, $\tilde{R} = \varepsilon^2 \tilde{R}$ in terms of

$$M := \begin{bmatrix} M_1 & D_1^T L_2 \\ D_2^T L_1 & M_2 \end{bmatrix}, \quad (8.26)$$

$$R := \begin{bmatrix} 0 & L_1^T D_2 J_2 M_2 - M_1^T J_1 D_1^T L_2 \\ L_2^T D_1 J_1 M_1 - M_2^T J_2 D_2^T L_1 & 0 \end{bmatrix}, \quad (8.27)$$

with $R = R^T \in \mathbb{R}^{n \times n}$, and hence, the matrices (2.7) of the closed-loop OQHO depend on ε as

$$A_\varepsilon = A_0 + 2\varepsilon^2 \Theta(R + M^T J M), \quad B_\varepsilon = \varepsilon B, \quad B := 2\Theta M^T, \quad (8.28)$$

with A_0 given by (8.21). The following theorem provides an appropriate adaptation of Theorem 1.

Theorem 4. *Suppose the CCR and energy matrices of the constituent OQHOs satisfy (8.22). Also, suppose the eigenfrequencies $\omega_1, \dots, \omega_n$ of the matrix A_0 in (8.21) are pairwise different. Then for all sufficiently small values of the coupling strength parameter ε in (8.25), the matrix A_ε in (8.28) has different eigenvalues $\lambda_1(\varepsilon), \dots, \lambda_n(\varepsilon)$ which, appropriately numbered, behave asymptotically as*

$$\lambda_k(\varepsilon) = \omega_k(i(1 + \varepsilon^2 \sigma_k) - \varepsilon^2 \mu_k) + o(\varepsilon^2), \quad \text{as } \varepsilon \rightarrow 0+. \quad (8.29)$$

Here,

$$\mu_k := -iv_k^* R_0^{-1/2} M^T J M R_0^{-1/2} v_k, \quad (8.30)$$

$$\sigma_k := v_k^* R_0^{-1/2} R R_0^{-1/2} v_k \quad k = 1, \dots, n, \quad (8.31)$$

are real-valued quantities using the columns v_1, \dots, v_n of the unitary matrix (3.11), associated with (8.24), and the matrices R_0, M, R from (8.19), (8.26), (8.27). \square

Proof. The relation (8.29) is established by repeating the proof of Theorem 1 almost verbatim, except that, in application to the matrix A_ε in (8.28), the similarity transformation (4.6) is modified as

$$\begin{aligned} S^{-1}A_\varepsilon S &= i\tilde{U} + 2\varepsilon^2 S^{-1}\Theta(R + M^T J M)S \\ &= i\tilde{U} + 2\varepsilon^2 V^* \sqrt{R_0} \Theta (R + M^T J M) R_0^{-1/2} V \\ &= i\tilde{U} + 2\varepsilon^2 V^* \sqrt{R_0} \Theta \sqrt{R_0} R_0^{-1/2} (R + M^T J M) R_0^{-1/2} V \\ &= i\tilde{U} + i\varepsilon^2 V^* V \tilde{U} V^* R_0^{-1/2} (R + M^T J M) R_0^{-1/2} V \\ &= i\tilde{U} + i\varepsilon^2 \tilde{U} V^* R_0^{-1/2} (R + M^T J M) R_0^{-1/2} V \end{aligned} \quad (8.32)$$

by using (8.23), (8.24). Accordingly, (4.7), leading to (8.30) with R_0 from (8.19) instead of R , is complemented by

$$(i\tilde{U} V^* R_0^{-1/2} R R_0^{-1/2} V)_{kk} = i\omega_k v_k^* R_0^{-1/2} R R_0^{-1/2} v_k = i\omega_k \sigma_k$$

in view of (8.31), which, together with (8.32), yields (8.29). The quantities σ_k are also real-valued since R in (8.27) is a real symmetric matrix. \blacksquare

The asymptotic relations (8.29) show that the quantities μ_1, \dots, μ_n are responsible for the stability of the closed-loop OQHO for all sufficiently small values of the coupling strength $\varepsilon > 0$ and participate in the Lyapunov exponents and decoherence time estimates of Section 4. More precisely, this stability is secured by the condition (4.10) from the proof of Theorem 2. The representation (8.30) allows μ_1, \dots, μ_n to be found as the diagonal entries of the Hermitian matrix

$$K := -iV^* R_0^{-1/2} M^T J M R_0^{-1/2} V, \quad (8.33)$$

which, in view of (8.26), depends in a quadratic fashion on the coupling shape matrices M_1, L_1, M_2, L_2 . This can be used for a rational choice of the coupling shape in order to achieve given specifications on the stability margins and decoherence levels for the OQHO interconnection in the weak-coupling framework.

In the absence of direct coupling between the OQHOs, when $R_{12} = 0$ in (8.7), the matrix R_0 in (8.19) is block-diagonal:

$$R_0 = \text{blockdiag}_{k=1,2}(R_k), \quad (8.34)$$

so that the condition $R_0 \succ 0$ in (8.22) is equivalent to $R_k \succ 0$ for $k = 1, 2$. By combining (8.34) with the block-diagonal structure of the CCR matrix Θ in (8.5), the matrix V in (8.23), (8.24) takes the form

$$V = \text{blockdiag}_{k=1,2}(V_k), \quad (8.35)$$

where $V_k \in \mathbb{C}^{n_k \times n_k}$ is a unitary matrix whose columns are the eigenvectors of the Hermitian matrix

$$-2i\sqrt{R_k} \Theta_k \sqrt{R_k} = V_k \tilde{U}_k V_k^*, \quad k = 1, 2,$$

with \tilde{U}_k a diagonal matrix formed from the eigenfrequencies of $2\Theta_k R_k$. In this case, the block-diagonal structure of the matrices J, R_0, V in (8.3), (8.34), (8.35) allows the matrix K in (8.33) to be computed as

$$K = \begin{bmatrix} K_1 & * \\ * & K_2 \end{bmatrix}, \quad K_j = -iV_j^* R_j^{-1/2} (M_j^T J_j M_j + L_j^T \tilde{J}_{3-j} L_j) R_j^{-1/2} V_j, \quad j = 1, 2, \quad (8.36)$$

where (8.15), (8.26) are also used, with the off-diagonal blocks “*” of the matrix K in (8.36) being irrelevant for (8.30).

9. CONCLUSION

For quantum harmonic oscillators, we have discussed their isolated and open dynamics, including the role of the system-field coupling matrix in the energy exchange with the environment and the decay in the two-point CCRs of the system variables. The decay time has been proposed as a decoherence measure for OQHOs and equipped with an upper bound using algebraic Lyapunov inequalities. For the class of OQHOs with a nonsingular CCR matrix and a positive definite energy matrix, with different eigenfrequencies in the absence of coupling, we have applied spectrum perturbation techniques to investigating the asymptotic behaviour of the leading Lyapunov exponent for the dynamics matrix of the OQHO with a small coupling strength parameter and a given coupling shape matrix. A threshold value has been established for the coupling strength in order to guarantee that the oscillator retains the dynamic properties of its uncoupled version over a large number of cycles before the decay sets in. The asymptotic properties of the covariance matrix of the invariant Gaussian quantum state of the system in the weak-coupling limit has also been discussed. These results have been demonstrated for one- and two-mode oscillators with multichannel external fields and also applied to a coherent feedback interconnection of OQHOs with direct and field-mediated coupling. The findings of the paper can be used for the formulation of performance criteria for quantum feedback networks [4, 10] requiring a controlled isolation from the environment for quantum information processing applications [15]. Another potential application of decoherence measures, discussed in the paper, is the robustness of coherent quantum control architectures [11, 13, 16, 24, 26, 31] to unmodelled noises.

REFERENCES

- [1] H.-P.Breuer, and F.Petruccione, *The Theory of Open Quantum Systems*, Clarendon Press, Oxford, 2006.
- [2] A.O.Caldeira, and A.J.Leggett, Influence of damping on quantum interference: An exactly soluble model, *Phys. Rev. A*, vol. 31, no. 2, 1985, pp. 1059–1066.
- [3] C.W.Gardiner, and P.Zoller, *Quantum Noise*. Springer, Berlin, 2004.
- [4] J.Gough, and M.R.James, Quantum feedback networks: Hamiltonian formulation, *Commun. Math. Phys.*, vol. 287, 2009, pp. 1109–1132.
- [5] M. de Gosson, *Symplectic Geometry and Quantum Mechanics*, Birkhäuser, Basel, 2006.
- [6] N.J.Higham, *Functions of Matrices*, SIAM, Philadelphia, 2008.
- [7] A.S.Holevo, *Statistical Structure of Quantum Theory*, Springer, Berlin, 2001.
- [8] R.A.Horn, and C.R.Johnson, *Matrix Analysis*, Cambridge University Press, New York, 2007.
- [9] R.L.Hudson, and K.R.Parthasarathy, Quantum Ito’s formula and stochastic evolutions, *Commun. Math. Phys.*, vol. 93, 1984, pp. 301–323.
- [10] M.R.James, and J.E.Gough, Quantum dissipative systems and feedback control design by interconnection, *IEEE Trans. Automat. Contr.*, vol. 55, no. 8, 2010, pp. 1806–1821.
- [11] M.R.James, H.I.Nurdin, and I.R.Petersen, H^∞ control of linear quantum stochastic systems, *IEEE Trans. Automat. Contr.*, vol. 53, no. 8, 2008, pp. 1787–1803.
- [12] H.Kwakernaak, and R.Sivan, *Linear Optimal Control Systems*, Wiley, New York, 1972.
- [13] A.I.Maalouf, and I.R.Petersen, Coherent LQG control for a class of linear complex quantum systems, IEEE European Control Conference, Budapest, Hungary, 23–26 August 2009, pp. 2271–2276.
- [14] J.R.Magnus, On differentiating eigenvalues and eigenvectors, *Econometric Theory*, vol. 1, no. 2, 1985, pp. 179–191.
- [15] M.A.Nielsen, and I.L.Chuang, *Quantum Computation and Quantum Information*, Cambridge University Press, Cambridge, 2000.
- [16] H.I.Nurdin, M.R.James, and I.R.Petersen, Coherent quantum LQG control, *Automatica*, vol. 45, 2009, pp. 1837–1846.
- [17] H.I.Nurdin, and N.Yamamoto, *Linear Dynamical Quantum Systems*, Springer, Netherlands, 2017.
- [18] K.R.Parthasarathy, *An Introduction to Quantum Stochastic Calculus*, Birkhäuser, Basel, 1992.
- [19] K.R.Parthasarathy, What is a Gaussian state? *Commun. Stoch. Anal.*, vol. 4, no. 2, 2010, pp. 143–160.
- [20] K.R.Parthasarathy, and K.Schmidt, *Positive Definite Kernels, Continuous Tensor Products, and Central Limit Theorems of Probability Theory*, Springer-Verlag, Berlin, 1972.
- [21] I.R.Petersen, A direct coupling coherent quantum observer, IEEE MSC 2014, Nice/Antibes, France, 8–10 October 2014, pp. 1960–1963.
- [22] I.R.Petersen, Quantum linear systems theory, *Open Automat. Contr. Syst. J.*, vol. 8, 2017, pp. 67–93.

- [23] J.J.Sakurai, *Modern Quantum Mechanics*, Addison-Wesley, Reading, Mass., 1994.
- [24] A.Kh.Sichani, I.G.Vladimirov, and I.R.Petersen, A numerical approach to optimal coherent quantum LQG controller design using gradient descent, *Automatica*, vol. 85, 2017, pp. 314–326.
- [25] W.G.Unruh, Maintaining coherence in quantum computers, *Phys. Rev. A*, vol. 51, no. 2, 1995, pp. 992–997.
- [26] I.G.Vladimirov, and I.R.Petersen, A quasi-separation principle and Newton-like scheme for coherent quantum LQG control, *Syst. Contr. Lett.*, vol. 62, no. 7, 2013, pp. 550–559.
- [27] I.G.Vladimirov, I.R.Petersen, and M.R.James, Multi-point Gaussian states, quadratic–exponential cost functionals, and large deviations estimates for linear quantum stochastic systems, *Appl. Math. Optim.*, vol. 83, 2021, pp. 83–137 (published 24 July 2018).
- [28] J.Williamson, On the algebraic problem concerning the normal forms of linear dynamical systems, *Am. J. Math.*, vol. 58, no. 1, 1936, pp. 141–163.
- [29] J.Williamson, On the normal forms of linear canonical transformations in dynamics, *Am. J. Math.*, vol. 59, no. 3, 1937, pp. 599–617.
- [30] N.Yamamoto, Pure Gaussian state generation via dissipation: a quantum stochastic differential equation approach, *Philos. Trans. R. Soc. Lond. Ser. A, Math. Phys. Eng. Sci.*, vol. 370, 2012, pp. 5324–5337.
- [31] G.Zhang, and M.R.James, Direct and indirect couplings in coherent feedback control of linear quantum systems, *IEEE Trans. Automat. Contr.*, vol. 56, no. 7, 2011, 1535–1550.

SCHOOL OF ENGINEERING, AUSTRALIAN NATIONAL UNIVERSITY, ACT 2601, AUSTRALIA
Email address: igor.g.vladimirov@gmail.com, i.r.petersen@gmail.com