

Necessary first and second order optimality conditions for a fractional order differential equation with state delay

Jasarat J. Gasimov, Nazim I. Mahmudov

Department of Mathematics, Eastern Mediterranean University, Mersin 10, 99628, T.R. North Cyprus, Turkey

Abstract

In this research paper, we examine an optimal control problem involving a dynamical system governed by a nonlinear Caputo fractional time-delay state equation. The primary objective of this study is to obtain the necessary conditions for optimality, both the first and second order, for the Caputo fractional time-delay optimal control problem. We derive the first-order necessary condition for optimality for the given fractional time-delay optimal control problem. Moreover, we focus on a case where the Pontryagin maximum principle degenerates, meaning that it is satisfied in a trivial manner. Consequently, we proceed to derive the second order optimality conditions specific to the problem under investigation. At the end illustrative examples are provided.

Keywords: retarded differential equation; a constant delay; pontryagin maximum principle; optimal control

1. Introduction

Fractional differential equations have attracted significant attention in the last 30 years [2, 3, 4, 5, 6, 7, 16, 22, 24, 29, 35, 36, 37]. This increased interest can be attributed to the advancements in fractional calculus theory and its diverse applications. One area of active research involves studying optimal control problems for systems incorporating fractional Riemann-Liouville and Caputo derivatives. These problems have wide-ranging applications in various fields such as biology [32], chemistry [9], economics [14], electrical engineering [17], and medicine [18]. It is worth noting that fractional optimal control problems, which are described by ordinary fractional differential equations, can be considered as an extension of traditional optimal control problems.

Fractional optimal control problems, which can be represented by ordinary fractional differential equations, can be considered as an advancement or an expansion of conventional optimal control problems.

The Pontryagin maximum principle is a key outcome in the theory of essential optimality conditions at the first order. It was originally demonstrated in [21] for optimal control problems involving ordinary differential equations. Subsequently, different essential optimality conditions have been derived for a range of systems, encompassing both first and higher order conditions [10, 21, 20, 33, 34].

An admissible control is referred to as a Pontryagin extremal if it satisfies the Pontryagin maximum condition. The maximum principle implies that any optimal control is a Pontryagin extremal. Thus, the problem of finding the optimal control is essentially reduced to selecting the best control among the Pontryagin extremals. If there exists an optimal control in the optimization problem and the Pontryagin extremal is unique, then it is the optimal control. However, it is important to note that even in simple cases, non-optimal controls can satisfy the Pontryagin maximum principle. In such situations, the maximum principle cannot effectively eliminate all non-optimal controls.

The process of narrowing down a subset of Pontryagin extremals that can be deemed optimal is a crucial and challenging task. Its complexity stems from the fact that the maximum principle itself serves as a very strong necessary condition for optimality.

*Corresponding author

**Corresponding author

Email addresses: jasarat.gasimov@emu.edu.tr (Jasarat J. Gasimov), nazim.mahmudov@emu.edu.tr (Nazim I. Mahmudov)

Consequently, investigating scenarios where the Pontryagin maximum principle fails to provide a unique determination of the optimal control has become a key focus in the advancement of optimal systems theory. Therefore, the need arises to develop new necessary conditions for optimality that can narrow down the set of controls that satisfy the Pontryagin maximum principle.

The paper [38] addresses the minimization problem of an integral functional with a non-convex control-dependent integrand. The focus is on solutions of a Riemann-Liouville fractional differential control system with mixed non-convex feedback constraints on the control. In [39], optimal control problems of fractional order are examined, where the dynamic control system involves derivatives of both integer and fractional orders, and the final time is not fixed. Necessary optimality conditions are derived for the triplet of state/control/terminal time. The cases with finite time constraints are also considered. It is demonstrated that, under suitable assumptions, the derived necessary optimality conditions become sufficient. In the paper [35], a necessary first-order optimality condition is obtained in the form of the Pontryagin maximum principle. Additionally, in the case of degenerate maximum principle, a necessary optimality condition is derived for singular controls according to the Pontryagin maximum principle. It should be noted that these results are obtained using the fundamental matrix. If the Pontryagin maximum principle holds along the control trajectory without degeneracy, then the findings of [8, 35] consider this control as a potential candidate for optimality. Hence, there is a need for new necessary optimality conditions that can effectively single out this control from the set of candidates for optimality.

This paper presents one of the potential approaches for establishing higher-order necessary optimality conditions for fractional optimal control problems based on the Caputo sense.

We investigate an optimal control problem for a dynamic system governed by a nonlinear differential equation, incorporating the Caputo fractional derivative of order $\alpha \in (0, 1)$. The control process occurs within a fixed and finite time interval. The objective is to minimize a Bolza-type cost functional consisting of two components. The first component assesses the state vector of the system at a predetermined terminal time T , while the second component involves the integral evaluation of a control over the entire time interval $[0, T]$. Notably, the second term corresponds to the Riemann-Liouville integral of order $\beta \geq \alpha$. The set of control functions assumes nonempty and compact values.

The presented optimal control problem is investigated using a novel variation of the increment method, which extensively employs the concept of an adjoint integral equation. It is worth noting that the solution of this integral equation does not exhibit any singularity.

2. Preliminaries

In this section, we will begin by providing concise explanations of key terms derived from fractional calculus that hold significance in this research.

Let R^n and $R^{n \times n}$ denote the spaces of n -dimensional vectors and $n \times n$ matrices, respectively, and let $E \in R^{n \times n}$ be the identity matrix. A norm is defined in R^n by $\|\cdot\|$, and in $R^{n \times n}$ by an appropriate norm for matrices. Consider the intervals $[0, T] \subset R$ and $[-h, T] \subset R$, where $T > 0$ and $h > 0$, and Let Y be either R^n or $R^{n \times n}$.

In the space $L^\infty([0, T], Y)$, we have a set of Lebesgue measurable functions $\varphi : [0, T] \rightarrow Y$ such that $\|\varphi(\cdot)\|_{[0, T]} < \infty$. Here, $\|\varphi(\cdot)\|_{[0, T]}$ is defined as the essential supremum of the norm of $\varphi(t)$ over all $t \in [0, T]$. Essentially, it measures the largest possible norm value attained by $\varphi(t)$ in that interval.

Furthermore, in the space $C([0, T], Y)$, we have a set of functions $\varphi : [0, T] \rightarrow Y$ such that $\|\varphi(\cdot)\| = \max_{t \in [0, T]} \|\varphi(t)\|$. In other words, it represents the maximum norm value achieved by $\varphi(t)$ over the interval $[0, T]$.

We also have the space of summable functions denoted as $L^1([0, T], Y)$, which encompasses functions that are integrable over the interval $[0, T]$ with respect to the appropriate norm in Y .

Definition 2.1. ([29]) The fractional integral of order $\alpha > 0$ for a function $\varphi : [0, T] \rightarrow Y$ is defined by

$$(I_{0+}^\alpha \varphi)(t) = \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} \varphi(\tau) d\tau, \quad t > 0,$$

where $\Gamma(\cdot)$ is the well-known Euler's gamma function.

Definition 2.2. ([29]) The Riemann-Liouville fractional derivative of order $0 < \alpha \leq 1$ for a function $\varphi(\cdot) \in L^\infty([0, T], Y)$ is defined by

$$({}^{RL}D_{0+}^\alpha \varphi)(t) = \frac{1}{\Gamma(1-\alpha)} \frac{d}{dt} \int_0^t (t-\tau)^{-\alpha} \varphi(\tau) d\tau, \quad t > 0,$$

Definition 2.3. ([29]) The Caputo fractional derivative of order $0 < \alpha \leq 1$ for a function $\varphi(\cdot) \in L^\infty([0, T], Y)$ is defined by

$$({}^CD_{0+}^\alpha \varphi)(t) = \frac{1}{\Gamma(1-\alpha)} \int_0^t (t-\tau)^{-\alpha} \frac{d}{d\tau} \varphi(\tau) d\tau, \quad t > 0,$$

The relationship between the Caputo and Riemann-Liouville fractional differentiation operators for the function $\varphi(\cdot) \in L^\infty([0, T], Y)$ can be described as follows:

$${}^CD_{0+}^\alpha \varphi(t) = {}^{RL}D_{0+}^\alpha (\varphi(t) - \varphi(0)), \quad \alpha \in (0, 1].$$

We denote

$$AC_\infty^\alpha([0, T], Y) = \{y(\cdot) | y : [0, T] \rightarrow Y, y(t) = y(0) + (I_{0+}^\alpha \varphi)(t), \quad t \in [0, T]\}$$

Lemma 2.1. ([29]) For any $y(t) \in AC_\infty^\alpha([0, T], Y)$, the value $({}^CD_{0+}^\alpha y)(t)$ is correctly defined for a.e. $t \in [0, T]$. Furthermore, the inclusion $({}^CD_{0+}^\alpha y)(\cdot) \in L^\infty([0, T], Y)$ holds (i.e., there exists $\varphi(\cdot) \in L^\infty([0, T], Y)$ such that $\varphi(t) = ({}^CD_{0+}^\alpha y)(t)$ for a.e. $t \in [0, T]$) and

$$(I_{0+}^\alpha ({}^CD_{0+}^\alpha y)(t))(t) = y(t) - y(0), \quad t \in [0, T].$$

Lemma 2.2. ([29]) If $\alpha \in (0, 1)$ and $\varphi(\cdot) \in L^1([0, T], Y)$, then $(D_{0+}^\alpha ({}^CI_{0+}^\alpha y)(t))(t) = \varphi(t)$, a.e. $t \in [0, T]$.

Lemma 2.3. ([35]) Let Y be Banach space and suppose $x \in C([-h, T], Y)$ satisfies the following inequality

$$\|y(t)\| \leq a(t) + b \int_0^t (t-s)^{(\beta-1)} \|y(s)\| ds + c \int_0^t (t-s)^{(\beta-1)} \|y_h\|_C ds \quad 0 \leq t \leq T, h > 0$$

$$y(t) = \psi(t) \quad -h \leq t \leq 0$$

$\psi \in C, 0 < \beta \leq 1$ and constants, $a, b, c \geq 0$. Then there exists constant $M > 0$ (independent on a and ψ) such that

$$\|y(t)\| \leq M(a(t) + \|\psi\|_C) \quad 0 \leq t \leq T.$$

Note: $\|y_h\|_C = \sup_{0 \leq \theta \leq h} \|y(t-\theta)\|$.

Lemma 2.4. ([37]) For an arbitrary function $a(\cdot) \in L^\infty(0, T)$, any of its Lebesgue points $\theta \in (0, T)$, and any numbers α, ε , $0 < \alpha < 1$, $0 < \varepsilon < T - \theta$, the equality

$$\int_\theta^{\theta+\varepsilon} (T-t)^{\alpha-1} (t-\theta)^\alpha a(t) dt = \frac{(T-\theta)^{\alpha-1} a(\theta)}{\alpha+1} \varepsilon^{\alpha+1} + o(\varepsilon^{\alpha+1}),$$

holds, where $\lim_{\varepsilon \rightarrow 0} \frac{o(\varepsilon^{\alpha+1})}{\varepsilon^{\alpha+1}} = 0$.

Lemma 2.5. ([37]) For an arbitrary function $a(\cdot) \in L^\infty(0, T)$, any of its Lebesgue point $\theta \in (0, T)$ of this function, the equality

$$\lim_{t \rightarrow \theta; t \in (\theta, T)} \frac{1}{(t-\theta)^\alpha} \int_\theta^t (t-\tau)^{\alpha-1} (t-\theta)^{\alpha-1} |a(\tau) - a(\theta)| d\tau = 0, \quad 0 < \alpha \leq 1,$$

holds.

3. Representation formula

Let us examine the subsequent nonhomogeneous Cauchy problem, which involves a linear delayed differential equation with variable coefficients and incorporates the Caputo fractional derivatives.

$$\begin{cases} {}^c D_{0+}^\alpha y(t) = a(t)y(t) + b(t)y(t - \tau) + f(t), & a.e. t \in [0, T] \\ y(0) = y_0, \\ y(t) = \varphi(t); & -h \leq t < 0, \quad h > 0. \end{cases} \quad (3.1)$$

where $a(\cdot), b(\cdot) \in L^\infty([0, T], R^{n \times n})$, $f(\cdot) \in L^\infty([0, T], R^n)$, $0 < \alpha < 1$.

This problem has a unique solution $y(\cdot) \in AC_\infty^\alpha([0, T], R^n)$.

Lemma 3.1. *The solution of (3.1) has the following representation:*

$$y(t) = \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(t, \tau) f(\tau) d\tau + F_1(t) y_0,$$

where

$$\begin{aligned} F(t, \tau) &= E + \frac{(t - \tau)^{1-\alpha}}{\Gamma(\alpha)} \int_\tau^t (t - s)^{\alpha-1} (s - \tau)^{\alpha-1} F(t, s) a(s) ds \\ &+ \frac{(t - \tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau+h}^t (t - s)^{\alpha-1} (s - \tau - h)^{\alpha-1} F(t, s) b(s) ds. \end{aligned}$$

Proof. By performing the operation of multiplying both sides of equation (3.1) by $\frac{1}{\Gamma(\alpha)}(t - \tau)^{\alpha-1}F(\tau)$ and F^1 separately, and subsequently combining the resulting equations, we can readily deduce the following outcome.

$$\begin{aligned} &\frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(\tau) \left[({}^c D_{0+}^\alpha y)(\tau) - a(\tau)y(\tau) - b(\tau)y(\tau - h) \right] d\tau + F_1 y(0) \\ &= \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(\tau) f(\tau) d\tau + F_1 y_0 \end{aligned} \quad (3.2)$$

Here, $F(t)$ remains an arbitrary $n \times n$ matrix-valued function that is integrable over the interval $[0, T]$, while F_1 is an arbitrary constant $n \times n$ matrix, $t \in (0, T]$ is a fixed point.

For a given representation

$$y(t) = y(0) + \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} ({}^c D_{0+}^\alpha y)(\tau) d\tau, \quad (3.3)$$

We modify the left-hand side of equation (3.2) using the following transformation.

$$\begin{aligned} &\frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(\tau) \left[({}^c D_{0+}^\alpha y)(\tau) - a(\tau) \left(y(0) + \frac{1}{\Gamma(\alpha)} \int_0^\tau (\tau - s)^{\alpha-1} ({}^c D_{0+}^\alpha y)(s) ds \right) \right. \\ &\left. - b(\tau) \left(\frac{1}{\Gamma(\alpha)} \int_0^{\tau-h} (\tau - h - s)^{\alpha-1} ({}^c D_{0+}^\alpha y)(s) ds + y(0) \right) \right] d\tau + F_1 y(0) \\ &= \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} \left[F(\tau) - \frac{(t - \tau)^{1-\alpha}}{\Gamma(\alpha)} \int_\tau^t (t - s)^{\alpha-1} (s - \tau)^{\alpha-1} F(s) a(s) ds \right. \\ &\left. - \frac{(t - \tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau+h}^t (t - s)^{\alpha-1} (s - \tau - h)^{\alpha-1} F(s) b(s) ds \right] ({}^c D_{0+}^\alpha y)(\tau) d\tau \\ &+ \left[F_1 - \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(\tau) (a(\tau) + b(\tau)) \right] y(0) = \frac{1}{\Gamma(\alpha)} \int_0^t (t - \tau)^{\alpha-1} F(\tau) f(\tau) d\tau + F_1 y_0. \end{aligned} \quad (3.4)$$

In order to simplify this equation, it is necessary for the matrix-valued function $F(t)$ to satisfy the given equation

$$\begin{aligned} F(\tau) &= E + \frac{(t-\tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau}^t (t-s)^{\alpha-1} (s-\tau)^{\alpha-1} F(s) a(s) ds \\ &+ \frac{(t-\tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau+h}^t (t-s)^{\alpha-1} (s-\tau-h)^{\alpha-1} F(s) b(s) ds \end{aligned} \quad (3.5)$$

and the matrix F_1 has a representation

$$F_1 = E + \frac{1}{\Gamma(\alpha)} \int_0^t (t-\tau)^{\alpha-1} F(\tau) (a(\tau) + b(\tau)) d\tau \quad (3.6)$$

where $E \in R^{n \times n}$ is a unit matrix.

Considering the representation (3.3), equation (3.4) can be expressed in the following form.

$$y(t) = \frac{1}{\Gamma(\alpha)} \int_0^t (t-\tau)^{\alpha-1} F(\tau) f(\tau) d\tau + F_1 y(0) \quad (3.7)$$

It is crucial to acknowledge that the matrix-function $F(\tau)$ and the matrix F_1 are dependent on the variable t as well. Hence, we express them as $F(t, \tau)$ and $F_1(t)$, respectively, with t belonging to the interval $[0, T]$. Consequently, equations (3.5) and (3.6) can be rewritten as follows

$$\begin{aligned} F(t, \tau) &= E + \frac{(t-\tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau}^t (t-s)^{\alpha-1} (s-\tau)^{\alpha-1} F(t, s) a(s) ds \\ &+ \frac{(t-\tau)^{1-\alpha}}{\Gamma(\alpha)} \int_{\tau+h}^t (t-s)^{\alpha-1} (s-\tau-h)^{\alpha-1} F(t, s) b(s) ds \end{aligned}$$

and

$$F_1(t) = E + \frac{1}{\Gamma(\alpha)} \int_0^t (t-\tau)^{\alpha-1} F(t, \tau) [a(\tau) + b(\tau)] d\tau$$

and representations (3.7) can be written as

$$y(t) = \frac{1}{\Gamma(\alpha)} \int_0^t (t-\tau)^{\alpha-1} F(t, \tau) f(\tau) d\tau + F_1(t) y_0.$$

□

4. Statement of main result

In this section, we address an optimal control problem where the dynamical system is governed by nonlinear delayed equations featuring fractional Caputo derivatives. The system is subject to Cauchy conditions.

$$\begin{cases} {}^c D_{0+}^{\alpha} y(t) = f(t, y(t), y(t-h), u(t)), & a.e. t \in [0, T] \\ y(0) = y_0, \\ y(t) = \varphi(t); & -h \leq t < 0, \quad h > 0. \end{cases} \quad (4.1)$$

Consider the optimal control problem, where $y(t)$ represents an n -dimensional vector of phase variables, $u(t)$ is a measurable and bounded control function on the interval $[0, T]$ with $u(t) \in U(t) \subset R^r$, $y_0 \in R^n$ is a fixed initial condition, and $0 < \alpha < 1$.

In this problem, the objective is to minimize the expected cost functional defined as follows.

$$J(u) = \Phi(y(T)) + \frac{1}{\Gamma(\beta)} \int_0^T (T - \tau)^{\beta-1} f_0(t, y(t), y(t-h), u(t)) dt \longrightarrow \min. \quad (4.2)$$

An admissible pair is referred to as the pair $(y(t), u(t))$ that satisfies the constraints (4.1). On the other hand, an optimal pair denotes the pair $(y(t), u(t))$ that serves as a solution to the problem (4.1)-(4.2).

Problem.

Minimize (4.2) over $U(t)$. Any $u(\cdot) \in U(t)$ satisfying

$$J(u(\cdot)) = \inf_{v \in U(t)} J(v(\cdot))$$

is called an optimal control.

•(C1) Let $d := f, f_0$. There exists a constant $L > 0$ such that

$$\|d(t, y_1, y'_1, u_1) - d(t, y_2, y'_2, u_2)\| \leq L(\|y_1 - y_2\| + \|y'_1 - y'_2\| + \|u_1 - u_2\|),$$

$$\|d(t, 0, 0, 0)\| \leq L, \quad t \in [0, T], \quad y_1, y_2, y'_1, y'_2 \in R^n, \quad u_1, u_2 \in R^r;$$

•(C2) Let $d := f, f_0$ be continuously differentiable with respect to x, y, u , and be measurable with respect to t . Moreover, there exists a constant $L_1 > 0$ such that

$$\begin{aligned} & \|d_y(t, y_1, y'_1, u_1) - d_y(t, y_2, y'_2, u_2)\| \\ & \vee \|d_{y'}(t, y_1, y'_1, u_1) - d_{y'}(t, y_2, y'_2, u_2)\| \\ & \vee \|d_u(t, y_1, y'_1, u_1) - d_u(t, y_2, y'_2, u_2)\| \\ & \leq L_1(\|y_1 - y_2\| + \|y'_1 - y'_2\| + \|u_1 - u_2\|), \end{aligned}$$

$$\|d_y(t, 0, 0, 0)\| \vee \|d_{y'}(t, 0, 0, 0)\| \vee \|d_u(t, 0, 0, 0)\| \leq L_1, \quad t \in [0, T], \quad y_1, y_2, y'_1, y'_2 \in R^n, \quad u_1, u_2 \in R^r;$$

• (C3) Φ is continuously differentiable and uniformly bounded;

• (C4) The set $U(t) : t \in [0, T]$ is compact.

Definition 4.1. The conjugate problem of the (4.1) – (4.2) is said the following integral equation:

$$\begin{aligned} \Psi(t) &= -\frac{\partial \Phi(y(T))}{\partial y(T)} + \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_t^T (T-\tau)^{\alpha-1} (\tau-t)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau)} d\tau \\ &+ \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_{t+h}^T (T-\tau)^{\alpha-1} (\tau-t-h)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau-h)} d\tau, \quad t \in [0, T], \\ \Psi(t) &= 0, \quad t \in (T, T+h]. \end{aligned}$$

Lemma 4.1. *Let $(u(t), y(t))$ be optimal pair for the problem (4.1) – (4.2). Then, increment of trajectory and functional is as follows:*

$$\begin{aligned}
\Delta J(u) = & -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Delta_{\tilde{u}} H(t, y(t), y(t-h), u(t), \Psi) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \frac{\partial \Delta_{\tilde{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial(y(t))} \Delta y(t) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \frac{\partial \Delta_{\tilde{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial(y(t-h))} \Delta y(t-h) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
& \left. + \frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\tilde{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 \Delta_{\tilde{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial^2 y(t-h)} \Delta y(t-h) \\
& \left. + \frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\tilde{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& + \frac{1}{2} \Delta y'(T) \frac{\partial^2 \Phi(y(T) + \mu_1 \Delta y(T))}{\partial y^2(T)} \Delta y(T).
\end{aligned}$$

Proof. To establish the necessary conditions for optimal pairs, we must introduce specific perturbations to the control variable and ascertain the resulting variations in both the state and the cost functional. This process is analogous to determining the Taylor expansion of the state and cost in relation to the control perturbation.

Let $y(t), u(t)$ and $\tilde{y}(t) + \Delta y(t), \tilde{u}(t) + \Delta u(t)$ be two admissible process. It is clear that the increment $\Delta y(t)$ satisfies the problem

$$\begin{cases} {}^c D_{0+}^\alpha \Delta y(t) = \Delta f(t, y(t), y(t-h), u(t)), & a.e. t \in [0, T], \\ \Delta y(0) = 0, \\ \Delta y(t) = 0; & -h \leq t < 0, \quad h > 0. \end{cases} \quad (4.3)$$

where $\Delta f(t, y(t), y(t-h), u(t)) = f(t, \tilde{y}(t), \tilde{y}(t-h), \tilde{u}(t)) - f(t, y(t), y(t-h), u(t))$. We can write increment of functional in the form

$$\Delta J(u) = J(\tilde{u}) - J(u) = \Delta \Phi(y(T)) + \frac{1}{\Gamma(\beta)} \int_0^T (T-t)^{\beta-1} \Delta f_0(t, y(t), y(t-h), u(t)) dt.$$

where $\Delta \Phi(y) = \Phi(\tilde{y}) - \Phi(y)$, and $\Delta f_0(t, y(t), y(t-h), u(t)) = f_0(t, \tilde{y}(t), \tilde{y}(t-h), \tilde{u}(t)) - f_0(t, y(t), y(t-h), u(t))$.

We introduce a nontrivial vector-function $\Psi(t) \in R^n$. By utilizing the Taylor formula, we can express the

increment of the functional as follows

$$\begin{aligned}
\Delta J(u) &= \Delta\Phi(y(T)) + \frac{1}{\Gamma(\beta)} \int_0^T (T-t)^{\beta-1} \Delta f_0(t, y(t), y(t-h), u(t)) \\
&+ \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Psi'(t) \left[({}^c D_{0+}^\alpha \Delta y)(t) - \Delta f(t, y(t), y(t-h), u(t)) \right] dt \\
&= \Delta\Phi(y(T)) - \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Delta H(t, y(t), y(t-h), u(t), \Psi) dt \\
&+ \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Psi(t) \left(({}^c D_{0+}^\alpha \Delta y)(t) \right) dt \\
&= \frac{\partial\Phi(y(T))}{\partial y(T)} \Delta y(T) + \frac{1}{2} \Delta y'(T) \frac{\partial^2 \Phi(y(T) + \mu_1 \Delta y(T))}{\partial y^2(T)} \Delta y(T) + \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Psi(t) \left(({}^c D_{0+}^\alpha \Delta y)(t) \right) dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T \Delta_u H(t, y(t), y(t-h), u(t), \Psi) dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{\partial H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t)} \Delta y(t) + \frac{\partial H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t-h)} \Delta y(t-h) \right] dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t)} \Delta y(t) + \frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t-h)} \Delta y(t-h) \right] dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
&+ \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
&+ \left. \frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
&+ \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial^2 y(t-h)} \Delta y(t-h) \\
&+ \left. \frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt.
\end{aligned}$$

Note that

$$H(t, y, y_h, u, \Psi) = \Psi' f(t, y, y_h, u) - \frac{\Gamma(\alpha)}{\Gamma(\beta)} (T-t)^{\beta-\alpha} f_0(t, y, y_h, u).$$

Using relations

$$\Delta y(t) = \frac{1}{\Gamma(\alpha)} \int_0^t (t-\tau)^{\alpha-1} ({}^c D_{0+}^\alpha \Delta y)(\tau) d\tau,$$

and

$$\Delta y(t-h) = \frac{1}{\Gamma(\alpha)} \int_0^{t-h} (t-h-\tau)^{\alpha-1} ({}^c D_{0+}^\alpha \Delta y)(\tau) d\tau$$

we obtain that

$$\begin{aligned}
\Delta J(u) &= \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{\partial \Phi(y(T))}{\partial y(T)} + \Psi'(t) \right. \\
&- \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_t^T (T-t)^{\alpha-1} (t-\tau)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau)} d\tau \\
&- \left. \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_{t+h}^T (T-t)^{\alpha-1} (t-\tau-h)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau-h)} d\tau \right] ({}^c D_{0+}^\alpha \Delta y)(t) dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi) dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t)} \Delta y(t) + \frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t-h)} \Delta y(t-h) \right] dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
&+ \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
&+ \left. \frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta x(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
&- \frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
&+ \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial^2 y(t-h)} \Delta y(t-h) \\
&+ \left. \frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
&+ \frac{1}{2} \Delta y'(T) \frac{\partial^2 \Phi(y(T) + \mu_1 \Delta y(T))}{\partial y^2(T)} \Delta y(T), \quad \text{where } 0 < \mu_i < 1, \quad i = 1, 2.
\end{aligned} \tag{4.4}$$

Next, we impose the condition that the vector-function $\Psi : [0, T] \rightarrow R^n$, satisfies the following integral equation

$$\begin{aligned}
\Psi(t) &= -\frac{\partial \Phi(y(T))}{\partial y(T)} + \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_t^T (T-\tau)^{\alpha-1} (\tau-t)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau)} d\tau \\
&+ \frac{(T-t)^{1-\alpha}}{\Gamma(\alpha)} \int_{t+h}^T (T-\tau)^{\alpha-1} (\tau-t-h)^{\alpha-1} \frac{\partial H(\tau, y(\tau), y(\tau-h), u(\tau), \Psi)}{\partial y(\tau-h)} d\tau, \quad t \in [0, T], \\
\Psi(t) &= 0, \quad t \in (T, T+h].
\end{aligned} \tag{4.5}$$

The problem stated in equation (4.5) is referred to as a conjugated problem. The integral equation (4.5) possesses a single continuous solution. By considering the equalities expressed in (4.5) within (4.4), we obtain

an auxiliary formula for determining the increment of the functional.

$$\begin{aligned}
\Delta J(u) = & -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial(y(t))} \Delta y(t) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \frac{\partial \Delta_{\bar{u}} H(t, y(t), y(t-h), u(t), \Psi)}{\partial(y(t-h))} \Delta y(t-h) dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
& \left. + \frac{1}{2} \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& -\frac{1}{\Gamma(\alpha)} \int_0^T (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \frac{1}{2} \Delta y'(t-h) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial^2 y(t-h)} \Delta y(t-h) \\
& \left. + \frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& + \frac{1}{2} \Delta y'(T) \frac{\partial^2 \Phi(y(T) + \mu_1 \Delta y(T))}{\partial y^2(T)} \Delta y(T).
\end{aligned} \tag{4.6}$$

□

Lemma 4.2. *Under the assumptions of Lemma 4.1 and (C1) – (C4), the following estimate holds for trajectory increment on the spike variation:*

$$\|\Delta y(t)\| \leq B\varepsilon,$$

$$\text{where } B = M \left(\frac{K_1(\alpha, \varepsilon)}{\Gamma(\alpha+1)} (t - (\theta + \varepsilon))^{\alpha-1} + \frac{MK(v)}{\Gamma(\alpha+1)} \varepsilon^{\alpha-1} \right).$$

Proof. In order to obtain effectively verifiable necessary optimal conditions, consider the following variation of $u(t)$:

$$\Delta_v u(t) = \begin{cases} 0, & t \notin [\theta, \theta + \varepsilon) \\ v - u(t), & t \in [\theta, \theta + \varepsilon). \end{cases} \tag{4.7}$$

where $v \in U, \varepsilon > 0$ is a sufficiently small parameter, $\theta \in [0, T), \theta + \varepsilon < T$, is the Lebesgue point of the functions $t \rightarrow f(t, y(t), y(t-h), u(t)), f_y(t, y(t), y(t-h), u(t))$. For all values of $\varepsilon > 0$ that are sufficiently small, the control $u_\varepsilon(t)$ defined as $u_\varepsilon(t) = u(t) + \Delta_\varepsilon u(t)$ is considered to be an admissible control. This control, obtained by perturbing the original control $u(t)$, is valid for all $v \in U$.

$$\begin{cases} {}^c D_{0+}^\alpha \Delta y(t) = f(t, y(t) + \Delta y(t), y(t-h) + \Delta y(t-h), u(t)) - f(t, y(t), y(t-h), u(t)) \\ \Delta y(t) = 0, \quad -h \leq t \leq \theta, \theta + \varepsilon \leq T. \end{cases} \tag{4.8}$$

As a consequence of $\Delta y(t) = 0$, it can be deduced from equation (4.8) that the function

$$\Delta y(t) \equiv 0 \quad 0 \leq t \leq \theta$$

serves as the only solution to equation (4.8) within the interval $[0, \theta]$.

$${}^c D_{0+}^\alpha \Delta y(t) = f(t, y(t) + \Delta y(t), y(t-h) + \Delta y(t-h), v) - f(t, y(t), y(t-h), u(t)), \quad \theta \leq t \leq \theta + \varepsilon. \quad (4.9)$$

Hence, the initial condition for equation (4.9) takes the form $\Delta y(\theta) = 0$. Consequently, equation (4.9) can be expressed in integral form.

$$\Delta y(t) = \frac{1}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} [f(\tau, y(\tau) + \Delta y(\tau), y(\tau-h) + \Delta y(\tau-h), v) - f(\tau, y(\tau), y(\tau-h), u(\tau))] d\tau. \quad (4.10)$$

According to the assumption C1, there exists a constant $L > 0$ such that

$$\|f(t, y(t) + \Delta y(t), y(t-h) + \Delta y(t-h), v) - f(t, y(t), y(t-h), u(t))\| \leq L[\|\Delta y(t)\| + \|\Delta y(t-h)\|]. \quad (4.11)$$

from equation (4.10) we obtain

$$\begin{aligned} \|\Delta y(t)\| &\leq \frac{1}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} \|f(\tau, y(\tau) + \Delta y(\tau), y(\tau-h) + \Delta y(\tau-h), v) - f(\tau, y(\tau), y(\tau-h), u(\tau))\| d\tau \\ &\leq \frac{L}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} [\|\Delta y(\tau)\| + \|\Delta y(\tau-h)\|_C] d\tau + \frac{L}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} \|\Delta_v f(\tau, y(\tau), y(\tau-h), u(\tau))\| d\tau \end{aligned} \quad (4.12)$$

where $\Delta_v f(\tau, y(\tau), y(\tau-h), u(\tau)) = f(\tau, y(\tau), y(\tau-h), v) - f(\tau, y(\tau), y(\tau-h), u)$.

Denoting

$$\operatorname{ess\,sup}_{t \in [0, T]} \|\Delta_v f(\tau, y(\tau), y(\tau-h), u(\tau))\| = K(v),$$

the inequality (4.12) can be expressed in the following form.

$$\|\Delta y(t)\| \leq \frac{K(v)}{\Gamma(\alpha+1)} (t-\theta)^\alpha + \frac{L}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} [\|\Delta y(\tau)\| + \|\Delta y(\tau-h)\|_C] d\tau. \quad (4.13)$$

$$\Delta y(\theta) = 0$$

By applying Lemma 2.3 (Gronwall's inequality) to equation (4.13), we can conclude that for all $0 < \varepsilon \leq \tilde{\varepsilon}$ and $\theta \leq t \leq \theta + \varepsilon$, the following inequality holds.

$$\|\Delta y(t)\| \leq \frac{MK(v)}{\Gamma(\alpha+1)} (t-\theta)^\alpha \quad (4.14)$$

holds.

Let us examine the behavior of the function $\Delta y(t)$ on the interval $[\theta + \varepsilon, T]$. This can be described by the integral equation

$$\begin{aligned} \Delta y(t) &= \frac{1}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} [f(s, y(s) + \Delta y(s), y(s-h) + \Delta y(s-h), v) - f(s, y(s), y(s-h), u(s))] ds \\ &\quad + \frac{1}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} [f(s, y(s) + \Delta y(s), y(s-h) + \Delta y(s-h), u(s)) - f(s, y(s), y(s-h), u(s))] ds. \end{aligned}$$

To simplify the analysis, assuming the Lipschitz constant remains constant, we obtain the following result

$$\begin{aligned}
\|\Delta y(t)\| &\leq \frac{K(v)}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} ds + \frac{L}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} \|\Delta y(s)\| ds \\
&+ \frac{L}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} \|\Delta y(s-h)\|_C ds + \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s)\| ds \\
&+ \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s-h)\|_C ds \leq \frac{K(v)}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} ds \\
&+ \frac{L}{\Gamma(\alpha)} \frac{MK(v)}{\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} (s-\theta)^{\alpha} ds + \frac{L}{\Gamma(\alpha)} \frac{MK(v)}{\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (t-s)^{\alpha-1} (s-\theta-h)^{\alpha} ds \\
&+ \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s)\| ds + \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s-h)\|_C ds
\end{aligned}$$

Substituting (4.14) into the above expression, we obtain

$$\begin{aligned}
\|\Delta y(t)\| &\leq \frac{K_1(\alpha, \varepsilon)\varepsilon}{\Gamma(\alpha+1)} (t - (\theta + \varepsilon))^{\alpha-1} + \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s)\| ds \\
&+ \frac{L}{\Gamma(\alpha)} \int_{\theta+\varepsilon}^t (t-s)^{\alpha-1} \|\Delta y(s-h)\|_C ds \\
\|\Delta y(\theta + \varepsilon)\| &\leq \frac{MK(v)}{\Gamma(\alpha+1)} \varepsilon^{\alpha}
\end{aligned}$$

Hence , by Lemma 2.3, we have

$$\|\Delta y(t)\| \leq M \left(\frac{K_1(\alpha, \varepsilon)\varepsilon}{\Gamma(\alpha+1)} (t - (\theta + \varepsilon))^{\alpha-1} + \frac{MK(v)}{\Gamma(\alpha+1)} \varepsilon^{\alpha} \right) = B\varepsilon$$

□

Lemma 4.3. *Under assumptions of the Lemma 4.2, increment of functional on the spike variation is as follows:*

$$\begin{aligned}
\Delta J(u) &= -\frac{1}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} \Delta_v H(t) dt \\
&- \frac{\varepsilon^{\alpha+1}}{\Gamma(\alpha)\Gamma(\alpha+1)} \left[(T-\theta)^{\alpha-1} \Delta_v H_y(\theta) \Delta_v f(\theta) + (T-\theta-h)^{\alpha-1} \Delta_v H_{y_h}(\theta) \Delta_v f(\theta) \right] + o(\varepsilon^{1+\alpha}).
\end{aligned}$$

Proof. By utilizing the integral representation

$$\Delta y(t) = \frac{1}{\Gamma(\alpha)} \int_{\theta}^t (t-\tau)^{\alpha-1} [f(\tau, y(\tau) + \Delta y(\tau), y(\tau-h) + \Delta y(\tau-h), v) - f(\tau, y(\tau), y(\tau-h), u(\tau))] d\tau,$$

and (lemma 2.5), the increment of the trajectory on the interval $[\theta, \theta + \varepsilon]$, can be

$$\Delta y(t) = \frac{1}{\Gamma(\alpha+1)} (t-\theta)^{\alpha} \Delta_v f(\theta) + o((t-\theta)^{\alpha}). \tag{4.15}$$

By considering equations (4.15) and (4.7) and incorporating them into equation (4.6), we derive the following result.

$$\begin{aligned}
\Delta J(u) &= -\frac{1}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} \Delta_v H(t, y(t), y(t-h), u(t), \Psi) dt \\
&- \frac{1}{\Gamma(\alpha)\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} (t-\theta)^{\alpha} \frac{\partial \Delta_v H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t)} \Delta_v f(\theta) dt \\
&- \frac{1}{\Gamma(\alpha)\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (T-t-h)^{\alpha-1} (t-\theta)^{\alpha} \frac{\partial \Delta_v H(t+h, y(t+h), y(t), u(t+h), \Psi(t+h))}{\partial y(t)} \Delta_v f(\theta) dt + \xi
\end{aligned} \tag{4.16}$$

where

$$\begin{aligned}
\xi = & -\frac{1}{2\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} \left[\Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
& \left. + \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& -\frac{1}{2\Gamma(\alpha)} \int_{\theta+\varepsilon}^T (T-t)^{\alpha-1} \left[\Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \Delta y'(t-h) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t-h)} \Delta y(t-h) \\
& \left. + \Delta y'(t) \frac{\partial^2 H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& -\frac{1}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} \left[\frac{1}{2} \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y^2(t)} \Delta y(t) \right. \\
& + \Delta y'(t-h) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial^2 y(t-h)} \Delta y(t-h) \\
& \left. + \Delta y'(t) \frac{\partial^2 \Delta_{\bar{u}} H(t, y(t) + \mu_2 \Delta y(t), y(t-h) + \mu_2 \Delta y(t-h), u(t), \Psi)}{\partial y(t) \partial y(t-h)} \Delta y(t-h) \right] dt \\
& + \frac{1}{2} \Delta y'(T) \frac{\partial^2 \Phi(y(T) + \mu_1 \Delta y(T))}{\partial y^2(T)} \Delta y(T).
\end{aligned}$$

by the same way in [37], it follows

$$|\xi| \leq K\varepsilon^{1+\nu}, \quad \nu > 0. \quad (4.17)$$

it implies

$$\begin{aligned}
& -\frac{1}{\Gamma(\alpha)\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} (t-\theta)^{\alpha} \frac{\partial \Delta_v H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t)} \Delta_v f(\theta) dt \\
& -\frac{1}{\Gamma(\alpha)\Gamma(\alpha+1)} \int_{\theta}^{\theta+\varepsilon} (T-t-h)^{\alpha-1} (t-\theta)^{\alpha} \frac{\partial \Delta_v H(t, y(t), y(t-h), u(t), \Psi)}{\partial y(t-h)} \Delta_v f(\theta) dt \\
& = -\frac{\varepsilon^{\alpha+1}}{\Gamma(\alpha)\Gamma(\alpha+1)} \left[(T-\theta)^{\alpha-1} \Delta_v H_y(\theta) \Delta_v f(\theta) + (T-\theta-h)^{\alpha-1} \Delta_v H_{y_h}(\theta+h) \Delta_v f(\theta) \right] + o(\varepsilon^{1+\alpha}).
\end{aligned} \quad (4.18)$$

After substituting the estimates (4.17) and (4.18) into the expression (4.16) representing the increment of the functional, we obtain the following result

$$\begin{aligned}
\Delta J(u) = & -\frac{1}{\Gamma(\alpha)} \int_{\theta}^{\theta+\varepsilon} (T-t)^{\alpha-1} \Delta_v H(t) dt \\
& -\frac{\varepsilon^{\alpha+1}}{\Gamma(\alpha)\Gamma(\alpha+1)} \left[(T-\theta)^{\alpha-1} \Delta_v H_y(\theta) \Delta_v f(\theta) + (T-\theta-h)^{\alpha-1} \Delta_v H_{y_h}(\theta+h) \Delta_v f(\theta) \right] + o(\varepsilon^{1+\alpha}).
\end{aligned} \quad (4.19)$$

□

First and second order necessary conditions.

Theorem 4.1. *Suppose that the admissible process $(u(t), y(t))$ is optimal for the problem (4.1)-(4.2), and let Ψ be a solution to the conjugate problem (4.5) on the optimal process. Assuming that assumptions (C1)-(C4) are satisfied, then for almost every $t \in [0, T]$, the following equality is satisfied:*

$$\max_{v \in U} H(t, y(t), y(t-h), v, \Psi(t)) = H(t, y(t), y(t-h), u(t), \Psi(t)). \quad (4.20)$$

Proof. When we divide the right side of (4.19) by ε and let ε approach zero from the positive side, we obtain (4.20). \square

Definition 4.2. An admissible control $u(t)$ is considered to be singular according to the Pontryagin maximum principle if, within the process $u(t), y(t)$, the maximum condition (4.3) is trivially satisfied on a subset $T_0 \subset [0, T]$. In other words, it implies that

$$\Delta_v H(t) = 0 \quad \text{for almost every } t \in T_0 \quad \text{and} \quad v \in U_0. \quad (4.21)$$

where $U_0 \neq \{u(t)\}$, $t \in T_0$ is a subset of U .

For simplicity of presentation, we assume that $U_0 = U$ and $T_0 = [0, T]$.

Theorem 4.2. *In order for a control $u(t)$ to be optimal according to the Pontryagin maximum principle, in the context of the problem (4.1)-(4.2), it is necessary that the following inequality holds:*

$$(T-t)^{\alpha-1} \Delta_v H_y(t) \Delta_v f(t) + (T-t-h)^{\alpha-1} \Delta_v H_{y_h}(t+h) \Delta_v f(t) \leq 0, \quad (4.22)$$

holds for all $v \in U$ and a.e. $t \in [0, T]$.

Proof. Now, considering $\Delta_v H(t) = 0$ in expression (4.19), we get

$$\begin{aligned} \Delta J(u) = & \\ & - \frac{\varepsilon^{\alpha+1}}{\Gamma(\alpha)\Gamma(\alpha+1)} \left[(T-\theta)^{\alpha-1} \Delta_v H_y(\theta) \Delta_v f(\theta) + (T-\theta-h)^{\alpha-1} \Delta_v H_{y_h}(\theta+h) \Delta_v f(\theta) \right] + o(\varepsilon^{1+\alpha}). \end{aligned} \quad (4.23)$$

dividing the right side of (4.23) by $\varepsilon^{\alpha+1}$ and let ε approach zero from the positive side, we get (4.22). \square

Example 4.1. Consider the problem

$$\begin{aligned} ({}^c D_{0+}^\alpha y)(t) &= Ay(t-h) + Bu(t), \quad t \in [0, 1], \\ y(t) &= 0, \quad -h \leq t \leq 0, \quad h = \frac{1}{2}, \\ |u(t)| &\leq 1, \quad J(u) = y_1(1) \longrightarrow \min, \end{aligned}$$

where

$$A = \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix} \quad B = \begin{bmatrix} 1 \\ 1 \end{bmatrix}.$$

We analyze the optimality of the control input $u(t) = 0$. This particular control choice corresponds to the solution $y(t) = 0$ of the equation and Hamiltonian of the problem is as follows

$$\begin{aligned} H(t, y(t), y(t-h), u(t), \psi) &= \langle \psi, f(t, y(t), y(t-h), u(t)) \rangle = \psi_1(y_1(t-h) + u(t)) + \psi_2 u(t), \\ \text{where } \psi &= (\psi_1, \psi_2) \quad \text{and} \quad y(t-h) = (y_1(t-h), y_2(t-h)). \end{aligned}$$

During the progression denoted by (0.0), we obtain the following outcome

$$\psi_1(t) = -1, \quad \psi_2(t) = -\frac{\Gamma(\alpha)}{\Gamma(2\alpha)} (1-t)^{1-\alpha} (1-t-h)^{2\alpha-1}, \quad t \in \left[0, \frac{1}{2}\right]$$

According to the theorem 4.1, we have

$$-\left(1 + \frac{\Gamma(\alpha)}{\Gamma(2\alpha)} (1-t)^{1-\alpha} (1-t-h)^{2\alpha-1}\right) v \leq 0, \quad v \in [-1, 1],$$

that is not possible for all $v \in [-1, 0)$. Therefore, $u(t) = 0$ is not optimal control.

Example 4.2. Consider the problem

$$\begin{aligned} ({}^c D_{0+}^\alpha y)(t) &= [A + By_1(t-h)]u(t), \quad t \in [0, 1], \\ y(t) &= 0, \quad t \in [-h, 0] \quad h = \frac{1}{2}, \\ |u(t)| &\leq 1, \quad J(u) = y_2(1) \longrightarrow \min, \end{aligned}$$

where

$$A = \begin{bmatrix} 1 \\ 0 \end{bmatrix} \quad B = \begin{bmatrix} 0 \\ -1 \end{bmatrix}.$$

We are examining the effectiveness of the control input $u(t) = 0$ and assessing its optimality. This specific choice of control corresponds to the solution $y(t) = 0$ of the equation. The Hamiltonian of the problem can be expressed as follows.

$$\begin{aligned} H(t, y(t), y(t-h), u(t), \psi) &= \langle \psi, f(t, y(t), y(t-h), u(t)) \rangle = \psi_1 u(t) - \psi_2 u(t) y_1(t-h), \\ \text{where } \psi &= (\psi_1, \psi_2) \quad \text{and} \quad y(t-h) = (y_1(t-h), y_2(t-h)). \end{aligned}$$

Along the process (0.0), we observe the following result.

$$\psi_1(t) = 0, \quad \psi_2(t) = -1, \quad \text{and} \quad H = 0.$$

Hence, the control $u(t) = 0$ is categorized as a singular control. We will now verify the satisfaction of the condition in equation (4.22). By examining equation (4.22), we can deduce that $v^2 \leq 0$ for all $v \in [-1, 1]$, which is not feasible for any $v \neq 0$. Consequently, the control $u(t) = 0$ is not considered optimal.

Clearly, when applying the control $u(t) = 0$, the value of the performance measure is $J(t) = y_2(1) = 0$. Now, let's examine whether there exists another control function that results in objective functional values less than zero. We will calculate the value of J for the admissible control $u(t) = -\frac{1}{2}$. For this function

$$y_1(t) = -\frac{t^\alpha}{2\Gamma(\alpha+1)},$$

$$y_2(t) = -\frac{(t-h)^{2\alpha}}{4\Gamma(2\alpha+1)}.$$

Then we have

$$J\left(-\frac{1}{2}\right) = -\frac{1}{2^{2\alpha+2}\Gamma(2\alpha+1)} < 0 = J(0).$$

This demonstrates that the choice of control $u(t) = 0$ for $t \in [0, 1]$, is not optimal.

5. Conclusion

By employing an updated iteration technique, we successfully derive a first-order condition for optimality, represented through the Pontryagin maximum principle, for the given fractional time-delay optimal control problem. Furthermore, in situations where the Pontryagin maximum principle degenerates, we also obtain a second-order necessary condition for optimality. As a result, we anticipate that this approach can be extended and generalized to address fractional optimal control problems involving neutral fractional equations, partial fractional differential equations, along with their respective boundary conditions, in future research.

References

- [1] O. P. Agrawal, O. Defterli and D. Baleanu, Fractal optimal control problems with several state and control variable, *J. Vib. Control.*, 16 (2010), 1967-1976.
- [2] N. U. Ahmed and C. D. Charalambous, Filtering for linear systems driven by fractional Brownian motion, *SIAM J. Control Optim.*, 41 (2002), 313-330.
- [3] D. Baleanu, K. Diethelm, E. Scalas and J. J. Trujillo, *Fractional Calculus Models and Numerical Methods*, World Scientific Publishing Co., Pte. Ltd. Hackensack, New York. 2012.
- [4] F. Baudoin and D. Nualart, Notes on the two-dimensional fractional Brownian motion, *Annals of Probability*, 34 (2006), 159-180.
- [5] M. Benchohra, J. Henderson, S. K. Ntouyas and A. Ouahab, Existence results for fractional order functional differential equations with infinite delay, *J. Math. Anal. Appl.*, 338 (2008), 1340-1350.
- [6] M. Bin and Z. Liu, Relaxation in nonconvex optimal control for nonlinear evolution hemivariational inequalities, *Nonlinear Anal.: Real World Appl.*, 50 (2019), 613-632.
- [7] A. Carpinteri and F. Mainardi, *Fractals and Fractional Calculus in Continuum Mechanics*, Springer, Berlin. 1997.
- [8] M. Bergounioux, K. Diethelm, Pontryagin maximum principle for general Caputo fractional optimal control problems with Bolza cost and terminal constraints, *ESAIM Control Optim. Calc. Var.*, 26 (2020), 1-38.
- [9] A. Flores-Tlacuahuac and L. T. Biegler, Optimization of fractional order dynamic chemical processing systems, *Ind. Engin. Chem. Res.*, 53 (2014), 5110-5127.
- [10] R. Gabasov and F. M. Kirillova, High-order necessary conditions for optimality, *SIAM J. Control.*, 10 (1972) 127-168.
- [11] M. I. Gomoyunov, On representation formulas for solution of linear differential equations with Caputo fractional derivative, *Fract. Calc. Appl. Anal.*, 23 (2020), 1141-1160.
- [12] Z. Gong, C. L. Teo, S. Wang and Y. Wu, Numerical solution of free final time fractional optimal control problems, *Appl. Math. Comput.*, 405 (2021), 1-15.
- [13] T. L. Guo, The necessary conditions of fractrional optimal control in the sense of Caputo, *J. Optim. Theory. Appl.*, 156 (2013), 115-126.
- [14] A. Hajipour, M. Hajipour and D. Baleanu, On the adaptive sliding mode controller for a hypercgaotic fractional-order financial system, *Physica A.*, 497 (2018), 139-153.
- [15] R. Kamocki, Pontryagin maximum principle for fractional ordinary optimal control problems, *Math. Methods. Appl. Sci.*, 37 (2014), 1668-1686.
- [16] A. A. Kilbas, H. M. Sirvastava and J. J. Trujillo, *Theory and Applications of Fractional Differential Equations*, Volume 204 of *North-Holland Mathematics Studies*, Elsevier Science B. V., Amsterdam, (2006).
- [17] T. Kaczorek, Minimum energy control of fractional positive electrical circuits with bounded inputs, *Circuits Syst. Signal Process.*, 35 (2016), 1815-1829.
- [18] H. Kheiri and M. Jafari, Optimal control of a fractional-order model for the HIV/AIDs epidemic, *Int. J. Biomath.*, 11 (2018), 1850086, 23 pp.
- [19] W. Li. Wang and V. Rehbock, Numerical solution of fractional optimal control, *J. Optim. Theory. Appl.*, 180 (2019), 556-573.

- [20] E. N. Mahmudov, Approximation and Optimization of Discrete and Differential Inclusions, *Elsevier, Inc., Amsterdam*, (2011).
- [21] E. N. Mahmudov, Optimal control of higher order differential inclusions with functional constraints, *ESAIM: COCV*.
- [22] E. N. Mahmudov and S. Sh. Yusubov, Nonlocal boundary value problems for hyperbolic equations with a Caputo fractional derivative, *J. Comput. Appl. Math.*, 398 (2021), Paper No. 113709, 15 pp.
- [23] P. Mu, L. Wang and C. Liu A control parameterization method to solve the fractional-order optimal control problem, *J. Optim. Theory. Appl.*, 187 (2020), 234-247.
- [24] I. Podlubny, Fractional Differential Equations. An Introduction to Fractional Derivatives, Fractional Differential Equations, to Methods of Their Solution and Some of Their Applications, *Mathematics in Science and Engineering*, 198. *Academic Press, Inc., San Diego, CA*, (1999).
- [25] E. S. Pontryagin, V. G. Boltyanski, R. V. Gamkrelidze and E. F. Mishenko, The Mathematical Theory of Optimal Processes, 4-th edition, *Nauko, Moscow*, 1983, 392pp.
- [26] S. Pooseh, R. Almeida and D. F. Torres, Fractional order optimal control problems with free terminal time, *J. Ind. Manag. Optim.*, 10 (2014), 363-381.
- [27] E. Rentsen, J. Zhou and K. L. Teo, A global optimization approach to fractional optimal control, *J. Ind. Manag. Optim.*, 12 (2016), 73-82.
- [28] L. I. Rozonoer, The maximum principle by L. S. Pontryagin in the theory of optimal systems, *I,II,III, Automatics and Remote Control*, 1959 (1959), 10-12.
- [29] S. G. Samko, A. A. Kilbas and O. I. Marichev, Fractional Integrals and Derivatives. Theory and Applications, *Gordan and Breach Science Publishers, Yverdon*, 1993.
- [30] X. Yang and S. Y. Wang and X. T. Deng, Symmetric duality for a class of multiobjective fractional programming problems, *J. Math. Anal. Appl.*, 274 (2002), 279-295.
- [31] X. Yang, X. Q. Yang, K. L. Teo, Duality and saddle-point type optimality for generalized nonlinear fractional programming, *J. Math. Anal. Appl.*, 289 (2004), 100-109.
- [32] R. Toledo-Hernandez, V. Rico-Ramírez, R. Rico-Martínez, S. Hernández-Castro and U. Diwekar, A fractional calculus approach to the dynamic optimization of biological reactive systems part: Numerical solution of fractional optimal control problems, *Chem. Eng. Sci.*, 117 (2014), 239-247.
- [33] S. S. Yusubov, Necessary optimality conditions for systems with impulsive actions, *Comput. Math and Math. Phys.*, 45 (2005), 222-226.
- [34] S. S. Yusubov, Necessary optimality conditions for singular controls, *Comput. Math and Math. Phys.*, 47 (2007), 1446-1451.
- [35] S. S. Yusubov and E. N. Mahmudov, Optimality conditions of singular controls for systems with Caputo fractional derivatives, *J. Ind. Manag. Optim.*, 19 (2022), 246-264.
- [36] Sh. Sh. Yusubov and E. N. Mahmudov, Necessary and sufficient optimality conditions for fractional Fornasini-Marchesini model, *J. Indust. Manag. Optim.*, 19 (2023), 7221-7244.
- [37] S. S. Yusubov and E. N. Mahmudov, Some necessary optimality conditions for systems with fractional Caputo derivatives, *J. Ind. Manag. Optim.*, 20 (2023).
- [38] C. Shi and M. Bi, Relaxation in nonconvex optimal control problems described by evolution Riemann-Liouville fractional differential inclusions, *J. Indust. Manag. Optim.*, 19 (2023), 5380-5397.
- [39] S. Pooseh, R. Almeida and D. F. M. Torres, Fractional order optimal control problems with free terminal time, *J. Ind. Manag. Optim.*, 10 (2014), 363-381
- [40] X. Xiaoling and K. Huawu, Delay systems and optimal control, *Acta Math. Appl. Sinica.*, 9 (2000), 27-35.