

Gaussian approximation of dynamic cavity equations for linearly-coupled stochastic dynamics

Mattia Tarabolo^{1*} and Luca Dall'Asta^{1,2,3†}

¹ Politecnico di Torino, Torino, Italy

² Collegio Carlo Alberto, Torino, Italy

³ Italian Institute for Genomic Medicine (IIGM), Candiolo, Italy

* mattia.tarabolo@polito.it, † luca.dallasta@polito.it

Abstract

Stochastic dynamics on sparse graphs and disordered systems often lead to complex behaviors characterized by heterogeneity in time and spatial scales, slow relaxation, localization, and aging phenomena. The mathematical tools and approximation techniques required to analyze these complex systems are still under development, posing significant technical challenges and resulting in a reliance on numerical simulations. We introduce a novel computational framework for investigating the dynamics of sparse disordered systems with continuous degrees of freedom. Starting with a graphical model representation of the dynamic partition function for a system of linearly-coupled stochastic differential equations, we use dynamic cavity equations on locally tree-like factor graphs to approximate the stochastic measure. Here, cavity marginals are identified with local functionals of single-site trajectories. Our primary approximation involves a second-order truncation of a small-coupling expansion, leading to a Gaussian form for the cavity marginals. For linear dynamics with additive noise, this method yields a closed set of causal integro-differential equations for cavity versions of one-time and two-time averages. These equations provide an exact dynamical description within the local tree-like approximation, retrieving classical results for the spectral density of sparse random matrices. Global constraints, non-linear forces, and state-dependent noise terms can be addressed using a self-consistent perturbative closure technique. The resulting equations resemble those of dynamical mean-field theory in the mode-coupling approximation used for fully-connected models. However, due to their cavity formulation, the present method can also be applied to ensembles of sparse random graphs and employed as a message-passing algorithm on specific graph instances.

Contents

1	Introduction	2
1.1	Notation	4
2	Methods	4
2.1	Dynamic cavity approach for linearly-coupled stochastic dynamics	4
2.2	Small-coupling expansion	7

2.3	Gaussian Expansion Cavity Method for linear dynamics with additive noise	8
2.3.1	Gaussian cavity ansatz	8
2.3.2	Relation with random matrix theory	12
2.4	Perturbative closure technique in the presence of non-gaussian terms	14
3	Results	15
3.1	Linear dynamics with thermal noise on Random Regular Graphs	15
3.2	Gaussian perturbative closure technique for a cubic perturbation	17
3.3	Noise-driven phase transition with multiplicative noise	20
3.4	Relaxation dynamics of the spherical 2-spin model	23
4	Conclusions	26
	References	28
S1	General GECaM equations with non-vanishing conjugate variables	34
S2	Non-Hermitian random matrices	35
S3	Noise-driven phase transition in the Bouchaud-Mézard model	37
S3.1	Critical point	37
S3.2	Adiabatic and independent assumption for GECaM	39
S3.2.1	Linear dynamics with additive noise	40
S3.2.2	Bouchaud-Mézard model	41

1 Introduction

Complex systems across various fields can be mathematically described as collections of random variables interacting through disordered network structures. These networks feature intricate local geometries and a variable number of interactions per degree of freedom, which can also change over time [1]. Despite the lack of finite-dimensional spatial embedding, which makes both equilibrium and non-equilibrium phenomena in these systems essentially mean-field in nature [2, 3], they exhibit several unique properties, including anomalous critical exponents [4], spatial localization [5, 6], and multiple relaxation scales [7–9]. In addition to numerical simulations, mean-field methods and moment closure techniques, in which local approximations of probability marginals are obtained assuming some level of decorrelation between variables, have been massively applied to investigate the dynamic properties of these systems [10–16].

For a wide range of stochastic processes with discrete degrees of freedom, the dynamic cavity method [17, 18] provides a very accurate description of the dynamics on locally tree-like graphs. However, this method typically involves significant computational complexity, which is reduced only for specific classes of non-recurrent or monotone processes, such as threshold models [19, 20] and epidemic processes [21, 22]. To address this limitation, further approximations of the dynamic cavity method have been introduced, resulting in more efficient algorithms for specific problems [23–27].

In contrast, there has been less progress in the study of stochastic dynamics with continuous degrees of freedom, despite their relevance in various fields such as epidemic diffusion in metapopulations, chemical reactions, and ecological networks. Typically, these

cases involve analyzing potentially large systems of coupled (non-linear) stochastic differential equations (SDEs). Common approximation techniques for these systems include linear noise approximation [28, 29], and dimensional reduction techniques [30–33]. However, a long-standing tradition exists in statistical physics for addressing coupled SDEs, in the limit of fully-connected interaction graphs, using path integral mean-field methods [34]. These methods, unified under the general concept of Dynamical Mean Field Theory (DMFT), allow for the derivation of an effective process for a single representative degree of freedom. The representative process is described by a single stochastic differential equation containing memory terms and a colored noise, generated by the interaction of the representative degree of freedom with a self-consistently defined stochastic bath characterized by the very same statistical properties. DMFT has been successfully applied to study the dynamics of spherical p-spin models for aging and glassy dynamics in disordered systems [35–37], and more recently to characterize dynamical phases in neural networks [38], ecological communities [39, 40] and gradient-based high-dimensional learning [41]. To our knowledge, a few works generalize path-integral and DMFT-like approaches beyond fully-connected graphs, most notably using dynamical replica approach [42], large-connectivity approximations [43, 44] and perturbative expansions [45].

In all these applications, DMFT is typically developed to study an effective process obtained after averaging over the disorder induced by the interaction structure. Algorithmic versions of DMFT were also introduced, like in the case of the Extended Plefka Expansion [46, 47], where two-time response/correlation functions are microscopically defined for every site of the system. The resulting equations are a kind of dynamic version of the TAP equations used for studying equilibrium properties of mean-field disordered systems. They provide an exact description of systems of linear SDEs with additive noise in the fully-connected limit, but they can be used also as an approximate algorithm for studying stochastic dynamics on generic graphs.

The present work generalizes these results to the study of linearly-coupled SDEs on sparse graphs introducing a message passing algorithm for local cavity moments, such as one-time averages, and two-time response functions and correlation functions. This is done first applying the dynamic cavity method to a graphical model representation obtained from the path-integral formulation of coupled SDEs (Martin-Siggia-Rose-Janssen-DeDominicis formalism [48–50]) and then employing a second-order expansion in the interaction strength to the obtained action, in the spirit of [27]. Notably, our expansion aligns with a Gaussian ansatz for the cavity messages, which is exact for linear systems of SDEs with additive noise and in the presence of global constraints, like in the case of spherical 2-spin models. This formulation also highlights a deep relationship with the use of cavity method in random matrix theory [51, 52]. Furthermore, we introduce a perturbative closure scheme to address the presence of non-linear terms, with applications to relaxation in a cubic force and to noise-driven phase transitions. Although without the algorithmic formulation presented here, Gaussian approximations for local cavity actions, corresponding to its parametrization in terms of one-time and two-times cavity averages, have been previously proposed starting from supersymmetric formulations of stochastic dynamics [53] and within the Bosonic-DMFT for quantum many-body system with imaginary-time formulation [54–56].

The manuscript is organized as follows: section 2 presents the method and its derivation. Section 2.3 illustrates the development of the small-coupling expansion of the dynamic cavity equations for linearly coupled SDEs with linear drift and additive noise. It also demonstrates the close relationship of the method with the theory of sparse random matrices. In section 2.4, we propose the perturbative closure technique to account for non-linearities. Results are presented in section 3, which include both linear dynamics

with additive noise on Random Regular Graphs (RRGs), as discussed in section 3.1, and a linear model with additive noise and cubic perturbation (section 3.2), the noise-driven phase transition in the Bouchaud-Mézard model of wealth distribution (section 3.3) and the spherical 2-spin model (section 3.4) on sparse graphs.

1.1 Notation

We summarise here the specific notation used throughout the paper. We consider graph instances $G = (V, E)$, where $V = \{1, \dots, N\}$ is the set of nodes, while $E \subseteq V \times V$ is the set of edges. The discrete indices corresponding to the nodes of the graph are indicated by letters i, j, k and l . Complex variables are denoted by z , and their real and imaginary part as $x = \text{Re } z$ and $y = \text{Im } z$ respectively, such that $z = x + iy$. The complex conjugate is $z^* = x - iy$. We denote the Dirac distribution over the complex plane as $\delta(z) = \delta(x)\delta(y)$ and we use the derivatives $\partial_z = (\partial_x - i\partial_y)/2$ and $\partial_{z^*} = (\partial_x + i\partial_y)/2$. The measure over the complex plane is defined as $d^2z = dx dy$. We use boldface letters \mathbf{x} for temporal vectors, whose indices are denoted by the letters n and m and correspond to discretized times, and letters with an arrow on top \vec{x} to denote large vectors of size $O(N)$, whose elements can be themselves time vectors (in that case we will use $\vec{\vec{x}}$). Boldface capital letters \mathbf{A} are used to denote large matrices of size $O(N)$, sans serif bold letters \mathbf{A} to denote 2×2 square matrices whose elements can be themselves square matrices, and capital letters A to denote time matrices in which indices correspond to discretized times.

2 Methods

2.1 Dynamic cavity approach for linearly-coupled stochastic dynamics

On each site i of a random graph $G = (V, E)$, we define a continuous degree of freedom $x_i \in \mathbb{R}, \forall i \in V$. The graph is defined by the adjacency matrix $\mathbf{A} = \{a_{ij}\}$ with symmetric elements $a_{ij} = a_{ji} \in \{0, 1\}$ for all $i, j \in V$. Each degree of freedom x_i undergoes a stochastic dynamics characterized by a linear coupling, with coupling constant J_{ij} , with neighboring degrees of freedom x_j , for $j \in \partial i = \{j : (i, j) \in E\}$. The stochastic dynamics under study in the present work can be described by a system of SDEs,

$$\frac{d}{dt}x_i(t) = f[x_i(t)] + \alpha \sum_{j \neq i} a_{ij} J_{ij} x_j(t) + \eta_i(t), \quad (1)$$

in which the noise η_i is Gaussian with mean and covariance

$$\langle \eta_i(t) \rangle = 0 \quad (2a)$$

$$\langle \eta_i(t) \eta_{i'}(t') \rangle = 2g[x_i(t)] \delta_{ii'} \delta(t - t'). \quad (2b)$$

A rescaling factor α is introduced in front of the interaction term to set a scale for the interaction terms. It will be used to perform a formal systematic series expansion around the non-interacting case, in a way reminiscent of Plefka's or other small-coupling expansions [46, 57].

It is more convenient to adopt a discrete-time formulation of the stochastic process by first discretizing the SDE according to the Euler-Maruyama scheme, where time is discretized as $t = n\Delta$, with Δ a small time step approaching zero. The trajectory $x_i(t)$ of node i becomes a time vector \mathbf{x}_i such that $x_i^n = x_i(t = n\Delta)$, and the same holds for the noise trajectories $\eta_i(t)$ which becomes $\Delta\boldsymbol{\eta}_i$ such that $\Delta\eta_i^n = \int_{n\Delta}^{(n+1)\Delta} dt \eta_i(t)$. We adopted here the Ito convention [58] to discretize the noise. We let $T = \mathcal{T}/\Delta$ be the dimension of

the time vector trajectories, where \mathcal{T} is the time horizon of the dynamics. The discretized version of the SDE is therefore

$$x_i^{n+1} = x_i^n + \left(f[x_i^n] + \alpha \sum_{j \neq i} a_{ij} J_{ij} x_j^n \right) \Delta + \Delta \eta_i^n, \quad (3)$$

with

$$\langle \Delta \eta_i^n \rangle = 0 \quad (4a)$$

$$\langle \Delta \eta_i^n \Delta \eta_{i'}^{n'} \rangle = 2g[x_i^n] \Delta \delta_{ii'} \delta_{nn'}. \quad (4b)$$

Classical path-integral representations of SDEs such as the Martin-Siggia-Rose-Janssen-De Dominicis (MSRJD) functional integral formalism [48–50] are based on interpreting the (discretized version of the) SDEs as a set of dynamical constraints for the degrees of freedom and on defining a dynamical partition function as the sum of all possible trajectories averaged over the noise realizations

$$Z = \left\langle \int D\vec{x} \prod_i p_i(x_i^0) \prod_n \delta \left(x_i^{n+1} - x_i^n - f[x_i^n] \Delta - \alpha \Delta \sum_{j \neq i} a_{ij} J_{ij} x_j^n - \Delta \eta_i^n \right) \right\rangle_{\vec{\Delta}\eta} \quad (5a)$$

$$= \left\langle \int D\vec{x} D\vec{\hat{x}} \prod_i p_i(x_i^0) \prod_n e^{-i\hat{x}_i^n (x_i^{n+1} - x_i^n - f[x_i^n] \Delta - \alpha \Delta \sum_{j \neq i} a_{ij} J_{ij} x_j^n - \Delta \eta_i^n)} \right\rangle_{\vec{\Delta}\eta} \quad (5b)$$

where we have defined $\int D\vec{x} = \prod_i \int D\mathbf{x}_i = \prod_{i,n} \int dx_i^n$ and $\int D\vec{\hat{x}} = \prod_i \int D\hat{\mathbf{x}}_i = \prod_{i,n} \int d\hat{x}_i^n$. The average over the Gaussian noise can be performed applying the identity

$$\left\langle e^{i\vec{\hat{x}}^T \vec{\Delta}\eta} \right\rangle_{\vec{\Delta}\eta} = e^{-\frac{1}{2} \vec{\hat{x}}^T g \vec{\hat{x}}} \quad (6)$$

where $g_{ii',nn'} = \langle \Delta \eta_i^n \Delta \eta_{i'}^{n'} \rangle = 2g[x_i^n] \Delta \delta_{ii'} \delta_{nn'}$ is the noise covariance.

It is convenient to factorize the dynamical partition function as follows

$$Z = \int D\vec{x} D\vec{\hat{x}} \prod_i \left\{ p_i(x_i^0) \prod_n e^{-i\hat{x}_i^n (x_i^{n+1} - x_i^n - f[x_i^n] \Delta) - \Delta g[x_i^n] (\hat{x}_i^n)^2} \right\} \\ \times \prod_{i < j} \prod_n e^{\alpha \Delta a_{ij} (J_{ij} i \hat{x}_i^n x_j^n + J_{ji} i \hat{x}_j^n x_i^n)} \quad (7)$$

and use this form to build a corresponding graphical model. The graphical model associated with the partition function is represented in Fig. 1, left panel. By reordering the variables, it becomes clear that, by grouping together for each node i the trajectories \mathbf{x}_i and $\hat{\mathbf{x}}_i$ into a single variable node, the factor graph reproduces a tree-like structure when the underlying interaction graph is also a tree (right panel in Fig. 1). This is a consequence of the linear coupling between variables on neighboring nodes, which makes straightforward to disentangle the locally-loopy structure of the factor graph associated to the space-time problem ¹.

¹In some discrete-state stochastic dynamical processes, it has been shown that a correct cavity approach (Belief Propagation) requires to consider factor graphs with variable nodes containing pairs of trajectories on neighboring sites of the underlying interaction graph [20, 23, 59]. As an alternative, depending on the structure of the dynamics, one can consider a pair of trajectories formed by the physical variable on a node and an auxiliary local field acting on that node and representing the collective effects of the neighboring variables [27]. In the present case, similarly to the application of the cavity approach (Belief Propagation) to the equilibrium Ising model [59], in which the spin variables are linearly coupled with neighboring ones in the energy term, only single-site trajectories are necessary. On the other hand, the conjugate variable $\hat{\mathbf{x}}_i$ is directly coupled with the neighboring nodes and plays a role similar to the auxiliary local field in discrete models [27].




Figure 1: **Graphical model associated with the dynamical partition function.** Left panel: graphical model associated with the dynamical partition function of Eq. (7), where each node corresponds to a variable and each edge corresponds to a factor in the associated factor graph. The time direction is indicated by the arrow on the far right. The factor graph of the model exhibits numerous short loops, rendering a direct cavity approach infeasible. Right panel: graphical model associated with the dynamical partition function when grouping together, for each node i , the trajectories \mathbf{x}_i and $\hat{\mathbf{x}}_i$. The factor graph maintains the same structure as the underlying interaction graph.

According to this graphical model construction, we put forward the following *dynamic cavity equations* as an ansatz for describing linearly coupled stochastic dynamics on sparse networks

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \frac{1}{Z_{ij}^{\text{cav}}} e^{\sum_n \{-i\hat{x}_i^n [x_i^{n+1} - x_i^n - f[x_i^n]\Delta] - g[x_i^n]\Delta(\hat{x}_i^n)^2\}} \times \prod_{k \in \partial i \setminus j} \int D\mathbf{x}_k D\hat{\mathbf{x}}_k c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] e^{\alpha \Delta \sum_n (J_{ki} i\hat{x}_k^n x_i^n + J_{ik} i\hat{x}_i^n x_k^n)} \quad (8)$$

with an arbitrary normalization factor

$$Z_{ij}^{\text{cav}} = \int D\mathbf{x}_i D\hat{\mathbf{x}}_i e^{\sum_n \{-i\hat{x}_i^n [x_i^{n+1} - x_i^n - f[x_i^n]\Delta] - g[x_i^n]\Delta(\hat{x}_i^n)^2\}} \times \prod_{k \in \partial i \setminus j} \int D\mathbf{x}_k D\hat{\mathbf{x}}_k c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] e^{\alpha \Delta \sum_n (J_{ki} i\hat{x}_k^n x_i^n + J_{ik} i\hat{x}_i^n x_k^n)}. \quad (9)$$

The full dynamic cavity marginals can be obtained from the cavity ones as follows

$$c_i[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \frac{1}{Z_i} e^{\sum_n \{-i\hat{x}_i^n [x_i^{n+1} - x_i^n - f[x_i^n]\Delta] - g[x_i^n]\Delta(\hat{x}_i^n)^2\}} \times \prod_{k \in \partial i} \int D\mathbf{x}_k D\hat{\mathbf{x}}_k c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] e^{\alpha \Delta \sum_n (J_{ki} i\hat{x}_k^n x_i^n + J_{ik} i\hat{x}_i^n x_k^n)} \quad (10)$$

and

$$Z_i = \int D\mathbf{x}_i D\hat{\mathbf{x}}_i e^{\sum_n \{-i\hat{x}_i^n [x_i^{n+1} - x_i^n - f[x_i^n]\Delta] - g[x_i^n]\Delta(\hat{x}_i^n)^2\}} \\ \times \prod_{k \in \partial i} \int D\mathbf{x}_k D\hat{\mathbf{x}}_k c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] e^{\alpha \Delta \sum_n (J_{ki} i \hat{x}_k^n x_i^n + J_{ik} i \hat{x}_i^n x_k^n)}. \quad (11)$$

The dynamic cavity marginals $c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i]$ are distributions defined on pairs of real-valued discrete-time trajectories, which become functionals in the limit of continuous time. Without any specific information on the parametric form of the cavity marginals, the dynamic cavity equations in Eq. (8) are of very limited utility in case of general linearly-coupled stochastic dynamics, because their algorithmic implementation is computationally demanding. In the following, we discuss a small coupling expansion of the dynamic cavity equations that leads to a more useful set of equations for physically measurable quantities. We notice that when taking the limit $\Delta \rightarrow 0$, the time sums $\Delta \sum_{n=0}^T$ become time integrals $\int_0^T dt$. For example, the cavity marginals become functionals of the trajectory $x_i(t), \hat{x}_i(t)$

$$c_{i \setminus j} [x_i(t), \hat{x}_i(t)] = \frac{1}{Z_{ij}^{\text{cav}}} e^{\int_0^T dt \{-i\hat{x}_i(t) [\frac{\partial}{\partial i} x_i(t) - f[x_i(t)]] - g[x_i(t)] \hat{x}_i(t)^2\}} \\ \times \prod_{k \in \partial i \setminus j} \int \mathcal{D}x_k(t) \mathcal{D}\hat{x}_k(t) c_{k \setminus i} [x_k(t), \hat{x}_k(t)] e^{\alpha \int_0^T (J_{ik} i \hat{x}_i(t) x_k(t) + J_{ki} i \hat{x}_k(t) x_i(t))} \quad (12)$$

where the integrals have to be understood as path integrals over the trajectories of the neighbors $x_k(t), \hat{x}_k(t)$. For the sake of simplicity, we will only use in what follows the discretized notation unless specified.

2.2 Small-coupling expansion

We exploit the presence of the “small” parameter α to perform an expansion of the exponential term containing the coupling between variables on neighboring sites. The expansion, reminiscent of the Plefka approach [57], can thus be interpreted as a small-coupling expansion around the non-interacting case or, equivalently, as a large-connectivity expansion.

By introducing a local statistical average over cavity marginals

$$\langle \mathcal{O}[\mathbf{x}_k, \hat{\mathbf{x}}_k] \rangle_{\setminus i} = \int D\mathbf{x}_k D\hat{\mathbf{x}}_k c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] \mathcal{O}[\mathbf{x}_k, \hat{\mathbf{x}}_k] \quad (13)$$

we can now define the *cavity averages*

$$\mu_{i \setminus j}(t) = \langle x_i(t) \rangle_{\setminus j} \quad (14)$$

and

$$\hat{\mu}_{i \setminus j}(t) = \langle \hat{x}_i(t) \rangle_{\setminus j}, \quad (15)$$

the *connected (local) two-time cavity correlation function*

$$C_{i \setminus j}(t, t') = \langle x_i(t) x_i(t') \rangle_{\setminus j} - \mu_{i \setminus j}(t) \mu_{i \setminus j}(t') \quad (16a)$$

$$= \tilde{C}_{i \setminus j}(t, t') - \mu_{i \setminus j}(t) \mu_{i \setminus j}(t'), \quad (16b)$$

the *(local) cavity response function*

$$R_{i \setminus j}(t, t') = \langle x_i(t) i \hat{x}_i(t') \rangle_{\setminus j} \quad (17)$$

and the two-time correlation of conjugate variables

$$\tilde{B}_{i \setminus j}(t, t') = \langle i\hat{x}_i(t)i\hat{x}_i(t') \rangle_{\setminus j}. \quad (18)$$

In principle, all these terms should be retained. However, it is expected that $\hat{\mu}_{i \setminus j}(t)$ and $\tilde{B}_{i \setminus j}(t, t')$ vanish for any t and t' because the dynamics is causal [46, 50, 60]. In addition, it can be demonstrated that, since $R_{i \setminus j}(t, t')$ is the response function of $x_i(t)$ to a perturbing field², it vanishes for any $t' \geq t$. Defining the discretized averages as $\mu_{i \setminus j}^n = \mu_{i \setminus j}(t = n\Delta)$, $\tilde{C}_{i \setminus j}^{n, n'} = \tilde{C}_{i \setminus j}(t = n\Delta, t' = n'\Delta)$ and $R_{i \setminus j}^{n, n'} = R_{i \setminus j}(t = n\Delta, t' = n'\Delta)$, the cavity marginal can be expanded at second order in α , obtaining

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] \propto \exp \left\{ \sum_n (-i\hat{x}_i^n (x_i^{n+1} - x_i^n - f[x_i^n]\Delta) - \Delta g[x_i^n](\hat{x}_i^n)^2) + \alpha \Delta \sum_{k \in \partial i \setminus j} \sum_n J_{ik} i\hat{x}_i^n \mu_{k \setminus i}^n \right. \\ \left. + \frac{1}{2} \alpha^2 \Delta^2 \sum_{k \in \partial i \setminus j} \sum_{n, n'} \left[J_{ik}^2 i\hat{x}_i^n C_{k \setminus i}^{n, n'} i\hat{x}_i^{n'} + 2J_{ik} J_{ki} i\hat{x}_i^n R_{k \setminus i}^{n, n'} x_i^{n'} \right] \right\}. \quad (19)$$

Having already discussed some possible justifications for performing the expansion, we will henceforth set $\alpha = 1$.

2.3 Gaussian Expansion Cavity Method for linear dynamics with additive noise

Consider the simplest dynamical scenario represented by a system of linear SDEs with additive thermal noise. Such a system is exactly solvable by direct diagonalization, so that its long-term dynamical properties can be fully determined by examining the spectral properties of the underlying interaction matrix. In this context, the second-order truncation of the small-coupling expansion yields Gaussian cavity messages. These messages are parametrized by one-time and two-time averages of the variables x_i and \hat{x}_i , from which a closed set of dynamical equations can be derived. We will demonstrate that solving these equations provides sufficient information to reconstruct (within the cavity approximation) the spectral density of the underlying random graph. This reveals a close relationship between our method and some well-established applications of the cavity method in random matrix theory.

2.3.1 Gaussian cavity ansatz

The Gaussian structure of the cavity marginals in the space of pairs of trajectories \mathbf{x}_i and $\hat{\mathbf{x}}_i$ becomes apparent once we substitute $f[x_i(t)] = -\lambda_i x_i(t)$ and $g[x_i(t)] = D$ into the expression in Eq. (19). For shortness of notation one can define

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \frac{1}{Z_{ij}^{\text{cav}}} e^{-S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i]} \quad (20)$$

where $S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i]$ is the Gaussian cavity action

$$S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \sum_n (i\hat{x}_i^n (x_i^{n+1} - x_i^n + \lambda_i x_i^n \Delta) + \Delta D (\hat{x}_i^n)^2) - \Delta \sum_{k \in \partial i \setminus j} \sum_n J_{ik} i\hat{x}_i^n \mu_{k \setminus i}^n \\ - \frac{1}{2} \Delta^2 \sum_{k \in \partial i \setminus j} \sum_{n, n'} \left[J_{ik}^2 i\hat{x}_i^n C_{k \setminus i}^{n, n'} i\hat{x}_i^{n'} + 2J_{ik} J_{ki} i\hat{x}_i^n R_{k \setminus i}^{n, n'} x_i^{n'} \right]. \quad (21)$$

²Adding a small external field $h_i(t)$ to the SDE Eq. (1) a term $i\hat{x}_i^n h_i^n$ appears in the exponent of the cavity measure, from which $R_{i \setminus j}(t, t') = \delta \langle x_i(t) \rangle / \delta h_i(t')|_{h=0}$.

Taking the limit $\Delta \rightarrow 0$, the action becomes a functional of the pair of trajectories \mathbf{x}_i and $\hat{\mathbf{x}}_i$

$$S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \int dt \left[i\hat{x}_i(t) \left(\frac{\partial}{\partial t} x_i(t) + \lambda_i x_i(t) \right) + D\hat{x}_i^2(t) - \sum_{k \in \partial i \setminus j} J_{ik} i\hat{x}_i(t) \mu_{k \setminus i}(t) \right] - \frac{1}{2} \int dt \int dt' \sum_{k \in \partial i \setminus j} [J_{ik}^2 i\hat{x}_i(t) C_{k \setminus i}(t, t') i\hat{x}_i(t') + 2J_{ik} J_{ki} i\hat{x}_i(t) R_{k \setminus i}(t, t') x_i(t')]. \quad (22)$$

Motivated by this result, it is convenient to consider again the discretized Euler-Maruyama version of the stochastic dynamics and put forward a Gaussian parametric ansatz for the corresponding dynamic cavity marginal,

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \frac{1}{Z_{ij}^{\text{cav}}} e^{-\frac{1}{2}(\mathbf{X}_i - \mathbf{M}_{i \setminus j})^T \mathbf{G}_{i \setminus j}^{-1} (\mathbf{X}_i - \mathbf{M}_{i \setminus j})} \quad (23)$$

with normalization factor

$$Z_{ij}^{\text{cav}} = \left((2\pi)^{2(T+1)} \det \mathbf{G}_{i \setminus j} \right)^{-1/2} \quad (24)$$

where $\mathbf{X}_i^T = (\mathbf{x}_i, i\hat{\mathbf{x}}_i)$ is a $2(T+1)$ dimensional vector. According to the previous derivation, $\mathbf{M}_{i \setminus j}^T = (\boldsymbol{\mu}_{i \setminus j}, i\hat{\boldsymbol{\mu}}_{i \setminus j})$ is a $2(T+1)$ dimensional vector and the elements of $\mathbf{G}_{i \setminus j}$ are $(T+1) \times (T+1)$ time matrices

$$\mathbf{G}_{i \setminus j} = \begin{pmatrix} C_{i \setminus j} & R_{i \setminus j} \\ R_{i \setminus j}^T & B_{i \setminus j} \end{pmatrix} \quad (25)$$

where $C_{i \setminus j}^{n, n'} = \langle x_i^n x_i^{n'} \rangle_{i \setminus j} - \langle x_i^n \rangle_{i \setminus j} \langle x_i^{n'} \rangle_{i \setminus j}$, $R_{i \setminus j}^{n, n'} = \langle x_i^n i\hat{x}_i^{n'} \rangle_{i \setminus j}$ and $B_{i \setminus j}^{n, n'} = \langle i\hat{x}_i^n i\hat{x}_i^{n'} \rangle_{i \setminus j} - \langle i\hat{x}_i^n \rangle_{i \setminus j} \langle i\hat{x}_i^{n'} \rangle_{i \setminus j}$. Again, due to the causality of the dynamics, $\hat{\boldsymbol{\mu}}_{i \setminus j}$ and $B_{i \setminus j}$ are assumed to be zero for all times. The validity of this assumption can be verified self-consistently.

In matrix form, the cavity expression in Eq. (8) becomes

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] \propto e^{-\frac{1}{2} \mathbf{X}_i^T \mathbf{G}_{0, i}^{-1} \mathbf{X}_i} \prod_{k \in \partial i \setminus j} \int D\mathbf{X}_k e^{-\frac{1}{2} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})} e^{-\mathbf{X}_i^T \mathbf{J}_{ik} \mathbf{X}_k}, \quad (26)$$

in which we introduced a matrix notation for the interaction terms,

$$\mathbf{J}_{ik} = \begin{pmatrix} 0 & J_{ki} \Delta \mathbb{I} \\ J_{ik} \Delta \mathbb{I} & 0 \end{pmatrix} \quad (27)$$

and the matrix operator

$$\mathbf{G}_{0, i}^{-1} = \begin{pmatrix} 0 & \mathbb{E}^{-1} - \mathbb{I} + \lambda_i \Delta \mathbb{I} \\ \mathbb{E}^{+1} - \mathbb{I} + \lambda_i \Delta \mathbb{I} & -2\Delta D \mathbb{I} \end{pmatrix} \quad (28)$$

where \mathbb{I} is the $(T+1) \times (T+1)$ identity matrix and $\mathbb{E}^{\pm 1}$ are shift operators represented by $(T+1) \times (T+1)$ square matrices

$$\mathbb{E}^{-1} = \begin{pmatrix} \ddots & 0 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & \ddots \end{pmatrix}, \quad \mathbb{E}^{+1} = \begin{pmatrix} \ddots & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & \ddots \end{pmatrix}. \quad (29)$$

Performing the Gaussian integrals, and using $\mathbf{X}_i^T \mathbf{J}_{ik} = (\mathbf{J}_{ik}^T \mathbf{X}_i)^T$, the cavity marginal can be written as follows

$$c_{i \setminus j} [\mathbf{x}_i, \hat{\mathbf{x}}_i] \propto e^{-\frac{1}{2} \mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i} \prod_{k \in \partial i \setminus j} \int D\mathbf{X}_k e^{-\frac{1}{2} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i}) + \mathbf{X}_i^T \mathbf{J}_{ik} \mathbf{X}_k} \quad (30a)$$

$$\propto e^{-\frac{1}{2} \mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i + \frac{1}{2} \sum_{k \in \partial i \setminus j} \mathbf{X}_i^T \mathbf{J}_{ik} \mathbf{G}_{k \setminus i} \mathbf{J}_{ik}^T \mathbf{X}_i + \sum_{k \in \partial i \setminus j} \mathbf{X}_i^T \mathbf{J}_{ik} \mathbf{M}_{k \setminus i}}. \quad (30b)$$

Expanding the matrix product in the exponent of Eq. (23) and comparing it with Eq. (30b) we obtain an identity for the exponents

$$\begin{aligned} -\frac{1}{2} \mathbf{X}_i^T \mathbf{G}_{i \setminus j}^{-1} \mathbf{X}_i + \frac{1}{2} \mathbf{X}_i^T \mathbf{G}_{i \setminus j}^{-1} \mathbf{M}_{i \setminus j} + \frac{1}{2} \mathbf{M}_{i \setminus j}^T \mathbf{G}_{i \setminus j}^{-1} \mathbf{X}_i &= -\frac{1}{2} \mathbf{X}_i^T \left(\mathbf{G}_{0,i}^{-1} - \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{G}_{k \setminus i} \mathbf{J}_{ik}^T \right) \mathbf{X}_i \\ &+ \frac{1}{2} \mathbf{X}_i^T \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{M}_{k \setminus i} + \frac{1}{2} \sum_{k \in \partial i \setminus j} (\mathbf{J}_{ik} \mathbf{M}_{k \setminus i})^T \mathbf{X}_i. \end{aligned} \quad (31)$$

Since the identity must be verified for any configuration \mathbf{X}_i , we can equate separately the terms appearing with different powers of \mathbf{X}_i , that results in two matrix relations

$$\mathbf{G}_{i \setminus j} = \left[\mathbf{G}_{0,i}^{-1} - \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{G}_{k \setminus i} \mathbf{J}_{ik}^T \right]^{-1} \quad (32a)$$

$$\mathbf{G}_{i \setminus j}^{-1} \mathbf{M}_{i \setminus j} = \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{M}_{k \setminus i}. \quad (32b)$$

Substituting Eq. (32a) into Eq. (32b), after some algebra, we obtain two sets of local equations for the cavity propagator (or cavity Green's function) $\mathbf{G}_{i \setminus j}$ and for the cavity means $\mathbf{M}_{i \setminus j}$, that is

$$\mathbf{G}_{0,i}^{-1} \mathbf{G}_{i \setminus j} = \mathbb{I} + \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{G}_{k \setminus i} \mathbf{J}_{ik}^T \mathbf{G}_{i \setminus j} \quad (33a)$$

$$\mathbf{G}_{0,i}^{-1} \mathbf{M}_{i \setminus j} = \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{M}_{k \setminus i} + \sum_{k \in \partial i \setminus j} \mathbf{J}_{ik} \mathbf{G}_{k \setminus i} \mathbf{J}_{ik}^T \mathbf{M}_{i \setminus j}, \quad (33b)$$

where \mathbb{I} stays for the identity matrix

$$\mathbb{I} = \begin{pmatrix} \mathbb{I} & 0 \\ 0 & \mathbb{I} \end{pmatrix}. \quad (34)$$

Performing the matrix product in Eq. (33a) explicitly results in a set of dynamical equations for the cavity response functions and the cavity correlation functions,

$$R_{0,i}^{-1} R_{i \setminus j} = \mathbb{I} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k \setminus i} R_{i \setminus j} \quad (35a)$$

$$R_{0,i}^{-1} C_{i \setminus j} = 2D\Delta R_{i \setminus j}^T + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k \setminus i} R_{i \setminus j}^T + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k \setminus i} C_{i \setminus j}, \quad (35b)$$

where the ‘‘non-interacting’’ response function $R_{0,i}$, satisfying the relation $R_{0,i}^{-1} = \mathbb{E}^{+1} - \mathbb{I} + \lambda_i \Delta \mathbb{I}$, was also introduced. From Eq. (33b) we obtain instead a dynamical equation for the cavity mean $\boldsymbol{\mu}_{i \setminus j}$,

$$R_{0,i}^{-1} \boldsymbol{\mu}_{i \setminus j} = \Delta \sum_{k \in \partial i \setminus j} J_{ik} \boldsymbol{\mu}_{k \setminus i} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k \setminus i} \boldsymbol{\mu}_{i \setminus j}. \quad (36)$$

Equations (33a) and (33b) also demonstrate that the assumption that the quantities $\hat{\mu}_{i\setminus j}$ and $B_{i\setminus j}$ vanish is self-consistently verified. In the Supplemental Material [61], a more general version of the equations, in which $\hat{\mu}_{i\setminus j}$ and $B_{i\setminus j}$ are not zero, is reported.

In the continuous-time limit $\Delta \rightarrow 0$, the non-interacting response takes the form $R_{0,i}^{-1}/\Delta \rightarrow \delta(t-t')(\partial_t + \lambda_i)$, and the previous matrix equations can be replaced by a (closed) set of integro-differential equations,

$$\frac{d}{dt}\mu_{i\setminus j}(t) = -\lambda_i\mu_{i\setminus j}(t) + \sum_{k \in \partial i \setminus j} J_{ik}\mu_{k\setminus i}(t) + \sum_{k \in \partial i \setminus j} \int_0^t dt' J_{ik}R_{k\setminus i}(t, t')J_{ki}\mu_{i\setminus j}(t') \quad (37a)$$

$$\frac{\partial}{\partial t}R_{i\setminus j}(t, t') = -\lambda_i R_{i\setminus j}(t, t') + \sum_{k \in \partial i \setminus j} \int_{t'}^t dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}R_{i\setminus j}(t'', t') + \delta(t, t') \quad (37b)$$

$$\begin{aligned} \frac{\partial}{\partial t}C_{i\setminus j}(t, t') &= -\lambda_i C_{i\setminus j}(t, t') + \sum_{k \in \partial i \setminus j} \int_0^t dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}C_{i\setminus j}(t'', t') + 2DR_{i\setminus j}(t', t) \\ &+ \sum_{k \in \partial i \setminus j} \int_0^{t'} dt'' R_{i\setminus j}(t', t'')J_{ik}^2 C_{k\setminus i}(t, t''). \end{aligned} \quad (37c)$$

which is the main result of the *Gaussian Expansion Cavity Method (GECaM)* in the case of linear dynamics with additive noise.

A set of self-consistent equations for the full averages (in terms of the cavity ones) can be similarly obtained,

$$\frac{d}{dt}\mu_i(t) = -\lambda_i\mu_i(t) + \sum_{k \in \partial i} J_{ik}\mu_{k\setminus i}(t) + \sum_{k \in \partial i} \int_0^t dt' J_{ik}R_{k\setminus i}(t, t')J_{ki}\mu_i(t') \quad (38a)$$

$$\frac{\partial}{\partial t}R_i(t, t') = -\lambda_i R_i(t, t') + \sum_{k \in \partial i} \int_{t'}^t dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}R_i(t'', t') + \delta(t-t') \quad (38b)$$

$$\begin{aligned} \frac{\partial}{\partial t}C_i(t, t') &= -\lambda_i C_i(t, t') + \sum_{k \in \partial i} \int_0^t dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}C_i(t'', t') + 2DR_i(t', t) \\ &+ \sum_{k \in \partial i} \int_0^{t'} dt'' R_i(t', t'')J_{ik}^2 C_{k\setminus i}(t, t''), \end{aligned} \quad (38c)$$

where we have defined the *full (local) mean* $\mu_i(t)$, the *full (local) response function* $R_i(t, t') = \langle x_i(t)\hat{x}_i(t') \rangle_i$ and the *full (local) two-times correlation function* $C_i(t, t') = \langle x_i(t)x_i(t') \rangle_i$. Here the average has to be intended over the full marginal

$$\langle \mathcal{O}[x_i, \hat{x}_i] \rangle_i = \int D\mathbf{x}_i D\hat{\mathbf{x}}_i c_i[\mathbf{x}_i, \hat{\mathbf{x}}_i] \mathcal{O}[\mathbf{x}_i, \hat{\mathbf{x}}_i]. \quad (39)$$

These GECaM equations are an intuitive cavity generalization of the dynamical TAP equations derived in [46] by means of the Extended Plefka Expansion, and reduce to them for sufficiently dense interaction graphs (in particular for fully-connected ones).

In the long-time limit $t, t' \rightarrow \infty$, the response functions and correlation functions become time translational invariant (TTI). In this limit, response/correlation functions depend only on time differences, that is $R(t, t') = R(t-t' = \tau) = R(\tau)$ and $C(t, t') = C(t-t' = \tau) = C(\tau)$. The TTI response functions obey the equations

$$\frac{\partial}{\partial \tau}R_{i\setminus j}(\tau) = -\lambda_i R_{i\setminus j}(\tau) + \sum_{k \in \partial i \setminus j} \int_0^\tau ds J_{ik}R_{k\setminus i}(\tau-s)J_{ki}R_{i\setminus j}(s) + \delta(\tau). \quad (40)$$

Introducing the (one-sided) Laplace transform $R(z) = \int_0^{+\infty} \frac{d\tau}{2\pi} R(\tau) e^{-z\tau}$, and moving to the Laplace domain, we get

$$zR_{i\setminus j}(z) = -\lambda_i R_{i\setminus j}(z) + \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k\setminus i}(z) R_{i\setminus j}(z) + 1 \quad (41)$$

or, explicitly,

$$R_{i\setminus j}(z) = \frac{1}{z + \lambda_i - \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k\setminus i}(z)}. \quad (42)$$

Similarly, the TTI equations for correlation functions read

$$\begin{aligned} \frac{\partial}{\partial \tau} C_{i\setminus j}(\tau) &= -\lambda_i C_{i\setminus j}(\tau) + \sum_{k \in \partial i \setminus j} \int_{-\infty}^{\infty} ds J_{ik} R_{k\setminus i}(\tau - s) J_{ki} C_{i\setminus j}(s) + 2DR_{i\setminus j}(-\tau) \\ &+ \sum_{k \in \partial i \setminus j} \int_{-\infty}^{\infty} ds R_{i\setminus j}(-s) J_{ik}^2 C_{k\setminus i}(\tau - s). \end{aligned} \quad (43)$$

Introducing the two-sided Laplace transform $C(z) = \int_{-\infty}^{+\infty} \frac{d\tau}{2\pi} C(\tau) e^{-z\tau}$, the equation becomes

$$zC_{i\setminus j}(z) = -\lambda_i C_{i\setminus j}(z) + \sum_{k \in \partial i \setminus j} J_{ik} R_{k\setminus i}(z) J_{ki} C_{i\setminus j}(z) + 2DR_{i\setminus j}(-z) + \sum_{k \in \partial i \setminus j} R_{i\setminus j}(-z) J_{ik}^2 C_{k\setminus i}(z). \quad (44)$$

Solving the equation for $C_{i\setminus j}(z)$ we obtain

$$C_{i\setminus j}(z) = \frac{R_{i\setminus j}(-z)}{z + \lambda_i - \sum_{k \in \partial i \setminus j} J_{ik} J_{ki} R_{k\setminus i}(z)} \left[2D + \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k\setminus i}(z) \right] \quad (45a)$$

$$= R_{i\setminus j}(-z) R_{i\setminus j}(z) \left[2D + \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k\setminus i}(z) \right]. \quad (45b)$$

Equivalently, the full response functions and correlation functions obey the following equations in the Laplace space

$$R_i(z) = \frac{1}{z + \lambda_i - \sum_{k \in \partial i} J_{ik} J_{ki} R_{k\setminus i}(z)} \quad (46a)$$

$$C_i(z) = R_i(-z) R_i(z) \left[2D + \sum_{k \in \partial i} J_{ik}^2 C_{k\setminus i}(z) \right]. \quad (46b)$$

2.3.2 Relation with random matrix theory

In the previous derivation, we have considered single instances of the coupling matrix $[\mathbf{J}]_{ij} = a_{ij} J_{ij}$. However, when considering disordered systems, at least one between the underlying interaction graph G and the couplings is usually assumed to be drawn from a probability distribution. This implies that the coupling matrix \mathbf{J} is a random matrix [62, 63].

It is convenient to use a vectorial form to write a general linear system of SDEs with additive thermal noise,

$$\frac{d}{dt} \vec{x}(t) = -\boldsymbol{\lambda} \vec{x}(t) + \mathbf{J} \vec{x}(t) + \vec{\eta}(t) + \vec{h}(t), \quad (47)$$

in which a linear term \vec{h} was also added and $[\boldsymbol{\lambda}]_{ij} = \lambda_{ij}\delta_{ij}$. The solution can be formally written as follows

$$\vec{x}(t) = \int_0^t dt' e^{(\mathbf{J}-\boldsymbol{\lambda})(t-t')} \left[\vec{\eta}(t') + \vec{h}(t') \right], \quad (48)$$

which gives access to the full response function matrix,

$$\mathbf{R}(t, t') = \frac{\delta}{\delta \vec{h}(t')} \langle \vec{x}(t) \rangle \Big|_{\vec{h}=0} = \Theta(t-t') e^{(\mathbf{J}-\boldsymbol{\lambda})(t-t')}. \quad (49)$$

The response function has a TTI form, that is

$$\mathbf{R}(\tau) = \Theta(\tau) e^{(\mathbf{J}-\boldsymbol{\lambda})\tau}. \quad (50)$$

Passing to the Laplace space,

$$\mathbf{R}(z) = \int_0^\infty d\tau e^{(\mathbf{J}-\boldsymbol{\lambda})\tau} e^{-z\tau} = [z - (\mathbf{J} - \boldsymbol{\lambda})]^{-1}, \quad (51)$$

the response function $\mathbf{R}(z)$ can be interpreted as the resolvent of the random matrix $\tilde{\mathbf{J}} = \mathbf{J} - \boldsymbol{\lambda}$. Its diagonal elements, which correspond in our case to the full node response functions $R_i(z)$, allow us to directly compute the average spectral distribution of the random matrix $\tilde{\mathbf{J}}$. If $\tilde{\mathbf{J}}$ is Hermitian the spectral distributions will be non-zero only for some cuts on the real axis. We can therefore safely substitute z with his real part $x = \text{Re}(z)$. The spectral distribution of $\tilde{\mathbf{J}}$ is then recovered as the inverse Stieltjes transform of the trace of the resolvent [62, 64, 65],

$$\rho_{\tilde{\mathbf{J}}}(x) = \frac{1}{N} \sum_i \delta(x - \nu_i(\tilde{\mathbf{J}})) = \frac{1}{\pi N} \lim_{\varepsilon \rightarrow 0^+} \text{Im} \left[\sum_i R_i(x - i\varepsilon) \right], \quad (52)$$

where $\nu_i(\tilde{\mathbf{J}})$ are the eigenvalues of $\tilde{\mathbf{J}}$. Since

$$\nu_i(\tilde{\mathbf{J}})|\nu_i\rangle = \tilde{\mathbf{J}}|\nu_i\rangle = \mathbf{J}|\nu_i\rangle - \boldsymbol{\lambda}|\nu_i\rangle = [\nu_i(\mathbf{J}) - \lambda_i] |\nu_i\rangle \quad (53)$$

the empirical spectral distribution of the random matrix \mathbf{J} is easily obtained as

$$\rho_{\mathbf{J}}(x) = \frac{1}{N} \sum_i \delta(x - \nu_i(\mathbf{J})) = \frac{1}{N} \sum_i \delta(x - \lambda_i - \nu_i(\tilde{\mathbf{J}})), \quad (54)$$

from which

$$\rho_{\mathbf{J}}(x) = \frac{1}{\pi N} \lim_{\varepsilon \rightarrow 0^+} \text{Im} \left[\sum_i R_i(x - \lambda_i - i\varepsilon) \right]. \quad (55)$$

If instead \mathbf{J} is non-hermitian we need to resort to hermitianisation methods [52, 66]. We show in Supplemental Material [61] how this can be adapted to our setting.

The relation between the GECaM approach and random matrix theory is double sided. One can compute the response/correlation functions of the system knowing the spectral distribution of the interaction matrix. In the case of a system of linear SDEs with additive thermal noise, the dynamics is diffusive and depends on the spectrum of the matrix \mathbf{J} . Knowing the spectral density is therefore sufficient to compute the response and correlation functions of the linear system.

Let $\rho(x)$ be the average spectral density of the random matrix ensemble from which \mathbf{J} was sampled, towards which the empirical spectral distribution $\rho_{\mathbf{J}}(z)$ converges in the thermodynamic limit. We consider here only symmetric real random matrices $\mathbf{J} \in \mathbb{R}^{N,N}$.

The response matrix of the system can be formally written as Eq. (50). An analogous equation can be found for the correlation matrix (also known as the correlator of the matrix)

$$\mathbf{C}(t, t') = \langle \vec{x}(t) \vec{x}^T(t') \rangle = \int_0^t dt_1 \int_0^{t'} dt_2 e^{(\mathbf{J}-\lambda)(t-t_1)} \langle \vec{\eta}(t_1) \vec{\eta}(t_2) \rangle e^{(\mathbf{J}^T-\lambda)(t'-t_2)} \quad (56a)$$

$$= 2D \int_0^{\min(t, t')} dt_1 e^{(\mathbf{J}-\lambda)(t-t_1)} e^{(\mathbf{J}^T-\lambda)(t'-t_1)}, \quad (56b)$$

If the coupling matrix \mathbf{J} is symmetric, the correlator is symmetric as well. Moreover, in the long time limit, it becomes explicitly TTI, i.e.

$$\mathbf{C}(\tau) = D \int_{|\tau|}^{\infty} dw e^{(\mathbf{J}-\lambda)w} \quad (57)$$

where we have defined $w = t + t' - 2t_1$. In this case, the fluctuation-dissipation theorem (FDT) is expected to hold, because the system satisfies detailed balance. Hence, we have

$$D\mathbf{R}(\tau) = -\frac{\partial}{\partial \tau} \mathbf{C}(\tau), \quad (58)$$

which can be easily checked comparing Eq. (50) with Eq. (57).

The response and correlation functions of the system can be computed from the spectral density as

$$R(\tau) = \left\langle \frac{1}{N} \sum_i R_i(\tau) \right\rangle = \langle \text{Tr } \mathbf{R}(\tau) \rangle = \int dx \rho(x) \Theta(\tau) e^{(x-\lambda)\tau} \quad (59a)$$

$$C(\tau) = \langle \text{Tr } \mathbf{C}(\tau) \rangle = \int dx \rho(x) D \int_{|\tau|}^{\infty} dw e^{(x-\lambda)w}, \quad (59b)$$

where we have assumed for simplicity $\lambda_i = \lambda$ for each site i .

2.4 Perturbative closure technique in the presence of non-gaussian terms

When terms higher than quadratic (or bilinear) in \mathbf{x}_i and $\hat{\mathbf{x}}_i$ appear in the local effective action at the exponent of the cavity message $c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i]$, the corresponding cavity probability is not Gaussian. This can be due to the presence of non-linear drift terms or multiplicative noise terms in the original SDEs. In this case, the cavity probability can be written as

$$c_{i \setminus j}[\mathbf{x}_i, \hat{\mathbf{x}}_i] \propto e^{-S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i] - S_{i \setminus j}^I[\mathbf{x}_i, \hat{\mathbf{x}}_i]}, \quad (60)$$

where $S_{i \setminus j}^0[\mathbf{x}_i, \hat{\mathbf{x}}_i] = \frac{1}{2} (\mathbf{X}_i - \mathbf{M}_{i \setminus j})^T \mathbf{G}_{i \setminus j}^{-1} (\mathbf{X}_i - \mathbf{M}_{i \setminus j})$ is the usual Gaussian action in Eq. (22), while $S_{i \setminus j}^I[\mathbf{x}_i, \hat{\mathbf{x}}_i]$ is the interaction action.

The non-quadratic terms can be addressed by employing a perturbative expansion and a self-consistent calculation of the response and correlation functions, similar to the methodology used in the *mode-coupling theory* of disordered systems [34, 67]. For every edge (i, j) we proceed as follow:

1. The incoming cavity messages are assumed to be Gaussian, parametrized by response functions $R_{k \setminus i}(t, t')$ and correlation functions $C_{k \setminus i}(t, t')$, which are collected in the matrix $\mathbf{G}_{k \setminus i}$, i.e.

$$c_{k \setminus i}[\mathbf{x}_k, \hat{\mathbf{x}}_k] \propto e^{-\frac{1}{2} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})}. \quad (61)$$

2. The matrix update is performed to compute the local Gaussian matrix $\mathbf{G}_{i \setminus j}^0$

$$\mathbf{G}_{i \setminus j}^0 = \left[\mathbf{G}_{0,i}^{-1} - \sum_{k \in \partial i \setminus j} J_{ik} \mathbf{G}_{k \setminus i} J_{ik}^T \right]^{-1}. \quad (62)$$

3. At this point, $\mathbf{G}_{i \setminus j}^0$ is known as function of the incoming $\{\mathbf{G}_{k \setminus i}\}$, but it is not in a closed form. Performing a perturbative expansion of the site factor, which is not Gaussian, and closing it self-consistently, the following Dyson equation is obtained

$$[\mathbf{G}_{i \setminus j}]^{-1} = [\mathbf{G}_{i \setminus j}^0]^{-1} - \Sigma_{i \setminus j}^{MF}, \quad (63)$$

where $\Sigma_{i \setminus j}^{MF}$ is the sum of all the 1PI contributions to the self energy $\Sigma_{i \setminus j}$, giving a so-called *mean-field* or *Hartree-Fock* approximation. The latter is also expressed in terms of $\mathbf{G}_{i \setminus j}^0$ and thus $\{\mathbf{G}_{k \setminus i}\}$.

The procedure is then repeated at every cavity message update, until convergence. Two applications of this self-consistent perturbative algorithm are discussed in sections 3.2-3.3.

3 Results

In this Section, we present analytical and numerical results on four straightforward applications of the GECaM approach. For analytical convenience, here we perform calculations only in the ensemble of Random Regular Graphs (RRG). First, we employ this method to study the (exactly solvable) case of a system of linear SDEs on a RRG with degree K and homogeneous couplings, directly showing its tight connection with well-known results from random matrix theory. Then, the additional effect of a local cubic force term is considered. This model exhibits a phase transition between two different stationary states upon varying a control parameter. The self-consistent perturbative closure method of Sect. 2.4 can be used to study the location of the critical point as function of K . Similarly, the self-consistent perturbative closure technique is employed to locate the critical point of a non-equilibrium phase transition driven by multiplicative noise. Finally, we demonstrate that the GECaM approach provides the exact solution for the relaxation dynamics of the spherical 2-spin model on a random regular graph. This holds true in the thermodynamic limit, where the tree-like approximation is valid.

3.1 Linear dynamics with thermal noise on Random Regular Graphs

Although the cavity equations for response and correlation function can be written on any instance of the underlying graph, to obtain analytical results it is convenient to work in the thermodynamic limit (or at the ensemble level) and assume homogeneity of all other parameters (i.e. $J_{ij} = J_{ji} = J$ for any $(i, j) \in E$, $\lambda_i = \lambda$ for any $i \in V$). Because of the equivalence between different nodes in this limit, we can forget about cavity indices and indicate with \hat{R} and \hat{C} the cavity responses and correlations and with R and C the full ones. Within this simplified setting, it is possible to analytically compute the responses and correlations in Laplace space, at least for a linear dynamics with additive noise. In this case, the cavity functions should satisfy the simplified version of self-consistent equations Eqs. (42) and (45b), i.e.

$$\hat{R}(z) = \frac{1}{z + \lambda - (K - 1)J^2 \hat{R}(z)} \quad (64a)$$

$$\hat{C}(z) = \hat{R}(-z) \hat{R}(z) \left[2D + (K - 1)J^2 \hat{C}(z) \right], \quad (64b)$$

where we have considered $R_{i \setminus j}(z) = \hat{R}(z)$ for any edge (i, j) due to the homogeneity of graph structure and interaction couplings. Solving Eq. (64a), we obtain the explicit expression of $\hat{R}(z)$ in the Laplace space,

$$\hat{R}(z) = \frac{z + \lambda \pm \sqrt{(z + \lambda)^2 - 4(K - 1)J^2}}{2(K - 1)J^2}. \quad (65)$$

The full response function $R_i(z) \equiv R(z)$, $\forall i$, can be straightforwardly computed from a label-free version of Eq. (46a), that is

$$R(z) = \frac{1}{z + \lambda - KJ^2\hat{R}(z)} \quad (66a)$$

$$= \frac{1}{2} \frac{(K - 2)(z + \lambda) \pm K\sqrt{(z + \lambda)^2 - 4(K - 1)J^2}}{K^2J^2 - (z + \lambda)^2}. \quad (66b)$$

Depending on the choice of the branch of the square root we obtain two different expressions $R_+(z)$ and $R_-(z)$, respectively. The response function in the long-time limit $R(t - t')$ must tend to one as $t - t' \rightarrow 0$. Therefore $R(z)$ has to decay as $1/z$ for $z \rightarrow \infty$. This correct behaviour is exhibited by the $R_-(z)$ branch. Henceforth, we will set $\hat{R}(z) \equiv \hat{R}_-(z)$ and $R(z) \equiv R_-(z)$ in the following.

Moreover, solving Eq. (64b) for $\hat{C}(z)$, we get

$$\hat{C}(z) = \frac{2D\hat{R}(-z)\hat{R}(z)}{1 - (K - 1)J^2\hat{R}(-z)\hat{R}(z)}, \quad (67)$$

and using the expression of $\hat{R}(z)$ in Eq. (65), we obtain an explicit expression for the correlation function in the Laplace space,

$$\hat{C}(z) = \frac{D}{(K - 1)J^2} \left[\frac{\sqrt{(z + \lambda)^2 - 4(K - 1)J^2}}{2z} - \frac{\sqrt{(z - \lambda)^2 - 4(K - 1)J^2}}{2z} - 1 \right], \quad (68)$$

Finally, the full correlation $C_i(z) = C(z)$ can be computed using Eq. (46b), i.e.

$$C(z) = R(z)R(-z) \left[2D + KJ^2\hat{C}(z) \right]. \quad (69)$$

It is instructive to show how the corresponding spectral distribution, namely the *Kesten-McKay distribution*, can be recovered from the GECaM response and vice-versa.

The average spectral density $\rho(x)$ of \mathbf{A} , where \mathbf{A} is the adjacency matrix of the RRG, was originally computed by Kesten and McKay starting from general theorems [68, 69]. For an RRG with locally tree-like structure and degree K , the spectral density converges in the thermodynamic limit $N \rightarrow \infty$ to the Kesten-McKay distribution

$$\rho(x) = \frac{K\sqrt{4(K - 1) - x^2}}{2\pi(K^2 - x^2)}, \quad |x| \leq 2\sqrt{K - 1}. \quad (70)$$

Starting from Eq. (55), and inserting the expression for the response computed in Eq. (66b), we obtain

$$\begin{aligned} \rho(x) &= \frac{J}{\pi} \lim_{\varepsilon \rightarrow 0^+} \text{Im} R(Jx - \lambda - i\varepsilon) \\ &= \frac{J}{\pi} \frac{\left[(x^2 - 4(K - 1))^2 \right]^{1/4}}{2J(x^2 - K^2)} \sin \left[\frac{1}{2} \arg(x^2 - 4(K - 1)) \right], \end{aligned} \quad (71)$$

from which we recover the Kesten-McKay distribution for $|x| \leq 2\sqrt{K-1}$.

Proceeding in the opposite direction, the response function can be computed from the knowledge of the Kesten-McKay distribution. The exact expression of the response function in the Laplace space, indeed, can be obtained from Eq. (51),

$$R(z) = \langle \text{Tr } \mathbf{R}(z) \rangle = \int dx \rho(x) [z - (Jx - \lambda)]^{-1}. \quad (72)$$

Inserting the Kesten-McKay distribution yields (see Supplemental Material for details [61]),

$$R(z) = \int_{-2\sqrt{K-1}}^{2\sqrt{K-1}} dx \frac{K\sqrt{4(K-1)-x^2}}{2\pi(K^2-x^2)} [z - (Jx - \lambda)]^{-1} \quad (73a)$$

$$= \frac{1}{2} \frac{(K-2)(z+\lambda) - K\sqrt{(z+\lambda)^2 - 4(K-1)J^2}}{K^2J^2 - (z+\lambda)^2}. \quad (73b)$$

which is identical to expression obtained with the GECaM approach.

3.2 Gaussian perturbative closure technique for a cubic perturbation

Adding a local non-linear cubic term to the deterministic part of the previously defined system yields the following one,

$$\frac{d}{dt}x_i(t) = -\lambda_i x_i(t) - ux_i^3(t) + \sum_{j \neq i} J_{ij} a_{ij} x_j(t) + \eta_i(t), \quad (74)$$

which is equivalent to Eq. (1) with a nonlinear drift term $f[x_i(t)] = -\lambda_i x_i(t) - ux_i^3(t)$ and additive noise term $g[x_i(t)] = D$. For clarity, we will consider the underlying interaction graph to be a RRG with homogeneous parameters (i.e. $J_{ij} = J_{ji} = J$ for any $(i, j) \in E$, $\lambda_i = \lambda$ for any $i \in V$). While this simplifies our discussion, extending the results to non-homogeneous cases is straightforward. The cavity probability can be written as in Eq. (60) with interaction action

$$S_{i \setminus j}^I[\mathbf{x}_i, \hat{\mathbf{x}}_i] = u \int_0^\mathcal{T} ds i \hat{x}_i(s) x_i^3(s). \quad (75)$$

The unperturbed system has a steady state fluctuating around zero when stable, i.e. when $\lambda \geq KJ$. We can therefore assume $M_{i \setminus j} = 0$ for any edge (i, j) without any loss of generality. When the perturbation is switched on, the system exhibits a phase transition between two steady states. For $\lambda \geq \lambda_c(u)$, the stationary values $\langle x_i \rangle$ vanish for all i , with stable noise-driven fluctuations around zero, whereas these values becomes finite for $\lambda < \lambda_c(u)$.

Using a perturbative expansion, valid for sufficiently small u , we obtain a Dyson equation Eq. (63) with a mean-field self energy

$$\Sigma_{i \setminus j}^{MF} = -3u C_{i \setminus j}^{0,0} \sigma_1, \quad (76)$$

where $C_{i \setminus j}^{0,0}$ is the perturbed cavity correlation function at times 0 and σ_1 is the generalized Pauli matrix

$$\sigma_1 = \begin{pmatrix} 0 & \mathbb{I} \\ \mathbb{I} & 0 \end{pmatrix}. \quad (77)$$

The Dyson equation reads

$$[R_{i \setminus j}]^{-1} = [R_{i \setminus j}^0]^{-1} + 3u C_{i \setminus j}^{0,0} \quad (78a)$$

$$[R_{i \setminus j}]^{-1} C_{i \setminus j} \left([R_{i \setminus j}]^{-1} \right)^T = [R_{i \setminus j}^0]^{-1} C_{i \setminus j}^0 \left([R_{i \setminus j}^0]^{-1} \right)^T. \quad (78b)$$

In the long-time limit, the system becomes TTI and Laplace transform can be conveniently applied. Because of the homogeneity assumption, we can neglect node and edge labels and, after inserting the expressions for the cavity response and correlation functions from Eqs. (64a) and (64b), we obtain

$$\hat{R}^{-1}(z) = z + \lambda + 3u \hat{C}(\tau = 0) - (K - 1)J^2 \hat{R}^{-1}(z) \quad (79)$$

$$\hat{C}(z) = \hat{R}(z) \left[2D + (K - 1)J^2 \hat{C}(z) \right] \hat{R}(-z), \quad (80)$$

where $\hat{C}(\tau = 0)$ should be computed solving self-consistently the equation for $\hat{C}(\tau)$ in the time domain. The perturbation then acts as a renormalization of the parameter λ and the problem can be reduced to solving a self-consistent equation for the renormalised parameter $\tilde{\lambda}$ such that

$$\tilde{\lambda} = \lambda + 3u \hat{C}_{\tilde{\lambda}}(\tau = 0). \quad (81)$$

and

$$\hat{R}_{\tilde{\lambda}}(z) = \frac{z + \tilde{\lambda} - \sqrt{(z + \tilde{\lambda})^2 - 4(K - 1)J^2}}{2(K - 1)J^2} \quad (82)$$

Inverting the Laplace transform of the correlation to find $\hat{C}_{\tilde{\lambda}}(\tau = 0)$ is challenging. However, one can alternatively compute the spectral density of the cavity graph and use this information to determine the equal-time correlation. Inserting Eq. (82) into Eq. (55) we obtain the ‘‘cavity’’ spectral density

$$\hat{\rho}(x) = \frac{J}{\pi} \lim_{\varepsilon \rightarrow 0^+} \text{Im} \hat{R}_{\tilde{\lambda}}(Jx - \tilde{\lambda} - i\varepsilon) \quad (83a)$$

$$= \frac{\sqrt{4(K - 1) - x^2}}{2\pi(K - 1)}, \quad (83b)$$

where $x \in [-2\sqrt{K - 1}, 2\sqrt{K - 1}]$. This quantity is similar to the Wigner semicircle law [62, 64] with a dependence on K . Inserting the result into Eq. (59b) we obtain

$$\hat{C}_{\tilde{\lambda}}(\tau = 0) = D \int_{-2\sqrt{K-1}}^{2\sqrt{K-1}} dx \frac{\sqrt{4(K-1) - x^2}}{2\pi(K-1)} \int_0^\infty dw e^{(Jx - \tilde{\lambda})w} \quad (84a)$$

$$= \frac{D}{2\pi(K-1)J} \int_{-2\sqrt{K-1}}^{2\sqrt{K-1}} dx \frac{\sqrt{4(K-1) - x^2}}{\frac{\tilde{\lambda}}{J} - x} \quad (84b)$$

$$= \frac{D\tilde{\lambda}}{2(K-1)J^2} \left[1 - \sqrt{1 - 4 \frac{J^2(K-1)}{\tilde{\lambda}^2}} \right]. \quad (84c)$$

Plugging this expression into Eq. (81), an equation for $\tilde{\lambda}$ is obtained, which is a function of the parameters of the unperturbed problem,

$$\tilde{\lambda} - 3u \frac{D\tilde{\lambda}}{2(K-1)J^2} \left[1 - \sqrt{1 - 4 \frac{J^2(K-1)}{\tilde{\lambda}^2}} \right] = \lambda \quad (85)$$




Figure 2: **Phase transition for a cubic perturbation on a RRG.** Estimates of the stationary average value $\langle x \rangle$ obtained from numerical simulations of the dynamical model Eq. (74) on a RRG with $N = 200$ nodes, $K = 3$ (left panel) and $K = 10$ (right panel) neighbors, $J = 1$ and $u = 0.01$ at different values of the product Du and λ . The stationary value was taken at $t = 1000$, setting the same initial condition $x_i(0) = 1$ for all the nodes. The numerical estimates are compared with the theoretical transition line Eq. (88), represented by the solid white line, demonstrating that our method gives an accurate prediction of the position of the phase transition.

with solution

$$\tilde{\lambda} = \lambda \left[1 + \frac{3}{2} \frac{Du}{(K-1)J^2 - 3Du} \left(1 - \sqrt{1 - 4 \frac{(K-1)J^2 - 3Du}{\lambda^2}} \right) \right]. \quad (86)$$

For $\tilde{\lambda} \geq KJ$, the system has a stable stationary phase, where the order parameter

$$\langle x \rangle = \lim_{t \rightarrow \infty} \lim_{N \rightarrow \infty} \frac{1}{N} \sum_i \langle x_i(t) \rangle \quad (87)$$

vanishes. The order parameter is non-zero for $\tilde{\lambda} < KJ$. From the critical condition for $\tilde{\lambda}$, we can therefore compute the perturbative expression of the critical value

$$\lambda_c(u) = KJ - 3 \frac{Du}{(K-1)J}. \quad (88)$$

The analytical transition line in Eq. (88) was compared with numerical simulations of the model on a Random Regular Graph (RRG) with $N = 200$ nodes, considering both $K = 3$ and $K = 10$ neighbors. Numerical simulations were performed using the Euler–Maruyama algorithm, starting with an initial condition of $x_i(0) = 1$ for each degree of freedom, and waiting for the system to reach the stationary state (in practice at time $t = 1000$). Some parameters were kept fixed ($J = 1$ and $u = 0.01$), while the stationary average value $\langle x \rangle$ was computed varying D and λ . Figure 2 reports a density plot of the stationary average values obtained from simulations alongside the theoretical transition line, demonstrating that the theoretical predictions are consistent with the numerical results.

3.3 Noise-driven phase transition with multiplicative noise

Stochastic differential equations with state-dependent (“multiplicative”) noise terms are very common in the description of physical, biological, and social systems as they naturally emerge when dealing with intrinsic, as well as environmental, fluctuations [70, 71]. Multiplicative noise interacts with the state variables, leading to more complex and often counterintuitive effects, such as non-equilibrium phase transitions driven by the presence of the noise that alters the stability properties of the dynamics. As a prototype of this behavior, we consider the Bouchaud-Mézard (BM) model [72], although similar stochastic dynamics can be found in various fields of application, from surface growth to ecology. It is known that the wealth distribution in a real economy exhibits a power-law behavior called Pareto’s law [73]. The BM model describes the evolution of the wealth in a population of agents, which was originally assumed to form a fully-connected graph, by the following system of SDEs

$$\frac{d}{dt}x_i(t) = J \sum_{j \neq i} a_{ij} (x_j(t) - x_i(t)) + \sigma x_i(t) \eta_i(t), \quad (89)$$

where $x_i(t)$ is the wealth of agent i at time t , J is the coupling between agents, σ^2 is the variance of noise and $\eta(t)$ is a Gaussian white noise with average $\langle \eta_i(t) \rangle = 0$ and correlation $\langle \eta_i(t) \eta_j(t') \rangle = \delta_{i,j} \delta(t-t')$. Defining $\lambda_i = J \sum_j a_{ij} = J |\partial i|$ the model corresponds to Eq. (1) with a linear drift term $f[x_i(t)] = -\lambda_i x_i(t)$ and a multiplicative noise with $g[x_i(t)] = \frac{1}{2} \sigma^2 x_i^2(t)$. The SDEs defining the model are invariant under the scaling transformation $x_i \rightarrow \alpha x_i$ for any positive constant α . Therefore, without loss of generality, we can set $\langle x_i(t) \rangle = 1$ in the theoretical analysis. In numerical studies, we will focus on the statistical properties of the normalized quantity x_i/\bar{x} , where \bar{x} is the average over all agents.

In their original paper, Bouchaud and Mézard showed using the mean-field theory that the stationary distribution of normalized wealth x_i/\bar{x} exhibits the expected power-law behavior. They also found out that the model exhibits a phase transition at $J \leq J_c = \sigma^2$, where the variance of x/\bar{x} diverges. The phenomenon is called *wealth condensation*, since the divergence of the variance implies that wealth condenses to a few rich agents. If instead $J > J_c$ the variance remains finite and most of the agents have a wealth close to the average. Alternatively, by keeping fixed the coupling constant J and varying the amplitude σ^2 of the noise, the wealth condensation phenomenon can be also interpreted as a realization of a transition from weak-noise to strong-noise regimes [71].

In [74], the wealth condensation phenomenon is studied on random graphs using a combination of an adiabatic assumption and an independence assumption. The first one allows the use of self-consistent conditional mean-field closure methods [75, 76], while the independence assumption enables treating neighbors as independent and applying the central limit theorem. This approximation method provides an improved prediction for the location of the phase transition on sparse graphs, such as Random Regular Graphs.

Here we propose an alternative solution employing the perturbative closure technique described in Sect.2.4. Equation (89) can be seen as a linear model with a vanishing additive noise ($D \rightarrow 0$ limit) and a multiplicative noise that will be treated using perturbation theory. We can therefore apply our perturbative closure technique expanding in powers of σ . In this case, the interaction term of the local action is

$$S_{i \setminus j}^I[\mathbf{x}_i, \hat{\mathbf{x}}_i] = -\frac{1}{2} \sigma^2 \int_0^\mathcal{T} ds x_i^2(s) (i\hat{x}_i(s))^2. \quad (90)$$

Before proceeding to apply perturbation theory, it is necessary to perform a change of variable in order to eliminate the constant part from $x_i(t)$ [77]. Since $\langle x_i(t) \rangle = 1$, we introduce the variable $\phi_i(t)$ defined by $x_i(t) = 1 + \phi_i(t)$ and the conjugate one $\hat{\phi}_i = i\hat{x}_i$.

The Gaussian part of the cavity action is unchanged, and since $\langle \phi_i \rangle = 0$, we can safely assume the average vector to be zero. The interaction term becomes

$$S_{i \setminus j}^I[\phi_i, \hat{\phi}_i] = -\frac{1}{2}\sigma^2 \int_0^\mathcal{T} ds (1 + \phi_i(s))^2 \hat{\phi}_i^2(s) \quad (91a)$$

$$= -\frac{1}{2}\sigma^2 \int_0^\mathcal{T} ds \hat{\phi}_i^2(s) - \sigma^2 \int_0^\mathcal{T} ds \phi_i(s) \hat{\phi}_i^2(s) - \frac{1}{2}\sigma^2 \int_0^\mathcal{T} ds \phi_i^2(s) \hat{\phi}_i^2(s). \quad (91b)$$

Although the first term of the previous expression is quadratic, the appearance of the perturbative parameter σ^2 imposes to include it in the interacting part of the action. It follows that the Gaussian correlation function vanishes, i.e.

$$C_{i \setminus j}^0(t, t') = \langle \phi_i(t) \phi_i(t') \rangle_{i \setminus j}^0 = 0, \quad (92)$$

while the Gaussian response function $R_{i \setminus j}^0(t, t') = \langle \phi_i(t) \hat{\phi}_i(t') \rangle_{i \setminus j}^0$ satisfies

$$R_{i \setminus j}^0(z) = \frac{1}{z + \lambda_i - \sum_{k \in \partial i \setminus j} J^2 R_{k \setminus i}(z)}, \quad (93)$$

which was already computed at least for RRGs.

The response function remains unperturbed due to causality restrictions, while the correlation function renormalizes due to the loop corrections coming from the first term in the interaction part of the action. At first order, the contribution is

$$C_{i \setminus j}(t, t') = \sigma^2 \int ds R_{i \setminus j}^0(t, s) R_{i \setminus j}^0(t', s). \quad (94)$$

This is the only contribution because all other non-vanishing terms can be absorbed in the renormalization of the coupling constant σ^2 (the others are zero because either $R_{i \setminus j}^0(s, s) = 0$ or $\langle \phi_i(t) \rangle_{i \setminus j}^0 = 0$). In matrix form

$$R_{i \setminus j} = R_{i \setminus j}^0 \quad (95a)$$

$$C_{i \setminus j} = \sigma_R^2 R_{i \setminus j}^0 \left[R_{i \setminus j}^0 \right]^T. \quad (95b)$$

The renormalization of the coupling constant is due to the perturbative renormalization of the third term in $S_{i \setminus j}^I[\phi_i, \hat{\phi}_i]$, which is easy to express as a geometric series of one-loop corrections (see Supplemental Material [61]). The resummation of the series gives

$$\sigma_R^2 = \frac{\sigma^2}{1 - \sigma^2 I} \quad (96)$$

where the term I is given by the integral

$$I = \int_{-\infty}^{\infty} \frac{d\omega}{2\pi} R_{i \setminus j}^0(\omega) R_{i \setminus j}^0(-\omega), \quad (97)$$

with $R_{i \setminus j}^0(\omega) = R_{i \setminus j}^0(z = i\omega)$ being the Gaussian response expressed in the Fourier space.

For a RRG with homogeneous parameters, where $\lambda_i = J|\partial i| = KJ$ for every node, the integral I can be reduced to a simpler one in real space. The final form of the integral is

$$I = \int_{-\infty}^{\infty} \frac{d\omega}{2\pi} \left[\frac{i\omega + KJ - \sqrt{(i\omega + KJ)^2 - 4(K-1)J^2}}{2(K-1)J^2} \right] \times \left[\frac{-i\omega + KJ - \sqrt{(-i\omega + KJ)^2 - 4(K-1)J^2}}{2(K-1)J^2} \right] \quad (98a)$$

$$= \frac{2}{\pi\sqrt{K-1}J} \int_{-1}^1 du \frac{\sqrt{1-u^2}}{\frac{K}{\sqrt{K-1}} - u + \sqrt{\left(\frac{K}{\sqrt{K-1}} - u\right)^2 - 1}}. \quad (98b)$$




Figure 3: **Tail exponent α of the BM model on a RRG.** Estimates of the tail exponent α obtained by simulation for $K = 3$ (dot, solid lines), $K = 10$ (star, dotted lines) and $K = 500$ (cross, dashed lines) at different values of σ^2 around the phase transition. Numerical simulations of the BM model on a RRG were carried out for $N = 5000$ nodes and repeated 100 times. Markers correspond to the average value of α , while ribbons represent the 95% confidence interval. Vertical lines correspond to the theoretical critical values as predicted by our method $\sigma_{c,G}^2$ (red) and by [74] $\sigma_{c,I}^2$ (green). The horizontal black line corresponds to the critical value $\alpha_c = 2$: a tail exponent below this critical line indicates that the system undergoes wealth condensation.

A detailed derivation of this expression is reported in the Supplemental Material [61].

The fully-connected (FC) limit is easily recovered setting $K = N - 1$, rescaling J to J/K and taking the limit $K \rightarrow \infty$,

$$I_{FC} \approx \frac{2}{\pi J} \frac{K}{\sqrt{K-1}} \int_{-1}^1 du \frac{\sqrt{1-u^2}}{2 \frac{K}{\sqrt{K-1}}} \rightarrow \frac{1}{2J}. \quad (99)$$

The renormalized noise parameter diverges at the critical value $\sigma_c = I^{-1}$, indicating a phase transition to the condensed phase. In the FC limit, we recover the value $\sigma_c^{FC} = 2J$, in agreement with the mean-field result [72].

To assess the accuracy of our method, we compared it with numerical simulations. We rescaled J to J/K to facilitate comparison of results across different connectivities K . Numerical simulations of the BM model on a RRG were carried out for $N = 5000$ nodes and repeated 100 times using the Milstein algorithm [78] with an initial condition $x_i(0) = 1$ for each parameter value (here we set $J = 1$). The distribution at $t = 1500$ was taken as the stationary distribution. The stationary distribution of x/\bar{x} is expected to have a heavy Pareto tail

$$p\left(\frac{x}{\bar{x}}\right) \stackrel{x/\bar{x} \rightarrow \infty}{\sim} \frac{1}{x^{\alpha+1}}, \quad (100)$$

where α is the tail index. The variance of normalized wealth diverges when $\alpha \leq 2$. To estimate the tail exponent we have run a simple Rank-1/2 Ordinary Least Squares (OLS) log-log rank-size regression [79] with a bias reduction term. Figure 3 shows the estimates of α for $K = 3$, $K = 10$ and $K = 500$ at different values of σ^2 around the phase transition, together with the prediction $\sigma_{c,I}^2$ of [74] and our prediction $\sigma_{c,G}^2 = I^{-1}$. Our method provides a better approximation for sparse graphs, while the two methods converge to the same mean-field value when K approaches N . Interestingly, the self-consistent method

proposed in [74] can be obtained within the GECaM approach when further approximating the cavity quantities by the corresponding full quantities taken at zero time differences (see Supplemental Material [61] for details).

3.4 Relaxation dynamics of the spherical 2-spin model

The spherical p -spin model, with $p \geq 3$, has been extensively studied as a prototypical model for the behavior of disordered systems, exhibiting a glassy free-energy landscape as well as complex dynamical phenomena such as slow relaxation and aging [35]. The $p = 2$ case is structurally much simpler, it does not present a glassy equilibrium free-energy landscape, but a more standard continuous transition into a disguised ferromagnetic phase [80]. The effect of disorder is however enough to ensure non-trivial dynamical properties. In fact, under nearly all initial conditions, the system fails to reach equilibrium, with its relaxation dynamics heavily influenced by the duration of time the system has already spent in the low-temperature phase, indicative of aging behavior. Due to its simplicity, this model can be exactly solved through the diagonalization of the system, provided the spectral properties of the underlying interaction graph are known [7, 81, 82]. Here, we will show how our method enables the study of this non-trivial relaxation dynamics without the explicit diagonalization of the system or the knowledge of the spectral properties of the underlying interaction graph.

The model is defined by the Hamiltonian

$$H[\vec{x}] = -\frac{1}{2} \sum_{i \neq j} a_{ij} J_{ij} x_i x_j, \quad (101)$$

where $x_i(t)$, $i = 1, \dots, N$ are continuous spins with spherical constraint $\sum_{i=1}^N x_i^2(t) = N$, a_{ij} are the elements of the adjacency matrix of a RRG with K neighbours and the couplings are independent and identically distributed (iid) symmetric random variables with binomial distribution

$$P(J_{ij}) = \frac{1}{2} [\delta(J_{ij} - J) + \delta(J_{ij} + J)]. \quad (102)$$

A notable choice for the coupling strength is $J \propto 1/\sqrt{K}$ that ensures to recover known results in the fully-connected limit ($K \rightarrow \infty$). The relaxation dynamics satisfies the Langevin equation

$$\frac{d}{dt} x_i(t) = -\frac{\delta H[\vec{x}]}{\delta x_i(t)} - \lambda(t) x_i(t) + \eta_i(t) \quad (103a)$$

$$= \sum_{j \neq i} a_{ij} J_{ij} x_j(t) - \lambda(t) x_i(t) + \eta_i(t), \quad (103b)$$

where $\lambda(t)$ is a Lagrange multiplier enforcing the spherical constraint and the thermal noise term $\xi_i(t)$ is Gaussian with zero mean and correlation $\langle \eta_i(t) \eta_j(t') \rangle = 2D \delta_{ij} \delta(t - t')$ (here D plays the role of temperature T in the usual formulations of the p -spin model).

Although the GECaM equations could be derived for any given graph and realization of the coupling constants, we will focus on a simplified setup that enables more straightforward analytic calculations. Because of the spatial homogeneity of the random regular graph, it is reasonable to assume that, in the thermodynamic limit and after averaging over the iid couplings, the cavity quantities and full quantities do not depend on the site/edge, that is $R_i = R$, $C_i = C$, $\forall i \in V$ and $R_{i \setminus j} = \hat{R}$ and $C_{i \setminus j} = \hat{C}$, $\forall (i, j) \in E$. The spherical constraint implies that the equal time correlation must be equal to 1 at any time, i.e.

$C(t, t) = 1$. In this homogeneous case, for a sudden quench from the high-temperature phase, the corresponding GECaM equations for the cavity response functions and cavity correlation functions are

$$\frac{\partial}{\partial t} \hat{R}(t, t') = -\lambda(t) \hat{R}(t, t') + (K-1) J^2 \int_{t'}^t dt'' \hat{R}(t, t'') \hat{R}(t'', t') + \delta(t-t') \quad (104a)$$

$$\begin{aligned} \frac{\partial}{\partial t} \hat{C}(t, t') &= -\lambda(t) \hat{C}(t, t') + (K-1) J^2 \int_0^t dt'' \hat{R}(t, t'') \hat{C}(t'', t') + 2D \hat{R}(t', t) \\ &+ (K-1) J^2 \int_0^{t'} dt'' \hat{R}(t', t'') \hat{C}(t, t''), \end{aligned} \quad (104b)$$

and for the full response and correlation

$$\frac{\partial}{\partial t} R(t, t') = -\lambda(t) R(t, t') + K J^2 \int_{t'}^t dt'' \hat{R}(t, t'') R(t'', t') + \delta(t-t') \quad (105a)$$

$$\begin{aligned} \frac{\partial}{\partial t} C(t, t') &= -\lambda(t) C(t, t') + K J^2 \int_0^t dt'' \hat{R}(t, t'') C(t'', t') + 2DR(t', t) \\ &+ K J^2 \int_0^{t'} dt'' R(t', t'') \hat{C}(t, t''). \end{aligned} \quad (105b)$$

Here, for random initial conditions, we neglected the corresponding equations for the cavity means and full means, that would in general explicitly depend on the chosen initial conditions. The spherical constraint $C(t, t) = 1$ implies that $[\partial_t C(t, t') + \partial_{t'} C(t, t')]_{t, t'=s} = 0$ from which the expression of the Lagrange multiplier

$$\lambda(t) = K J^2 \int_0^t dt'' \hat{R}(t, t'') C(t'', t) + K J^2 \int_0^t dt'' R(t, t'') \hat{C}(t, t'') + D, \quad (106)$$

which gives now coupled equations for (cavity and full) responses and correlations. When setting $J^2 \propto 1/K$ and taking the $K \rightarrow \infty$ limit, the cavity and full quantities satisfy the same set of equations and the latter represent a $p = 2$ version of the Cugliandolo-Kurchan dynamical mean-field equations for the fully-connected p -spin model [37].

The GECaM equations can be further simplified by using the following parametric ansatz,

$$\hat{R}(t, t') = \frac{f(t')}{f(t)} \hat{R}_{\text{st}}(t-t') \quad (107a)$$

$$\hat{C}(t, t') = \frac{1}{f(t)f(t')} \hat{C}_1(t, t'), \quad (107b)$$

which are inspired by the form of the exact solution obtained in [81]. The physical meaning of $\hat{R}_{\text{st}}(t-t')$, $\hat{C}_1(t, t')$ and $f(t)$ becomes clear when inserting the ansatz in Eq. (104). In fact, the quantity \hat{R}_{st} turns out to represent the stationary time-translation invariant cavity response function of a linear system with additive noise and it must satisfy the equation

$$\frac{\partial}{\partial t} \hat{R}_{\text{st}}(t-t') = (K-1) J^2 \int_{t'}^t dt'' \hat{R}_{\text{st}}(t-t'') \hat{R}_{\text{st}}(t''-t') + \delta(t-t'). \quad (108)$$

On the other hand, \hat{C}_1 does not represent the TTI correlation; rather, it must satisfy the following equation

$$\begin{aligned} \frac{\partial}{\partial t} \hat{C}_1(t, t') &= 2D f^2(t) \hat{R}_{\text{st}}(t-t') + (K-1) J^2 \int_0^t dt'' \hat{R}_{\text{st}}(t-t'') \hat{C}_1(t'', t') \\ &+ (K-1) J^2 \int_0^{t'} dt'' \hat{R}_{\text{st}}(t'-t'') \hat{C}_1(t, t''). \end{aligned} \quad (109)$$

The scaling function $f(t)$ is given by

$$f(t) = f(t_0) e^{\int_{t_0}^t \lambda(t') dt'}, \quad (110)$$

where $f(t_0) = 1$ for the present choice of initial conditions.

An equivalent parametric ansatz can be also assumed for the full response and correlation functions

$$R(t, t') = \frac{f(t')}{f(t)} R_{\text{st}}(t - t') \quad (111a)$$

$$C(t, t') = \frac{1}{f(t) f(t')} C_1(t, t'), \quad (111b)$$

where R_{st} is the usual stationary TTI response function

$$\frac{\partial}{\partial t} R_{\text{st}}(t - t') = K J^2 \int_{t'}^t dt'' \hat{R}_{\text{st}}(t - t'') R_{\text{st}}(t'' - t') + \delta(t - t'), \quad (112)$$

while C_1 must satisfy the equation

$$\begin{aligned} \frac{\partial}{\partial t} C_1(t, t') = & 2D f^2(t) R_{\text{st}}(t' - t) + K J^2 \int_0^t dt'' \hat{R}_{\text{st}}(t - t'') C_1(t'', t') \\ & + K J^2 \int_0^{t'} dt'' R_{\text{st}}(t' - t'') \hat{C}_1(t, t''). \end{aligned} \quad (113)$$

With a bit of algebra it can be shown that the system of coupled integro-differential equations for $\hat{C}_1(t, t')$ and $C_1(t, t')$ admits as a solution the expressions

$$\hat{C}_1(t, t') = \hat{R}_{\text{st}}(t + t') + 2D \int_0^{\min(t, t')} dt_1 f^2(t_1) \hat{R}_{\text{st}}(t + t' - 2t_1) \quad (114a)$$

$$C_1(t, t') = R_{\text{st}}(t + t') + 2D \int_0^{\min(t, t')} dt_1 f^2(t_1) R_{\text{st}}(t + t' - 2t_1), \quad (114b)$$

where the scaling function $f(t)$ solves the (linear) Volterra integral equation

$$f^2(t) = R_{\text{st}}(2t) + 2D \int_0^t dt_1 f^2(t_1) R_{\text{st}}(2t - 2t_1). \quad (115)$$

This is the exact solution first obtained in [81]. In principle, an explicit solution can be constructed as follows. The TTI equations for \hat{R}_{st} and R_{st} can be solved in the Laplace space, and used to solve the equation for $f(t)$ in the Laplace space. If an explicit time-domain expression of $f(t)$ can be computed, then the time behavior of the cavity and full correlation functions can be obtained. Unfortunately, analytically computing the inverse Laplace transform of f is cumbersome. A numerical solution of Eqs. (104) and (105) with the spherical constraint Eq. (106) can be obtained by forward-in-time integration. Figure 4 shows the decay of the correlation function $C(t_w + \tau, t_w)$ for fixed temperature $D = 0.3$ and coupling constant $J = 1.0$, where τ is the time elapsed after a “waiting time” t_w . The correlation function shows the typical “aging” behaviour, i.e. it has an initial fast decay for $\tau \ll t_w$, after which it decays slowly to zero for $\tau > t_w$. The sparseness however decreases the aging effect at fixed waiting time as can be seen from the top-right right and bottom panes. Further insights on the dynamics of sparse p -spin models (also for $p \geq 3$) using GECaM approximation go beyond the purpose of the present work and will be discussed elsewhere [83].




Figure 4: **Correlation function of the 2-spin model on RRGs.** Decay of $C(t_w + \tau, \tau)$ against τ for the spherical 2-spin model on a RGG with fixed coupling constant $J = 1.0$ and at temperature $D = 0.3$. (Top-left panel) Correlation function decay at fixed $K = 10$ for increasing values of the waiting time t_w (from bottom to top). (Top-right and bottom panels) Correlation function decay at fixed waiting time $t_w = 30, 100, 300$ for $K = 3, 4, 5, 7, 10, 100$ (from bottom to top) together with the fully-connected (FC) case (dashed gray line).

4 Conclusions

This work establishes a flexible and robust framework for studying complex stochastic (Langevin-type) dynamics on networked systems. This is done introducing a novel approximation scheme for the dynamic cavity method, which is applicable to systems with continuous degrees of freedom and bilinear pairwise coupling between them. By deriving the dynamic cavity equations for a system of linearly-coupled stochastic differential equations through the MSRJD functional theory, we have obtained a path-integral formulation of the dynamic probability measure. This formulation, once represented as a graphical model, enables to identify the cavity marginals with local functionals of single-site trajectories for both the physical variables and their MSRJD conjugate variables. This approach mirrors the quantum cavity method used for quantum many-body systems in the imaginary-time representation.

The main approximation of the method involves a small-coupling expansion of the cavity equations, with a second-order truncation, which corresponds to effectively assuming a Gaussian approximation for the cavity marginals. The resulting integro-differential GECaM equations, depending on cavity versions of response functions and two-time correlation functions, provide an approximate description of the dynamics. For stochastic dynamics on fully-connected graphs, this approximation is equivalent to the extended Plefka expansion and results in a dynamical version of the TAP equations [46]. However,

the GECaM equations are also suitable for investigating linearly-coupled SDEs on sparse graphs, where the cavity formulation offers a more precise approximation. In analogy with the standard cavity equations, the GECaM equations serve as an algorithm for studying stochastic dynamics on a specific graph instance. Alternatively, by means of a population dynamics algorithm, these equations can be used to explore general dynamical properties of disordered systems at the level of random graph ensembles.

We applied the GECaM equations to various dynamical problems where the quality of the approximation is controllable. For a linear system of SDEs with additive noise, the GECaM equations provide an exact description of the dynamics, limited by the validity of the local tree-like approximation. This is reflected in the relationship between the GECaM equations for the cavity response functions and those for the resolvent obtained through the cavity method in random matrix theory. Classical results for the calculation of the spectral density of hermitian and non-hermitian random matrices are recovered.

The presence of non-linear forces and state-dependent noise terms in the system of SDEs is addressed using a perturbative closure technique, based on a self-consistent resummation of 1-loop contributions reminiscent of the mode-coupling theory for disorders systems. On RRG, the phase transitions under study have a mean-field nature, but with a non-trivial dependence of the critical point on graph connectivity. In both cases, the perturbative closure method applied to GECaM equations provides a very good description of the dependency of the critical point on the degree K of the RRG. Further studies will be devoted to explore the dependency of the critical behavior on other properties of the graph ensemble, such as degree heterogeneity, perhaps using a population dynamics version of these equations. Finally, we applied the GECaM approximation scheme to the relaxation dynamics of the spherical 2-spin model, where a system of linear SDEs with additive noise is endowed with a self-consistent non-linearity through a global constraint. Despite its simplicity, this model showcases non-trivial dynamical properties like slow relaxation and aging effects. Remarkably, the corresponding GECaM equations are exact on RRG, suggesting their potential applicability to similar dynamics on more general graphs with local tree-like structures.

Although the current GECaM approach has been effective for the problems under study, a non-perturbative closure scheme appears indispensable to incorporate the local effects of non-linearities without further approximations. One possible improvement could involve using a numerical scheme to sample on-site stochastic trajectories given incoming Gaussian cavity messages, as proposed for random ecosystems [84], and computing updated versions of cavity response and correlation functions from these samples.

A significant limitation of the method is the linear coupling between neighboring degrees of freedom. In many relevant applications, local interactions are not exclusively represented by a weighted sum of the neighboring variables, because of the existence of non-linear activation functions (e.g., in neural networks and learning models) and higher-order interaction patterns (e.g., in ecosystems and reaction networks). Generalizing the path integral approach to model these more complex interactions would necessitate a more intricate structure of the graphical model representation and a more complex functional form for the corresponding cavity messages. This could involve introducing additional auxiliary variables, as demonstrated in [27]. In specific cases, such as multilinear interactions in p -spin models with $p \geq 3$, extending the GECaM equation appears straightforward [83]. However, further research is needed to address these limitations and broaden the applicability of the GECaM approach.

Acknowledgements

Computational resources were provided by the SmartData@PoliTO (smartdata.polito.it) interdepartmental center on Big Data and Data Science. The authors would like to thank G. Catania, T. Galla, A. Gamba, A. Gambassi, R. Mulet, P. Sollich for fruitful discussions on the topics of this work.

References

- [1] S. N. Dorogovtsev and J. F. Mendes, *The nature of complex networks*, Oxford University Press (2022).
- [2] S. N. Dorogovtsev, A. V. Goltsev and J. F. F. Mendes, *Critical phenomena in complex networks*, Rev. Mod. Phys. **80**(4), 1275 (2008), doi:[10.1103/RevModPhys.80.1275](https://doi.org/10.1103/RevModPhys.80.1275).
- [3] S. Bradde, F. Caccioli, L. Dall'Asta and G. Bianconi, *Critical Fluctuations in Spatial Complex Networks*, Phys. Rev. Lett. **104**(21), 218701 (2010), doi:[10.1103/PhysRevLett.104.218701](https://doi.org/10.1103/PhysRevLett.104.218701).
- [4] A. Goltsev, S. Dorogovtsev and J. Mendes, *Critical phenomena in networks*, Physical Review E **67**(2), 026123 (2003).
- [5] R. Pastor-Satorras and C. Castellano, *Distinct types of eigenvector localization in networks*, Scientific reports **6**(1), 18847 (2016).
- [6] F. L. Metz and I. Neri, *Localization and universality of eigenvectors in directed random graphs*, Physical Review Letters **126**(4), 040604 (2021).
- [7] G. Semerjian and L. F. Cugliandolo, *Dynamics of dilute disordered models: A solvable case*, EPL **61**(2), 247 (2003), doi:[10.1209/epl/i2003-00226-8](https://doi.org/10.1209/epl/i2003-00226-8).
- [8] M. A. Munoz, R. Juhász, C. Castellano and G. Ódor, *Griffiths phases on complex networks*, Physical review letters **105**(12), 128701 (2010).
- [9] R. Kühn, *Spectra of random stochastic matrices and relaxation in complex systems*, Europhysics Letters **109**(6), 60003 (2015).
- [10] A. Barrat, M. Barthélemy and A. Vespignani, *Dynamical processes on complex networks*, Cambridge university press (2008).
- [11] B. Karrer and M. E. Newman, *Message passing approach for general epidemic models*, Physical Review E **82**(1), 016101 (2010).
- [12] J. P. Gleeson, *High-accuracy approximation of binary-state dynamics on networks*, Physical Review Letters **107**(6), 068701 (2011).
- [13] C. Kuehn, *Moment closure—a brief review*, Control of self-organizing nonlinear systems pp. 253–271 (2016).
- [14] M. A. Porter and J. P. Gleeson, *Dynamical systems on networks*, Frontiers in Applied Dynamical Systems: Reviews and Tutorials **4**, 29 (2016).
- [15] I. Z. Kiss, J. C. Miller, P. L. Simon *et al.*, *Mathematics of epidemics on networks*, Cham: Springer **598**(2017), 31 (2017).

-
- [16] D. Machado, R. Mulet and F. Ricci-Tersenghi, *Improved mean-field dynamical equations are able to detect the two-step relaxation in glassy dynamics at low temperatures*, Journal of Statistical Mechanics: Theory and Experiment **2023**(12), 123301 (2023).
- [17] I. Neri and D. Bollé, *The cavity approach to parallel dynamics of Ising spins on a graph*, J. Stat. Mech. **2009**(08), P08009 (2009), doi:[10.1088/1742-5468/2009/08/P08009](https://doi.org/10.1088/1742-5468/2009/08/P08009).
- [18] Y. KANORIA and A. MONTANARI, *Majority dynamics on trees and the dynamic cavity method*, The Annals of Applied Probability **21**(5), 1694 (2011).
- [19] F. Altarelli, A. Braunstein, L. Dall'Asta and R. Zecchina, *Large deviations of cascade processes on graphs*, Physical Review E **87**(6), 062115 (2013).
- [20] F. Altarelli, A. Braunstein, L. Dall'Asta and R. Zecchina, *Optimizing spread dynamics on graphs by message passing*, J. Stat. Mech. **2013**(09), P09011 (2013), doi:[10.1088/1742-5468/2013/09/P09011](https://doi.org/10.1088/1742-5468/2013/09/P09011).
- [21] F. Altarelli, A. Braunstein, L. Dall'Asta, A. Lage-Castellanos and R. Zecchina, *Bayesian inference of epidemics on networks via belief propagation*, Physical review letters **112**(11), 118701 (2014).
- [22] A. Baker, I. Biazzo, A. Braunstein, G. Catania, L. Dall'Asta, A. Ingrosso, F. Krzakala, F. Mazza, M. Mézard, A. P. Muntoni *et al.*, *Epidemic mitigation by statistical inference from contact tracing data*, Proceedings of the National Academy of Sciences **118**(32), e2106548118 (2021).
- [23] G. Del Ferraro and E. Aurell, *Dynamic message-passing approach for kinetic spin models with reversible dynamics*, Phys. Rev. E **92**(1), 010102 (2015), doi:[10.1103/PhysRevE.92.010102](https://doi.org/10.1103/PhysRevE.92.010102).
- [24] E. Aurell, G. Del Ferraro, E. Domínguez and R. Mulet, *Cavity master equation for the continuous time dynamics of discrete-spin models*, Physical Review E **95**(5), 052119 (2017).
- [25] T. Barthel, *The matrix product approximation for the dynamic cavity method*, Journal of Statistical Mechanics: Theory and Experiment **2020**(1), 013217 (2020).
- [26] S. Crotti and A. Braunstein, *Matrix product belief propagation for reweighted stochastic dynamics over graphs*, Proceedings of the National Academy of Sciences **120**(47), e2307935120 (2023).
- [27] A. Braunstein, G. Catania, L. Dall'Asta, M. Mariani, F. Mazza and M. Tarabolo, *Small-Coupling Dynamic Cavity: A Bayesian mean-field framework for epidemic inference*, Comment: 29 pages, 7 figures (including appendices) (2023).
- [28] G. W. Constable and A. J. McKane, *Population genetics on islands connected by an arbitrary network: An analytic approach*, Journal of theoretical biology **358**, 149 (2014).
- [29] G. Rozhnova, A. Nunes and A. McKane, *Stochastic oscillations in models of epidemics on a network of cities*, Physical Review E **84**(5), 051919 (2011).
- [30] G. W. Constable and A. J. McKane, *Fast-mode elimination in stochastic metapopulation models*, Physical Review E **89**(3), 032141 (2014).

-
- [31] D. Schnoerr, G. Sanguinetti and R. Grima, *Approximation and inference methods for stochastic biochemical kinetics—a tutorial review*, Journal of Physics A: Mathematical and Theoretical **50**(9), 093001 (2017).
- [32] J. Gao, B. Barzel and A.-L. Barabási, *Universal resilience patterns in complex networks*, Nature **530**(7590), 307 (2016).
- [33] M. Vegué, V. Thibeault, P. Desrosiers and A. Allard, *Dimension reduction of dynamics on modular and heterogeneous directed networks*, PNAS nexus **2**(5), pgad150 (2023).
- [34] J. A. Hertz, Y. Roudi and P. Sollich, *Path integral methods for the dynamics of stochastic and disordered systems*, J. Phys. A: Math. Theor. **50**(3), 033001 (2017), doi:[10.1088/1751-8121/50/3/033001](https://doi.org/10.1088/1751-8121/50/3/033001).
- [35] T. Castellani and A. Cavagna, *Spin-glass theory for pedestrians*, Journal of Statistical Mechanics: Theory and Experiment **2005**(05), P05012 (2005).
- [36] A. Altieri, G. Biroli and C. Cammarota, *Dynamical mean-field theory and aging dynamics*, J. Phys. A: Math. Theor. **53**(37), 375006 (2020), doi:[10.1088/1751-8121/aba3dd](https://doi.org/10.1088/1751-8121/aba3dd), Publisher: IOP Publishing.
- [37] L. F. Cugliandolo, *Recent Applications of Dynamical Mean-Field Methods*, Annu. Rev. Condens. Matter Phys. **15**(Volume 15, 2024), 177 (2024), doi:[10.1146/annurev-conmatphys-040721-022848](https://doi.org/10.1146/annurev-conmatphys-040721-022848).
- [38] E. Agoritsas, G. Biroli, P. Urbani and F. Zamponi, *Out-of-equilibrium dynamical mean-field equations for the perceptron model*, J. Phys. A: Math. Theor. **51**(8), 085002 (2018), doi:[10.1088/1751-8121/aaa68d](https://doi.org/10.1088/1751-8121/aaa68d).
- [39] T. Galla, *Random replicators with asymmetric couplings*, J. Phys. A: Math. Gen. **39**(15), 3853 (2006), doi:[10.1088/0305-4470/39/15/001](https://doi.org/10.1088/0305-4470/39/15/001).
- [40] T. Galla, *Generating-functional analysis of random lotka-volterra systems: A step-by-step guide*, arXiv preprint arXiv:2405.14289 (2024).
- [41] S. d’Ascoli, M. Refinetti and G. Biroli, *Optimal learning rate schedules in high-dimensional non-convex optimization problems*, doi:[10.48550/arXiv.2202.04509](https://doi.org/10.48550/arXiv.2202.04509) (2022).
- [42] N. S. Skantzos and J. P. L. Hatchett, *Statics and dynamics of the Lebwohl–Lasher model in the Bethe approximation*, Physica A: Statistical Mechanics and its Applications **381**, 202 (2007), doi:[10.1016/j.physa.2007.03.005](https://doi.org/10.1016/j.physa.2007.03.005).
- [43] S. Azaele and A. Maritan, *Large system population dynamics with non-Gaussian interactions*, doi:[10.48550/arXiv.2306.13449](https://doi.org/10.48550/arXiv.2306.13449) (2023).
- [44] F. Aguirre-López, *Heterogeneous mean-field analysis of the generalized Lotka–Volterra model on a network*, doi:[10.48550/arXiv.2404.11164](https://doi.org/10.48550/arXiv.2404.11164), Comment: 20 pages, 6 figures (2024).
- [45] E. Aurell, R. Mulet and J. Tuziowski, *Real-time dynamics in diluted quantum networks*, Phys. Rev. A **105**(2), 022205 (2022), doi:[10.1103/PhysRevA.105.022205](https://doi.org/10.1103/PhysRevA.105.022205).
- [46] B. Bravi, P. Sollich and M. Opper, *Extended Plefka expansion for stochastic dynamics*, J. Phys. A: Math. Theor. **49**(19), 194003 (2016), doi:[10.1088/1751-8113/49/19/194003](https://doi.org/10.1088/1751-8113/49/19/194003).

-
- [47] B. Bravi and P. Sollich, *Inference for dynamics of continuous variables: The extended Plefka expansion with hidden nodes*, J. Stat. Mech. **2017**(6), 063404 (2017), doi:[10.1088/1742-5468/aa657d](https://doi.org/10.1088/1742-5468/aa657d).
- [48] P. C. Martin, E. D. Siggia and H. A. Rose, *Statistical Dynamics of Classical Systems*, Phys. Rev. A **8**(1), 423 (1973), doi:[10.1103/PhysRevA.8.423](https://doi.org/10.1103/PhysRevA.8.423).
- [49] H.-K. Janssen, *On a Lagrangean for classical field dynamics and renormalization group calculations of dynamical critical properties*, Z Phys. B **23**(4), 377 (1976), doi:[10.1007/BF01316547](https://doi.org/10.1007/BF01316547).
- [50] C. De Dominicis, *Dynamics as a substitute for replicas in systems with quenched random impurities*, Phys. Rev. B **18**(9), 4913 (1978), doi:[10.1103/PhysRevB.18.4913](https://doi.org/10.1103/PhysRevB.18.4913).
- [51] V. A. Susca, P. Vivo and R. Kühn, *Cavity and replica methods for the spectral density of sparse symmetric random matrices*, SciPost Physics Lecture Notes p. 033 (2021).
- [52] F. Lucas Metz, I. Neri and T. Rogers, *Spectral theory of sparse non-Hermitian random matrices*, J. Phys. A: Math. Theor. **52**(43), 434003 (2019), doi:[10.1088/1751-8121/ab1ce0](https://doi.org/10.1088/1751-8121/ab1ce0).
- [53] G. Semerjian, L. F. Cugliandolo and A. Montanari, *On the Stochastic Dynamics of Disordered Spin Models*, Journal of Statistical Physics **115**(1), 493 (2004), doi:[10.1023/B:JOSS.0000019821.08230.72](https://doi.org/10.1023/B:JOSS.0000019821.08230.72).
- [54] K. Byczuk and D. Vollhardt, *Correlated bosons on a lattice: Dynamical mean-field theory for bose-einstein condensed and normal phases*, Physical Review B **77**(23), 235106 (2008).
- [55] G. Semerjian, M. Tarzia and F. Zamponi, *Exact solution of the bose-hubbard model on the bethe lattice*, Physical Review B **80**(1), 014524 (2009).
- [56] P. Anders, E. Gull, L. Pollet, M. Troyer and P. Werner, *Dynamical mean-field theory for bosons*, New Journal of Physics **13**(7), 075013 (2011).
- [57] T. Plefka, *Convergence condition of the TAP equation for the infinite-ranged Ising spin glass model*, J. Phys. A: Math. Gen. **15**(6), 1971 (1982), doi:[10.1088/0305-4470/15/6/035](https://doi.org/10.1088/0305-4470/15/6/035).
- [58] N. G. Van Kampen, *Stochastic Processes in Physics and Chemistry*, North-Holland Personal Library. Elsevier, Amsterdam, third edition edn., ISBN 978-0-08-047536-3, doi:[10.1016/B978-0-444-52965-7.X5000-4](https://doi.org/10.1016/B978-0-444-52965-7.X5000-4) (2007).
- [59] M. Mézard and A. Montanari, *Information, Physics, and Computation*, Oxford University Press, ISBN 978-0-19-171875-5, doi:[10.1093/acprof:oso/9780198570837.001.0001](https://doi.org/10.1093/acprof:oso/9780198570837.001.0001) (2009).
- [60] A. C. C. Coolen, *Chapter 15 Statistical mechanics of recurrent neural networks II — Dynamics*, In F. Moss and S. Gielen, eds., *Handbook of Biological Physics*, vol. 4 of *Neuro-Informatics and Neural Modelling*, pp. 619–684. North-Holland, doi:[10.1016/S1383-8121\(01\)80018-X](https://doi.org/10.1016/S1383-8121(01)80018-X) (2001).
- [61] See Supplemental Material at [URL-will-be-inserted-by-publisher] for a full derivation of the methods.

-
- [62] G. Livan, M. Novaes and P. Vivo, *Introduction to Random Matrices*, vol. 26 of *SpringerBriefs in Mathematical Physics*, Springer International Publishing, Cham, 1 edn., ISBN 978-3-319-70885-0, doi:[10.1007/978-3-319-70885-0](https://doi.org/10.1007/978-3-319-70885-0) (2018).
- [63] T. Tao, *Topics in Random Matrix Theory*, vol. 132 of *Graduate Studies in Mathematics*, American Mathematical Society, doi:[10.1090/gsm/132](https://doi.org/10.1090/gsm/132) (2012).
- [64] R. Couillet and M. Debbah, *Random Matrix Methods for Wireless Communications*, Cambridge University Press, Cambridge, doi:[10.1017/CBO9780511994746](https://doi.org/10.1017/CBO9780511994746) (2011).
- [65] G. Semerjian and L. F. Cugliandolo, *Sparse random matrices: The eigenvalue spectrum revisited*, J. Phys. A: Math. Gen. **35**(23), 4837 (2002), doi:[10.1088/0305-4470/35/23/303](https://doi.org/10.1088/0305-4470/35/23/303).
- [66] W. Cui, J. W. Rocks and P. Mehta, *An elementary mean-field approach to the spectral densities of random matrix ensembles*, Phys. Stat. Mech. Its Appl. **637**, 129608 (2024), doi:[10.1016/j.physa.2024.129608](https://doi.org/10.1016/j.physa.2024.129608).
- [67] J.-P. Bouchaud, L. Cugliandolo, J. Kurchan and M. Mézard, *Mode-coupling approximations, glass theory and disordered systems*, Physica A: Statistical Mechanics and its Applications **226**(3-4), 243 (1996).
- [68] H. Kesten, *Symmetric random walks on groups*, Trans. Am. Math. Soc. **92**, 336 (1959), doi:[10.1090/S0002-9947-1959-0109367-6](https://doi.org/10.1090/S0002-9947-1959-0109367-6).
- [69] B. D. McKay, *The expected eigenvalue distribution of a large regular graph*, Linear Algebra Its Appl. **40**, 203 (1981), doi:[10.1016/0024-3795\(81\)90150-6](https://doi.org/10.1016/0024-3795(81)90150-6).
- [70] W. Horsthemke and R. Lefever, *Noise-induced transitions in physics, chemistry, and biology*, Noise-induced transitions: theory and applications in physics, chemistry, and biology pp. 164–200 (1984).
- [71] M. A. Muñoz, *Multiplicative noise in non-equilibrium phase transitions: A tutorial*, Advances in condensed matter and statistical physics, Korutcheva, E and Cuerno R. eds. (2004).
- [72] J.-P. Bouchaud and M. Mézard, *Wealth condensation in a simple model of economy*, Physica A: Statistical Mechanics and its Applications **282**(3-4), 536 (2000), doi:[10.1016/S0378-4371\(00\)00205-3](https://doi.org/10.1016/S0378-4371(00)00205-3).
- [73] V. Pareto, *Cours d'économie Politique. Œuvres Complètes Publiées Sous La Direction de Giovanni Busino. Tomes 1 et 2 En Un Volume*, Travaux de Sciences Sociales. Librairie Droz, Genève (1964).
- [74] T. Ichinomiya, *Bouchaud-Mézard model on a random network*, Phys. Rev. E **86**(3), 036111 (2012), doi:[10.1103/PhysRevE.86.036111](https://doi.org/10.1103/PhysRevE.86.036111).
- [75] T. Birner, K. Lippert, R. Müller, A. Kühnel and U. Behn, *Critical behavior of nonequilibrium phase transitions to magnetically ordered states*, Physical Review E **65**(4), 046110 (2002).
- [76] M. A. Muñoz, F. Colaiori and C. Castellano, *Mean-field limit of systems with multiplicative noise*, Physical Review E **72**(5), 056102 (2005).
- [77] K. J. Wiese, *On the perturbation expansion of the kpz equation*, Journal of statistical physics **93**(1), 143 (1998).

-
- [78] G. N. Mil'shtejn, *Approximate Integration of Stochastic Differential Equations*, Theory Probab. Appl. **19**(3), 557 (1975), doi:[10.1137/1119062](https://doi.org/10.1137/1119062).
- [79] X. Gabaix and R. Ibragimov, *Rank - 1 / 2: A Simple Way to Improve the OLS Estimation of Tail Exponents*, J. Bus. Econ. Stat. **29**(1), 24 (2011), doi:[10.1198/jbes.2009.06157](https://doi.org/10.1198/jbes.2009.06157).
- [80] C. De Dominicis and I. Giardinà, *The $p = 2$ spherical model*, In *Random Fields and Spin Glasses: A Field Theory Approach*, pp. 57–78. Cambridge University Press, Cambridge, ISBN 978-0-521-84783-4, doi:[10.1017/CBO9780511534836.005](https://doi.org/10.1017/CBO9780511534836.005) (2006).
- [81] L. F. Cugliandolo and D. S. Dean, *Full dynamical solution for a spherical spin-glass model*, J. Phys. A: Math. Gen. **28**(15), 4213 (1995), doi:[10.1088/0305-4470/28/15/003](https://doi.org/10.1088/0305-4470/28/15/003).
- [82] W. Zippold, R. Kühn and H. Horner, *Non-equilibrium dynamics of simple spherical spin models*, Eur. Phys. J. B **13**(3), 531 (2000), doi:[10.1007/s100510050065](https://doi.org/10.1007/s100510050065).
- [83] L. Dall'Asta and M. Tarabolo, In preparation (2024).
- [84] F. Roy, G. Biroli, G. Bunin and C. Cammarota, *Numerical implementation of dynamical mean field theory for disordered systems: Application to the Lotka–Volterra model of ecosystems*, J. Phys. A: Math. Theor. **52**(48), 484001 (2019), doi:[10.1088/1751-8121/ab1f32](https://doi.org/10.1088/1751-8121/ab1f32), Publisher: IOP Publishing.
- [85] T. Ichinomiya, *Wealth distribution on complex networks*, Phys. Rev. E **86**(6), 066115 (2012), doi:[10.1103/PhysRevE.86.066115](https://doi.org/10.1103/PhysRevE.86.066115).
- [86] T. Ichinomiya, *Power-law exponent of the Bouchaud-M\`ezard model on regular random networks*, Phys. Rev. E **88**(1), 012819 (2013), doi:[10.1103/PhysRevE.88.012819](https://doi.org/10.1103/PhysRevE.88.012819).

Supplemental Material: Gaussian approximation of dynamic cavity equations for linearly-coupled stochastic dynamics

S1 General GECaM equations with non-vanishing conjugate variables

We consider the Gaussian ansatz in Eq. (23) without further assuming that the conjugate averages $\hat{\mu}_{i\setminus j}$ and $B_{i\setminus j}$ vanish due to causality of the dynamics. Writing explicitly the matrix product in Eq. (33a), we find the dynamical equations

$$R_{0,i}^{-1}R_{i\setminus j} = \mathbb{I} + 2D\Delta B_{i\setminus j} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}J_{ki}R_{k\setminus i}R_{i\setminus j} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k\setminus i} B_{i\setminus j} \quad (\text{S1a})$$

$$R_{0,i}^{-1}C_{i\setminus j} = 2\Delta D R_{i\setminus j}^T + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k\setminus i} R_{i\setminus j}^T + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}J_{ki}R_{k\setminus i}C_{i\setminus j} \quad (\text{S1b})$$

$$\left(R_{0,i}^{-1}\right)^T B_{i\setminus j} = \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}J_{ki}R_{k\setminus i}^T B_{i\setminus j} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ki}^2 B_{k\setminus i} R_{i\setminus j} \quad (\text{S1c})$$

From Eq. (33b) we obtain the dynamical equations

$$R_{0,i}^{-1}\mu_{i\setminus j} = \Delta \sum_{k \in \partial i \setminus j} J_{ik}\mu_{k\setminus i} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}J_{ki}R_{k\setminus i}\mu_{i\setminus j} + 2D\Delta i\hat{\mu}_{i\setminus j} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}^2 C_{k\setminus i} i\hat{\mu}_{i\setminus j} \quad (\text{S2a})$$

$$\left(R_{0,i}^{-1}\right) i\hat{\mu}_{i\setminus j} = \Delta \sum_{k \in \partial i \setminus j} J_{ki}i\hat{\mu}_{k\setminus i} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ki}^2 B_{k\setminus i}\mu_{i\setminus j} + \Delta^2 \sum_{k \in \partial i \setminus j} J_{ik}J_{ki}R_{k\setminus i}^T i\hat{\mu}_{i\setminus j}. \quad (\text{S2b})$$

In the limit $\Delta \rightarrow 0$, the non-interacting response becomes $R_{0,i}^{-1}/\Delta \rightarrow \left(\frac{\partial}{\partial t} + \lambda_i\right)$ and the complete set of Gaussian Expansion Cavity Method (GECaM) equations is

$$\begin{aligned} \frac{d}{dt}\mu_{i\setminus j}(t) &= -\lambda_i\mu_{i\setminus j}(t) + \sum_{k \in \partial i \setminus j} J_{ik}\mu_{k\setminus i}(t) + \sum_{k \in \partial i \setminus j} \int dt' J_{ik}R_{k\setminus i}(t, t')J_{ki}\mu_{i\setminus j}(t') \\ &\quad + 2Di\hat{\mu}_{i\setminus j}(t) + \sum_{k \in \partial i \setminus j} \int dt' J_{ik}^2 C_{k\setminus i}(t, t')i\hat{\mu}_{i\setminus j}(t') \end{aligned} \quad (\text{S3a})$$

$$\begin{aligned} \frac{d}{dt}i\hat{\mu}_{i\setminus j}(t) &= \lambda_i i\hat{\mu}_{i\setminus j}(t) - \sum_{k \in \partial i \setminus j} J_{ki}i\hat{\mu}_{k\setminus i}(t) - \sum_{k \in \partial i \setminus j} \int dt' J_{ki}^2 B_{k\setminus i}(t, t')\mu_{i\setminus j}(t') \\ &\quad - \sum_{k \in \partial i \setminus j} \int dt' J_{ik}J_{ki}R_{k\setminus i}(t', t)i\hat{\mu}_{i\setminus j}(t') \end{aligned} \quad (\text{S3b})$$

$$\begin{aligned} \frac{\partial}{\partial t}R_{i\setminus j}(t, t') &= -\lambda_i R_{i\setminus j}(t, t') + \sum_{k \in \partial i \setminus j} \int dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}R_{i\setminus j}(t'', t') \\ &\quad + \sum_{k \in \partial i \setminus j} \int dt'' J_{ik}^2 C_{k\setminus i}(t, t'')B_{i\setminus j}(t'', t') + \delta(t, t') \end{aligned} \quad (\text{S3c})$$

$$\begin{aligned} \frac{\partial}{\partial t}C_{i\setminus j}(t, t') &= -\lambda_i C_{i\setminus j}(t, t') + \sum_{k \in \partial i \setminus j} \int dt'' J_{ik}R_{k\setminus i}(t, t'')J_{ki}C_{i\setminus j}(t'', t') + 2DR_{i\setminus j}(t', t) \\ &\quad + \sum_{k \in \partial i \setminus j} \int dt'' R_{i\setminus j}(t', t'')J_{ik}^2 C_{k\setminus i}(t, t'') \end{aligned} \quad (\text{S3d})$$

$$\begin{aligned} \frac{\partial}{\partial t}B_{i\setminus j}(t, t') &= \lambda_i B_{i\setminus j}(t, t') - \sum_{k \in \partial i \setminus j} \int dt'' J_{ik}J_{ki}R_{k\setminus i}(t'', t)B_{i\setminus j}(t'', t') \\ &\quad - \sum_{k \in \partial i \setminus j} \int dt'' J_{ki}^2 B_{k\setminus i}(t, t'')R_{i\setminus j}(t'', t') \end{aligned} \quad (\text{S3e})$$

We can ascertain that if $\hat{\mu}_{k \setminus i}$ and $B_{k \setminus i}$ vanish, the general GECaM equations reduce to the ones reported in the main text. In addition to that, $\hat{\mu}_{i \setminus j}$ and $B_{i \setminus j}$ vanish consequently, and therefore the assumption is self-consistently verified.

S2 Non-Hermitian random matrices

In what follows we will adopt the method proposed in [66] adapting it to our dynamical setting. To maintain generality, we consider complex-valued coupling matrices $\tilde{\mathbf{J}} \in \mathbb{C}^{N,N}$. From a dynamical point of view, this is equivalent to duplicating the system introducing an auxiliary degree of freedom $y_i \in \mathbb{C}$ for each node of the graph. The duplicated system evolves according to the system of SDEs

$$\frac{d}{dt}x_i(t) = \sum_j \tilde{J}_{ij}y_j(t) - zy_i(t) + \xi_i(t) \quad (\text{S1a})$$

$$\frac{d}{dt}y_i(t) = - \sum_j \tilde{J}_{ji}^*x_j(t) + z^*x_i(t) + \zeta_i(t) \quad (\text{S1b})$$

where $z \in \mathbb{C}$ is a complex valued parameter, corresponding to the eigenvalue of the coupling matrix. The variables ξ_i and ζ_i are complex gaussian noise terms with mean and covariance given by

$$\langle \xi_i(t) \rangle = \langle \zeta_i(t) \rangle = 0 \quad (\text{S2a})$$

$$\langle \xi_i^*(t)\xi_{i'}(t') \rangle = \langle \zeta_i^*(t)\zeta_{i'}(t') \rangle = 2D\delta_{ii'}\delta(t-t'). \quad (\text{S2b})$$

The MSRJD functional integral formalism can now be applied, performing an integration over complex-valued trajectories using the complex Dirac delta function

$$\delta^{(2)}(x) = \delta(\text{Re}x)\delta(\text{Im}x) \propto \int_{\mathbb{C}} d\hat{x}d\hat{x}^* e^{-\hat{x}^*x + \hat{x}x^*}, \quad (\text{S3})$$

where $d\hat{x}d\hat{x}^* = d(\text{Re}x)d(\text{Im}x) = dx^2$ and the integral is taken over the whole complex plane. The dynamical partition function of the system after discretization of time is

$$\begin{aligned} Z \propto \left\langle \int D\vec{x}^2 D\vec{x}^2 D\vec{y}^2 D\vec{y}^2 \prod_{i,n} \exp \left[-(\hat{x}_i^n)^* \left(x_i^{n+1} - x_i^n - \Delta \sum_j \tilde{J}_{ij}y_j^n + \Delta z y_i^n - \Delta \xi_i^n \right) \right. \right. \\ \left. \left. + \hat{x}_i^n \left((x_i^{n+1})^* - (x_i^n)^* - \Delta \sum_j \tilde{J}_{ij}^* (y_j^n)^* + \Delta z^* (y_i^n)^* - (\Delta \xi_i^n)^* \right) \right. \right. \\ \left. \left. - (\hat{y}_i^n)^* \left(y_i^{n+1} - y_i^n + \Delta \sum_j \tilde{J}_{ji}^* x_j^n - \Delta z^* x_i^n - \Delta \zeta_i^n \right) \right. \right. \\ \left. \left. + \hat{y}_i^n \left((y_i^{n+1})^* - (y_i^n)^* + \Delta \sum_j \tilde{J}_{ji} (x_j^n)^* - \Delta z (x_i^n)^n - (\Delta \zeta_i^n)^n \right) \right] \right\rangle_{\Delta \vec{\xi}, \Delta \vec{\zeta}}, \quad (\text{S4}) \end{aligned}$$

where we have introduced $\int D\vec{x}^2 D\vec{x}^2 D\vec{y}^2 D\vec{y}^2 = \prod_{i,n} \int (dx_i^n)^2 (d\hat{x}_i^n)^2 (dy_i^n)^2 (d\hat{y}_i^n)^2$. For notational convenience, we set $\Delta = 1$ below. The average over the complex Gaussian noise can be performed applying the identity

$$\left\langle e^{\vec{x}^\dagger \Delta \vec{\xi} - \Delta \vec{\xi}^\dagger \vec{x} + \vec{y}^\dagger \Delta \vec{\zeta} - \Delta \vec{\zeta}^\dagger \vec{y}} \right\rangle_{\Delta \vec{\xi}, \Delta \vec{\zeta}} = e^{-\vec{x}^\dagger g_x \vec{x} - \vec{y}^\dagger g_y \vec{y}}, \quad (\text{S5})$$

where $[g_x]_{ii',nn'} = \langle (\Delta \xi_i^n)^* \Delta \xi_{i'}^{n'} \rangle = 2D\delta_{ii'}\delta_{nn'} = [g_y]_{ii',nn'} = \langle (\Delta \zeta_i^n)^* \Delta \zeta_{i'}^{n'} \rangle$ is the noise covariance. The

dynamical partition function can be factorized as

$$\begin{aligned}
Z &\propto \int D\vec{x}^2 D\vec{\hat{x}}^2 D\vec{y}^2 D\vec{\hat{y}}^2 \prod_i \exp \left\{ \sum_n \left[-(\hat{x}_i^n)^* (x_i^{n+1} - x_i^n + z y_i^n) \right. \right. \\
&\quad \left. \left. + \hat{x}_i^n \left((x_i^{n+1})^* - (x_i^n)^* + z^* (y_i^n)^* \right) - 2D |\hat{x}_i^n|^2 \right] \right\} \\
&\quad \times \prod_{i<j} \exp \left\{ \sum_n \left[(\hat{x}_i^n)^* \tilde{J}_{ij} y_j^n + y_i^n \tilde{J}_{ji} (\hat{x}_j^n)^* - \hat{x}_i^n \tilde{J}_{ij}^* (y_j^n)^* - (y_i^n)^* \tilde{J}_{ji}^* \hat{x}_j^n \right] \right\} \\
&\quad \times \prod_i \exp \left\{ \sum_n \left[-(\hat{y}_i^n)^* (y_i^{n+1} - y_i^n - z^* x_i^n) + \hat{y}_i^n \left((y_i^{n+1})^* - (y_i^n)^* - z (x_i^n)^* \right) - 2D |\hat{y}_i^n|^2 \right] \right\} \\
&\quad \times \prod_{i<j} \exp \left\{ \sum_n \left[-(\hat{y}_i^n)^* \tilde{J}_{ji}^* x_j^n - x_i^n \tilde{J}_{ij}^* (\hat{y}_j^n)^* + \hat{y}_i^n \tilde{J}_{ji} (x_j^n)^* + (x_i^n)^* \tilde{J}_{ij} \hat{y}_j^n \right] \right\}. \tag{S6}
\end{aligned}$$

It turns out that, in order to properly consider a dynamic cavity ansatz, the trajectories \mathbf{x}_i , $\hat{\mathbf{x}}_i$, \mathbf{y}_i and $\hat{\mathbf{y}}_i$ have to be grouped together into a single variable $\mathcal{W}_i^T = (\mathbf{x}_i, \hat{\mathbf{x}}_i, \mathbf{y}_i, \hat{\mathbf{y}}_i)$. We can write the dynamical partition function as a quadratic form

$$Z \propto \int D\vec{W}^2 \prod_i e^{-\mathcal{W}_i^\dagger \mathcal{G}_{0,i}^{-1} \mathcal{W}_i} \prod_{i<j} e^{-\mathcal{W}_i^\dagger \tilde{\mathcal{J}}_{ij} \mathcal{W}_j - \mathcal{W}_j^\dagger \tilde{\mathcal{J}}_{ji} \mathcal{W}_i}, \tag{S7}$$

where we have introduced $\int D\vec{W}^2 = \prod_i \int D\mathcal{W}_i^2 = \int D\vec{x}^2 D\vec{\hat{x}}^2 D\vec{y}^2 D\vec{\hat{y}}^2$ and the matrices

$$\mathcal{G}_{0,i}^{-1} = \begin{pmatrix} \mathbf{G}_{0,i}^{-1} & \mathbf{H} \\ -\mathbf{H}^\dagger & \mathbf{G}_{0,i}^{-1} \end{pmatrix}, \tag{S8a}$$

$$\tilde{\mathcal{J}}_{ij} = \begin{pmatrix} 0 & -\tilde{\mathbf{J}}_{ij} \\ \tilde{\mathbf{J}}_{ji}^\dagger & 0 \end{pmatrix} = -\tilde{\mathcal{J}}_{ji}^\dagger, \tag{S8b}$$

whose elements are the matrices

$$\mathbf{G}_{0,i}^{-1} = \begin{pmatrix} 0 & [\mathbf{R}_{0,i}^{-1}]^\dagger \\ \mathbf{R}_{0,i}^{-1} & -2D\mathbb{I} \end{pmatrix}, \tag{S9a}$$

$$\mathbf{H} = \begin{pmatrix} 0 & z\mathbb{I} \\ z\mathbb{I} & 0 \end{pmatrix}, \tag{S9b}$$

$$\tilde{\mathbf{J}}_{ij} = \begin{pmatrix} 0 & \tilde{\mathbf{J}}_{ij}\mathbb{I} \\ \tilde{\mathbf{J}}_{ij}\mathbb{I} & 0 \end{pmatrix}. \tag{S9c}$$

The cavity messages are

$$c_{i \setminus j}[\mathcal{W}_i] \propto e^{-\mathcal{W}_i^\dagger \mathcal{G}_{0,i}^{-1} \mathcal{W}_i} \prod_{k \in \partial i \setminus j} \int D\mathcal{W}_k^2 c_{k \setminus i}[\mathcal{W}_k] e^{-\mathcal{W}_k^\dagger \tilde{\mathcal{J}}_{ki} \mathcal{W}_i - \mathcal{W}_i^\dagger \tilde{\mathcal{J}}_{ik} \mathcal{W}_k}. \tag{S10}$$

We assume once again that the cavity messages have a Gaussian functional form, that is

$$c_{i \setminus j}[\mathcal{W}_i] \propto e^{-\mathcal{W}_i^\dagger \mathcal{G}_{i \setminus j}^{-1} \mathcal{W}_i}, \tag{S11}$$

where the cavity propagator is given by

$$\mathcal{G}_{i \setminus j} = \begin{pmatrix} \mathbf{G}_{i \setminus j}^{\text{XX}} & \mathbf{G}_{i \setminus j}^{\text{XY}} \\ \mathbf{G}_{i \setminus j}^{\text{YX}} & \mathbf{G}_{i \setminus j}^{\text{YY}} \end{pmatrix}. \tag{S12}$$

and $G_{i\setminus j}^{AB}$ is the usual propagator between variables A_i and B_i , with A and B being either $X^T = (\mathbf{x}, \hat{\mathbf{x}})$ or $Y^T = (\mathbf{y}, \hat{\mathbf{y}})$

$$G_{i\setminus j}^{AB} = \begin{pmatrix} \langle \mathbf{a}_i \mathbf{b}_i^\dagger \rangle_{\setminus j} & \langle \hat{\mathbf{a}}_i \hat{\mathbf{b}}_i^\dagger \rangle_{\setminus j} \\ \langle \hat{\mathbf{a}}_i \mathbf{b}_i^\dagger \rangle_{\setminus j} & \langle \hat{\mathbf{a}}_i \hat{\mathbf{b}}_i^\dagger \rangle_{\setminus j} \end{pmatrix} = \begin{pmatrix} C_{i\setminus j}^{AB} & R_{i\setminus j}^{AB} \\ (R_{i\setminus j}^{BA})^\dagger & 0 \end{pmatrix}. \quad (\text{S12})$$

Integrating out the variables \mathcal{W}_k , we obtain

$$c_{i\setminus j}[\mathcal{W}_i] \propto e^{-\mathcal{W}_i^\dagger \mathcal{G}_{0,i}^{-1} \mathcal{W}_i} \prod_{k \in \partial i \setminus j} \int D\mathcal{W}_k^2 e^{-\mathcal{W}_k^\dagger \mathcal{G}_{k\setminus i}^{-1} \mathcal{W}_k - \mathcal{W}_k^\dagger \tilde{\mathcal{J}}_{ki} \mathcal{W}_i - \mathcal{W}_i^\dagger \tilde{\mathcal{J}}_{ik} \mathcal{W}_k} \quad (\text{S13a})$$

$$\propto e^{-\mathcal{W}_i^\dagger \mathcal{G}_{0,i}^{-1} \mathcal{W}_i + \sum_{k \in \partial i \setminus j} \mathcal{W}_i^\dagger \tilde{\mathcal{J}}_{ik} \mathcal{G}_{k\setminus i} \tilde{\mathcal{J}}_{ki} \mathcal{W}_i}, \quad (\text{S13b})$$

from which we get the extended GECaM matrix equation

$$\mathcal{G}_{i\setminus j}^{-1} = \mathcal{G}_{0,i}^{-1} - \sum_{k \in \partial i \setminus j} \tilde{\mathcal{J}}_{ik} \mathcal{G}_{k\setminus i} \tilde{\mathcal{J}}_{ki}. \quad (\text{S14})$$

To compute the spectral density, we only need the equations for the response functions. Conveniently expressed in matrix form and in the Laplace space, these equations are

$$\mathbf{R}_{i\setminus j}^{-1} = \mathbf{z} + \eta \mathbf{l} - \sum_{k \in \partial i \setminus j} \tilde{\mathbf{J}}_{ik} \mathbf{R}_{k\setminus i} \tilde{\mathbf{J}}_{ki}, \quad (\text{S15})$$

where we have introduced the matrices,

$$\mathbf{R}_{i\setminus j} = \begin{pmatrix} R_{i\setminus j}^{XX} & R_{i\setminus j}^{XY} \\ R_{i\setminus j}^{YX} & R_{i\setminus j}^{YY} \end{pmatrix} \quad (\text{S16a})$$

$$\mathbf{z} = \begin{pmatrix} 0 & z \\ -z^* & 0 \end{pmatrix} \quad (\text{S16b})$$

and redefined for convenience the coupling matrix $\tilde{\mathbf{J}}_{ij}$ as follows

$$\tilde{\mathbf{J}}_{ij} = \begin{pmatrix} 0 & a_{ij} \\ -a_{ji}^* & 0 \end{pmatrix}. \quad (\text{S17})$$

Equation (S15) is equivalent to Eq. (64) in [52]. We can therefore compute the spectral distribution of \mathbf{J} as

$$\rho_{\mathbf{J}}(z) = \lim_{\eta \rightarrow 0} \frac{1}{\pi N} \partial_{z^*} R_i^{YX}(z - \lambda_i). \quad (\text{S18})$$

S3 Noise-driven phase transition in the Bouchaud-Mézard model

S3.1 Critical point

We consider the integral Eq. (98a) obtained from the Gaussian perturbation closure technique of the BM model on an homogeneous RRG.

$$I = \int_{-\infty}^{\infty} \frac{d\omega}{2\pi} \left[\frac{i\omega + \lambda - \sqrt{(i\omega + \lambda)^2 - 4(K-1)J^2}}{2(K-1)J^2} \right] \left[\frac{-i\omega + \lambda - \sqrt{(-i\omega + \lambda)^2 - 4(K-1)J^2}}{2(K-1)J^2} \right] \quad (\text{S1a})$$

$$= -\frac{2i}{\pi} \int_{-\infty}^{\infty} d(i\omega) \frac{1}{\lambda + i\omega + \sqrt{(\lambda + i\omega)^2 - 4(K-1)J^2}} \frac{1}{\lambda - i\omega + \sqrt{(\lambda - i\omega)^2 - 4(K-1)J^2}}, \quad (\text{S1b})$$

where $\lambda = KJ$. The integral on the second line can be viewed as a complex integral over the imaginary axis $\tilde{\mathfrak{I}}\mathfrak{m}$.

$$I = -\frac{2i}{\pi} \int_{\tilde{\mathfrak{I}}\mathfrak{m}} dz F(z), \quad (\text{S2})$$




Figure 5: Contour used for the computation of Eq. (S2). The paths γ_R^+ and γ_R^- are circular arcs of radius $R \rightarrow \infty$, while γ_ϵ^+ , γ_ϵ^- and γ'_ϵ are circular arcs of radius $\epsilon \rightarrow 0$. It can be showed that all of them vanish in the proper limit.

where we have defined $F(z) = f(z)f(-z)$ with

$$f(z) = \left(\lambda + z + \sqrt{(\lambda + z)^2 - 4(K-1)J^2} \right). \quad (\text{S3})$$

$F(z)$ has two symmetric branch cuts associated with the square root validity intervals, i.e $\mathcal{B}_- = [-\lambda - A, -\lambda + A]$ and $\mathcal{B}_+ = [\lambda - A, \lambda + A]$, with $A = 2\sqrt{K-1}J$. The integral along the imaginary axis can be computed from a contour integral on the complex plane in which the complex variable z is integrated along a contour \mathcal{C} that goes along the imaginary axis then closes in a semicircle with a detour to avoid the inclusion of the \mathcal{B}_- branch cut. Figure 5 shows that the contour \mathcal{C} can be decomposed into elementary paths.

More precisely,

$$\oint_{\mathcal{C}} dz F(z) = \left(\int_{\gamma} + \int_{\gamma_R^+} + \int_{\gamma_R^-} + \int_{\gamma_\epsilon^+} + \int_{\gamma_\epsilon^-} + \int_{\gamma'_\epsilon} + \int_{\gamma_1} + \int_{\gamma_2} + \int_{\gamma_3} + \int_{\gamma_4} \right) dz F(z) = 0, \quad (\text{S4})$$

since the contour contains no singularity or branch cuts. Taking the appropriate limits we can therefore write

$$I = \frac{2i}{\pi} \left[\lim_{R \rightarrow +\infty} \left(\int_{\gamma_R^+} + \int_{\gamma_R^-} \right) + \lim_{\epsilon \rightarrow 0^+} \left(\int_{\gamma_\epsilon^+} + \int_{\gamma_\epsilon^-} + \int_{\gamma'_\epsilon} \right) + \int_{\gamma_1} + \int_{\gamma_2} + \int_{\gamma_3} + \int_{\gamma_4} \right] dz F(z). \quad (\text{S5})$$

It can be shown that the only non-vanishing integrals are those along γ_1 , γ_2 , γ_3 and γ_4 , however the first two cancels out due to analyticity. The integrals along γ_3 and γ_4 instead sum up, since the square roots have opposite signs on the two sides of the branch cut.

$$\int_{\gamma_3} dz F(z) = \int_{-\lambda-A}^{-\lambda+A} dx \left[\frac{1}{\lambda + x + i\sqrt{A^2 - (\lambda + x)^2}} \right] \left[\frac{1}{\lambda - x + \sqrt{(\lambda - x)^2 - A^2}} \right] \quad (\text{S6a})$$

$$\int_{\gamma_4} dz F(z) = \int_{-\lambda+A}^{-\lambda-A} dx \left[\frac{1}{\lambda + x - i\sqrt{A^2 - (\lambda + x)^2}} \right] \left[\frac{1}{\lambda - x + \sqrt{(\lambda - x)^2 - A^2}} \right], \quad (\text{S6b})$$

where we used the parametrization $z = -xe^{i\pi}$ for the first integral and $z = -xe^{-i\pi}$ for the second one.

Gathering all terms,

$$I = \frac{2i}{\pi} \int_{-\lambda-A}^{-\lambda+A} dx \left[\frac{1}{\lambda+x+i\sqrt{A^2-(\lambda+x)^2}} - \frac{1}{\lambda+x-i\sqrt{A^2-(\lambda+x)^2}} \right] \left[\frac{1}{\lambda-x+\sqrt{(\lambda-x)^2-A^2}} \right] \quad (S7a)$$

$$= \frac{2i}{\pi} \int_{-\lambda-A}^{-\lambda+A} dx \left[\frac{-2i\sqrt{A^2-(\lambda+x)^2}}{\left(\lambda+x+i\sqrt{A^2-(\lambda+x)^2}\right)\left(\lambda+x-i\sqrt{A^2-(\lambda+x)^2}\right)} \right] \left[\frac{1}{\lambda-x+\sqrt{(\lambda-x)^2-A^2}} \right] \quad (S7b)$$

$$= \frac{4}{\pi A^2} \int_{-\lambda-A}^{-\lambda+A} dx \left[\frac{\sqrt{A^2-(\lambda+x)^2}}{\lambda-x+\sqrt{(\lambda-x)^2-A^2}} \right]. \quad (S7c)$$

Changing variable $u = (\lambda+x)/A$, the integral is simplified as follows

$$I = I_K = \frac{2}{\pi\sqrt{K-1}J} \int_{-1}^1 du \frac{\sqrt{1-u^2}}{\frac{K}{\sqrt{K-1}} - u + \sqrt{\left(\frac{K}{\sqrt{K-1}} - u\right)^2 - 1}}, \quad (S8)$$

which gives the correct result in the FC limit after rescaling $J = J/K$ and taking the limit $K \rightarrow \infty$

$$I_\infty \approx \frac{2}{\pi J} \frac{K}{\sqrt{K-1}} \int_{-1}^1 du \frac{\sqrt{1-u^2}}{2\frac{K}{\sqrt{K-1}}} = \frac{1}{2J}. \quad (S9)$$

S3.2 Adiabatic and independent assumption for GECaM

The approximation method proposed in [74, 85, 86] is based on the combination of two assumptions: (1) the ‘‘local field’’ $\sum_{j \in \partial i} x_j$ acting on i is assumed to change much more slowly than x_i (*adiabatic assumption*); (2) the neighbouring variables x_j for $j \in \partial i$ are assumed to be independent, so that the local field satisfies the Central Limit Theorem and converges to a Gaussian distribution (*independence assumption*). In this Section, we show that this approximation naturally follows from the GECaM approximation under specific conditions. To simplify the calculations, we will only consider the case of a RRG with degree K .

Employing as usual the Gaussian ansatz in Eq. (23), the local marginal of node i with a perturbation action $S_i^I[\mathbf{X}_i]$ can be written as follows

$$c_i[\mathbf{X}_i] \propto e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - S_i^I[\mathbf{X}_i]} \prod_{k \in \partial i} \int D\mathbf{X}_k e^{-\frac{1}{2}(\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})} e^{-\mathbf{X}_i^T \mathbf{J}_{ik} \mathbf{X}_k}. \quad (S10)$$

We also assume that all couplings are the same, i.e. $\mathbf{J}_{ik} = \mathbf{J}$, and introduce a local field $K\mathbf{H}_i = \sum_{j \in \partial i} \mathbf{X}_j$. The previous expression becomes

$$c_i[\mathbf{X}_i] \propto e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - S_i^I[\mathbf{X}_i]} \prod_{k \in \partial i} \int D\mathbf{X}_k e^{-\frac{1}{2}(\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})} e^{-\mathbf{X}_i^T \mathbf{J} \mathbf{X}_k} \int D\mathbf{H}_i \delta\left(K\mathbf{H}_i - \sum_{j \in \partial i} \mathbf{X}_j\right) \quad (S11a)$$

$$\propto e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - S_i^I[\mathbf{X}_i]} \prod_{k \in \partial i} \int D\mathbf{X}_k e^{-\frac{1}{2}(\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i})} e^{-\mathbf{X}_i^T \mathbf{J} \mathbf{X}_k} \int D\mathbf{H}_i D\hat{\mathbf{H}}_i e^{-i\hat{\mathbf{H}}_i^T (K\mathbf{H}_i - \sum_{k \in \partial i} \mathbf{X}_k)} \quad (S11b)$$

$$\propto e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - S_i^I[\mathbf{X}_i]} \int D\mathbf{H}_i D\hat{\mathbf{H}}_i e^{-K i \hat{\mathbf{H}}_i^T \mathbf{H}_i} \prod_{k \in \partial i} \int D\mathbf{X}_k e^{-\frac{1}{2}(\mathbf{X}_k - \mathbf{M}_{k \setminus i})^T \mathbf{G}_{k \setminus i}^{-1} (\mathbf{X}_k - \mathbf{M}_{k \setminus i}) + (i\hat{\mathbf{H}}_i - \mathbf{J}^T \mathbf{X}_i)^T \mathbf{X}_k}. \quad (S11c)$$

Performing the Gaussian integral and introducing $\mathbf{M}_i = \sum_{k \in \partial i} \mathbf{M}_{k \setminus i}$ and $\mathbf{G}_i = \sum_{k \in \partial i} \mathbf{G}_{k \setminus i}$, we get

$$c_i[\mathbf{X}_i] \propto e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - S_i^I[\mathbf{X}_i]} \int D\mathbf{H}_i D\hat{\mathbf{H}}_i e^{-K i \hat{\mathbf{H}}_i^T \mathbf{H}_i + (i\hat{\mathbf{H}}_i - \mathbf{J}^T \mathbf{X}_i)^T \mathbf{M}_i + \frac{1}{2}(i\hat{\mathbf{H}}_i - \mathbf{J}^T \mathbf{X}_i)^T \mathbf{G}_i (i\hat{\mathbf{H}}_i - \mathbf{J}^T \mathbf{X}_i)}. \quad (S12)$$

The integral in \hat{H} is also Gaussian and it can be done to obtain

$$c_i[\mathbf{X}_i] \propto \int D\mathbf{H}_i e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - K\mathbf{X}_i^T \mathbf{J}\mathbf{H}_i - S_i^I[\mathbf{X}_i]} e^{-\frac{1}{2}(\mathbf{K}\mathbf{H}_i - \mathbf{M}_i)^T \mathbf{G}_i^{-1} (\mathbf{K}\mathbf{H}_i - \mathbf{M}_i)}. \quad (\text{S13})$$

The local marginal can be written in a conditional form, which reminds of the previously discussed adiabatic assumption,

$$c_i[\mathbf{X}_i] = \int D\mathbf{H}_i c_i[\mathbf{X}_i|\mathbf{H}_i] p[\mathbf{H}_i] \quad (\text{S14a})$$

$$c_i[\mathbf{X}_i|\mathbf{H}_i] = \frac{1}{Z_{\mathbf{X}}[\mathbf{H}_i]} e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - K\mathbf{X}_i^T \mathbf{J}\mathbf{H}_i - S_i^I[\mathbf{X}_i]} \quad (\text{S14b})$$

$$p[\mathbf{H}_i] = \frac{1}{Z_{\mathbf{H}}} e^{-\frac{1}{2}(\mathbf{K}\mathbf{H}_i - \mathbf{M}_i)^T \mathbf{G}_i^{-1} (\mathbf{K}\mathbf{H}_i - \mathbf{M}_i)}, \quad (\text{S14c})$$

where the partition functions are

$$Z_{\mathbf{X}}[\mathbf{H}_i] = \int D\mathbf{X}_i e^{-\frac{1}{2}\mathbf{X}_i^T \mathbf{G}_{0,i}^{-1} \mathbf{X}_i - K\mathbf{X}_i^T \mathbf{J}\mathbf{H}_i - S_i^I[\mathbf{X}_i]} \quad (\text{S15a})$$

$$Z_{\mathbf{H}} = \left((2\pi)^{2(T+1)} \det \mathbf{G}_i \right)^{-1/2}. \quad (\text{S15b})$$

In the case of a random regular graph with homogeneous coupling constants, there is no distinction between nodes in the thermodynamic limit, therefore we drop all the corresponding indices. It follows that the contributions from the neighbours are the same

$$\mathbf{M}_i = \sum_{k \in \partial i} \mathbf{M}_{k \setminus i} = K\mathbf{M}_{\text{cav}}, \quad \mathbf{G}_i = \sum_{k \in \partial i} \mathbf{G}_{k \setminus i} = K\mathbf{G}_{\text{cav}}, \quad (\text{S16})$$

therefore $\mathbf{H}^T = (\mathbf{h}_1, \mathbf{h}_2)$ is a local field with Gaussian statistics, with mean $\langle \mathbf{H} \rangle = \mathbf{M}_{\text{cav}}$ and variance $\langle \mathbf{H}^2 \rangle - \langle \mathbf{H} \rangle^2 = \mathbf{G}_{\text{cav}}/K$.

The first two moments of x can be computed as

$$\langle x(t) \rangle = \int D\mathbf{X} c[\mathbf{X}] x(t) \quad (\text{S17a})$$

$$= \int D\mathbf{H} p[\mathbf{H}] \int D\mathbf{X} \frac{x(t)}{Z_{\mathbf{X}}[\mathbf{H}]} e^{-\frac{1}{2}\mathbf{X}^T \mathbf{G}_0^{-1} \mathbf{X} - K\mathbf{X}^T \mathbf{J}\mathbf{H} - S^I[\mathbf{X}]} \quad (\text{S17b})$$

$$= -\frac{1}{KJ} \left\langle \frac{1}{Z_{\mathbf{X}}[\mathbf{H}]} \frac{\delta}{\delta h_2(t)} Z_{\mathbf{X}}[\mathbf{H}] \right\rangle_{\mathbf{H}} \quad (\text{S17c})$$

and

$$\langle x^2(t) \rangle = \int D\mathbf{X} c[\mathbf{X}] x^2(t) \quad (\text{S18a})$$

$$= \int D\mathbf{H} p[\mathbf{H}] \int D\mathbf{X} \frac{x^2(t)}{Z_{\mathbf{X}}[\mathbf{H}]} e^{-\frac{1}{2}\mathbf{X}^T \mathbf{G}_0^{-1} \mathbf{X} - K\mathbf{X}^T \mathbf{J}\mathbf{H} - S^I[\mathbf{X}]} \quad (\text{S18b})$$

$$= \frac{1}{(KJ)^2} \left\langle \frac{1}{Z_{\mathbf{X}}[\mathbf{H}]} \frac{\delta^2}{\delta h_2^2(t)} Z_{\mathbf{X}}[\mathbf{H}] \right\rangle_{\mathbf{H}}. \quad (\text{S18c})$$

S3.2.1 Linear dynamics with additive noise

We now focus on the simplest case of a linear dynamics with additive noise ($S^I = 0$), where $\lambda = KJ$ is the drift coefficient and D is the noise coefficient. The partition function is easily obtained as a Gaussian integral

$$Z_{\mathbf{X}}[\mathbf{H}] = \int D\mathbf{X} e^{-\frac{1}{2}\mathbf{X}^T \mathbf{G}_0^{-1} \mathbf{X} - K\mathbf{X}^T \mathbf{J}\mathbf{H}} \propto e^{\frac{K}{2}(\mathbf{J}^T \mathbf{H})^T \mathbf{G}_0 (\mathbf{J}^T \mathbf{H})}, \quad (\text{S19})$$

where G_0 is the free particle propagator

$$\mathbf{G}_0(t, t') = \begin{pmatrix} C_f(t, t') & R_f(t, t') \\ R_f(t', t) & 0 \end{pmatrix}, \quad (\text{S20})$$

with $C_f(t, t') = D/\lambda \exp(-\lambda|t-t'|)$ being the free particle correlation function and $R_f(t, t') = \Theta(t-t') \exp(-\lambda(t-t'))$ the free particle response function. It follows that the partition function can be written as

$$Z_X[\mathbf{H}] \propto \exp \left\{ \frac{(KJ)^2}{2} \int dt \int dt' (h_2(t)C_f(t, t')h_2(t') + 2h_2(t)R_f(t, t')h_1(t')) \right\}, \quad (\text{S21})$$

from which the first and second moments of x follow

$$\langle x(t) \rangle = -\frac{1}{KJ} \left\langle \frac{1}{Z_X[\mathbf{H}]} \frac{\delta}{\delta h_2(t)} Z_X[\mathbf{H}] \right\rangle_{\mathbf{H}} \quad (\text{S22a})$$

$$= -\frac{KJ}{2} \int dt' (2C_f(t, t')\langle h_2(t') \rangle_{\mathbf{H}} + 2R_f(t, t')\langle h_1(t') \rangle_{\mathbf{H}}) \quad (\text{S22b})$$

$$= -KJ \int dt' (C_f(t, t')i\hat{\mu}_{\text{cav}}(t'))_{\mathbf{H}} + R_f(t, t')\mu_{\text{cav}}(t') \quad (\text{S22c})$$

$$= -KJ \int dt' R_f(t, t')\mu_{\text{cav}}(t') \quad (\text{S22d})$$

$$\langle x^2(t) \rangle = \frac{1}{(KJ)^2} \left\langle \frac{1}{Z_X[\mathbf{H}]} \frac{\delta^2}{\delta h_2^2(t)} Z_X[\mathbf{H}] \right\rangle_{\mathbf{H}} \quad (\text{S23a})$$

$$= C_f(t, t) + \frac{(KJ)^2}{4} \left\langle \left[\int dt' (2C_f(t, t')h_2(t') + 2R_f(t, t')h_1(t')) \right]^2 \right\rangle_{\mathbf{H}} \quad (\text{S23b})$$

$$= C_f(t, t) + \frac{(KJ)^2}{4} \int dt' dt'' (4C_f(t, t')C_f(t, t'')\langle h_2(t')h_2(t'') \rangle_{\mathbf{H}} + 4R_f(t, t')R_f(t, t'')\langle h_1(t')h_1(t'') \rangle_{\mathbf{H}} + 2C_f(t, t')R_f(t, t'')\langle h_2(t')h_1(t'') \rangle_{\mathbf{H}} + 2R_f(t, t')C_f(t, t'')\langle h_1(t')h_2(t'') \rangle_{\mathbf{H}}) \quad (\text{S23c})$$

$$= C_f(t, t) + (KJ)^2 \int dt' dt'' \left(R_f(t, t')R_f(t, t'')\frac{\tilde{C}_{\text{cav}}(t', t'')}{K} + R_f(t, t')C_f(t, t'')\frac{R_{\text{cav}}(t', t'')}{K} \right), \quad (\text{S23d})$$

where $\tilde{C}_{\text{cav}}(t', t'') = K\langle h_1(t')h_1(t'') \rangle_{\mathbf{H}}$ is the cavity disconnected correlation. In summary, in the stationary state,

$$s^2 = \frac{D}{\lambda} + (KJ)^2 \int_0^\infty d\tau \int_0^\infty ds \left(R_f(\tau)R_f(s)\frac{C_{\text{cav}}(s-\tau)}{K} + R_f(\tau)C_f(s)\frac{R_{\text{cav}}(s-\tau)}{K} \right). \quad (\text{S24})$$

It can be shown that the ‘‘adiabatic and independent’’ approximation of [74] corresponds to approximating the cavity quantities by the full quantities at zero time differences, i.e $C_{\text{cav}}(s-\tau) \approx C(0) = s^2$ and $R_{\text{cav}}(s-\tau) \approx R(0) = 0$, so that we obtain

$$s^2 = \frac{D}{\lambda} + \frac{s^2}{K}(KJ)^2 \int_0^\infty d\tau e^{-\lambda\tau} \int_0^\infty ds e^{-\lambda s} \quad (\text{S25a})$$

$$= \frac{D}{\lambda} + \frac{s^2}{K} \left(\frac{KJ}{\lambda} \right)^2, \quad (\text{S25b})$$

and, since $\lambda = KJ$, we get the relation

$$s^2 = \frac{D}{J(K-1)}, \quad (\text{S26})$$

which can be obtained using the approximation in [74].

S3.2.2 Bouchaud-Mézard model

We apply the previous approximation to the BM model, in which case $\lambda = KJ$ and $D = 0$ in the Gaussian part of the action. The interacting part of the action is non-gaussian

$$S^I[\mathbf{X}] = -\frac{1}{2}\sigma^2 \int dt x^2(t)(i\hat{x}(t))^2 = -\frac{1}{8}\sigma^2 (\mathbf{X}^T \sigma_1 \mathbf{X})^2, \quad (\text{S27})$$

and it has to be computed perturbatively. In order to properly perturb the system, we have to rescale the variables as usual, defining $X^T = (1 + \phi, \hat{\phi})$. The field $K\tilde{H}_i = \sum_{j \in \partial i} \Phi_j$ has now a different average. The site label will be dropped in the rest of the calculation. The field $\tilde{H}^T = (\mathbf{h}_1 - 1, \mathbf{h}_2)$ is a Gaussian random variable with mean $\langle \tilde{H} \rangle = \tilde{M}_{\text{cav}}$ and variance $\langle \tilde{H}^2 \rangle - \langle \tilde{H} \rangle^2 = \mathbf{G}_{\text{cav}}/K$, where $\tilde{M}_{\text{cav}}^T = (\boldsymbol{\mu}_{\text{cav}} - 1, 0)$. In summary the distribution of Φ is

$$c[\Phi] = \int D\tilde{H} c[\Phi|\tilde{H}] p[\tilde{H}] \quad (\text{S28a})$$

$$c[\Phi|\tilde{H}] = \frac{1}{Z_\Phi[\tilde{H}]} e^{-\frac{1}{2}\Phi^T \mathbf{G}_0^{-1} \Phi - K\Phi^T \mathbf{J}\tilde{H} - S^I[\Phi]} \quad (\text{S28b})$$

$$p[\tilde{H}] = \frac{1}{Z_{\tilde{H}}} e^{-\frac{1}{2}(\tilde{H} - \tilde{M}_{\text{cav}})^T K \mathbf{G}_{\text{cav}}^{-1} (\tilde{H} - \tilde{M}_{\text{cav}})}, \quad (\text{S28c})$$

where the partition functions are

$$Z_\Phi[\tilde{H}] = \int D\Phi e^{-\frac{1}{2}\Phi^T \mathbf{G}_0^{-1} \Phi - K\Phi^T \mathbf{J}\tilde{H} - S^I[\Phi]} \quad (\text{S29a})$$

$$Z_{\tilde{H}} = \left(\left(\frac{2\pi}{K} \right)^{2(T+1)} \det \mathbf{G}_{\text{cav}} \right)^{-1/2}. \quad (\text{S29b})$$

In terms of the field Φ , the interacting part of the action can be written as

$$S^I[\Phi] = -\frac{1}{2}\sigma^2 \int dt (1 + \phi(t))^2 \hat{\phi}(t)^2 = -\frac{\sigma^2}{2} \int dt \hat{\phi}^2(t) - \sigma^2 \int dt \hat{\phi}^2(t) \phi(t) - \frac{\sigma^2}{2} \int dt \hat{\phi}^2(t) \phi^2(t). \quad (\text{S30})$$

The partition function $Z_\Phi[\tilde{H}]$ can be computed perturbatively. At first order in σ^2

$$Z_\Phi[\tilde{H}] \approx \int D\Phi e^{-\frac{1}{2}\Phi^T \mathbf{G}_0^{-1} \Phi - K\Phi^T \mathbf{J}\tilde{H}} \left(1 + \frac{\sigma^2}{2} \int dt \hat{\phi}^2(t) + \sigma^2 \int dt \hat{\phi}^2(t) \phi(t) + \frac{\sigma^2}{2} \int dt \hat{\phi}^2(t) \phi^2(t) \right) \quad (\text{S31a})$$

$$= \left\{ 1 + \frac{\sigma^2}{2} \frac{1}{(KJ)^2} \int dt \frac{\delta^2}{\delta \tilde{h}_1^2(t)} - \sigma^2 \frac{1}{(KJ)^3} \int dt \frac{\delta^3}{\delta \tilde{h}_2(t) \delta \tilde{h}_1^2(t)} + \frac{\sigma^2}{2} \frac{1}{(KJ)^4} \int dt \frac{\delta^4}{\delta \tilde{h}_2^2(t) \delta \tilde{h}_1^2(t)} \right\} Z_\Phi^0[\tilde{H}] \quad (\text{S31b})$$

$$= \left\{ 1 + \frac{\sigma^2}{2} \hat{T}_1 - \sigma^2 \hat{T}_2 + \frac{\sigma^2}{2} \hat{T}_3 \right\} Z_\Phi^0[\tilde{H}], \quad (\text{S31c})$$

where \hat{T}_1 , \hat{T}_2 and \hat{T}_3 are operators acting on the Gaussian single particle partition function

$$Z_\Phi^0[\tilde{H}] = \int D\Phi e^{-\frac{1}{2}\Phi^T \mathbf{G}_0^{-1} \Phi - K\Phi^T \mathbf{J}\tilde{H}} = e^{-\tilde{S}^0[\tilde{H}]} \quad (\text{S32a})$$

$$\tilde{S}^0[\tilde{H}] = -(KJ)^2 \int dt_1 \int dt_2 \tilde{h}_2(t_1) R_f(t_1, t_2) \tilde{h}_1(t_2), \quad (\text{S32b})$$

where we have used $C_f(t, t') = 0$ for the BM model. The operators act on it as

$$\hat{T}_1 Z_\Phi^0[\tilde{H}] = (KJ)^2 \int dt \int dt_1 R_f(t_1, t) \tilde{h}_2(t_1) \int dt_2 R_f(t_2, t) \tilde{h}_2(t_2) Z_\Phi^0[\tilde{H}] \quad (\text{S33a})$$

$$= T_1[\tilde{H}] Z_\Phi^0[\tilde{H}] \quad (\text{S33b})$$

$$\hat{T}_2 Z_\Phi^0[\tilde{H}] = (KJ)^3 \int dt \int dt_1 R_f(t_1, t) \tilde{h}_2(t_1) \int dt_2 R_f(t_2, t) \tilde{h}_2(t_2) \int dt_3 R_f(t, t_3) \tilde{h}_1(t_3) Z_\Phi^0[\tilde{H}] \quad (\text{S33c})$$

$$= T_2[\tilde{H}] Z_\Phi^0[\tilde{H}] \quad (\text{S33d})$$

$$\hat{T}_3 Z_\Phi^0[\tilde{H}] = (KJ)^4 \int dt \int dt_1 R_f(t_1, t) \tilde{h}_2(t_1) \int dt_2 R_f(t_2, t) \tilde{h}_2(t_2) \int dt_3 \tilde{h}_1(t_3) R_f(t, t_3) \int dt_4 R_f(t, t_4) \tilde{h}_1(t_4) Z_\Phi^0[\tilde{H}] \quad (\text{S33e})$$

$$= T_3[\tilde{H}] Z_\Phi^0[\tilde{H}],$$

where we have used $R_f(t, t) = 0$ in the Itô case. In summary,

$$Z_\Phi[\tilde{H}] \approx Z_\Phi^0[\tilde{H}] \left(1 + \frac{\sigma^2}{2} T_1[\tilde{H}] - \sigma^2 T_2[\tilde{H}] + \frac{\sigma^2}{2} T_3[\tilde{H}] \right) \quad (\text{S34a})$$

$$\approx e^{-\tilde{S}^0[\tilde{H}] + \frac{\sigma^2}{2} T_1[\tilde{H}] - \sigma^2 T_2[\tilde{H}] + \frac{\sigma^2}{2} T_3[\tilde{H}]} \quad (\text{S34b})$$

$$= e^{-\tilde{S}[\tilde{H}]}. \quad (\text{S34c})$$

It is now possible to compute the first and second moments of the field ϕ . We neglect contributions in the local self-consistent field beyond second order. The mean is

$$\langle \phi(t) \rangle = -\frac{1}{KJ} \left\langle \frac{1}{Z_\Phi[\tilde{H}]} \frac{\delta}{\delta \tilde{h}_2(t)} Z_\Phi[\tilde{H}] \right\rangle_{\tilde{H}} \quad (\text{S35a})$$

$$= -(KJ) \left(\int dt' R_f(t, t') \langle \tilde{h}_1(t') \rangle_{\tilde{H}} - 2\sigma^2 \int dt_1 R_f(t, t_1) \int dt_2 R_f(t_2, t_1) \int dt_3 R_f(t_1, t_3) \langle \tilde{h}_2(t_2) \tilde{h}_1(t_3) \rangle_{\tilde{H}} \right) \quad (\text{S35b})$$

$$= 2\sigma^2 (KJ) \int dt_1 R_f(t, t_1) \int dt_2 R_f(t_2, t_1) \int dt_3 R_f(t_1, t_3) \frac{R_{\text{cav}}(t_3, t_2)}{K} = 0 \quad (\text{S35c})$$

due to causality ($R_f(t, t') = R_{\text{cav}}(t, t') = 0$ if $t' > t$). Computing the second moment is more complicated. We use that

$$\langle \phi(t)^2 \rangle = \frac{1}{(KJ)^2} \left\langle \frac{1}{Z_\Phi[\tilde{H}]} \frac{\delta^2}{\delta \tilde{h}_2^2(t)} Z_\Phi[\tilde{H}] \right\rangle_{\tilde{H}} \quad (\text{S36a})$$

$$= \frac{1}{(KJ)^2} \left[\left\langle \left(\frac{\delta}{\delta \tilde{h}_2(t)} \tilde{S}[\tilde{H}] \right)^2 \right\rangle_{\tilde{H}} - \left\langle \frac{\delta^2}{\delta \tilde{h}_2^2(t)} \tilde{S}[\tilde{H}] \right\rangle_{\tilde{H}} \right], \quad (\text{S36b})$$

where the first average is given by

$$\left\langle \left(\frac{\delta}{\delta \tilde{h}_2(t)} \tilde{S}[\tilde{H}] \right)^2 \right\rangle_{\tilde{H}} = (KJ)^4 \left\{ \int dt_1 \int dt_2 R_f(t, t_1) R_f(t, t_2) \langle \tilde{h}_1(t_1) \tilde{h}_1(t_2) \rangle_{\tilde{H}} \right. \\ \left. + 2\sigma^2 \int dt_1 \int dt_2 R_f(t, t_2) \int dt_3 R_f(t, t_3) R_f(t_1, t_3) \langle \tilde{h}_2(t_1) \tilde{h}_1(t_2) \rangle_{\tilde{H}} \right\} \quad (\text{S37a})$$

$$= (KJ)^4 \left\{ \int dt_1 \int dt_2 R_f(t, t_1) R_f(t, t_2) \frac{C_{\text{cav}}(t_1, t_2)}{K} \right. \\ \left. + 2\sigma^2 \int dt_1 \int dt_2 R_f(t, t_2) \int dt_3 R_f(t, t_3) R_f(t_1, t_3) \frac{R_{\text{cav}}(t_2, t_1)}{K} \right\}, \quad (\text{S37b})$$

and the second one is

$$\left\langle \frac{\delta^2}{\delta \tilde{h}_2^2(t)} \tilde{S}[\tilde{H}] \right\rangle_{\tilde{H}} = (KJ)^2 \sigma^2 \int dt_1 R_f^2(t, t_1) \left(1 + (KJ)^2 \int dt_2 \int dt_3 R_f(t_1, t_2) R_f(t_1, t_3) \langle \tilde{h}_1(t_2) \tilde{h}_1(t_3) \rangle_{\tilde{H}} \right) \quad (\text{S38a})$$

$$= (KJ)^2 \sigma^2 \int dt_1 R_f^2(t, t_1) \left(1 + (KJ)^2 \int dt_2 \int dt_3 R_f(t_1, t_2) R_f(t_1, t_3) \frac{C_{\text{cav}}(t_1, t_2)}{K} \right). \quad (\text{S38b})$$

In summary, at stationarity,

$$s^2 = \langle x^2 \rangle - \langle x \rangle^2 = \langle \phi^2 \rangle \quad (\text{S39a})$$

$$= \sigma^2 \int_0^\infty d\tau R_f^2(\tau) + (KJ)^2 \int_0^\infty d\tau R_f(\tau) \int_0^\infty ds R_f(s) \frac{C_{\text{cav}}(s, \tau)}{K} \\ + \sigma^2 (KJ)^2 \int_0^\infty d\tau \int_0^\infty ds \int_0^{\min(\tau, s)} d\theta R_f^2(\theta) R_f(\tau - \theta) R_f(s - \theta) \frac{C_{\text{cav}}(\tau - \theta)}{K} \\ + 2\sigma^2 (KJ)^2 \int_0^\infty d\tau R_f(\tau) \int_0^\tau ds R_f(\tau - s) \int_0^s d\theta R_f(\theta) \frac{R_{\text{cav}}(s - \theta)}{K}. \quad (\text{S39b})$$

Making the choice of response and correlation functions that corresponds to the adiabatic and independent approximation of [74], i.e setting $C_{\text{cav}}(s - \tau) \approx C(0) = s^2$ and $R_{\text{cav}}(s - \tau) \approx R(0) = 0$, we obtain

$$s^2 = \frac{\sigma^2}{2KJ} + \left(1 + \frac{\sigma^2}{2KJ}\right) \frac{s^2}{K}. \quad (\text{S40})$$

This formula leads to a wrong prediction of the critical point $\sigma_c^2 = 2KJ(K - 1)$. This is due to the fact we neglected relevant higher-order contributions in the loop expansion generated by the noise term. Performing the resummation of all terms of the geometric series expansion containing enchainned 1-loops diagrams only, the previous relation becomes

$$s^2 = \left(1 + \frac{\sigma^2}{2KJ} + \left(\frac{\sigma^2}{2KJ}\right)^2 + \dots\right) \left(1 + \frac{s^2}{K}\right) - 1 \quad (\text{S41a})$$

$$= \left(1 - \frac{\sigma^2}{2KJ}\right)^{-1} \left(1 + \frac{s^2}{K}\right) - 1, \quad (\text{S41b})$$

from which we get the same prediction $\sigma_c^2 = 2J(K - 1)$ already obtained in [74].