

# Measuring quantum relative entropy with finite-size effect

Masahito Hayashi<sup>1,2,3,\*</sup>

<sup>1</sup>*School of Data Science, The Chinese University of Hong Kong, Shenzhen, Longgang District, Shenzhen, 518172, China*

<sup>2</sup>*International Quantum Academy (SIQA), Futian District, Shenzhen 518048, China*

<sup>3</sup>*Graduate School of Mathematics, Nagoya University, Nagoya, 464-8602, Japan*

We study the estimation of relative entropy  $D(\rho\|\sigma)$  when  $\sigma$  is known. We show that the Cramér-Rao type bound equals the relative varentropy. Our estimator attains the Cramér-Rao type bound when the dimension  $d$  is fixed. It also achieves the sample complexity  $O(d^2)$  when the dimension  $d$  increases. This sample complexity is optimal when  $\sigma$  is the complexity mixed state. Also, it has time complexity  $O(d^5 \text{ polylog } d)$ . Our proposed estimator unifiedly works under both settings.

## I. INTRODUCTION

Distinguishing a given known state  $\sigma$  from another state  $\rho$  is a fundamental task in quantum information. When the state  $\rho$  is known as well as  $\sigma$  and  $n$  copies of the unknown state are prepared, quantum Stein's lemma [1, 2] guarantees that the quantum relative entropy  $D(\rho\|\sigma) := \text{Tr}\rho(\log \rho - \log \sigma)$  gives the limitation of the optimal discrimination power. The measurement achieving the optimal performance depends only on the state  $\sigma$  [3]. Further, quantum Sanov theorem [4, 5] shows that the construction of the test achieving the optimal performance depends only on the state  $\sigma$  and the value of the quantum relative entropy  $D(\rho\|\sigma)$ . That is, when we construct the test achieving the optimal performance, the information of the quantum relative entropy  $D(\rho\|\sigma)$  is needed in addition to the information of  $\sigma$ . Although the papers [6, 7] studied the estimation of von Neumann entropy and Rényi entropy, they did not study the estimation of the quantum relative entropy  $D(\rho\|\sigma)$  with the known state  $\sigma$ . Due to the non-commutativity between  $\rho$  and  $\sigma$ , the method in [6, 7] cannot be applied to the estimation of the quantum relative entropy  $D(\rho\|\sigma)$  even when the state  $\sigma$  is known. In particular, the simple use of Schur sampling [8–13] does not work for the estimation of the quantum relative entropy  $D(\rho\|\sigma)$  although the paper [6] employs Schur sampling. Therefore, this paper studies how to estimate the quantum relative entropy  $D(\rho\|\sigma)$  with  $n$  copies of the unknown state  $\rho$  when  $\sigma$  is known.

The estimation of  $D(\rho\|\sigma)$  with the unknown state  $\rho$  is formulated as a special case of the estimation of a function output with nuisance parameter, which was formulated in [14, Section 4.3]. In this formulation, the optimal performance of the estimation precision is given by the Cramér-Rao type bound with nuisance parameters, which equals the inverse of the projected symmetric logarithmic derivative (SLD) Fisher information in the one-parameter case. As the first step, using the results for estimation with nuisance parameters, we show that the

Cramér-Rao type bound of this problem equals the relative varentropy  $V(\rho\|\sigma) := \text{Tr}\rho((\log \rho - \log \sigma) - D(\rho\|\sigma))^2$ , which appears in the second-order theory of hypothesis testing. The meaning of the Cramér-Rao type bound is the following; when  $n$  copies of the unknown state  $\rho$  is prepared, the mean square of our best estimator behaves as  $\frac{V(\rho\|\sigma)}{n} + o(\frac{1}{n})$ . Under special models, the recent paper [15] showed the existence of an estimator whose  $n$  times the mean square error equals the Cramér-Rao type bound without nuisance parameter. However, such an estimator does not exist in general.

In practice, it is necessary to find an estimator to achieve the above performance. In addition, it is also desired to clearly evaluate the difference between its mean square error and the Cramér-Rao type bound. Since our problem is one-parameter estimation, it is possible to achieve the above bound without the use of collective measurements across several quantum systems. However, this method requires an adaptive choice of measurement. One typical method for this approach is a two-step estimator, which is composed of the pre-estimation stage and the local optimal estimation. When we have  $n$  copies of the unknown state  $\rho$ , theoretically, in order to achieve the optimal bound, it is sufficient to allocate  $\sqrt{n}$  copies to the pre-estimation stage [16, 17]. Although this method achieves the optimal mean square error in the order  $\frac{1}{n}$ , i.e., the first order, it is not so clear how the mean square error is close to the leading term  $\frac{V(\rho\|\sigma)}{n}$ . From the practical viewpoint, it is needed to upper bound this difference by using the number  $n$  of unknown copies. Unfortunately, the above method has difficulty to evaluate the difference between its mean square error and  $\frac{V(\rho\|\sigma)}{n}$ . The papers [18, 19] also proposed different adaptive methods for the parameter estimation, but their methods have the same problem. In addition, the above adaptive approach does not work when the dimension  $d$  of the quantum system increases in addition to the number  $n$  of copies.

In summary, considering the finite size effect of our estimation, we need to find an estimator of the quantum relative entropy  $D(\rho\|\sigma)$  to satisfy the following conditions. It asymptotically attains the Cramér-Rao type bound  $V(\rho\|\sigma)$  in the sense of the order  $\frac{1}{n}$  when the dimension  $d$  is fixed. The difference between its mean square error and the Cramér-Rao type bound is evalu-

---

\* [hmasahito@cuhk.edu.cn](mailto:hmasahito@cuhk.edu.cn)

ated with the number  $n$  of copies. Further, the estimator works well even when the dimension  $d$  of the quantum system increases in addition to the number  $n$  of the prepared copies.

As the second step, to satisfy the above requirements, we propose an alternative estimation method by using Schur transform [20]. Then, we evaluate its mean square error and clarify its difference from the Cramér-Rao type bound with a finite number  $n$ . In addition, we evaluate the tail probability.

As the third step, similar to the papers [6, 7], we study the case when the dimension  $d$  increases when  $n$  increases. Unlike the estimation of von Neumann entropy, the range of the quantum relative entropy nor the relative varentropy is not bounded even with fixed dimension  $d$ . Therefore, to study the sample complexity, we need to restrict the possible range of  $\rho$  and  $\sigma$ . We show that the sample complexity of our method is  $O(d^2)$  under a certain natural restriction for this range. In particular, the restriction of the possible range of  $\sigma$  is crucial in this analysis. We also show that our time complexity is  $O(d^5 \text{polylog } d)$ .

When  $\sigma$  is fixed to the completely mixed state, our problem is the same as the estimation of von Neumann entropy, which was studied in the papers [6, 7]. Our result contains the case studied in the papers [6, 7]. In this special case, the paper [6] also showed that the lower bound of the sample complexity is  $O(d^2)$  when our measurement is limited to Schur sampling. The paper [7] also showed that the lower bound of the sample complexity is  $O(d)$  without this restriction. In this special case, we show that our measurement can be restricted to Schur sampling so that the lower bound by [6] holds even without this restriction.

The remaining part of this paper is organized as follows. First, Section II derives the Cramér-Rao type bound for the estimation of quantum relative entropy. Section III presents our estimator for quantum relative entropy, and its performance. Then, this section shows that this estimator asymptotically attains the Cramér-Rao type bound when  $d$  is fixed. Section IV studies the sample complexity of our method when  $d$  increases. Section V studies the time complexity of our method when  $d$  increases. Section VI shows the optimality of the use of Schur sampling when  $\sigma$  is fixed to the completely mixed state. Appendices are devoted to the proofs of the results presented in Section III.

## II. CRAMÉR-RAO TYPE BOUND

To clarify the minimum mean square error with the first order  $\frac{1}{n}$ , we calculate the Cramér-Rao type bound with nuisance parameters of  $D(\rho\|\sigma)$  at  $\rho = \rho_*$ . For this aim, we review the Cramér-Rao type bound for a general function  $f(\rho)$  in the full parameter model under a  $d$ -dimensional system as follows. We choose a parametrization  $\rho_\theta$  with  $\theta = (\theta^1, \theta^2, \dots, \theta^{d^2-1}) \in \mathbb{R}^{d^2-1}$  such that the

first parameter gives the value of the function to be estimated and the other parameters are orthogonal to the first parameter at  $\rho = \rho_*$ . That is, our parameter needs to satisfy the following conditions.

$$\rho_{\theta_0} = \rho_*, \quad (1)$$

$$\left. \frac{\partial f(\rho_\theta)}{\partial \theta^1} \right|_{\theta=\theta_0} = 1, \quad (2)$$

$$\left. \frac{\partial f(\rho_\theta)}{\partial \theta^j} \right|_{\theta=\theta_0} = 0 \quad (3)$$

for  $j = 2, \dots, d^2 - 1$ , where  $\theta_0 := (\theta_0^1, 0, \dots, 0)$ , and  $\theta_0^1 := f(\rho_*)$ .

For the latter discussion, we introduce the symmetric logarithmic derivative (SLD) inner product. Given two Hermitian matrices  $X, Y$ , we define  $X \circ Y := (XY + YX)/2$ . Then, we define the SLD inner product  $\langle X, Y \rangle_\rho := \text{Tr}(\rho \circ X)Y = \text{Tr}\rho(X \circ Y)$ . We define the SLD norm  $\|X\|_\rho := \sqrt{\langle X, X \rangle_\rho}$ . We choose the SLD  $L_1, \dots, L_{d^2-1}$  as

$$\left. \frac{\partial \rho_\theta}{\partial \theta^j} \right|_{\theta=\theta_0} = \rho_* \circ L_j \quad (4)$$

for  $j = 1, \dots, d^2 - 1$ . We also assume the following orthogonal condition;

$$\langle L_1, L_j \rangle_{\rho_*} = \text{Tr} \frac{\partial \rho_\theta}{\partial \theta^j} \Big|_{\theta=\theta_0} L_1 = 0 \quad (5)$$

for  $j = 2, \dots, d^2 - 1$ . Then, we can calculate the Cramér-Rao type bound, i.e., the minimum mean square error under the local unbiasedness condition even under the full parameter model.

**Proposition 1** ([14, Theorem 5.3]). *Assume the conditions (1)–(5). The Cramér-Rao type bound for the estimation of  $f(\rho_\theta)$  is  $\langle L_1, L_1 \rangle_{\rho_*}^{-1}$  at  $\theta = \theta_0$ .*

To calculate the Cramér-Rao type bound for  $D(\rho\|\sigma)$  at  $\rho = \rho_*$ , we choose the Hermitian matrix

$$L^1 := ((\log \rho_* - \log \sigma) - D(\rho_*\|\sigma)I), \quad (6)$$

and  $d^2 - 1$  linearly independent Hermitian traceless matrices  $X_1, X_2, \dots, X_{d^2-1}$  such that

$$X_1 = V(\rho_*\|\sigma)^{-1} \rho_* \circ L^1 \quad (7)$$

$$\text{Tr} X_j L^1 = 0 \quad (8)$$

for  $j = 2, \dots, d^2 - 1$ . Then, we choose our parametrization  $\rho_\theta$  as

$$\rho_\theta := \rho_* + (\theta^1 - \theta_0^1)X_1 + \sum_{j=2}^{d^2-1} \theta^j X_j. \quad (9)$$

This parameterization satisfies the condition (1). Since  $\frac{\partial \rho_\theta}{\partial \theta^j} \Big|_{\theta=\theta_0} = X_j$ , we have

$$\begin{aligned} & \frac{\partial D(\rho_\theta \| \sigma)}{\partial \theta^1} \Big|_{\theta=\theta_0} \\ &= \text{Tr} \frac{\partial \rho_\theta}{\partial \theta^1} \Big|_{\theta=\theta_0} (\log \rho_* - \log \sigma) + \text{Tr} \rho_* \frac{\partial \log \rho_\theta}{\partial \theta^1} \Big|_{\theta=\theta_0} \\ &\stackrel{(a)}{=} \text{Tr} X_1 (\log \rho_* - \log \sigma) + \text{Tr} X_1 \\ &\stackrel{(b)}{=} \text{Tr} X_1 L^1 + \text{Tr} X_1 D(\rho_* \| \sigma) I + \text{Tr} X_1 \stackrel{(c)}{=} 1. \end{aligned} \quad (10)$$

Here, (b) and (c) follows from (6) and (7) and the relation  $\langle L^1, L^1 \rangle_{\rho_*} = V(\rho_* \| \sigma)$ , respectively. In addition, (a) can be shown as follows.

$$\begin{aligned} & \text{Tr} \rho_{\theta_0} \frac{\partial \log \rho_\theta}{\partial \theta^1} \Big|_{\theta=\theta_0} \stackrel{(a)}{=} \text{Tr} \int_0^1 \rho_{\theta_0}^s \frac{\partial \log \rho_\theta}{\partial \theta^1} \Big|_{\theta=\theta_0} \rho_{\theta_0}^{1-s} ds \\ &= \text{Tr} \frac{\partial \rho_\theta}{\partial \theta^1} \Big|_{\theta=\theta_0} = \text{Tr} X_1, \end{aligned} \quad (11)$$

where (a) follows from [21, Eq. (6.32)].

Using (8) and a similar discussion, we have

$$\frac{\partial D(\rho_\theta \| \sigma)}{\partial \theta^j} \Big|_{\theta=\theta_0} = \text{Tr} X_j (\log \rho_* - \log \sigma) + \text{Tr} X_j = 0. \quad (12)$$

Then, (11) and (12) imply the conditions (2) and (3).

Due to (7) and (8), we have  $L_1 = V(\rho_* \| \sigma)^{-1} L^1$  and

$$\text{Tr} \frac{\partial \rho_\theta}{\partial \theta^j} L_1 = \text{Tr} X_j L_1 = 0 \text{ for } j = 2, \dots, d^2 - 1, \quad (13)$$

which implies the condition (5). Therefore, since all the conditions (1) – (5) hold, due to Proposition 1, the Cramér-Rao type bound for the estimation of  $D(\rho \| \sigma)$  is  $\langle L_1, L_1 \rangle_{\rho_*}^{-1} = V(\rho_* \| \sigma)^{-1}$  at  $\theta = \theta_0$ . That is, the minimum mean square error under the local unbiasedness condition is  $V(\rho_* \| \sigma)$ . That is, the Cramér-Rao type bound for the estimation of  $D(\rho \| \sigma)$  is the relative varentropy  $V(\rho_* \| \sigma)$ .

### III. ESTIMATOR BASED ON SCHUR TRANSFORM

Similar to the papers [3, 4, 8–13, 22–24], we employ Schur duality of  $\mathcal{H}^{\otimes n}$ . For this aim, we prepare several notations. A sequence of monotone-increasing non-negative integers  $\lambda = (\lambda_1, \dots, \lambda_d)$  is called Young index. Although many references [24–26] define Young index as monotone-decreasing non-negative integers, we define it in the opposite way for notational convenience. We denote the set of Young indices  $\lambda$  with condition  $\sum_{j=1}^d \lambda_j = n$  by  $Y_d^n$ . Then, as explained in [24, Section 6.2], we have

$$\mathcal{H}^{\otimes n} = \bigoplus_{\lambda \in Y_d^n} \mathcal{U}_\lambda \otimes \mathcal{V}_\lambda. \quad (14)$$

Here,  $\mathcal{U}_\lambda$  expresses the irreducible space of  $\text{SU}(d)$  and  $\mathcal{V}_\lambda$  expresses the irreducible space of the representation  $\pi$  of the permutation group  $\mathfrak{S}_n$ . We define  $d_\lambda := \dim \mathcal{U}_\lambda$ ,  $d'_\lambda := \dim \mathcal{V}_\lambda$ . Then, for states  $\sigma, \rho$ , we have

$$\rho^{\otimes n} = \bigoplus_{\lambda \in Y_d^n} \rho_\lambda \otimes \rho_{\lambda, \text{mix}}, \quad (15)$$

$$\sigma^{\otimes n} = \bigoplus_{\lambda \in Y_d^n} \sigma_\lambda \otimes \rho_{\lambda, \text{mix}}, \quad (16)$$

where  $\rho_{\lambda, \text{mix}}$  is the completely mixed state on  $\mathcal{V}_\lambda$ . We choose a basis  $\{|u_{\lambda, j}\rangle\}_{j=1}^{d'_\lambda}$  of  $\mathcal{U}_\lambda$  such that  $|u_{\lambda, j}\rangle$  is an eigenvector of  $\sigma_\lambda$ .

To estimate the quantum relative entropy  $D(\rho \| \sigma)$ , we employ the POVM  $M = \{M_{\lambda, j}\}_{\lambda, j}$  defined as

$$M_{\lambda, j} := |u_{\lambda, j}\rangle \langle u_{\lambda, j}| \otimes I(\mathcal{V}_\lambda), \quad (17)$$

where  $I(\mathcal{V}_\lambda)$  is the identity operator on  $\mathcal{V}_\lambda$ . The measurement outcome is given as  $(\lambda, j)$  so that it obeys the probability distribution

$$P_{\rho, \sigma}^{(n)}(\lambda, j) := \text{Tr} M_{\lambda, j} \rho^{\otimes n}. \quad (18)$$

To estimate the quantum relative entropy  $D(\rho \| \sigma)$ , we employ the estimate  $x_{\lambda, j}$  defined as  $-\frac{1}{n} \log \text{Tr} M_{\lambda, j} \sigma^{\otimes n}$ . This measurement can be done by Schur transform efficiently [20].

To evaluate the mean square error of this estimator, we denote the dimension of  $\bigoplus_{\lambda \in Y_d^n} \mathcal{U}_\lambda$  by  $d_n$ . Since as shown in [24, (6.16) and (6.18)], we have

$$\dim \mathcal{U}_\lambda \leq (n+1)^{d(d-1)/2}, \quad |Y_d^n| \leq (n+1)^{d-1}, \quad (19)$$

the relation

$$d_n \leq (n+1)^{(d+2)(d-1)/2} \quad (20)$$

holds. The mean square error of this estimator is evaluated as follows.

**Theorem 2.** *For any states  $\rho$  and  $\sigma$ , we have*

$$\begin{aligned} \text{MSE}_n(\rho \| \sigma) &:= \sum_{(\lambda, j)} P_{\rho, \sigma}^{(n)}(\lambda, j) (x_{\lambda, j} - D(\rho \| \sigma))^2 \\ &\leq \left( \frac{1}{\sqrt{n}} \sqrt{V(\rho \| \sigma)} + \frac{1}{n} \log d_n \right)^2. \end{aligned} \quad (21)$$

This theorem is proved in Appendix A. The difference between the upper bound (21) and the leading term  $\frac{1}{n} V(\rho \| \sigma)$  is  $\frac{1}{n^2} \log d_n + \frac{2}{n\sqrt{n}} \sqrt{V(\rho \| \sigma)} \log d_n$ . Using (20), this different is upper bounded by  $\frac{1}{n^2} \left( \frac{(d+2)(d-1)}{2} \log(n+1) \right)^2 + \frac{2}{n\sqrt{n}} \sqrt{V(\rho \| \sigma)} \frac{(d+2)(d-1)}{2} \log(n+1)$ .  $n$  times of these terms go to zero.

Next, we focus on the tail probability for our estimator, i.e., we study the estimation error probability as

$$\delta_{\rho, \sigma}^{(n), +, \epsilon} := P_{\rho, \sigma}^{(n)} \{(\lambda, j) : x_{\lambda, j} - D(\rho \| \sigma) > \epsilon\} \quad (22)$$

$$\delta_{\rho, \sigma}^{(n), -, \epsilon} := P_{\rho, \sigma}^{(n)} \{(\lambda, j) : x_{\lambda, j} - D(\rho \| \sigma) < -\epsilon\}. \quad (23)$$

When  $\epsilon$  behaves as  $c/\sqrt{n}$ , as shown in Appendix B the probabilities  $\delta_{\rho,\sigma}^{(n),\pm,c/\sqrt{n}}$  converges to a normal distribution as follows.

**Theorem 3.** For any states  $\rho$  and  $\sigma$ , we have

$$\delta_{\rho,\sigma}^{(n),+,c/\sqrt{n}} \rightarrow \int_{c/\sqrt{V(\rho\|\sigma)}}^{\infty} \frac{1}{\sqrt{2\pi}} e^{-\frac{x^2}{2}} dx \quad (24)$$

$$\delta_{\rho,\sigma}^{(n),-,c/\sqrt{n}} \rightarrow \int_{-\infty}^{c/\sqrt{V(\rho\|\sigma)}} \frac{1}{\sqrt{2\pi}} e^{-\frac{x^2}{2}} dx. \quad (25)$$

This property is called local asymptotic normality.

When the error term  $\epsilon$  is constant, the tail probability goes to zero exponentially. We use the sandwich relative entropy  $D_\alpha(\sigma\|\rho) := \frac{1}{\alpha-1} \log \text{Tr}(\rho^{\frac{1-\alpha}{2\alpha}} \sigma \rho^{\frac{1-\alpha}{2\alpha}})^\alpha$ . As shown in Appendix C, using the method in Section X of [23], we have the following theorem.

**Theorem 4.** For any states  $\rho$ ,  $\sigma$ , and  $R, r > 0$ , we have

$$\delta_{\rho,\sigma}^{(n),+,R-D(\rho\|\sigma)} \leq d_n^\alpha e^{-n\alpha(D_{1-\alpha}(\rho\|\sigma) - R)}, \quad (26)$$

$$\delta_{\rho,\sigma}^{(n),-,R-D(\rho\|\sigma)} \leq e^{-n(R-r-\alpha(D_{1+\alpha}(\rho\|\sigma)))} + d_n e^{-nr}. \quad (27)$$

In (26),  $\alpha \in (0, 1)$ , and in (27),  $\alpha > 0$ .

Theorem 4 guarantees that  $\delta_{\rho,\sigma}^{(n),+,\epsilon}$  and  $\delta_{\rho,\sigma}^{(n),-,\epsilon}$  go to zero exponentially. This property is called the large deviation.

#### IV. ANALYSIS WITH INCREASING $d$

Similar to [6, 7], we consider the case when the dimension  $d$  increases. When  $n = O(d^{4+\delta})$ ,  $\frac{1}{\sqrt{n}} \log d_n \leq \frac{1}{\sqrt{n}} \frac{(d+1)(d-1)}{2} \log(n+1) \rightarrow 0$ . In this case, due to Theorem 2, the Cramér-Rao type bound can be attained because the second term of RHS in (21) goes to zero.

Now, we consider when the error goes to zero under the condition  $d \rightarrow \infty$ . We denote the  $d$ -dimensional system by  $\mathcal{H}_d$ . To discuss this case, we consider the sequence of states  $\sigma_d$  depending on the dimension  $d$ . We also choose a subset  $\mathcal{S}_d$  of the set  $\mathcal{S}(\mathcal{H}_d)$  of states on  $\mathcal{H}_d$ . We assume the following condition for  $\sigma_d$  and  $\mathcal{S}_d$ ;

$$c_0 := \lim_{d \rightarrow \infty} \frac{1}{d^2} \max_{\rho \in \mathcal{S}_d} V(\rho\|\sigma_d) < \infty. \quad (28)$$

For example, the condition (28) holds under certain conditions.

**Lemma 5.** When the minimum eigenvalue of  $\sigma_d$  is lower bounded by  $e^{-td}$  with a fixed real number  $t > 0$ , the condition (28) holds even when  $\mathcal{S}_d$  equals  $\mathcal{S}(\mathcal{H}_d)$ .

*Proof.* Considering the definition of  $V(\rho\|\sigma_d)$  and the norm  $\|\cdot\|_\rho$ , we have

$$\begin{aligned} & \sqrt{V(\rho\|\sigma_d)} \\ &= \|\log \rho - (\text{Tr} \rho \log \rho) - \log \sigma_d + (\text{Tr} \rho \log \sigma_d)\|_\rho \\ &\leq \|\log \rho - (\text{Tr} \rho \log \rho)\|_\rho + \|\log \sigma_d - (\text{Tr} \rho \log \sigma_d)\|_\rho. \end{aligned} \quad (29)$$

Using the property of the norm  $\|\cdot\|_\rho$ , we have

$$\begin{aligned} & \|\log \rho - (\text{Tr} \rho \log \rho)\|_\rho^2 = \text{Tr} \rho (\log \rho - (\text{Tr} \rho \log \rho))^2 \\ &= (\text{Tr} \rho (\log \rho)^2) - (\text{Tr} \rho \log \rho)^2 \leq (\text{Tr} \rho (\log \rho)^2) \stackrel{(a)}{\leq} (\log d)^2, \end{aligned} \quad (30)$$

where (a) follows from [3, Lemma 8]. Similarly, we have

$$\begin{aligned} & \|\log \sigma_d - (\text{Tr} \rho \log \sigma_d)\|_\rho^2 = \text{Tr} \rho (\log \sigma_d - (\text{Tr} \rho \log \sigma_d))^2 \\ &= (\text{Tr} \rho (\log \sigma_d)^2) - (\text{Tr} \rho \log \sigma_d)^2 \leq (\text{Tr} \rho (\log \sigma_d)^2) \leq (td)^2. \end{aligned} \quad (31)$$

Combining (29), (30), and (31), we obtain the condition (28).  $\square$

**Theorem 6.** When the condition (28) holds and  $n = cd^2$ , we have

$$\begin{aligned} \lim_{d \rightarrow \infty} \max_{\rho \in \mathcal{S}_d} \delta_{\rho,\sigma}^{(n),+,\epsilon} + \delta_{\rho,\sigma}^{(n),-,\epsilon} &\leq \frac{1}{\epsilon^2} \left( \frac{\sqrt{c_0}}{\sqrt{c}} + \min_{0 < s < 1} \frac{c^{s-1}}{s(1-s)} \right)^2 \\ &\leq \frac{(\sqrt{c_0} + 4)^2}{c\epsilon^2}. \end{aligned} \quad (32)$$

When we choose  $c$  to be  $\frac{(\sqrt{c_0} + 4)^2}{\epsilon'\epsilon^2}$  for any  $\epsilon, \epsilon' > 0$ , we have

$$\lim_{d \rightarrow \infty} \max_{\rho \in \mathcal{S}_d} \delta_{\rho,\sigma}^{(n),+,\epsilon} + \delta_{\rho,\sigma}^{(n),-,\epsilon} \leq \epsilon'. \quad (33)$$

Hence, we obtain an upper bound  $O(d^2)$  of the sample complexity for the estimation of  $D(\rho\|\sigma_d)$  when  $\rho$  belongs to  $\mathcal{S}_d$ .

*Proof.* We choose  $s \in (0, 1)$ . Using Weyl's dimension formula [25, Theorem 7.1.7], we have

$$\begin{aligned} \log \dim \mathcal{U}_\lambda &= \log \prod_{1 \leq i < j \leq d} \frac{j - i + \lambda_j - \lambda_i}{j - i} \\ &= \sum_{1 \leq i < j \leq d} \log \left( 1 + \frac{\lambda_j - \lambda_i}{j - i} \right) = \sum_{l=1}^d \sum_{i=1}^{d-l} \log \left( 1 + \frac{\lambda_{l+i} - \lambda_i}{l} \right) \\ &= \sum_{l=1}^d (d-l) \sum_{i=1}^{d-l} \frac{1}{d-l} \log \left( 1 + \frac{\lambda_{l+i} - \lambda_i}{l} \right) \\ &\stackrel{(a)}{\leq} \sum_{l=1}^d (d-l) \log \left( 1 + \sum_{i=1}^{d-l} \frac{1}{d-l} \frac{\lambda_{l+i} - \lambda_i}{l} \right) \\ &\leq \sum_{l=1}^d (d-l) \log \left( 1 + \frac{n}{(d-l)l} \right) \\ &\stackrel{(b)}{\leq} \sum_{l=1}^d \frac{(d-l)}{s} \left( \frac{n}{(d-l)l} \right)^s = \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{s l^s}, \end{aligned} \quad (34)$$

where (a) follows from Jensen inequality for the concave function  $x \mapsto \log(1+x)$  and the uniform distribution over

$\{1, \dots, d-l\}$ . (b) can be shown as follows.

$$\begin{aligned} \log\left(1 + \frac{n}{(d-l)l}\right) &= \frac{1}{s} \log\left(1 + \frac{n}{(d-l)l}\right)^s \\ &\stackrel{(c)}{\leq} \frac{1}{s} \log\left(1 + \left(\frac{n}{(d-l)l}\right)^s\right) \stackrel{(d)}{\leq} \frac{1}{s} \left(\frac{n}{(d-l)l}\right)^s, \end{aligned} \quad (35)$$

where (c) follows from the inequality  $(x+y)^s \leq x^s + y^s$  for  $x, y \geq 0$ , and (d) follows from the inequality  $\log(1+x) \leq x$ . Thus, we have

$$\begin{aligned} \log d_n &\leq \log |Y_d^n| \max_{\lambda} \dim \mathcal{U}_{\lambda} \\ &\leq \log |Y_d^n| + \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{sl^s} \\ &\leq (d-1) \log(n+1) + \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{sl^s}. \end{aligned} \quad (36)$$

When  $n = cd^2$ , we have

$$\begin{aligned} \frac{1}{d^2} \log \dim \mathcal{U}_{\lambda} &\leq \frac{1}{d^2} \sum_{l=1}^d \frac{(d-l)^{1-s} c^s d^{2s}}{sl^s} \\ &\rightarrow \int_0^1 \frac{(1-x)^{1-s} c^s}{sx^s} dx \\ &\leq \int_0^1 \frac{c^s}{sx^s} dx = \left[ \frac{c^s}{s(1-s)} x^{1-s} \right]_0^1 = \frac{c^s}{s(1-s)}. \end{aligned} \quad (37)$$

Since the term  $\frac{1}{n}(d-1) \log(n+1)$  goes to zero, the term  $\frac{1}{n} \log d_n$  is evaluated as

$$\lim_{n \rightarrow \infty} \frac{1}{n} \log d_n \leq \min_{0 < s < 1} \frac{c^{s-1}}{s(1-s)}. \quad (38)$$

The definition of  $c_0$  implies

$$\lim_{n \rightarrow \infty} \frac{1}{\sqrt{n}} \sqrt{V(\rho \parallel \sigma)} = \frac{\sqrt{c_0}}{\sqrt{c}}. \quad (39)$$

Thus, we have

$$\begin{aligned} &\lim_{n \rightarrow \infty} \text{MSE}_n(\rho \parallel \sigma_d) \\ &\stackrel{(e)}{\leq} \left( \frac{\sqrt{c_0}}{\sqrt{c}} + \min_{0 < s < 1} \frac{c^{s-1}}{s(1-s)} \right)^2 \stackrel{(f)}{\leq} \frac{(\sqrt{c_0} + 4)^2}{c}, \end{aligned} \quad (40)$$

where (e) follows from the combination of (38), (39), and Theorem 2, (f) follows by choosing  $s = 1/2$ . Finally, applying Chebyshev's inequality, we obtain the desired inequalities.  $\square$

The key point of this proof is the derivation (34). In particular, the derivation (35) is the heart in this part. The idea of this derivation comes from the proof of (12) given in Appendix IV of the paper [27], which gives the security analysis in information theoretic security.

## V. ANALYSIS ON TIME COMPLEXITY

To implement our estimator, we need to apply suitable unitary gates before the measurement based on the computation basis. For simplicity, we consider the case when  $\sigma$  is a diagonal matrix. For a general density  $\sigma$ , we need to apply a unitary diagonalizing the density  $\sigma$  to each system  $\mathcal{H}$  before the following procedure.

First, we apply the Schur transform. The references [20, 28, 29] proposed its quantum algorithm. We evaluate its prevision as follows. Given a required error  $\epsilon > 0$  and a target unitary  $V$ , we say that a unitary  $U$  is an  $\epsilon$ -approximate of  $V$  when any pure state  $|\psi\rangle$  satisfies

$$\|(U - V)|\psi\rangle\| \leq \epsilon. \quad (41)$$

When the constructed unitary is an  $\epsilon$ -approximate of the Schur transform, the time complexity of the construction [20, 29] is  $O(nd^3 \text{polylog}(n, d, 1/\epsilon))$ . Since these constructions realize the approximation (41), the estimation error probability increases at most only  $\epsilon^2$ . We denote the distribution of  $(\lambda, j)$  when we employ an  $\epsilon$ -approximate of the Schur transform by  $P_{\rho, \sigma}^{(n), \epsilon}$ .

In the classical part of our estimator, we need to calculate  $x_{\lambda, j} = -\frac{1}{n} \log \text{Tr} M_{\lambda, j} \sigma^{\otimes n}$ . When  $\sigma$  has diagonal elements  $s_1, \dots, s_d$ , the eigenvalue of  $\sigma^{\otimes n}$  on the projection  $M_{\lambda, j}$  has the form  $\prod_{j=1}^d s_j^{n_j}$ , where  $\sum_{j=1}^d n_j = n$ . Then, we have

$$\text{Tr} M_{\lambda, j} \sigma^{\otimes n} = \dim \mathcal{V}_{\lambda} \prod_{j=1}^d s_j^{n_j}. \quad (42)$$

For a Young index  $\lambda$ , the dimension  $\mathcal{V}_{\lambda}$  is evaluated as

$$\dim \mathcal{V}_{\lambda} = \frac{n!}{\lambda!} e(\lambda) \quad (43)$$

$$e(\lambda) := \prod_{j>i} \frac{\lambda_j - \lambda_i - i + j}{\lambda_j + j - i} < 1, \quad (44)$$

where  $\lambda! := \lambda_1! \lambda_2! \cdots \lambda_d!$ . For its detail, see [26, Eq. (2.72)]. Using [21, Theorem 2.5], we have

$$e^{nH(\frac{\lambda}{n})} (n+1)^{-(d-1)} \leq \frac{n!}{\lambda!} \leq e^{nH(\frac{\lambda}{n})}. \quad (45)$$

The value  $e(\boldsymbol{\lambda})$  is evaluated as

$$\begin{aligned}
-\log e(\boldsymbol{\lambda}) &= \sum_{j>i} \log \frac{\lambda_j + j - i}{\lambda_j - \lambda_i - i + j} \\
&= \sum_{j>i} \log \left( 1 + \frac{\lambda_i}{\lambda_j - \lambda_i + j - i} \right) \leq \sum_{j>i} \log \left( 1 + \frac{\lambda_i}{j - i} \right) \\
&= \sum_{l=1}^d (d-l) \sum_{i=1}^{d-l} \frac{1}{d-l} \log \left( 1 + \frac{\lambda_i}{l} \right) \\
&\stackrel{(a)}{\leq} \sum_{l=1}^d (d-l) \log \left( 1 + \sum_{i=1}^{d-l} \frac{1}{d-l} \frac{\lambda_i}{l} \right) \\
&\leq \sum_{l=1}^d (d-l) \log \left( 1 + \frac{n}{(d-l)l} \right) \stackrel{(b)}{\leq} \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{sl^s},
\end{aligned} \tag{46}$$

where (a) follows from Jensen inequality for the concave function  $x \mapsto \log(1+x)$ , and (b) follows from (35) in the same way as (34).

Instead of  $x_{\boldsymbol{\lambda},j}$ , we use its approximation  $x_{\boldsymbol{\lambda},j}^* := H(\frac{\Delta}{n}) - \sum_{j=1}^d \frac{n_j}{n} \log s_j$ , whose time complexity is  $O(n)$ . Then, we have

$$\begin{aligned}
0 \leq x_{\boldsymbol{\lambda},j}^* - x_{\boldsymbol{\lambda},j} &\leq \frac{1}{n} (d \log(n+1) - \log e(\boldsymbol{\lambda})) \\
&\leq \frac{1}{n} \left( d \log(n+1) - \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{sl^s} \right).
\end{aligned} \tag{47}$$

When  $n = cd^2$ ,  $\lim_{n \rightarrow \infty} \frac{1}{n} (d \log(n+1) - \sum_{l=1}^d \frac{(d-l)^{1-s} n^s}{sl^s}) \leq \frac{4}{\sqrt{c}}$ .

Given an arbitrary number  $\epsilon > 0$ , we choose  $c = \frac{16}{\epsilon}$ . When  $n = cd^2$ , the limit of the upper bound in (47) can be bounded by  $\epsilon$ . Then, we define

$$\delta_{\rho,\sigma}^{(n),+, \epsilon, \epsilon_1} := P_{\rho,\sigma}^{(n), \epsilon_1} \{(\boldsymbol{\lambda}, j) : x_{\boldsymbol{\lambda},j}^* - D(\rho \parallel \sigma) > \epsilon\} \tag{48}$$

$$\delta_{\rho,\sigma}^{(n),-, \epsilon, \epsilon_1} := P_{\rho,\sigma}^{(n), \epsilon_1} \{(\boldsymbol{\lambda}, j) : x_{\boldsymbol{\lambda},j}^* - D(\rho \parallel \sigma) < -\epsilon\}. \tag{49}$$

Thus, when  $n = cd^2$ , using (33), we have

$$\lim_{d \rightarrow \infty} \max_{\rho \in \mathcal{S}_d} \delta_{\rho,\sigma}^{(n),+, \epsilon, \epsilon_1} + \delta_{\rho,\sigma}^{(n),-, \epsilon, \epsilon_1} \leq \frac{(\sqrt{c_0} + 4)^2}{c(\epsilon - \frac{4}{\sqrt{c}})^2} + \epsilon_1^2. \tag{50}$$

Hence, when we choose  $\epsilon_1 = \sqrt{\epsilon'/2}$  and  $c = \min(\frac{64}{\epsilon^2}, \frac{8(4+\sqrt{c_0})^2}{\epsilon^2 \epsilon'})$  for any  $\epsilon, \epsilon' > 0$ , we have

$$\lim_{d \rightarrow \infty} \max_{\rho \in \mathcal{S}_d} \delta_{\rho,\sigma}^{(n),+, \epsilon, \epsilon_1} + \delta_{\rho,\sigma}^{(n),-, \epsilon, \epsilon_1} \leq \epsilon'. \tag{51}$$

Overall, when  $n = O(d^2)$ , we use the construction of Schur transform by [20, 29] with the time complexity  $O(d^5 \text{polylog}(d))$  and the estimate  $x_{\boldsymbol{\lambda},j}$  with the time complexity  $O(n) = O(d^2)$ . That is, the construction has a total time complexity  $O(d^5 \text{polylog}(d))$ .

## VI. OPTIMALITY OF USE OF SCHUR SAMPLING

The paper [6] studied the case when  $\sigma_d$  is the completely mixed state  $\rho_{\text{mix}}$ . In this case, the paper [6] showed that the lower bound of sample complexity is  $O(d^2)$  when  $d$  is increasing, Schur sampling is employed. In this case, the estimate  $x_{\boldsymbol{\lambda},j}$  of our estimator depends only on  $\boldsymbol{\lambda}$ . So,  $x_{\boldsymbol{\lambda},j}$  is given as a function of the measurement outcome of Schur sampling.

In the following, we show that the optimal estimator can be given with the use of Schur sampling when  $\sigma_d$  is the completely mixed state  $\rho_{\text{mix}}$ . That is, for any estimator POVM  $M$ , there exists an estimator POVM  $M'$  based on Schur sampling such that the performance of  $M'$  is not worse than the performance of  $M$ . For its precise statement, we introduce the following minimax criterion. When the true state is  $\rho$  and the estimator POVM is  $M$ , we denote the distribution of the estimate  $\hat{x}$  of the value  $D(\rho \parallel \rho_{\text{mix}})$  by  $P_{\rho;M}$ . We focus on the following quantities

$$R(\rho, M, \epsilon) := \max_{g \in \text{SU}(d)} P_{g\rho g^\dagger; M} \{|\hat{x}|x - D(\rho \parallel \rho_{\text{mix}})| > \epsilon\}. \tag{52}$$

We denote the projection to  $\mathcal{U}_\lambda \otimes \mathcal{V}_\lambda$  by  $E_\lambda$ . Then, we have the following lemma.

**Lemma 7.** *For any estimator POVM  $M = \{(M_i, \hat{x}_i)\}_i$ , there exists an estimator POVM  $M' = \{(M'_i, \hat{x}_i)\}_i$  such that each operator  $M'_i$  is written as the form*

$$M'_i = \sum_{\lambda} c_{i|\lambda} E_\lambda, \tag{53}$$

and

$$R(\rho, M, \epsilon) \geq R(\rho, M', \epsilon). \tag{54}$$

Here,  $\hat{x}_i$  expresses the estimate when a measurement outcome  $i$  is observed.

Eq. (53) means that the estimator  $M'$  is given by using Schur sampling. Eq. (54) means that the estimator  $M'$  is better than the estimator  $M$ . Hence, if we do not care about the time complexity, it is allowed that our estimator is a function of Schur sampling including a randomized function of Schur sampling. Hence, combining the result by [6], we find that the lower bound of sample complexity is  $O(d^2)$  when  $d$  is increasing and  $\sigma$  is the completely mixed state.

*Proof.* To prove this lemma, we employ the method of Holevo's covariant measurement [30, Chapter 4], [24, Chapter 4]. We denote the invariant probability measure on  $\text{SU}(d)$  by  $\mu$ . Since  $M'_i := \int_{\text{SU}(d)} (g^{\otimes n})^\dagger M_i g^{\otimes n} \mu(dg)$  is invariant for the representation  $g^{\otimes n}$ , it has the form  $\sum_{\lambda} c_{i|\lambda} E_\lambda$ . We set the set  $B_\epsilon := \{i \mid |x - D(\rho \parallel \rho_{\text{mix}})| > \epsilon\}$ .

Then, we have

$$\begin{aligned}
R(\rho, M, \epsilon) &= \max_{g \in \text{SU}(d)} \sum_{i \in B_\epsilon} \text{Tr} g^{\otimes n} \rho^{\otimes n} (g^{\otimes n})^\dagger M_i \\
&\geq \int_{\text{SU}(d)} \sum_{i \in B_\epsilon} \text{Tr} g^{\otimes n} \rho^{\otimes n} (g^{\otimes n})^\dagger M_i \mu(dg) \\
&= \sum_{i \in B_\epsilon} \text{Tr} \rho^{\otimes n} \left( \int_{\text{SU}(d)} (g^{\otimes n})^\dagger M_i g^{\otimes n} \mu(dg) \right) \\
&= \sum_{i \in B_\epsilon} \text{Tr} \rho^{\otimes n} M'_i = R(\rho, M', \epsilon). \tag{55}
\end{aligned}$$

□

## VII. DISCUSSION

We have studied the estimation of quantum relative entropy  $D(\rho\|\sigma)$  when the second argument  $\sigma$  is known. Our estimator has a good performance in the following two senses. First, when the dimension  $d$  is fixed, our estimator attains Cramér-Rao type bound asymptotically. Second, when the dimension  $d$  increases, our estimator has sample complexity  $O(d^2)$  under natural assumptions. This sample complexity is optimal when  $\sigma$  is the completely mixed state. Third, when  $d$  is large, although the calculation of our estimator is difficult, we have an alternative estimator whose time complexity is  $O(d^5 \text{polylog}(d))$ . The difference between this alternative estimator and our original estimator is zero asymptotically. In the above way, our estimator works well unifiedly, which is a unique feature and did not appear in existing studies [6, 7, 14].

Since our estimator assumes the knowledge of the form of the second argument  $\sigma$ , it is needed to develop an estimator that works without this knowledge. In this case, we need to prepare  $n$  copies of the unknown state  $\sigma$  as well. To attain the Cramér-Rao type bound with fixed  $d$ , it is sufficient to estimate the form of the density matrix  $\sigma$ . However, such a method has a large time complexity when  $d$  increases. It is an interesting open problem to derive an efficient estimator of the quantum relative entropy in the above setting.

## ACKNOWLEDGEMENT

MH is supported in part by the National Natural Science Foundation of China (Grant No. 62171212). The author is grateful for Professor Kun Fang to a helpful discussion.

### Appendix A: Evaluation of mean square error: Proof of Theorem 2

We define the state  $\rho_n := \sum_{\lambda} \rho_{\lambda}$  on the system  $\oplus_{\lambda \in Y_d^n} \mathcal{U}_{\lambda}$ . We choose an orthogonal basis  $\{|v_{\lambda, j'}\}_{j'}$  of

$\mathcal{V}_{\lambda}$ .

$$\begin{aligned}
&\sum_{(\lambda, j)} P_{\rho, \sigma}^{(n)}(\lambda, j) (x_{\lambda, j} - D(\rho\|\sigma))^2 \\
&= \sum_{(\lambda, j)} P_{\rho, \sigma}^{(n)}(\lambda, j) \left( \frac{1}{n} (-\log \langle u_{\lambda, j} | \sigma_{\lambda} | u_{\lambda, j} \rangle - D(\rho\|\sigma)) \right)^2 \\
&= \sum_{(\lambda, j, j')} \langle u_{\lambda, j}, v_{\lambda, j'} | \rho^{\otimes n} | u_{\lambda, j}, v_{\lambda, j'} \rangle \\
&\quad \left( \frac{1}{n} (-\log \langle u_{\lambda, j}, v_{\lambda, j'} | \sigma_{\lambda} \otimes \rho_{\lambda, \text{mix}} | u_{\lambda, j}, v_{\lambda, j'} \rangle \right. \\
&\quad \left. + \log \langle v_{\lambda, j'} | \rho_{\lambda, \text{mix}} | v_{\lambda, j'} \rangle - D(\rho\|\sigma) \right)^2 \\
&= \sum_{(\lambda, j, j')} \langle u_{\lambda, j}, v_{\lambda, j'} | \rho^{\otimes n} | u_{\lambda, j}, v_{\lambda, j'} \rangle \\
&\quad \left( \frac{1}{n} (-\log \langle u_{\lambda, j}, v_{\lambda, j'} | \sigma^{\otimes n} | u_{\lambda, j}, v_{\lambda, j'} \rangle \right. \\
&\quad \left. + \log \langle u_{\lambda, j}, v_{\lambda, j'} | \sum_{\lambda'} I_{\mathcal{U}_{\lambda}} \otimes \rho_{\lambda', \text{mix}} | u_{\lambda, j}, v_{\lambda, j'} \rangle \right) \\
&\quad - D(\rho\|\sigma) \Big)^2 \\
&= \text{Tr} \rho^{\otimes n} \left( \frac{1}{n} (-\log \sigma^{\otimes n} + \sum_{\lambda} \log(I_{\mathcal{U}_{\lambda}} \otimes \rho_{\lambda, \text{mix}})) \right. \\
&\quad \left. - D(\rho\|\sigma) \right)^2 \\
&= \text{Tr} \rho^{\otimes n} \left( \frac{1}{n} (-\log \sigma^{\otimes n} + \sum_{\lambda} \log(\rho_{\lambda} \otimes \rho_{\lambda, \text{mix}})) \right. \\
&\quad \left. - D(\rho\|\sigma) - \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right)^2 \\
&= \text{Tr} \rho^{\otimes n} \left( \frac{1}{n} (-\log \sigma^{\otimes n} + \log \rho^{\otimes n}) - D(\rho\|\sigma) \right. \\
&\quad \left. - \frac{1}{n} \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right)^2 \\
&= \left\| \frac{1}{n} (-\log \sigma^{\otimes n} + \log \rho^{\otimes n}) - D(\rho\|\sigma) \right. \\
&\quad \left. - \frac{1}{n} \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right\|_{\rho^{\otimes n}}^2 \\
&\leq \left( \left\| \frac{1}{n} (-\log \sigma^{\otimes n} + \log \rho^{\otimes n}) - D(\rho\|\sigma) \right\|_{\rho^{\otimes n}} \right. \\
&\quad \left. + \left\| \frac{1}{n} \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right\|_{\rho^{\otimes n}} \right)^2. \tag{A1}
\end{aligned}$$

Also, we have

$$\begin{aligned}
&\left\| \frac{1}{n} (-\log \sigma^{\otimes n} + \log \rho^{\otimes n}) - D(\rho\|\sigma) \right\|_{\rho^{\otimes n}} \\
&= \text{Tr} \rho^{\otimes n} \left( \frac{1}{n} (-\log \sigma^{\otimes n} + \log \rho^{\otimes n}) - D(\rho\|\sigma) \right)^2 \\
&= \frac{1}{n} V(\rho\|\sigma), \tag{A2}
\end{aligned}$$

and

$$\begin{aligned}
& \left\| -\frac{1}{n} \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right\|_{\rho^{\otimes n}} \\
&= \text{Tr} \rho^{\otimes n} \left( \frac{1}{n} \sum_{\lambda} \log(\rho_{\lambda} \otimes I_{V_{\lambda}}) \right)^2 \\
&= \frac{1}{n^2} \text{Tr} \rho_n (\log \rho_n)^2 \stackrel{(a)}{\leq} \frac{1}{n^2} (\log d_n)^2, \quad (\text{A3})
\end{aligned}$$

where (a) follows from [3, Lemma 8]. The combination of (A1), (A2), and (A3) implies (21).

### Appendix B: Local asymptotic normality: Proof of Theorem 3

We use the methods [3, 31, 32].

$$\begin{aligned}
x_{\lambda,j} - D(\rho \parallel \sigma) &= -\frac{1}{n} \log \text{Tr} M_{\lambda,j} \sigma^{\otimes n} - D(\rho \parallel \sigma) \\
&= -\frac{1}{n} (\log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \sigma^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle + \log d'_{\lambda}) - D(\rho \parallel \sigma) \\
&= -\frac{1}{n} (\log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \sigma^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle \\
&\quad - \log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \rho^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle) - D(\rho \parallel \sigma) \\
&\quad - \frac{1}{n} (\log d'_{\lambda} + \log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \rho^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle) \\
&= \frac{1}{n} (-\log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \sigma^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle \\
&\quad + \log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \rho^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle) - D(\rho \parallel \sigma) \\
&\quad - \frac{1}{n} \log \langle u_{\lambda,j} \mid \rho_{\lambda} \mid u_{\lambda,j} \rangle. \quad (\text{B1})
\end{aligned}$$

The random variable  $\sqrt{n}(-\frac{1}{n}(\log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \sigma^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle) + \log \langle u_{\lambda,j}, v_{\lambda,j'} \mid \rho^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle) - D(\rho \parallel \sigma)$  has additional variable  $j'$ . The joint distribution of  $(\lambda, j, j')$  is given as  $\langle u_{\lambda,j}, v_{\lambda,j'} \mid \rho^{\otimes n} \mid u_{\lambda,j}, v_{\lambda,j'} \rangle$ . This random variable coincides with  $\sqrt{n}(\frac{1}{n}(\log \mathcal{E}_{\sigma^{\otimes n}}(\rho^{\otimes n}) - \log \sigma^{\otimes n}) - D(\rho \parallel \sigma))$  under the state  $\mathcal{E}_{\sigma^{\otimes n}}(\rho^{\otimes n})$  studied in Section V of [32]. The discussion in Section V of [32] showed that it converges to Gaussian distribution with variance  $V(\rho \parallel \sigma)$  in probability as  $n \rightarrow \infty$ .

In addition, in the same way as (A3), using [3, Lemma 8], we have

$$\begin{aligned}
& \sum_{(\lambda,j)} P_{\rho,\sigma}^{(n)}(\lambda,j) \left( \frac{1}{\sqrt{n}} \log \langle u_{\lambda,j} \mid \rho_{\lambda} \mid u_{\lambda,j} \rangle \right)^2 \\
&= \sum_{(\lambda,j)} P_{\rho,\sigma}^{(n)}(\lambda,j) \left( \frac{1}{\sqrt{n}} \log P_{\rho,\sigma}^{(n)}(\lambda,j) \right)^2 \\
&= \frac{1}{n} \text{Tr} \rho_n (\log \rho_n)^2 \leq \frac{1}{n} (\log d_n)^2 \\
&\leq \frac{1}{n} \left( \frac{(d+2)(d-1)}{2} \log(n+1) \right)^2 \rightarrow 0. \quad (\text{B2})
\end{aligned}$$

Thus, the random variable  $\frac{1}{\sqrt{n}} \log \langle u_{\lambda,j} \mid \rho_{\lambda} \mid u_{\lambda,j} \rangle$  under the distribution  $P_{\rho,\sigma}^{(n)}$  converges to zero in probability

as  $n \rightarrow \infty$ . Therefore, the probabilities  $\delta_{\rho,\sigma}^{(n),\pm,c/\sqrt{n}}$  can be asymptotically characterized by Gaussian distribution with variance  $V(\rho \parallel \sigma)$ .

## Appendix C: Large deviation evaluation

### 1. Preparation

We define the pinching map  $\Gamma_{\rho,n}$  as

$$\begin{aligned}
& \Gamma_{\sigma,n}(\rho') \\
&:= \sum_{\lambda \in Y_d^n, j} (|u_{\lambda,j}\rangle \langle u_{\lambda,j}| \otimes P(\mathcal{V}_{\lambda})) \rho' (|u_{\lambda,j}\rangle \langle u_{\lambda,j}| \otimes P(\mathcal{V}_{\lambda})) \\
&\hspace{15em} (\text{C1})
\end{aligned}$$

for a general state  $\rho'$  on  $\mathcal{H}^{\otimes n}$ . Since the system  $\mathcal{V}_{\lambda}$  has no information, it is sufficient to handle the two states  $\bigoplus_{\lambda \in Y_d^n} \rho_{\lambda}$  and  $\bigoplus_{\lambda \in Y_d^n} \sigma_{\lambda}$  over  $\bigoplus_{\lambda \in Y_d^n} \mathcal{U}_{\lambda}$ . We define the map

$$\begin{aligned}
\kappa_{\sigma,n}(\rho') &:= \sum_{\lambda \in Y_d^n, j} \text{Tr}_{\mathcal{V}_{\lambda}} (|u_{\lambda,j}\rangle \langle u_{\lambda,j}| \otimes P(\mathcal{V}_{\lambda})) \rho' \\
&\quad \cdot (|u_{\lambda,j}\rangle \langle u_{\lambda,j}| \otimes P(\mathcal{V}_{\lambda})) \quad (\text{C2})
\end{aligned}$$

for a general state  $\rho'$  on  $\mathcal{H}^{\otimes n}$ . Due to the above-mentioned structure, the states  $\Gamma_{\sigma,n}(\rho^{\otimes n})$  and  $\sigma^{\otimes n}$  are commutative with each other.

We have the pinching inequality:

$$\rho' \leq d_n \Gamma_{\sigma,n}(\rho'). \quad (\text{C3})$$

In fact, applying the matrix monotone function to (C3), for  $\alpha \in (0, 1)$ , we have

$$\begin{aligned}
& d_n^{\alpha-1} ((\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \Gamma_{\sigma,n}(\rho^{\otimes n}) (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}})^{\alpha-1} \\
&= \left( d_n \Gamma_{\sigma,n} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right) \right)^{\alpha-1} \\
&\leq \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha-1}. \quad (\text{C4})
\end{aligned}$$

Thus, we have

$$\begin{aligned}
& \text{Tr} \Gamma_{\sigma,n}(\rho^{\otimes n})^{\alpha} (\sigma^{\otimes n})^{1-\alpha} \\
&= \text{Tr} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \Gamma_{\sigma,n}(\rho^{\otimes n}) (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha} \\
&= \text{Tr} \Gamma_{\sigma,n} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha} \\
&= \text{Tr} \left( \Gamma_{\sigma,n} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right) \right. \\
&\quad \cdot \left. \left( \Gamma_{\sigma,n} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right) \right)^{\alpha-1} \right) \\
&= \text{Tr} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right) \\
&\quad \cdot \Gamma_{\sigma,n} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha-1} \\
&\stackrel{(a)}{\leq} d_n^{1-\alpha} \text{Tr} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right) \\
&\quad \cdot \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha-1} \\
&= d_n^{1-\alpha} \text{Tr} \left( (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \rho^{\otimes n} (\sigma^{\otimes n})^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha} \\
&= d_n^{1-\alpha} \left( \text{Tr} \left( \sigma^{\frac{1-\alpha}{2\alpha}} \rho \sigma^{\frac{1-\alpha}{2\alpha}} \right)^{\alpha} \right)^n, \quad (\text{C5})
\end{aligned}$$

where Step (a) follows from (C4).



## 2. Proof of Theorem 4

For  $\alpha \in (0, 1)$ , we have

$$\begin{aligned}
& \sum_{(\lambda, j): x_{\lambda, j} < R} \text{Tr} M_{\lambda, j} \rho^{\otimes n} \\
&= \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\sigma^{\otimes n}) > e^{-nR} \} \\
&\stackrel{(b)}{\leq} \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\sigma^{\otimes n}) > e^{-nR} \kappa_{\sigma, n}(\rho^{\otimes n}) \} \\
&\leq \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n})^{1-\alpha} \kappa_{\sigma, n}(\sigma^{\otimes n})^{\alpha} e^{n\alpha R} \\
&= \text{Tr} \Gamma_{\sigma, n}(\rho^{\otimes n})^{1-\alpha} (\sigma^{\otimes n})^{\alpha} e^{n\alpha R} \\
&\stackrel{(c)}{\leq} d_n^{\alpha} (\text{Tr}(\sigma^{\frac{\alpha}{2(1-\alpha)}} \rho \sigma^{\frac{\alpha}{2(1-\alpha)}})^{1-\alpha} e^{\alpha R})^n \\
&= d_n^{\alpha} e^{-n\alpha(D_{1-\alpha}(\rho \parallel \sigma) - R)}. \tag{C6}
\end{aligned}$$

Here, (b) follows from  $\kappa_{\sigma, n}(\rho^{\otimes n}) \leq I$ , and (c) follows from (C5).

For  $\alpha > 0$ , we have

$$\begin{aligned}
& \sum_{(\lambda, j): x_{\lambda, j} > R} \text{Tr} M_{\lambda, j} \rho^{\otimes n} \\
&= \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\sigma^{\otimes n}) < e^{-nR} \} \\
&\leq \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\sigma^{\otimes n}) < e^{-nR} \} \{ \kappa_{\sigma, n}(\rho^{\otimes n}) > e^{-nr} \} \\
&\quad + \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\rho^{\otimes n}) \leq e^{-nr} \} \\
&\leq \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\sigma^{\otimes n}) < e^{-nR+nr} \kappa_{\sigma, n}(\rho^{\otimes n}) \} \\
&\quad + \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n}) \{ \kappa_{\sigma, n}(\rho^{\otimes n}) \leq e^{-nr} \} \\
&\leq \text{Tr} \kappa_{\sigma, n}(\rho^{\otimes n})^{1+\alpha} \kappa_{\sigma, n}(\sigma^{\otimes n})^{-\alpha} e^{-n\alpha(R-r)} + d_n e^{-nr} \\
&= \text{Tr} \Gamma_{\sigma, n}(\rho^{\otimes n})^{1+\alpha} (\sigma^{\otimes n})^{-\alpha} e^{-n\alpha(R-r)} + d_n e^{-nr} \\
&\stackrel{(d)}{\leq} \text{Tr}(\rho^{\otimes n})^{1+\alpha} (\sigma^{\otimes n})^{-\alpha} e^{-n\alpha(R-r)} + d_n e^{-nr} \\
&= (\text{Tr}(\sigma^{-\frac{\alpha}{2(1+\alpha)}} \rho \sigma^{-\frac{\alpha}{2(1+\alpha)}})^{1+\alpha} e^{-\alpha(R-r)})^n + d_n e^{-nr} \\
&= e^{-n(R-r-\alpha(D_{1+\alpha}(\rho \parallel \sigma)))} + d_n e^{-nr}. \tag{C7}
\end{aligned}$$

(d) follows from the monotonicity of sandwich Rényi relative entropy.

- 
- [1] F. Hiai and D. Petz, “The proper formula for relative entropy and its asymptotics in quantum probability,” *Comm. Math. Phys.*, **143**, 99 – 114 (1991).
- [2] T. Ogawa and H. Nagaoka, “Strong converse and Stein’s lemma in quantum hypothesis testing,” *IEEE Trans. Inf. Theory*, **46**, 2428 – 2433 (2000).
- [3] M. Hayashi, “Optimal sequence of quantum measurements in the sense of Stein’s lemma in quantum hypothesis testing” *J. Phys. A: Math. Gen.*, **35**, 10759 – 10773 (2002).
- [4] J. Nötzel, “Hypothesis testing on invariant subspaces of the symmetric group: part I. Quantum Sanov’s theorem and arbitrarily varying sources,” *J. Phys. A: Math. Theor.*, **47**, 235303 (2014)
- [5] I. Bjelaković, J.-D. Deuschel, T. Krüger, R. Seiler, R. Siegmund-Schultze, and A. Szkoła, “A Quantum Version of Sanov’s Theorem,” *Commun. Math. Phys.*, **260**, 659 – 671 (2005).
- [6] J. Acharya, I. Issa, N. V. Shende and A. B. Wagner, “Estimating Quantum Entropy,” *IEEE Journal on Selected Areas in Information Theory*, **1**, 454 – 468 (2020).
- [7] Q. Wang and Z. Zhang, “Time-Efficient Quantum Entropy Estimator via Sampler,” <https://arxiv.org/abs/2401.09947> (2024).
- [8] M. Keyl and R.F. Werner, “Estimating the spectrum of a density operator,” *Phys. Rev. A*, **64**, 052311 (2001).
- [9] M. Christandl and G. Mitchison, “The Spectra of Quantum States and the Kronecker Coefficients of the Symmetric Group,” *Commun. Math. Phys.*, **261**, 789 – 797 (2006).
- [10] M. Christandl, A.W. Harrow, and G. Mitchison, “Nonzero Kronecker Coefficients and What They Tell us about Spectra,” *Commun. Math. Phys.*, **270**, 575 – 585 (2007).
- [11] R. O’Donnell and J. Wright, “Quantum Spectrum Testing,” *Commun. Math. Phys.*, **387**, 1 – 75 (2021).
- [12] M. Hayashi and K. Matsumoto, “Quantum universal variable-length source coding,” *Phys. Rev. A*, **66**, 022311 (2002).
- [13] M. Hayashi, “Exponents of quantum fixed-length pure state source coding,” *Phys. Rev. A*, **66**, 032321 (2002). *Phys. Rev. A*, **66**, 069901(E) (2002).
- [14] J. Suzuki, Y. Yang, and M. Hayashi, “Quantum state estimation with nuisance parameters,” *J. Phys. A: Math. Theor.*, **53**, 453001 (2020).
- [15] H. Nagaoka and A. Fujiwara, “Autoparallelity of Quantum Statistical Manifolds in The Light of Quantum Estimation Theory,” <https://arxiv.org/abs/2307.03431> (2023).
- [16] Y. Yang, G. Chiribella, and M. Hayashi, “Attaining the Ultimate Precision Limit in Quantum State Estimation,” *Commun. Math. Phys.*, **368**, 223 – 293 (2019).
- [17] M. Hayashi, “Comparison between the Cramer-Rao and the mini-max approaches in quantum channel estimation,” *Commun. Math. Phys.*, **304**, 689 – 709 (2011).
- [18] A. Fujiwara, “Strong consistency and asymptotic efficiency for adaptive quantum estimation problems,” *J. Phys. A: Math. Gen.*, **39**, 12489 (2006)
- [19] M. A. Rodríguez-García, I. P. Castillo, and P. Barberis-Blostein “Efficient qubit phase estimation using adaptive measurements,” *Quantum*, **5**, 467 (2021).
- [20] D. Bacon, I L. Chuang, and A. W. Harrow, “Efficient Quantum Circuits for Schur and Clebsch-Gordan Transforms,” *Phys. Rev. Lett.*, **97**, 170502 (2006).
- [21] M. Hayashi, *Quantum Information Theory: Mathematical Foundation, Graduate Texts in Physics*, Springer (2017). (First edition was published from Springer in 2006).
- [22] M. Hayashi, “Asymptotics of quantum relative entropy from a representation theoretical viewpoint,” *J. Phys. A: Math. Gen.*, **34**, 3413 – 3419 (2001).
- [23] M. Hayashi and Y. Ito, “Entanglement measures for de-

- tectability,” arXiv: 2311.11189 (2024).
- [24] M. Hayashi, *A Group Theoretic Approach to Quantum Information*, Springer (2017).
- [25] R. Goodman and N. R. Wallach, *Representations and Invariants of the Classical Groups*, Encyclopedia of Mathematics and Its Applications, vol. 68 (Cambridge University Press, Cambridge, 1999).
- [26] M. Hayashi, *Group Representation for Quantum Theory*, Springer (2017). (Originally published from Kyoritsu Shuppan in 2014 with Japanese.)
- [27] M. Hayashi, “Exponential decreasing rate of leaked information in universal random privacy amplification,” *IEEE Trans. Inf. Theory*, **57**, 3989–4001 (2011).
- [28] H. Krovi, “An efficient high dimensional quantum Schur transform,” *Quantum*, **3**, 122 (2019).
- [29] Q. T. Nguyen, “The mixed Schur transform: efficient quantum circuit and applications,” <https://arxiv.org/abs/2310.01613> (2023).
- [30] A. S. Holevo, *Probabilistic and statistical aspects of quantum theory*, (Edizioni della Normale, 2011).
- [31] M. Hayashi and M. Tomamichel, “Correlation Detection and an Operational Interpretation of the Renyi Mutual Information,” *Journal of Mathematical Physics*, **57**, 102201 (2016).
- [32] M. Tomamichel and M. Hayashi, “A Hierarchy of Information Quantities for Finite Block Length Analysis of Quantum Tasks,” *IEEE Trans. Inf. Theory*, **59**, 7693 – 7710 (2013).