

Multiple testing in multi-stream sequential change detection

Sanjit Dandapanthula*
sanjitd@cmu.edu

Aaditya Ramdas†
aramdas@cmu.edu

January 15, 2025

Abstract

Multi-stream sequential change detection involves simultaneously monitoring many streams of data and trying to detect when their distributions change, if at all. Here, we theoretically study multiple testing issues that arise from detecting changes in many streams. We point out that any algorithm with finite average run length (ARL) must have a trivial worst-case false detection rate (FDR), family-wise error rate (FWER), and per-family error rate (PFER); thus, any attempt to control these Type I error metrics is fundamentally in conflict with the desire for a finite ARL (which is typically necessary in order to have a small detection delay). One of our contributions is to define a new class of metrics which can be controlled, called *error over patience* (EOP). We propose algorithms that combine the recent e-detector framework (which generalizes the Shiryaev-Roberts and CUSUM methods) with the recent e-Benjamini-Hochberg procedure and e-Bonferroni procedures. We prove that these algorithms control the EOP at any desired level under very general dependence structures on the data within and across the streams. In fact, we prove a more general error control that holds uniformly over all stopping times and provides a smooth trade-off between the conflicting metrics. Additionally, if finiteness of the ARL is forfeited, we show that our algorithms control the Type I error.

1	Introduction	3
2	Background: multi-stream sequential change detection	5

*Carnegie Mellon University, Department of Statistics

†Carnegie Mellon University, Department of Statistics and Machine Learning Department

3	Related work	8
3.1	Multiple testing in single-stream change detection	9
3.2	Multiple testing in multi-stream change detection	9
4	Simultaneous control over Type I error and ARL	10
4.1	Impossibility of achieving nontrivial worst-case Type I error	10
4.2	New metric: error over patience (EOP)	12
5	Background: e-detectors and the e-BH procedure	13
5.1	Change detection using e-detectors	13
5.2	The e-BH procedure	15
6	The e-detector Benjamini-Hochberg (e-d-BH) procedure	16
6.1	Upper-bounding EOP_{FDR} using the e-d-BH procedure	17
6.2	Universal FDR control using the e-d-BH procedure	19
7	The e-d-Bonferroni procedure	20
7.1	Upper-bounding EOP_{PFER} using the e-d-Bonferroni procedure	20
7.2	Universal PFER control using the e-d-Bonferroni procedure	22
8	The e-d-Holm procedure: universal FWER control	24
9	A more detailed discussion about dependence	26
9.1	Subtleties about filtrations	26
9.2	Counterexample: when dependence breaks EOP control	26
9.3	Positive examples: when dependence poses no threat	27
9.3.1	Gaussian mean change with unknown covariance	27
9.3.2	Nonparametric symmetry change with dependence	27
10	Simulations	28
10.1	Gaussian mean change	28
10.2	Nonparametric symmetry testing	32
10.3	Nonparametric independence testing	34
11	Conclusion	36
A	Relating the CCD and ARL	38
B	Piggybacking of evidence by e-d-BH	39

1 Introduction

In single-stream sequential change detection, we observe a sequence of random variables $(X_t)_{t=1}^\infty$ one at a time and (informally) our goal is stop as soon as we detect that there has been some change in the data-generating distribution. A common metric considered in the single-stream setting — not without its critics — is the average run length (ARL), which is the expected time until a false alarm when there is no change. One typically seeks change detection algorithms that come with an upper bound on the detection delay while guaranteeing a lower bound on the ARL.

The multi-stream sequential change detection setting is concerned with simultaneously detecting changes in many streams. However, an algorithm which is effective in the single-stream setting may not be good when deployed without alteration on each of the multiple streams. This is because we would only obtain a guarantee on the per-stream ARL, but not on error metrics that evaluate performance more holistically across streams.

For instance, we may want control over the false detection rate (FDR), which is the expected proportion of detections which are false. False detections may be costly, and one may consequently desire to not make too many of these mistakes. In this case, we may want to control the family-wise error rate (FWER), which is the probability of making any false detection, or the per-family error rate (PFER), which is the expected number of false detections. All of these Type I error metrics have been heavily studied in the multiple testing literature, but their interplay with metrics like the ARL have not been thoroughly studied in the multi-stream change detection context. In fact, we later formally point out that having a finite ARL (which is typically necessary for an algorithm to have a small detection delay) forces the worst-case Type I error to be essentially trivial.

Given this inherent and unavoidable tension between the ARL and the Type I error, can we still design procedures that deliver sensible and nontrivial guarantees? We make a novel proposal: we suggest a new class of metrics as *error over patience* (EOP), that take the form:

$$\text{EOP} = \sup_{\text{stopping times } \tau} \frac{\text{Type I error at time } \tau}{\mathbb{E}[\tau]}.$$

Here, the denominator is termed *patience*. Upper bounding the EOP will force the Type I error to be small when changes are declared quickly (the low-patience regime), but allow the Type I error to be larger when changes are declared more slowly (the high-patience regime). This metric might initially appear odd, so we will spend some time unpacking the definition and justifying that it is sensible; in some sense, it is the best we can hope for given the aforementioned unavoidable tradeoffs. For example, when instantiated under the global null (no change in any stream), the numerator equals 1 as soon as any change is declared, and the denominator equals the ARL. Therefore, upper bounding the EOP yields a lower bound on the ARL, as one would typically desire.

A new metric is useful only if it can be controlled. We present a somewhat general framework for multi-stream change detection that combines two modern tools involving *e-values*. In particular, we combine the recent *e-detector* framework for single-stream change detection with the recent *e-Benjamini-Hochberg* (e-BH) procedure for FDR control and the *e-Bonferroni* procedure for PFER control, and show that the resulting procedures can bound the EOP at any predefined level. Note that the guarantee holds *uniformly over all stopping times*, by definition of the EOP; this can include the time of the first detection. We call these the *e-d-BH* and *e-d-Bonferroni* procedures. One benefit of using e-detectors is that our algorithms are widely applicable even when the pre-change distribution is unknown but comes from a composite (possibly nonparametric) class, and under very general dependence structures between the data across streams. Finally, we show that if finiteness of the ARL is forfeited, the e-d-BH and e-d-Bonferroni methods provide universal control over the FDR and PFER respectively.

To summarize, this paper has three main contributions:

- Articulating the fundamental tension between the Type I error and ARL.
- Proposing a new class of metrics: the EOP — this is the Type I error over patience.
- Developing algorithms (e-d-BH and e-d-Bonferroni) that can control the EOP metric (and more) under rather general settings and weak assumptions.

As is typical in the multiple testing literature, this paper provides bounds on false detections (Type I errors) rather than true detections (power), and on the ARL rather than detection delay. This is for two reasons; first, the initial part of the paper will be agnostic to the precise details of the problem setup and the specific change detection procedure one chooses to use for each stream. While the second part of the paper does specify which change detection *framework* to use (e-detectors), any further details of the problem setup will not matter to us. Thus, we present our methods and guarantees abstractly, but discussions of detection delay must necessarily be grounded in the specifics of concrete change detection problems. This is somewhat analogous to the Benjamini-Hochberg (or e-BH) procedure taking in a set of p-values (or e-values), but being agnostic to their power due to the lack of assumptions on what hypotheses are being tested or how the p-values were constructed. These issues are of course important in practice, but they are irrelevant for presenting the BH procedure and its Type I error guarantees. For the same reason, we do not discuss computational issues in this paper — computationally efficient schemes for multi-stream change detection are practically important, but the methods will depend on details of the problem definition. Instead, we aim to provide a more abstract (and thus more comprehensive from that regard) treatment of the interplay between Type I error metrics and the ARL.

We begin by formalizing the problem and setting up some notation. We will not do this all at once; the e-d-BH framework (and the past work it builds on: e-detectors and the e-BH

procedure) is likely unfamiliar to most readers and can appear mysterious at first glance, so we will introduce the appropriate background as needed. We will also provide several examples later in the paper that instantiate the framework for concrete problems.

2 Background: multi-stream sequential change detection

Consider a general formulation of the multi-stream sequential change detection problem. We allow the streams to be dependent and allow the observations within each stream to also be dependent. Technically, each stream could have data lying in any space, but for simplicity we present the framework assuming that each stream has real-valued observations. Let $\mathcal{M}(\mathbb{R}^{\mathbb{N}})$ denote the set of probability measures over $\mathbb{R}^{\mathbb{N}}$ (these are joint distributions over infinite sequences of observations, which are not necessarily i.i.d.).

Suppose we are monitoring $K \in \mathbb{N}$ streams of data, denoted $(X_t^{(k)})_{t=1}^{\infty}$ for $k \in [K]$, where $[K] = \{1, \dots, K\}$. We observe the data sequentially, meaning that at time t , we observe $(X_t^{(1)}, \dots, X_t^{(K)})$. Suppose each stream $k \in [K]$ has a single changepoint at some unknown time $1 < \xi^{(k)} \leq \infty$ (where $\xi^{(k)} = \infty$ means that there is no change in the k th stream). We use $\xi = (\xi^{(1)}, \dots, \xi^{(K)}) \in \mathbb{N}^K$ to denote the list of true changepoints; we call this the *configuration*. We'll use $\xi_G = (\infty, \dots, \infty)$ to denote the special configuration corresponding to the *global null* (when there is no change in any stream). We will not assume that the pre-change or post-change distributions in each stream are known exactly, but only that they lie in some known sets; let $\mathcal{P}_0^{(k)}, \mathcal{P}_1^{(k)} \subseteq \mathcal{M}(\mathbb{R}^{\mathbb{N}})$ be the pre-change and post-change classes of distributions over data sequences $(X_t^{(k)})_{t=1}^{\infty}$ for each stream $k \in [K]$. Importantly, these classes refer to the joint distributions *across time* of each individual stream — but the joint distribution *across streams* is arbitrary (see [Section 9](#) for a discussion on implicit restrictions on the cross-stream dependence that is placed by later results).

Then, suppose that $(X_t^{(k)})_{t=1}^{\xi^{(k)}-1}$ is drawn from some unknown distribution $\mathbb{P}_0^{(k)} \in \mathcal{P}_0^{(k)}$ (more formally, from its restriction to the first $\xi^{(k)} - 1$ coordinates), and that $(X_t^{(k)})_{t=\xi^{(k)}}^{\infty}$ is drawn from some distribution $\mathbb{P}_1^{(k)} \in \mathcal{P}_1^{(k)}$. Let $\mathcal{F}^{(k)}$ denote a filtration for the k -th stream, which if left unspecified is taken to be the natural filtration of the data:

$$\mathcal{F}_t^{(k)} = \sigma(X_1^{(k)}, \dots, X_t^{(k)}).$$

For example, consider a scenario in which we want to detect a change in symmetry, meaning that pre-change observations are assumed to have a symmetric conditional distribution around zero, while post-change observations do not. One can think of symmetry testing as a nonparametric generalization of the t -test, which assumes that the data is a centered Gaussian with unknown variance. Letting $=_d$ denote equality in distribution, we could choose:

$$\mathcal{P}_0^{(k)} = \left\{ \mathbb{P} \in \mathcal{M}(\mathbb{R}^{\mathbb{N}}) : (X_t =_d -X_t) \mid \mathcal{F}_{t-1}^{(k)} \text{ for all } t \in \mathbb{N}, \text{ where } (X_t)_{t=1}^{\infty} \sim \mathbb{P} \right\}.$$

Then, $\mathcal{P}_1^{(k)}$ would be some subset of the complement of $\mathcal{P}_0^{(k)}$.

Notice that in general, the sets $\mathcal{P}_0^{(k)}$ and $\mathcal{P}_1^{(k)}$ need not be parametric, and this framework allows for dependence within each stream. For example, the pre-change class contains distributions of the type: “Draw the first stream’s observation from a standard Gaussian. If it is positive, draw the second stream’s observation from a standard Gaussian, else draw it from a standard Cauchy”. As mentioned before, our algorithms can handle dependence with streams and across streams in some scenarios as well, which we discuss in [Section 9](#).

We will let \mathbb{P} denote the true data generating distribution (over all K data streams and for all times $t \in \mathbb{N}$). Note that the data distribution \mathbb{P} depends implicitly on the configuration ξ , although this dependence may be hidden in future notation. Furthermore, suppose we have a global filtration $\mathcal{F} = (\mathcal{F}_t)_{t=1}^\infty$. If the filtration is left unspecified, let \mathcal{F} be the natural global filtration generated by all the data:

$$\mathcal{F}_t = \sigma \left(X_j^{(k)} : j \in [t], k \in [K] \right).$$

Throughout this paper, we use the notation $x \vee y = \max\{x, y\}$ and $x \wedge y = \min\{x, y\}$.

Definition 2.1 (Stopping times). A *stopping time* is a random variable τ such that the event $\{\tau \leq t\}$ is \mathcal{F}_t -measurable for all $t \in \mathbb{N}$.

Naturally, stopping times in this paper are allowed to depend on data from all streams, so they are based on the global filtration \mathcal{F} (and not any stream-specific filtration $\mathcal{F}^{(k)}$).

Definition 2.2 (Sequential change monitoring algorithm). A *sequential change monitoring algorithm* is a list of sequences $(\varphi_t^{(k)})_{t=1}^\infty \in \{0, 1\}^\mathbb{N}$ for $k \in [K]$, where $\varphi_t^{(k)}$ is adapted to \mathcal{F} . We let $\varphi^{(k)}$ denote the sequence $(\varphi_t^{(k)})_{t=1}^\infty$ and we let $\varphi = (\varphi^{(1)}, \dots, \varphi^{(K)})$.

We interpret $\{\varphi_t^{(k)} = 0\}$ to be the event that the algorithm has not found that a change in stream k has previously occurred before time t and $\{\varphi_t^{(k)} = 1\}$ to be the event that the algorithm did detect that a change in stream k has occurred before time t . Suppose that at some time t , the algorithm detected a change in stream k ; later, upon accumulating more evidence, we allow the algorithm to change its mind and decide that there was actually no change in stream k . In short, we do not require that $\varphi_t^{(k)} = 1$ necessarily implies $\varphi_s^{(k)} = 1$ for $s > t$ (although for specific algorithms it could). Note that we allow $\varphi^{(k)}$ to be adapted to \mathcal{F} and do not restrict it to be adapted to $\mathcal{F}^{(k)}$, meaning that $\varphi^{(k)}$ is allowed to depend on data from all streams up to time t , not just the k -th stream. This will later allow us to control error metrics (like the EOP) that evaluate decisions across all streams.

A change monitoring algorithm can be continually monitored, and sequentially gives the user a changing subset of streams in which it has thus far detected a change. In our terminology, a change *monitoring* algorithm needs to be coupled with a stopping time in order to yield a change *detection* algorithm.

Definition 2.3 (Sequential change detection algorithm). A *sequential change detection algorithm* is a pair (φ, τ) , where φ is a change monitoring algorithm and τ is a stopping time (with respect to \mathcal{F}). At time τ , the algorithm stops and outputs $(\varphi_\tau^{(k)})_{k=1}^K$, representing its final decisions at time τ about which streams have purportedly had a change by time τ .

In practice, one may run the change monitoring algorithm and continuously peek at the data $(X_t^{(k)})_{k=1}^K$ (if the filtration \mathcal{F} is the natural one) in order to decide when to stop. One important summary statistic of the data is the value of an e-detector, which we will define later in [Section 5.1](#). For instance, τ can be the first time that the e-detector exceeds some threshold in at least η streams for some $\eta \geq 1$. In practice, τ may even depend on random noise irrelevant to the problem or on external circumstances; for example, a researcher may choose to stop the monitoring algorithm due to lack of funds to continue an experiment or when the number of claimed detections stays constant for ten steps. Therefore, we would like guarantees on the performance of the monitoring algorithm which are robust to the choice of τ . This motivates the supremum over τ taken in the definition of the EOP (previewed in the introduction but formally defined later).

Definition 2.4 (Global null). For stream k , define the null hypothesis $\mathcal{H}_0^{(k)} : \xi^{(k)} = \infty$. We define the *global null* \mathcal{H}_0^* to be the scenario in which $\mathcal{H}_0^{(k)}$ is true for all k ; namely, this is the scenario in which there are no changes at all. We will let $\mathbb{E}_\infty[\cdot]$ denote expectation under the global null and $\mathbb{P}_\infty(\cdot)$ denote the probability measure under the global null.

In the single-stream setting, the average run length (ARL) is defined as the expected first time that an algorithm declares a change, assuming that there is no change. Here, we extend the definition of the ARL to the more general multi-stream setting, and the single-stream ARL will be a special case when $K = \eta = 1$.

Definition 2.5 (Average run length $(\text{ARL}_\eta(\varphi))$). For a given multi-stream change monitoring algorithm φ , let $\tau_\eta^*(\varphi)$ denote the first time that our algorithm declares a change in at least $1 \leq \eta \leq K$ streams:

$$\tau_\eta^*(\varphi) = \inf_{t \in \mathbb{N}} \left\{ \sum_{k=1}^K \varphi_t^{(k)} \geq \eta \right\}. \quad (1)$$

Then, the *average run length* $\text{ARL}_\eta(\varphi)$ is defined as:

$$\text{ARL}_\eta(\varphi) = \mathbb{E}_\infty[\tau_\eta^*(\varphi)]. \quad (2)$$

Note that $\text{ARL}_\eta(\varphi)$ as could also be described as the “average run length to η detections”.

We typically want the ARL to be large. For example, one might want the ARL to be larger than $1/\alpha$ for some $\alpha \in (0, 1)$. However, methods with a large ARL must also have a large detection delay; the detection delay typically scales proportional to $\log(1/\alpha)$ (see [Chan](#)

(2017)). Therefore, the most interesting regime is that in which the ARL is large but still finite, since it is only then that we can still hope to control the detection delay.

Definition 2.6 (False detection rate at time t ($\text{FDR}(\varphi, \xi, t)$)). For a sequential change monitoring algorithm φ and configuration ξ , the false detection proportion at time t ($\text{FDP}(\varphi, \xi, t)$) is the ratio of null hypotheses rejected to total hypotheses rejected at time $t \in \mathbb{N}$:

$$\text{FDP}(\varphi, \xi, t) = \frac{\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} > t}}{\left(\sum_{k=1}^K \varphi_t^{(k)}\right) \vee 1}.$$

Here, $\text{FDP}(\varphi, \xi, t)$ is a random variable. The *false detection rate at time t* ($\text{FDR}(\varphi, \xi, t)$) measures the expected false detection proportion (FDP) at time $t \in \mathbb{N}$:

$$\text{FDR}(\varphi, \xi, t) = \mathbb{E}[\text{FDP}(\varphi, \xi, t)] = \mathbb{E} \left[\frac{\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} > t}}{\left(\sum_{k=1}^K \varphi_t^{(k)}\right) \vee 1} \right].$$

Definition 2.7 (Family-wise error rate at time t ($\text{FWER}(\varphi, \xi, t)$)). For a given sequential change monitoring algorithm φ and configuration ξ , the *family-wise error rate at time t* ($\text{FWER}(\varphi, \xi, t)$) measures the probability of having at least one false detection in any stream at time $t \in \mathbb{N}$:

$$\text{FWER}(\varphi, \xi, t) = \mathbb{P} \left(\bigcup_{k=1}^K \{\varphi_t^{(k)} = 1\} \cap \{\xi^{(k)} > t\} \right).$$

Definition 2.8 (Per-family error rate at time t ($\text{PFER}(\varphi, \xi, t)$)). For a given sequential change monitoring algorithm φ and configuration ξ , the *per-family error rate at time t* ($\text{PFER}(\varphi, \xi, t)$) measures the expected number of false detections at time $t \in \mathbb{N}$:

$$\text{PFER}(\varphi, \xi, t) = \mathbb{E} \left[\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} > t} \right].$$

These three metrics are the most common measures of Type I error when testing multiple hypotheses. Note that the PFER is a more stringent metric than the FWER, which in turn is a more stringent metric than the FDR. Since the configuration ξ is unknown, we typically aim to control these metrics uniformly over ξ . Before presenting our results, we review some related work.

3 Related work

In this section, we discuss some related work in the field of change detection. In particular, we point out that the issue of multiple testing has not been comprehensively addressed in prior multi-stream change detection literature, especially from a theoretical perspective.

3.1 Multiple testing in single-stream change detection

The need for control over multiple testing statistics has been discussed in the related context of multiple change detection in a *single stream*; here, we briefly mention some of the prior work in this area. For example, [Bodenham and Adams \(2017\)](#) introduce the metrics¹ CCD (changes correctly detected) and FDR for change detection. They argue that current metrics used for change detection in streams (ARL and detection delay) are insufficient and that current algorithms, even in the single-stream setting, do not seem to have good theoretical control on CCD and FDR. They provide empirical estimates on these quantities and show that some of the popular methods in the area (such as [Jiang et al. \(2008\)](#)) actually do not do a good job of controlling the CCD or FDR.

[Plasse et al. \(2021\)](#) studies change detection in the context of transition matrices of Markov processes. In this work, ARL and detection delay are referenced as being insufficient to fully characterize the quality of their method. In addition to these metrics, the empirical F_1 scores of the algorithm in [Bodenham and Adams \(2017\)](#) is also reported. However, they do not provide any theoretical guarantees on the F_1 score.

[Plasse and Adams \(2019\)](#) discusses a new method for multiple change detection in a single data stream, specifically in the setting where the data is categorical. Even so, [Plasse and Adams \(2019\)](#) references [Bodenham and Adams \(2017\)](#) to point out that ARL and detection delay are not sufficient to analyze the performance of a change detector. Therefore, they empirically estimate the CCD and FDR of their method, but as with most methods in this field, do not provide any theoretical bounds on these quantities or discuss the relationship between the FDR and the ARL.

3.2 Multiple testing in multi-stream change detection

[Mei \(2010\)](#) develops methods that work for sequential multi-stream change detection when the number of streams is large. Prior work had used mixture likelihood ratio methods but [Mei \(2010\)](#) offered more computationally efficient methods. [Mei \(2010\)](#) argues that “the Type I and II error [...] criteria of the off-line hypothesis testing problem have been replaced by the average run length [...] in the online change detection problem” [Mei \(2010, p. 2\)](#). The setting in their work is as follows: suppose you are monitoring K data streams, where streams $\{k_1, \dots, k_m\}$ change at the same time ν (although the methods generalize when these streams do not all change at the same time). The goal of [Mei \(2010\)](#) is to minimize the detection delay ($\mathbb{E}^{\{k_1, \dots, k_m\} \subseteq [K]}[\tau]$) subject to an ARL constraint ($\mathbb{E}_\infty[\tau] \geq \gamma$). But even if the detection delay is small and the ARL is large but not infinite, this objective does not identify streams

¹The CCD is the proportion of changed streams in which a change monitoring algorithm correctly declares a change. Also, [Bodenham and Adams \(2017\)](#) and others use the metric $\text{DNF} = 1 - \text{FDR}$.

with changes or provide any clean control of the false detection rate (which would equal 1 under the global null, as proved later).

Xu and Mei (2021) is a more recent paper with the same objective. They show the second-order asymptotic optimality of a class of methods for multi-stream change detection under this regime. Once more, the identification of streams (and the resulting Type I errors) are not discussed.

Chan (2017) derives asymptotic lower bounds on the detection delay and thereby shows that a modified version of a mixed likelihood ratio method is optimal for the problem described in Mei (2010). The goal again is to minimize detection delay subject to an ARL constraint. As above, Chan (2017) does not have any mention to CCD, FDR, or any similar metrics.

Tartakovsky and Spivak (2024) studies the detection of changes in multi-stream stochastic models. In their paper, they define the metric $\text{PFA} = \sum_{k=0}^{\infty} \pi_k \mathbb{P}_{\infty}(\tau \leq k)$ (where π_k is a prior distribution over the true changepoint ξ); this metric represents the probability of a false alarm (related to the ARL). The goal as described in their work is to design a method whose PFA is bounded by α and whose detection delay is minimal, plus a term which is $o(1)$ as $\alpha \downarrow 0$. This goal is stricter than control over the FDR, since it bounds the probability that there is ever a false alarm.

Chen et al. (2020) is the first to propose methods for multi-stream change detection that control the FDR instead of the FWER (which can be difficult to control in general). They present three methods, each of which have asymptotic guarantees on the FDR and average detection delay. However, none of these methods simultaneously provide control over the average run length.

Note that none of the above works treat the FDR and ARL simultaneously. For more examples of such works, see Chen and Li (2023), Eriksson and Olofsson (2018), Wang and Mei (2015), and Xie and Siegmund (2013). We will now show that it is impossible to achieve nontrivial FDR or FWER when the ARL is finite, which then leads into our proposed metric (EOP) and general algorithms to control it.

4 Simultaneous control over Type I error and ARL

We begin with several impossibility results to motivate our discussion of the new EOP metrics for simultaneous control over the Type I error. These impossibility phenomena are fundamental, but relatively straightforward (and even obvious in hindsight). Nevertheless, they do not appear to have been articulated before, and so we develop carefully and generally below.

4.1 Impossibility of achieving nontrivial worst-case Type I error

Suppose we are in the multi-stream change detection problem as described in Section 2. Recall that $\text{FDR}(\varphi, \xi, \tau)$ is the expected false discovery proportion of the change monitoring

algorithm φ if stopped at time τ with configuration ξ , that the global null corresponds to the configuration where no change occurs in any stream ($\xi^{(k)} = \infty$ for all streams $k \in [K]$), and that $\tau_\eta^*(\varphi)$ is the first time that η changes are declared.

Theorem 4.1 (Relating the FDR and ARL). *Suppose we have a configuration ξ and consider a multi-stream change monitoring algorithm φ for which $\text{ARL}_1(\varphi) = \mathbb{E}_\infty[\tau_1^*(\varphi)] < \infty$. If \mathcal{T} denotes the set of all stopping times with respect to \mathcal{F} , then we have:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \text{FDR}(\varphi, \xi, \tau) = \text{FDR}(\varphi, \xi_G, \tau_1^*(\varphi)) = 1,$$

Hence, we also have:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \text{FWER}(\varphi, \xi, \tau) = \text{FWER}(\varphi, \xi_G, \tau_1^*(\varphi)) = 1.$$

Proof. Suppose that we are in the scenario of the global null. Markov's inequality gives:

$$\mathbb{P}(\tau_1^*(\varphi) \geq (1 + \alpha) \text{ARL}_1(\varphi)) \leq \frac{1}{1 + \alpha}.$$

So with probability at least $\alpha/(1 + \alpha)$, we have $\tau_1^*(\varphi) \leq (1 + \alpha) \text{ARL}_1(\varphi) < \infty$. Conditioning on this event, we have:

$$\max_{1 \leq t \leq (1 + \alpha) \text{ARL}_1(\varphi)} \sum_{k=1}^K \varphi_t^{(k)} \geq \sum_{k=1}^K \varphi_{\tau_1^*(\varphi)}^{(k)} \geq 1 > 0.$$

Finally, it follows that $\max_{1 \leq t \leq (1 + \alpha) \text{ARL}_1(\varphi)} \text{FDP}(\varphi, t) = \text{FDP}(\varphi, \tau_1^*(\varphi)) = 1$ with probability at least $\alpha/(1 + \alpha)$, since under the global null we have $\xi^{(k)} = \infty$ for all streams $k \in [K]$. Furthermore, we find that $\sup_{\tau \in \mathcal{T}} \text{FDR}(\varphi, \xi_G, \tau) = \text{FDR}(\varphi, \xi_G, \tau_1^*(\varphi)) = 1$ because $\text{FDP}(\varphi, \tau_1^*(\varphi)) = 1$ on the event $\{\tau_1^*(\varphi) < \infty\}$.

The FWER claim follows since the FWER is bounded below by the FDR. \square

In particular, no change detection algorithm (φ, τ) can be guaranteed to have a nontrivial FDR (uniformly over stopping times τ) when $\text{ARL}_1(\varphi)$ is finite, under the global null. In fact, the same is true of the FWER. We now state a similar result for the per-family error rate:

Theorem 4.2 (Relating the PFER and ARL). *Fix $1 \leq \eta \leq K$. Suppose we have a configuration ξ and consider a multi-stream change monitoring algorithm φ for which $\text{ARL}_\eta(\varphi) = \mathbb{E}_\infty[\tau_\eta^*(\varphi)] < \infty$. If \mathcal{T} denotes the set of all stopping times with respect to \mathcal{F} , then we have:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \text{PFER}(\varphi, \xi, \tau) \geq \text{PFER}(\varphi, \xi_G, \tau_\eta^*(\varphi)) \geq \eta.$$

Proof. Suppose that we are in the scenario of the global null. Markov's inequality gives:

$$\mathbb{P}(\tau_\eta^*(\varphi) \geq (1 + \alpha) \text{ARL}_\eta(\varphi)) \leq \frac{1}{1 + \alpha}.$$

So with probability at least $\alpha/(1 + \alpha)$, we have $\tau_\eta^*(\varphi) \leq (1 + \alpha) \text{ARL}_1(\varphi) < \infty$. Conditioning on this event, we have:

$$\max_{1 \leq t \leq (1 + \alpha) \text{ARL}_\eta(\varphi)} \sum_{k=1}^K \varphi_t^{(k)} \geq \sum_{k=1}^K \varphi_{\tau_\eta^*(\varphi)}^{(k)} \geq \eta.$$

However, recall that under the global null, we have $\xi^{(k)} = \infty$ for all streams k . Then, this forces the following inequality with probability at least $\alpha/(1 + \alpha)$:

$$\max_{1 \leq t \leq (1 + \alpha) \text{ARL}_\eta(\varphi)} \sum_{k=1}^K \varphi_t^{(k)} \geq \sum_{k=1}^K \varphi_{\tau_\eta^*(\varphi)}^{(k)} \geq \eta.$$

Finally, because $\text{PFER}(\varphi, \xi_G, \tau_\eta^*(\varphi)) \geq \eta$ on the event $\{\tau_\eta^*(\varphi) < \infty\}$, it follows that:

$$\sup_{\tau \in \mathcal{T}} \text{PFER}(\varphi, \xi_G, \tau) \geq \text{PFER}(\varphi, \xi_G, \tau_\eta^*(\varphi)) \geq \eta. \quad \square$$

Intuitively, if we have a finite stopping time with $\eta \geq 1$ detections under the global null, then the PFER at that stopping time must be at least η and the FDR must be 1 (since any detection is an incorrect). Furthermore, the stopping times used in our impossibility theorems are natural stopping times to use in practice: “the first time to η detections”. Hence, any reasonable algorithm which hopes to control the Type I error cannot have finite ARL.

In [Appendix A](#), we show that (similarly to the Type I error) the CCD is related to the ARL. Since we cannot ask for the Type I error to be small when the ARL is finite, we would like new metrics which somehow simultaneously control the ARL and the Type I error. However, we will show that if we allow the ARL to be infinite, we can obtain universal Type I error control.

4.2 New metric: error over patience (EOP)

Definition 4.1 (Error over patience (EOP)). Fix a filtration \mathcal{F} and a sequential change monitoring algorithm φ , and let \mathcal{T} denote the set of stopping times with respect to \mathcal{F} . The *error over patience for FDR, FWER and PFER* are respectively defined as:

$$\begin{aligned} \text{EOP}_{\text{FDR}}(\varphi) &= \sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{FDR}(\varphi, \xi, \tau)}{\mathbb{E}[\tau]}, \\ \text{EOP}_{\text{FWER}}(\varphi) &= \sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{FWER}(\varphi, \xi, \tau)}{\mathbb{E}[\tau]}, \\ \text{EOP}_{\text{PFER}}(\varphi) &= \sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{PFER}(\varphi, \xi, \tau)}{\mathbb{E}[\tau]}. \end{aligned}$$

We will typically seek to upper bound the EOP at a predefined level $\alpha \in (0, 1)$. One can intuitively think of the regime when $\mathbb{E}[\tau]$ is small (when we stop the change monitoring algorithm quickly) as “low-patience”. Similarly, one can think of the regime when $\mathbb{E}[\tau]$ is large (when we stop the algorithm slowly) as “high-patience”. When a stopping time is impatient, these metrics insist that the Type I error rate must be low; conversely, when a stopping time is patient, the metrics relax their desired control over Type I error. However, note that any bound on these metrics implies a bound which is *uniform* over the choice of stopping time; we say that algorithms which bound these quantities are “anytime-valid”. Now, we will construct algorithms to control these metrics using e-detectors.

Upper bounding the EOP by α implies a lower bound on the ARL of $1/\alpha$. The reader may observe this in two steps: first, instantiate the bound under the global null where \mathbb{E} is \mathbb{E}_∞ , and second, consider the specific stopping time $\tau_1^*(\varphi)$. Recalling that $\text{ARL}_1(\varphi) = \mathbb{E}_\infty[\tau_1^*(\varphi)]$ yields the claim.

The above argument also shows that upper bounding the EOP by α is *much stronger* than just ARL control. Indeed, ARL control is only relevant under the global null, while we instead will seek to control the EOP under any configuration of null streams. Further, upper bounding the supremum over stopping times is significantly stronger than considering the specific time $\tau_1^*(\varphi)$.

However, it is also apparent that upper bounding the EOP by α is much weaker than controlling the Type I error at level α . As has already been proved, the latter condition cannot be guaranteed when the ARL is finite, and so this weakening of the Type I error control appears to be a necessary compromise.

5 Background: e-detectors and the e-BH procedure

Here, we give some useful background for the construction of our algorithm. In the following definitions, one should think of \mathcal{P}_0 as the (possibly composite) null hypothesis. In the context of change detection, one should think of \mathcal{P}_0 as the set of all global distributions \mathbb{P} such that $\mathbb{P}_0^{(k)} \in \mathcal{P}_0^{(k)}$, $\mathbb{P}_1^{(k)} \in \mathcal{P}_1^{(k)}$, and $\xi^{(k)} = \infty$ for $k \in [K]$. Furthermore, in the context of change detection, one should think of \mathcal{F} as the global (cross-stream) filtration.

5.1 Change detection using e-detectors

We first begin by defining e-processes, the building blocks of e-detectors. We do so in the single stream setting; when there are multiple streams, one can apply these definitions separately on a per-stream basis.

Definition 5.1 (e-processes). A process $(E_t)_{t \geq 0}$ is called an *e-process* for a set of distributions \mathcal{P}_0 (with respect to a filtration \mathcal{F}) if it is a nonnegative \mathcal{F} -adapted process satisfying $\mathbb{E}_{\mathbb{P}}[E_\tau] \leq$

1 for all stopping times τ (with respect to \mathcal{F}) and distributions $\mathbb{P} \in \mathcal{P}_0$.

Note that an e-process is a generalization of a nonnegative supermartingale, which one can think of as a wealth process in an unfair game (where the odds are not in your favor). In this context, one can think of an e-process as accumulating evidence against the null hypothesis (there is no change in a particular stream). By Ville's martingale inequality, it follows from this definition that for all $\alpha > 0$ and all $\mathbb{P} \in \mathcal{P}_0$:

$$\mathbb{P} \left(\sup_{t \in \mathbb{N}} E_t \geq \frac{1}{\alpha} \right) \leq \alpha.$$

In particular, the e-process is uniformly bounded with high probability under the null. The goal is to create an e-process which grows quickly under the alternative hypothesis for a powerful test. See [Ramdas et al. \(2023\)](#) for more details on e-processes.

Using e-processes, we are now ready to construct e-detectors.

Definition 5.2 (*j*-delay e-processes). A process $(\Lambda_t^{(j)})_{t \geq 0}$ is called a *j*-delay e-process² for a set of distributions \mathcal{P}_0 (with respect to a filtration \mathcal{F}) if it satisfies $\Lambda_t^{(j)} = 1$ for $1 \leq t \leq j - 1$ and if $(\Lambda_t^{(j)})_{t=j}^\infty$ is an e-process for \mathcal{P}_0 (with respect to $(\mathcal{F}_t)_{t=j}^\infty$).

Note that a *j*-delay e-process is also an e-process with respect to \mathcal{F} .

Definition 5.3 (e-detectors). A process $(M_t)_{t \geq 0}$ is called an *e-detector* for a set of distributions \mathcal{P}_0 (with respect to a filtration \mathcal{F}) if it is a nonnegative \mathcal{F} -adapted process satisfying $\mathbb{E}_{\mathbb{P}}[M_\tau] \leq \mathbb{E}_{\mathbb{P}}[\tau]$ for all \mathcal{F} -stopping times τ and for all $\mathbb{P} \in \mathcal{P}_0$.

In the context of multi-stream change detection, an e-detector for \mathcal{F} in stream $k \in [K]$ is a nonnegative \mathcal{F} -adapted process which satisfies $\mathbb{E}_{\mathbb{P}}[M_\tau] \leq \mathbb{E}_{\mathbb{P}}[\tau]$ for all \mathcal{F} -stopping times τ and global distributions \mathbb{P} with $\xi^{(k)} = \infty$.

Note that the e-detector is defined by a bound on how quickly the process $(M_t)_{t=1}^\infty$ can grow when there is no change. The e-detector can intuitively be thought of as a generalization of the popular CUSUM and Shiryaev-Roberts (SR) procedures for change detection. If the pre-change and post-change distributions are known (and have densities p_0 and p_1 respectively with respect to some common reference measure), then the CUSUM procedure corresponds to the following e-detector (with $M_0 = 0$):

$$M_{t+1} = \frac{p_1(X_{t+1})}{p_0(X_{t+1})} \max\{M_t, 1\}.$$

Similarly, the SR procedure corresponds to using the following e-detector (with $M_0 = 0$):

$$M_{t+1} = \frac{p_1(X_{t+1})}{p_0(X_{t+1})} (M_t + 1).$$

²In [Shin et al. \(2023\)](#), the authors use the term e_j -process for a *j*-delay e-process.

More generally, here is how to construct e-detectors using e-processes: given j -delay e-processes $\Lambda_t^{(j)}$ for $j \in \mathbb{N}$, one can define the SR e-detector:

$$M_t^{\text{SR}} = \sum_{j=1}^t \Lambda_t^{(j)}$$

Similarly, one can define the CUSUM e-detector:

$$M_t^{\text{CU}} = \max_{1 \leq j \leq t} \Lambda_t^{(j)}$$

Both of these are e-detectors that in fact reduce to the earlier SR and CUSUM formulae when $\Lambda_t^{(j)}$ is the likelihood ratio of p_1 to p_0 from time j to t . In particular, the problem of constructing e-detectors comes down to constructing e-processes. For more details, including how to construct e-detectors for a variety of processes and how to compute them more efficiently, see [Shin et al. \(2023\)](#). For more discussion on the construction of e-processes for a large variety of composite null hypotheses, see [Ramdas et al. \(2023\)](#).

As such, an e-detector by itself does not involve making a decision at any stopping time to declare a change — it is simply a nonnegative process that quantifies evidence of a change. One would typically declare a change when the e-detector crosses some threshold c_α , which is chosen so that the ARL is (at least) $1/\alpha$.

In simple settings, such as when \mathcal{P}_0 is simple (and thus known), c_α can be accurately determined using simulations. One advantage of using e-detectors (over standard methods for change detection like CUSUM or SR) is that e-detectors can be constructed for nonparametric change detection when \mathcal{P}_0 is composite and potentially very complicated. In such cases, it may be hard to run simulations to calculate c_α numerically, and one can resort to the backup choice of $c_\alpha = 1/\alpha$, which is always a valid (though conservative) choice of threshold.

A few examples of pre-change classes \mathcal{P}_0 for which one can construct e-detectors are: a) distributions where likelihood ratios with \mathcal{P}_1 are well-defined, b) distributions with a negative mean, c) distributions over a pair (used for two-sample testing about equality of distributions), d) symmetric distributions, e) log-concave distributions, f) exchangeable distributions, g) product distributions (used for tests about independence). This is by no means an exhaustive list, and a more thorough discussion of this topic can be found in [Shin et al. \(2023\)](#). We will see that another advantage of using e-detectors is that our methods can be applied under very general dependence structures between the streams. Next, we will construct algorithms which provide control of the Type I error over patience (as defined in [Section 4.2](#)).

5.2 The e-BH procedure

The e-BH (e-Benjamini Hochberg) procedure described in [Wang and Ramdas \(2022\)](#) provides a method for false discovery rate control using e-values. The method described in this paper

(the e-d-BH procedure) is an extension of the e-BH procedure to multi-stream sequential change detection. The e-BH procedure is in turn related to the popular Benjamini-Hochberg method for controlling the FDR (Benjamini and Hochberg, 1995).

Definition 5.4 (e-variables). A nonnegative random variable e is an *e-variable* for \mathcal{P} if $\mathbb{E}[E] \leq 1$, where the expectation can be taken with respect to any distribution $\mathbb{P} \in \mathcal{P}$. A realized value of an e-variable (after looking at the data) is called an *e-value*.

Note that the e-variable is useful for the same reason the e-process is useful; it is a measure of evidence against the null. By Markov's inequality, we have for all $\mathbb{P} \in \mathcal{P}$ and $\alpha > 0$:

$$\mathbb{P}\left(E \geq \frac{1}{\alpha}\right) \leq \alpha.$$

Suppose you have K null hypotheses that we are testing, denoted H_1, H_2, \dots, H_K . Fix $\alpha > 0$; we are going to control the false detection rate at level α . The simplest version of the e-BH procedure can then be described as follows. Suppose we have e-values e_i for $1 \leq i \leq K$ associated with the hypotheses H_i . Then, let $e_{[k]}$ be the k th order statistic of $(e_i)_{i=1}^K$, sorted from largest to smallest. For instance, $e_{[1]}$ will be the largest e-value. Then, we reject the hypotheses associated with the largest k^* e-values, where:

$$k^* = \max\left\{k \in [K] : \frac{ke_{[k]}}{K} \geq \frac{1}{\alpha}\right\}.$$

Theorem 5.1 (FDR guarantee of the e-BH procedure). *The e-BH procedure controls the FDR (expected number of false rejections to total rejections) at level $\alpha k_0/K$, where k_0 is the number of null hypotheses which are true.*

A full proof of this statement, as well as a full discussion of the e-BH procedure (boosting the e-values, etc.), can be found in Wang and Ramdas (2022).

6 The e-detector Benjamini-Hochberg (e-d-BH) procedure

Here, we introduce a new algorithm for multi-stream change monitoring, which we call the e-detector Benjamini-Hochberg (e-d-BH) procedure.

Algorithm 1: e-detector Benjamini-Hochberg procedure (e-d-BH procedure)

Input: $(\alpha_t)_{t=1}^\infty \in (0, 1)^\mathbb{N}$, $(M_t^{(k)})_{t=1}^\infty$ (an e-detector for stream k where $k \in [K]$)

Output: $(\varphi_t^{(k)})_{t=1}^\infty$ for $k \in [K]$, declarations of changes in stream k at time t

1 $t \leftarrow 1$

2 **while** $t \geq 1$ **do**

3 $M_t^{[0]} \leftarrow 0$

4 **for** $k \in [K]$ **do**

5 $M_t^{[k]} \leftarrow k$ th order statistic of $(M_t^{(i)})_{i=1}^K$, sorted from largest to smallest

6 **end**

7 $k_t^* \leftarrow \max \left\{ 0 \leq k \leq K : M_t^{[k]} \geq \frac{K}{k\alpha_t} \right\}$

8 $S_t \leftarrow$ stream indices k corresponding to the largest k_t^* values of $M_t^{(k)}$

9 $\varphi_t^{(k)} \leftarrow \mathbf{1}_{k \in S_t}$

10 $t \leftarrow t + 1$

11 **end**

Now, we explore several guarantees of this algorithm.

6.1 Upper-bounding EOP_{FDR} using the e-d-BH procedure

First, suppose that $\alpha_t = \alpha \in (0, 1)$ is a constant sequence. Then, we have the following guarantee on the performance of [Algorithm 1](#), where $\text{EOP}_{\text{FDR}}(\varphi)$ is taken with respect to \mathcal{F} .

Theorem 6.1 (e-d-BH bounds the error over patience for FDR). *Suppose $\alpha_t = \alpha \in (0, 1)$ for all $t \in \mathbb{N}$ and for $k \in [K]$, suppose that $(M_t^{(k)})_{t=1}^\infty$ is an e-detector with respect to the global filtration \mathcal{F} . Then, if \mathcal{T} denotes the set of stopping times with respect to \mathcal{F} , [Algorithm 1](#) satisfies the following guarantee for any constant sequence $\alpha_t = \alpha \in (0, 1)$:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{FDR}(\varphi, \xi, \tau)}{\left(\sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1} \leq \frac{\alpha}{K}.$$

In particular, it follows that:

$$\text{EOP}_{\text{FDR}}(\varphi) \leq \alpha.$$

Notice that one condition for [Theorem 6.1](#) is that $M_t^{(k)}$ must be an e-detector for the global filtration \mathcal{F} ; we discuss the choice of filtration further in [Section 9](#). Further, note that we could have defined patience as $\left(\frac{1}{K} \sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1$, but we chose to keep the current definition for interpretability.

Proof. Fix $\alpha \in (0, 1)$ and any stopping time τ with respect to \mathcal{F} . Now, we can explicitly bound the FDR at time τ (since $\mathbf{1}_{x \geq 1} \leq x$ for $x \geq 0$):

$$\begin{aligned} \text{FDR}(\varphi, \xi, \tau) &= \mathbb{E} \left[\frac{\sum_{k=1}^K \varphi_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}}{\left(\sum_{k=1}^K \varphi_\tau^{(k)} \right) \vee 1} \right] \\ &= \sum_{k=1}^K \mathbb{E} \left[\frac{\mathbf{1}_{M_\tau^{(k)} k_\tau^* \alpha / K \geq 1} \mathbf{1}_{\xi^{(k)} > \tau}}{k_\tau^* \vee 1} \right] \\ &\leq \frac{\alpha}{K} \sum_{k=1}^K \mathbb{E} \left[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau} \left(\frac{k_\tau^*}{k_\tau^* \vee 1} \right) \right] \\ &\leq \frac{\alpha}{K} \sum_{k=1}^K \mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}]. \end{aligned}$$

Define $M_0^{(k)} = 0$ for $k \in [K]$. Now, considering the events $\{\xi^{(k)} > \tau\}$ and $\{\xi^{(k)} \leq \tau\}$, we have the inequality:

$$\mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}] \leq \mathbb{E}[M_{\tau \wedge (\xi^{(k)} - 1)}^{(k)}].$$

By the definition of the e-detector (because $\tau \wedge (\xi^{(k)} - 1)$ is a stopping time), we obtain:

$$\mathbb{E}[M_{\tau \wedge (\xi^{(k)} - 1)}^{(k)}] \leq \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \leq \mathbb{E}[\tau].$$

Putting the pieces together, we obtain:

$$\text{FDR}(\varphi, \xi, \tau) \leq \frac{\alpha}{K} \sum_{k=1}^K \mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}] \leq \frac{\alpha}{K} \sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \leq \alpha \mathbb{E}[\tau].$$

Rearranging and taking a supremum over stopping times τ and configurations ξ gives the desired result. \square

The proof of [Theorem 6.1](#) essentially shows the stronger result that [Algorithm 1](#) satisfies:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \left\{ \mathbb{E} \left[\sup_{\alpha \in (0, 1)} \frac{\sum_{k=1}^K \varphi_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}}{\alpha \left(\left(\sum_{k=1}^K \varphi_\tau^{(k)} \right) \vee 1 \right)} \right] \frac{1}{\left(\sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1} \right\} \leq \frac{1}{K}.$$

Note that the detections $\varphi_\tau^{(k)}$ implicitly depend on α . This means that for any post-hoc choice of $\alpha \in (0, 1)$, we retain a nontrivial guarantee.

We end with a short but important observation that under the global null, one can show that e-d-BH controls the ARL.

Corollary 6.1.1. *For any constant sequence $\alpha_t = \alpha \in (0, 1)$, let $\tau_1^*(\varphi)$ denote the first time that [Algorithm 1](#) declares a change. Under the global null ($\xi^{(k)} = \infty$ for $k \in [K]$), [Algorithm 1](#) satisfies:*

$$\text{ARL}_1(\varphi) = \mathbb{E}_\infty[\tau_1^*(\varphi)] \geq \frac{1}{\alpha}.$$

Proof. Recall that $\text{FDR}(\varphi, \xi, \tau_1^*(\varphi)) = 1$ under the global null. Then, this result follows from [Theorem 6.1](#) by letting $\tau = \tau_1^*(\varphi)$. \square

6.2 Universal FDR control using the e-d-BH procedure

In this section, we will show that the e-d-BH procedure can be used to provide universal control over the FDR if we forfeit ARL control. Here, we let $(\alpha_t)_{t=1}^\infty \in (0, 1)^\mathbb{N}$ be an arbitrary sequence.

Theorem 6.2 (e-d-BH gives universal FDR control). *Recalling that $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$, [Algorithm 1](#) satisfies the following guarantee:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{FDR}(\varphi, \xi, t)}{t\alpha_t |\mathcal{H}_0(t)|} \leq \frac{1}{K}.$$

In particular, because $\sup_{t \in \mathbb{N}} |\mathcal{H}_0(t)| \leq K$, it follows that:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{FDR}(\varphi, \xi, t)}{t\alpha_t} \leq 1.$$

Proof. Fix a sequence $(\alpha_t)_{t=1}^\infty \in (0, 1)^\mathbb{N}$ and any fixed time $t \in \mathbb{N}$. Now, we can explicitly bound the FDR at the time t :

$$\begin{aligned} \text{FDR}(\varphi, \xi, t) &= \mathbb{E} \left[\frac{\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} > t}}{\left(\sum_{k=1}^K \varphi_t^{(k)}\right) \vee 1} \right] \\ &= \mathbb{E} \left[\frac{\sum_{k \in \mathcal{H}_0(t)} \mathbf{1}_{M_t^{(k)} \geq K/(k_t^* \alpha_t)}}{k_t^* \vee 1} \right] \\ &= \sum_{k \in \mathcal{H}_0(t)} \mathbb{E} \left[\frac{\mathbf{1}_{M_t^{(k)} \geq K/(k_t^* \alpha_t)}}{k_t^* \vee 1} \right]. \end{aligned}$$

Now, notice that we always have $M_t^{(k)}(k_t^* \alpha_t)/K \geq \mathbf{1}_{M_t^{(k)} \geq K/(k_t^* \alpha_t)}$, since $M_t^{(k)}(k_t^* \alpha_t)/K$ is nonnegative. Hence, we obtain the bound:

$$\sum_{k \in \mathcal{H}_0(t)} \mathbb{E} \left[\frac{\mathbf{1}_{M_t^{(k)} \geq K/(k_t^* \alpha_t)}}{k_t^* \vee 1} \right] \leq \sum_{k \in \mathcal{H}_0(t)} \mathbb{E} \left[\frac{M_t^{(k)}(k_t^* \alpha_t)}{(k_t^* \vee 1)K} \right] \leq \frac{\alpha_t}{K} \sum_{k \in \mathcal{H}_0(t)} \mathbb{E}[M_t^{(k)}].$$

But by the definition of an e-detector, we have $\mathbb{E}[M_t^{(k)}] \leq t$ for all $k \in \mathcal{H}_0(t)$. Hence, we obtain the final bound:

$$\text{FDR}(\varphi, \xi, t) \leq \frac{\alpha_t}{K} \sum_{k \in \mathcal{H}_0(t)} \mathbb{E}[M_t^{(k)}] \leq \frac{t\alpha_t |\mathcal{H}_0(t)|}{K}.$$

Rearranging and taking a supremum over $t \in \mathbb{N}$ and $\xi \in \mathbb{N}^K$ gives the desired result. \square

Corollary 6.2.1. Let $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$. Choosing $\alpha_t = \alpha/t$ for some $\alpha \in (0, 1)$ in [Algorithm 1](#) gives uniform FDR control for all $t \in \mathbb{N}$:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{FDR}(\varphi, \xi, t)}{|\mathcal{H}_0(t)|} \leq \frac{\alpha}{K}.$$

In particular, because $\sup_{t \in \mathbb{N}} |\mathcal{H}_0(t)| \leq K$, it follows that:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \text{FDR}(\varphi, \xi, t) \leq \alpha.$$

This follows immediately from [Theorem 6.2](#) by choosing $\alpha_t = \alpha/t$. Since this algorithm provides universal control over the FDR, $\text{ARL}_1(\varphi) = \infty$ is forced due to [Theorem 4.1](#).

7 The e-d-Bonferroni procedure

Here, we introduce a new algorithm for multi-stream change monitoring, which we call the e-d-Bonferroni procedure.

Algorithm 2: e-detector Bonferroni procedure (e-d-Bonferroni procedure)

Input: $(\beta_t)_{t=1}^\infty \in (0, \infty)^\mathbb{N}$, $(M_t^{(k)})_{t=1}^\infty$ (an e-detector for stream k where $k \in [K]$)

Output: $(\varphi_t^{(k)})_{t=1}^\infty$ for $k \in [K]$, declarations of changes in stream k at time t

1 $t \leftarrow 1$

2 **while** $t \geq 1$ **do**

3 $M_t^{[0]} \leftarrow 0$

4 **for** $k \in [K]$ **do**

5 $M_t^{[k]} \leftarrow k$ th order statistic of $(M_t^{(i)})_{i=1}^K$, sorted from largest to smallest

6 **end**

7 $k_t^* \leftarrow \max \left\{ 0 \leq k \leq K : M_t^{[k]} \geq \frac{K}{\alpha_t} \right\}$

8 $S_t \leftarrow$ stream indices k corresponding to the largest k_t^* values of $M_t^{(k)}$

9 $\varphi_t^{(k)} \leftarrow \mathbf{1}_{k \in S_t}$

10 $t \leftarrow t + 1$

11 **end**

Now, we explore several guarantees of this algorithm.

7.1 Upper-bounding EOP_{PFER} using the e-d-Bonferroni procedure

We have the following guarantee on the performance of [Algorithm 2](#), where $\text{EOP}_{\text{PFER}}(\varphi)$ is taken with respect to \mathcal{F} .

Theorem 7.1 (e-d-Bonferroni bounds the error over patience for PFER). *First, suppose that $\beta_t = \beta > 0$ is a constant sequence. Furthermore, suppose that $(M_t^{(k)})_{t=1}^\infty$ is an e-detector with respect to the global filtration \mathcal{F} for $k \in [K]$. Then, if \mathcal{T} denotes the set of stopping times with respect to \mathcal{F} , [Algorithm 2](#) satisfies the following guarantee for any $\beta > 0$:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{PFER}(\varphi, \xi, \tau)}{\left(\sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1} \leq \frac{\beta}{K}.$$

In particular, it follows that:

$$\text{EOP}_{\text{PFER}}(\varphi) \leq \beta.$$

Notice that one condition for [Theorem 7.1](#) is that $M_t^{(k)}$ must be an e-detector for the global filtration \mathcal{F} ; we discuss the choice of filtration further in [Section 9](#). Further, note that we could have defined patience as $\left(\frac{1}{K} \sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1$, but we chose to keep the current definition for interpretability.

Proof. Fix $\beta > 0$ and any stopping time τ with respect to \mathcal{F} . Now, we can explicitly bound the PFER at time τ (since $\mathbf{1}_{x \geq 1} \leq x$ for $x \geq 0$):

$$\begin{aligned} \text{PFER}(\varphi, \xi, \tau) &= \mathbb{E} \left[\sum_{k=1}^K \varphi_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau} \right] \\ &\leq \sum_{k=1}^K \mathbb{E}[\mathbf{1}_{M_\tau^{(k)} \geq K/\beta} \mathbf{1}_{\xi^{(k)} > \tau}] \\ &\leq \frac{\beta}{K} \sum_{k=1}^K \mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}]. \end{aligned}$$

Define $M_0^{(k)} = 0$ for $k \in [K]$. Now, considering the events $\{\xi^{(k)} > \tau\}$ and $\{\xi^{(k)} \leq \tau\}$, we have the inequality:

$$\mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}] \leq \mathbb{E}[M_{\tau \wedge (\xi^{(k)} - 1)}^{(k)}].$$

By the definition of the e-detector (because $\tau \wedge (\xi^{(k)} - 1)$ is a stopping time), we obtain:

$$\mathbb{E}[M_{\tau \wedge (\xi^{(k)} - 1)}^{(k)}] \leq \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \leq \mathbb{E}[\tau].$$

Putting the pieces together, we have the following inequality:

$$\text{PFER}(\varphi, \xi, \tau) \leq \frac{\beta}{K} \sum_{k=1}^K \mathbb{E}[M_\tau^{(k)} \mathbf{1}_{\xi^{(k)} > \tau}] \leq \beta \mathbb{E}[\tau].$$

Rearranging and taking a supremum over stopping times τ and configurations ξ gives the desired result. \square

In fact, the proof of [Theorem 7.1](#) essentially shows the stronger result that [Algorithm 2](#) satisfies:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \left\{ \mathbb{E} \left[\sup_{\beta > 0} \frac{1}{\beta} \sum_{k=1}^K \varphi_{\tau}^{(k)} \mathbf{1}_{\xi^{(k)} > \tau} \right] \frac{1}{\left(\sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1} \right\} \leq \frac{1}{K}.$$

Note that the detections $\varphi_{\tau}^{(k)}$ implicitly depend on β . This means that for any post-hoc choice of $\beta > 0$, we retain some reasonable guarantee in the form of [Theorem 7.1](#). As previously established in the FDR case, under the global null, one can prove that e-d-Bonferroni controls the ARL.

Corollary 7.1.1. *For any constant sequence $\beta_t = \beta \in (0, \infty)$, let $\tau_{\eta}^*(\varphi)$ denote the first time that we declare a change in at least η streams. Under the global null ($\xi^{(k)} = \infty$ for $k \in [K]$), [Algorithm 2](#) satisfies (for all $\beta > 0$):*

$$\text{ARL}_{\eta} = \mathbb{E}_{\infty}[\tau_{\eta}^*(\varphi)] \geq \frac{\eta}{\beta}.$$

Proof. Recall that $\text{PFER}(\varphi, \xi, \tau_{\eta}^*(\varphi)) \geq \eta$ under the global null. Then, this result follows from [Theorem 6.1](#) by letting $\tau = \tau_{\eta}^*(\varphi)$. \square

Corollary 7.1.2 (e-d-Bonferroni bounds the error over patience for FWER). *Under the same setting as [Theorem 7.1](#), [Algorithm 2](#) satisfies the following formal guarantee for any constant sequence $\beta_t = \beta \in (0, 1)$:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{\tau \in \mathcal{T}} \frac{\text{FWER}(\varphi, \xi, \tau)}{\left(\sum_{k=1}^K \mathbb{E}[\tau \wedge (\xi^{(k)} - 1)] \right) \vee 1} \leq \frac{\beta}{K}.$$

In particular, it follows that:

$$\text{EOP}_{\text{FWER}}(\varphi) \leq \beta.$$

This immediately follows from [Theorem 7.1](#), since the PFER bounds the FWER from above. Next, we will show that e-d-Bonferroni can be used to obtain uniform control over the PFER.

7.2 Universal PFER control using the e-d-Bonferroni procedure

In this section, we will show that the e-d-Bonferroni procedure can be used to provide universal control over the PFER if we forfeit ARL control. Here, we let $(\beta_t)_{t=1}^{\infty} \in (0, \infty)^{\mathbb{N}}$ be an arbitrary sequence.

Theorem 7.2 (e-d-Bonferroni gives universal PFER control). *First, recall that $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$. Then, [Algorithm 2](#) satisfies the following formal guarantee:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{PFER}(\varphi, \xi, t)}{t\beta_t |\mathcal{H}_0(t)|} \leq \frac{1}{K}.$$

In particular, since $\sup_{t \in \mathbb{N}} |\mathcal{H}_0(t)| \leq K$, it follows that:

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{PFER}(\varphi, \xi, t)}{t\beta_t} \leq 1.$$

Proof. Fix a sequence $(\beta_t)_{t=1}^\infty \in (0, \infty)^\mathbb{N}$ and any fixed time $t \in \mathbb{N}$. Recall that $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$. Now, we can explicitly bound the PFER at time t :

$$\begin{aligned} \text{PFER}(\varphi, \xi, t) &= \mathbb{E} \left[\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} > t} \right] \\ &= \mathbb{E} \left[\sum_{k \in \mathcal{H}_0(t)} \varphi_t^{(k)} \right] \\ &\leq \sum_{k \in \mathcal{H}_0(t)} \mathbb{P} \left(M_t^{(k)} \geq \frac{K}{\beta_t} \right). \end{aligned}$$

Using Markov's inequality, we obtain:

$$\sum_{k \in \mathcal{H}_0} \mathbb{P} \left(M_t^{(k)} \geq \frac{K}{\beta_t} \right) \leq \sum_{k \in \mathcal{H}_0} \frac{\beta_t \mathbb{E}[M_t^{(k)}]}{K}.$$

But by the definition of an e-detector, we have $\mathbb{E}[M_t^{(k)}] \leq t$ for all $k \in \mathcal{H}_0$. Hence, we obtain the final bound:

$$\text{PFER}(\varphi, \xi, t) \leq \sum_{k \in \mathcal{H}_0(t)} \frac{\beta_t \mathbb{E}[M_t^{(k)}]}{K} \leq \frac{t\beta_t |\mathcal{H}_0(t)|}{K}.$$

Rearranging and taking a supremum over $t \in \mathbb{N}$ and $\xi \in \mathbb{N}^K$ gives the desired result. \square

Corollary 7.2.1. *Let $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$. Choosing $\beta_t = \beta/t$ for some $\beta > 0$ in [Algorithm 2](#) gives uniform PFER control for all $t \in \mathbb{N}$:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{PFER}(\varphi, \xi, t)}{|\mathcal{H}_0(t)|} \leq \frac{\beta}{K}.$$

The proof follows directly from [Theorem 7.2](#) by choosing $\beta_t = \beta/t$. Since this algorithm provides universal control over the PFER, $\text{ARL}_1(\varphi) = \infty$ is forced due to [Theorem 4.2](#). Although e-d-Bonferroni can also provide universal FWER control, we now derive a modified version of the Holm procedure to obtain a less conservative bound on FWER.

8 The e-d-Holm procedure: universal FWER control

Here, we introduce a new algorithm for multi-stream change monitoring, which we call the e-d-Holm procedure. This algorithm is inspired by Holm's original procedure for controlling FWER in multiple testing problems, as described in [Holm \(1979\)](#). Note that e-d-Holm does not necessarily control the error over patience for FWER, but one may still use e-d-Bonferroni to control $\text{EOP}_{\text{FWER}}(\varphi)$ since PFER bounds FWER from above. The goal of this algorithm will be to provide a sharper universal control over the FWER than the guarantee provided by e-d-Bonferroni.

Algorithm 3: e-detector Holm procedure (e-d-Holm procedure)

Input: $(\alpha_t)_{t=1}^{\infty} \in (0, 1)^{\mathbb{N}}$, $(M_t^{(k)})_{t=1}^{\infty}$ (an e-detector for stream k where $k \in [K]$)
Output: $(\varphi_t^{(k)})_{t=1}^{\infty}$ for $k \in [K]$, declarations of changes in stream k at time t

```

1  $t \leftarrow 1$ 
2 while  $t \geq 1$  do
3    $M_t^{[0]} \leftarrow 0$ 
4   for  $k \in [K]$  do
5      $M_t^{[k]} \leftarrow k$ th order statistic of  $(M_t^{(i)})_{i=1}^K$ , sorted from largest to smallest
6   end
7    $k_t^* \leftarrow \max \left\{ 0 \leq k \leq K : \frac{M_t^{[i]}}{K-i+1} \geq \frac{1}{\alpha_t} \text{ for all } 1 \leq i \leq k \right\}$ 
8    $S_t \leftarrow$  stream indices  $k$  corresponding to the largest  $k_t^*$  values of  $M_t^{(k)}$ 
9    $\varphi_t^{(k)} \leftarrow \mathbf{1}_{k \in S_t}$ 
10   $t \leftarrow t + 1$ 
11 end

```

Here, we will show that the e-d-Holm procedure can be used to provide universal control over the FWER if we forfeit ARL control.

Theorem 8.1 (e-d-Holm gives universal FWER control). *Algorithm 3 satisfies the following formal guarantee:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \frac{\text{FWER}(\varphi, \xi, t)}{t\alpha_t} \leq 1.$$

Note that here, [Algorithm 3](#) depends on the choice of α_t .

Proof. Let $t \in \mathbb{N}$ be a fixed time and fix a sequence $\alpha_t \in (0, 1)^{\mathbb{N}}$. Define $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} > t\}$, and assume that $|\mathcal{H}_0(t)| \geq 1$ since otherwise the result is trivially true. Suppose that we have rejected a true hypothesis at time t ; namely, we have declared a

change in some stream where there was no change. Then, let $(s_t^{[1]}, \dots, s_t^{[K]})$ be the values $\{1, 2, \dots, K\}$, sorted by their mapped values through $k \mapsto M_t^{[k]}$ (from largest to smallest). For instance, $s_t^{[1]}$ would be the stream with the largest e-detector value at time t . In this case, let $k_0 = \min\{k \in [K] : s_t^{[k]} \in \mathcal{H}_0(t) \text{ and } M_t^{[k]}/(K - k + 1) \geq 1/\alpha_t\}$. In particular, if we have sorted the streams by their evidence values, k_0 is the first index corresponding to a stream with no change but for which our algorithm rejected the null.

Now, notice that streams $(s_t^{[1]}, \dots, s_t^{[k_0-1]})$ must have also rejected the null at time t , since their e-detector values are at least as large as that of stream $s_t^{[k_0]}$. By construction, this means that changes have occurred in all of these streams. Because there are $K - |\mathcal{H}_0(t)|$ streams with a change by time t , we have $k_0 - 1 \leq K - |\mathcal{H}_0(t)|$. Rearranging, this implies that:

$$\frac{1}{K - k_0 + 1} \leq \frac{1}{|\mathcal{H}_0(t)|}.$$

But now it follows by definition that:

$$\frac{1}{\alpha_t} \leq \frac{M_t^{[k_0]}}{K - k_0 + 1} \leq \frac{M_t^{[k_0]}}{|\mathcal{H}_0(t)|}.$$

So whenever there is any stream in which we falsely reject the null at time t , there always exists a stream $k \in \mathcal{H}_0(t)$ such that $\frac{M_t^{(k)}}{|\mathcal{H}_0(t)|} \geq \frac{1}{\alpha_t}$. But this means that we can bound the family-wise error rate at time t :

$$\text{FWER}(\varphi, \xi, t) \leq \mathbb{P} \left(\bigcup_{k \in \mathcal{H}_0(t)} \left\{ \frac{M_t^{(k)}}{|\mathcal{H}_0(t)|} \geq \frac{1}{\alpha_t} \right\} \right) \leq \sum_{k \in \mathcal{H}_0(t)} \mathbb{P} \left(\frac{M_t^{(k)}}{|\mathcal{H}_0(t)|} \geq \frac{1}{\alpha_t} \right).$$

By Markov's inequality, we have:

$$\sum_{k \in \mathcal{H}_0(t)} \mathbb{P} \left(\frac{M_t^{(k)}}{|\mathcal{H}_0(t)|} \geq \frac{1}{\alpha_t} \right) \leq \sum_{k \in \mathcal{H}_0(t)} \frac{\alpha_t \mathbb{E}[M_t^{(k)}]}{|\mathcal{H}_0(t)|}.$$

Recall that we have $\mathbb{E}[M_t^{(k)}] \leq t$ for all $k \in \mathcal{H}_0(t)$ by the definition of an e-detector. Therefore, we have:

$$\sum_{k \in \mathcal{H}_0(t)} \frac{\alpha_t \mathbb{E}[M_t^{(k)}]}{|\mathcal{H}_0(t)|} \leq \sum_{k \in \mathcal{H}_0(t)} \frac{t\alpha_t}{|\mathcal{H}_0(t)|} = t\alpha_t.$$

Rearranging and taking a supremum over $t \in \mathbb{N}$ and $\xi \in \mathbb{N}^K$ gives the desired result. \square

Corollary 8.1.1. *Choosing $\alpha_t = \alpha/t$ for some $\alpha \in (0, 1)$ in [Algorithm 3](#) gives uniform FWER control for all $t \in \mathbb{N}$:*

$$\sup_{\xi \in \mathbb{N}^K} \sup_{t \in \mathbb{N}} \text{FWER}(\varphi, \xi, t) \leq \alpha.$$

The proof follows directly from [Theorem 8.1](#) by choosing $\alpha_t = \alpha/t$. Since this algorithm provides universal control over the FWER, $\text{ARL}_1(\varphi) = \infty$ is forced due to [Theorem 4.1](#).

9 A more detailed discussion about dependence

In this section, we discuss several scenarios in which our algorithms can (or cannot) be used to provide guarantees when there is dependence across the K streams.

9.1 Subtleties about filtrations

As long as the e-detector for each stream is an e-detector with respect to the global filtration \mathcal{F} (not just with respect to $\mathcal{F}^{(k)}$), then our theorems on EOP control hold. If $\mathcal{F}^{(k)}$ was unspecified, we had assumed it to be the natural filtration generated by the data. As an important special case, if the streams are independent, then an e-detector with respect to $\mathcal{F}^{(k)}$ is also an e-detector with respect to \mathcal{F} . Here, we ask the question: could this condition also hold under some types of dependence? Can we provide simple examples when this condition does or does not hold?

Intuitively, our condition means that the aggregate data collected by time t from one stream does not contain information from the future of any other stream. In particular, it is alright for the streams to depend on each other arbitrarily, as long as the dependence structure always remains in the past. For instance, if we are simultaneously monitoring data from a group of sensors, we must assume that all streams are synchronized in order to attain EOP control (no sensor can “see into the future” of any other).

However, although this stronger condition is required for EOP control, it is not required for our algorithms to be sensible. In fact, all of our theorems about universal Type I error control ([Theorem 6.2](#), [Theorem 7.2](#), and [Theorem 8.1](#)) still hold without this condition. This is because fixed times are always stopping times, regardless of the choice of filtration.

9.2 Counterexample: when dependence breaks EOP control

For example, here is a concrete scenario that is disallowed in all of our theorems about EOP ([Theorem 6.1](#) and [Theorem 7.1](#)). Suppose that we are observing two streams $(X_t^{(1)})_{t=1}^\infty$ and $(X_t^{(2)})_{t=1}^\infty$, where $(X_t^{(1)})_{t=1}^\infty \sim \otimes_{t=1}^\infty \mathcal{N}(0, 1)$ and $X_t^{(2)} = X_{t+1}^{(1)}$ for $t \in \mathbb{N}$ (setting $\xi^{(k)} = \infty$ in all streams for simplicity). Furthermore, suppose for simplicity that \mathcal{F} is the natural filtration generated by the data:

$$\mathcal{F}_t = \sigma \left(\bigcup_{j=1}^t \{X_j^{(1)}, X_j^{(2)}\} \right).$$

Then, suppose we construct some e-detector $M_t^{(1)}$ for the first data stream. Even if $M_t^{(1)}$ is an e-detector with respect to $(\mathcal{F}_t^{(1)})_{t=1}^\infty$, it is not necessarily an e-detector with respect to $\mathcal{F} = (\mathcal{F}_{t+1}^{(1)})_{t=1}^\infty$. Since the second stream can “see into the future” of the first stream, the global filtration is more refined than the filtration in the first stream. Therefore, there

are more stopping times τ with respect to the global filtration \mathcal{F} than $\mathcal{F}^{(1)}$ alone, and the e-detector property ($\mathbb{E}[M_\tau^{(k)}] \leq \mathbb{E}[\tau]$) will not necessarily hold for all stopping times τ with respect to \mathcal{F} .

9.3 Positive examples: when dependence poses no threat

Here, we provide nontrivial examples with dependence for which our theorems about EOP (Theorem 6.1 and Theorem 7.1) do hold. In both of these examples, assume for simplicity that \mathcal{F} is the natural filtration generated by the data:

$$\mathcal{F}_t = \sigma \left(\bigcup_{j=1}^t \{X_j^{(1)}, X_j^{(2)}\} \right).$$

9.3.1 Gaussian mean change with unknown covariance

Suppose that we are observing $K = 2$ streams, which are such that $(X_t^{(1)}, X_t^{(2)}) | \mathcal{F}_{t-1} \sim \mathcal{N}(\mu_t, \Sigma_t)$. The pre-change class may be specified as, for example, $\mu_t \leq 0$, while the post-change class may be specified as $\mu_t > 0$ (the exact details of the mean are less important here, because the dependence is captured by Σ_t). Suppose that $\text{diag}(\Sigma_t) = (\sigma_1^2, \sigma_2^2)$ is known but the off-diagonal entries are unknown; in particular, the two streams may be dependent. Then, for any $\lambda \geq 0$ and $k \in \{1, 2\}$, the following is an e-detector with respect to the global filtration \mathcal{F} (not just $\mathcal{F}^{(k)}$):

$$M_t^{(k)} = \sum_{j=1}^t \exp \left(\lambda \sum_{s=j}^t X_s^{(k)} - \lambda^2 \frac{\sigma_k^2 (t-j+1)}{2} \right).$$

This is an SR e-detector (as defined in Section 5.1), since each summand is the exponential martingale associated to the running sum started at time j ; each summand is therefore a j -delay e-process. Despite the potentially unknown dependence between the streams, we can construct a nontrivial e-detector and apply our algorithms to achieve EOP control.

9.3.2 Nonparametric symmetry change with dependence

Suppose that we are observing $K = 2$ streams, which are such that $X_t^{(1)} \sim \mathcal{N}(0, 1)$ for all t (meaning that the first stream is i.i.d. standard Gaussian), while

$$(X_t^{(2)} | \mathcal{F}_{t-1}) \sim \mathcal{N}(0, 1) \mathbf{1}_{X_t^{(1)} \leq 0} + \text{Cauchy}(0, 1) \mathbf{1}_{X_t^{(1)} > 0}.$$

The above only specifies the pre-change class. For a sensible post-change class, one can simply shift the observations to the right by a constant μ (as in the previous example).

Now, since the pre-change (joint) distribution is symmetric (conditional on the past), the following is an e-process introduced in Ramdas et al. (2020) for $k \in \{1, 2\}$ with respect to \mathcal{F} (with $\Lambda_0 = 1$ and for any $\lambda \in [-1, 1]$):

$$\Lambda_{t+1}^{(k)} = \Lambda_t^{(k)} + \lambda \operatorname{sign}(X_t^{(k)}) \mathbf{1}_{X_t^{(k)} \neq 0}.$$

More generally, for any odd function $h : \mathbb{R} \rightarrow \mathbb{R}$ (recall that h is odd if $h(-x) = -h(x)$ for all $x \in \mathbb{R}$) such that $\sup_{x \in \mathbb{R}} |h(x)| \leq 1$, we can set:

$$\Lambda_{t+1}^{(k)} = \Lambda_t^{(k)} (1 + h(X_t^{(k)})).$$

Thus, we construct j -delay e-processes $\Lambda_t^{(k,j)}$ in each stream $k \in [K]$; recall that these are simply e-processes started at time $j \in \mathbb{N}$ (remaining at 0 until time j). We can then define the SR e-detector by:

$$M_t^{(k)} = \sum_{j=1}^t \Lambda_t^{(k,j)}.$$

Again, despite the dependence between the streams, we can instantiate a nontrivial e-detector and run our algorithms to achieve EOP control. Next, we will empirically verify our results using simulations.

10 Simulations

We run three distinct simulations, using our algorithms for multi-stream change detection in three settings: parametric Gaussian mean change, nonparametric symmetry testing, and nonparametric independence testing. Through these simulations, we verify that our algorithms control the EOP, and that detection delay does not suffer significantly through the use of these algorithms. All code for these simulations, including generic implementations of all relevant algorithms, can be found in the following GitHub repository:

<https://www.github.com/sanjitdp/multistream-change-detectors>.

10.1 Gaussian mean change

Consider a simple parametric change detection problem with $\mathcal{P}_0^{(k)} = \{\otimes_{t=1}^{\infty} \mathcal{N}(-\delta, 1)\}$ and $\mathcal{P}_1^{(k)} = \{\otimes_{t=1}^{\infty} \mathcal{N}(\delta, 1)\}$ for streams $k \in [K] = 50$ and a signal strength parameter $\delta > 0$. In this case, since the likelihood ratio is well-defined, we can define the Shiryaev-Roberts (SR) e-detector by $M_1 = 0$ and:

$$M_{t+1}^{(k)} = \exp\left(-\frac{1}{2} \left((X_t^{(k)} - \delta)^2 - (X_t^{(k)} + \delta)^2 \right)\right) (M_t^{(k)} + 1).$$

Note that we could have also used the CUSUM e-detector to arrive at very similar results (with $M_1 = 0$):

$$M_{t+1}^{(k)} = \exp\left(-\frac{1}{2}\left((X_t^{(k)} - \delta)^2 - (X_t^{(k)} + \delta)^2\right)\right) \max\{M_t^{(k)}, 1\}.$$

In the following experiments, we consider the SR e-detector. For some intuition on the SR e-detector, here is a plot of the e-detectors in each stream if the change occurs at time $\xi^{(k)} = 200$ for streams $k \in [K] = 1000$:




Figure 1: *SR e-detectors over time for detecting a Gaussian mean change at time 200 (y-axis is on a logarithmic scale).*

Now, suppose that $\xi^{(k)} = \infty$ for $k \in [K] = 1000$, so that we are in the scenario of the global null. A naive change detection algorithm would declare a change in stream k when $M_t^{(k)} \geq 1/\alpha$. We find that e-d-BH (setting $\alpha_t = \alpha = 0.001$) keeps the FDR at a much lower level than the naive algorithm, even in the long-run:




Figure 2: *FDR of the naive algorithm and e-d-BH for Gaussian mean change.*

We know from [Theorem 6.1](#) that e-d-BH theoretically keeps $\text{EOP}_{\text{FDR}}(\varphi)$ controlled at level α ; in fact, we observe empirically that this translates to nontrivial control on the FDR.

Similarly, although the naive algorithm provides almost no control over the FWER, e-d-Holm (setting $\alpha_t = \alpha = 0.001$) is able to keep the FWER non-trivially bounded away from 1:




Figure 3: *FWER of the naive algorithm and e-d-Holm for Gaussian mean change (note the different y-axis scales).*

Finally, setting $\beta_t = \beta = 10$ we see empirically that e-d-Bonferroni keeps the PFER controlled at a much lower level than the naive algorithm:




Figure 4: *PFER of the naive algorithm and e-d-Bonferroni for Gaussian mean change ($\beta_t = \beta = 10$).*

Next, suppose $\xi^{(k)} = 10$ for $k \in [K] = 1000$ and we set $\alpha_t = \alpha = 0.001$. We run the naive algorithm, e-d-BH, and e-d-Bonferroni 100 times, tracking the number of detections that they make at each timestep. Here, we plot the mean number of detections made at each timestep (across the 100 runs of the algorithm) for varying values of δ :




Figure 5: Mean detections of *e-d-BH*, *e-d-Bonferroni*, and the naive algorithm over time for a Gaussian mean change (with varying signal strength).

Hence, we see that our algorithms do not increase the detection delay too much, even compared to the naive algorithm. Despite the very small choice of $\alpha = 0.001$, we can see that our algorithms still only have a very small detection delay. Note that *e-d-Bonferroni* is more conservative than *e-d-BH*, which in turn is more conservative than the naive algorithm. As expected, the detection delay of all three methods decreases as the signal strength is increased.

Next, suppose that $\xi^{(k)} = 400$ only for streams $1 \leq k \leq 100$ and $\xi^{(k)} = \infty$ for streams $100 < k \leq K = 1000$; in particular, changes only occur in 100 streams. Suppose also that the signal strength is $\delta = 0.125$. Again, we plot the mean number of detections made at each timestep (across 5 runs of the algorithms, setting $\alpha_t = \alpha = 0.001$):




Figure 6: Mean detections of *e-d-BH*, *e-d-Bonferroni*, and the naive algorithm over time for a Gaussian mean change, with only 100 streams changing.

Hence, in exchange for the conservatism of *e-d-BH* and *e-d-Bonferroni*, we make significantly fewer false detections. Note that there is no stipulation that all changes must happen at the same time. In fact, when changes occur at different times, we sometimes observe a phenomenon called *piggybacking of evidence*, described in [Appendix B](#).

10.2 Nonparametric symmetry testing

Consider a nonparametric change detection problem where we would like to detect a change in symmetry, under the simplifying assumption that the observations are i.i.d. across time and independent across $K = 50$ streams. Recall that $\mathcal{M}(S)$ denotes the set of probability measures over S . Then, we can choose $\mathcal{P}_0^{(k)}$ as follows:

$$\mathcal{P}_0^{(k)} = \left\{ \otimes_{t=1}^{\infty} \mathbb{P}_0^{(k)} : \mathbb{P}_0^{(k)} \in \mathcal{M}(\mathbb{R}) \text{ is symmetric} \right\}.$$

On the other hand, we can choose $\mathcal{P}_1^{(k)}$ as follows:

$$\mathcal{P}_1^{(k)} = \left\{ \otimes_{t=1}^{\infty} \mathbb{P}_1^{(k)} : \mathbb{P}_1^{(k)} \in \mathcal{M}(\mathbb{R}) \text{ is asymmetric} \right\}.$$

Here, [Ramdas et al. \(2020\)](#) introduces a simple e-process for testing symmetry (with $M_1 = 1$):

$$E_{t+1}^{(k)} = E_t^{(k)} + \text{sign}(X_t^{(k)}) \mathbf{1}_{X_t^{(k)} \neq 0}.$$

Then, we construct j -delay e-processes $\Lambda_t^{(k,j)}$ in each stream $k \in [K]$; recall that these are simply e-processes started at time $j \in \mathbb{N}$ (remaining at 0 until time j). We can then define the SR e-detector by:

$$M_t^{(k)} = \sum_{j=1}^t \Lambda_t^{(k,j)}.$$

Similarly, we could have defined the CUSUM e-detector by:

$$M_t^{(k)} = \max_{1 \leq j \leq t} \Lambda_t^{(k,j)}.$$

In this simulation, we will consider the SR e-detector. For this simulation, we consider the pre-change distribution $\mathcal{N}(0, 1)$ and the post-change distribution $\mathcal{N}(1, 1)$ in all streams. Suppose that $\xi^{(k)} = 400$ for $k \in [K] = 50$; we plot the e-detectors for testing symmetry here:




Figure 7: *SR e-detectors over time for detecting a symmetry change at time 400.*

Next, we set $\alpha_t = \alpha = 0.001$. We run the naive algorithm, e-d-BH, and e-d-Bonferroni 100 times, tracking the number of detections that they make at each timestep. Here, we plot the mean number of detections made at each timestep (across the 100 runs of the algorithm):




Figure 8: *Mean detections of e-d-BH, e-d-Bonferroni, and the naive algorithm over time for a symmetry change.*

Note that we would expect the detection delay to be larger for symmetry testing than for Gaussian mean change detection, since nonparametric problems are generally much harder. Still, our algorithms do not increase the detection delay very much.

On the other hand, suppose that we only have $\xi^{(k)} = 400$ for streams $1 \leq k \leq 10$ but $\xi^{(k)} = \infty$ for streams $10 < k \leq K = 50$; in particular, there are only changes in 10 streams. Then, we obtain the following plot for the mean number of detections made at each timestep (across 100 runs of the algorithms, setting $\alpha_t = \alpha = 0.001$):




Figure 9: *Mean detections of e-d-BH, e-d-Bonferroni, and the naive algorithm over time for a symmetry change (with only 10 streams changing).*

Again, we see that in exchange for their conservatism, e-d-BH and e-d-Holm make far fewer false detections than the naive algorithm.

10.3 Nonparametric independence testing

Finally, consider a change detection problem where we would like to detect a change in the independence between coordinates of a pair, under the simplifying assumption that the observations are i.i.d. across time and independent across $K = 50$ streams (each stream being a pair of potentially dependent random variables). Recall that $\mathcal{M}(S)$ denotes the set of probability measures over S . Then, we can choose $\mathcal{P}_0^{(k)}$ as follows:

$$\mathcal{P}_0^{(k)} = \left\{ \otimes_{t=1}^{\infty} (\mathbb{P}_0^{(k,1)} \times \mathbb{P}_0^{(k,2)}) : \mathbb{P}_0^{(k,1)}, \mathbb{P}_0^{(k,2)} \in \mathcal{M}(\mathbb{R}) \right\}.$$

On the other hand, we can choose \mathcal{P}_1 as follows:

$$\mathcal{P}_1^{(k)} = \left\{ \otimes_{t=1}^{\infty} \mathbb{P}_1^{(k)} : \mathbb{P}_1^{(k)} \in \mathcal{M}(\mathbb{R}^2) \text{ cannot be written as a product} \right\}.$$

In particular, the goal here is to create an e-detector to sequentially test for independence between the coordinates of a tuple, which is generally much harder than Gaussian mean change detection or symmetry testing. Here, we use the Hilbert-Schmidt independence criterion (HSIC) based sequential kernelized independence test (SKIT) using an online Newton step (ONS); a full description of how to build e-detectors for sequential kernelized independence testing (SKIT) can be found in [Podkopaev et al. \(2023\)](#).

Suppose that $(a_t^{(k)}, b_t^{(k)}) \sim \mathcal{N}(0, I_2)$ are independent for $t \in \mathbb{N}$ and $k \in [K] = 50$. For our simulations, we choose the pre-change observations $X_t^{(k)} = (a_t^{(k)}, b_t^{(k)})$ and the post-change observations $X_t^{(k)} = (a_t^{(k)}, \frac{1}{2}(a_t^{(k)} + b_t^{(k)}))$ in each stream. In particular, the first coordinate is mixed into the second coordinate after the change occurs. Further, suppose that $\xi^{(k)} = 400$ for $k \in [K] = 50$; we now plot the e-detectors for testing independence:




Figure 10: *e-detectors over time for detecting an independence change at time 400.*

Next, we set $\alpha_t = \alpha = 0.001$. We run the naive algorithm, e-d-BH, and e-d-Bonferroni 100 times, tracking the number of detections that they make at each timestep. Here, we plot the mean number of detections made at each timestep (across the 100 runs of the algorithm):




Figure 11: *Mean detections of e-d-BH, e-d-Bonferroni, and the naive algorithm over time for an independence change.*

As expected, the detection delay is larger for independence testing than for either Gaussian mean change detection or symmetry testing because independence testing is the hardest problem of the three. The reason for including this example is to demonstrate the applicability of e-detectors even in nonparametric settings where traditional methods like CUSUM and SR cannot be applied. In a wide variety of settings, we see that our algorithms provide Type

I error control without a significant increase in detection delay.

11 Conclusion

We showed that it is impossible to have a nontrivial worst-case Type I error when the ARL is finite, and put forth that the error over patience (EOP) is a sensible metric to control. Furthermore, we presented novel algorithms to provide this control uniformly over stopping times using e-detectors and the e-BH procedure. Our e-d-BH, e-d-Bonferroni, and e-d-Holm procedures can be considered an extension of the Benjamini-Hochberg, Bonferroni, and Holm procedures used in multiple testing to the setting of change detection.

Acknowledgments

We would like to thank Neil Xu and Yiming Xing for their invaluable feedback on this work.

References

- Benjamini, Y., & Hochberg, Y. (1995). Controlling the false discovery rate: A practical and powerful approach to multiple testing. *Journal of the Royal statistical society: series B (Methodological)*, 57(1), 289–300.
- Bodenham, D., & Adams, N. (2017). Continuous monitoring for changepoints in data streams using adaptive estimation. *Statistics and Computing*, 27, 1257–1270.
- Chan, H. P. (2017). Optimal sequential detection in multi-stream data. *The Annals of Statistics*.
- Chen, J., Zhang, W., & Poor, H. V. (2020). A false discovery rate oriented approach to parallel sequential change detection problems. *IEEE Transactions on Signal Processing*, 68, 1823–1836.
- Chen, Y., & Li, X. (2023). Compound sequential change-point detection in parallel data streams. *Statistica Sinica*, 33(1).
- Eriksson, M., & Olofsson, T. (2018). Computationally efficient off-line joint change point detection in multiple time series. *IEEE Transactions on Signal Processing*, 67(1), 149–163.
- Holm, S. (1979). A simple sequentially rejective multiple test procedure. *Scandinavian journal of statistics*, 65–70.
- Jiang, W., Shu, L., & Apley, D. W. (2008). Adaptive CUSUM procedures with EWMA-based shift estimators. *Iie Transactions*, 40(10), 992–1003.
- Mei, Y. (2010). Efficient scalable schemes for monitoring a large number of data streams. *Biometrika*, 97(2), 419–433.

- Plasse, J., & Adams, N. (2019). Multiple changepoint detection in categorical data streams. *Statistics and Computing*, *29*, 1109–1125.
- Plasse, J., Hoeltgebaum, H., & Adams, N. (2021). Streaming changepoint detection for transition matrices. *Data Mining and Knowledge Discovery*, *35*(4), 1287–1316.
- Podkopaev, A., Blöbaum, P., Kasiviswanathan, S., & Ramdas, A. (2023). Sequential kernelized independence testing. *International Conference on Machine Learning*, 27957–27993.
- Ramdas, A., Grünwald, P., Vovk, V., & Shafer, G. (2023). Game-theoretic statistics and safe anytime-valid inference. *Statistical Science*, *38*(4), 576–601.
- Ramdas, A., Ruf, J., Larsson, M., & Koolen, W. (2020). Admissible anytime-valid sequential inference must rely on nonnegative martingales. *arXiv preprint arXiv:2009.03167*.
- Shin, J., Ramdas, A., & Rinaldo, A. (2023). E-detectors: A nonparametric framework for sequential change detection. *The New England Journal of Statistics in Data Science*, *2*(2), 229–260. <https://doi.org/10.51387/23-NEJSDS51>
- Tartakovsky, A. G., & Spivak, V. (2024). Quickest changepoint detection in general multi-stream stochastic models: Recent results, applications and future challenges. In *2021-2022 matrix annals* (pp. 569–611). Springer Nature Switzerland. https://doi.org/10.1007/978-3-031-47417-0_29
- Wang, R., & Ramdas, A. (2022). False discovery rate control with e-values. *Journal of the Royal Statistical Society Series B: Statistical Methodology*, *84*(3), 822–852.
- Wang, Y., & Mei, Y. (2015). Large-scale multi-stream quickest change detection via shrinkage post-change estimation. *IEEE Transactions on Information Theory*, *61*(12), 6926–6938.
- Xie, Y., & Siegmund, D. (2013). Sequential multi-sensor change-point detection. *2013 Information Theory and Applications Workshop (ITA)*, 1–20.
- Xu, Q., & Mei, Y. (2021). Multi-stream quickest detection with unknown post-change parameters under sampling control. *2021 IEEE International Symposium on Information Theory (ISIT)*, 112–117.

A Relating the CCD and ARL

Suppose we have a change monitoring algorithm φ . Recall that $\text{ARL}_\eta(\varphi)$ is the expected first time that changes are declared in at least η streams.

Definition A.1 (Changes correctly detected at time t ($\text{CCD}(\varphi, \xi, t)$)). For a given sequential change monitoring algorithm φ and configuration ξ , the *changes correctly detected at time t* ($\text{CCD}(\varphi, \xi, t)$) measures the expected ratio of changes correctly detected at time t to the total number of changes that have happened at time t :

$$\text{CCD}(\varphi, \xi, t) = \mathbb{E} \left[\frac{\sum_{k=1}^K \varphi_t^{(k)} \mathbf{1}_{\xi^{(k)} < t+1}}{\left(\sum_{k=1}^K \mathbf{1}_{\xi^{(k)} < t+1} \right) \vee 1} \right].$$

Just as the FDR is related to the expected first declaration time of a change ($\text{ARL}_1(\varphi)$), the CCD is related to the expected first time at which all K streams declare a change ($\text{ARL}_K(\varphi)$). This is not a surprising result; when a change monitoring stream declares changes in all streams, the CCD is automatically 1.

Proposition A.1. Let $\mathcal{H}_0(t) = \{k \in [K] : \xi^{(k)} \geq t+1\}$ denote the set of streams in which a change has not yet happened by time t and let $\mathcal{H}_1(t) = \{1, 2, \dots, K\} \setminus \mathcal{H}_0(t)$. Then if $\text{ARL}_K(\varphi) < \infty$, we have:

$$\inf_{\xi \in \mathbb{N}^K} \mathbb{P} \left(\bigcup_{1 \leq t \leq (1+\alpha) \text{ARL}_K(\varphi)} \{\text{CCD}(\varphi, \xi, t) = 1\} \right) \geq \frac{\alpha}{1+\alpha}.$$

Proof. Let ξ be any configuration and let $\tau_K^*(\varphi)$ denote the first time that changes are declared in all K streams. Then, we have for all $\alpha > 0$:

$$\mathbb{P}(\tau_K^*(\varphi) \geq (1+\alpha) \text{ARL}_K(\varphi)) \leq \frac{1}{1+\alpha}.$$

So with probability at least $\alpha/(1+\alpha)$, we have $\tau_K^*(\varphi) \leq (1+\alpha) \text{ARL}_K(\varphi)$. The result now follows because $\text{CCD}(\varphi, \xi, \tau_K^*(\varphi)) = 1$. \square

Corollary A.1.1. In the setting of [Proposition A.1](#), having $\text{ARL}_K(\varphi) < \infty$ implies that $\sup_{t \in \mathbb{N}} \text{CCD}(\varphi, \xi, t) = 1$.

Proof. Apply the dominated convergence theorem to the inequality in [Proposition A.1](#) (since we know that CCD is uniformly bounded in $[0, 1]$) as $t \rightarrow \infty$. \square

B Piggybacking of evidence by e-d-BH

In this section, we describe a phenomenon surrounding e-d-BH, which we call *piggybacking of evidence*. In particular, suppose that detections are consistently being made for some subset of streams which have changed. Then, suppose that there are changes in some second (disjoint) subset of streams. In this case, the detection delays of e-d-BH for the second subset of streams will be smaller than the detection delays for the first subset of streams. This happens because the thresholds for future detections in e-d-BH are lower, due to the existing detections.

To observe this empirically, suppose that we are performing nonparametric symmetry testing using the e-detector described in Section 10.2. Consider the pre-change distribution class $\mathcal{P}_0^{(k)} = \{\otimes_{t=1}^{\infty} \mathcal{N}(0, 1)\}$ and the post-change distribution class $\mathcal{P}_1^{(k)} = \{\otimes_{t=1}^{\infty} \mathcal{N}(1, 1)\}$ for streams $k \in [K] = 50$. Further, suppose that $\xi^{(k)} = 100$ for streams $1 \leq k \leq 10$, $\xi^{(k)} = 500$ for streams $10 < k \leq 20$, and $\xi^{(k)} = \infty$ for streams $20 < k \leq K = 50$. Then, we run e-d-BH (setting $\alpha_t = \alpha = 0.0002$) 50 times, plotting the mean number of detections at each timestep:




Figure 12: Mean detections of e-d-BH over time for symmetry changes at times $t = 100$ and $t = 500$.

It takes 340 timesteps for e-d-BH to consistently detect all changes after the first subset of streams change at $t = 100$. However, it takes only 247 timesteps for e-d-BH to consistently detect all changes after the second subset of streams change at $t = 500$ (due to the decreased threshold for detection). We call this piggybacking of evidence, since existing evidence for changes reduces the amount of evidence required to declare future changes.