

Matrix exponential solution of the Landau-Zener problem

Alberto G. Rojo*

Department of Physics, Oakland University, Rochester, MI 48309.

Abstract

We present a derivation of the Landau-Zener solution through the explicit evaluation of the time ordered propagator. The result is exact and does not involve the solution of the differential equation for the spin amplitudes.

PACS numbers: 03.65.Aa, 03.65.Xp, 33.80.Be

arXiv:1004.2914v1 [quant-ph] 16 Apr 2010

*Electronic address: rojo@oakland.edu

In 1932, C. Zener presented an exact solution for the non-adiabatic transition probability of a two level problem[1]. Landau solved it simultaneously (with an error factor of 2π)[2] and the problem—one of the few cases where a non-adiabatic transition can be computed exactly—became a classic and is now called the Landau-Zener (LZ) model.

Although the time dependent problem for two level systems is simple at first sight, the exact solutions are known for a handful of cases. One is the LZ model considered in this paper, where the level spacing $\epsilon_1 - \epsilon_2$ varies linearly with time and level coupling between them, ϵ_{12} , is constant. On the other hand there is a class of models for which the level spacing is constant and the coupling is $\epsilon_{12} = g(t)$ with g an integrable function. Surprisingly the only cases of a smooth and even g for which the solution is known is $g(t) = \lambda / \cosh(t/\beta)$ and some specific time-dependent energies and couplings .[3, 4]

Zener solves Schrödinger's equation for all times in terms of Weber's functions and then computes the exact transition probability. This is the basis of most approaches, with the exception (to our knowledge) of the recent paper by C. Wittig[5], who derives the Landau-Zener formula using contour integration, bypassing the solution of the differential equation.

In this paper we present a different derivation of the transition probability by direct evaluation of the time-ordered matrix propagator. The solution is exact, does not involve any approximation, and does not make reference to the differential equation. Instead, we solve the time ordered propagator with a couple of simple manipulations and obtain the transition probability (and not the full time dependence of the problem). Since the Landau-Zener has innumerable applications to quantum problems and is the subject of current approaches (theoretical and experimental) in solid-state artificial atoms[7], quantum information[8], quantum dissipation[6] (to name just a few cases), we believe that this new derivation of an old result can be useful and hopefully motivate new avenues for the problem. In addition, it is a pleasure to solve an old problem from a new perspective.

The following is the Schrödinger equation of Landau-Zener problem[1].

$$i\hbar \frac{d}{dt} \begin{pmatrix} a(t) \\ b(t) \end{pmatrix} = \begin{pmatrix} \alpha t & \Gamma \\ \Gamma & -\alpha t \end{pmatrix} \begin{pmatrix} a(t) \\ b(t) \end{pmatrix}. \quad (1)$$

It is interesting that, for

$$a(-\infty) = 1, \quad b(-\infty) = 0, \quad (2)$$

the exact solution gives

$$|a(\infty)|^2 = e^{-\pi\Gamma^2/\hbar\alpha}$$

The fact that the solution is an exponential of the relevant dimension-less parameter suggests (to us) that there should be a simple derivation.

First transform the hamiltonian to

$$\overline{H} = UHU^*$$

and the spinor to

$$\begin{pmatrix} \overline{a}(t) \\ \overline{b}(t) \end{pmatrix} = U \begin{pmatrix} a(t) \\ b(t) \end{pmatrix}$$

with

$$U = \begin{pmatrix} e^{i\alpha t^2/2\hbar} & 0 \\ 0 & e^{-i\alpha t^2/2\hbar} \end{pmatrix}. \quad (3)$$

We obtain

$$\begin{aligned} i\hbar \frac{d}{dt} \begin{pmatrix} \overline{a} \\ \overline{b} \end{pmatrix} &= \begin{pmatrix} 0 & \Gamma e^{-i\alpha t^2/\hbar} \\ \Gamma e^{i\alpha t^2/\hbar} & 0 \end{pmatrix} \begin{pmatrix} \overline{a} \\ \overline{b} \end{pmatrix} \\ &\equiv \overline{H}(t) \begin{pmatrix} \overline{a} \\ \overline{b} \end{pmatrix}. \end{aligned} \quad (4)$$

The formal solution of (4) is

$$\begin{pmatrix} \overline{a}(\infty) \\ \overline{b}(\infty) \end{pmatrix} = T e^{-\frac{i}{\hbar} \int_{-\infty}^{\infty} dt \overline{H}(t)} \begin{pmatrix} \overline{a}(-\infty) \\ \overline{b}(-\infty) \end{pmatrix}, \quad (5)$$

with

$$T e^{-\frac{i}{\hbar} \int_{-\infty}^{\infty} dt \overline{H}(t)} = 1 - \frac{i}{\hbar} \int_{-\infty}^{\infty} dt \overline{H}(t) - \frac{1}{\hbar^2} \int_{-\infty}^{\infty} dt_1 \overline{H}(t_1) \int_{-\infty}^{t_1} dt_2 \overline{H}(t_2) + \dots \quad (6)$$

the time ordered exponential. The time ordering is crucial since the two dimensional matrices $\overline{H}(t)$ do not commute at different times.

Note that the even powers of \overline{H} have diagonal terms only whereas the odd powers have only off-diagonal terms. For example

$$\begin{aligned}\overline{H}(t_1)\overline{H}(t_2)\overline{H}(t_3) &= \begin{pmatrix} 0 & \Gamma^3 e^{-i\alpha(t_1^2-t_2^2+t_3^2)/\hbar} \\ \Gamma^3 e^{i\alpha(t_1^2-t_2^2+t_3^2)/\hbar} & 0 \end{pmatrix}, \\ \overline{H}(t_1)\overline{H}(t_2)\overline{H}(t_3)\overline{H}(t_4) &= \begin{pmatrix} \Gamma^4 e^{-i\alpha(t_1^2-t_2^2+t_3^2-t_4^2)/\hbar} & 0 \\ 0 & \Gamma^4 e^{i\alpha(t_1^2-t_2^2+t_3^2-t_4^2)/\hbar} \end{pmatrix}.\end{aligned}$$

This means that, if our initial condition is $\overline{a}(-\infty) = 1$, $\overline{b}(-\infty) = 0$, the solution for \overline{a} requires only the diagonal term and will be given by

$$\begin{aligned}\overline{a}(\infty) &= 1 - \left(\frac{\Gamma}{\hbar}\right)^2 \int_{-\infty}^{\infty} dt_1 e^{-i\alpha t_1^2/\hbar} \int_{-\infty}^{t_1} dt_2 e^{i\alpha t_2^2/\hbar} \\ &\quad + \left(\frac{\Gamma}{\hbar}\right)^4 \int_{-\infty}^{\infty} dt_1 e^{-i\alpha t_1^2/\hbar} \int_{-\infty}^{t_1} dt_2 e^{i\alpha t_2^2/\hbar} \int_{-\infty}^{t_2} dt_3 e^{-i\alpha t_3^2/\hbar} \int_{-\infty}^{t_3} dt_4 e^{i\alpha t_4^2/\hbar} + \dots\end{aligned}$$

or, in terms of the quantity

$$\gamma = \frac{\Gamma^2}{\hbar\alpha}, \quad (7)$$

$$\begin{aligned}\overline{a}(\infty) &= 1 - \gamma \int_{-\infty}^{\infty} dt_1 e^{-it_1^2} \int_{-\infty}^{t_1} dt_2 e^{it_2^2} \\ &\quad + \gamma^2 \int_{-\infty}^{\infty} dt_1 e^{-it_1^2} \int_{-\infty}^{t_1} dt_2 e^{it_2^2} \int_{-\infty}^{t_2} dt_3 e^{-it_3^2} \int_{-\infty}^{t_3} dt_4 e^{it_4^2} + \dots \\ &\equiv \sum_{n=0}^{\infty} (-\gamma)^n T_{2n}.\end{aligned} \quad (8)$$

Since the time ordered integrals T_{2n} involve alternating exponentials e^{it^2} and e^{-it^2} we cannot use simple permutation symmetry of the indices to evaluate them. This in contrast with a time ordered integral I_n of n identical functions $f(t)$, where we have:

$$I_n = \int_{-\infty}^{\infty} dt_1 f(t_1) \int_{-\infty}^{t_1} dt_2 f(t_2) \cdots \int_{-\infty}^{t_{n-1}} dt_n f(t_n) = \frac{1}{n!} \left[\int_{-\infty}^{\infty} dt f(t) \right]^n. \quad (9)$$

Time ordered integrals can be written using the the step function Θ defined as

$$\Theta(t) = \begin{cases} 1 & \text{for } t > 0 \\ 0 & \text{for } t < 0 \end{cases}. \quad (10)$$

Using Θ , the above integral of identical functions can be written as

$$I_n = \int_{-\infty}^{\infty} \left(\prod_{i=1}^n dt_i \right) f(t_1) \Theta(t_1 - t_2) f(t_2) \Theta(t_2 - t_3) \cdots \Theta(t_{n-1} - t_n) f(t_n) \equiv \frac{(I_1)^n}{n!}. \quad (11)$$

In order to evaluate the time ordered integrals T_{2n} of alternating exponentials we use the functions Θ in its integral representation:

$$\Theta(t) = \frac{1}{2\pi i} \int_{-\infty}^{\infty} d\omega \frac{e^{i\omega t}}{\omega + i\epsilon}. \quad (12)$$

Using Θ , the expression for T_{2n} becomes:

$$\begin{aligned} T_{2n} &= \int_{-\infty}^{\infty} \left(\prod_{i=1}^{2n} dt_i \right) e^{it_1^2} \Theta(t_1 - t_2) e^{-it_2^2} \Theta(t_2 - t_3) \cdots e^{it_{2n-1}^2} \Theta(t_{2n-1} - t_{2n}) e^{-it_{2n}^2} \\ &= \frac{1}{(2\pi i)^{2n-1}} (\sqrt{\pi})^{2n} \int_{-\infty}^{\infty} \left(\prod_{i=1}^{2n-1} d\omega_i \right) \frac{1}{\bar{\omega}_1} \frac{e^{i\omega_2(\omega_1 - \omega_3)}}{\bar{\omega}_2} \frac{1}{\bar{\omega}_3} \frac{e^{i\omega_4(\omega_3 - \omega_5)}}{\bar{\omega}_4} \cdots \frac{1}{\bar{\omega}_{2n-1}}, \end{aligned} \quad (13)$$

where, to abbreviate notation we have introduced

$$\bar{\omega}_k = \omega_k + i\epsilon. \quad (14)$$

Also, in going from the first to the second line of (13) we completed squares and used the gaussian integral

$$\int_{-\infty}^{\infty} dt e^{\pm it^2} = \sqrt{\frac{\pi}{\pm i}}. \quad (15)$$

Since we have an equal number of $+i$'s and $-i$'s in the integrals we get the positive factor $(\sqrt{\pi})^{2n}$. Also notice that, since we have alternating signs in the exponents, the terms quadratic in ω_k vanish. This is the feature that makes the integral T_{2n} easily solvable.

Next we perform the integrals in (13) over the $n - 1$ frequencies ω_k with even index k and use the fact that [see Eq.(12)]

$$\int_{-\infty}^{\infty} d\omega_k \frac{e^{i\omega_k(\omega_{k-1} - \omega_{k+1})}}{\omega_k + i\epsilon} = 2\pi i \Theta(\omega_{k-1} - \omega_{k+1}). \quad (16)$$

If we replace (16) in (13) we are left with n integrals. After relabeling the odd indices to consecutive indices we get:

$$T_{2n} = \frac{1}{(2\pi i)^n} (\sqrt{\pi})^{2n} \int_{-\infty}^{\infty} \left(\prod_{k=1}^n d\omega_k \right) \frac{1}{\bar{\omega}_1} \Theta(\omega_1 - \omega_2) \frac{1}{\bar{\omega}_2} \Theta(\omega_2 - \omega_3) \cdots \Theta(\omega_{n-1} - \omega_n) \frac{1}{\bar{\omega}_n}. \quad (17)$$

But this is precisely the structure of Eq. (11): in this case we have a “frequency ordered” integral of identical functions $1/(\omega_k + i\epsilon)$. The result is simply:

$$\begin{aligned}
T_{2n} &= \pi^n \frac{1}{n!} \left(\frac{1}{2\pi i} \int_{-\infty}^{\infty} d\omega \frac{1}{\omega + i\epsilon} \right)^n \\
&\equiv \frac{1}{n!} \left(\frac{\pi}{2} \right)^n .
\end{aligned} \tag{18}$$

Replacing in (8) we obtain

$$\begin{aligned}
\bar{a}(\infty) &= \sum_{n=0}^{\infty} \frac{1}{n!} \left(-\frac{\pi\gamma}{2} \right)^n = e^{-\pi\gamma/2} \\
&\equiv e^{-\pi\Gamma^2/2h\alpha},
\end{aligned} \tag{19}$$

and

$$|a(\infty)|^2 = e^{-\pi\Gamma^2/h\alpha}, \tag{20}$$

which is the exact Landau-Zener result.

We thank Anthony Bloch for useful discussions.

-
- [1] C. Zener, “Non-adiabatic Crossing of Energy Levels”. Proc. Roy. Soc. Lond. A **137** pp. 692-702 (1932).
 - [2] L. Landau . “Zur Theorie der Energieubertragung. II”. Physics of the Soviet Union **2** pp. 46-51, (1932).
 - [3] A. Bambini and P. R. Berman, “Analytic Solutions to the two–state problem for a class of coupling potentials”. Phys. Rev. A **23** pp. 2496-2501, (1981).
 - [4] P. R. Berman, Lixin Yan, Keng-Hwee Chiam and Ruwang Sung “ Nonadiabatic transitions in a two-level quantum system: Pulse-shape dependence of the transition probability for a two-level atom driven by a pulsed radiation field”. Phys. Rev. A **57** pp. 79-92, (1998).
 - [5] C. Wittig “The Landau-Zener Formula”, J. Phys. Chem., **109**, 8428–8420, (2005).
 - [6] P. Nalbach and M. Thorwart, “Landau-Zener Transitions in a Dissipative Environment: Numerically Exact Results”, *Phys. Rev. Lett* **103**, 220401 (2009).
 - [7] D. M. Berns *et al.*, “Amplitude spectroscopy of a solid-state artificial atom” Nature (London) **455**, 51 (2008).
 - [8] M. D. LaHaye, J. Suh, P. M. Echternach, K. C. Schwab and M. L. Roukes, “Nanomechanical measurements of a superconducting qubit”, Nature **459**, pp. 960–964 18 (2009).