

Spectral Camera based on true thermal light Ghost Imaging via Sparsity Constraints

Zhentao Liu,¹ Shiyu Tan,¹ Jianrong Wu,¹ Enrong Li,¹ and Shensheng Han^{1, a)}

*Key Laboratory for Quantum Optics and Center for Cold Atom Physics,
Shanghai Institute of Optics and Fine Mechanics, Chinese Academy of Sciences,
Shanghai 201800, China*

(Dated: 27 November 2024)

The image information acquisition ability of a conventional camera is usually much lower than the Shannon Limit since it does not make use of the correlation between pixels of image data. Applying a random phase modulator to code the spectral images and combining with compressive sensing (CS) theory, a spectral camera based on true thermal light ghost imaging via sparsity constraints (GISC spectral camera) is proposed and demonstrated experimentally. GISC spectral camera can acquire the information at a rate significantly below the Nyquist rate, and the resolution of the cells in the three-dimensional (3D) spectral images data-cube can be achieved with a two-dimensional (2D) detector in a single exposure. For the first time, GISC spectral camera opens the way of approaching the Shannon Limit determined by Information Theory in optical imaging instruments.

^{a)}sshhan@mail.shcnc.ac.cn

I. INTRODUCTION

Conventional Camera, as one of the most important appliances to get image information, records the image of an object based on the point-to-point correspondence between the object-space and the image-space. Because the correlation between pixels of image¹ cant be applied, the image information acquisition efficiency of such conventional point-to-point imaging mode is much lower than the Shannon Limit^{2,3} determined by Information Theory in optical imaging instruments⁴⁻¹⁰. Unlike the conventional direct point-to-point imaging mode, the resolution of the pixels of ghost imaging is determined by the correlation of light field fluctuations corresponding to the two pixels respectively, which can be measured on-line or pre-determined.^{11,12} Combining with compressive sensing (CS) theory^{1,13-17}, ghost imaging via sparsity constraints (GISC) has many potential applications including super-resolution imaging¹⁸⁻²¹, three-dimensional (3D) computational imaging with single-pixel detectors²², 3D remote sensing^{23,24}, imaging through scattering media^{25,26}, object tracking²⁷, object authentication^{28,29} and X-ray Fourier transform diffraction imaging³⁰⁻³². For thermal light ghost imaging, according to the illumination source, it can be classified to two categories: ghost imaging with pseudo-thermal light and true thermal light. Ghost imaging with true thermal light and sunlight have been respectively demonstrated by detecting the temporal fluctuation of thermal light and applying the intensity correlation between the intensity distributions at the reference arm and the test arm.³³⁻³⁵ Comparing with ghost imaging with pseudo-thermal light, this scheme of ghost imaging with true thermal light has to face the difficulty of detecting the temporal fluctuation of true thermal light which requires the response time of detector less than the coherence time of true thermal light $\tau = \frac{\lambda^2/\Delta\lambda}{c} \propto \frac{1}{\Delta\lambda}$ (λ is the wavelength, $\Delta\lambda$ is the linewidth, c is the speed of light) which can be as short as femtosecond. In order to increase the coherence time of the illuminating true thermal light, monochrome imaging is required which results in the vast majority of radiation energy from the target scene being filtered out, making the energy efficiency of ghost imaging applying the temporal fluctuation of true thermal light very low. Moreover, the fluctuating true thermal field needs to be split before the light field illuminating the object in the system and recorded in the reference path which makes the scheme even more difficult to be applied in remote sensing. In this paper, for the first time, we propose a spectral camera based on true thermal light ghost imaging via sparsity constraints (GISC spectral camera) without a

splitter. GISC spectral camera modulates the true thermal light into a spatially fluctuating pseudo-thermal light using a spatial random phase modulator^{36,37} which, at the same time, also acts as a random grating generating the uncorrelated speckles for different wavelengths, the 3D spectral images data-cube is then modulated into a two-dimensional (2D) data plane and GISC spectral camera can achieve the whole wavelength image in a single exposure, leading to a more convenient detection process and higher energy efficiency compared to ghost imaging applying the temporal fluctuation of true thermal light. Combining with CS, GISC spectral camera can acquire the information at a rate significantly below the Nyquist rate which opens the way of approaching the Shannon Limit determined by Information Theory in optical imaging instruments^{3-6,8}.

II. SCHEMATIC & RESOLUTION

The schematic of GISC spectral camera is shown in Fig.1. The system consists of (1) an imaging system, which projects the object image in the object plane ‘*a*’ onto the first image plane ‘*b*’, (2) a spatial random phase modulator, which disperses the image with different wavelengths as a random grating and modulates the image to generate the speckles in plane ‘*c*’^{36,37}, (3) a microscope objective, which magnifies the speckles in plane ‘*c*’, and (4) a charge-coupled device (CCD) detector recording the magnified speckles.




FIG. 1. Schematic of GISC spectral camera. (a) The object plane; (b) the first image plane; (c) the speckles plane; (1) an imaging system; (2) a spatial random phase modulator; (3) a microscope objective; (4) CCD detector.

Denoting the spectral light intensity distribution in the first image plane ‘*b*’ by $I_b(r_i, \lambda_l)$ and the intensity distribution in plane ‘*c*’ by $I_c(r_t)$ respectively, we have³⁸

$$I_c(r_t) = \int \int I_b(r_i, \lambda_l) h_I(r_t; r_i, \lambda_l) dr_i d\lambda_l, \quad (1)$$

where $h_I(r_t; r_i, \lambda_l)$ is the incoherent intensity impulse response function, r_t is the coordinate in plane 'c', r_i and λ_l are respectively the coordinate and wavelength of the light intensity distribution in the first image plane 'b'. To record the pre-determined reference spatial intensity fluctuation of the pseudo-thermal light without objects, a coherent monochrome point source at pixel r'_i with wavelength λ'_l in the first image plane 'b', denoted as $I_{b_r}(r_i, \lambda_l; r'_i, \lambda'_l) = \delta(r_i - r'_i, \lambda_l - \lambda'_l)$, is used to illuminate the spatial random phase modulator, and the recorded light intensity $I_{c_r}(r_t; r'_i, \lambda'_l)$ in the plane 'c' is given by

$$\begin{aligned} I_{c_r}(r_t; r'_i, \lambda'_l) &= \int \int I_{b_r}(r_i, \lambda_l) h_I(r_t; r_i, \lambda_l) dr_i d\lambda_l \\ &= \int \int \delta(r_i - r'_i, \lambda_l - \lambda'_l) h_I(r_t; r_i, \lambda_l) dr_i d\lambda_l \\ &= h_I(r_t; r'_i, \lambda'_l). \end{aligned} \quad (2)$$

During the imaging process, the intensity distribution in the first image plane 'b' $I_{b_t}(r_i, \lambda_l)$ is simply the image, denoted as $T_i(r_i, \lambda_l)$, of the object $T_s(r_s, \lambda_l)$ in the object plane 'a',

$$I_{b_t}(r_i, \lambda_l) = T_i(r_i, \lambda_l). \quad (3)$$

Combining Eqs. (1)(2) with (3), the intensity distribution $I_{c_t}(r_t)$ in the speckle plane 'c' is

$$I_{c_t}(r_t) = \int \int T_i(r_i, \lambda_l) I_{c_r}(r_t; r_i, \lambda_l) dr_i d\lambda_l. \quad (4)$$

Eq. (4) shows that $I_{c_t}(r_t)$ is the $T_i(r_i, \lambda_l)$ weighted integration of the pre-determined reference spatial intensity fluctuation of pseudo-thermal light $I_{c_r}(r_t; r_i, \lambda_l)$. Therefore, each pixel r_t of CCD detector is equivalent to a measurement of the bucket detector in the test arm of ghost imaging scheme. The second-order correlation function between the spatial intensity fluctuation in the pre-determined reference arm and test arm is defined as

$$G^{(2)}(r'_i, \lambda'_l) = \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}^*(r_t) E_{c_t}(r_t) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t}, \quad (5)$$

where $\langle \dots \rangle_{r_t}$ is the ensemble average about the coordinate of the light intensity distribution r_t . Combining Eqs. (2)(4) with (5), the second-order correlation function $G^{(2)}(r'_i, \lambda'_l)$ is given by

$$G^{(2)}(r'_i, \lambda'_l) = \int \int T_i(r_i, \lambda_l) G_{c_r}^{(2)}(r_i, \lambda_l, r'_i, \lambda'_l) dr_i d\lambda_l, \quad (6)$$

where $G_{c_r}^{(2)}(r_i, \lambda_l, r'_i, \lambda'_l) = \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}^*(r_t; r_i, \lambda_l) E_{c_r}(r_t; r_i, \lambda_l) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t}$ is the second-order correlation function of the light fields at different pixels and wavelengths in the first

image plane ‘b’. In order to calculate $G_{c_r}^{(2)}(r_i, \lambda_l, r'_i, \lambda'_l)$, the height autocorrelation function of the spatial random phase modulator is assumed as³⁹

$$R_\eta(r_0, r'_0) = \langle \eta(r_0)\eta(r'_0) \rangle = \omega^2 \exp - \frac{r_0 - r'_0}{\zeta}^2 = R_\eta(\Delta r_0), \Delta(r_0) = r_0 - r'_0, \quad (7)$$

where $\eta(r_0)$ and $\eta(r'_0)$ are respectively the height of the spatial random phase modulator at r_0 and r'_0 , ω and ζ are respectively the height standard deviation and transverse correlation length of the spatial random phase modulator. Assuming that the light field fluctuations in the speckles plane ‘c’ corresponding to pixel r'_i in the first image plane ‘b’ with wavelength λ'_l obeys the complex circular Gaussian distribution, $G_{c_r}^{(2)}(r_i, \lambda_l, r'_i, \lambda'_l)$ can be written as

$$\begin{aligned} G_{c_r}^{(2)}(r_i, \lambda_l, r'_i, \lambda'_l) &= \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}^*(r_t; r_i, \lambda_l) E_{c_r}(r_t; r_i, \lambda_l) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \\ &= \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \langle E_{c_r}^*(r_t; r_i, \lambda_l) E_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} \\ &+ \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}^*(r_t; r_i, \lambda_l) \rangle_{r_t} \langle E_{c_r}(r_t; r_i, \lambda_l) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \quad (8) \\ &= \langle I_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \langle I_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} + |J_{c_r}(r_i, \lambda_l, r'_i, \lambda'_l)|^2 \\ &= \langle I_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \langle I_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} [1 + g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l))], \end{aligned}$$

where

$$J_{c_r}(r_i, \lambda_l, r'_i, \lambda'_l) = \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}^*(r_t; r_i, \lambda_l) \rangle_{r_t}, \quad (9)$$

$$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l)) = \frac{|J_{c_r}(r_i, \lambda_l, r'_i, \lambda'_l)|^2}{\langle I_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} \langle I_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t}}. \quad (10)$$

$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l))$ is defined as the normalized second-order correlation function of the light fields at different pixels and wavelengths in the first image plane ‘b’. According to the Fresnel diffraction theorem, the light field in the speckles plane ‘c’ propagated from pixel r'_i in the first image plane ‘b’ with wavelength λ'_l is

$$\begin{aligned} E_{c_r}(r_t; r'_i, \lambda'_l) &= \frac{\exp\{j\pi[2(z_1 + z_2) + (r_t - r'_i)^2/(z_1 + z_2)]/\lambda'_l\}}{j\lambda'_l z_1 z_2} \\ &\times \int t(r_0, \lambda'_l) \exp[j\frac{\pi(z_1 + z_2)}{\lambda'_l z_1 z_2} (r_0 - \frac{z_1 r_t + z_2 r'_i}{z_1 + z_2})^2] dr_0, \quad (11) \end{aligned}$$

where $t(r_0, \lambda'_l) = \exp[j2\pi(n-1)\eta(r_0)/\lambda'_l]$ is the transmission function of the spatial random phase modulator. $\langle I_{c_r}(r_t; r'_i, \lambda'_l) \rangle$ and $\langle I_{c_r}(r_t; r_i, \lambda_l) \rangle$ are respectively given by

$$\langle I_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} = \langle E_{c_r}^*(r_t; r'_i, \lambda'_l) E_{c_r}(r_t; r'_i, \lambda'_l) \rangle_{r_t} = \frac{1}{z_1 z_2 \lambda'_l (z_1 + z_2)}, \quad (12)$$

$$\langle I_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} = \langle E_{c_r}^*(r_t; r_i, \lambda_l) E_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} = \frac{1}{z_1 z_2 \lambda_l (z_1 + z_2)}. \quad (13)$$

Substituting Eqs. (7)(9)(11) into (10) yields

$$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l) = \frac{(z_1 + z_2)^2 \exp\{-[2\pi\omega(n-1)]^2(\frac{1}{\lambda_l^2} + \frac{1}{\lambda'_l{}^2})\}}{z_1^2 z_2^2 \lambda_l \lambda'_l} \quad (14)$$

$$\times \left| \int \int \exp\{[2\pi(n-1)]^2 \frac{R_\eta(\mu, \nu)}{\lambda_l \lambda'_l}\} \exp\{j \frac{\pi(z_1 + z_2)}{z_1 z_2} (\frac{\mu^2}{\lambda_l} - \frac{\nu^2}{\lambda'_l})\} d\mu d\nu \right|^2,$$

where

$$\mu = r_0 - \frac{z_1 r_t + z_2 r_i}{z_1 + z_2}, \quad (15)$$

$$\nu = r'_0 - \frac{z_1 r_t + z_2 r'_i}{z_1 + z_2}, \quad (16)$$

$$\Delta \lambda'_l = \lambda'_l - \lambda_l, \quad (17)$$

$$R_\eta(\mu, \nu) = \omega^2 \exp\{-(\mu - \nu - \frac{z_2(r_i - r'_i)}{z_1 + z_2} / \zeta)^2\} = \omega^2 \exp\{-(\mu - \nu) - \frac{z_2 \Delta r'_i}{z_1 + z_2} / \zeta]^2\}, \quad (18)$$

$$\Delta r'_i = r_i - r'_i. \quad (19)$$

Assuming $\frac{|\Delta \lambda'_l|}{\lambda_l} \ll 1$, we have

$$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l)$$

$$\approx \frac{(z_1 + z_2)^2 \exp\{-[2\pi\omega(n-1)]^2(\frac{1}{\lambda_l^2} + \frac{1}{\lambda'_l{}^2})\}}{z_1^2 z_2^2 \lambda_l \lambda'_l} \quad (20)$$

$$\times \left| \int \int \exp\{[2\pi(n-1)]^2 \frac{R_\eta(\mu, \nu)}{\lambda_l \lambda'_l}\} \exp\{j \frac{\pi(z_1 + z_2)}{z_1 z_2 \lambda_l} (\mu^2 - \nu^2 + \frac{\Delta \lambda'_l}{\lambda_l} \nu^2)\} d\mu d\nu \right|^2.$$

Assuming $\frac{z_1}{z_2} \gg 1$, and the diameter σ of the illuminated region in the spatial random phase modulator by each cells of 3D data-cube in calibration satisfies $\pi\sigma^2/\lambda_l z_2 < 1$,

$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l)$ is given by

$$g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l) \approx \exp\{-[2\pi\omega(n-1)]^2(\frac{1}{\lambda_l} - \frac{1}{\lambda'_l})^2\} \exp\{\frac{2[2\pi\omega(n-1)]^2}{\lambda_l^2} \{ \exp\{-[\frac{z_2 \Delta r'_i}{(z_1 + z_2)\zeta}]^2\} - 1\}\}. \quad (21)$$

Taking Eqs. (8)(12)(13) and (21) into Eq. (6), we get the correlation function of intensity fluctuations⁴⁰

$$\Delta G^{(2)}(r'_i, \lambda'_l)$$

$$= G^{(2)}(r'_i, \lambda'_l) - \langle I_{c_r}(r_t; r_i, \lambda_l) \rangle_{r_t} \langle I_{c_t}(r_t) \rangle_{r_t}$$

$$\approx -\frac{1}{z_1^2 z_2^2 (z_1 + z_2)^2} \{ \{ T_i(r'_i, k'_l) \}_{r'_i} \otimes \{ \exp\{2[2\pi\omega(n-1)k'_l]^2 \{ \exp\{-[\frac{z_2 r'_i}{(z_1 + z_2)\zeta}]^2\} - 1\}\} \}_{r'_i} \}_{k'_l}$$

$$\otimes \exp\{-[2\pi\omega(n-1)]^2 k'_l{}^2\}, \quad (22)$$

where $k_l = \frac{1}{\lambda_l}$, $k'_l = \frac{1}{\lambda'_l}$, \otimes denotes the operation of convolution. Eq. (22) specifies that $T_i(r'_i, \lambda'_l)$ can be separated from the correlation function of intensity fluctuations $\Delta G^{(2)}(r'_i, \lambda'_l)$, and the resolution is determined by the normalized second-order correlation $g_{c_r}^{(2)}((r_i, \lambda_l, r'_i, \lambda'_l))$ at different pixels and wavelengths in the first image plane 'b'. When $r_i = r'_i$, according to Eq. (14), the normalized second-order correlation function of the light fields at pixel r'_i in the first image plane 'b' with two different wavelengths is given by

$$g_{c_r}^{(2)}(r'_i, \lambda_l, r'_i, \lambda'_l) = \frac{(z_1 + z_2)^2 \exp\{-[2\pi\omega(n-1)]^2(\frac{1}{\lambda_l^2} + \frac{1}{\lambda'^2_l})\}}{z_1^2 z_2^2 \lambda_l \lambda'_l} \times \left| \int \int \exp\{[2\pi(n-1)]^2 \frac{R_\eta(r_0, r'_0)}{\lambda_l \lambda'_l}\} \right. \quad (23)$$

$$\left. \exp\{j \frac{\pi(z_1 + z_2)}{z_1 z_2} [(r_0 - \frac{z_1 r_t + z_2 r_i}{z_1 + z_2})^2 / \lambda_l - (r'_0 - \frac{z_1 r_t + z_2 r'_i}{z_1 + z_2})^2 / \lambda'_l]\} dr_0 dr'_0 \right|^2.$$

Similarly, when $\lambda_l = \lambda'_l$, according to Eq. (14), the normalized second-order correlation function of the light fields at two different pixels in the first image plane 'b' with wavelength λ'_l is given by

$$g_{c_r}^{(2)}(r_i, \lambda'_l, r'_i, \lambda'_l) = \exp\{-2[2\pi\omega(n-1)/\lambda'_l]^2 \{1 - \exp[-(\frac{z_2 \Delta r'_i}{(z_1 + z_2)\zeta})^2]\}\}. \quad (24)$$

Fig.2(a) and Fig.2(b) respectively show the comparison of $g_{c_r}^{(2)}(r'_i, \lambda_l, r'_i, \lambda'_l)$ and $g_{c_r}^{(2)}(r_i, \lambda'_l, r'_i, \lambda'_l)$ between experiment and theory, and the experiment diagram is given in Fig.1 with $z_1 = 20mm$, $z_2 = 0.3mm$, $\omega = 2.1\mu m$, $\zeta = 16.75\mu m$, $n = 1.516$ and the central wavelength $\lambda'_l = 600nm$.




FIG. 2. (a) The normalized second-order correlation function of the light fields $g_{c_r}^{(2)}(r'_i, \lambda_l, r'_i, \lambda'_l)$ at pixel in the first image plane 'b' with two different wavelengths; (b) The normalized second-order correlation function of the light fields $g_{c_r}^{(2)}(r_i, \lambda'_l, r'_i, \lambda'_l)$ at two different pixels in the first image plane 'b' with wavelength λ'_l .

III. THE MEASUREMENT MATRIX & RECONSTRUCTION ALGORITHM.

There are many methods to improve the imaging quality of ghost imaging.^{41–43} However, ghost imaging reconstructions based on the ensemble statistics cannot provide the criterion of the necessary number of sampling for a perfect imaging, which makes it impossible to optimize the design of ghost imaging system. Combining with CS which provides the recovery condition of perfect reconstruction, the quantitative analysis for the necessary measurements data can be made. Under the framework of CS theory, the measurement matrix of GISC spectral camera is obtained as follows: each of the speckle intensity distributions generated by a point light source at pixel r'_i in the $\lambda \pm \Delta\lambda'_i$ spectrum band in the first image plane ‘ b ’ is recorded by the randomly selected $M_{r'_i}$ pixels of CCD detector and reshaped as a column vector of length M of the measurement matrix. Repeating the process for all the N image pixels in the first image plane ‘ b ’ and all the L spectral bands, one may have the pre-determined random measurement matrix $A_{M \times K}$, where $K = L \times N$. If we denote the unknown spectral object image as a K -dimensional column vector $X_{K \times 1}$, and reshape the modulated object intensity distribution recorded by the same M pixels of CCD detector in a similar way as a column vector $Y_{M \times 1}$, then we may have the discrete from Eq. (4),

$$Y = AX. \quad (25)$$

Spectral object image is usually both spatially and spectrally correlated, which has already been utilized in spectral image reconstructions.^{44–46} The reconstruction of the spectral object image can generally be regarded as solving a minimization problem which penalizes both the l_1 norm and the nuclear norm of the data matrix:

$$\min_X \mu_1 \|\psi X\|_{l_1} + \mu_2 \|\tilde{X}\|_*, s.t., Y = AX, \quad (26)$$

where $\tilde{X}_{L \times N}$ a matrix representation of the spectral object image whose columns represent different bands of the spectral object image, ψ the sparsifying transform, μ_1 and μ_2 the weight coefficients and $\mu_1, \mu_2 > 0$. In this work, we use a modified approach based on the method described by Eq. (26)⁴⁷:

$$\min_X \mu_1 \|\psi X\|_{l_1} + \mu_2 \|\Delta s\|_{l_1}, s.t., Y = AX, X \geq 0, \quad (27)$$

where $\Delta s_i = s_{i+1} - s_1$, is the subtraction of the largest singular value s_1 and the other s_i . The solution of Eq. (27) tends to have a simultaneous low-effective-rank and sparse structure, which much improves the reconstruction quality with low sampling rate.

IV. EXPERIMENTAL RESULTS..

In the experimental setup of GISC spectral camera shown in Fig.3, the imaging system (Tamron AF70-300mm f/4-5.6) with focal length of $f = 180mm$ projects the object image onto the first image plane, a beam splitter (BS) with split ratio 50:50 splits the light field into two paths, CCD1 detector (AVT Sting F-504C with pixel size of $3.45\mu m \times 3.45\mu m$) is placed in one of the two paths at the position of the first image plane of the system to obtain the conventional image of the object for comparison, a spatial random phase modulator (SIGMA KOKI CO., LTD. DFSQ1-30C02-1000) disperses the images with different wavelengths acting as a random grating and modulates the image to generate the speckles, a microscope objective with magnification $\beta = 10$ and the numerical aperture $N.A. = 0.25$ magnifies the speckles which are then recorded by CCD2 detector (Andor iKon-M) with the pixel size $13\mu m \times 13\mu m$. The first image plane is divided into $N_x \times N_y = 140 \times 140$ pixels with the square of each pixel approximately equal to Δr_s determined by the Eq. (24). The number of spectrum bands for single exposure is 7, and the images in two wavelength ranges of $520 \sim 580nm$ and $620 \sim 680nm$ are respectively obtained in two exposures, while the theoretical spectral resolution is $20nm$ in the experimental setup according to Eq. (23). In order to compare the spectral & spatial resolution of GISC spectral camera with the theoretical resolution, as shown in Fig.4, the spectral object ‘SIOM’ with different parts passing through different wavelengths has been selected, and the illuminating source is a xenon lamp. The original spectral images of ‘SIOM’ obtained by CCD1 detector placed in the first image plane ‘b’ with corresponding narrowband filter in front of it are shown in Fig.4 (pixel size is equal to the theoretical resolution of reconstructed images by GISC spectral camera for comparing them). The corresponding modulated object intensity distribution Y is achieved by CCD2 detector of GISC spectral camera and the reconstructed spectral images of ‘SIOM’ with 30% sampling rate of 3D date-cube are shown in Fig.5. The comparison between the original and reconstructed spectral images shows that the resolution of GISC spectral camera is in accordance with the theoretical calculation.




FIG. 3. Experimental setup of GISC spectral camera.




FIG. 4. The original spectral images of ‘SIOM’ obtained by CCD1 detector placed on the first image plane ‘b’ with corresponding narrowband filter in front of it, showing all the channels from $620 \sim 680nm$.

The images of the outdoor scene consisting of Mario & Luigi with sunlight illumination are shown in Fig.6. Fig.6(a) is obtained by a camera, while Fig.6(b) and Fig.6(c) respectively show the pictures taken by CCD1 detector with narrowband filters of $550 \pm 10nm$ and $650 \pm 10nm$ in front of it (pixel size is equal to the theoretical resolution of reconstructed images by GISC spectral camera for the sake of comparison). The reconstructed spectral images of Mario & Luigi with 30% sampling rate of 3D date-cube are shown in Fig.7. The experimental results show that the spectral imaging ability of GISC spectral camera for complex scenes is also pretty good.




FIG. 5. The reconstructed spectral images of ‘SIOM’ with 30% sampling rate of 3D date-cube, showing all the channels from 620 ~ 680nm.




FIG. 6. taken by (a) a camera; (b) CCD1 detector passing through narrowband filters of $550 \pm 10nm$; (c) CCD1 detector passing through narrowband filters of $650 \pm 10nm$.

V. DISCUSSION & CONCLUSION.

Based on Information Theory, the transmitted information of an imaging system can be described by the entropy^{2,3}

$$H(X) = - \sum_i p(x_i) \log p(x_i), \quad (28)$$

where $p(x_i)$ is the probability of x_i occurrence. For the conventional direct point-of-object-space to point-of-image-space imaging mode, the conditional entropy $H(X|Y) = 0$, and thus the channel capacity of the conventional monochrome camera is

$$C = \max_{p(x_i)} I(X;Y) = \max_{p(x_i)} [H(X) - H(X|Y)] = \max_{p(x_i)} H(X) = H_C(X), \quad (29)$$

where $I(X;Y)$ is the mutual information, $H_C(X) = \max_{p(x_i)} H(X)$ the maximum information entropy of source X for conventional imaging instrument, which is the Shannon Limit of the imaging system. According to the principle of maximum entropy¹, the information content of an image is maximized when $p(x_i)$ is Gaussian distribution with average power constraints, which doesnt contain any useful information. Therefore, the entropy of the image with structured information $H(X)$ has

$$H(X) < H_C(X) = C. \quad (30)$$




FIG. 7. The reconstructed spectral images of Mario & Luigi with 30% sampling rate of 3D data-cube, showing all the channels from 520 ~ 580nm and 620 ~ 680nm.

Eq. (30) shows that the image information acquisition efficiency of such conventional point-to-point imaging mode is lower than the Shannon Limit determined by Information Theory in optical imaging instruments. The channel capacity of an imaging system based on Information Theory for conventional optical imaging instruments is⁴⁻⁸

$$C = N_{DOF} \log_2(1 + m), \quad (31)$$

where m is signal to noise ratio (SNR), N_{DOF} is degrees of freedom and has

$$N_{DOF} = N_t \cdot N_s \cdot N_c \cdot N_\phi, \quad (32)$$

where N_t, N_s, N_c and N_ϕ are respectively time, spatial, color and polarization degrees of freedom. Spatial degrees of freedom N_s has⁷

$$N_s = SW = \left(N_x \frac{0.61\lambda}{\alpha_x}\right) \left(N_y \frac{0.61\lambda}{\alpha_y}\right) \frac{1}{\lambda/(2\alpha_x)} \frac{1}{\lambda/(2\alpha_y)} = 1.22^2 N_x N_y, \quad (33)$$

where S is the image area, W is the space bandwidth, α_x, α_y and N_x, N_y are respectively the image-space aperture angle and the resolved pixel number in the image-space of coordinate x and y . The color degrees of freedom N_c depend on the number of spectral channels, while polarization degrees of freedom N_ϕ is determined by the independent polarization state. According to Eqs. (28)(31) and (33), the channel capacity of the conventional camera in our experiment (where $N_{t_1} = 1, N_{c_1} = 1, N_{\phi_1} = 1, N_{x_1} \times N_{y_1} = 140 \times 140, m_1 = 255$) is $C_1 = N_{DOF_1} \log_2(1 + m_1) \approx 2.33 \times 10^5$, and the corresponding transmitted information of Fig.6(b) is $H_1(X) \approx 1.07 \times 10^5 < C_1$. In order to transmit the 520 ~ 580nm wavelength ranges data, the required channel capacity of the conventional camera (where $N_{t_2} = 1, N_{c_2} = 7, N_{\phi_2} = 1, N_{x_2} \times N_{y_2} = 140 \times 140, m_2 = 255$) is $C \approx 1.63 \times 10^6$, while

the required channel capacity in GISC spectral camera with 30% sampling rate in our experiment is $C_3 \approx 4.90 \times 10^5$. $C_3 < C_2$ shows that GISC spectral camera has the higher information acquisition efficiency in a single exposure compared to the conventional camera. With the development of optical imaging technology, many new imaging technologies (such as CT image⁴⁸) are not based on the point-to-point imaging mode. However, because the correlation between pixels of image data doesn't be applied in the imaging reconstruction algorithm, the information acquisition efficiency of those new coding imaging technology also can't approaching the Shannon Limit determined by Information Theory for conventional optical imaging instruments. However, GISC imaging solution applies a spatial random phase modulation to satisfy the restricted isometry property (RIP)¹⁹ required by applying CS that makes the improvement of information acquisition efficiency of the imaging system possible. Comparing with CS imaging technology (such as Single-Pixel Imaging via Compressive Sampling⁴⁹, coded aperture snapshot spectral imagers⁵⁰), which forces on the compressive sampling of electric signal after photoelectric conversion to improve the channel capacity utilization efficiency of the electric signal, GISC imaging solution improves the optical channel capacity utilization efficiency and achieves the compressive sampling of the image data during the imaging acquisition process, which opens the way of approaching the Shannon Limit determined by Information Theory in optical imaging instruments. As a new optical imaging technology, GISC spectral camera provides a unique solution for the spectral imaging of dynamic processes. This GISC imaging solution may also be expanded to other multi-dimensional information (such as polarization information) acquisition⁵¹, ultra-fast measurement⁵², and super-resolution imaging^{20,53,54}.

REFERENCES

- ¹E. Jacobs, Y. Fisher, and R. Boss, "Image compression: A study of the iterated transform method," *Signal Processing* **29**, 251–263 (1992).
- ²C. SHANNON, "A mathematical theory of communication," *The Bell System Technical Journal* **27**, 397–423,623–656 (1948).
- ³T. M. Cover and J. A. Thomas, *Elements of information theory* (John Wiley & Sons, 2012) pp. 657–687.
- ⁴P. Elias, "Optics and communication theory," *JOSA* **43**, 229–232 (1953).

- ⁵G. Francia, “Resolving power and information,” *JOSA* **45**, 497–499 (1955).
- ⁶W. Tan and Z. Wang, “Series of optical information theory,” Changchun Institute of Optics, Fine Mechanics and Physics, Chinese Academy of Sciences **1** (1964).
- ⁷G. T. Di Francia, “Degrees of freedom of an image,” *JOSA* **59**, 799–804 (1969).
- ⁸W. Tan, “Optical information theory-retrospect and prospect,” *Optics and Precision Engineering* **3**, 17–22 (1982).
- ⁹F. O. Huck, C. L. Fales, R. Alter-Gartenberg, S. K. Park, and Z.-u. Rahman, “Information-theoretic assessment of sampled imaging systems,” *Optical Engineering* **38**, 742–762 (1999).
- ¹⁰B. A. Strange, A. Duggins, W. Penny, R. J. Dolan, and K. J. Friston, “Information theory, novelty and hippocampal responses: unpredicted or unpredictable?” *Neural Networks* **18**, 225–230 (2005).
- ¹¹M. I. Kolobov, *Quantum imaging*, Vol. 12 (Springer Science & Business Media, 2007) pp. 79–110.
- ¹²J. H. Shapiro and R. W. Boyd, “The physics of ghost imaging,” *Quantum Information Processing* **11**, 949–993 (2012).
- ¹³R. C. Gonzalez, R. E. Woods, and S. L. Eddins, *Digital image processing using MATLAB* (Pearson Education India, 2004) pp. 282–315.
- ¹⁴D. L. Donoho, “Compressed sensing,” *Information Theory, IEEE Transactions on* **52**, 1289–1306 (2006).
- ¹⁵E. J. Candès, J. Romberg, and T. Tao, “Robust uncertainty principles: Exact signal reconstruction from highly incomplete frequency information,” *Information Theory, IEEE Transactions on* **52**, 489–509 (2006).
- ¹⁶Y. C. Eldar and G. Kutyniok, *Compressed sensing: theory and applications* (Cambridge University Press, 2012).
- ¹⁷J. Wu, X. Shen, H. Yu, Z. Chen, Z. Liu, S. Tan, and S. Han, “Snapshot compressive imaging by phase modulation,” *Acta Optical Sinica* , 113–120 (2014).
- ¹⁸W. Gong and S. Han, “Super-resolution far-field ghost imaging via compressive sampling,” arXiv preprint arXiv:0911.4750 (2009).
- ¹⁹W. Gong and S. Han, “Experimental investigation of the quality of lensless super-resolution ghost imaging via sparsity constraints,” *Physics Letters A* **376**, 1519–1522 (2012).

- ²⁰H. Wang, S. Han, and M. I. Kolobov, “Quantum limits of super-resolution of optical sparse objects via sparsity constraint,” *Optics express* **20**, 23235–23252 (2012).
- ²¹W. Gong and S. Han, “High-resolution far-field ghost imaging via sparsity constraint,” *Scientific reports* **5** (2015).
- ²²B. Sun, M. P. Edgar, R. Bowman, L. E. Vittert, S. Welsh, A. Bowman, and M. Padgett, “3d computational imaging with single-pixel detectors,” *Science* **340**, 844–847 (2013).
- ²³C. Zhao, W. Gong, M. Chen, E. Li, H. Wang, W. Xu, and S. Han, “Ghost imaging lidar via sparsity constraints,” *Applied Physics Letters* **101**, 141123 (2012).
- ²⁴W. Gong, C. Zhao, J. Jiao, E. Li, M. Chen, H. Wang, W. Xu, and S. Han, “Three-dimensional ghost imaging lidar,” arXiv preprint arXiv:1301.5767 (2013).
- ²⁵W. Gong and S. Han, “Correlated imaging in scattering media,” *Optics letters* **36**, 394–396 (2011).
- ²⁶M. Bina, D. Magatti, M. Molteni, A. Gatti, L. Lugiato, and F. Ferri, “Backscattering differential ghost imaging in turbid media,” *Physical review letters* **110**, 083901 (2013).
- ²⁷O. S. Magaña-Loaiza, G. A. Howland, M. Malik, J. C. Howell, and R. W. Boyd, “Compressive object tracking using entangled photons,” *Applied Physics Letters* **102**, 231104 (2013).
- ²⁸W. Chen and X. Chen, “Object authentication in computational ghost imaging with the realizations less than 5% of nyquist limit,” *Optics letters* **38**, 546–548 (2013).
- ²⁹X. Xu, E. Li, H. Yu, W. Gong, and S. Han, “Morphology separation in ghost imaging via sparsity constraint,” *Optics express* **22**, 14375–14381 (2014).
- ³⁰J. Cheng and S. Han, “Incoherent coincidence imaging and its applicability in x-ray diffraction,” *Physical review letters* **92**, 093903 (2004).
- ³¹M. Zhang, Q. Wei, X. Shen, Y. Liu, H. Liu, J. Cheng, and S. Han, “Lensless fourier-transform ghost imaging with classical incoherent light,” *Physical Review A* **75**, 021803 (2007).
- ³²H. Wang and S. Han, “Coherent ghost imaging based on sparsity constraint without phase-sensitive detection,” *EPL (Europhysics Letters)* **98**, 24003 (2012).
- ³³D. Zhang, Y.-H. Zhai, L.-A. Wu, and X.-H. Chen, “Correlated two-photon imaging with true thermal light,” *Optics letters* **30**, 2354–2356 (2005).
- ³⁴M. D’Angelo and Y. Shih, “Quantum imaging,” *Laser Physics Letters* **2**, 567–596 (2005).

- ³⁵X.-F. Liu, X.-H. Chen, X.-R. Yao, W.-K. Yu, G.-J. Zhai, and L.-A. Wu, “Lensless ghost imaging with sunlight,” *Optics letters* **39**, 2314–2317 (2014).
- ³⁶M. Giglio, M. Carpineti, and A. Vailati, “Space intensity correlations in the near field of the scattered light: a direct measurement of the density correlation function $g(\mathbf{r})$,” *Physical review letters* **85**, 1416 (2000).
- ³⁷R. Cerbino, L. Peverini, M. Potenza, A. Robert, P. Bösecke, and M. Giglio, “X-ray-scattering information obtained from near-field speckle,” *Nature Physics* **4**, 238–243 (2008).
- ³⁸J. W. Goodman, *Introduction to Fourier optics* (Roberts and Company Publishers, 2005) pp. 154–160.
- ³⁹C.-F. Cheng, D.-P. Qi, D.-L. Liu, and S.-Y. Teng, “The computational simulations of the gaussian correlation random surface and its light-scattering speckle field and the analysis of the intensity probability density,” *Acta Physica Sinica* **48**, 1635–1643 (1999).
- ⁴⁰A. Gatti, E. Brambilla, M. Bache, and L. A. Lugiato, “Ghost imaging with thermal light: comparing entanglement and classical correlation,” *Physical review letters* **93**, 093602 (2004).
- ⁴¹K. W. C. Chan, M. N. O’Sullivan, and R. W. Boyd, “High-order thermal ghost imaging,” *Optics letters* **34**, 3343–3345 (2009).
- ⁴²W. Gong and S. Han, “A method to improve the visibility of ghost images obtained by thermal light,” *Physics Letters A* **374**, 1005–1008 (2010).
- ⁴³F. Ferri, D. Magatti, L. Lugiato, and A. Gatti, “Differential ghost imaging,” *Physical review letters* **104**, 253603 (2010).
- ⁴⁴S. Oymak, A. Jalali, M. Fazel, Y. C. Eldar, and B. Hassibi, “Simultaneously structured models with application to sparse and low-rank matrices,” *arXiv preprint arXiv:1212.3753* (2012).
- ⁴⁵M. Golbabaee and P. Vandergheynst, “Compressed sensing of simultaneous low-rank and joint-sparse matrices,” *arXiv preprint arXiv:1211.5058* (2012).
- ⁴⁶M. Golbabaee and P. Vandergheynst, “Joint trace/tv norm minimization: A new efficient approach for spectral compressive imaging,” in *Image Processing (ICIP), 2012 19th IEEE International Conference on* (IEEE, 2012) pp. 933–936.
- ⁴⁷H. Zhang, W. He, L. Zhang, H. Shen, and Q. Yuan, “Hyperspectral image restoration using low-rank matrix recovery,” *Geoscience and Remote Sensing, IEEE Transactions on* **52**, 4729–4743 (2014).

- ⁴⁸J. Hsieh, “Computed tomography: principles, design, artifacts, and recent advances,” (SPIE Bellingham, WA, 2009).
- ⁴⁹M. F. Duarte, M. A. Davenport, D. Takhar, J. N. Laska, T. Sun, K. E. Kelly, R. G. Baraniuk, *et al.*, “Single-pixel imaging via compressive sampling,” *IEEE Signal Processing Magazine* **25**, 83 (2008).
- ⁵⁰D. Kittle, K. Choi, A. Wagadarikar, and D. J. Brady, “Multiframe image estimation for coded aperture snapshot spectral imagers,” *Applied Optics* **49**, 6824–6833 (2010).
- ⁵¹S. P. Morgan and I. Stockford, “Surface-reflection elimination in polarization imaging of superficial tissue,” *Optics Letters* **28**, 114–116 (2003).
- ⁵²L. Gao, J. Liang, C. Li, and L. V. Wang, “Single-shot compressed ultrafast photography at one hundred billion frames per second,” *Nature* **516**, 74–77 (2014).
- ⁵³D. L. Donoho, “Superresolution via sparsity constraints,” *SIAM Journal on Mathematical Analysis* **23**, 1309–1331 (1992).
- ⁵⁴E. J. Candès and C. Fernandez-Granda, “Towards a mathematical theory of super-resolution,” *Communications on Pure and Applied Mathematics* **67**, 906–956 (2014).