

# Connection coefficients and monodromy representations for a class of Okubo systems of ordinary differential equations, II

Shotaro KONNAI  
Department of Mathematics, Kobe University

## Abstract

Explicit connection coefficients and monodromy representations are constructed for the canonical solution matrices of Okubo systems  $II^*, III^*, IV$  and  $IV^*$  of ordinary differential equations in Yokoyama's list.

## 1 Introduction

In this paper we construct explicit connection coefficients and monodromy representations for the canonical solution matrices of Okubo systems  $II^*, III^*, IV$  and  $IV^*$  of ordinary differential equations in Yokoyama's list. This work is a continuation of our previous work [5].

Recall that Yokoyama [13] classified the types of irreducible rigid Okubo systems under the condition that the nontrivial local exponents are mutually distinct at each finite singular point; this class consists of eight types I, II, III, IV and  $I^*, II^*, III^*, IV^*$ , which is usually referred to as *Yokoyama's list*. For each type in Yokoyama's list, Haraoka constructed a canonical form of the Okubo system [1], as well as the corresponding monodromy representation, up to the conjugation by diagonal matrices [2].

In [5], we determined explicit monodromy representations for the canonical solution matrices of types I,  $I^*$ , II and III, including the diagonal matrix factors which had not been fixed in [2]. The argument of [5] is based on the fact that all the Okubo systems in Yokoyama's list can be constructed by finite iterations of the Katz operations of type

$$\text{add}_{(0, \dots, \rho, \dots, 0)} \circ \text{mc}_{-\rho-c} \circ \text{add}_{(0, \dots, c, \dots, 0)}(\mathbf{A}) \quad (c, \rho \in \mathbb{C}) \quad (1.1)$$

for Okubo systems. A characteristic feature of this operation is that for each Okubo system, the resulting system is also an Okubo system, and its explicit form is computed recursively. The canonical solution matrix of the resulting Okubo system can also be constructed recursively by the corresponding operation on solution matrices. By these operations, we specified in [5] the connection coefficients, as well as the monodromy representations, for the canonical solution matrices of I,  $I^*$ , II, III in Yokoyama's list.

The purpose of this paper is to give explicit connection coefficients and monodromy representations for the canonical solution matrices of remaining types  $II^*, III^*, IV$  and  $IV^*$ . To derive connection coefficients of these types, we need to carefully investigate *symmetry* of the systems with respect to the characteristic exponents, in contrast to the cases discussed in [5] (for the detail, see Section 4).



and  $\xi_i \in \text{Mat}(n_i, \tilde{n}_k)$  and  $\eta_j \in \text{Mat}(\tilde{n}_k, n_j)$  are matrices characterized by the conditions

$$\xi_i \eta_j = A_{ij} - A_{ik}(A_{kk} - \rho)^{-1}A_{kj} \quad (i, j = 1, \dots, r; i, j \neq k). \quad (2.8)$$

Under the condition (2.4), for each  $j = 1, \dots, r$ , the Okubo system (2.1) has a unique  $n \times n_j$  solution matrix  $\Psi_j(x)$  characterized by the local behavior

$$\Psi_j(x) = F_j(x)(x - t_j)^{A_{jj}}, \quad F_j(x) \in \text{Mat}(n, n_j; \mathcal{O}_{t_j}), \quad F_j(t_j) = (0, I_{n_j}, 0)^t, \quad (2.9)$$

around  $x = t_j$ . Collecting these solution matrices, we consider the  $n \times n$  solution matrix  $\Psi(x) = (\Psi_1(x), \dots, \Psi_r(x))$ . It is known that this  $\Psi(x)$  is a fundamental solution matrix, which we call the *canonical solution matrix* of (2.1) (for the detail, see [5, Section 1.1]).

We remark that for each pair  $(i, j)$  ( $i, j = 1, \dots, r$ ), the solution matrix  $\Psi_j(x)$  is expressed uniquely in the form

$$\Psi_j(x) = \Psi_i(x)C_{ij} + H_{ij}(x) \quad (2.10)$$

around  $x = t_i$ , where  $C_{ij}$  is an  $n_i \times n_j$  constant matrix and  $H_{ij}(x)$  is an  $n \times n_j$  solution matrix holomorphic around  $x = t_i$ . These matrices  $C_{ij}$  are called the *connection coefficients* for the canonical solution matrix  $\Psi(x)$ .

Fixing a base point  $p_0$  on  $\mathcal{D}$ , we denote by  $\gamma_i$  ( $i = 1, \dots, r$ ) and  $\gamma_\infty$  the homotopy classes in  $\pi_1(\mathcal{D}, p_0)$  of continuous paths encircling  $x = t_i$  and  $x = \infty$  in the positive direction, respectively; we choose these paths so that  $\gamma_\infty \gamma_1 \cdots \gamma_r = 1$  in  $\pi_1(\mathcal{D}, p_0)$  ([5, Figure 1]). The analytic continuation of  $\Psi(x)$  by  $\gamma_i$  ( $i = 1, \dots, r$ ) defines an  $r$ -tuple of matrices  $\mathbf{M} = (M_1, \dots, M_r) \in \text{GL}(n; \mathbb{C})^r$  as

$$\gamma_i \cdot \Psi(x) = \Psi(x)M_i \quad (i = 1, \dots, r). \quad (2.11)$$

These *monodromy matrices* are expressed as follows in terms of the connection coefficients ([5, Section 1.2]):

$$M_i = \begin{pmatrix} 1 & & & & & \\ & \ddots & & & & \\ (e(A_{ii}) - 1)C_{i1} & \dots & e(A_{ii}) & \dots & (e(A_{ii}) - 1)C_{ir} & \\ & & & \ddots & & \\ & & & & & 1 \end{pmatrix} \quad (i = 1, \dots, r), \quad (2.12)$$

where  $e(\mu) = e^{2\pi i \mu}$ .

In view of Theorem 2.5, we consider the Okubo system (2.6) obtained from (2.1) by the Katz operation (2.5). Let  $\Psi^{mc}(x) = (\Psi_1^{mc}(x), \dots, \Psi_k^{mc}(x), \dots, \Psi_r^{mc}(x))$  be the canonical solution matrix of (2.6), for which the  $k$ -th component is further decomposed as  $\Psi_k^{mc}(x) = (\Psi_{k1}^{mc}(x), \Psi_{k2}^{mc}(x))$ . The components of  $\Psi^{mc}(x)$  are characterized by the conditions

$$\Psi_j^{mc}(x) = F_j^{mc}(x)(x - t_j)^{A_{jj} - \rho + c}, \quad F_j^{mc}(t_j) = (0, I_{n_j}, 0)^t, \quad (j = 1, \dots, r; j \neq k), \quad (2.13)$$

around  $x = t_j$ , and

$$\begin{aligned} \Psi_{k1}^{mc}(x) &= F_{k1}^{mc}(x)(x - t_k)^{A_{kk}}, & F_{k1}^{mc}(t_k) &= (0, I_{n_k}, 0)^t, \\ \Psi_{k2}^{mc}(x) &= F_{k2}^{mc}(x)(x - t_k)^\rho, & F_{k2}^{mc}(t_k) &= (0, I_{\tilde{n}_k - n_k}, 0)^t. \end{aligned} \quad (2.14)$$

around  $x = t_k$ .



We remark that the connection coefficients  $C_{i(k2)}$  and  $C_{(k2)j}$  are not specified in this theorem. In the cases of the Okubo systems in Yokoyama's list, however, those coefficients can be determined by the symmetry of the characteristic exponents (Section 4).

### 3 Canonical forms of Okubo system of types II\*,III\*,IV,IV\*

Yokoyama's list is a class of rigid irreducible Okubo systems such that each diagonal block  $A_{ii} \in \text{Mat}(n_i; \mathbb{C})$  ( $i = 1, \dots, r$ ) of  $A$  has  $n_i$  mutually distinct eigenvalues and that the matrix  $A \in \text{Mat}(n; \mathbb{C})$  is diagonalizable. In this class we can assume that the diagonal blocks  $A_{ii}$  ( $i = 1, \dots, r$ ) are diagonal matrices with mutually distinct entries. We assume that  $A$  is diagonalized as

$$A \sim \text{diag}(\rho_1 I_{m_1}, \dots, \rho_q I_{m_q}) \quad (m_1 \geq \dots \geq m_q) \quad (3.1)$$

with mutually distinct  $\rho_1, \dots, \rho_q \in \mathbb{C}$ . Then the Okubo systems in Yokoyama's list are characterized by the following eight pairs  $(n_1, \dots, n_r)$ ,  $(m_1, \dots, m_q)$  of partitions of  $n$  respectively.

$$\begin{aligned} \text{(I)}_n : & \begin{cases} (n_1, n_2) = (n-1, 1) \\ (m_1, \dots, m_n) = (1, \dots, 1) \end{cases} & \text{(I}^*)_n : & \begin{cases} (n_1, \dots, n_n) = (1, \dots, 1) \\ (m_1, m_2) = (n-1, 1) \end{cases} \\ \text{(II)}_{2n} : & \begin{cases} (n_1, n_2) = (n, n) \\ (m_1, m_2, m_3) = (n, n-1, 1) \end{cases} & \text{(II}^*)_{2n} : & \begin{cases} (n_1, n_2, n_3) = (n, n-1, 1) \\ (m_1, m_2) = (n, n) \end{cases} \\ \text{(III)}_{2n+1} : & \begin{cases} (n_1, n_2) = (n+1, n) \\ (m_1, m_2, m_3) = (n, n, 1) \end{cases} & \text{(III}^*)_{2n+1} : & \begin{cases} (n_1, n_2, n_3) = (n, n, 1) \\ (m_1, m_2) = (n+1, n) \end{cases} \\ \text{(IV)}_6 : & \begin{cases} (n_1, n_2) = (4, 2) \\ (m_1, m_2, m_3) = (2, 2, 2) \end{cases} & \text{(IV}^*)_6 : & \begin{cases} (n_1, n_2, n_3) = (2, 2, 2) \\ (m_1, m_2) = (4, 2) \end{cases} \end{aligned} \quad (3.2)$$

In what follows, we use the symbols  $(\text{II}^*)_{2n}$ ,  $(\text{III}^*)_{2n+1}$ ,  $(\text{IV})_6$ , and  $(\text{IV}^*)_6$  to refer to the corresponding tuples  $\mathbf{A}$ . As for the nontrivial eigenvalues of  $A_{11}$ ,  $A_{22}$ ,  $A_{33}$  and  $A$ , we use the notations  $\alpha_i = \alpha_i^{(l)}$ ,  $\beta_i = \beta_i^{(l)}$ ,  $\gamma_i = \gamma_i^{(l)}$  and  $\rho_i = \rho_i^{(l)}$ , where  $l$  denotes the rank  $l$  of the Okubo system. In the following theorems, we give canonical forms of the Okubo systems of Yokoyama's list which we will use throughout this paper.

**Theorem 3.1.** *The systems  $(\text{II}^*)_{2n}$  and  $(\text{III}^*)_{2n+1}$  are expressed in the form*

$$(x - T) \frac{d}{dx} Y = \begin{pmatrix} \alpha & A_{12} & A_{13} \\ A_{21} & \beta & A_{23} \\ A_{31} & A_{32} & \gamma \end{pmatrix} Y, \quad (3.3)$$

where the matrices  $A_{kl}$  are given as follows.

(II\*)<sub>2n</sub>

$$\begin{aligned}
(A_{12})_{ij} &= \frac{\prod_{k \neq i}^n (\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1} (\beta_j - \beta_k)} \quad (i = 1, \dots, n; j = 1, \dots, n-1), \\
(A_{13})_i &= 1 \quad (i = 1, \dots, n), \\
(A_{23})_i &= 1 \quad (i = 1, \dots, n-1), \\
(A_{21})_{ij} &= (\alpha_j - \rho_1)(\alpha_j - \rho_2) \frac{\prod_{k \neq i}^{n-1} (\alpha_j + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\alpha_j - \alpha_k)} \quad (i = 1, \dots, n-1, j = 1, \dots, n), \\
(A_{31})_j &= -(\alpha_j - \rho_1)(\alpha_j - \rho_2) \frac{\prod_{k=1}^{n-1} (\alpha_j + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\alpha_j - \alpha_k)} \quad (j = 1, \dots, n), \\
(A_{32})_j &= -\frac{\prod_{k=1}^n (\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1} (\beta_j - \beta_k)} \quad (j = 1; \dots, n-1),
\end{aligned} \tag{3.4}$$

(III\*)<sub>2n+1</sub>

$$\begin{aligned}
(A_{12})_{ij} &= (\beta_j - \rho_1) \frac{\prod_{k \neq i}^n (\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\beta_j - \beta_k)} \quad (i, j = 1, \dots, n), \\
(A_{13})_i &= 1 \quad (i = 1, \dots, n), \\
(A_{23})_i &= 1 \quad (i = 1, \dots, n), \\
(A_{21})_{ij} &= (\alpha_j - \rho_1) \frac{\prod_{k \neq i}^n (\alpha_j + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\alpha_j - \alpha_k)} \quad (i, j = 1, \dots, n), \\
(A_{31})_j &= -(\alpha_j - \rho_1) \frac{\prod_{k=1}^n (\alpha_j + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\alpha_j - \alpha_k)} \quad (j = 1, \dots, n), \\
(A_{32})_j &= -(\beta_j - \rho_1) \frac{\prod_{k=1}^n (\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^n (\beta_j - \beta_k)} \quad (j = 1, \dots, n).
\end{aligned} \tag{3.5}$$

The symbol  $\prod_{k \neq i}^m$  stands for the product over  $k$  such that  $1 \leq k \leq m$  and  $k \neq i$ .

**Theorem 3.2.** *The system (IV)<sub>6</sub> is expressed in the form*

$$(x - T) \frac{d}{dx} Y = \begin{pmatrix} \alpha & A_{12} \\ A_{21} & \beta \end{pmatrix} Y \tag{3.6}$$

where the matrices  $A_{kl}$  are given as follows.

$$\begin{aligned}
(A_{12})_{ij} &= \frac{\prod_{k \neq i}^3 (\alpha_k + \alpha_4 + \beta_j - \rho_1 - \rho_2 - \rho_3)}{\prod_{k \neq j}^2 (\beta_j - \beta_k)} \quad (i = 1, 2, 3; j = 1, 2), \\
(A_{12})_{4j} &= \frac{1}{\prod_{k \neq j}^2 (\beta_j - \beta_k)} \quad (j = 1, 2), \\
(A_{21})_{ij} &= \prod_{k=1}^3 (\alpha_j - \rho_k) \frac{\prod_{k \neq i}^2 (\alpha_j + \alpha_4 + \beta_k - \rho_1 - \rho_2 - \rho_3)}{\prod_{k \neq j}^4 (\alpha_j - \alpha_k)} \quad (i = 1, 2; j = 1, 2, 3), \\
(A_{21})_{i4} &= \prod_{k=1}^3 (\alpha_j - \rho_k) \frac{\prod_{k=1}^3 \prod_{l \neq i}^2 (\alpha_k + \alpha_4 + \beta_l - \rho_1 - \rho_2 - \rho_3)}{\prod_{k \neq j}^4 (\alpha_j - \alpha_k)} \quad (i = 1, 2).
\end{aligned} \tag{3.7}$$

**Theorem 3.3.** *The system  $(IV^*)_6$  is expressed in the form*

$$(x-T)\frac{d}{dx}Y = \begin{pmatrix} \alpha_1 & 0 & h_{212} & h_{222} & 1 & h_{212}h_{222} \\ 0 & \alpha_2 & h_{112} & h_{122} & 1 & h_{112}h_{122} \\ h_{122} & h_{222} & \beta_1 & 0 & 1 & -h_{122}h_{222} \\ h_{112} & h_{212} & 0 & \beta_2 & 1 & -h_{112}h_{212} \\ -h_{112}h_{122} & -h_{212}h_{222} & -h_{112}h_{212} & -h_{122}h_{222} & \gamma_1 & 0 \\ -1 & -1 & 1 & 1 & 0 & \gamma_2 \end{pmatrix} DY, \quad (3.8)$$

where the notations

$$h_{ijk} = \alpha_i + \beta_j + \gamma_k - 2\rho_1 - \rho_2, \quad (3.9)$$

and  $D = \text{diag}(a_1, a_2, b_1, b_2, c_1, c_2)$  denotes the diagonal matrix defined by

$$a_j = \frac{\alpha_j - \rho_1}{\prod_{k \neq j}^2 (\alpha_j - \alpha_k)}, \quad b_j = \frac{\beta_j - \rho_1}{\prod_{k \neq j}^2 (b_j - b_k)}, \quad c_j = \frac{\gamma_j - \rho_1}{\prod_{k \neq j}^2 (\gamma_j - \gamma_k)} \quad (j = 1, 2). \quad (3.10)$$

*Proof of Theorems 3.1, 3.2 and 3.3. Case II\*, III\*:* Firstly, the system  $(III^*)_3$  is obtained by  $\text{mc}_{\mu_1}$  from the differential equation

$$\frac{dy}{dx} = \left( \frac{\alpha_1^{(1)}}{x-t_1} + \frac{\beta_1^{(1)}}{x-t_2} + \frac{\gamma_1^{(1)}}{x-t_3} \right) y. \quad (3.11)$$

The resulting system is given by

$$(x-T)\frac{d}{dx}Y = \begin{pmatrix} \alpha_1 & \beta_1 - \rho_1 & \rho_1 + \rho_2 - \alpha_1 - \beta_1 \\ \alpha_1 - \rho_1 & \beta_1 & \rho_1 + \rho_2 - \alpha_1 - \beta_1 \\ \alpha_1 - \rho_1 & \beta_1 - \rho_1 & \gamma \end{pmatrix} Y \quad (3.12)$$

with characteristic exponents specified by

$$\begin{cases} \alpha_1 = \alpha_1^{(1)} + \mu_1, & \beta_1 = \beta_1^{(1)} + \mu_1, & \gamma = \gamma_1^{(1)} + \mu_1, \\ \rho_1 = \mu_1, & \rho_2 = \alpha_1^{(1)} + \beta_1^{(1)} + \gamma_1^{(1)} + \mu_1. \end{cases} \quad (3.13)$$

It can be transformed into the canonical form

$$(III^*)_3 = \begin{pmatrix} \alpha_1 & \beta_1 - \rho_1 & 1 \\ \alpha_1 - \rho_1 & \beta_1 & 1 \\ \frac{\alpha_1 - \rho_1}{\rho_1 + \rho_2 - \alpha_1 - \beta_1} & \frac{\beta_1 - \rho_1}{\rho_1 + \rho_2 - \alpha_1 - \beta_1} & \gamma \end{pmatrix} \quad (3.14)$$

by conjugation with the diagonal matrix

$$\text{diag}(1, 1, \rho_1 + \rho_2 - \alpha_1 - \beta_1). \quad (3.15)$$

Starting from the  $(III^*)_3$ , the Okubo systems  $(II^*)_{2n}$  and  $(III^*)_{2n+1}$  can be constructed inductively by the following Katz operations:

$$\begin{aligned} (II^*)_{2n} &= \text{add}_{(\rho_2, 0, 0)} \circ \text{mc}_{-a_{n-1} - \rho_2} \circ \text{add}_{(a_{n-1}, 0, 0)} (III^*)_{2n-1}, \\ (III^*)_{2n+1} &= \text{add}_{(0, \rho_2, 0)} \circ \text{mc}_{-b_n - \rho_2} \circ \text{add}_{(0, b_n, 0)} (II^*)_{2n}. \end{aligned} \quad (3.16)$$

Therefore, by Theorem 2.1 we obtain canonical forms of the Okubo system types  $(\text{II}^*)_{2n}$  and  $(\text{III}^*)_{2n+1}$  inductively. We remark that the construction of the system is equivalent to the computation of  $\xi$  and  $\eta$  of Theorem 2.1.

Assume that the system  $(\text{III}^*)_{2n-1}$  is given as in our canonical form of Theorem 3.1. By Theorem 2.1, the Katz operation (3.16) for  $(\text{III}^*)_{2n-1}$  gives rise to the Okubo system  $(x - T)\frac{d}{dx}W = A^{mc}W$  where

$$A^{mc} = \begin{pmatrix} \alpha & 0 & A_{12} & A_{13} \\ 0 & \rho_2 & \eta_2 & \eta_3 \\ A_{21}(\alpha + a_{n-1})(\alpha - \rho_2)^{-1} & (\rho_2 + a_{n-1})\xi_2 & \beta - a_{n-1} - \rho_2 & A_{23} \\ A_{31}(\alpha + a_{n-1})(\alpha - \rho_2)^{-1} & (\rho_2 + a_{n-1})\xi_3 & A_{32} & \gamma - a_{n-1} - \rho_2 \end{pmatrix}. \quad (3.17)$$

Renaming the characteristic exponents of (3.17) as

$$\begin{cases} \alpha_i^{(2n)} = \alpha_i & (1 \leq i \leq n-1), & \alpha_n^{(2n)} = \rho_2, \\ \beta_i^{(2n)} = \beta_i - \rho_2 - a_{n-1} & (1 \leq i \leq n), \\ \gamma^{(2n)} = \gamma - a_{n-1} - \rho_2, & \rho_1^{(2n)} = -a_{n-1}, & \rho_2^{(2n)} = \rho_1, \end{cases} \quad (3.18)$$

we see that  $A^{mc}$  is in the canonical form of type  $(\text{II}^*)_{2n}$  except for the vectors  $\xi_k, \eta_l$  to be determined by the formula

$$\xi_k \eta_l = A_{kl} - A_{k1}(A_{11} - \rho_2)A_{1l}. \quad (3.19)$$

The values of  $(\xi_k)_i(\eta_l)_j$  are computed as follows by partial fractional expansions:

$$\begin{aligned} (\xi_2)_i(\eta_2)_j &= (\beta_i - \rho_2)\delta_{ij} - \sum_{p=1}^{n-1} \frac{\alpha_p - \rho_1}{\alpha_p - \rho_2} \frac{\prod_{k \neq i}^{n-1}(\alpha_p + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq p}^{n-1}(\alpha_p - \alpha_k)} (\beta_j - \rho_1) \frac{\prod_{k \neq p}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \\ &= (\beta_i - \rho_2)\delta_{ij} - \frac{(\beta_j - \rho_1)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \sum_{p=1}^{n-1} \frac{\alpha_p - \rho_1}{\alpha_p - \rho_2} \frac{\prod_{k \neq i}^{n-1}(\alpha_p + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq p}^{n-1}(\alpha_p - \alpha_k)} \prod_{k \neq p}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2) \\ &= (\beta_i - \rho_2)\delta_{ij} - \frac{(\beta_j - \rho_1) \prod_{k=1}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \sum_{p=1}^{n-1} \frac{\alpha_p - \rho_1}{\alpha_p - \rho_2} \frac{\prod_{k \neq i, j}^{n-1}(\alpha_p + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq p}^{n-1}(\alpha_p - \alpha_k)} \\ &= (\beta_i - \rho_2)\delta_{ij} - \frac{(\beta_j - \rho_1) \prod_{k=1}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \sum_{p=1}^{n-1} \frac{\prod_{k \neq i, j}^n(\alpha'_p + \beta'_k - \rho'_1 - \rho'_2)}{\prod_{k \neq p}^n(\alpha'_p - \alpha'_k)} \\ &= \frac{(\beta_j - \rho_1) \prod_{k=1}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \frac{\prod_{k \neq i, j}^n(\alpha'_n + \beta'_k - \rho'_1 - \rho'_2)}{\prod_{k \neq n}^n(\alpha'_n - \alpha'_k)} \\ &= (\rho_2 - \rho_1) \frac{(\beta_j - \rho_1) \prod_{k=1}^{n-1}(\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1}(\beta_j - \beta_k)} \frac{\prod_{k \neq i, j}^{n-1}(\beta_k - \rho_1)}{\prod_{k \neq n}^n(\rho_2 - \alpha_k)} \end{aligned} \quad (3.20)$$

where  $\alpha_i = \alpha'_i$ ,  $\beta_i = \beta'_i + \alpha'_n - \beta'_n$ ,  $\rho_1 = \rho'_1 + \rho'_2 - \beta'_n$ ,  $\rho_2 = \alpha'_n$ , and

$$\xi_3 \eta_3 = \gamma - \rho_2 - \sum_{p=1}^{n-1} \frac{\alpha_p - \rho_1}{\alpha_p - \rho_2} \frac{\prod_{k=1}^{n-1}(\alpha_p + \beta_k - \rho_1 - \rho_2)}{\prod_{k \neq p}^{n-1}(\alpha_p - \alpha_k)} = \frac{\prod_{k=1}^{n-1}(\beta_k - \rho_1)}{\prod_{k=1}^{n-1}(\rho_2 - \alpha_k)}. \quad (3.21)$$



Therefore we can choose  $(\xi_2)_i, (\eta_2)_j, \xi_3, \eta_3$  as

$$\begin{aligned} (\xi_2)_i &= (\rho_2 - \rho_1) \frac{\prod_{k \neq i}^{n-1} (\beta_k - \rho_1)}{\prod_{k=1}^{n-1} (\rho_2 - \alpha_k)}, & (\eta_2)_j &= \frac{\prod_{k=1}^{n-1} (\beta_j + \alpha_k - \rho_1 - \rho_2)}{\prod_{k \neq j}^{n-1} (\beta_j - \beta_k)}, \\ \xi_3 &= \frac{\prod_{k=1}^{n-1} (\beta_k - \rho_1)}{\prod_{k=1}^{n-1} (\rho_2 - \alpha_k)}, & \eta_3 &= 1, \end{aligned} \quad (3.22)$$

so that  $A^{mc}$  gives rise to the canonical form of type  $(\text{II}^*)_{2n}$ . Similarly, applying the Katz operation to the canonical form of  $(\text{II}^*)_{2n}$ , we obtain the canonical form of type  $(\text{III}^*)_{2n+1}$ .

**Case IV:** The Okubo system of type  $(\text{IV})_6$  is constructed by

$$(\text{IV})_6 = \text{add}_{(\rho_3, 0)} \circ \text{mc}_{-c-\rho_3} \circ \text{add}_{(c, 0)} (\text{III})_5. \quad (3.23)$$

One can directly verify that the the canonical form of type  $(\text{IV})_6$  is obtained from the canonical form of type  $(\text{III})_5$  in [5] by choosing  $\xi$  and  $\eta$  appropriately.

**Case IV\*:** The Okubo system of type  $(\text{IV}^*)_6$  is constructed by

$$(\text{IV}^*)_6 = \text{add}_{(0, 0, \rho_1)} \circ \text{mc}_{-c-\rho_1} \circ \text{add}_{(0, 0, c)} (\text{III}^*)_5. \quad (3.24)$$

One can directly verify that the the canonical form of type  $(\text{IV}^*)_6$  is obtained from the canonical form of type  $(\text{III}^*)_5$  of Theorem 3.1 by choosing  $\xi$  and  $\eta$  appropriately.  $\square$

## 4 Construction of connection coefficients of Okubo system

### 4.1 Main results

In this section we present explicit formulas for the connection matrices  $C_{kl}$  of types  $\text{II}^*, \text{III}^*, \text{IV}, \text{IV}^*$  corresponding to the canonical forms of Theorems 3.1, 3.2, 3.3.

**Theorem 4.1.** *For the Okubo systems (3.4) and (3.5) of types  $(\text{II}^*)_{2n}$  and  $(\text{III}^*)_{2n+1}$ , the connection coefficients of the canonical solution matrices are expressed as follows:*

$(\text{II}^*)_{2n}$

$$\begin{aligned} (C_{12}^{(2n)})_{ij} &= (-1)^{n-1} e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_i - \beta_j - \gamma)\right)} \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_i - \gamma}}{(t_2 - t_1)^{\rho_1 + \rho_2 - \beta_j - \gamma}} \left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_i - \beta_j} \\ &\quad \frac{\Gamma(-\alpha_i) \Gamma(\beta_j + 1)}{\Gamma(1 + \rho_1 - \alpha_i) \Gamma(1 + \rho_2 - \alpha_i)} \frac{\prod_{k \neq j}^{n-1} \Gamma(\beta_j - \beta_k)}{\prod_{k \neq i}^n \Gamma(\beta_j + \alpha_k - \rho_1 - \rho_2)} \frac{\prod_{k \neq i}^n \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq j}^{n-1} \Gamma(1 + \rho_1 + \rho_2 - \alpha_i - \beta_k)} \end{aligned} \quad (4.1)$$

$$\begin{aligned} (C_{13}^{(2n)})_i &= (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_i - \beta_1 - \gamma)\right)} \frac{(t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_i - \beta_1}}{(t_3 - t_1)^{\rho_1 + \rho_2 - \beta_1 - \gamma}} \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_i - \gamma} \\ &\quad (\rho_1 + \rho_2 - \alpha_i - \beta_1)^{-1} \frac{\Gamma(\gamma + 1) \Gamma(-\alpha_i)}{\Gamma(1 + \rho_1 - \alpha_i) \Gamma(1 + \rho_2 - \alpha_i)} \frac{\prod_{k \neq i}^n \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k=1}^{n-1} \Gamma(1 + \rho_1 + \rho_2 - \alpha_i - \beta_k)} \end{aligned} \quad (4.2)$$

$$(C_{23}^{(2n)})_i = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_i - \gamma)\right)} \frac{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_i}}{(t_3 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}} \left(\frac{t_2 - t_1}{t_3 - t_1}\right)^{\rho_1 + \rho_2 - \beta_i - \gamma} \\ (\rho_1 + \rho_2 - \alpha_1 - \beta_i)^{-1} \Gamma(\gamma + 1) \Gamma(-\beta_i) \frac{\prod_{k \neq i}^{n-1} \Gamma(1 + \beta_k - \beta_i)}{\prod_{k=1}^n \Gamma(1 + \rho_1 + \rho_2 - \alpha_k - \beta_i)} \quad (4.3)$$

$$(C_{21}^{(2n)})_{ij} = (-1)^n e^{\left(\frac{-1}{2}(\alpha_j + \beta_i + \gamma - \rho_1 - \rho_2)\right)} \frac{(t_2 - t_1)^{\rho_1 + \rho_2 - \beta_i - \gamma}}{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_j - \gamma}} \left(\frac{t_2 - t_3}{t_1 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_i - \beta_j} \\ \frac{\Gamma(\alpha_j + 1) \Gamma(-\beta_i)}{\Gamma(1 + \rho_1 - \beta_j) \Gamma(1 + \rho_2 - \beta_j)} \frac{\prod_{k \neq i}^{n-1} \Gamma(\beta_k - \beta_i + 1)}{\prod_{k \neq j}^n \Gamma(1 + \rho_1 + \rho_2 - \beta_i - \alpha_k)} \frac{\prod_{k \neq j}^n \Gamma(\alpha_j - \alpha_k)}{\prod_{k \neq i}^{n-1} \Gamma(\alpha_j + \beta_k - \rho_1 - \rho_2)} \quad (4.4)$$

$$(C_{31}^{(2n)})_j = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_j - \beta_1 - \gamma)\right)} \frac{(t_3 - t_1)^{\rho_1 + \rho_2 - \alpha_j - \beta_1}}{(t_1 - t_3)^{\rho_1 + \rho_2 - \beta_1 - \gamma}} \left(\frac{t_3 - t_2}{t_1 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_j - \gamma} \\ (\rho_1 + \rho_2 - \alpha_i - \beta_1) \frac{\Gamma(-\gamma) \Gamma(\alpha_j + 1)}{\Gamma(\alpha_j - \rho_1) \Gamma(\alpha_j - \rho_2)} \frac{\prod_{k \neq j}^n \Gamma(\alpha_j - \alpha_k)}{\prod_{k=1}^{n-1} \Gamma(\alpha_j + \beta_k - \rho_1 - \rho_2)} \quad (4.5)$$

$$(C_{32}^{(2n)})_j = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_j - \gamma)\right)} \frac{(t_3 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}}{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_j}} \left(\frac{t_3 - t_1}{t_2 - t_1}\right)^{\rho_1 + \rho_2 - \beta_j - \gamma} \\ (\rho_1 + \rho_2 - \alpha_1 - \beta_j) \Gamma(-\gamma) \Gamma(\beta_j + 1) \frac{\prod_{k \neq j}^{n-1} \Gamma(\beta_j - \beta_k)}{\prod_{k=1}^n \Gamma(\alpha_k + \beta_j - \rho_1 - \rho_2)} \quad (4.6)$$

(III\*)<sub>2n+1</sub>

$$(C_{12}^{(2n+1)})_{ij} = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_i - \beta_j - \gamma)\right)} \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_i - \gamma}}{(t_2 - t_1)^{\rho_1 + \rho_2 - \beta_j - \gamma}} \left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_i - \beta_j} \\ \frac{\Gamma(-\alpha_i) \Gamma(\beta_j + 1)}{\Gamma(1 + \rho_1 - \alpha_i) \Gamma(\beta_j - \rho_1)} \frac{\prod_{k \neq j}^n \Gamma(\beta_j - \beta_k)}{\prod_{k \neq i}^n \Gamma(\beta_j + \alpha_k - \rho_1 - \rho_2)} \frac{\prod_{k \neq i}^n \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq j}^n \Gamma(1 + \rho_1 + \rho_2 - \alpha_i - \beta_k)} \quad (4.7)$$

$$(C_{13}^{(2n+1)})_i = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_i - \beta_1 - \gamma)\right)} \frac{(t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_i - \beta_1}}{(t_3 - t_1)^{\rho_1 + \rho_2 - \beta_1 - \gamma}} \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_i - \gamma} \\ \frac{\Gamma(\gamma + 1) \Gamma(-\alpha_i)}{\Gamma(1 + \rho_1 - \alpha_i)} \frac{\prod_{k \neq i}^n \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k=1}^n \Gamma(1 + \rho_1 + \rho_2 - \alpha_i - \beta_k)} \quad (4.8)$$

$$(C_{23}^{(2n+1)})_i = (-1)^n e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_i - \gamma)\right)} \frac{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_i}}{(t_3 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}} \left(\frac{t_2 - t_1}{t_3 - t_1}\right)^{\rho_1 + \rho_2 - \beta_i - \gamma} \\ \frac{\Gamma(\gamma + 1) \Gamma(-\beta_i)}{\Gamma(1 + \rho_1 - \beta_i)} \frac{\prod_{k \neq i}^n \Gamma(1 + \beta_k - \beta_i)}{\prod_{k=1}^n \Gamma(1 + \rho_1 + \rho_2 - \alpha_k - \beta_i)} \quad (4.9)$$

$$(C_{21}^{(2n+1)})_{ij} = (-1)^n e\left(\frac{-1}{2}(\rho_1 + \rho_2 - \alpha_j - \beta_i - \gamma)\right) \frac{(t_2 - t_1)^{\beta_i + \gamma - \rho_1 - \rho_2}}{(t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_i - \beta_j}} \left(\frac{t_2 - t_3}{t_1 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_j - \gamma} \\ \frac{\Gamma(\alpha_j + 1)\Gamma(-\beta_i)}{\Gamma(\alpha_j - \rho_1)\Gamma(1 + \rho_1 - \beta_i)} \frac{\prod_{k \neq i}^n \Gamma(1 + \beta_k - \beta_j)}{\prod_{k \neq j}^n \Gamma(1 + \rho_1 + \rho_2 - \beta_i - \alpha_k)} \frac{\prod_{k \neq j}^n \Gamma(\alpha_j - \alpha_k)}{\prod_{k \neq i}^n \Gamma(\alpha_j + \beta_k - \rho_1 - \rho_2)} \quad (4.10)$$

$$(C_{31}^{(2n+1)})_j = (-1)^n e\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_j - \beta_1 - \gamma)\right) \frac{(t_3 - t_1)^{\rho_1 + \rho_2 - \alpha_j - \beta_1}}{(t_1 - t_3)^{\rho_1 + \rho_2 - \beta_1 - \gamma}} \left(\frac{t_3 - t_2}{t_1 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_j - \gamma} \\ \frac{\Gamma(-\gamma)\Gamma(\alpha_j + 1)}{\Gamma(\alpha_j - \rho_1)} \frac{\prod_{k \neq j}^n \Gamma(\alpha_j - \alpha_k)}{\prod_{k=1}^n \Gamma(\alpha_j + \beta_k - \rho_1 - \rho_2)} \quad (4.11)$$

$$(C_{32}^{(2n+1)})_j = (-1)^n e\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_i - \gamma)\right) \frac{(t_3 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}}{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_i}} \left(\frac{t_3 - t_1}{t_2 - t_1}\right)^{\rho_1 + \rho_2 - \beta_i - \gamma} \\ \frac{\Gamma(-\gamma)\Gamma(\beta_j + 1)}{\Gamma(\beta_j - \rho_1)} \frac{\prod_{k \neq j}^n \Gamma(\beta_j - \beta_k)}{\prod_{k=1}^n \Gamma(\alpha_k + \beta_j - \rho_1 - \rho_2)} \quad (4.12)$$

**Theorem 4.2.** For the Okubo systems (3.7) of type (IV)<sub>6</sub>, the connection coefficients of the canonical solution matrix are expressed as follows.

$$(C_{12})_{ij} = e\left(\frac{1}{2}(-\alpha_i - \beta_j)\right) \frac{(t_2 - t_1)^{\rho_3 - \alpha_i}}{(t_1 - t_2)^{\rho_3 - \beta_j}} \frac{\Gamma(-\alpha_i)\Gamma(\beta_j + 1)}{\prod_{k=1}^3 \Gamma(1 + \rho_k - \alpha_i)} \\ \frac{\prod_{k \neq j}^2 \Gamma(\beta_j - \beta_k) \prod_{k \neq i, 4}^4 \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq i}^3 \Gamma(\beta_j + \alpha_k + \alpha_4 - \rho_1 - \rho_2 - \rho_3) \prod_{k \neq j}^2 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \alpha_i - \alpha_4 - \beta_k)} \quad (i = 1, 2, 3; j = 1, 2). \quad (4.13)$$

$$(C_{12})_{4j} = \frac{e\left(\frac{1}{2}(-\alpha_4 - \beta_j)\right)}{\prod_{k \neq j}^2 \prod_{k \neq 1}^3 (\alpha_1 + \alpha_k + \beta_j - \rho_1 - \rho_2 - \rho_3)} \frac{(t_2 - t_1)^{\rho_3 - \alpha_4}}{(t_1 - t_2)^{\rho_3 - \beta_j}} \frac{\Gamma(-\alpha_4)\Gamma(\beta_j + 1)}{\prod_{k=1}^3 \Gamma(1 + \rho_k - \alpha_4)} \\ \frac{\prod_{k \neq j}^2 \Gamma(\beta_j - \beta_k) \prod_{k \neq 4}^4 \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq 1, 4}^4 \Gamma(\beta_j + \alpha_k + \alpha_1 - \rho_1 - \rho_2 - \rho_3) \prod_{k \neq j}^2 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \alpha_1 - \alpha_4 - \beta_k)} \quad (j = 1, 2). \quad (4.14)$$

$$(C_{21})_{ij} = -e\left(\frac{1}{2}(\alpha_j + \alpha_4 + \beta_i - 2\rho_3)\right) \frac{(t_2 - t_1)^{\alpha_4 - \beta_i}}{(t_1 - t_2)^{\alpha_4 - \alpha_j}} \frac{\Gamma(-\beta_i)\Gamma(\alpha_j + 1)}{\Gamma(\alpha_j - \rho_1)\Gamma(\alpha_j - \rho_2)\Gamma(\alpha_j - \rho_3)} \\ \frac{\prod_{k \neq j}^4 \Gamma(\alpha_j - \alpha_k) \prod_{k \neq i}^2 \Gamma(1 + \beta_k - \beta_i)}{\prod_{k \neq i}^2 \Gamma(\alpha_j + \alpha_4 + \beta_k - \rho_1 - \rho_2 - \rho_3) \prod_{k \neq j, 4}^4 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \alpha_k - \beta_i - \alpha_4)} \quad (i = 1, 2; j = 1, 2, 3). \quad (4.15)$$

$$(C_{21})_{i4} = \prod_{k \neq i}^3 (\alpha_1 + \alpha_k + \beta_j - \rho_1 - \rho_2 - \rho_3) e^{\left(\frac{1}{2}(\alpha_1 + \alpha_4 + \beta_i - 2\rho_3)\right)} \frac{(t_2 - t_1)^{\alpha_4 - \beta_i}}{(t_1 - t_2)^{\alpha_4 - \alpha_j}} \frac{\Gamma(-\beta_i)\Gamma(\alpha_4 + 1)}{\Gamma(\alpha_4 - \rho_1)\Gamma(\alpha_4 - \rho_2)\Gamma(\alpha_4 - \rho_3)} \\ \frac{\prod_{k \neq j}^4 \Gamma(\alpha_j - \alpha_k) \prod_{k \neq i}^2 \Gamma(1 + \beta_k - \beta_i)}{\prod_{k \neq i}^2 \Gamma(\alpha_1 + \alpha_4 + \beta_k - \rho_1 - \rho_2 - \rho_3) \prod_{k \neq 1,4}^4 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \alpha_k - \beta_i - \alpha_1)} \quad (i = 1, 2). \quad (4.16)$$

**Theorem 4.3.** For the Okubo systems (3.8) of types  $(\text{IV}^*)_6$ , the connection coefficients of the canonical solution matrices are expressed as follows.

$$(C_{12})_{ij} = e^{\left(\frac{1}{2}(2\rho_1 + \rho_2 - \alpha_i - \beta_j - \gamma_1 - \gamma_2)\right)} \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_i - \gamma_1}}{(t_2 - t_1)^{\rho_1 + \rho_2 - \beta_j - \gamma_1}} \left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_i - \beta_j} \\ \frac{\Gamma(-\alpha_i)\Gamma(\beta_j + 1)}{\Gamma(1 + \rho_1 - \alpha_i)\Gamma(\beta_j - \rho_1)} \frac{\prod_{k \neq j}^2 \Gamma(\beta_j - \beta_k) \prod_{k \neq i}^2 \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq i}^2 \Gamma(\alpha_k + \beta_j + \gamma_2 - 2\rho_1 - \rho_2) \prod_{k \neq j}^2 \Gamma(1 + 2\rho_1 + \rho_2 - \alpha_i - \beta_k - \gamma_2)} \quad (4.17)$$

$$(C_{13})_{ij} = \left(\prod_{k \neq i}^2 h_{k2j} \prod_{k \neq j}^2 h_{i2k}\right)^{\delta_{2j}} e^{\left(\frac{1}{2}(2\rho_1 + \rho_2 - \alpha_i - \beta_1 - \gamma_1 - \gamma_2)\right)} \frac{(t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_i - \beta_1}}{(t_3 - t_1)^{\rho_1 + \rho_2 - \beta_1 - \gamma_j}} \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_i - \gamma_j} \\ \frac{\Gamma(\gamma_j + 1)\Gamma(-\alpha_i)}{\Gamma(1 + \rho_1 - \alpha_i)\Gamma(\gamma_j - \rho_1)} \frac{\prod_{k \neq j}^2 \Gamma(\gamma_j - \gamma_k) \prod_{k \neq i}^2 \Gamma(1 + \alpha_k - \alpha_i)}{\prod_{k \neq i}^2 \Gamma(1 + \alpha_k + \beta_2 + \gamma_j - 2\rho_1 - \rho_2) \prod_{k \neq j}^2 \Gamma(1 + 2\rho_1 + \rho_2 - \alpha_i - \beta_2 - \gamma_k)} \quad (4.18)$$

$$(C_{23})_{ij} = \left(\prod_{k \neq i}^2 h_{2kj} \prod_{k \neq j}^2 h_{2ik}\right)^{\delta_{2j}} e^{\left(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_i - \gamma_j)\right)} \frac{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_i}}{(t_3 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma_j}} \left(\frac{t_2 - t_1}{t_3 - t_1}\right)^{\rho_1 + \rho_2 - \beta_i - \gamma_j} \\ \frac{\Gamma(\gamma_j + 1)\Gamma(-\beta_i)}{\Gamma(1 + \rho_1 - \beta_i)\Gamma(\gamma_j - \rho_1)} \frac{\prod_{k \neq j}^2 \Gamma(\gamma_j - \gamma_k) \prod_{k \neq i}^2 \Gamma(1 + \beta_k - \beta_i)}{\prod_{k \neq i}^2 \Gamma(1 + \alpha_2 + \beta_k + \gamma_j - 2\rho_1 - \rho_2) \prod_{k \neq j}^2 \Gamma(1 + 2\rho_1 + \rho_2 - \alpha_2 - \beta_i - \gamma_k)} \quad (4.19)$$

$$(C_{21})_{ij} = e^{\left(\frac{1}{2}(2\rho_1 + \rho_2 - \alpha_i - \beta_j - \gamma_1 - \gamma_2)\right)} \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_j - \gamma_1}}{(t_2 - t_1)^{\rho_1 + \rho_2 - \beta_i - \gamma_1}} \left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_i - \beta_j} \\ \frac{\Gamma(\alpha_j + 1)\Gamma(-\beta_i)}{\Gamma(1 + \rho_1 - \beta_i)\Gamma(\alpha_j - \rho_1)} \frac{\prod_{k \neq j}^2 \Gamma(\alpha_j - \alpha_k) \prod_{k \neq i}^2 \Gamma(1 + \beta_k - \beta_i)}{\prod_{k \neq i}^2 \Gamma(\alpha_j + \beta_k + \gamma_2 - 2\rho_1 - \rho_2) \prod_{k \neq j}^2 \Gamma(1 + 2\rho_1 + \rho_2 - \alpha_k - \beta_i - \gamma_2)} \quad (4.20)$$

$$(C_{31})_{ij} = \frac{e^{\left(\frac{1}{2}(2\rho_1 + \rho_2 - \alpha_j - \beta_1 - \gamma_i - \gamma_2)\right)} (t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_j - \beta_1}}{\left(\prod_{k \neq i}^2 h_{j2k} \prod_{k \neq j}^2 h_{k2i}\right)^{\delta_{i2}} (t_3 - t_1)^{\beta_1 + \gamma_i - \rho_1 - \rho_2}} \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_j - \gamma_i} \\ \frac{\Gamma(-\gamma_i)\Gamma(1 + \alpha_j)}{\Gamma(1 + \rho_1 - \gamma_i)\Gamma(\alpha_j - \rho_1)} \frac{\prod_{k \neq j} \Gamma(\alpha_j - \alpha_k) \prod_{k \neq i} \Gamma(1 + \gamma_i - \gamma_k)}{\prod_{k \neq i} \Gamma(\alpha_j + \beta_2 + \gamma_k - 2\rho_1 - \rho_2) \prod_{k \neq j}^2 \Gamma(2\rho_1 + \rho_2 - \alpha_k - \beta_2 - \gamma_i)} \quad (4.21)$$

$$(C_{32})_{ij} = \frac{e(\frac{1}{2}(2\rho_1 + \rho_2 - \alpha_1 - \beta_j - \gamma_1 - \gamma_2))}{(\prod_{k \neq i}^2 h_{2jk} \prod_{k \neq i}^2 h_{2ki})^{\delta_{i2}}} \frac{(t_2 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_j}}{(t_3 - t_2)^{\alpha_1 + \gamma_i - \rho_1 - \rho_2}} \left( \frac{t_2 - t_1}{t_3 - t_1} \right)^{\rho_1 + \rho_2 - \beta_j - \gamma_i}$$

$$\frac{\Gamma(-\gamma_i)\Gamma(1 + \beta_j)}{\Gamma(1 + \rho_1 - \gamma_i)\Gamma(\beta_j - \rho_1)} \frac{\prod_{k \neq j} \Gamma(\beta_j - \beta_k) \prod_{k \neq i} \Gamma(1 + \gamma_i - \gamma_k)}{\prod_{k \neq i} \Gamma(\alpha_2 + \beta_j + \gamma_k - 2\rho_1 - \rho_2) \prod_{k \neq j} \Gamma(\rho_1 + \rho_2 - \alpha_2 - \beta_k - \gamma_i)}$$
(4.22)

## 4.2 Proof of the main theorems

Before the proof of Theorems 4.1, 4.2 and 4.3, we give a simple remark concerning the symmetry of Okubo systems.

**Lemma 4.4.** *Assume that the Okubo system (2.1) is obtained by conjugation from an Okubo system*

$$(x - T) \frac{d}{dx} Y = BY \quad (4.23)$$

as

$$A = \text{Ad}(D)B = DBD^{-1}, \quad D = \text{diag}(D_1, \dots, D_r), \quad D_i \in \text{GL}(n_i, \mathbb{C}) \quad (i = 1, \dots, r). \quad (4.24)$$

Let  $C_{ij}^A$  and  $C_{ij}^B$  ( $1 \leq i, j \leq r$ ) be the connection matrices for the canonical solution matrices of (2.1) and (4.23), respectively. Then we have

$$C_{ij}^A = D_i C_{ij}^B D_j^{-1} \quad (i, j = 1, \dots, r). \quad (4.25)$$

In the context of the Okubo system in Yokoyama's list, we apply this lemma to analyze how the connection coefficients transform under the permutation of characteristic exponents.

Case II\*, III\*: Recall that the canonical form of the system (III\*)<sub>3</sub> is constructed by the middle convolution  $\text{mc}_\mu$  for the differential system

$$\frac{d}{dx} Y = \left( \frac{\alpha}{x - t_1} + \frac{\beta}{x - t_2} + \frac{\gamma}{x - t_3} \right) Y, \quad Y = (x - t_1)^\alpha (x - t_2)^\beta (x - t_3)^\gamma. \quad (4.26)$$

Since the Okubo system of type (III\*)<sub>3</sub> is equivalent to the Okubo system of type (I\*)<sub>3</sub> up to conjugation, the connection coefficients in this case are directly computed as in [5]. The connection coefficients  $(C_{12}^{(3)})_{11}$  and  $(C_{13}^{(3)})_1$  are in fact given as

$$(C_{12}^{(3)})_{11} = -e(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_1 - \gamma)) \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}}{(t_2 - t_1)^{\beta_1 + \gamma - \rho_1 - \rho_2}}$$

$$\left( \frac{t_1 - t_3}{t_2 - t_3} \right)^{\rho_1 + \rho_2 - \alpha_1 - \beta_1} \frac{\Gamma(-\alpha_1)\Gamma(\beta_1 + 1)}{\Gamma(1 + \rho_1 - \alpha_1)\Gamma(\beta_1 - \rho_1)}$$
(4.27)

$$(C_{13}^{(3)})_1 = -(\gamma - \rho_1)^{-1} e(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_1 - \gamma)) \frac{(t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_1}}{(t_3 - t_1)^{\beta_1 + \gamma - \rho_1 - \rho_2}}$$

$$\left( \frac{t_1 - t_2}{t_3 - t_2} \right)^{\rho_1 + \rho_2 - \alpha_1 - \gamma} \frac{\Gamma(-\alpha_i)\Gamma(\gamma + 1)}{\Gamma(1 + \rho_1 - \alpha_1)\Gamma(\gamma - \rho_1)}$$
(4.28)

Using Theorem 2.2, the connection coefficients  $(C_{12}^{(2n+1)})_{11}$  and  $(C_{13}^{(2n+1)})_1$  of  $(\text{III}^*)_{2n+1}$  are computed as follows:

$$\begin{aligned}
(C_{12}^{(2n+1)})_{11} &= (-1)^{n-1} \prod_{k=2}^n e(\frac{1}{2}(\beta_k^{(2k+1)} - \rho_1^{(2k+1)}))(t_1 - t_2)^{\beta_k^{(2k+1)} - \rho_1^{(2k+1)}} e(\frac{1}{2}(\alpha_k^{(2k)} - \rho_1^{(2k)}))(t_2 - t_1)^{\rho_1^{(2k)} - \alpha_k^{(2k)}} \\
&\prod_{k=2}^n \frac{\Gamma(-\alpha_1^{(2k+1)}) \Gamma(\beta_1^{(2k+1)} - \beta_k^{(2k+1)}) \Gamma(1 + \alpha_k^{(2k)} - \alpha_1^{(2k)}) \Gamma(\beta_1^{(2k)} + 1)}{\Gamma(-\alpha_1^{(2k)}) \Gamma(\beta_1^{(2k+1)} - \rho_1^{(2k+1)}) \Gamma(1 + \rho_1^{(2k)} - \alpha_1^{(2k)}) \Gamma(\beta_1^{(2k-1)} + 1)} (C_{12}^{(3)})_{11} \\
&= (-1)^{n-1} e(\frac{1}{2}(-\rho_1^{(2n+1)} + \beta_2^{(5)})) e(\frac{1}{2}(-\rho_1^{(2n)} + \alpha_2^{(4)})) (t_1 - t_2)^{-\rho_1^{(2n+1)} + \beta_2^{(5)}} (t_2 - t_1)^{\rho_1^{(2n)} - \alpha_2^{(4)}} \\
&\frac{\Gamma(-\alpha_1^{(2n+1)}) \Gamma(\beta_1^{(2n)} + 1)}{\Gamma(-\alpha_1^{(3)}) \Gamma(\beta_1^{(3)} + 1)} \prod_{k=2}^n \frac{\Gamma(\beta_1^{(2k+1)} - \beta_k^{(2k+1)}) \Gamma(1 + \alpha_k^{(2k)} - \alpha_1^{(2k)})}{\Gamma(\beta_1^{(2k+1)} - \rho_1^{(2k+1)}) \Gamma(1 + \rho_1^{(2k)} - \alpha_1^{(2k)})} (C_{12}^{(3)})_{11} \\
&= (-1)^n e(\frac{1}{2}(-\rho_1^{(2n+1)} - \rho_1^{(2n)} + \beta_2^{(5)} + \alpha_2^{(4)} - \rho_1^{(3)})) \frac{(t_1 - t_2)^{-\rho_1^{(2n+1)} + \beta_1^{(3)}}}{(t_2 - t_1)^{\rho_1^{(2n)} - \alpha_2^{(4)} + \rho_1^{(3)} - \alpha_1^{(3)}} \\
&\left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1^{(2n+1)} + \rho_2^{(2n+1)} - \alpha_1^{(2n+1)} - \beta_1^{(2n+1)}} \frac{\Gamma(-\alpha_1^{(2n+1)}) \Gamma(\beta_1^{(2n+1)} + 1)}{\Gamma(1 + \rho_1^{(2n+1)} - \alpha_1^{(2n+1)}) \Gamma(\beta_1^{(2n+1)} - \rho_1^{(2n+1)})} \\
&\prod_{k=2}^n \frac{\Gamma(\beta_1^{(2n+1)} - \beta_k^{(2n+1)})}{\Gamma(\beta_1^{(2n+1)} + \alpha_k^{(2n+1)} - \rho_1^{(2n+1)} - \rho_2^{(2n+1)})} \frac{\Gamma(1 + \alpha_k^{(2n+1)} - \alpha_1^{(2n+1)})}{\Gamma(1 + \rho_1^{(2n+1)} + \rho_2^{(2n+1)} - \alpha_1^{(2n+1)} - \beta_k^{(2n+1)})} \\
&= (-1)^n e(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_1 - \gamma)) \frac{(t_1 - t_2)^{\rho_1 + \rho_2 - \alpha_1 - \gamma}}{(t_2 - t_1)^{\beta_1 + \gamma - \rho_1 - \rho_2}} \left(\frac{t_1 - t_3}{t_2 - t_3}\right)^{\rho_1 + \rho_2 - \alpha_1 - \beta_1} \\
&\frac{\Gamma(-\alpha_1) \Gamma(\beta_1 + 1)}{\Gamma(1 + \rho_1 - \alpha_1) \Gamma(\beta_1 - \rho_1)} \prod_{k=2}^n \frac{\Gamma(\beta_1 - \beta_k)}{\Gamma(\beta_1 + \alpha_k - \rho_1 - \rho_2)} \frac{\Gamma(1 + \alpha_k - \alpha_1)}{\Gamma(1 + \rho_1 + \rho_2 - \alpha_1 - \beta_k)}
\end{aligned} \tag{4.29}$$

$$\begin{aligned}
(C_{13}^{(2n+1)})_1 &= (-1)^{n-1} \prod_{k=2}^n \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\beta_k^{(2k+1)} - \rho_1^{(2k+1)}} \frac{e(\frac{1}{2}(\beta_k^{(2k+1)} - \rho_1^{(2k+1)})) \Gamma(-\alpha_1^{(2k+1)}) \Gamma(\gamma^{(2k+1)} + 1)}{\Gamma(-\alpha_1^{(2k)}) \Gamma(\gamma^{(2k)} + 1)} \\
&e(\frac{1}{2}(\alpha_k^{(2k)} - \rho_1^{(2k)}))(t_3 - t_1)^{\rho_1^{(2k)} - \alpha_k^{(2k)}} \frac{\Gamma(1 + \alpha_k^{(2k)} - \alpha_1^{(2k)}) \Gamma(\gamma^{(2k)} + 1)}{\Gamma(1 + \rho_1^{(2k)} - \alpha_1^{(2k)}) \Gamma(\gamma^{(2k-1)} + 1)} (C_{13}^{(3)})_{11} \\
&= (-1)^{n-1} e(\frac{1}{2}(-\rho_1^{(2n+1)} - \rho_2^{(2n+1)} + \beta_2^{(5)} + \alpha_2^{(2)})) (t_3 - t_1)^{\rho_2^{(2n+1)} - \alpha_2^{(4)}} \left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{-\rho_1^{(2n+1)} + \beta_2^{(5)}} \\
&\frac{\Gamma(\gamma^{(2n+1)} + 1) \Gamma(-\alpha_1^{(2n+1)})}{\Gamma(\gamma^{(3)} + 1) \Gamma(-\alpha_1^{(4)})} \prod_{k=2}^n \frac{\Gamma(1 + \alpha_k^{(2n+1)} - \alpha_1^{(2n+1)})}{\Gamma(1 + \rho_1^{(2n+1)} + \rho_2^{(2n+1)} - \alpha_1^{(2n+1)} - \beta_k^{(2n+1)})} (C_{13}^{(3)})_{11} \\
&= (-1)^n e(\frac{1}{2}(\rho_1 + \rho_2 - \alpha_1 - \beta_1 - \gamma)) (t_1 - t_3)^{\rho_1 + \rho_2 - \alpha_1 - \beta_1} (t_3 - t_1)^{\beta_1 + \gamma - \rho_1 - \rho_2} \\
&\left(\frac{t_1 - t_2}{t_3 - t_2}\right)^{\rho_1 + \rho_2 - \alpha_1 - \gamma} \frac{\Gamma(\gamma + 1) \Gamma(-\alpha_1)}{\Gamma(1 + \rho_1 - \alpha_1)} \frac{\prod_{k=2}^n \Gamma(1 + \alpha_k - \alpha_1)}{\prod_{k=1}^n \Gamma(1 + \rho_1 + \rho_2 - \alpha_1 - \beta_k)}
\end{aligned} \tag{4.30}$$

The connection coefficients  $(C_{12})_{ij}$  and  $(C_{13})_i$  for other  $i, j$  are derived by Lemma 4.4. In the following we denote by  $\sigma_{ij}^\alpha$  (resp.  $\sigma_{ij}^\beta$ ) the operation which exchanges the parameters  $\alpha_i$  and  $\alpha_j$  (resp.  $\beta_i$  and  $\beta_j$ ). Then the matrix  $A$  of the canonical form of type  $(\text{III}^*)_{2n+1}$  satisfies

$$A = \text{Ad}(D) \sigma_{1i}^\alpha \sigma_{1j}^\beta(A), \quad D = \text{diag}(S_{1i}, S_{1j}, 1) \tag{4.31}$$

where  $S_{ij}$  is the permutation matrix corresponding the transposition  $(ij)$  of matrix indices. From (4.31), applying Lemma 4.4 to  $B = \sigma_{1i}^\alpha \sigma_{1j}^\beta(A)$  we obtain

$$C_{12} = S_{1i} \sigma_{1i}^\alpha \sigma_{1j}^\beta(C_{12}) S_{1j}, \quad C_{13} = S_{1i} \sigma_{1i}^\alpha \sigma_{1j}^\beta(C_{13}). \quad (4.32)$$

Therefore the connection coefficients  $(C_{12})_{ij}$  and  $(C_{13})_i$  are given by

$$(C_{12})_{ij} = \sigma_{1i}^\alpha \sigma_{1j}^\beta(C_{12})_{11}, \quad (C_{13})_i = \sigma_{1i}^\alpha(C_{13})_1. \quad (4.33)$$

The other connection coefficients of type III\* and connection coefficients of type II\* are computed similarly.

**Case IV:** The canonical forms of type IV is given by the operation

$$(IV)_6 = \text{add}_{(\rho_3,0)} \circ \text{mc}_{-\rho_3-c} \circ \text{add}_{(c,0)}(\text{III}_5). \quad (4.34)$$

Using Theorem 2.2, we can completely determine  $(C_{12}^{(6)})_{11}$  for (3.7) by the following computation:

$$\begin{aligned} (C_{12}^{(6)})_{11} &= (C_{(11)2}^{mc})_{11} = -e(\frac{1}{2}(\rho_3 + c))(t_2 - t_1)^{-\rho_3-c} \frac{\Gamma(1 + \rho_3 - \alpha_1)}{\Gamma(1 - \alpha_1 - c)} (C_{12}^{(5)})_{11} \frac{\Gamma(\beta_1 - \rho_3 - c + 1)}{\Gamma(\beta_1 + 1)} \\ &= -e(\frac{1}{2}(\alpha_4 - \rho_3))(t_2 - t_1)^{\rho_3 - \alpha_4} \frac{\Gamma(1 + \alpha_4 - \alpha_1)}{\Gamma(1 + \rho_3 - \alpha_1)} (C_{12})_{11} \frac{\Gamma(\beta_1^{(6)} + 1)}{\Gamma(\beta_1^{(5)} + 1)} \\ &= e(\frac{1}{2}(\alpha_4 - \rho_3))(t_2 - t_1)^{\rho_3 - \alpha_4} \frac{\Gamma(1 + \alpha_4 - \alpha_1)}{\Gamma(1 + \rho_3 - \alpha_1)} \frac{\Gamma(\beta_1^{(6)} + 1)}{\Gamma(\beta_1^{(5)} + 1)} \frac{(t_2 - t_1)^{\alpha_4 - \alpha_1}}{(t_1 - t_2)^{\rho_3 - \beta_j}} e(\frac{1}{2}(\rho_3 - \alpha_1 - \beta_1 - \alpha_4)) \\ &\quad \frac{\Gamma(-\alpha_1)\Gamma(\beta_1^{(5)} + 1)}{\Gamma(1 + \rho_1 - \alpha_1)\Gamma(1 + \rho_2 - \alpha_1)} \frac{\prod_{k \neq 1}^2 \Gamma(\beta_1 - \beta_k)}{\prod_{k \neq 1}^3 \Gamma(\beta_1 + \alpha_k + \alpha_4 - \rho_1 - \rho_2 - \rho_3)} \frac{\prod_{k \neq 1}^3 \Gamma(1 + \alpha_k - \alpha_1)}{\prod_{k \neq 1}^2 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \beta_k - \alpha_1 - \alpha_4)} \\ &= e(\frac{1}{2}(-\alpha_1 - \beta_1)) \frac{(t_2 - t_1)^{\rho_3 - \alpha_1}}{(t_1 - t_2)^{\rho_3 - \beta_j}} \frac{\Gamma(-\alpha_1)\Gamma(\beta_1 + 1)}{\Gamma(1 + \rho_1 - \alpha_1)\Gamma(1 + \rho_2 - \alpha_1)\Gamma(1 + \rho_3 - \alpha_1)} \\ &\quad \frac{\prod_{k \neq 1}^2 \Gamma(\beta_1 - \beta_k)}{\prod_{k \neq 1}^3 \Gamma(\beta_1 + \alpha_k + \alpha_4 - \rho_1 - \rho_2 - \rho_3)} \frac{\prod_{k \neq 1}^4 \Gamma(1 + \alpha_k - \alpha_1)}{\prod_{k \neq 1}^2 \Gamma(1 + \rho_1 + \rho_2 + \rho_3 - \beta_k - \alpha_1 - \alpha_4)}. \end{aligned} \quad (4.35)$$

As in the cases of types II\* and III\*, we determine the other connection coefficients by Lemma 4.4 and operations  $\sigma_{ij}^\alpha, \sigma_{ij}^\beta$ . For  $\sigma_{1i}^\alpha, \sigma_{12}^\beta$ , the Okubo system (3.7) satisfies the relations

$$A = \text{Ad}(D)\sigma_{1i}^\alpha \sigma_{12}^\beta(A) \quad D = \text{diag}(S_{1i}, S_{12}), \quad (i = 1, 2, 3). \quad (4.36)$$

By taking account of Lemma 4.4 and (4.36), the connection coefficients  $(C_{12})_{ij}$  ( $i = 1, 2, 3; j = 1, 2$ ) are given by

$$(C_{12})_{ij} = \sigma_{1i}^\alpha \sigma_{1j}^\beta(C_{12})_{11}. \quad (4.37)$$

Although the system (3.7) is *not* symmetric with respect to  $(\alpha_1, \alpha_4)$ , for the operation  $\sigma_{14}^\alpha$  it satisfies the relation

$$A = \text{Ad}(D_{14}^\alpha)\sigma_{14}^\alpha(A) \quad (4.38)$$

where  $D_{14}^\alpha = \text{diag}(d_1, \dots, d_6) \text{diag}(S_{14}, I_2)$  is the matrix defined by

$$\begin{aligned} d_1 &= \prod_{k=1}^2 (\alpha_1 + \alpha_2 + \beta_k - \rho_1 - \rho_2 - \rho_3)(\alpha_1 + \alpha_3 + \beta_k - \rho_1 - \rho_2 - \rho_3), \\ d_2 &= - \prod_{k=1}^2 (\alpha_1 + \alpha_3 + \beta_k - \rho_1 - \rho_2 - \rho_3), \quad d_3 = - \prod_{k=1}^2 (\alpha_1 + \alpha_2 + \beta_k - \rho_1 - \rho_2 - \rho_3), \quad d_4 = 1, \\ d_5 &= \prod_{k \neq 1}^3 (\alpha_1 + \alpha_k + \beta_1 - \rho_1 - \rho_2 - \rho_3), \quad d_6 = \prod_{k \neq 1}^3 (\alpha_1 + \alpha_k + \beta_2 - \rho_1 - \rho_2 - \rho_3). \end{aligned} \quad (4.39)$$

Therefore the connection coefficient  $(C_{12})_{41}$  is derived by

$$(C_{12})_{41} = d_4 \sigma_{14}^\alpha (C_{12})_{11} d_6^{-1}. \quad (4.40)$$

Since  $C_{12} = \sigma_{12}^\beta (C_{12}) S_{12}$ , we obtain

$$(C_{12})_{4j} = \sigma_{12}^\beta (d_4 \sigma_{14}^\alpha (C_{12})_{11} d_6^{-1}). \quad (4.41)$$

The other connection coefficients  $(C_{21})_{ij}$  of type IV are computed similarly.

Case IV\*: The canonical form of type IV\* is constructed by

$$(IV^*)_6 = \text{add}_{(0,0,\rho_1)} \circ \text{mc}_{-c-\rho_1} \circ \text{add}_{(0,0,c)} (III^*)_5. \quad (4.42)$$

The connection coefficients  $(C_{12})_{11}, (C_{13})_{11}, (C_{23})_{11}$  are directly computed from the connection coefficients  $(C_{ij})_{11}^{(5)}$  of type  $(III^*)_5$  by Theorem 2.2. The other connection coefficients can be determined by combining Lemma 4.4 and the operations  $\sigma_{12}^\alpha, \sigma_{12}^\beta, \sigma_{12}^\gamma$ . For  $\sigma_{12}^\alpha, \sigma_{12}^\beta$ , the Okubo system (3.8) satisfies the relation

$$A = \text{Ad}(D) \sigma_{12}^\alpha \sigma_{12}^\beta (A), \quad D = \text{diag}(S_{12}, S_{12}, I_2). \quad (4.43)$$

For  $\sigma_{12}^\gamma$ , the Okubo system (3.8) satisfies

$$A = \text{Ad}(D^\gamma) \sigma_{12}^\gamma (A), \quad (4.44)$$

where  $D^\gamma$  is the matrix given by

$$D^\gamma = \text{diag}(h_{111} h_{121}, h_{211} h_{221}, -h_{111} h_{211}, -h_{121} h_{221}, h_{111} h_{121} h_{211} h_{221}, 1) \text{diag}(I_2, I_2, S_{12}). \quad (4.45)$$

With these relations, the other connection matrices are determined by Lemma 4.4 as follows:

$$\begin{aligned} C_{12} &= S_{1i} \sigma_{1i}^\alpha \sigma_{1j}^\beta (C_{12}) S_{1j}, \quad C_{13} = S_{1i} \sigma_{1i}^\alpha (C_{13}), \quad C_{23} = S_{1i} \sigma_{1i}^\beta (C_{23}), \\ C_{13} &= \begin{pmatrix} h_{111} h_{121} & 0 \\ 0 & h_{211} h_{221} \end{pmatrix} \sigma_{12}^\gamma (C_{13}) S_{12} \begin{pmatrix} h_{111} h_{121} h_{211} h_{221} & 0 \\ 0 & 1 \end{pmatrix}^{-1}, \\ C_{23} &= \begin{pmatrix} -h_{111} h_{211} & 0 \\ 0 & -h_{121} h_{221} \end{pmatrix} \sigma_{12}^\gamma (C_{23}) S_{12} \begin{pmatrix} h_{111} h_{121} h_{211} h_{221} & 0 \\ 0 & 1 \end{pmatrix}^{-1}. \end{aligned} \quad (4.46)$$

This completes the proof of the main theorems.



## References

- [1] Y. Haraoka: Canonical forms of differential equations free from accessory parameters SIAM **25** (1994),1203–1226
- [2] Y. Haraoka: Monodromy representations of systems of differential equations free from accessory parameters SIAM **25** (1994),1595–1621
- [3] N.M. Katz: *Rigid Local Systems*, Annals of Mathematics Studies **139**, Princeton University Press, Princeton, 1996.
- [4] M. Kohno: *Global Analysis in Linear Differential Equations*, Mathematics and its Applications, 471. Kluwer Academic Publishers, 1999. xvi+526 pp.
- [5] S. Konnai: Connection coefficients and monodromy representations for a class of Okubo systems of ordinary differential equations, arXiv:1606.07187v1.
- [6] K. Okubo: *On the Group of Fuchsian Equations*, Seminar Reports of Tokyo Metropolitan University, 1987.
- [7] K. Okubo, K. Takano and S. Yosida: A connection problem for the generalized hypergeometric equation, Funkcial. Ekvac. **31** (1988), 483–295.
- [8] M. Dettweiler and S. Reiter: An algorithm of Katz and its application to the inverse Galois problem, J. Symbolic Comput. **30** (2000), 761–798.
- [9] M. Dettweiler and S. Reiter: Middle convolution of Fuchsian systems and the construction of rigid differential systems, J. Algebra **318** (2007), 1–24.
- [10] T. Oshima: Fractional calculus of Weyl algebra and Fuchsian differential equations, MSJ Memoirs **28**, Mathematical Society of Japan, 2012.
- [11] T. Oshima: Katz’s middle convolution and Yokoyama’s extending operation, Opuscula Math. **35** (2015), 665–688
- [12] D. Yamakawa: Middle convolution and Harnad duality, Math. Ann. **349** (2011), 215–262.
- [13] T. Yokoyama: On an irreducibility condition for hypergeometric systems, Funkcial. Ekvac. **38** (1995), 11–19
- [14] T. Yokoyama: Construction of systems of differential equations of Okubo normal form with rigid monodromy, Math. Nachr. **279** (2006),No. 3 327–348
- [15] T. Yokoyama: Recursive Calculation of Connection Formulas for Systems of Differential Equations of Okubo Normal Form, J. Dyn Control Syst. **20** (2014), 241–292