

Lewis and Berry phases for a gravitational wave interacting with a quantum harmonic oscillator

Soham Sen,^{*} Manjari Dutta,[†] and Sunandan Gangopadhyay[‡]

Department of Astrophysics and High Energy Physics

S. N. Bose National Centre for Basic Sciences, JD Block, Sector-III, Salt Lake, Kolkata 700106, India

In this work, we consider a gravitational wave interacting with a quantum harmonic oscillator in the transverse-traceless gauge. We take the gravitational wave to be carrying the signatures of both plus and cross polarization at first. We then try to obtain a suitable form of the Lewis invariant using the most general form possible while considering only quadratic order contributions from both position and momentum variables. In order to progress further, we then drop the cross terms obtaining a separable Hamiltonian in terms of the first and the second spatial coordinates. We then obtain two Lewis invariants corresponding to each separable parts of the entire Hamiltonian of the system. Using both Lewis invariants, one can obtain two Ermakov-Pinney equations, from which we finally obtain the corresponding Lewis phase and eventually the Berry phase for the entire system. Finally, we obtain some explicit expressions of the Berry phase for a plane polarized gravitational wave with different choices of the harmonic oscillator frequency.

I. INTRODUCTION

In 1916, Albert Einstein predicted that gravitational radiation must exist by linearizing general theory of relativity. This was the birth of gravitational waves. The detection of gravitational wave in 2015 (from two colliding neutron stars), led to the upsurge in research related to gravitational waves and its various aspects almost after a century had passed from the initial theoretical prediction in 1916. From its initial detection, several theoretical models have been proposed to investigate the effects of gravitational waves in several quantum mechanical scenarios. Although it is theoretically more prudent to consider the background geometry to be curved as most of the gravitational wave detectors (LIGO and VIRGO) are ground based detectors but the usual theoretical notion is to consider the gravitational wave as a fluctuation over a flat Minkowski background.

The analysis involving the interaction between a gravitational wave and time dependent quantum harmonic oscillator is very rare in the literature. The study of time dependent quantum harmonic oscillators is of immense interest among the scientific community as well. With the work of Lewis *et. al.* [1], the study of time dependent quantum harmonic oscillators using exact invariants paved a new way to critically study these systems [2, 3]. There have been several analysis involving the damping in a one dimensional quantum harmonic oscillator [4–8]. There also have been few studies involving damping in a two dimensional quantum harmonic oscillator [9] and later extended to noncommutative space [10]. An explicit analysis of damped harmonic oscillator with time dependent frequency in a noncommutative space in the presence of magnetic field was done in [11].

On the other hand in a process if a very gradual change of external parameters occur [12, 13] then we call it an adi-

abatic process with which two characteristic time scales are involved. These two characteristic time scales are termed as “*external time*” and “*internal time*”. The “*external time*” signifies the parameters (of the system), over which the system changes significantly and the “*internal time*” is related to the motion of the system. For an adiabatic process, the “*external time*” is dominant over the internal time which signifies that the Hamiltonian parameters evolve quite slowly over time. During such processes, the system picks up a phase.

In [14, 15], Berry showed that along with the time dependent dynamical phase, a time independent and path dependent geometric phase is also picked up by the system. This path dependent geometric phase is also known as the “*Berry phase*” which is a physically measurable quantity. As it is not as large as compared to the dynamical phase, it is possible to pick up the geometric phase by means of sophisticated experiments [16, 17]. It is a general wisdom that the Hamiltonian should have more than one time-dependent parameters and the eigenfunctions of the Hamiltonian should be complex for obtaining a non-zero Berry phase. Now if the set of parameters change adiabatically for such a system through a closed path (such that it can return to its initial position), then the system acquires a geometric phase [18] and for these systems the time reversal symmetry of the Hamiltonian must be broken [19]. The investigation of such phases have been of great interest especially in the case of quantum harmonic oscillators [20–24].

In this paper, we consider a gravitational wave in the transverse-traceless gauge interacting with a two dimensional time dependent quantum harmonic oscillator with time dependent frequency. We have then followed the analysis by Lewis *et. al.* [1] to obtain an invariant corresponding to the total Hamiltonian of the system. We start our analysis by considering both the plus and cross polarizations of the gravitational wave. Following the calculation of the Lewis invariant operator, we find out that the cross term leads to a very complicated form of the invariant operator. For the next part of our analysis, we proceed with the plus polarization only to simplify

^{*} sensohomhary@gmail.com, soham.sen@bose.res.in

[†] chandromouli15@gmail.com

[‡] sunandan.gangopadhyay@gmail.com

things and obtain the Lewis phase and eventually the Berry phase of the two-dimensional harmonic oscillator-gravitational wave system. The importance to look for the Berry phase in the quantum harmonic oscillator-gravitational wave system is evident. Finding a non-trivial detectable Berry phase can prove to be important in the detection of gravitational waves in resonant bar detector systems [25–28].

The organization of the paper goes as follows. In section II, we discuss the Hamiltonian of the system. In section III, we have discussed in brief the method of Lewis invariant and obtained the Lewis invariant corresponding to our system in section IV. In section V, we have obtained the creation and annihilation operators from the Lewis invariant obtained in section IV. In section VI, we have obtained the Lewis and the Berry phases for our system Hamiltonian. Next in section VII, we have obtained few explicit Berry phases and then finally have concluded the paper in section VIII.

II. HAMILTONIAN OF THE SYSTEM

In this paper we consider a two dimensional simple harmonic oscillator interacting with a gravitational wave in the transverse-traceless gauge. The background metric in the linearized approximation can then be expressed as the flat Minkowski metric plus the perturbation due to the gravitational wave

$$g_{\mu\nu} = \eta_{\mu\nu} + h_{\mu\nu} \quad (1)$$

where $\eta_{\mu\nu} = \text{diag}\{-1, 1, 1, 1\}$ with $\mu, \nu = \{0, 1, 2, 3\}$. The form of $h_{\mu\nu}$ in the transverse traceless is given in the matrix form as

$$h_{\mu\nu} = \begin{pmatrix} 0 & 0 & 0 & 0 \\ 0 & h_+(t) & h_\times(t) & 0 \\ 0 & h_\times(t) & -h_+(t) & 0 \\ 0 & 0 & 0 & 0 \end{pmatrix} \quad (2)$$

where $h_+(t) = 2\chi(t)\varepsilon_+$ and $h_\times(t) = 2\chi(t)\varepsilon_\times$ with ε_+ and ε_\times denoting the plus and the cross polarization. If we now define the polarization tensor in three spatial dimensions to be $\varepsilon_l = (\varepsilon_\times, 0, \varepsilon_+)$, we can write down the fluctuation term as follows

$$\begin{aligned} h_{jk}(t) &= 2\chi(t) (\varepsilon_+ \sigma_{jk}^3 + \varepsilon_\times \sigma_{jk}^1) \\ &= 2\chi(t) \varepsilon_l \sigma_{jk}^l \end{aligned} \quad (3)$$

where $l = \{1, 2, 3\}$ and $j, k = \{1, 2\}$. In order to write down eq.(3) from $h_{\mu\nu}$, it is important to note that the matrix $h_{\mu\nu}$ can be reduced effectively to 2×2 matrix spanning the x and y directions only. Before explicitly making use of the gravitational wave perturbation term in eq.(3), we shall write down the classical form of the action for the system as

$$S = \int dt \left(\frac{1}{2} m \dot{x}_k \dot{x}^k - \frac{1}{2} m R^j_{0k0} x_j x^k - V \right) \quad (4)$$

where $j, k = \{1, 2\}$ and V is the harmonic oscillator potential which is given by

$$V = \frac{1}{2} m \omega^2 x_k x^k. \quad (5)$$

In general, it is more convenient to consider ω as a constant but in our analysis we consider the frequencies of the harmonic oscillator to be time dependent ($\omega = \omega(t)$). Dropping the boundary terms, we can recast the form of the action in eq.(4) given as

$$S = \int dt \left(\frac{1}{2} m \dot{x}_k \dot{x}^k - m \Gamma^j_{0k} \dot{x}_j x^k - V \right) \quad (6)$$

where $R^j_{0k0} = -\partial_0 \Gamma^j_{0k}$ and the modified Lagrangian of the system is given by

$$L' = \frac{1}{2} m \dot{x}_k \dot{x}^k - m \Gamma^j_{0k} \dot{x}_j x^k - V. \quad (7)$$

The Hamiltonian corresponding to the Lagrangian in eq.(4) is given by

$$H = \frac{1}{2m} p_k p^k + \Gamma^j_{0k} x^k p_j + \frac{1}{2} m \omega^2(t) x_k x^k \quad (8)$$

where up to $\mathcal{O}(h)$ we can express $\Gamma^j_{0k} \cong \frac{1}{2} \eta^{jm} \partial_0 h_{mk}$. Using eq.(3) in the above equation and raising the phase space variables to operator status, we can finally write down the Hamiltonian for the quantum harmonic oscillator to be

$$\begin{aligned} \hat{H}(t) &= \frac{a}{2} (\hat{p}_1^2 + \hat{p}_2^2) + \frac{b(t)}{2} (\hat{x}_1^2 + \hat{x}_2^2) + d(t) (\hat{x}_1 \hat{p}_1 + \hat{p}_1 \hat{x}_1) \\ &\quad - d(t) (\hat{x}_2 \hat{p}_2 + \hat{p}_2 \hat{x}_2) + f(t) (\hat{x}_1 \hat{p}_2 + \hat{p}_1 \hat{x}_2) \end{aligned} \quad (9)$$

where $a = \frac{1}{m}$, $b(t) = m\omega^2(t)$, $d(t) = \frac{1}{2} \varepsilon_+ \dot{\chi}(t)$, and $f(t) = \varepsilon_\times \dot{\chi}(t)$. It is important to note that $d(t), f(t) \sim \mathcal{O}(h)$. We will now try to find out the Lewis invariant corresponding to the Hamiltonian given in eq.(9).

III. BASIC INTRODUCTION TO LEWIS INVARIANT

The model Hamiltonian obtained in eq.(9) is an explicit function of time. Following the analysis in [1], it may be possible to construct a time dependent Hermitian operator $\hat{I}(t)$ such that

$$\frac{d\hat{I}}{dt} = \frac{\partial \hat{I}}{\partial t} + \frac{1}{i\hbar} [\hat{I}, \hat{H}] = 0. \quad (10)$$

If a time dependent Schrödinger state vector $|\psi\rangle$ satisfies the following relation

$$i\hbar \frac{\partial |\psi_k\rangle}{\partial t} = \hat{H} |\psi_k\rangle \quad (11)$$

then we can deduce the following relation (by making use of eq.(10))

$$\begin{aligned} i\hbar \frac{\partial}{\partial t} (\hat{I}|\psi_k\rangle) &= i\hbar \frac{\partial \hat{I}}{\partial t} |\psi_k\rangle + \hat{I} \left[i\hbar \frac{\partial |\psi_k\rangle}{\partial t} \right] \\ &= \left[i\hbar \frac{\partial \hat{I}}{\partial t} + \hat{I} \hat{H} \right] |\psi_k\rangle \\ &= \hat{H} (\hat{I}|\psi_k\rangle) \end{aligned} \quad (12)$$

where to obtain the last line of the above equation, we have made use of eq.(10). Eq.(12) suggests that the action of $\hat{I}(t)$ on the Schrödinger state vector creates another state vector. If one now assumes that the invariant operator is one among a complete set of commuting observables, then it is straight forward to find out a complete set of eigenstates for the Hermitian invariant operator $\hat{I}(t)$. We assume that for the invariant in our case, the eigenstate is $|\varphi_k\rangle$. Then we can write down the following relation

$$\hat{I}(t)|\varphi_k\rangle = \zeta|\varphi_k\rangle \quad (13)$$

with ζ being the eigenvalue. Following the analysis in [1], one can write down the time dependent solution of the Schrödinger equation in eq.(11) in terms of the eigenstate $|\varphi_k\rangle$ as follows

$$|\psi_k\rangle = e^{i\theta_k(t)} |\varphi_k\rangle \quad (14)$$

where $\theta_k(t)$ is a real function of time. Substituting eq.(14) back in the time dependent Schrödinger equation given in eq.(11), we obtain the following relation

$$e^{i\theta_k(t)} \left(i\hbar \partial_t - \hbar \dot{\theta}_k(t) \right) |\phi_k\rangle = e^{i\theta_k(t)} \hat{H} |\phi_k\rangle. \quad (15)$$

We can recast eq.(15) via the action of $\langle \psi_k |$ which gives

$$\dot{\theta}_k(t) = \frac{1}{\hbar} \langle \phi_k | i\hbar \partial_t - \hat{H} | \phi_k \rangle. \quad (16)$$

The real function $\theta_k(t)$ is also known as the Lewis phase factor. Later we shall make use of eq.(16) to obtain the form of the Lewis phase and eventually the Berry phase for our model system. With the initial introduction regarding the invariant operator, we will try to find a suitable form of $\hat{I}(t)$ corresponding to the Hamiltonian in eq.(9).

IV. LEWIS INVARIANT OF THE SYSTEM

Investigating the form of the Hamiltonian in eq.(9), we can write the most general form of the Lewis invariant to be

$$\begin{aligned} \hat{I}(t) &= \alpha_1(t) \hat{p}_1^2 + \alpha_2(t) \hat{p}_2^2 + \beta_1(t) \hat{x}_1^2 + \alpha_2(t) \hat{x}_2^2 \\ &\quad + \delta_1(t) (\hat{x}_1 \hat{p}_1 + \hat{p}_1 \hat{x}_1) + \delta_2(t) (\hat{x}_2 \hat{p}_2 + \hat{p}_2 \hat{x}_2) \\ &\quad + \lambda_1(t) \hat{x}_1 \hat{p}_2 + \lambda_2(t) \hat{p}_1 \hat{x}_2 + \lambda_3(t) \hat{p}_1 \hat{p}_2 + \lambda_4(t) \hat{x}_1 \hat{x}_2 \end{aligned} \quad (17)$$

where $\alpha_1, \alpha_2, \beta_1, \beta_2, \delta_1, \delta_2, \lambda_1, \lambda_2, \lambda_3$, and λ_4 are all unknown time dependent parameters. We shall now try to determine all the undetermined constants by inserting the form of $\hat{I}(t)$ from eq.(17) back in eq.(10) and equating the coefficients of all quadratic operators to zero. Computing $i\hbar \frac{\partial \hat{I}(t)}{\partial t}$ and $[\hat{I}, \hat{H}]$, we obtain a set of ordinary differential equations given by

$$\dot{\alpha}_1 - 4\alpha_1 d + 2\delta_1 a - \lambda_3 f = 0, \quad (18)$$

$$\dot{\alpha}_2 + 4\alpha_2 d + 2\delta_2 a - \lambda_3 f = 0, \quad (19)$$

$$\dot{\beta}_1 + 4\beta_1 d - 2\delta_1 b + \lambda_4 f = 0, \quad (20)$$

$$\dot{\beta}_2 - 4\beta_2 d - 2\delta_2 b + \lambda_4 f = 0, \quad (21)$$

$$\dot{\delta}_1 - \alpha_1 b + \beta_1 a - \lambda_1 f = 0, \quad (22)$$

$$\dot{\delta}_1 - \alpha_1 b + \beta_1 a + \lambda_2 f = 0, \quad (23)$$

$$\dot{\delta}_2 - \alpha_2 b + \beta_2 a + \lambda_1 f = 0, \quad (24)$$

$$\dot{\delta}_1 - \alpha_2 b + \beta_2 a - \lambda_2 f = 0, \quad (25)$$

$$\dot{\lambda}_1 - 2\delta_1 f + 2\delta_2 f + 4\lambda_1 d - \lambda_3 b + \lambda_4 a = 0, \quad (26)$$

$$\dot{\lambda}_2 + 2\delta_1 f - 2\delta_2 f - 4\lambda_2 d - \lambda_3 b + \lambda_4 a = 0, \quad (27)$$

$$\dot{\lambda}_3 - 2\alpha_1 f - 2\alpha_2 f + (\lambda_1 + \lambda_2) a = 0, \quad (28)$$

$$\dot{\lambda}_4 + 2\beta_1 f + 2\beta_2 f - (\lambda_1 + \lambda_2) b = 0. \quad (29)$$

Comparing eq.(22) with eq.(23) (or eq.(24) with eq.(25)), one can easily find out that $\lambda_1 = -\lambda_2 = \lambda_0$. Substituting $\lambda_1 = -\lambda_2 = \lambda_0$ in eq.(s)(26,27), we obtain one differential equation and a constraint equation given by

$$\dot{\lambda}_0 - 2\delta_1 f + 2\delta_2 f = 0, \quad (30)$$

$$4\lambda_1 d - \lambda_3 b + \lambda_4 a = 0. \quad (31)$$

We shall now introduce two time dependent parameters $\rho_1(t)$ and $\rho_2(t)$ such that

$$\alpha_1(t) = \kappa_1 \rho_1^2(t), \quad \alpha_2(t) = \kappa_2 \rho_2^2(t) \quad (32)$$

with κ_1 and κ_2 being two time independent unknown constants. Using the forms of α_1 and α_2 , we can now obtain the form of the other unidentified time dependent parameters up to $\mathcal{O}(\hbar)$ to be

$$\beta_1(t) = \frac{\kappa_1}{a^2} \left(\dot{\rho}_1^2 + \rho_1 \ddot{\rho}_1 - 2\rho_1^2 \dot{d} - 4\rho_1 \dot{\rho}_1 d + ab\rho_1^2 \right), \quad (33)$$

$$\beta_2(t) = \frac{\kappa_2}{a^2} \left(\dot{\rho}_2^2 + \rho_2 \ddot{\rho}_2 - 2\rho_2^2 \dot{d} - 4\rho_2 \dot{\rho}_2 d + ab\rho_2^2 \right), \quad (34)$$

$$\delta_1(t) = -\frac{\kappa_1}{a} (\rho_1 \dot{\rho}_1 - 2\rho_1^2 d), \quad (35)$$

$$\delta_2(t) = -\frac{\kappa_2}{a} (\rho_2 \dot{\rho}_2 + 2\rho_2^2 d), \quad (36)$$

$$\lambda_0(t) = \frac{2}{a} \int_0^t dt' f(t') (\kappa_2 \rho_2(t') \dot{\rho}_2(t') - \kappa_1 \rho_1(t') \dot{\rho}_1(t')), \quad (37)$$

$$\lambda_3(t) = 2 \int_0^t dt' f(t') (\kappa_1 \rho_1^2(t') + \kappa_2 \rho_2^2(t')), \quad (38)$$

$$\lambda_4(t) = \frac{2b}{a} \int_0^t dt' f(t') (\kappa_1 \rho_1^2(t') + \kappa_2 \rho_2^2(t')). \quad (39)$$

Instead of progressing further with these parameters, due to the complicated forms of the λ_0 , λ_3 , and λ_4 , we shall now drop any contributions from cross polarization of the gravitational wave by setting $f(t) = 0$. As a result $\lambda_0 = \lambda_3 = \lambda_4 = 0$. The Hamiltonian in eq.(9) can now be recast in the following form

$$\begin{aligned}\hat{H}(t) &= \frac{a}{2}\hat{p}_1^2 + \frac{b(t)}{2}\hat{x}_1^2 + d(t)(\hat{x}_1\hat{p}_1 + \hat{p}_1\hat{x}_1) \\ &+ \frac{a}{2}\hat{p}_2^2 + \frac{b(t)}{2}\hat{x}_2^2 - d(t)(\hat{x}_2\hat{p}_2 + \hat{p}_2\hat{x}_2) \\ &= \hat{H}_1(t) + \hat{H}_2(t)\end{aligned}\quad (40)$$

where

$$\hat{H}_1(t) = \frac{a}{2}\hat{p}_1^2 + \frac{b(t)}{2}\hat{x}_1^2 + d(t)(\hat{x}_1\hat{p}_1 + \hat{p}_1\hat{x}_1), \quad (41)$$

$$\hat{H}_2(t) = \frac{a}{2}\hat{p}_2^2 + \frac{b(t)}{2}\hat{x}_2^2 - d(t)(\hat{x}_2\hat{p}_2 + \hat{p}_2\hat{x}_2). \quad (42)$$

It is important to note from eq.(40) that in the absence of the cross terms, we can effectively write down the Hamiltonian as a sum of two Hamiltonians describing the dynamics of the system corresponding to each spatial dimension. As a result of this decoupling, it is now also possible to break the invariant $\hat{I}(t)$ from eq.(17) (setting $f(t) = 0$) into two parts given by

$$\hat{I}(t) = \hat{I}_1(t) + \hat{I}_2(t) \quad (43)$$

where the forms of \hat{I}_1 and $\hat{I}_2(t)$ are given as follows

$$\hat{I}_k(t) = \alpha_k(t)\hat{p}_k^2 + \beta_k(t)\hat{x}_k^2 + \delta_k(t)(\hat{x}_k\hat{p}_k + \hat{p}_k\hat{x}_k) \quad (44)$$

with $k = \{1, 2\}$. In order to further simplify the forms of $\beta_1(t)$ and $\beta_2(t)$ from eq.(s)(33,34), we substitute the forms of these two parameters (as well as $\delta_1(t)$ and $\delta_2(t)$) back in the following differential equations

$$\dot{\beta}_1 + 4\beta_1 d - 2\delta_1 b = 0, \quad (45)$$

$$\dot{\beta}_2 - 4\beta_2 d - 2\delta_2 b = 0. \quad (46)$$

We can finally obtain from the above two differential equations (using the forms of the parameters), two nonlinear equations involving the parameters $\rho_1(t)$ and $\rho_2(t)$ as follows

$$\ddot{\rho}_1(t) + \left(ab(t) - 2\dot{d}(t)\right)\rho_1(t) = \frac{a^2\xi_1^2}{\rho_1^3(t)}, \quad (47)$$

$$\ddot{\rho}_2(t) + \left(ab(t) + 2\dot{d}(t)\right)\rho_2(t) = \frac{a^2\xi_2^2}{\rho_2^3(t)} \quad (48)$$

where ξ_1^2 and ξ_2^2 are integration constants. It is important to note that $\epsilon_+^2 + \epsilon_-^2 = 1$ and for a gravitational wave in the absence of the cross polarization term, $\epsilon_+ = 1$ which indicates $d(t) = \frac{1}{2}\dot{\chi}(t)$. Eq.(s)(47,48) are the Ermakov-Pinney [29, 30] equations corresponding to the two directions presented in this analysis.

We shall now make use of the Ermakov-Pinney equations to subsequently simplify the forms of $\beta_1(t)$ and $\beta_2(t)$ from

eq.(s)(33,34) given as follows

$$\beta_1(t) = \frac{\kappa_1}{a^2}(\dot{\rho}_1^2 - 4\rho_1\dot{\rho}_1 d) + \frac{\kappa_1\xi_1^2}{\rho_1^2}, \quad (49)$$

$$\beta_2(t) = \frac{\kappa_2}{a^2}(\dot{\rho}_2^2 + 4\rho_2\dot{\rho}_2 d) + \frac{\kappa_2\xi_2^2}{\rho_2^2}. \quad (50)$$

With the analytical forms of the parameters, we can now recast the separable Lewis invariants from eq.(44) as follows

$$\begin{aligned}\hat{I}_1(t) &= \kappa_1\rho_1^2\hat{p}_1^2 + \left(m^2\kappa_1(\dot{\rho}_1^2 - 2\rho_1\dot{\rho}_1\dot{\chi}(t)) + \frac{\kappa_1\xi_1^2}{\rho_1^2}\right)\hat{x}_1^2 \\ &- m\kappa_1\rho_1(\dot{\rho}_1 - \dot{\chi}(t)\rho_1)(\hat{x}_1\hat{p}_1 + \hat{p}_1\hat{x}_1),\end{aligned}\quad (51)$$

$$\begin{aligned}\hat{I}_2(t) &= \kappa_2\rho_2^2\hat{p}_2^2 + \left(m^2\kappa_2(\dot{\rho}_2^2 + 2\rho_2\dot{\rho}_2\dot{\chi}(t)) + \frac{\kappa_2\xi_2^2}{\rho_2^2}\right)\hat{x}_2^2 \\ &- m\kappa_2\rho_2(\dot{\rho}_2 + \dot{\chi}(t)\rho_2)(\hat{x}_2\hat{p}_2 + \hat{p}_2\hat{x}_2).\end{aligned}\quad (52)$$

It is important to note that κ_1 and κ_2 being arbitrary constants, can be set to unity for a simplified analysis. In order to proceed further, we would try to compute the raising and lowering operators corresponding to the new separable invariant operators \hat{I}_1 and \hat{I}_2 .

V. OBTAINING THE CREATION AND ANNIHILATION OPERATORS

In this section, we will obtain the creation and annihilation operators corresponding to the invariant operator $\hat{I}_1(t)$ using a simple “*completing the square*” approach and proceed to do the same for $\hat{I}_2(t)$. Our primary aim is to recast $\hat{I}_1(t)$ in such a way that $\hat{I}_1(t) = A_1^2(\hat{x}_1, \hat{p}_1) + A_2^2(\hat{x}_1, \hat{p}_1) + A_3$, where A_3 is a constant. We can recast $\hat{I}_1(t)$ in the following way

$$\begin{aligned}\frac{\hat{I}_1}{\kappa_1} &= \frac{\xi_1^2\hat{x}_1^2}{\rho_1^2} + \rho_1^2\hat{p}_1^2 + m\rho_1(\rho_1\dot{\chi}(t) - \dot{\rho}_1)\hat{p}_1\hat{x}_1 + m\rho_1(\rho_1\dot{\chi}(t) \\ &- \dot{\rho}_1)\hat{x}_1\hat{p}_1 + m^2(\rho_1\dot{\chi}(t) - \dot{\rho}_1)^2\hat{x}_1^2 - m^2(\rho_1\dot{\chi}(t) \\ &- \dot{\rho}_1)^2\hat{x}_1^2 + m^2(\dot{\rho}_1^2 - 2\rho_1\dot{\rho}_1\dot{\chi}(t))\hat{x}_1^2.\end{aligned}\quad (53)$$

From the last line of the above equation, we can see that the final two terms cancel each other up to $\mathcal{O}(\hbar)$. Hence, we can recast eq.(53) in the following form

$$\frac{\hat{I}_1}{\kappa_1} = \frac{\xi_1^2\hat{x}_1^2}{\rho_1^2} + (\rho_1\hat{p}_1 + m(\rho_1\dot{\chi}(t) - \dot{\rho}_1)\hat{x}_1)^2. \quad (54)$$

From now on, we shall be working in the $\hbar = c = 1$ unit. As a result the commutation relation between the position and momentum variables take the form $[\hat{x}_1, \hat{p}_1] = [\hat{x}_2, \hat{p}_2] = i$. We can now recast eq.(54) in the following form

$$\begin{aligned}\hat{I}_1 &= \kappa_1 \left[\frac{\xi_1\hat{x}_1}{\rho_1} - i(\rho_1\hat{p}_1 + m(\rho_1\dot{\chi}(t) - \dot{\rho}_1)\hat{x}_1) \right] \\ &\times \left[\frac{\xi_1\hat{x}_1}{\rho_1} + i(\rho_1\hat{p}_1 + m(\rho_1\dot{\chi}(t) - \dot{\rho}_1)\hat{x}_1) \right] + \kappa_1\xi_1.\end{aligned}\quad (55)$$

As κ_1 and ξ_1 are both arbitrary constants, we can choose $\kappa_1 = \frac{1}{2}$ and $\xi_1 = 1$. We can again recast eq.(55) as follows

$$\hat{I}_1(t) = \hat{a}_1^\dagger(t)\hat{a}_1(t) + \frac{1}{2} \quad (56)$$

where

$$\begin{aligned} \hat{a}_1 &= \frac{1}{\sqrt{2}\rho_1} (\hat{x}_1 + i\rho_1^2\hat{p}_1 + im\rho_1(\rho_1\dot{\chi} - \dot{\rho}_1)\hat{x}_1) \\ &= \frac{1}{\sqrt{2}\rho_1} (\hat{x}_1 + i\rho_1^2\hat{p}_1 + im\rho_1(\rho_1\Gamma_{01}^1 - \dot{\rho}_1)\hat{x}_1) \end{aligned} \quad (57)$$

where $\Gamma_{01}^1 = \dot{\chi}(t)$. It can be easily checked using the form of eq.(57) that $[\hat{a}_1, \hat{a}_1^\dagger] = 1$. We can also recast the invariant operator \hat{I}_2 as follows

$$\hat{I}_2(t) = \hat{a}_2^\dagger(t)\hat{a}_2(t) + \frac{1}{2} \quad (58)$$

where

$$\begin{aligned} \hat{a}_2 &= \frac{1}{\sqrt{2}\rho_2} (\hat{x}_2 + i\rho_2^2\hat{p}_2 - im\rho_2(\rho_2\dot{\chi} + \dot{\rho}_2)\hat{x}_2) \\ &= \frac{1}{\sqrt{2}\rho_2} (\hat{x}_2 + i\rho_2^2\hat{p}_2 + im\rho_2(\rho_2\Gamma_{02}^2 - \dot{\rho}_2)\hat{x}_2) \end{aligned} \quad (59)$$

where $\Gamma_{02}^2 = -\dot{\chi}(t)$ and $[\hat{a}_2, \hat{a}_2^\dagger] = 1$. From eq.(s)(57,58), we can write down a generalized commutation relation involving the ladder operators given by

$$[\hat{a}_j, \hat{a}_k^\dagger] = \delta_{jk} \quad (60)$$

for $j, k = \{1, 2\}$. With the forms of the creation and annihilation operators in hand, we shall now proceed to obtain the Lewis phase for the system.

VI. LEWIS AND BERRY PHASE FOR THE SYSTEM

In this section, we shall obtain the Lewis phase and eventually the Berry phase for the system. To obtain the Lewis phase, we need to properly construct the eigenstates corresponding to the Lewis invariant operators. It is important to note that the total Lewis invariant of the system can be divided into two Lewis invariants (eq.(43)) and each of the invariant operators can be expressed as a number operator plus a constant. Hence, it is straightforward to write down the total eigenstate corresponding to $\hat{I}(t)$ as a tensor product of two number states corresponding to each of the two directions given by

$$|n_1, n_2\rangle = |n_1\rangle \otimes |n_2\rangle \quad (61)$$

such that

$$(\hat{a}_1 \otimes \mathbb{1}_2)|0, n_2\rangle = 0, \text{ and, } (\mathbb{1}_1 \otimes \hat{a}_2)|n_1, 0\rangle = 0. \quad (62)$$

We can further define the action of the invariant operator on the number state as follows

$$\begin{aligned} \hat{I}(t)|n_1, n_2\rangle &= \left(\hat{I}_1(t) \otimes \mathbb{1}_2 + \mathbb{1}_1 \otimes \hat{I}_2(t) \right) |n_1, n_2\rangle \\ &= \left(n_1 + \frac{1}{2} \right) |n_1, n_2\rangle + \left(n_2 + \frac{1}{2} \right) |n_1, n_2\rangle \\ &= (n_1 + n_2 + 1)|n_1, n_2\rangle. \end{aligned} \quad (63)$$

It is straightforward to write down the number state as an action of creation operators on the individual vacuum states as follows

$$|n_1, n_2\rangle = \frac{1}{\sqrt{n_1!n_2!}} \left((\hat{a}_1^\dagger)^{n_1}|0\rangle \right) \otimes \left((\hat{a}_2^\dagger)^{n_2}|0\rangle \right). \quad (64)$$

For $\hbar = 1$, we can recast eq.(16) (and for $|\phi_n\rangle = |n_1, n_2\rangle$) as follows

$$\begin{aligned} \dot{\theta}(t) &= \langle n_1, n_2 | i(\partial_t)_1 \otimes \mathbb{1}_2 + \mathbb{1}_1 \otimes i(\partial_t)_2 - (\hat{H}_1(t) \otimes \mathbb{1}_2 \\ &\quad + \mathbb{1}_1 \otimes \hat{H}_2(t)) | n_1, n_2 \rangle \\ &= \langle n_1 | i(\partial_t)_1 - \hat{H}_1(t) | n_1 \rangle \langle n_2 | \mathbb{1}_2 | n_2 \rangle + \langle n_1 | \mathbb{1}_1 | n_1 \rangle \\ &\quad \times \langle n_2 | i(\partial_t)_2 - \hat{H}_2(t) | n_2 \rangle \\ &= \langle n_1 | i(\partial_t)_1 - \hat{H}_1(t) | n_1 \rangle + \langle n_2 | i(\partial_t)_2 - \hat{H}_2(t) | n_2 \rangle \\ &= \dot{\theta}_1(t) + \dot{\theta}_2(t) \end{aligned} \quad (65)$$

where

$$\dot{\theta}_1(t) = \langle n_1 | i(\partial_t)_1 - \hat{H}_1(t) | n_1 \rangle, \quad (66)$$

$$\dot{\theta}_2(t) = \langle n_2 | i(\partial_t)_2 - \hat{H}_2(t) | n_2 \rangle. \quad (67)$$

We shall now make use of eq.(s)(66,67) to obtain the forms of the Lewis phases $\theta_1(t)$ and $\theta_2(t)$. In order to obtain the form of $\dot{\theta}_1(t)$, we at first need to calculate the commutator bracket $[\hat{a}_1, i\partial_t - \hat{H}_1(t)]$ given as follows

$$[\hat{a}_1, i\partial_t - \hat{H}_1]|\psi\rangle = \left(-i\dot{\hat{a}}_1 - [\hat{a}_1, \hat{H}_1] \right) |\psi\rangle. \quad (68)$$

The analytical form of $-i\dot{\hat{a}}_1$ is given by

$$-i\dot{\hat{a}}_1 = \frac{i\dot{\rho}_1}{\sqrt{2}\rho_1^2}\hat{x}_1 + \frac{\dot{\rho}_1\hat{p}_1}{\sqrt{2}} + \frac{m}{\sqrt{2}} \left[\dot{\rho}_1\Gamma_{01}^1 + \rho_1\dot{\Gamma}_{01}^1 - \dot{\rho}_1 \right] \hat{x}_1 \quad (69)$$

and the form of $[\hat{a}_1, \hat{H}_1]$ is given by

$$\begin{aligned} [\hat{a}_1, \hat{H}_1] &= \frac{i\hat{p}_1}{\sqrt{2}m\rho_1} + \frac{i\Gamma_{01}^1\hat{x}_1}{\sqrt{2}\rho_1} + \frac{\rho_1 m\omega_1^2\hat{x}_1}{\sqrt{2}} + \frac{\dot{\rho}_1\hat{p}_1}{\sqrt{2}} \\ &\quad + \frac{m\Gamma_{01}^1\dot{\rho}_1\hat{x}_1}{\sqrt{2}}. \end{aligned} \quad (70)$$

Summing eq.(69) with eq.(70) and making use of the Ermakov-Pinney equation in eq.(47) (for $\xi_1 = 1$ and $\dot{d}(t) = \frac{1}{2}\dot{\Gamma}_{01}^1$), we can express the form of the commutator bracket in eq.(68) as follows

$$[\hat{a}_1, i\partial_t - \hat{H}_1] = -\frac{1}{m\rho_1^2}\hat{a}_1. \quad (71)$$

Making use of the analytical form of the commutator bracket given in eq.(71), again we can recast the right hand side of eq.(66) as

$$\langle n_1 | i(\partial_t)_1 - \hat{H}_1(t) | n_1 \rangle = -\frac{n_1}{m\rho_1^2} + \langle 0 | i\partial_t - \hat{H}_1 | 0 \rangle. \quad (72)$$

Now $\langle 0 | i\partial_t - \hat{H}_1 | 0 \rangle$ can be set to any value. It is convenient for our analysis to choose

$$\langle 0 | i\partial_t - \hat{H}_1 | 0 \rangle = -\frac{1}{2m\rho_1^2}. \quad (73)$$

Using, eq.(s)(72,73), we can write down the Lewis phase $\theta_1(t)$ as follows

$$\theta_1(t) = -\left(n_1 + \frac{1}{2}\right) \int_0^t \frac{d\tau}{m\rho_1^2(\tau)}. \quad (74)$$

Following similar analysis, we can obtain the other Lewis phase $\theta_2(t)$ as follows

$$\theta_2(t) = -\left(n_2 + \frac{1}{2}\right) \int_0^t \frac{d\tau}{m\rho_2^2(\tau)}. \quad (75)$$

With the forms of $\theta_1(t)$ and $\theta_2(t)$ in hand, we can now proceed to obtain the geometric part of the phase making use of the adiabatic approximation. In the adiabatic approximation, $\ddot{\rho}_1(t) = \ddot{\rho}_2(t) = 0$ and the modified Ermakov-Pinney equations corresponding to the two coordinates take the form

$$\omega^2(t) - \dot{\Gamma}_{01}^1(t) \simeq \frac{1}{m^2\rho_1^4(t)}, \quad (76)$$

$$\omega^2(t) + \dot{\Gamma}_{01}^1(t) \simeq \frac{1}{m^2\rho_2^4(t)}. \quad (77)$$

As $\dot{\Gamma}_{01}^1(t)$ is a very small quantity, we can further simplify eq.(s)(76,77) in the following forms

$$\frac{1}{m\rho_1^2(t)} \simeq \omega(t) - \frac{\dot{\Gamma}_{01}^1(t)}{2\omega(t)}, \quad (78)$$

$$\frac{1}{m\rho_2^2(t)} \simeq \omega(t) + \frac{\dot{\Gamma}_{01}^1(t)}{2\omega(t)}. \quad (79)$$

It is straightforward to show that, corresponding to the two coordinate directions, if one considers the hamonic oscillator frequencies to be different in the two coordinate directions then eq.(s)(78,79) take the forms given by

$$\frac{1}{m\rho_1^2(t)} = \omega_1(t) - \frac{\dot{\Gamma}_{01}^1(t)}{2\omega_1(t)}, \quad \frac{1}{m\rho_2^2(t)} = \omega_2(t) + \frac{\dot{\Gamma}_{01}^1(t)}{2\omega_2(t)}. \quad (80)$$

Substituting eq.(80) back in eq.(s)(74,75), we obtain the following two relations

$$\tilde{\theta}_1(t) = -\left(n_1 + \frac{1}{2}\right) \left(\int_0^t \omega_1(\tau) d\tau - \int_0^t \frac{\dot{\Gamma}_{01}^1(\tau)}{2\omega_1(\tau)} d\tau \right), \quad (81)$$

$$\tilde{\theta}_2(t) = -\left(n_2 + \frac{1}{2}\right) \left(\int_0^t \omega_2(\tau) d\tau + \int_0^t \frac{\dot{\Gamma}_{01}^1(\tau)}{2\omega_2(\tau)} d\tau \right) \quad (82)$$

where $\tilde{\theta}_n(t)$ (for $n = \{1, 2\}$) denotes the Lewis phase $\theta_n(t)$ in the adiabatic approximation. From eq.(s)(81,82), it is straightforward to observe that the first integrals introduce a dynamic phase whereas the second integrals are geometric in nature. Now we consider that the Hamiltonian of the system completes an adiabatic cycle at $t = \mathcal{T}$ in the parameter space and as a result it is possible to write down

$$\mathcal{R}(0) = \mathcal{R}(\mathcal{T}); \quad \mathcal{R} = (b, d). \quad (83)$$

We can now easily write down the first order time derivative in terms of \mathcal{R} as

$$\frac{d}{dt} = \frac{d\mathcal{R}}{dt} \nabla_{\mathcal{R}}. \quad (84)$$

Hence, corresponding to the two coordinate directions and making use of eq.(84), we can write down the Berry's geometric phases to be of the following form

$$\Theta_1^G = \left(n_1 + \frac{1}{2}\right) \oint^{\mathcal{R}} \frac{1}{\omega_1} \vec{\nabla}_{\mathcal{R}}(\Gamma_{01}^1) \cdot d\vec{\mathcal{R}}, \quad (85)$$

$$\Theta_2^G = -\left(n_2 + \frac{1}{2}\right) \oint^{\mathcal{R}} \frac{1}{\omega_2} \vec{\nabla}_{\mathcal{R}}(\Gamma_{01}^1) \cdot d\vec{\mathcal{R}}. \quad (86)$$

VII. EXPLICIT BERRY PHASE CALCULATION

In this section, we shall make use of eq.(s)(85,86) to compute some explicit forms of the Berry phases corresponding to the two coordinate directions.

For a linearly polarized gravitational wave

$$h_{jk}(t) = 2f_0 \cos \Omega t (\varepsilon_+ \sigma_{jk}^3 + \varepsilon_- \sigma_{jk}^1) \quad (87)$$

where we have set $\chi(t) = f_0 \cos \Omega t$ in eq.(3) with f_0 being the amplitude of the gravitational wave and Ω being the frequency of the same. It is important to note that we have considered that the gravitational wave is carrying plus polarization only. Using eq.(87), we can write down the first order time derivative of the Christoffel symbol $\dot{\Gamma}_{01}^1 = \frac{\ddot{h}_{11}(t)}{2} = -f_0 \Omega^2 \varepsilon_+ \cos \Omega t$. For a linearly polarized gravitational wave, eq.(s)(85,86) give

$$\Theta_1^G = -f_0 \Omega^2 \varepsilon_+ \left(n_1 + \frac{1}{2}\right) \int_0^{\frac{2\pi}{\Omega}} d\tau \frac{\cos \Omega \tau}{2\omega_1(\tau)}, \quad (88)$$

$$\Theta_2^G = f_0 \Omega^2 \varepsilon_+ \left(n_2 + \frac{1}{2}\right) \int_0^{\frac{2\pi}{\Omega}} d\tau \frac{\cos \Omega \tau}{2\omega_2(\tau)}. \quad (89)$$

Now for an explicit set of choices of the frequencies $\omega_1(t) = \omega_{01} \cos \Omega t$ and $\omega_2(t) = \omega_{02} \cos \Omega t$, we can evaluate Θ_1^G and Θ_2^G as follows

$$\Theta_1^G = -\frac{f_0 \pi \Omega \varepsilon_+}{\omega_{01}} \left(n_1 + \frac{1}{2}\right), \quad (90)$$

$$\Theta_2^G = \frac{f_0 \pi \Omega \varepsilon_+}{\omega_{02}} \left(n_2 + \frac{1}{2}\right). \quad (91)$$

Our second choice of the frequencies are $\omega_1(t) = \omega_1 + \tilde{\omega}_1 \cos \Omega t$ and $\omega_2(t) = \omega_2 + \tilde{\omega}_2 \cos \Omega t$, such that $|\omega_1| \neq |\tilde{\omega}_1|$ and $|\omega_2| \neq |\tilde{\omega}_2|$. Under this choice of frequencies, we can evaluate Θ_1^G and Θ_2^G given by

$$\Theta_1^G = -\frac{\pi f_0 \Omega \varepsilon_+}{\tilde{\omega}_1} \left(n_1 + \frac{1}{2} \right), \quad (92)$$

$$\Theta_2^G = \frac{\pi f_0 \Omega \varepsilon_+}{\tilde{\omega}_2} \left(n_2 + \frac{1}{2} \right). \quad (93)$$

VIII. SUMMARY

In this work we have considered a gravitational wave interacting with a harmonic oscillator. Our initial analysis considers the gravitational wave (in the transverse traceless gauge) to be in both the plus and cross polarizations.

We have then used the Lewis invariant method to obtain a suitable Lewis invariant corresponding to the total Hamiltonian of the system. In order to find a Lewis invariant, we have used an ansatz considering contributions from all quadratic order terms in the phase space variables and finally obtained two separable Lewis invariants by dropping the cross polarization terms. The reason behind dropping the cross polarization is to avoid unnecessary complications during the calculation of the Lewis phase. Using the “*completing the square*” approach, we have then obtained the ladder operators corresponding to the two coordinate directions from the obtained Lewis invariants. Next we have obtained the Lewis phases for the system and making use of the adiabatic approximation, we have finally obtained the geometric phases corresponding to the two coordinate directions of the system. Finally, we have obtained explicit Berry phases for a linearly polarized gravitational wave and for different choices of the frequencies of the harmonic oscillator system.

-
- [1] H. R. Lewis Jr. and W. B. Riesenfeld, *J. Math. Phys.* **10** (1969) 1458.
- [2] H. R. Lewis Jr., *J. Math. Phys.* **9** (1968) 1976.
- [3] H. R. Lewis Jr., *Phys. Rev. Lett.* **18** (1967) 510; *Erratum: Phys. Rev. Lett.* **18** (1967) 636.
- [4] I. A. Pedrosa, *J. Math. Phys. A* **28** (1987) 2662.
- [5] A. Jannussis and V. E. Bartzis, *Phys. Lett. A* **132** (1988) 324.
- [6] I. A. Pedrosa, *Rev. Bras. Fis.* **19** (1989) 502.
- [7] M. S. Abdalla and N. A. Ismael, *Int. J. Theor. Phys.* **48** (2009) 2757.
- [8] I. A. Pedrosa and D. A. P. de Lima, *Int. J. Mod. Phys. B* **28** (2014) 1450177.
- [9] L. M. Lawson, G. Y. H. Avossevou, and L. Gouba, *J. Math. Phys.* **59** (2018) 112101.
- [10] M. Dutta, S. Ganguly, and S. Gangopadhyay, *Int. J. Theor. Phys.* **59** (2020) 3852.
- [11] M. Dutta, S. Ganguly, and S. Gangopadhyay, *Phys. Scr.* **96** (2021) 125224.
- [12] M. Born and V. Fock, *Z. Physik* **51** (1965) 128.
- [13] D. J. Griffiths, “*Introduction to Quantum Mechanics*” (2005) II edn (Upper Saddle River: Prentice Hall).
- [14] M. V. Berry, *Proc. R. Soc. Lond. A* **392** (1984) 45.
- [15] M. V. Berry, *J. Phys. A: Math. Gen.* **18** (1985) 15.
- [16] R. Y. Chiao and Y. S. Wu, *Phys. Rev. Lett.* **57** (1986) 933; *Erratum: Phys. Rev. Lett.* **57** (1986) 2471.
- [17] A. Tomita and R. Y. Chiao, *Phys. Rev. Lett.* **57** (1986) 937.
- [18] J. Anandan, *Nature* **360** (1992) 307.
- [19] G. Ghosh and B. Dutta-Roy, *Phys. Rev. D* **37** (1988) 1709.
- [20] G. Giavarini, E. Gozzi, D. Rohrlich, and W. D. Thacker, *J. Phys. A* **22** (1989) 3513.
- [21] G. Giavarini, E. Gozzi, D. Rohrlich, and W. D. Thacker, *Phys. Lett. A* **138** (1989) 235.
- [22] G. Giavarini, E. Gozzi, D. Rohrlich, and W. D. Thacker, *Phys. Rev. D* **39** (1989) 3007.
- [23] W. Dittrich and M. Reuter, *Phys. Lett. A* **155** (1991) 94.
- [24] M. Dutta, S. Ganguly, and S. Gangopadhyay, *Phys. Scr.* **97** (2022) 105204.
- [25] A. Saha and S. Gangopadhyay, *Class. Quant. Gravit.* **33** (2016) 205006.
- [26] S. Bhattacharyya, S. Gangopadhyay, and A. Saha, *Class. Quant. Gravit.* **36** (2019) 055006.
- [27] S. Gangopadhyay, S. Bhattacharyya, and A. Saha, *Ukr. J. Phys.* **64** (2019) 1029.
- [28] S. Sen, S. Bhattacharyya, and S. Gangopadhyay, *Universe* **8** (2022) 450.
- [29] V. P. Ermakov, *Univ. Izv. Kiev* **20** (1880) 1; English translation: V. P. Ermakov, *Appl. Anal. Discrete Math.* **2** (2008) 123145.
- [30] E. Pinney, *Proc. Amer. Math. Soc.* **1** (1950) 681.