

ON THE APPROXIMATION OF OPERATOR-VALUED RICCATI EQUATIONS IN HILBERT SPACES

JAMES CHEUNG

Millennium Space Systems, A Boeing Company. 2265 E. El Segundo Blvd, El Segundo, CA, 90245.

ABSTRACT. In this work, we present an abstract theory for the approximation of operator-valued Riccati equations posed on Hilbert spaces. It is demonstrated here, under the assumption of compactness in the coefficient operators, that the error of the approximate solution to the operator-valued Riccati equation is bounded above by the approximation error of the governing semigroup. One significant outcome of this result is the correct prediction of optimal convergence for finite element approximations of the operator-valued Riccati equations for when the governing semigroup involves parabolic, as well as hyperbolic processes. We derive the abstract theory for the time-dependent and time-independent operator-valued Riccati equations in the first part of this work. In the second part, we prove optimal convergence rates for the finite element approximation of the functional gain associated with model one-dimensional weakly damped wave and thermal LQR control systems. These theoretical claims are then corroborated with computational evidence.

CONTENTS

1. Introduction	2
2. Problem Setting	3
2.1. Notation	3
2.2. Bochner Integral Operator-Valued Riccati Equations	5
2.3. An Abstract Approximation of Operator-Valued Riccati Equations	8
2.4. Application Problems	11
2.5. The Brezzi-Rappaz-Raviart Theorem	12
3. An Error Estimate for Time-Dependent Approximations	13
3.1. Time-Dependent Lyapunov Operator	14
3.2. Convergence of the Time-Dependent Lyapunov Operator Approximation	15
3.3. Approximation Error	16
4. An Error Estimate for Time-Independent Approximations	18
4.1. Time-Independent Lyapunov Operator	18
4.2. Convergence of Time-Independent Lyapunov Operator Approximations	19
4.3. Approximation Error	20
5. One Dimensional Model LQR Control Problems	20
5.1. Notation	21
5.2. Finite-Horizon LQR Control of a 1D Thermal Process	21
5.3. Infinite-Horizon LQR Control of a 1D Weakly Damped Wave System	25
6. Conclusion	28
7. Future Work	28
References	29
Appendix A. Technical Lemmas	30
Appendix B. Error Estimates for Finite Element Approximation of Semigroups	31
B.1. Finite Element Approximation of the Thermal Semigroup	31
B.2. Finite Element Approximation of the Weakly Damped Wave Semigroup	32

1. INTRODUCTION

In recent years, the reinforcement learning community has been rediscovering the usefulness of optimal control in the context of determining action policies. In general, reinforcement learning is involved with the direct numerical approximation of the dynamic programming principle, where the Hamilton-Jacobi-Bellman equation is solved to obtain the value of each possible state in the state space. A simplification of these equations can be made if the cost function to be minimized is quadratic and if the dynamical system governing the state is linear. This simplified problem is known in the optimal control community as the linear quadratic regulator (LQR) [39]. For these control systems, the dynamic programming principle gives an optimal feedback law which depends on the solution of Riccati equations. Aside from optimal controls, Riccati equations can be found in the Kálmán filter [31], in two-player linear quadratic games, and H^∞ -control [35]. The broad implications of Riccati equations make it a very important problem to study in science, engineering, and mathematics.

Many application problems require solving the Riccati equation on infinite dimensional topologies, for example, in the control of systems whose state is governed by partial differential equations. For these systems, we call the associated Riccati equation *operator-valued Riccati equations* to emphasize its potentially infinite dimensional nature. It is most often the case that the state equation is approximated with a finite dimensional set of equations and that all the operators in the operator-valued Riccati equation is approximated with finite dimensional operators.

There has been a great body of literature written discussing the convergence of approximate solutions of operator-valued Riccati equations. We cite some works on this topic here [4, 34, 30, 10, 13]. While the theory presented in these works prove the pointwise convergence of approximate solutions to the exact solution, they fail to predict the rate at which approximate solutions converge. Of course, convergence rates (i.e. error estimates) are important in predicting how accurate an approximation is a priori.

Several works have provided insight on error bounds for the approximate solution of operator-valued Riccati equations for parabolic systems. In [29], it was proven that $\mathcal{O}(h)$ convergence is achieved for when the operators in the Riccati equation are approximated using the finite element method. Here, the differential form of the Riccati equation was used in the error analysis for deriving the error bound. The theoretical convergence rate has then been improved upon in [33], where an error bound of $\mathcal{O}(h^2 \log(\frac{1}{h}))$ was proven. In this work, the mild form of the operator-valued Riccati equation was used in the analysis. Following this pattern of increasing the strength of the form of the equation analyzed, [12] used the Bochner integral form of the operator-valued Riccati equation to derive an optimal theoretical convergence rate of $\mathcal{O}(h^{k+1})$ for k -order finite element approximations. While optimal convergence rates were proven in [12], the theory was limited to steady-state operator-valued Riccati equations. It also only applies to the case for when the semigroup of the process is compact. The shortcomings of the previous approaches indicates to us that a new approach is necessary to analyze the approximation error associated with approximating the solution to the operator-valued Riccati equation.

In this work, we seek to derive a more general theory that is able to predict optimal convergence for when the process semigroup is only bounded, e.g. for both parabolic and hyperbolic partial differential equation systems. Additionally, we aim to provide results for both the time-dependent and time-independent operator-valued Riccati equations. While the focus of this work is indeed on demonstrating optimal finite element error bounds, we emphasize that the general theory presented here can be applied to other approximation methods and also to systems that are not necessarily governed by partial differential equations. We provide some possible example applications in the beginning section of this work.

This work will first begin by defining the necessary notation and theoretical framework necessary for our discussion. Afterwards, we will then discuss the Bochner integral form of the operator-valued Riccati equations and present an abstract approximation that we study the converge of in the subsequent sections. With this, we provide some examples of potential application problems and approximation methods that can be analyzed within the framework provided in this work. After discussing these potential applications we then derive abstract error estimates that allows for the approximate solution to the operator-valued Riccati equation to be bounded by the error of the semigroup approximation for both the time-dependent and time-independent problems. Finally, we move on to present theoretical and computational results for model problems involving controlling a weakly damped wave system and a thermal control system.

2. PROBLEM SETTING

This section is concerned with establishing the theoretical framework necessary to analyze the approximation of operator-valued Riccati equations. We begin our discussion by defining the notation that we will use throughout this work. Then, we discuss the Bochner integral form of the time-dependent and time-independent operator Riccati equations and their approximations. Afterwards, we move on to state several examples to show that the operator-valued Riccati equations are pervasive in optimal control, state estimation, and game theory. And finally, we conclude this section with a brief discussion of the Brezzi-Rappaz-Raviart theorem.

2.1. Notation. In this subsection, we will define the notation that we will utilize throughout this work.

2.1.1. Bounded Linear Operators on Hilbert Spaces. In this work, we are interested in the Riccati equation posed on Hilbert spaces. To that end, let us denote H as a separable Hilbert space and

$$(\cdot, \cdot)_H : H \times H \rightarrow \mathbb{R}_+$$

as the inner product on H . The norm on H is then defined as

$$\|\phi\|_H := (\phi, \phi)_H^{\frac{1}{2}}$$

for any $\phi \in H$. Further, we will denote $\mathcal{L}(H)$ as the space of bounded linear operators on H . The $\mathcal{L}(H)$ norm is then defined as

$$\|T\|_{\mathcal{L}(H)} := \sup_{\phi \in H} \frac{\|T\phi\|_H}{\|\phi\|_H} \quad \forall \phi \in H,$$

for any bounded linear operator $T \in \mathcal{L}(H)$.

The space of all compact operators on H will be denoted as \mathcal{J}_∞ to be consistent with the trace-class spaces the solution to the problem of interest belong to. To be more precise,

$$\mathcal{J}_\infty := \{T \in \mathcal{L}(H) : T\phi \in K, \quad \forall \phi \in H \text{ and for any compact } K \subset H\}.$$

The \mathcal{J}_∞ norm is then given by

$$\|T\|_{\mathcal{J}_\infty} := \sup_{j \in \mathbb{N}_0} |\sigma_j|,$$

where $\{\sigma_j\}_{j=1}^\infty \in \mathbb{C}$ are the singular-values of the operator T . The \mathcal{J}_∞ norm is known to coincide with the $\mathcal{L}(H)$ norm for the operators that we discuss in this work (i.e. $\|T\|_{\mathcal{L}(H)} = \|T\|_{\mathcal{J}_\infty}$ for all $T \in \mathcal{J}_\infty$ where T is a normal operator). Although the $\mathcal{L}(H)$ and \mathcal{J}_∞ norms are equivalent, we will denote the norm of \mathcal{J}_∞ -valued operators as $\|\cdot\|_{\mathcal{J}_\infty}$ to emphasize the compactness of the operator being measured. Additionally, it is known that \mathcal{J}_∞ is a two-sided *-ideal on $\mathcal{L}(H)$, which can be restated as the following.

Proposition 1. *Let $X \in \mathcal{J}_\infty$ and $Y \in \mathcal{L}(H)$, then we have that $XY \in \mathcal{J}_\infty$, $YX \in \mathcal{J}_\infty$.*

Proof. See [2, Theorem 10.69] for a proof. □

Symmetric operators are prevalent in our discussion on the equations studied in this work. We will denote $\mathcal{J}_\infty^s \subset \mathcal{J}_\infty$ as the space of all symmetric compact operators defined on H . In mathematical notation,

$$\mathcal{J}_\infty^s := \{T \in \mathcal{J}_\infty : T\phi = T^*\phi \quad \forall \phi \in H\}.$$

It is a simple exercise to see that \mathcal{J}_∞^s is a topological vector space.

The space of bounded linear operators mapping a Hilbert space H_1 to a Hilbert space H_2 will be denoted as $\mathcal{L}(H_1, H_2)$, whose norm is defined as

$$\|T\|_{\mathcal{L}(H_1, H_2)} = \sup_{\psi \in H_1} \frac{\|T\psi\|_{H_2}}{\|\psi\|_{H_1}},$$

for any bounded linear operator $T \in \mathcal{L}(H_1, H_2)$. For any bounded linear operator $T \in \mathcal{L}(H_1, H_2)$, we have that $T^* \in \mathcal{L}(H_2, H_1)$, where T^* is defined as the adjoint of T . Additionally, it is known that

$$(T\psi, \eta)_{H_2} = (\psi, T^*\eta)_{H_1}$$

for all $\psi \in H_1$ and $\eta \in H_2$. This implies that $\|T\|_{\mathcal{L}(H_1, H_2)} = \|T^*\|_{\mathcal{L}(H_2, H_1)}$ [2, Theorem 10.11].

Let now, $K \subset H$ be a compact subset relative to a Hilbert space H . Throughout this work, we will utilize the following properties regarding $\mathcal{L}(H, K)$ and $\mathcal{L}(K, H)$.

Proposition 2. *Let H be a Hilbert space and K be a compact subset of H . Then the following inclusions hold*

$$\mathcal{L}(K, H) \subset \mathcal{J}_\infty \subset \mathcal{L}(H, K).$$

Proof. We begin by proving the first assertion presented in the above statement. From basic definitions, we have that

$$\|T\|_{\mathcal{J}_\infty} = \sup_{\phi \in H} \frac{\|T\phi\|_H}{\|\phi\|_H} \leq \sup_{\phi \in H} \frac{\|T\phi\|_K}{\|\phi\|_H} = \|T\|_{\mathcal{L}(H, K)},$$

since $K \subset H$. This result implies that $\mathcal{L}(H, K) \subset \mathcal{J}_\infty$, therefore proving our first assertion.

The second assertion is proven similarly by seeing that

$$\|T\|_{\mathcal{L}(K, H)} = \sup_{\phi \in K} \frac{\|T\phi\|_H}{\|\phi\|_K} \leq \sup_{\phi \in H} \frac{\|T\phi\|_H}{\|\phi\|_H} = \|T\|_{\mathcal{L}(H)},$$

again because $K \subset H$. This result then implies that $\mathcal{L}(K, H) \subset \mathcal{L}(H)$, therefore proving our second assertion. \square

Remark 1. *Additionally, in the Lemma 7 of the technical appendix, we provide a proof that $\mathcal{L}(H, K)$ is also forms a two-sided *-ideal on $\mathcal{L}(H)$. This is not a surprising result, since we already know that $\mathcal{L}(H, K) \subset \mathcal{J}_\infty$.*

The final class of operator spaces of interest in this work are the continuous Bochner spaces $\mathcal{C}(I; \mathcal{V})$, where $I \subset \mathbb{R}$ and $\mathcal{V} \subset \mathcal{L}(H)$ is an arbitrary operator space. This space is characterized by

$$\mathcal{C}(I; \mathcal{V}) := \{V(t) \in \mathcal{V} : \|V(t)\|_{\mathcal{V}} \text{ is a continuous function with respect to } t \in \mathbb{R}\}.$$

The $\mathcal{C}(I; \mathcal{V})$ norm is then defined as

$$\|V(\cdot)\|_{\mathcal{C}(I; \mathcal{V})} := \sup_{t \in I} \|V(t)\|_{\mathcal{V}}.$$

With the necessary functional analytic notations defined, we are now ready to discuss C_0 -semigroups and their approximations.

2.1.2. C_0 -Semigroups and Approximation on Hilbert Spaces. Let $A : \mathcal{D}(A) \rightarrow H$, where $\mathcal{D}(A) \subset H$ is the domain of A , be the (infinitesimal) generator of a C_0 -semigroup $S(t) \in \mathcal{L}(H)$. (See [27] for a discussion on C_0 -semigroups). $\mathcal{D}(A)$ is understood to be dense in H . By definition of C_0 -semigroups, we have that there exists constants $M, \omega \in \mathbb{R}_+$ so that

$$(1) \quad \|S(t)\|_{\mathcal{L}(H)} \leq M e^{\omega t} \quad \forall t \in \mathbb{R}_+.$$

It is known that for all $\phi \in \mathcal{D}(A)$ and $t \in \mathbb{R}_+$,

$$\frac{d}{dt} S(t)\phi = AS(t)\phi = S(t)A\phi.$$

Denoting $A^* : \mathcal{D}(A^*) \rightarrow H$ be the adjoint of A , then [27, Theorem 4.3] implies that A^* is the generator of a semigroup $S^*(t) \in \mathcal{L}(H)$ and that $S^*(t)$ is the adjoint of $S(t) \in \mathcal{L}(H)$ generated by A . By extension, we have also that

$$\frac{d}{dt} S^*(t)\phi = A^*S^*(t)\phi = S^*(t)A^*\phi$$

for all $\phi \in \mathcal{D}(A^*)$.

Define $H_n \subset H$ as a subset of H and $\pi_n : H \rightarrow H_n$ as the orthogonal projection operator defined by

$$(2) \quad \pi_n v := \sum_{j=1}^{\infty} (\phi_j, v)_H \phi_j,$$

where $\{\phi_j\}_{j=1}^{\infty}$ are the basis functions of H_n . We have assumed an infinite sum in (2) since we generally do not need any assumptions on the dimensionality of H_n in the abstract theory that we present in this work.

If H_n is a finite dimensional space, we can simply take $\phi_j := 0$ for all $j > n$. Let now $\iota_H : H_n \rightarrow H$ be the canonical injection operator. It is generally known that

$$(3) \quad \iota_H v_n := \pi_n^* v_n \quad \forall v_n \in H_n.$$

The projection and injection operators will play an important role in extending operators defined on $\mathcal{L}(H_n)$ to $\mathcal{L}(H)$, as we will see in the following paragraph.

Let now $A_n : \mathcal{D}(A_n) \rightarrow H_n$ be the generator of a C_0 -semigroup $\widehat{S}_n(t) \in \mathcal{L}(H_n)$. Again, by definition, there exists constants $M_n, \omega_n \in \mathbb{R}_+$ such that

$$(4) \quad \left\| \widehat{S}_n(t) \right\|_{\mathcal{L}(H_n)} \leq M_n e^{\omega_n t} \quad \forall t \in \mathbb{R}_+$$

We can now extend this semigroup to $\mathcal{L}(H)$ by defining $S_n(t) := \iota_H \widehat{S}_n(t) \pi_n$. Since the projection and injection operators are bounded above by 1, it becomes clear that

$$(5) \quad \|S_n(t)\|_{\mathcal{L}(H)} \leq M_n e^{\omega_n t} \quad \forall t \in \mathbb{R}_+,$$

where the constants $M_n, \omega_n \in \mathbb{R}_+$ are the same constants used in (4). It should be made clear that $S_n(t) \in \mathcal{L}(H)$ is not a C_0 -semigroup on H . This is because $\lim_{t \rightarrow 0} S_n(t)\phi \neq \phi$ for all $\phi \in H$. It is however a C_0 -semigroup on H_n . The definition of $S_n(t) \in \mathcal{L}(H)$ becomes useful when measuring the distance between $S(t) \in \mathcal{L}(H)$ and $\widehat{S}_n(t) \in \mathcal{L}(H_n)$ in the $\mathcal{L}(H)$ metric topology. Throughout this work, we will assume that $A_n : \mathcal{D}(A_n) \rightarrow H$ is defined in a way that it generates a parameterized sequence of C_0 -semigroup approximations $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ so that for any $t \in \mathbb{R}_+$

$$(6) \quad \lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_H = 0 \quad \forall \phi \in H.$$

This then implies that

$$\lim_{n \rightarrow \infty} \|S(t) - S_n(t)\|_{\mathcal{L}(K, H)} = 0$$

for any compact subset $K \subset H$ (as a consequence of [17, Theorem 5.3-2]). The convergence of $S_n(t) \in \mathcal{L}(H)$ to $S(t) \in \mathcal{L}(H)$ implies that $S_n^*(t) \in \mathcal{L}(H)$ converges to $S^*(t) \in \mathcal{L}(H)$. For reference, the conditions that must be satisfied in order for (6) to be true are given in [27, Chapter 1, §7]. These semigroup approximation conditions must be verified by the reader if they wish to use the abstract results presented in this work to their application problem.

Having established the basic operator-theoretic and semigroup notations, we now move on to define the equations that we wish to approximate using the theory derived in this work.

2.2. Bochner Integral Operator-Valued Riccati Equations. The first problem that we wish to approximate the solution to is given by seeking a $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ that satisfies

$$(7) \quad \Sigma(t) = S(t)\Sigma_0 S^*(t) + \int_0^t S(s) (F - \Sigma G \Sigma) (s) S^*(s) ds, \quad \forall t \in I$$

where $I := [0, \tau]$ for some $\tau \in \mathbb{R}_+$, $\Sigma_0 \in \mathcal{J}_\infty^s$, $F(\cdot), G(\cdot) \in \mathcal{C}(I, \mathcal{J}_\infty^s)$ are self-adjoint coefficient operators, and $S(t) \in \mathcal{L}(H)$ is again a C_0 -semigroup. This equation is shown to be equivalent to the weak differential operator Riccati equation found in, e.g. [22, Equation 6.45], as we demonstrate in Proposition 3.

From ([14, Theorem 3.6]), we have the following simplified statement of the well-posedness theorem for the Bochner integral representation of operator-valued Riccati equations.

Theorem 1 (Burns-Rautenberg). *Let H be a separable complex Hilbert space, $I = [0, \tau]$ be a bounded subset with $\tau \in \mathbb{R}_+$, and $S(t) \in \mathcal{L}(H)$ be a C_0 -semigroup on H . In addition, assume that*

- (1) $\Sigma_0 \in \mathcal{J}_\infty^s$;
- (2) $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$,

where $F(t)$ and $G(t)$ are non-negative and self-adjoint on H for all $t \in I$. Then the equation

$$\Sigma(t) = S(t)\Sigma_0 S^*(t) + \int_0^t S(t-s) (F - \Sigma G \Sigma) (s) S^*(t-s) ds,$$

where the integral is understood to be a Bochner integral, has a unique solution $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$. Furthermore $\Sigma(t)$ is non-negative and self-adjoint on H for all $t \in I$.

The operator-valued Riccati equation, in most applications, is stated in its differential form. To justify the error analysis presented in this work, we must prove that the Bochner integral representation of the Riccati equation is equivalent to the differential form of the Riccati equation. We do so in the following.

Proposition 3 (Equivalence of Bochner Integral and Differential Form). *Let H be a separable Hilbert space and $S(t) \in \mathcal{L}(H)$ be a C_0 -semigroup on H . Then $\Sigma(\cdot) \in \mathcal{C}(I, \mathcal{J}_\infty^s)$ satisfies*

$$(8) \quad \Sigma(t) = S(t)\Sigma_0 S^*(t) + \int_0^t S(t-s)(F - \Sigma G \Sigma)(s)S^*(t-s)ds \quad \forall t \in I,$$

if and only if $\Sigma(\cdot)$ satisfies

$$(9) \quad \begin{cases} \frac{d}{dt}(\psi, \Sigma(t)\phi)_H = (\psi, A\Sigma(t)\phi)_H + (\psi, \Sigma(t)A^*\phi)_H - (\psi, (\Sigma G \Sigma)(t)\phi)_H + (\psi, F(t)\phi)_H \\ (\psi, \Sigma(0)\phi)_H = (\psi, \Sigma_0\phi)_H \quad \{t = 0\}, \end{cases}$$

for all $\phi, \psi \in \mathcal{D}(A^*)$ and $t \in I$, where $I := [0, \tau]$ is a compact time interval, $\Sigma_0 \in \mathcal{J}_\infty^s$, $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ are non-negative and self-adjoint for all $t \in I$, and $A : \mathcal{D}(A) \subset H \rightarrow H$ is the generator of $S(t) \in \mathcal{L}(H)$.

Remark 2. Equation (9) is known as the weak form of the time-dependent operator-valued Riccati equation.

Proof. Recall that (8) is a well-posed problem by virtue of Theorem 1. We begin this analysis by testing this integral equation with test functions $\phi, \psi \in \mathcal{D}(A^*)$. This yields the following weak form of the Riccati equation

$$(10) \quad (\psi, \Sigma(t)\phi)_H = (\psi, S(t)\Sigma_0 S^*(t)\phi)_H + \int_0^t (\psi, S(t-s)(F - \Sigma G \Sigma)(s)S^*(t-s)\phi)_H ds \quad \forall \phi, \psi \in \mathcal{D}(A^*),$$

for almost every $t \in I$. It is clear that the solution of (8) satisfies (10), since strong solutions satisfy weak formulations. We then differentiate with respect to $t \in I$ to see that

$$(11) \quad \frac{d}{dt}(\psi, \Sigma\phi)_H = (\psi, A\Sigma(t)\phi)_H + (\psi, \Sigma A^*\phi)_H - (\psi, \Sigma G \Sigma(t)\phi)_H + (\psi, F(t)\phi)_H \quad \forall \phi, \psi \in \mathcal{D}(A^*)$$

for almost every $t \in I$. This is made clear by seeing that, for any $\phi \in \mathcal{D}(A^*)$,

$$(12) \quad \begin{aligned} \frac{d}{dt}S(t)\Sigma_0 S^*(t)\phi &= \left(\frac{d}{dt}S(t)\right)\Sigma_0 S^*(t)\phi + S(t)\Sigma_0 \left(\frac{d}{dt}S^*(t)\phi\right) \\ &= AS(t)\Sigma_0 S^*(t)\phi + S(t)\Sigma_0 S^*(t)A^*\phi \\ &= A\Sigma(t)\phi + \Sigma A^*\phi \\ &\quad - \int_0^t AS(t-s)(F + \Sigma G \Sigma)(s)S^*(t-s)\phi ds \\ &\quad - \int_0^t S(t-s)(F + \Sigma G \Sigma)(s)S^*(t-s)A^*\phi ds \\ &= A\Sigma(t)\phi + \Sigma A^*\phi - \int_0^t \frac{\partial}{\partial t}(S(t-s)(F - \Sigma G \Sigma)(s)S^*(t-s))\phi ds, \end{aligned}$$

and that

$$(13) \quad \begin{aligned} \frac{d}{dt} \int_0^t S(t-s)(F - \Sigma G \Sigma)(s)S^*(t-s)\phi ds = \\ F(t)\phi - \Sigma G \Sigma(t)\phi + \int_0^t \frac{\partial}{\partial t}(S(t-s)(F - \Sigma G \Sigma)(s)S^*(t-s))\phi ds \end{aligned}$$

for all $t \in I$ after applying the Leibniz integral rule and seeing that $S(0)\phi = \phi$ for all $\phi \in \mathcal{D}(A^*)$. Summing together (12) and (13), and then taking the inner product with the test function $\psi \in \mathcal{D}(A^*)$ yields (11).

The weak form of the initial condition is then derived by evaluating (8) at $t = 0$ and testing against $\phi, \psi \in \mathcal{D}(A^*)$, i.e.

$$(14) \quad (\psi, \Sigma(0)\phi)_H = (\psi, \Sigma_0\phi)_H$$

for all $\phi \in \mathcal{D}(A^*)$ since $S(0)\phi = S^*(0)\phi = \phi$ for all $\phi \in \mathcal{D}(A^*)$. Thus we have shown that the solution of (8) also satisfies (9). Equation (9) is then satisfied by testing (11) and (14) with a test function $\psi \in \mathcal{D}(A^*)$. Therefore, $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ satisfying (8) also satisfies (9).

We now prove the result in the other direction. Let us now suppose that $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ satisfies (9). Then integrating both sides of the equation gives us

$$(\psi, \Sigma(t)\phi)_H = (\psi, S(t)\Sigma_0 S^*(t)\phi)_H + \left(\psi, \int_0^t S(t-s)(F - \Sigma G \Sigma)(s) S^*(t-s)\phi ds \right)_H$$

for all $\phi, \psi \in \mathcal{D}(A^*)$. Theorem 1 demonstrates that the test functions $\phi, \psi \in \mathcal{D}(A^*)$ are not needed in order for the integral equation (8) to be well-posed. In light of this, we see that the operator $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ satisfying (9) also satisfies (8). This concludes the proof. \square

The well-posedness of the Bochner integral form of the time-dependent operator-valued Riccati equation and the equivalence of the Bochner integral form to the differential form of the Riccati equation have thus been established.

2.2.1. Time-Independent Bochner Integral Riccati Equation. We have shown in the previous subsection that the Bochner integral Riccati equation is well-posed and that it is equivalent to the differential Riccati equation in the sense that the solution of both equations coincide on any time interval. We will use this equivalence to derive an integral equation that allows us to solve for the steady-state solution of the time-dependent equation. Using the commonly used notation, we define the steady-state solution of the Riccati equation as the asymptotic limit of $\Sigma(t) \in \mathcal{J}_\infty^s$ solving as $t \rightarrow \infty$.

It is known, under the assumption of stabilizability and detectability of a system, that there exists a unique steady-state solution to the differential form of the Riccati equation [6, Part V, Theorem 3.1]. It is therefore sufficient to assume that $S(t) \in \mathcal{L}(H)$ is an exponentially stable semigroup and that $F, G \in \mathcal{J}_\infty^s$ are constant in time. We formalize the definition of the steady-state Bochner integral Riccati equation and show that its solution is unique in the following.

Proposition 4. *Let H be a separable Hilbert space and $S(t) \in \mathcal{L}(H)$ be an exponentially stable semigroup such that there exists constants $M, \alpha \in \mathbb{R}_+$ so that*

$$\|S(t)\|_{\mathcal{L}(H)} \leq M e^{-\alpha t} \quad \forall t \in \mathbb{R}_+.$$

Additionally, assume that $F, G \in \mathcal{J}_\infty^s$ are non-negative self-adjoint operators. Then, the steady-state of (8) is given by the solution of

$$(15) \quad \Sigma_\infty = \int_0^\infty S(s)(\Sigma_\infty G \Sigma_\infty - F) S^*(s) ds.$$

Proof. Under the assumptions given in the statement of the Lemma, we know that there exists a unique steady-state for the weak differential form of the Riccati equation given on almost all $t \in I$ by

$$(16) \quad \begin{cases} \frac{d}{dt} (\psi, \Sigma(t)\phi)_H = (\psi, A\Sigma(t)\phi)_H + (\psi, \Sigma(t)A^*\phi) - (\psi, (\Sigma(t)G\Sigma)(t)\phi)_H + (\psi, F(t)\phi)_H \\ (\psi, \Sigma(0)\phi)_H = (\psi, \Sigma_0\phi)_H, \end{cases}$$

for all $\phi, \psi \in \mathcal{D}(A^*)$ and any non-negative self-adjoint initial state $\Sigma_0 \in \mathcal{J}_\infty^s$ [6, Part V, Proposition 2.2, 2.3]. From the definition of the steady-state solution [6, Part V, Proposition 2.1], we have that $\lim_{t \rightarrow \infty} \frac{d}{dt} (\psi, \Sigma(t)\phi)_H = 0$ for all $\phi \in \mathcal{D}(A^*)$. Denoting $\Sigma_\infty = \lim_{t \rightarrow \infty} \Sigma(t)$, we observe that the system

$$(17) \quad \begin{cases} \frac{d}{dt} (\psi, \Sigma_\infty\phi)_H = (\psi, A\Sigma_\infty\phi)_H + (\psi, \Sigma_\infty A^*\phi)_H - (\psi, \Sigma_\infty F \Sigma_\infty\phi)_H + (\psi, G\phi)_H \\ (\psi, \Sigma(0)\phi)_H = (\psi, \Sigma_\infty\phi)_H, \end{cases}$$

is stationary (i.e. $\frac{d}{dt} \Sigma_\infty = 0$ for almost all $t \in \mathbb{R}_+$) for all $\phi, \psi \in \mathcal{D}(A^*)$ if we choose $\Sigma_0 := \Sigma_\infty$. Hence, the solution of the differential Riccati equation will remain at the steady-state if it starts at the steady state.

We then utilize Proposition 3 to see that $\Sigma_\infty \in \mathcal{J}_\infty^s$ also satisfies

$$\Sigma_\infty = S(t)\Sigma_\infty S^*(t) + \int_0^t S(t-s)(F - \Sigma_\infty G \Sigma_\infty) S^*(t-s) ds.$$

for any $t \in \mathbb{R}_+$. Taking the limit as $t \rightarrow \infty$ of the above equation results in

$$\begin{aligned}\Sigma_\infty &= \lim_{t \rightarrow \infty} \int_0^t S(t-s) (F - \Sigma_\infty G \Sigma_\infty) S^*(t-s) ds \\ &= - \int_0^\infty S(s) (F - \Sigma_\infty G \Sigma_\infty) S^*(s) ds,\end{aligned}$$

after a change of variables since we have assumed that $\|S(t)\|_{\mathcal{L}(H)} \leq M e^{-\alpha t}$. \square

It should be noted that the conditions given in Proposition 4 imply that the solution to (15) is unique. This is a direct consequence of Theorem 1. With this, we have established the well-posedness of the Bochner integral form of the time-dependent and stationary operator-valued Riccati equations. We proceed by discussing the approximation of these equations in the following subsection.

2.3. An Abstract Approximation of Operator-Valued Riccati Equations. This subsection is aimed at justifying the approach taken in the error analysis for the approximation of the Bochner integral form of the operator-valued Riccati equations. It is our goal here to demonstrate that many operator approximation methods can fit into the abstract theory that we present in this work.

2.3.1. Time-Dependent Abstract Approximation. Recall that the time-dependent problem of interest is to seek a solution $\Sigma(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ that satisfies

$$\Sigma(t) = S(t) \Sigma_0 S^*(t) + \int_0^t S(t-s) (F - \Sigma G \Sigma) (s) S^*(t-s) ds,$$

where $\Sigma_0 = \mathcal{J}_\infty^s$, $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$, and $S(t) \in \mathcal{L}(H)$ is a C_0 -semigroup. The approximate problem we are interested in analyzing involves seeking a solution $\Sigma_n(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ that satisfies

$$(18) \quad \Sigma_n(t) = S_n(t) \Sigma_0 S_n^*(t) + \int_0^t S_n(t-s) (F - \Sigma_n G \Sigma_n) (s) S_n^*(t-s) ds,$$

where we have approximated $S(t) \in \mathcal{L}(H)$ with $S_n(t) \in \mathcal{L}(H)$. Since $S_n(t)$ is, in general, not a semigroup on all of H , we cannot directly apply Proposition 3 to demonstrate that (18) has a unique solution. However, we recall that $S_n(t) := \iota_H \widehat{S}_n(t) \pi_n$, where $\widehat{S}_n(t) \in \mathcal{L}(H_n)$ is a semigroup on H_n . We prove that (18) is well-posed in the following by showing that its solution is the unique extension of the solution of the approximate operator-valued Riccati equation posed on H_n .

Proposition 5. *Let $H_n \subset H$ be a separable Hilbert space that represents the space of functions approximating the elements of H and let $S_n(t) \in \mathcal{L}(H)$ be the time-dependent approximation to the C_0 -semigroup $S(t) \in \mathcal{L}(H)$, where $S_n(t) = \iota_H \widehat{S}_n(t) \pi_n$ with $\widehat{S}_n(t) \in \mathcal{L}(H_n)$ being the restriction of $S_n(t)$ to $\mathcal{L}(H_n)$ (see §2.1.2). Then there exists a unique solution $\Sigma_n(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ that satisfies (18) with $I := [0, \tau]$ and $\tau \in \mathbb{R}_+$.*

Proof. We begin the analysis by taking (18) and applying the projection operator π_n as follows

$$(19) \quad \pi_n \Sigma_n(t) \pi_n = \pi_n S_n(t) \Sigma_0 S_n^*(t) \pi_n + \int_0^t \pi_n S_n(t-s) (F - \Sigma_n G \Sigma_n) (s) S_n^*(t-s) \pi_n ds$$

on H . Placement of π_n in the integral is achieved by observing that it is not a time-dependent operator. From here, we observe that

$$\pi_n S_n(t) \Sigma_0 S_n^*(t) \pi_n = \pi_n \widehat{S}_n(t) (\pi_n \Sigma_0 \iota_H \pi_n) \widehat{S}_n^*(t) \pi_n$$

for $t \in I$, after seeing that the range of $\widehat{S}_n^*(t)$ is H_n , which implies that $\iota_H \widehat{S}_n^*(t) = \iota_H \pi_n \widehat{S}_n^*(t)$. With this, we have that

$$(20) \quad \pi_n S_n(t) \Sigma_0 S_n^*(t) \pi_n = \widehat{S}_n(t) \widehat{\Sigma}_{0,n} \widehat{S}_n^*(t)$$

for $t \in I$ on H_n , where we have defined $\widehat{\Sigma}_{0,n} := \pi_n \Sigma_0 \pi_n$. Following a similar strategy, we have that

$$(21) \quad \int_0^t \pi_n S_n(t-s) F(s) S_n^*(t-s) \pi_n ds = \int_0^t \widehat{S}_n(t-s) \widehat{F}_n(s) \widehat{S}_n^*(t-s) ds,$$

on H_n with $\widehat{F}_n(s) := \pi_n F(s) \pi_n$. Finally, we see that

$$(22) \quad \int_0^t \pi_n S_n(t-s) (\Sigma_n G \Sigma_n)(s) S_n^*(t-s) \pi_n ds = \int_0^t \widehat{S}_n(t-s) \left(\widehat{\Sigma}_n \widehat{G}_n \widehat{\Sigma}_n \right)(s) \widehat{S}_n^*(t-s) ds,$$

where $\widehat{\Sigma}_n(t) := \pi_n \Sigma_n(t) \pi_n$, for $t \in I$ on H_n after applying the above argument and seeing that the range and domain of Σ_n is H_n after inspecting (18) (The range is injected in to H from H_n and the domain is projected from H onto H_n from the definition of $S_n(t) \in \mathcal{L}(H)$). With (20), (21), and (22) we see that (18) becomes the following equation when restricting the domain and range of the equation to H_n

$$(23) \quad \widehat{\Sigma}_n(t) = \widehat{S}_n(t) \widehat{\Sigma}_0 \widehat{S}_n^*(t) + \int_0^t \widehat{S}_n(t-s) \left(\widehat{F}_n - \widehat{\Sigma}_n \widehat{G}_n \widehat{\Sigma}_n \right) S_n^*(t-s) ds.$$

Since $\widehat{S}_n(t) \in \mathcal{L}(H_n)$, $\widehat{\Sigma}_0 \in \mathcal{J}_\infty^s(H_n)$, and $\widehat{F}_n(\cdot), \widehat{G}_n(\cdot) \in \mathcal{C}(I, \mathcal{J}_\infty^s(H_n))$ with $\mathcal{J}_\infty^s(H_n)$ denoting the space of symmetric compact operators in H_n (compactness is preserved since π_n is a continuous operator), Proposition 1 implies that there exists a unique $\widehat{\Sigma}_n(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s(H_n))$ that satisfies (23).

Extending the domain and range of (23) to all of H then allows us to see that (23) becomes

$$\widetilde{\Sigma}_n(t) = S_n(t) \Sigma_0 S_n^*(t) + \int_0^t S_n(t-s) \left(F - \widetilde{\Sigma}_n G \widetilde{\Sigma}_n \right)(s) S_n^*(t-s) ds,$$

for $t \in I$, where $\widetilde{\Sigma}_n(t) := \iota_H \widehat{\Sigma}_n(t) \pi_n$. This equation is simply (18), and hence $\Sigma_n(\cdot) = \widetilde{\Sigma}_n(\cdot)$. This establishes the existence of a solution to (18). Uniqueness then follows from the definition of ι_H and π_n , and the uniqueness of the solution $\widehat{\Sigma}_n$ that satisfies (23). \square

The above result then implies the solution to (18) also satisfies the following equation

$$(24) \quad \begin{cases} \frac{d}{dt} (\psi, \Sigma_n(t) \phi)_H = (\psi, A_n \Sigma_n(t) \phi)_H + (\psi, \Sigma_n(t) A_n^* \phi)_H - (\psi, (\Sigma_n G \Sigma_n)(t) \phi)_H + (\psi, F(t) \phi)_H \\ (\psi, \Sigma_n(0) \phi)_H = (\psi, \Sigma_0 \phi)_H, \end{cases}$$

for all $t \in I$ and for all $\phi, \psi \in \mathcal{D}(A_n^*)$, where $A_n \in \mathcal{D}(A_n) \rightarrow H_n$ is again the generator of the approximate semigroup $\widehat{S}_n(t) \in \mathcal{L}(H)$, with $S_n(t) := \iota_H \widehat{S}_n(t) \pi_n$.

2.3.2. Time-Independent Abstract Approximation. Similarly, recall that the time-independent problem of interest is to seek a $\Sigma_\infty \in \mathcal{J}_\infty^s$ that satisfies

$$\Sigma_\infty = \int_0^\infty S(s) (\Sigma_\infty G \Sigma_\infty - F) S^*(s) ds,$$

where $F, G \in \mathcal{J}_\infty^s$, and $S(t) \in \mathcal{L}(H)$ is a C_0 -semigroup. The correspondent approximation is to seek a solution $\Sigma_{\infty, n} \in \mathcal{J}_\infty^s$ that satisfies

$$(25) \quad \Sigma_{\infty, n} = \int_0^\infty S_n(s) (\Sigma_{\infty, n} G \Sigma_{\infty, n} - F) S_n^*(s) ds,$$

where $S_n(t) \in \mathcal{L}(H)$ again approximates $S(t) \in \mathcal{L}(H)$. The well-posedness of (25) follows from a similar argument used in Proposition 5. Likewise, the differential form of the approximation is given by the following

$$(26) \quad (\psi, A_n \Sigma_{\infty, n} \phi)_H + (\psi, \Sigma_{\infty, n} A_n^* \phi)_H - (\psi, \Sigma_{\infty, n} G \Sigma_{\infty, n} \phi)_H + (\psi, F \phi)_H = 0 \quad \forall \phi, \psi \in \mathcal{D}(A_n^*),$$

where $A_n : \mathcal{D}(A_n) \rightarrow H_n$ is again the generator to $\widehat{S}_n(t) \in \mathcal{L}(H)$ with $S_n(t) := \iota_n S(t) \pi_n$.

2.3.3. Galerkin Approximation. The Galerkin approximation framework is likely the most utilized framework for approximating the solution to infinite dimensional equations with the solution to a finite dimensional problem. Its widespread popularity is due to its strong theoretical foundation and its flexibility in regards to choosing an approximating function space. Examples of popular Galerkin approximation methods are Finite Element methods [16, 40], Discontinuous Galerkin methods [18], Isogeometric Analysis [20], Spectral Galerkin methods [7], and Fourier Transform methods [42]. Here, we provide a brief overview of how the Galerkin approximation can be applied to the problems studied in this work.

The Galerkin approximation of a semigroup generator $A : \mathcal{D}(A) \rightarrow H$ is given by

$$A_n^g := \pi_n^g A \pi_n^g,$$

where $\pi_n^g : H \rightarrow H_n^g$ is the orthogonal projection operator mapping H into H_n^g . The subset $H_n^g \subset H$ is chosen so that

$$(27) \quad (\psi, \iota_H \pi_n^g A \pi_n^g \phi)_H < \infty \quad \forall \phi, \psi \in H,$$

where $\iota_H : H_n^g \rightarrow H$ is again the canonical injection operator. The Galerkin approximation of (7) is most commonly given in the weak form by

$$(28) \quad \begin{cases} \frac{d}{dt} (\psi_n^g, \Sigma_n^g(t) \phi_n^g)_H = (\psi_n^g, A_n^g \Sigma_n^g(t) \phi_n^g)_H + (\psi_n^g, \Sigma_n^g(t) (A_n^g)^* \phi_n^g)_H - (\psi_n^g, (\Sigma_n^g G \Sigma_n^g)(t) \phi_n^g)_H + (\psi_n^g, F(t) \phi_n^g)_H \\ (\psi_n^g, \Sigma_n(0) \phi_n^g)_H = (\psi_n^g, \Sigma_0 \phi_n^g)_H, \end{cases}$$

for all $\phi_n^g, \psi_n^g \in H_n^g$ and $t \in I$. It is then clear that (28) is a variant of the class of problems given by (24), where $\mathcal{D}(A_n^g) = H_n^g$.

Since (28) is posed on a finite-dimensional topology (of dimension n), we can represent this problem by seeking a $\widehat{\Sigma}_n^g(\cdot) \in \mathcal{C}(I; \mathcal{L}(H_n))$ that satisfies the following equation

$$(29) \quad \begin{cases} \frac{d}{dt} \widehat{\Sigma}_n^g(t) = A_n^g \widehat{\Sigma}_n^g(t) + \widehat{\Sigma}_n^g(t) (A_n^g)^* - (\widehat{\Sigma}_n^g G_n^g \widehat{\Sigma}_n^g)(t) + F_n^g(t) \\ \widehat{\Sigma}_n^g(0) = \Sigma_{0,n}^g, \end{cases}$$

where $\Sigma_{0,n}^g := \pi_n^g \Sigma_0 \pi_n^g$, $F_n^g(t) := \pi_n^g F(t) \pi_n^g$, and $G_n^g(t) := \pi_n^g G(t) \pi_n^g$ are the Galerkin approximations to $\Sigma_0 \in \mathcal{J}_\infty^s$ and $F(t), G(t) \in \mathcal{J}_\infty^s$ respectively. This becomes apparent after recalling (27), and seeing that the domain and range of $\Sigma_n^g(t)$ must be H_n^g in order to satisfy (28). Integrating (29) then gives us the following integral equation posed on H_n^g

$$(30) \quad \widehat{\Sigma}_n^g(t) = \widehat{\Sigma}_n^g(t) \Sigma_{0,n}^g (\widehat{\Sigma}_n^g)^*(t) + \int_0^t \widehat{\Sigma}_n^g(t-s) \left(F_n^g - \widehat{\Sigma}_n^g G_n^g \widehat{\Sigma}_n^g \right) (s) (\widehat{\Sigma}_n^g)^*(t-s) ds.$$

Let us now define $\Sigma_n^g(t) := \iota_H \widehat{\Sigma}_n^g(t) \pi_n^g$ and $S_n^g(t) := \iota_H \widehat{\Sigma}_n^g(t) \pi_n^g$. It then follows from inspection, by injecting the range of (30) into H , that $\Sigma_n^g(t) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ satisfies

$$(31) \quad \Sigma_n^g(t) = S_n^g(t) \Sigma_0 (S_n^g)^*(t) + \int_0^t S_n^g(t-s) (F - \Sigma_n G \Sigma_n) (s) (S_n^g)^*(t-s) ds.$$

It then becomes clear that (31) satisfies the abstract form of the approximate problem given in (25). Therefore, the Galerkin approximation of the time-dependent approximation of the operator-valued Riccati equation can be analyzed within the context of the abstract theory presented in this work. A similar argument applies to the Galerkin approximation variant of the time-independent problem given in (28).

2.3.4. Asymptotic Approximation. Oftentimes, the generator $A : \mathcal{D}(A) \rightarrow H$ is parameterized by a presumably small parameter $\epsilon \in \mathbb{R}_+$. The operator perturbation theory [32] tells us that this operator can be represented in the following asymptotic series

$$A = \sum_{j=0}^{\infty} \epsilon^j A_j,$$

where each A_j must necessarily map $\mathcal{D}(A)$ into H . Truncating the sum to $n \in \mathbb{N}_0$ terms gives us the asymptotic approximation

$$A_n^a := \sum_{j=0}^n \epsilon^j A_j.$$

Let now $S(t) \in \mathcal{L}(H)$ and $S_n^a(t) \in \mathcal{L}(H)$ be the semigroups generated by A and A_n^a respectively. Then, the conditions laid out in the semigroup approximation theory presented in [27, Chapter 1, §7] must be satisfied in order for $S_n^a(t) \rightarrow S(t)$ as $n \rightarrow \infty$. If convergence can be established in the limit, then as an approximation, we can simply replace $S(t) \in \mathcal{L}(H)$ with $S_n^a(t) \in \mathcal{L}(H)$ in (7) without any issue because the domain and range of $S(t)$ and $S_n^a(t)$ coincide. This describes the process of the asymptotic approximation of operator-valued Riccati equation. As an example, The application of asymptotic operator approximation can be found in applications involving the Born first order approximation for wave scattering in RADAR and quantum mechanical systems [15, 28].

2.4. Application Problems. This subsection will describe how the discussion presented in the preceding discussion may be applied to many important problems of practical interest. This framework may be applied to the Kálmán filter, Linear Quadratic Regulator, and Two-Player Differential Games, among other potential applications not described here (e.g. H^∞ optimal control). In the following discussion we will first pose the application problem, highlight its use of a Riccati equation, and finally demonstrate how the Riccati equation fits into the abstract framework described in this section. For each of the application problems, we will present the associated time-dependent Riccati equation in the weak form and will defer the derivation of the steady-state form of these equations to the reader. The reader is reminded that the differential and Bochner integral form of the operator-valued Riccati equation are shown to be equivalent in Proposition 3.

2.4.1. Kálmán Filter. The Kálmán filter [31] has become the predominant method used in the field of state estimation. It has been so successful that state estimation practitioners have made many attempts to extend its application to estimating the state of nonlinear systems [38]. Here, we describe the Kálmán filter for linear-quadratic systems.

First, let us define H, X , and Y as separable Hilbert spaces associated with the state, noise, and sensor output respectively. Then the cost functional is defined as

$$\mathcal{J}(\hat{z}) := \mathbb{E} \left[\int_0^\tau \|z(t; \eta(t)) - \hat{z}(t; \eta(t), \nu(t))\|_H^2 dt \right],$$

where $\mathbb{E}(\cdot)$ denotes the expectation operator with respect to the Gaussian measures associated with the random processes $\eta(t) \in X$ and $\nu(t) \in Y$ representing the process and measurement noise with covariance operators $R_\eta \in \mathcal{L}(X)$ and $R_\nu \in \mathcal{L}(Y)$ respectively, and $z(\cdot), \hat{z}(\cdot) \in L^2([0, \tau], H)$ is the solution of the following set of stochastic differential equations (stated here with an abuse of notation)

$$\begin{cases} \frac{dz}{dt} = Az(t) + B\eta(t), & z(0) = z_0 \\ y(t) = Cz(t) + \nu(t) \\ \frac{d\hat{z}}{dt} = A\hat{z}(t) + L(y(t) - C\hat{z}), & \hat{z}(0) = \hat{z}_0 \end{cases}$$

for all $t \in [0, \tau]$, where $A : \mathcal{D}(A) \rightarrow H$ is a generator of a C_0 -semigroup, $B : X \rightarrow H$ is the state noise operator, $C : H \rightarrow Y$ is the sensing operator. The functional gain $L : Y \rightarrow H$ updates the state estimate $\hat{z}(t)$ based on the difference between the sensor data $y(t)$ and predicted sensor output $C\hat{z}(t)$ for almost all $t \in [0, \tau]$. This operator is given by

$$L := \Sigma(t)R_\nu^{-1}C,$$

where $\Sigma(t) \in \mathcal{L}(H)$ is the covariance operator given by the solution of the following operator-valued Riccati equation

$$\begin{cases} \frac{d}{dt} (\psi, \Sigma(t)\phi)_H = (\psi, A\Sigma(t)\phi)_H + (\psi, \Sigma(t)A^*\phi)_H - (\psi, (\Sigma C^* R_\nu^{-1} C \Sigma)(t)\phi)_H + (\psi, (BR_\eta B)(t)\phi)_H \\ (\psi, \Sigma(0)\phi)_H = (\psi, \Sigma_0\phi)_H \end{cases}$$

for all $t \in [0, \tau]$ and for all $\phi, \psi \in \mathcal{D}(A)$. It then becomes clear that the above equation is a variation of (9) after setting $F := BR_\eta B^*$ and $G := C^* R_\nu^{-1} C$.

2.4.2. Linear Quadratic Regulator. The linear quadratic regulator (LQR) [39] is a fundamental closed-loop control method that forces the state of a linear system to the desired terminal state. Like the Kálmán filter, the LQR has been used extensively in the control of many linear systems. It has also been applied to nonlinear systems, where the state system has been linearized about a desired set point [41, 9, 36].

Let H and U be separable Hilbert spaces associated with the state and control respectively. The cost function to be minimized is a quadratic functional given by

$$\mathcal{J}(u) := (z(\tau), \Pi_\tau z(\tau))_H + \int_0^\tau \|C(t)z\|_Y^2 + (u(t), Ru(t))_U dt,$$

where $\Pi_\tau \in \mathcal{J}_\infty^s$, $C(t) \in \mathcal{L}(H, Y)$ and $R \in \mathcal{L}(U)$ are weighting operators whose values can be tuned to adjust the importance of minimizing the terminal state, running cost, and the control effort respectively in the cost

functional. The system to be controlled is given by

$$\begin{cases} \frac{d}{dt}z = \mathcal{A}z(t) + B(t)u(t) \\ z(0) = z_0 \end{cases}$$

for all $t \in [0, \tau]$, where $B(t) : U \rightarrow H$ is the actuation operator. The optimal control, given as a function of $z(t)$, is the following

$$u_{opt}(t) = -\mathcal{K}z(t),$$

where $\mathcal{K} : H \rightarrow U$ is the functional gain given by

$$\mathcal{K} = R^{-1}(t)B(t)^*\Pi(t)z(t),$$

and $\Pi(t) \in \mathcal{L}^s$ is the solution of the following operator-valued Riccati equation

$$\begin{aligned} \frac{d}{dt}(\psi, \Pi(t)\phi)_H &= -(\psi, \mathcal{A}^*\Pi(t)\phi)_H - (\psi, \Pi(t)\mathcal{A}\phi)_H + (\psi, (\Pi BR^{-1}B^*\Pi)(t)\phi)_H - (\psi, (C^*C)(t)\phi)_H \\ (\psi, \Pi(\tau)\phi)_H &= (\psi, \Pi_\tau\phi)_H \end{aligned}$$

for all $t \in [0, \tau]$ and for every $\phi, \psi \in \mathcal{D}(A)$. A change of variables $t \mapsto s$, where $s = \tau - t$ transforms the terminal value problem into the initial value problem that we seek in the abstract description of the operator-valued Riccati equation. Taking $A := \mathcal{A}^*$, $F(t) := C^*C(t)$, and $G(t) := (BR^{-1}B^*)(t)$ then allows us to see that the Riccati equation associated with LQR control can be analyzed within the framework described in this work.

2.4.3. Linear Quadratic Two-Player Differential Games. In a linear quadratic two-player differential game [8], there exists two sets of strategies $u_1(t) \in U_1$ and $u_2(t) \in U_2$, associated with player 1 and player 2 respectively, that aims to find the saddle-point of the following cost functional

$$\mathcal{J}(u_1, u_2) := (z(t), P_\tau z(t))_H + \int_0^\tau (z(t), Qz(t))_H + \|u_1\|_{U_1}^2 - \|u_2\|_{U_2}^2 dt.$$

The dynamical system affected by these competing strategies is given by

$$\begin{cases} \frac{d}{dt}z = \mathcal{A}z(t) + B_1u_1(t) + B_2u_2(t) \\ z(0) = z_0 \end{cases}$$

The optimal strategy for each player is then given by

$$u_{1,opt}(t) = -B_1P(t)z(t) \quad u_{2,opt}(t) = B_2^*P(t)z(t),$$

where $Q(t) \in \mathcal{L}(H)$ is the solution of the following operator-valued Riccati equation:

$$\begin{aligned} \frac{d}{dt}(\psi, P(t)\phi)_H &= -(\psi, \mathcal{A}^*P(t)\phi)_H - (\psi, P(t)\mathcal{A}\phi)_H + (\psi, (PRP(t))\phi)_H - (\psi, P\phi)_H \\ (\psi, P(\tau)\phi)_H &= (\psi, P_\tau\phi)_H \end{aligned}$$

for every $t \in [0, \tau]$ and $\phi, \psi \in \mathcal{D}(A)$, where $R = B_1B_1^* - B_2B_2^*$. Like in the LQR Riccati equation presented in the previous example, our desired initial-value problem is obtained through a variable transformation. Of course, setting $A := \mathcal{A}^*$, $G := R$, and $F := Q$ allows us to see that the Riccati equation associated with linear quadratic two-player games fits within the abstract framework of this work.

2.5. The Brezzi-Rappaz-Raviart Theorem. The Brezzi-Rappaz-Raviart (BRR) Theorem [26, Part IV, Theorem 3.3] is an important result in numerical analysis that provides a framework for deriving error bounds for the approximation of certain classes of nonlinear equations. We demonstrate in the following sections that approximations to both the time-dependent and time-independent operator-valued Riccati equation can be analyzed within this framework. A brief statement of the problem setting and the BRR theorem itself is presented in the following paragraph.

Consider the fixed point problem

$$(32) \quad u = T\mathcal{G}(\lambda, u),$$

where $u \in \mathcal{X}$, $\lambda \in \Lambda$ belongs to a compact interval in \mathbb{R}_+ , $T \in \mathcal{L}(\mathcal{Y}; \mathcal{X})$ is a linear operator, and $\mathcal{G} : \Lambda \times \mathcal{X} \rightarrow \mathcal{Y}$ is a C^2 smooth mapping. Let us introduce $T_n \in \mathcal{L}(\mathcal{Y}; \mathcal{X})$ as an operator approximation to $T \in \mathcal{L}(\mathcal{Y}; \mathcal{X})$. We then have that (32) can be approximated by the following:

$$(33) \quad u_n = T_n \mathcal{G}(\lambda, u_n).$$

Now suppose that there exists another space $\mathcal{Z} \hookrightarrow \mathcal{Y}$ with continuous imbedding such that

$$(34) \quad D_u \mathcal{G}(\lambda, u) \in \mathcal{L}(\mathcal{X}; \mathcal{Z}) \quad \forall \lambda \in \Lambda \text{ and } u \in \mathcal{X}.$$

Then, additionally under the convergence assumptions

$$(35) \quad \lim_{n \rightarrow \infty} \|(T - T_n)g\|_{\mathcal{X}} = 0 \quad \forall g \in \mathcal{Y}$$

and

$$(36) \quad \lim_{n \rightarrow 0} \|T - T_n\|_{\mathcal{L}(\mathcal{X}; \mathcal{X})} = 0$$

the following holds.

Theorem 2 (Brezzi–Rappaz–Raviart). *Assume that conditions (34), (35), and (36) are satisfied. In addition, assume that $\mathcal{G} : \Lambda \times \mathcal{X} \rightarrow \mathcal{Y}$ is a C^2 operator, with $D^2 \mathcal{G}$ bounded on all subsets of $\Lambda \times \mathcal{X}$. Then, there exists a neighborhood \mathcal{O} of the origin in \mathcal{X} , and for $n \geq N$ large enough, a unique C^2 -function $\lambda \in \Lambda \rightarrow u_n(\lambda) \in \mathcal{X}$ such that*

$$(\lambda, u_n(\lambda); \lambda \in \Lambda) \text{ is a branch of nonsingular solutions of (33)}$$

and

$$u(\lambda) - u_n(\lambda) \in \mathcal{O} \quad \forall \lambda \in \Lambda.$$

Furthermore, there exists a constant $C \in \mathbb{R}_+$ independent of n and λ with:

$$\|u(\lambda) - u_n(\lambda)\|_{\mathcal{X}} \leq C \|(T - T_n)\mathcal{G}(\lambda, u(\lambda))\|_{\mathcal{X}} \quad \forall \lambda \in \Lambda.$$

In the next two sections, we utilize this theorem to demonstrate that the error estimate for the approximate solution to the operator-valued Riccati equation, in principle, only depends on the error induced by the approximate semigroup over the compact subspace characterized by the range of the coefficient operators in (7) and (15).

3. AN ERROR ESTIMATE FOR TIME-DEPENDENT APPROXIMATIONS

In this section, we will analyze the convergence of the approximate solutions of time-dependent operator-valued Riccati equations. Recall that on $t \in I$, where $I := [0, \tau]$, we have defined the Bochner integral form of the problem as

$$(37) \quad \Sigma(t) = S(t)\Sigma_0 S^*(t) + \int_0^t S(t-s)(F - \Sigma G \Sigma)(s) S^*(t-s) ds,$$

where $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ and $\Sigma_0 \in \mathcal{J}_\infty^s$ are self-adjoint and nonnegative operators on H . We wish to seek an approximation to (37) by solving the following approximating equation

$$(38) \quad \Sigma_n(t) = S_n(t)\Sigma_0 S_n^*(t) + \int_0^t S_n(t-s)(F - \Sigma_n G \Sigma_n)(s) S_n^*(t-s) ds,$$

where $S(t) \in \mathcal{L}(H)$ is approximated with $S_n(t) \in \mathcal{L}(H)$.

In the following analysis, we will derive a fundamental estimate that will allow for the derivation of optimal convergence rates of $\Sigma_n(t) \rightarrow \Sigma(t)$ in the \mathcal{J}_∞ topology. The convergence rate will depend principally on which compact subset K of H the coefficient operators $\Sigma_0, F(t)$, and $G(t)$ map to. *To make this point clear in the analysis, we will take $\Sigma_0, F(t), G(t) \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$.* The choice of the compact space K will remain abstract and will vary depending on the application problem.

The analysis presented in the remainder of this section seeks to prove that the equations (37) and (38) have the necessary nonlinear structure necessary to utilize the Brezzi–Rappaz–Raviart theorem (Theorem 2) so that we can bound the error of the approximate solution to the exact solution by the error associated

with the way the semigroup in (38) is approximated. To be more descriptive, we aim to prove that there exists a constant $C \in \mathbb{R}_+$ so that

$$\|\Sigma(\cdot) - \Sigma_n(\cdot)\|_{\mathcal{C}(I, \mathcal{J}_\infty^s)} \leq C \sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{L}(K, H)}.$$

The following analysis will begin with an inspection of the linear operator from which (37) and (38) are perturbations of. We then conclude our analysis by utilizing the derived properties of this operator to prove our desired result with the Brezzi-Rappaz-Raviart theorem (Theorem 2).

3.1. Time-Dependent Lyapunov Operator. Let us define $\Phi : \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$ as

$$(39) \quad \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} := S(t)XS^*(t) + \int_0^t S(t-s)Y(s)S^*(t-s)ds$$

where $X \in \mathcal{J}_\infty^s$ and $Y \in \mathcal{J}_\infty^s$.

Remark 3. We call $\Phi : \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$ the Lyapunov operator, since it is the solution operator for the time-dependent variant of the Lyapunov equation shown below

$$\begin{cases} \frac{dX}{dt} = AX + XA^* \\ X(0) = X_0. \end{cases}$$

This equation arises from the study of the stability of linear dynamical systems [5].

Let us now define $\mathcal{Q}(\cdot) : \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{L}(H, K) \times \mathcal{C}(I; \mathcal{L}(H, K))$ as

$$(40) \quad \mathcal{Q}(X(\cdot)) := \begin{bmatrix} \Sigma_0 \\ F(\cdot) - (XGX)(\cdot) \end{bmatrix},$$

where we again take $\Sigma_0 \in \mathcal{L}(H, K)$ and $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K))$. It is then clear that (37) can be written succinctly as

$$(41) \quad \Sigma(t) = \Phi[\mathcal{Q}(\Sigma(\cdot))].$$

We will verify the range of $\mathcal{Q}(\cdot)$ in the following.

Proposition 6. Let H be a separable Hilbert space, and K be a compact subset of H and $I := [0, \tau]$ be a compact time interval, where $\tau \in \mathbb{R}_+$. Then, if $\Sigma_0 \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$, and $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$, we have that $\mathcal{Q}(\cdot)$, as defined in (40), is a mapping from $\mathcal{C}(I; \mathcal{J}_\infty^s)$ into $\mathcal{L}(H, K) \cap \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$.

Proof. We only need to show that $(XGX)(\cdot)$ belongs to $\mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$ since $\Sigma_0 \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$ and $F(\cdot), G(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$, by definition. The result of this proposition follows immediately from a direct application of Corollary 1, and seeing that $(XGX)^*(t) = (X^*G^*X^*)(t) = (XGX)(t)$ on H for any $X \in \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$. \square

Similarly, we will define $\Phi_n : \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$, as the following approximation to the Lyapunov operator

$$(42) \quad \Phi_n \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} := S_n(t)XS_n^*(t) + \int_0^t S_n(t-s)Y(s)S_n^*(t-s)ds,$$

for all $X \in \mathcal{J}_\infty^s$ and $Y \in \mathcal{C}(I; \mathcal{J}_\infty^s)$. Likewise, (38) can be written succinctly as

$$(43) \quad \Sigma_n(t) = \Phi_n[\mathcal{Q}(\Sigma_n(\cdot))].$$

By now, it should be clear that the convergence of $\Sigma_n(\cdot) \rightarrow \Sigma(\cdot)$ will depend on the properties of the mappings $\Phi(\cdot)$, $\Phi_n(\cdot)$, and $\mathcal{Q}(\cdot)$. With this, we proceed to analyze the convergence of $\Phi_n \rightarrow \Phi$ as $n \rightarrow \infty$.

3.2. Convergence of the Time-Dependent Lyapunov Operator Approximation. We begin this section by establishing the linearity and continuity of $\Phi(\cdot)$ and $\Phi_n(\cdot)$ in the following.

Lemma 1. *Let H be a separable Hilbert space, and $S(t), S_n(t) \in \mathcal{L}(H)$ be C_0 -semigroups defined on a compact time interval $t \in I$, where $I := [0, \tau]$ and $\tau \in \mathbb{R}_+$. Then for all $X \in \mathcal{J}_\infty^s$ and $Y \in \mathcal{C}(I; \mathcal{J}_\infty^s)$, we have that $\Phi(\cdot)$ and $\Phi_n(\cdot)$ are bounded linear mappings from $\mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$. Furthermore, $\Phi(\cdot)$ and $\Phi_n(\cdot)$ are bounded linear mappings from $\mathcal{L}(H, K) \cap \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$.*

Proof. In this proof, we only prove the result for $\Phi(\cdot)$. It will become clear that the same sequence of steps can be repeated with instead $\Phi_n(\cdot)$ to establish its linearity and continuity.

From the definition of $\Phi(\cdot)$ (see (39)), it is easy to see that

$$\begin{aligned} \Phi \begin{bmatrix} X + \alpha C \\ Y(\cdot) + \alpha D(\cdot) \end{bmatrix} &= S(t)(X + \alpha C)S^*(t) + \int_0^t S(t-s)(Y + \alpha D)(s)S^*(t-s)ds \\ &= S(t)XS^*(t) + \int_0^t S(t-s)Y(s)S^*(t-s)ds \\ &\quad + \alpha \left(S(t)CS^*(t) + \int_0^t S(t-s)D(s)S^*(t-s)ds \right) \\ &= \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} + \alpha \Phi \begin{bmatrix} C \\ D(\cdot) \end{bmatrix}. \end{aligned}$$

for all $X, C \in \mathcal{J}_\infty^s$, $Y(\cdot), D(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$, and $\alpha \in \mathbb{R}$. Therefore, it is established that $\Phi : \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$ is a linear mapping, where the self-adjoint property of Φ is established by seeing that $S(t)XS^*(t)$ is self-adjoint on H for all $X \in \mathcal{J}_\infty^s$.

The boundedness properties of the Lyapunov operator is then established by seeing that

$$\begin{aligned} \left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty)} &\leq \sup_{t \in I} \left\{ \|S(t)XS^*(t)\|_{\mathcal{J}_\infty} + \int_0^t \|S(t-s)Y(s)S^*(t-s)\|_{\mathcal{J}_\infty} ds \right\} \\ &\leq M^2 e^{2\omega\tau} \left(\|X\|_{\mathcal{J}_\infty} + \int_0^\tau e^{-2\omega s} \|Y(s)\|_{\mathcal{J}_\infty} ds \right) \\ &\leq M^2 e^{2\omega\tau} \left(\|X\|_{\mathcal{J}_\infty} + \frac{1}{2\omega} (1 - e^{-2\omega\tau}) \|Y\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \right) \\ &\leq C_{M, \omega, \tau} \left(\|X\|_{\mathcal{J}_\infty} + \|Y\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \right), \end{aligned}$$

after applying (1). Hence, $\Phi : \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$ is a bounded operator on $\mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s)$. A continuation of the above series of inequalities yields

$$\left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty(H))} \leq C_{M, \omega, \tau} \left(\|X\|_{\mathcal{L}(H, K)} + \|Y(\cdot)\|_{\mathcal{C}(I; \mathcal{L}(H, K))} \right)$$

where we have used the fact that $\mathcal{L}(K, H) \subset \mathcal{L}(H)$. With this, we have also demonstrated that Φ is a bounded linear operator from $\mathcal{L}(H, K) \cap \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$ into $\mathcal{C}(I; \mathcal{J}_\infty^s)$.

Applying the same strategy, with instead the estimate (5), establishes the linearity and boundedness of Φ_n as a mapping from $\mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s)$ and $\mathcal{L}(H, K) \cap \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$ into $\mathcal{C}(I; \mathcal{J}_\infty^s)$. This concludes this proof. \square

Now that we have established that $\Phi(\cdot)$ and $\Phi_n(\cdot)$ are continuous linear operators, we can then begin to analyze the convergence of $\Phi_n(\cdot)$ to $\Phi(\cdot)$ as $n \rightarrow \infty$ in the \mathcal{J}_∞ norm. The analysis is presented in the proof of the following.

Lemma 2. *Let H be a separable Hilbert space and K be a compact subset of H . Additionally, let $S(t) \in \mathcal{L}(H)$ be a C_0 -semigroup and $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ be an approximating sequence of C_0 -semigroups on H_n so that*

$$\lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_H = 0 \quad \forall \phi \in H,$$

for all values in a bounded time interval $t \in I$, where $I := [0, \tau]$ with $\tau \in \mathbb{R}_+$. Furthermore, let $\Phi(\cdot), \Phi_n(\cdot) \in \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty^s)$ be defined as in (39) and (42) respectively. Then, we have that

$$(44) \quad \lim_{n \rightarrow \infty} \left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} - \Phi_n \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty^s)} = 0$$

for all non-negative self-adjoint operators $X \in \mathcal{J}_\infty^s$ and $Y \in \mathcal{C}(I; \mathcal{J}_\infty^s)$, and that there exists a constant $C_{M, \omega, \tau} \in \mathbb{R}_+$ such that

$$(45) \quad \left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} - \Phi_n \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty(H))} \leq C_{M, \omega, \tau} \sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{L}(K, H)} \left(\|X\|_{\mathcal{L}(H, K)} + \|Y(\cdot)\|_{\mathcal{C}(I; \mathcal{L}(H, K))} \right),$$

for all $X \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$ and $Y(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$.

Proof. Throughout this proof, we will denote $M_* := \sup \{M_n\}_{n=1}^\infty$ and $\omega_* := \sup \{\omega_n\}_{n=1}^\infty$. From the definition of $\Phi(\cdot)$ and $\Phi_n(\cdot)$, we see that

$$\begin{aligned} & \left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} - \Phi_n \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty^s)} \\ & \leq \sup_{t \in I} \left(\|S(t)X(S(t) - S_n(t))^*\|_{\mathcal{J}_\infty} + \|(S(t) - S_n(t))XS_n^*(t)\|_{\mathcal{J}_\infty} \right) \\ & \quad + \int_0^\tau \|S(t-s)Y(s)(S(t-s) - S_n(t-s))^*\|_{\mathcal{J}_\infty} ds \\ & \quad + \int_0^\tau \|(S(t-s) - S_n(t-s))Y(s)S_n^*(t-s)\|_{\mathcal{J}_\infty} ds \\ & \leq \sup_{t \in I} \left(\|(S(t) - S_n(t))X\|_{\mathcal{J}_\infty} \left(\|S(t)\|_{\mathcal{L}(H)} + \|S_n(t)\|_{\mathcal{L}(H)} \right) \right) \\ & \quad + \int_0^\tau \|(S(t-s) - S_n(t-s))Y(s)\|_{\mathcal{J}_\infty} \left(\|S(t-s)\|_{\mathcal{L}(H)} + \|S_n(t-s)\|_{\mathcal{L}(H)} \right) ds. \end{aligned}$$

The assertion (44) then follows by an application of Lemma 8 and seeing that the integral is defined on a bounded interval.

It then follows by continuing the previous sequence of inequalities that

$$\begin{aligned} & \left\| \Phi \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} - \Phi_n \begin{bmatrix} X \\ Y(\cdot) \end{bmatrix} \right\|_{\mathcal{C}(I; \mathcal{J}_\infty^s)} \\ & \leq 2M_* e^{\omega_* \tau} \left(\sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{C}(I; \mathcal{L}(K, H))} \|X\|_{\mathcal{L}(H, K)} + \int_0^\tau e^{-\omega_* s} \|(S(t-s) - S_n(t-s))Y(s)\|_{\mathcal{J}_\infty} ds \right) \\ & \leq 2M_* e^{\omega_* \tau} \sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{C}(I; \mathcal{L}(K, H))} \left(\|X\|_{\mathcal{L}(H, K)} + \frac{1}{\omega_*} (1 - e^{-\omega_* \tau}) \|Y(\cdot)\|_{\mathcal{C}(I; \mathcal{L}(H, K))} \right), \end{aligned}$$

thus proving (45). \square

The well-posedness and the convergence of approximate Lyapunov operators, in pointwise and uniform sense, to the exact Lyapunov operator was established in the results presented in this subsection. In the final part of this section, we will apply Theorem 2 to determine that the error of the approximate solution of the operator-valued Riccati equation is bounded by the semigroup approximation error.

3.3. Approximation Error. Throughout this subsection, we will denote our function spaces of interest in the following manner

$$\mathcal{X} := \mathcal{C}(I; \mathcal{J}_\infty^s) \quad \mathcal{Y} := \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{J}_\infty^s) \quad \mathcal{Z} := \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s \times \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$$

to make the application of Theorem 2 easier to visualize. We note that $\mathcal{Z} \subset \mathcal{Y}$ is a continuous embedding by recalling the definition of these spaces.

We begin by seeing again that (37) and (38) can be written in a fixed-point form as

$$\Sigma(\cdot) = \Phi[\mathcal{Q}(\Sigma(\cdot))] \quad \text{and} \quad \Sigma_n(\cdot) = \Phi_n[\mathcal{Q}(\Sigma_n(\cdot))]$$

respectively. The linearity and boundedness of $\Phi(\cdot), \Phi_n(\cdot) \in \mathcal{L}(\mathcal{Y}, \mathcal{X})$ was established in Lemma 1. It is then easy to see from the definition of $\mathcal{Q}(\cdot) : \mathcal{X} \rightarrow \mathcal{Y}$ that it is infinitely Fréchet with respect to $X \in \mathcal{X}$. The first Gâteaux derivative of $\mathcal{Q}(\cdot)$ with respect to X is given explicitly as

$$(46) \quad (D_X \mathcal{Q}(X))T = \left[\begin{array}{c} 0 \\ (TGX)(\cdot) + (XGT)(\cdot) \end{array} \right],$$

for any test operator $T \in \mathcal{X}$. Since $G \in \mathcal{C}(I; \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s)$ and that 0 is an element in every space, we can see that $D_X \mathcal{Q} \in \mathcal{L}(\mathcal{X}, \mathcal{Z})$ as a result of Lemma 7. Finally, we restate the pointwise and uniform convergence result that we have derived in Lemma 2 in our new notation below, i.e.

$$\lim_{n \rightarrow \infty} \|\Phi(T) - \Phi_n(T)\|_{\mathcal{X}} = 0 \quad \forall T \in \mathcal{Y} \quad \text{and} \quad \lim_{n \rightarrow \infty} \|\Phi - \Phi_n\|_{\mathcal{L}(\mathcal{Z}, \mathcal{X})} = 0.$$

A direct comparison of the above observations against the conditions stated in §2.5 allow us to apply the Brezzi-Rappaz-Raviart theorem (Theorem 2) to see that there exists a constant $C \in \mathbb{R}_+$ such that

$$\|\Sigma(\cdot) - \Sigma_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \leq C \|\Phi[\mathcal{Q}(\Sigma(\cdot))] - \Phi_n[\mathcal{Q}(\Sigma(\cdot))]\|_{\mathcal{C}(I; \mathcal{J}_\infty)},$$

after recalling that $\mathcal{X} := \mathcal{C}(I; \mathcal{J}_\infty^s)$. Bounding this inequality with (45) yields the first main result of this work.

Theorem 3. *Let H be a separable Hilbert space and K be a compact subset of H . Additionally, let $S(t) \in \mathcal{L}(H)$ be a C_0 -semigroup and $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ be an approximating sequence of C_0 -semigroups on H_n so that*

$$\lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_H = 0 \quad \forall \phi \in H,$$

for all values in a bounded time interval $t \in I$, where $I := [0, \tau]$ with $\tau \in \mathbb{R}_+$. Furthermore, let $\Phi(\cdot), \Phi_n(\cdot) \in \mathcal{J}_\infty \times \mathcal{C}(I; \mathcal{J}_\infty) \rightarrow \mathcal{C}(I; \mathcal{J}_\infty)$ be defined as in (39) and (42) respectively. And finally, let $\mathcal{Q}(\cdot)$ be defined as in (40). Then, we have that there exists a constant $\beta_{M, \omega, \tau} \in \mathbb{R}_+$ so that

$$\|\Sigma(\cdot) - \Sigma_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \leq \beta_{M, \omega, \tau} \sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{L}(K, H)} \|\mathcal{Q}(\Sigma(\cdot))\|_{\mathcal{L}(H, K) \times \mathcal{C}(I; \mathcal{L}(H, K))},$$

where $\Sigma(\cdot), \Sigma_n(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ are the solutions of the operator-valued Riccati equation (37) and its approximation (38) respectively.

Remark 4. *In practice, the above result needs to be supplemented with additional analysis to resolve the time approximation error associated with time-stepping techniques. This error can be accounted for by simply utilizing the Minkowski inequality and applying known approximation results for time-stepping, i.e.,*

$$(47) \quad \|\Sigma(\cdot) - \Sigma_{n,k}(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \leq \|\Sigma(\cdot) - \Sigma_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} + \|\Sigma_n(\cdot) - \Sigma_{n,k}(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)},$$

where we have introduced $\Sigma_{n,k}(\cdot) \in \mathcal{C}(I; \mathcal{J}_\infty^s)$ as the solution approximation where both space and time-approximation has been applied. The error between $\Sigma_n(\cdot)$ and $\Sigma_{n,k}(\cdot)$ can then be bounded with existing results, under sufficient smoothness of Σ with respect to $t \in I$ (see [37, Chapter 11]).

With this, we have established an abstract error estimate for the solution of an approximation to time-dependent operator-valued Riccati equations. This estimate shows that the error bound on the approximate solution to time-independent operator Riccati equations is a function of the error of the semigroup approximation used in the approximate equation. The implication of this result is that many previous results in the approximation of time-dependent processes can be applied in deriving the error bound of the approximate solution of the Riccati equation in a control and/or estimation system in question. We will qualify this claim in §5. In the next section, we demonstrate in Theorem 4 that this observation can be applied to the time-independent variant of operator-valued Riccati equations.

4. AN ERROR ESTIMATE FOR TIME-INDEPENDENT APPROXIMATIONS

In this section, we will continue our analysis by deriving an abstract error estimate for approximate solutions to the time-dependent operator Riccati equation. Most of the analysis presented in this section is analogous to what we have already presented in the previous section. We begin by recalling again that the steady-state form of the operator Riccati equation is given as

$$(48) \quad \Sigma_\infty = \int_0^\infty S(s) (\Sigma_\infty G \Sigma_\infty - F) S^*(s) ds,$$

where $S(t) \in \mathcal{L}(H)$ is an exponentially stable semigroup satisfying $\|S(t)\|_{\mathcal{L}(H)} \leq M e^{-\alpha t}$, $F, G \in \mathcal{J}_\infty^s$ are compact, non-negative, and self-adjoint operators on H . We will again make the range of F and G explicit in this analysis by indicating that $F, G \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$, where $K \subset H$ is a compact subset. For reference, it was demonstrated in Lemma 4 that (48) is a well-posed problem.

The corresponding approximation to (48) is given by

$$(49) \quad \Sigma_{\infty, n} = \int_0^\infty S_n(s) (\Sigma_{\infty, n} G \Sigma_{\infty, n} - F) S_n^*(s) ds,$$

where $S_n(t) \in \mathcal{L}(H)$ is an approximation to $S(t) \in \mathcal{L}(H)$ satisfying $\|S_n(t)\|_{\mathcal{L}(H)} \leq M_n e^{-\alpha_n t}$. The analysis presented below implies that the semigroup approximation $S_n(t) \in \mathcal{L}(H)$ must satisfy the known preservation of exponential stability (POES) property in order for there to exist a bounded approximate solution $\Sigma_{\infty, n} \in \mathcal{J}_\infty^s$ to (49) [4].

The analysis presented in this section will follow the same structure as the analysis presented in Section 3. It is our goal to attempt to present our analysis in this section succinctly since its underlying logic is similar to (and simpler than) what we have presented in the previous section. To that end, we will first define the steady-state Lyapunov operator and its approximation and show that they are linear and bounded operators on \mathcal{J}_∞^s . Then, we move to demonstrate that the approximate Lyapunov operator converges to the exact Lyapunov operator in the pointwise and uniform sense on compact subsets. And finally, we apply the Brezzi-Rappaz-Raviart theorem (Theorem 2) to derive the main result of this section.

4.1. Time-Independent Lyapunov Operator. Let us define $\Phi_\infty(\cdot) : \mathcal{J}_\infty^s \rightarrow \mathcal{J}_\infty^s$ as

$$(50) \quad \Phi_\infty(X) := \int_0^\infty S(s) X S^*(s) ds$$

for all $X \in \mathcal{J}_\infty^s$. We call this operator the steady-state Lyapunov operator. Additionally, let us define $\mathcal{Q}_\infty^s : \mathcal{J}_\infty^s \rightarrow \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$ as

$$(51) \quad \mathcal{Q}_\infty(X) := X G X - F,$$

where $F, G \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$. It is then clear that we can represent (48) by

$$(52) \quad \Sigma_\infty = \Phi_\infty[\mathcal{Q}_\infty(\Sigma_\infty)].$$

This representation indicates that Theorem 2 is applicable to (48). We verify the range of $\mathcal{Q}_\infty : \mathcal{J}_\infty^s \rightarrow \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$ in the following.

Proposition 7. *Let H be a separable Hilbert space and K be a compact subset of H . If $F, G \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$, then $\mathcal{Q}_\infty(\cdot)$ is a mapping from \mathcal{J}_∞^s to $\mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$.*

Proof. We need to only show that $X G X \in \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s$ for any $X \in \mathcal{J}_\infty^s$. This is easily seen by applying Lemma 7 and seeing that $(X G X)^* = X^* G^* X^* = X G X$ by definition. \square

The approximation of interest to the steady-state Lyapunov operator given in (50) is defined as

$$(53) \quad \Phi_{\infty, n}(X) := \int_0^\infty S_n(s) X S_n^*(s) ds.$$

Similarly, the approximate steady-state operator Riccati equation (49) can be written as

$$(54) \quad \Sigma_{\infty, n} = \Phi_{\infty, n}[\mathcal{Q}_\infty(\Sigma_{\infty, n})].$$

We now verify the linearity and boundedness of $\Phi_\infty(\cdot)$ and $\Phi_{\infty, n}(\cdot)$ in the following.

Lemma 3. Let H be a separable Hilbert space and let $\Phi_\infty(\cdot)$ and $\Phi_{\infty,n}(\cdot)$ be defined as in (50) and (53) respectively. Then $\Phi_\infty(\cdot), \Phi_{\infty,n}(\cdot) : \mathcal{J}_\infty^s \rightarrow \mathcal{J}_\infty^s$ are bounded linear operators on \mathcal{J}_∞^s .

Proof. We begin this proof by observing that $(S(t)XS^*(t))^* = S(t)X^*S^*(t) = S(t)XS^*(t)$ on H for any $X \in \mathcal{J}_\infty^s$. It is then clear from the definition of $\Phi_\infty(\cdot)$ that

$$\begin{aligned}\Phi_\infty(X + \alpha Y) &= \int_0^\infty S(s)(X + \alpha Y)S^*(s)ds \\ &= \int_0^\infty S(s)XS^*(s)ds + \alpha \int_0^\infty S(s)YS^*(s)ds \\ &= \Phi_\infty(X) + \alpha\Phi_\infty(Y)\end{aligned}$$

for all $X, Y \in \mathcal{J}_\infty^s$ and $\alpha \in \mathbb{R}$. Hence, $\Phi(\cdot)$ is a linear operator.

The boundedness of $\Phi(\cdot)$ on \mathcal{J}_∞^s , is established by seeing that

$$\begin{aligned}\|\Phi_\infty(X)\| &\leq \int_0^\infty \|S(s)\|^2 \|X\|_{\mathcal{J}_\infty} ds \\ &\leq M^2 \|X\|_{\mathcal{J}_\infty} \int_0^\infty e^{-2\alpha s} ds \\ &= \frac{M^2}{2\alpha} \|X\|_{\mathcal{J}_\infty}\end{aligned}$$

for all $X \in \mathcal{J}_\infty^s$.

The above analysis applies to $\Phi_{\infty,n}(\cdot)$ as well, since $S_n(t) \in \mathcal{L}(H)$ is a C_0 -semigroup assumed to preserve exponential stability. This concludes the proof. \square

4.2. Convergence of Time-Independent Lyapunov Operator Approximations. We now move forward to analyze the convergence of $\Phi_{\infty,n} \rightarrow \Phi_\infty$ in the following.

Lemma 4. Let H be a separable Hilbert space and K be a compact subset of H . Additionally, let $S(t) \in \mathcal{L}(H)$ be an exponentially stable C_0 -semigroup and $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ be an approximating sequence of C_0 -semigroups so that

$$\lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_{\mathcal{L}(H)} = 0 \quad \forall \phi \in H$$

for any $t \in \mathbb{R}_+$. Under these assumptions, we observe that

$$(55) \quad \lim_{n \rightarrow \infty} \|\Phi_\infty(X) - \Phi_{\infty,n}(X)\|_{\mathcal{J}_\infty} = 0 \quad \forall X \in \mathcal{J}_\infty^s$$

and

$$(56) \quad \|\Phi_\infty(X) - \Phi_{\infty,n}(X)\|_{\mathcal{J}_\infty} \leq 2M \|X\|_{\mathcal{L}(H,K)} \int_0^\infty e^{-\alpha s} \|S(s) - S_n(s)\|_{\mathcal{L}(H,K)} ds \quad \forall X \in \mathcal{L}(H, K),$$

where $M, \alpha \in \mathbb{R}_+$, and the operators $\Phi_\infty(\cdot), \Phi_{\infty,n}(\cdot) : \mathcal{J}_\infty^s \rightarrow \mathcal{J}_\infty^s$ are defined as in (50) and (53) respectively.

Proof. We begin the proof by seeing that $\{\Phi_{\infty,n}\}_{n=1}^\infty : \mathcal{J}_\infty^s \rightarrow \mathcal{J}_\infty^s$ is a bounded sequence as a consequence of Lemma 3 since $S_n(t) \in \mathcal{L}(H)$ is assumed to be exponentially stable for any $n \in [1, \infty)$. This observation validates the notion of convergence of $\Phi_{\infty,n} \rightarrow \Phi_\infty$.

From the definition of $\Phi_\infty(\cdot)$ and $\Phi_{\infty,n}(\cdot)$, we see that

$$\Phi_\infty(X) - \Phi_{\infty,n}(X) = \int_0^\infty (S(s) - S_n(s))XS^*(s)ds + \int_0^\infty S_n(s)X(S(s) - S_n(s))^* ds.$$

Taking the \mathcal{J}_∞ norm on both sides of the above equation then gives us the following inequality.

$$\|\Phi_\infty(X) - \Phi_{\infty,n}(X)\|_{\mathcal{J}_\infty} = \int_0^\infty \|S(s)X - S_n(s)X\|_{\mathcal{J}_\infty} \left(\|S(s)\|_{\mathcal{L}(H)} + \|S_n(s)\|_{\mathcal{L}(H)} \right) ds.$$

We establish (55) by seeing that $\Phi_{\infty,n}(\cdot)$ and $\Phi_\infty(\cdot)$ are bounded and that $\|S(s)X - S_n(s)X\|_{\mathcal{J}_\infty}$ is pointwise convergent by Lemma 8.

We continue bounding the inequality above by seeing that

$$\|\Phi_\infty(X) - \Phi_{\infty,n}(X)\|_{\mathcal{J}_\infty} \leq 2M_* \|X\|_{\mathcal{L}(H,K)} \int_0^\infty \|S(s) - S_n(s)\|_{\mathcal{L}(K,H)} e^{-\alpha s} ds,$$

by observing that

$$\|S(t)X - S_n(t)X\|_{\mathcal{J}_\infty} \leq \|S(t) - S_n(t)\|_{\mathcal{L}(K,H)} \|X\|_{\mathcal{L}(H,K)}$$

for any $t \in \mathbb{R}_+$, and that $\|S(t)\|_{\mathcal{L}(H)} \leq Me^{-\alpha t}$ and $\|S_n(t)\|_{\mathcal{L}(H)} \leq M_n e^{-\alpha_n t}$. Thus (56) is verified. This concludes the proof. \square

4.3. Approximation Error. In this section, we will utilize the Brezzi-Rappaz-Raviart Theorem (Theorem 2) to derive an error estimate for the approximation of the operator-valued steady state Riccati equation on Hilbert spaces. To that end, we begin by defining

$$\mathcal{X} := \mathcal{J}_\infty^s \quad \mathcal{Y} := \mathcal{J}_\infty^s \quad \mathcal{Z} := \mathcal{L}(H, K) \cap \mathcal{J}_\infty^s.$$

From the definition of $\mathcal{Q}_\infty(\cdot) : \mathcal{X} \rightarrow \mathcal{Z}$, we see that $\mathcal{Q}_\infty(X)$ is infinitely Fréchet differentiable. Further, we see that

$$[D_X \mathcal{Q}_\infty(X)]T = TGX + XGT \quad \forall T \in \mathcal{X},$$

therefore $D_X \mathcal{Q}_\infty(X) \in \mathcal{L}(\mathcal{X}, \mathcal{Z})$ for any $X \in \mathcal{X}$. In Lemma 4, we have shown that

$$\lim_{n \rightarrow \infty} \|\Phi_\infty(X) \Phi_{\infty,n}(X)\|_{\mathcal{Z}} = 0$$

and

$$\lim_{n \rightarrow \infty} \|\Phi_\infty - \Phi_{\infty,n}\|_{\mathcal{L}(\mathcal{Z}, \mathcal{Z})} = 0.$$

With these observations, we see that there exists a constant $C \in \mathbb{R}_+$ that satisfies

$$\|\Sigma_\infty - \Sigma_{\infty,n}\|_{\mathcal{J}_\infty} \leq C \|\Phi_\infty[\mathcal{Q}_\infty(\Sigma_\infty)] - \Phi_{\infty,n}[\mathcal{Q}_\infty(\Sigma_\infty)]\|_{\mathcal{J}_\infty},$$

after applying Theorem 2 and recalling that $\mathcal{X} := \mathcal{J}_\infty^s$. Applying (56) then allows us to establish the main result of this section.

Theorem 4. *Let H be a separable Hilbert space and K be a compact subset of H . Additionally, let $S(t) \in \mathcal{L}(H)$ be an exponentially stable semigroup and $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ be an approximating sequence of exponentially stable semigroups so that*

$$\lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_{\mathcal{L}(H)} = 0.$$

Additionally, let $\Sigma_\infty, \Sigma_{\infty,n} \in \mathcal{J}_\infty^s$ be the solution of (48) and (49) respectively. Then there exists a constant $\gamma_M, \alpha \in \mathbb{R}_+$ so that

$$\|\Sigma_\infty - \Sigma_{\infty,n}\|_{\mathcal{J}_\infty(H)} \leq \gamma_M \|\mathcal{Q}_\infty(\Sigma_\infty)\|_{\mathcal{L}(H,K)} \int_0^\infty e^{-\alpha s} \|S(s) - S_n(s)\|_{\mathcal{L}(K,H)} ds.$$

With this result, we conclude the analysis for the approximation of the time-dependent operator Riccati equation. Like in the approximation theorem presented in the previous section (Theorem 3), we observe that the error bound of the approximate solution to the Riccati equation is a function of the error of the semigroup approximation. Similarly, we can utilize the many existing results on the approximation of time-dependent processes to derive error estimates for time-independent operator Riccati equations. We will apply this knowledge in the following section.

5. ONE DIMENSIONAL MODEL LQR CONTROL PROBLEMS

In this section, we demonstrate the applicability of the theory derived in the earlier sections of this work to the finite element approximation of LQR control systems approximated with the finite element method. Here, the finite element method is applied a thermal control system and a weakly damped wave control system, where the time-dependent operator-valued Riccati equation is approximated in the first model problem and the time-independent operator-valued Riccati equation is approximated in the second model problem. Because the operator norm is difficult to compute, we instead choose to compute the error of the functional gain associated with the optimal feedback law associated with the approximate control system. We demonstrate in both model problems that the error of the approximate functional gain is dependent on the error of the approximate solution to the relevant Riccati equation. We conclude each subsection by presenting convergence rates computed from the computational implementation of the model problems.

5.1. **Notation.** In the model problems considered in the following, the problem domain will be defined as the one-dimensional interval $\Omega := (-1, 1)$, and the boundary as the endpoints $\Gamma = \{-1\} \cup \{1\}$. We then define

$$\langle v, w \rangle = \int_{\Omega} v w dx$$

as the duality pairing between $v \in X$ and $w \in X'$, where X is a topological vector space of vectors defined on Ω , and X' denotes the dual space associated with X . The norm on X is then denoted $\|v\|_X$.

Let now Y be a second topological vector space. The tensor product space $X \times Y$ can then be defined as

$$X \times Y := \{\mathbf{v} = [v, w] : v \in X \text{ and } w \in Y\},$$

where X and Y are topological vector spaces. The norm on $X \times Y$ can then be defined by

$$\|\mathbf{v}\|_{X \times Y} = \|v\|_X + \|w\|_Y,$$

for all $\mathbf{v} := [v, w] \in X \times Y$.

The topological vector spaces of interest for the discussion presented here are the Sobolev spaces $L^2(\Omega)$ and $H^k(\Omega)$. These spaces are defined as follows:

$$L^2(\Omega) := \left\{ v \text{ is Lebesgue measurable on } \Omega : \int_{\Omega} v(x)^2 dx < \infty \right\}$$

$$H^k(\Omega) := \{v \in L^2(\Omega) : \partial_x^j v \in L^2(\Omega) \text{ for } j = 1, \dots, k\},$$

where ∂_x^j denotes the j -th partial derivative with respect to $x \in \Omega$. The Sobolev norms are then defined as

$$\|v\|_{L^2(\Omega)} := \sqrt{\int_{\Omega} v^2 dx} \quad \text{and} \quad \|v\|_{H^k(\Omega)} = \sqrt{\sum_{j=0}^k \int_{\Omega} (\partial_x^j v)^2 dx}.$$

Additionally, we are interested in the space $H_0^1(\Omega)$, which is defined as

$$H_0^1(\Omega) := \{v \in H^1(\Omega) : v = 0 \text{ on } \Gamma\}.$$

This space is the solution space of the Poisson equation with homogeneous Dirichlet boundary conditions.

We use the Finite Element Method (see, e.g., [40]) in the numerical approximations presented in the subsections below. One dimensional piecewise Lagrange polynomials [11, Chapter 3, Section 1] of arbitrary order $k \in \mathbb{N}$ are chosen as the approximation space. The domain Ω is segmented into n disjoint line segments $\mathcal{T}_n := \{\ell_j\}_{j=1}^n$ of equal length $h_n := \frac{1}{n}$. On \mathcal{T}_n , the piecewise Lagrange polynomial approximation space is then defined as

$$(57) \quad V_n^k := \{v \in C^0(\bar{\Omega}) : v|_{\ell_i} \in \mathcal{P}^k(\ell_i) \quad \forall i = 1, \dots, n\},$$

where $C^0(\bar{\Omega})$ denotes the space of continuous functions defined on $\bar{\Omega}$ and $\mathcal{P}^k(\ell_i)$ denotes the space of polynomials of order k defined over ℓ_i . The dimension of V_n^k is then denoted as $N = n + 1$. We will then denote $\{\phi_i\}_{i=1}^N$ as an admissible basis of V_n^k . Furthermore, we define the space

$$(58) \quad V_{n,0}^k := V_n^k \cap H_0^1(\Omega),$$

which consists of all functions belonging to V_n^k that are zero on Γ . The dimensionality of this space is then $N - 2$ since we do not require any approximating polynomials centered at the endpoints of the domain.

5.2. Finite-Horizon LQR Control of a 1D Thermal Process.

5.2.1. *Problem Definition.* In this example problem, we consider an one dimensional thermal control system whose state is controlled by adjusting the heat flux into and out of the interior domain. Additionally, we will let $I := [0, \tau]$ be the finite time domain on which we want to exercise the control law. The mathematical model for this system is then given by

$$(59) \quad \begin{cases} \partial_t z(x, t) = \alpha \partial_x^2 z(x, t) - \beta z(x, t) + b(x)u(t) & \text{on } \Omega \times I \\ \partial_x z(x, t) = 0 & \text{on } \Gamma \\ z(x, 0) = z_0(x) & \text{on } \Omega, \end{cases}$$

where $u(\cdot) \in L^2(I, \mathbb{R})$ is the control input and $b(x) \in H^{k+3}(\Omega)$ is the actuator function. The $\alpha, \beta \in \mathbb{R}_+$ coefficients determines the rate of thermal dissipation within the domain and out of the domain respectively. Here, we apply the LQR methodology and choose an optimal control $u_{opt}(\cdot) \in L^2(I; \mathbb{R})$ that minimizes the following cost functional

$$(60) \quad \mathcal{J}(u) := (z(T), P_\tau z(T))_H + \int_0^\tau \left(\int_{-1}^1 q(x)z(t)dx \right)^2 + |u(t)|^2 dt,$$

where $q \in H^{k+3}(\Omega)$.

For this problem, we will define $B : \mathbb{R} \rightarrow H$ and $C : H \rightarrow \mathbb{R}$ as the following

$$B(\cdot) := b(x)(\cdot) \quad \text{and} \quad C(\cdot) := \int_{-1}^1 q(x)(\cdot)dx.$$

We will now map the model equations into the infinite-dimensional state space setting. To that end, let us now define $H := L^2(\Omega)$ as the state space for the thermal control problem and $A : \mathcal{D}(A) \rightarrow H$ as the generator $\alpha \partial_{xx}(\cdot) - \beta(\cdot)$, where $\mathcal{D}(A) := \{v \in H^2(\Omega) : \partial_x v = 0 \text{ on } \Gamma\}$. The theory behind the generation of the dissipative semigroup $S(t) \in \mathcal{L}(H)$ from A can be found in [25, Chapter 7.4]. The compact space of interest for this problem is then $K := H^{k+3}(\Omega)$, where we have assumed that $b(x), q(x) \in K$. The compactness of K relative to H is verified by the Rellich-Kondrachov theorem [1, Chapter 6]. We now write the state space representation of the model problem as

$$\begin{cases} \frac{d}{dt}z = Az(t) + Bu(t) \\ z(0) = z_0, \end{cases}$$

which is well-defined for all $z(t) \in \mathcal{D}(A)$ and $u(t) \in \mathbb{R}$ since we have shown that the range of A and B are in H . The correspondent optimal feedback law can be given by

$$u_{opt}(t) = -\mathcal{K}(t)z(t),$$

where $\mathcal{K}(t) := B^*P(t)$ and $P(t) \in \mathcal{J}_\infty^s$ satisfies the following weak time-dependent algebraic Riccati equation

$$\begin{cases} \frac{d}{dt}(\psi, P(t)\phi)_H = -(\psi, A^*\phi)_H - (\psi, A\phi)_H + (\psi, (PBB^*P)(t))_H - (\psi, C^*C\phi)_H \\ (\psi, P(\tau)\phi)_H = (\psi, P_\tau\phi)_H \end{cases}$$

for all $\phi, \psi \in \mathcal{D}(A)$. The theory discussed in §3 applies to this example problem, since $BB^*, C^*C \in \mathcal{J}_\infty^s \cap \mathcal{L}(H, K)$, by definition.

5.2.2. Finite Element Approximation with Piecewise Lagrange Elements. The finite element approximation of (59) is given by seeking a $z_n \in V_n^k$ that satisfies

$$(61) \quad \begin{cases} \frac{d}{dt} \langle z_n, q_n \rangle = a(z_n, q_n) + (b(x)u_n(t), q_n) \\ \langle z_n(0), q_n \rangle = \langle z_0, q_n \rangle \end{cases}$$

for all $q_n \in V_n^k$ and $t \in I$, where

$$a(q_n, r_n) := - \int_{-1}^1 (\alpha q_n'(x)r_n'(x) + \beta q_n(x)r_n(x)) dx$$

is the bilinear form associated with the diffusion operator A . Here, the homogeneous Neumann boundary condition is enforced naturally through integration-by-parts and setting the boundary terms to zero. The solution $z_n(\cdot, t) \in V_n^k$ can then be represented as

$$z_n(x, t) := \sum_{i=1}^n \hat{z}_i(t)\phi_i(x),$$

where $\{\phi_i\}_{i=1}^N \in V_n^k$ is a set of functions representing the basis of the approximation space V_n^k . The coefficients $\hat{\mathbf{z}}(t) = [\hat{z}_1(t), \dots, \hat{z}_n(t)]$ is then the solution of the following matrix system

$$\begin{cases} \frac{d}{dt} \hat{\mathbf{z}}(t) = [\mathbf{A}_n] \hat{\mathbf{z}}(t) + [\mathbf{B}_n] u_n(t), \\ \hat{\mathbf{z}}(0) = \hat{\mathbf{z}}_0 \end{cases},$$

where

$$[\mathbf{A}_n] := [M_n]^{-1} [K_n] \quad \text{and} \quad [\mathbf{B}_n] := [M_n]^{-1} [B_n],$$

with

$$[M_n]_{ij} := \int_{-1}^1 \phi_i(x) \phi_j(x) dx, \quad [K_n]_{ij} := a(\phi_i, \phi_j), \quad \text{and} \quad [B_n]_i := \int_{-1}^1 b(x) \phi_i(x) dx.$$

The resultant cost functional to be minimized is then given in matrix form as

$$(62) \quad \mathcal{J}(u_n) = \hat{\mathbf{z}}^T(\tau) [\mathbf{P}_{\tau,n}] \hat{\mathbf{z}}(\tau) + \int_0^\tau \hat{\mathbf{z}}(t) [\mathbf{C}]^T [\mathbf{C}] \hat{\mathbf{z}}(t) + u_n^2(t) dt,$$

where

$$[\mathbf{P}_{\tau,n}]_{ij} := \int_{-1}^1 \phi_i(x) \mathbf{P}_\tau \phi_j(x) dx \quad \text{and} \quad [\mathbf{C}]_i = \left[\int_{-1}^1 q(x) \phi_i(x) dx, \dots, \int_{-1}^1 q(x) \phi_n(x) dx \right].$$

This cost functional is derived by substituting z with \hat{z} and u with u_n in (60) and recalling that $z_n(t) := \sum_{i=1}^n \hat{z}_i(t) \phi_i(x)$.

The optimal feedback law for the finite element matrix control system is then given by

$$u_{n,opt}(t) := [\mathcal{K}_n(t)] \hat{\mathbf{z}}(t),$$

where $[\mathcal{K}_n(t)] := [\hat{\kappa}_1(t), \dots, \hat{\kappa}_n(t)]$ is the vector representation of the functional gain given by

$$[\mathcal{K}_n(t)] = -[\mathbf{B}]^T [\mathbf{P}_n(t)],$$

and $[\mathbf{P}_n(t)] \in \mathbb{R}^{n \times n}$ is the solution of the following matrix Riccati equation

$$\begin{cases} \frac{d}{dt} [\mathbf{P}_n(t)] = -[\mathbf{A}_n]^T [\mathbf{P}_n(t)] - [\mathbf{P}_n(t)] [\mathbf{A}_n] + \left([\mathbf{P}_n(t)] [\mathbf{B}]^T [\mathbf{B}] [\mathbf{P}_n(t)] \right) - [\mathbf{C}]^T [\mathbf{C}] \\ [\mathbf{P}_n](\tau) = [\mathbf{P}_{n,\tau}] \end{cases}$$

for all $t \in I$. The functional gain of the matrix system can then be defined as a function in V_n^k by setting $\boldsymbol{\kappa}_n(t) := -[\mathbf{B}]^T [\mathbf{P}_n(t)] [\mathbf{M}_n]^{-1}$ and then defining $\kappa_n(t) := \sum_{i=1}^n \hat{\kappa}_i(t) \phi_i(x)$, where $\hat{\kappa}_i(t)$ are the elements of the vector $\boldsymbol{\kappa}_n(t)$. In functional form, we may write the functional gain as

$$\mathcal{K}_n(t) := \langle \boldsymbol{\kappa}_n(t), \cdot \rangle.$$

With this, we move on to present the main result of this section.

Lemma 5. *Let $H = L^2(\Omega)$ and $K = H^{k+3}(\Omega)$, then there exists a constant $M \in \mathbb{R}_+$ such that*

$$\|\mathcal{K}(t) - \mathcal{K}_n(t)\|_{\mathcal{C}(I; \mathcal{L}(H; \mathbb{R}))} \leq M h_n^{k+1},$$

where \mathcal{K} and \mathcal{K}_n are the functional gains associated with the optimal feedback laws for the infinite dimensional control system and its finite element approximation respectively.

Proof. For the purpose of analysis only, we may equivalently represent the finite element weak problem (61) as

$$\begin{cases} \frac{d}{dt} z_n = A_n z_n(t) + B_n u_n(t) \\ z_n(0) = \pi_n z_0 \end{cases}$$

for all $t \in I$, where the operator $A_n : H_n \rightarrow H_n$ is defined by

$$\begin{aligned} A_n \phi_i &= \sum_{i=1}^n \langle \phi_i, A \phi_i \rangle \phi_i \\ &= - \sum_{i=1}^n a(\phi_i, \phi_i) \phi_i \end{aligned}$$

for all $\phi_i \in V_n^k$. Here, $\mathcal{D}(A_n) := \{v_n \in V_n^k : \partial_x v_n = 0 \text{ on } \Gamma\}$ since homogeneous Neumann boundary condition is enforced implicitly as a natural condition. The actuator operator $B_n : \mathbb{R} \rightarrow V_n^k$ can be simply taken as the simple $L^2(\Omega)$ projection of B , i.e.

$$B_n := \pi_n B,$$

where $\pi_n : H \rightarrow V_n^k$ is the orthogonal projection operator associated with the approximation space V_n^k . Then, the optimal feedback law for the state space representation of the finite element approximation can then be given as

$$u_{n,opt}(t) = -B_n P_n(t) z_n(t),$$

where $P_n(t) \in \mathcal{J}_\infty^s$ is the solution of the following operator-valued Riccati equation

$$\begin{cases} \frac{d}{dt} (\psi_n, P_n(t) \phi_n)_H = -(\psi_n, A_n^* P_n(t) \phi_n)_H - (\psi_n, A_n P_n(t) \phi_n)_H + (\psi_n, (P_n B_n B_n^* P_n)(t) \phi_n)_H - (\psi_n, C_n^* C_n \phi_n)_H \\ (\psi_n, P_n(\tau) \phi_n)_H = (\psi_n, P_\tau \phi_n)_H \end{cases}$$

for all $\phi_n, \psi_n \in V_n^k$ and $t \in I$.

From Theorem 3, we have that there exists a constant $C_1 \in \mathbb{R}_+$ so that

$$\|P(\cdot) - P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \leq C_1 \sup_{t \in I} \|S(t) - S_n(t)\|_{\mathcal{L}(K, H)} \|\mathcal{Q}(P)\|_{\mathcal{C}(I; \mathcal{L}(H, K))},$$

where $S(t) \in \mathcal{L}(H)$ is the C_0 -semigroup generated by $A : \mathcal{D}(A) \rightarrow H$, and $S_n(t) = \iota_H \exp(tA_n) \pi_n \in \mathcal{L}(H)$ is the C_0 -semigroup approximation generated by $A_n : \mathcal{D}(A_n) \rightarrow V_n^k$. Applying Lemma 10 allows us to see that there exists a constant $C_1 \in \mathbb{R}_+$ so that

$$\|P(\cdot) - P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \leq C_1 h_n^{k+1} \|\mathcal{Q}(P)\|_{\mathcal{C}(I; \mathcal{L}(H, K))},$$

where $\mathcal{Q}(P) \in \mathcal{C}(I; \mathcal{L}(H, K))$ is verified by inspecting the definition of $B : \mathbb{R} \rightarrow C^\infty(\bar{\Omega})$ and the smoothness assumption made on $q(x) \in H^{k+3}(\Omega)$. Following this, we have that there exists a constant $C_2 \in \mathbb{R}_+$

$$\|B - B_n\|_{\mathcal{L}(\mathbb{R}, H)} \leq C_2 h_n^{k+1} |b|_{H^{k+1}(\Omega)}$$

after seeing that $\|v - \pi_n v\|_H \leq C h_n^{k+1} |v|_{H^{k+1}(\Omega)}$ for all $v \in K$ as a consequence of the one dimensional Lagrange interpolation error estimate given in [24, Proposition 1.12]. Putting these error bounds together allows us to see that

$$\begin{aligned} \|\mathcal{K}(\cdot) - \mathcal{K}_n(\cdot)\|_{\mathcal{C}(I; \mathcal{L}(H, \mathbb{R}))} &= \|B^* P(\cdot) - B_n^* P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{L}(H, \mathbb{R}))} \\ &\leq \|P(\cdot) - P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \|B\|_{\mathcal{L}(\mathbb{R}; H)} + \|B - B_n\|_{\mathcal{L}(\mathbb{R}; H)} \|P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)} \\ &\leq C_1 h_n^{k+1} \|\mathcal{Q}(P)\|_{\mathcal{C}(I; \mathcal{L}(H, K))} \|B\|_{\mathcal{L}(\mathbb{R}; H)} + C_2 h_n^{k+1} \|P_n(\cdot)\|_{\mathcal{C}(I; \mathcal{J}_\infty)}. \end{aligned}$$

Thus proving the error bound presented in this Lemma. \square

This concludes the analytical discussion regarding the theoretical error estimate for the finite element approximation of the model thermal control system. We corroborate the error estimate for the functional gain in the computational results presented in below.

5.2.3. Computational Results. In this computational illustration, we set $I := [0, 0.1]$, $\alpha = 1$, $\beta = 1$, and $b(x), q(x) = \exp\left(\frac{-1}{1-x^2}\right)$. With these parameters, the time-dependent matrix Riccati equation was solved using the trapezoidal time-stepping method [11, §5.4] with a time-step of $\Delta t = 10^{-4}$. The `linalg.solve_continuous_are()` function in the SciPy numerical library was used to solve the matrix Riccati equation at every implicit time step. The terminal condition was taken to be $P_\tau = 0$.

The functional gain error is plotted in Figure 5.2.3 with respect to the $L^2(\Omega)$ norm, where we have compared the finite element solution to a spectral element solution on a single element with a 128-th order Lagrange polynomial basis defined on the Lobatto quadrature points. We observe good agreement between the numerically computed errors and our theoretical results, albeit with numerical precision error on the convergence of the quartic finite element approximation.

We now move forward to discuss the error estimate for the finite element approximation of our model damped wave control system.




FIGURE 1. Approximation error in $\|\kappa - \kappa_n\|_H$ for the finite element approximation of the thermal control system, where $H = L^2(\Omega)$.

5.3. Infinite-Horizon LQR Control of a 1D Weakly Damped Wave System.

5.3.1. *Problem Definition.* The model problem we approximate in this section is given by

$$(63) \quad \min_{u(\cdot) \in L^2((0, \infty); \mathbb{R})} \int_0^\infty \left[\left(\int_{-1}^1 p(x)v(s)dx \right)^2 + \beta |u(s)|^2 \right] ds$$

subject to the 1D weakly damped wave system

$$\begin{cases} \partial_t v(x, t) = w(x, t) & \text{for } (x, t) \in (-1, 1) \times (0, \infty) \\ \partial_t w(x, t) = c^2 \partial_x^2 v(x, t) - \gamma w(x, t) + b(x)u(t) & \text{for } (x, t) \in (-1, 1) \times (0, \infty) \\ v(x, 0) = v_0(x) & \text{for } x \in (-1, 1) \\ w(x, 0) = w_0(x) & \text{for } x \in (-1, 1) \\ v(-1, t) = v(1, t) = 0 & \text{for } t \in (0, \infty), \end{cases}$$

for some arbitrary initial conditions $v_0 \in H_0^1(\Omega)$, and $w_0 \in L^2(\Omega)$. The functions $p(x)$ and $b(x)$ are chosen to be $H^{k+3}(\Omega)$ smooth for this example and we require that they are zero on Γ , i.e. $p(x), b(x) \in H^{k+3}(\Omega) \cap H_0^1(\Omega)$. The homogeneous boundary condition here is required in order to derive an optimal error estimate because of the way the Galerkin projection is utilized in the error analysis for the finite element approximation for the wave equation (see [3] for a complete discussion). Here $k \in \mathbb{N}$ will denote the polynomial order of the approximation space used in the finite element approximation.

We can map this control problem into the state space form required by our theory by setting

$$z(t) := \begin{pmatrix} v(t) \\ w(t) \end{pmatrix}, \quad \mathcal{A} := \begin{bmatrix} 0 & \mathcal{I}_{L^2(\Omega)} \\ c^2 \partial_{xx}(\cdot) & -\gamma(\cdot) \end{bmatrix},$$

$$B := \begin{bmatrix} 0 \\ b(x)(\cdot) \end{bmatrix}, \quad C := \begin{bmatrix} \int_{-1}^1 p(x)(\cdot) dx \\ 0 \end{bmatrix}, \quad \text{and } R := \beta,$$

where we have denoted $\mathcal{I}_{L^2(\Omega)}$ as the identity operator in $L^2(\Omega)$. We can write the above control system in the following form

$$\min_{u(\cdot) \in L^2((0, \infty); \mathbb{R})} \int_0^\infty \|Cz(t)\|_Y^2 + (u(t), Ru(t))_U dt$$

subject to

$$\begin{cases} \frac{d}{dt}z = \mathcal{A}z(t) + Bu(t) \\ z(0) = z_0, \end{cases}$$

for all $t \in \mathbb{R}_+$, where we have chosen $U := \mathbb{R}$, $Y := \mathbb{R}$, $H := H_0^1(\Omega) \times L^2(\Omega)$ and $\mathcal{D}(\mathcal{A}) := (H^2(\Omega) \cap H_0^1(\Omega)) \times H_0^1(\Omega)$. This choice of H and $\mathcal{D}(\mathcal{A})$ is required in order for \mathcal{A} to generate an exponentially stable C_0 -semigroup (e.g., see [21]). With this, it is clear that this example problem falls into the set of problems presented in §2.4.2. The associated Riccati equation for this model problem is then given in the weak form by

$$(\psi, \mathcal{A}^*P\phi)_H + (\psi, P\mathcal{A}\phi)_H - (\psi, PBR^{-1}B^*P\phi)_H + (\psi, C^*C\phi)_H = 0$$

for all $\phi, \psi \in H$. It is then clear that $BR^{-1}B^*$ and C^*C are operators belonging to $\mathcal{J}_\infty^s \cap \mathcal{L}(H, K)$, where $K := H^{k+3}(\Omega) \times H^{k+2}(\Omega)$. The choice of K is derived from our earlier definition of the functions $q(x)$ and $b(x)$ as well as the analysis given in §B.2. The optimal feedback law for this model control system is then given by

$$(64) \quad u_{opt}(t) = -\mathcal{K}z(t)$$

for all $t \in \mathbb{R}_+$, where $\mathcal{K} : H \rightarrow \mathbb{R}$ is the functional gain defined as $\mathcal{K} := R^{-1}B^*P$.

5.3.2. *Finite Element Approximation with Piecewise Lagrange Elements.* The approximation space associated with this model problem is given by

$$H_n := V_{n,0}^k \times V_{n,0}^k.$$

This approximation space is chosen since w must be zero on Γ because $w(x, t) = \partial_t v(x, t)$ and v is zero on Γ for all $t \in \mathbb{R}_+$. An inspection indicates that $H_n \subset H$ and hence the orthogonal projection operator $\pi_n : H \rightarrow H_n$ is well defined.

In the finite element approximation of the weakly damped wave system, the approximate system is defined in the weak form by

$$\begin{cases} \frac{d}{dt} \langle v_n, q_n \rangle = \langle w_n, q_n \rangle, & \langle v_n(0), q_n \rangle = \langle v_0, q_n \rangle \quad \forall q_n \in V_n^k \\ \frac{d}{dt} \langle w_n, r_n \rangle = a(v_n, r_n) - \gamma \langle w_n, r_n \rangle + \langle bu_n(t), r_n \rangle, & \langle w_n(0), r_n \rangle = \langle w_0, r_n \rangle \quad \forall r_n \in V_n^k, \end{cases}$$

where

$$v_n(x, t) = \sum_{i=1}^{N-2} \hat{v}_i(t) \phi_i(x) \quad \text{and} \quad w_n(x, t) = \sum_{i=1}^{N-2} \hat{w}_i(t) \phi_i(x)$$

are the finite element approximation of $v(t)$ and $w(t)$ respectively, given time-dependent coefficients $\hat{v}_i(t), \hat{w}_i(t) \in \mathbb{R}$, and

$$a(q, r) := - \int_{-1}^1 c^2 q'(x) r'(x) dx$$

is a bilinear form mapping any $q, r \in H_0^1(\Omega)$ to \mathbb{R} . It then follows, by the finite dimensional nature of the space $V_{n,0}^k$, that the finite element description of the approximate problem can be written in an equivalent matrix form given by

$$\begin{cases} [M_n] \frac{d}{dt} \hat{\mathbf{v}} = [M_n] \hat{\mathbf{w}}(t), & \hat{\mathbf{v}}(0) = \hat{\mathbf{v}}_0 \\ [M_n] \frac{d}{dt} \hat{\mathbf{w}} = [K_n] \hat{\mathbf{v}}(t) - \gamma [M_n] \hat{\mathbf{w}}(t) + [b_n] u_n(t) & \hat{\mathbf{w}}(0) = \hat{\mathbf{w}}_0, \end{cases}$$

where for $i, j = 1, \dots, N-2$,

$$[M_n]_{ij} = \int_{-1}^1 \phi_i(x)\phi_j(x)dx, \quad [K_n]_{ij} = \int_{-1}^1 \phi_i'(x)\phi_j'(x)dx, \quad [b_n] = \int_{-1}^1 b(x)\phi_i(x)dx,$$

with $[b_n] : \mathbb{R}^{N-2} \rightarrow \mathbb{R}$ being a column vector. Denoting

$$[\mathbf{M}_n] := \begin{bmatrix} [M_n] & 0 \\ 0 & [M_n] \end{bmatrix}, \quad [\mathbf{K}_n] := \begin{bmatrix} 0 & [M_n] \\ [K_n] & -\gamma [M_n] \end{bmatrix}, \quad \text{and} \quad [\mathbf{b}_n] := \begin{bmatrix} 0 \\ [b_n] \end{bmatrix},$$

we may write the finite dimensional problem in the following block form

$$(65) \quad \begin{cases} \frac{d}{dt} \hat{\mathbf{z}} = [\mathbf{A}_n] \hat{\mathbf{z}} + [\mathbf{B}_n] u_n(t) \\ \hat{\mathbf{z}}(0) = \hat{\mathbf{z}}_0, \end{cases}$$

where $\hat{\mathbf{z}}(t) = [\hat{\mathbf{v}}(t), \hat{\mathbf{w}}(t)]^T$, $[\mathbf{A}_n] = [\mathbf{M}_n]^{-1} [\mathbf{K}_n]$, and $[\mathbf{B}_n] = [\mathbf{M}_n]^{-1} [\mathbf{b}_n]$.

With this, we wish to choose $u_n(\cdot)$ that minimizes following cost functional

$$(66) \quad \int_0^\infty \hat{\mathbf{z}}^T(t) [\mathbf{C}_n]^T [\mathbf{C}_n] \hat{\mathbf{z}}(t) + R u_n^2(t) dt,$$

where $[\mathbf{C}_n] := [[q_n], 0]$ is a row vector with $[q_n]_i = \int_{-1}^1 q(x)\phi_i(x)dx$ for $i = 1, \dots, N-2$. The matrix form of the cost functional given in (66) arises by replacing v with v_n and u with u_n in (63). The optimal feedback law for the finite element approximation of the control system is then given in matrix form by

$$u_{n,opt}(t) = -[\mathcal{K}_n] \hat{\mathbf{z}}(t),$$

where $[\mathcal{K}_n] := R^{-1} [\mathbf{B}_n]^T [\mathbf{P}_n]$ and $[\mathbf{P}_n]$ is the solution of the following matrix Riccati equation

$$(67) \quad [\mathbf{A}_n]^T [\mathbf{P}_n] + [\mathbf{P}_n] [\mathbf{A}_n] - [\mathbf{P}_n] [\mathbf{B}_n] R^{-1} [\mathbf{B}_n]^T [\mathbf{P}_n] + [\mathbf{C}_n]^T [\mathbf{C}_n] = 0.$$

We now wish to represent the optimal feedback law in the functional sense, where

$$u_{n,opt}(t) := -\mathcal{K}_n z_n(t).$$

The approximate functional gain as an element of H by first defining $\kappa_n := \left[\sum_{i=1}^{N-2} \hat{\kappa}_i^1 \phi_i(x), \sum_{i=1}^{N-2} \hat{\kappa}_i^2 \phi_i(x) \right]^T$, where the coefficients $\hat{\kappa}_i^1, \hat{\kappa}_i^2 \in \mathbb{R}$ are computed using

$$[\kappa] = R^{-1} [\mathbf{B}_n]^T [\mathbf{P}_n] [\mathbf{M}_n]^{-1},$$

where we have denoted $[\kappa] := [\hat{\kappa}_1^1, \dots, \hat{\kappa}_N^1, \hat{\kappa}_1^2, \dots, \hat{\kappa}_N^2]^T$. The functional form is then given by setting

$$\mathcal{K}_n := \langle \kappa_n, \cdot \rangle.$$

With this, we can now prove that \mathcal{K}_n converges to \mathcal{K} with an optimal order of convergence.

Lemma 6. *Let $H = H_0^1(\Omega) \times L^2(\Omega)$ and $K = [H^{k+3}(\Omega) \cap H_0^1(\Omega)] \times H^{k+2}(\Omega)$ for all $k \in \mathbb{N}$. If $b(\cdot), q(\cdot) \in H^{k+3}(\Omega) \cap H_0^1(\Omega)$, then there exists a constant $M \in \mathbb{R}_+$ so that*

$$\|\mathcal{K} - \mathcal{K}_n\|_{\mathcal{L}(H, \mathbb{R})} \leq M h_n^k \|\mathcal{Q}(\Sigma)\|_{\mathcal{L}(H, K)},$$

where $\mathcal{K}, \mathcal{K}_n \in \mathcal{L}(H; \mathbb{R})$ are the functional gains associated with the optimal feedback control law for the infinite dimensional control system (64) and its finite element approximation respectively.

Proof. From the definition of $\mathcal{K}, \mathcal{K}_n : H \rightarrow \mathbb{R}$, we see that

$$\begin{aligned} \|\mathcal{K} - \mathcal{K}_n\|_H &\leq |R^{-1}| \|B^* P - B_n^* P_n\|_{\mathcal{L}(H, \mathbb{R})} \\ &\leq |R^{-1}| \left(\|B^*\|_{\mathcal{L}(H, \mathbb{R})} \|P - P_n\|_{\mathcal{J}_\infty} + \|B^* - B_n\|_{\mathcal{L}(H, \mathbb{R})} \|P_n\|_{\mathcal{L}(H)} \right), \end{aligned}$$

where $B_n := [0, \pi_n b(x)]^T$. From Theorem 4, we observe that

$$\begin{aligned} \|P - P_n\|_{\mathcal{L}(H)} &\leq \gamma_n \|\mathcal{Q}(P)\|_{\mathcal{L}(H,K)} \int_0^\infty e^{-\alpha s} \|S(s) - S_n(s)\|_{\mathcal{L}(K,H)} ds \\ &\leq C_\gamma h^k \|\mathcal{Q}(P)\|_{\mathcal{L}(H,K)} \int_0^\infty e^{-\alpha s} ds \\ &= C_{\gamma,\alpha} \|\mathcal{Q}(P)\|_{\mathcal{L}(H,K)} \end{aligned}$$

as a consequence of Lemma 12. We observe that $\mathcal{Q}(P)$ is bounded in $\mathcal{L}(H, K)$ from the smoothness assumptions made on $b(s)$ and $q(x)$.

We continue by seeing that

$$\begin{aligned} \|B - B_n\|_{\mathcal{L}(H,\mathbb{R})} &= \left\| (0, b(x) - \pi_n b(x))^T \right\|_H \\ &= \|b(x) - \pi_n b(x)\|_{L^2(\Omega)} \\ &\leq C h_n^{k+1} |b|_{H^{k+1}(\Omega)}, \end{aligned}$$

after bounding the error associated with the $L^2(\Omega)$ projection onto V_n^k by the error associated with one-dimensional Lagrange interpolation. ([24, Proposition 1.12]). With this, it becomes clear that there exists a constant $M \in \mathbb{R}_+$ so that

$$\|\mathcal{K} - \mathcal{K}_n\|_H \leq M h_n^{k+1}.$$

This concludes the proof. \square

5.3.3. Computational Results. In the computational illustration, the author's personal code was utilized to generate the operator matrices defined above. The `linalg.solve_continuous_are()` function in SciPy was utilized to solve (67). We set $c = 1$, $\gamma = 10^{-4}$, and $b(x) = q(x) := \cos(\frac{\pi}{2}x)$. With these parameters, the matrix Riccati equation was solved and the functional gain was computed. The functional gain error is plotted in Figure 5.3.3 with respect to the $H_0^1(\Omega) \times L^2(\Omega)$ norm and $L^2(\Omega) \times L^2(\Omega)$ norm, where we have compared the finite element solution to a spectral element solution on a single element with a 128th order Lagrange polynomial basis defined on the Lobatto quadrature points. We observe good agreement between the numerically computed errors and our theoretical results, albeit with numerical precision error past 10^{-8} .

6. CONCLUSION

In this work, we have presented an abstract theory for the approximation of operator-valued Riccati equations. This theory indicates that the error of the solution of these equations, in the time-dependent and time-independent forms, is bounded by error associated with the governing semigroup approximation. This result was derived through the use of the Brezzi-Rappaz-Raviart theorem on the equivalent Bochner integral form of the operator-valued Riccati equations. This form is particularly useful because it possesses the necessary fixed-point structure for applying the Brezzi-Rappaz-Raviart theorem. It was shown at the beginning of this work that the abstract theory presented can be used on many different problems and also on many different approximation methods.

In the model problems presented, we have shown that the finite element approximation of the functional gains, under certain smoothness conditions, are expected to converge to the exact functional gain with optimal order. Correspondingly, our computational result corroborates these theoretical findings.

7. FUTURE WORK

While we believe that the theory presented in this work has wide-reaching implications, we are also aware of several theoretical shortcomings. The most notable shortcoming is the treatment of unbounded operators. These operators typically occur in e.g. boundary and point control and observation systems. Our work cannot be applied to these problems since the unbounded operators violate the compactness assumptions required by our theory. A possible path forward is to demonstrate that the Bochner integral form of the operator-valued Riccati equation is well-posed for when the coefficient operators are unbounded, and then

adapting the analysis presented in this work to that general case. We plan on exploring in this direction in future works.

REFERENCES

- [1] Robert A Adams and John JF Fournier. *Sobolev spaces*. Elsevier, 2003.
- [2] Sheldon Axler. *Measure, integration & real analysis*. Springer Nature, 2020.
- [3] Garth A. Baker. Error estimates for finite element methods for second order hyperbolic equations. *SIAM Journal on Numerical Analysis*, 13(4):564–576, 1976.
- [4] H. T. Banks and K. Kunisch. The linear regulator problem for parabolic systems. *SIAM Journal on Control and Optimization*, 22(5):684–698, 1984.
- [5] Maximilian Behr, Peter Benner, and Jan Heiland. Solution formulas for differential sylvester and lyapunov equations. *Calcolo*, 56(4):51, 2019.
- [6] Alain Bensoussan, Giuseppe Da Prato, Michel C Delfour, and Sanjoy K Mitter. *Representation and control of infinite dimensional systems*, volume 1. Springer, 2007.
- [7] Christine Bernardi and Yvon Maday. Spectral methods. *Handbook of numerical analysis*, 5:209–485, 1997.
- [8] Pierre Bernhard. Linear-quadratic, two-person, zero-sum differential games: necessary and sufficient conditions. *Journal of Optimization Theory and Applications*, 27(1):51–69, 1979.
- [9] RI Boby, H Mansor, TS Gunawan, and S Khan. Robust adaptive lqr control of nonlinear system application to 3-dof flight control system. In *2014 IEEE International Conference on Smart Instrumentation, Measurement and Applications (ICSIMA)*, pages 1–4. IEEE, 2014.
- [10] Jeff Borggaard, John A Burns, Eric Vugrin, and Lizette Zietsman. On strong convergence of feedback operators for non-normal distributed parameter systems. In *2004 43rd IEEE Conference on Decision and Control (CDC)(IEEE Cat. No. 04CH37601)*, volume 2, pages 1526–1531. IEEE, 2004.
- [11] Richard L Burden, J Douglas Faires, and Annette M Burden. *Numerical analysis*. Cengage learning, 2015.
- [12] John A Burns and James Cheung. Optimal convergence rates for galerkin approximation of operator riccati equations. *Numerical Methods for Partial Differential Equations*, 2022.
- [13] John A Burns and Kevin P Hulsing. Numerical methods for approximating functional gains in lqr boundary control problems. *Mathematical and Computer Modelling*, 33(1-3):89–100, 2001.
- [14] John A Burns and Carlos N Rautenberg. Solutions and approximations to the riccati integral equation with values in a space of compact operators. *SIAM Journal on Control and Optimization*, 53(5):2846–2877, 2015.
- [15] Margaret Cheney and Brett Borden. *Fundamentals of radar imaging*. SIAM, 2009.
- [16] Philippe G Ciarlet. *The finite element method for elliptic problems*. SIAM, 2002.
- [17] Philippe G Ciarlet. *Linear and nonlinear functional analysis with applications*, volume 130. Siam, 2013.
- [18] Bernardo Cockburn, George E Karniadakis, and Chi-Wang Shu. *Discontinuous Galerkin methods: theory, computation and applications*, volume 11. Springer Science & Business Media, 2012.
- [19] Monica Conti, Lorenzo Liverani, and Vittorino Pata. On the optimal decay rate of the weakly damped wave equation. *Communications on Pure and Applied Analysis*, 21(10):3421–3424, 2022.
- [20] J Austin Cottrell, Thomas JR Hughes, and Yuri Bazilevs. *Isogeometric analysis: toward integration of CAD and FEA*. John Wiley & Sons, 2009.
- [21] Steven Cox and Enrique Zuazua. The rate at which energy decays in a damped string. *Communications in partial differential equations*, 19(1-2):213–243, 1994.
- [22] Ruth F Curtain and Hans Zwart. *An introduction to infinite-dimensional linear systems theory*, volume 21. Springer Science & Business Media, 2012.
- [23] Todd Dupont. l^2 -estimates for galerkin methods for second order hyperbolic equations. *SIAM Journal on Numerical Analysis*, 10(5):880–889, 1973.
- [24] Alexandre Ern and Jean-Luc Guermond. *Theory and practice of finite elements*, volume 159. Springer, 2004.
- [25] Lawrence C Evans. *Partial differential equations*, volume 19. American Mathematical Society, 2022.
- [26] Vivette Girault and Pierre-Arnaud Raviart. *Finite element methods for Navier-Stokes equations: theory and algorithms*, volume 5. Springer Science & Business Media, 2012.
- [27] Jerome A Goldstein. *Semigroups of linear operators and applications*. Courier Dover Publications, 2017.
- [28] JE Gubernatis, E Domany, JA Krumhansl, and M Huberman. The born approximation in the theory of the scattering of elastic waves by flaws. *Journal of Applied Physics*, 48(7):2812–2819, 1977.
- [29] Kazufumi Ito. Strong convergence and convergence rates of approximating solutions for algebraic riccati equations in hilbert spaces. In *Distributed Parameter Systems*, pages 153–166. Springer, 1987.
- [30] Kazufumi Ito and Kirsten A Morris. An approximation theory of solutions to operator riccati equations for h^∞ control. *SIAM journal on control and optimization*, 36(1):82–99, 1998.
- [31] Rudolph Emil Kalman. A new approach to linear filtering and prediction problems. 1960.
- [32] Tosio Kato. *Perturbation theory for linear operators*, volume 132. Springer Science & Business Media, 2013.
- [33] Michael Kroller and Karl Kunisch. Convergence rates for the feedback operators arising in the linear quadratic regulator problem governed by parabolic equations. *SIAM journal on numerical analysis*, 28(5):1350–1385, 1991.
- [34] Irena Lasiecka and Roberto Triggiani. *Differential and algebraic Riccati equations with application to boundary/point control problems: continuous theory and approximation theory*. Springer, 1991.

- [35] C. McMillan and R. Triggiani. Algebraic riccati equations arising in game theory and in h^∞ -control problems for a class of abstract systems. In W.F. Ames, E.M. Harrell, and J.V. Herod, editors, *Differential Equations with Applications to Mathematical Physics*, volume 192 of *Mathematics in Science and Engineering*, pages 239–247. Elsevier, 1993.
- [36] Lal Bahadur Prasad, Barjeev Tyagi, and Hari Om Gupta. Optimal control of nonlinear inverted pendulum system using pid controller and lqr: performance analysis without and with disturbance input. *International Journal of Automation and Computing*, 11:661–670, 2014.
- [37] Alfio Quarteroni, Riccardo Sacco, and Fausto Saleri. *Numerical mathematics*, volume 37. Springer Science & Business Media, 2010.
- [38] Maria Isabel Ribeiro. Kalman and extended kalman filters: Concept, derivation and properties. *Institute for Systems and Robotics*, 43(46):3736–3741, 2004.
- [39] Robert F Stengel. *Optimal control and estimation*. Courier Corporation, 1994.
- [40] Gilbert Strang, George J Fix, and DS Griffin. An analysis of the finite-element method. 1974.
- [41] Russ Tedrake. Lqr-trees: Feedback motion planning on sparse randomized trees. 2009.
- [42] Jaroslav Vondřejc, Jan Zeman, and Ivo Marek. An fft-based galerkin method for homogenization of periodic media. *Computers & Mathematics with Applications*, 68(3):156–173, 2014.

APPENDIX A. TECHNICAL LEMMAS

In this section, we present the technical lemmas that we will use throughout the analysis presented in this work. We begin by demonstrating that $\mathcal{L}(H, K)$ forms a two-sided *-ideal (stated in a different manner).

Lemma 7. *Let H be a separable Hilbert space and K be a compact subset of H . In addition, let $U, V \in \mathcal{L}(H)$ and $X \in \mathcal{L}(H, K)$, Then $UXV \in \mathcal{L}(H, K)$.*

Proof. We begin by seeing that

$$\|UXV\|_{\mathcal{L}(H,K)} \leq \|UX\|_{\mathcal{L}(H,K)} \|V\|_{\mathcal{L}(H)}.$$

It then follows by Proposition 2 that

$$\|UX\|_{\mathcal{L}(H,K)} = \|X^*U^*\|_{\mathcal{L}(K,H)} \leq \|X^*\|_{\mathcal{L}(H)} \|U^*\|_{\mathcal{L}(K,H)} \leq \|X\|_{\mathcal{L}(H)} \|U^*\|_{\mathcal{L}(H)}.$$

Therefore

$$\|UXV\|_{\mathcal{L}(H,K)} \leq \|U\|_{\mathcal{L}(H)} \|X\|_{\mathcal{L}(H)} \|V\|_{\mathcal{L}(H)}.$$

The right hand side of the above inequality is bounded because $\mathcal{L}(H, K) \subset \mathcal{L}(H)$ (see Proposition 2). The boundedness of UXV in the $\mathcal{L}(H, K)$ norm implies that $UXV \in \mathcal{L}(H, K)$. \square

The following result is then easily proven.

Corollary 1. *Let H be a separable Hilbert space and K be a compact subset of H , and I be a compact subset of \mathbb{R}_+ . Additionally, let $U(\cdot), V(\cdot) \in \mathcal{C}(I; \mathcal{L}(H))$ and $X(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K))$. Then $(UXV)(\cdot) \in \mathcal{C}(I; \mathcal{L}(H, K))$.*

Proof. For any $t \in I$, we have that $U(t), V(t) \in \mathcal{L}(H)$ and $X \in \mathcal{L}(H, K)$. A direct application of Lemma 7 allows us to see that $(UXV)(t) \in \mathcal{L}(H, K)$. The result of this corollary is proven after recalling the definition of $\mathcal{C}(I; \mathcal{L}(H))$ and $\mathcal{C}(I; \mathcal{L}(H, K))$ and recalling that the product of continuous functions is also continuous [1, Theorem 4.12]. \square

We conclude this section by seeing that the pointwise convergence of approximate semigroups $S_n(t) \in \mathcal{L}(H)$ also applies to when the semigroup acts on an operator belonging to $\mathcal{L}(H)$.

Lemma 8. *Let H be a separable Hilbert space and $S(t) \in \mathcal{L}(H)$ be a C_0 -semigroup. In addition let $\{S_n(t)\}_{n=1}^\infty \in \mathcal{L}(H)$ be an approximating sequence of C_0 -semigroups such that*

$$\lim_{n \rightarrow \infty} \|S(t)\phi - S_n(t)\phi\|_H = 0 \quad \forall \phi \in H.$$

Then we have that

$$(68) \quad \lim_{n \rightarrow \infty} \|(S(t) - S_n(t))X\|_{\mathcal{L}(H)} = 0$$

and

$$(69) \quad \lim_{n \rightarrow \infty} \|X(S(t) - S_n(t))^*\|_{\mathcal{L}(H)} = 0$$

for all $X \in \mathcal{L}(H)$ and $t \in \mathbb{R}_+$.

Proof. From the definition of the operator norm, we have that

$$\|(S(t) - S_n(t))X\|_{\mathcal{L}(H)} = \sup_{\phi \in H} \frac{\|S(t)X\phi - S_n(t)X\phi\|_H}{\|\phi\|_H}.$$

Since $X \in \mathcal{L}(H)$, the range of X is H . Therefore, it is clear that

$$\lim_{n \rightarrow \infty} \|S(t)X\phi - S_n(t)X\phi\|_H = 0$$

for all $\phi \in H$. It is then clear that (68) is satisfied. (69) follows by seeing that $((S(t) - S_n(t))X)^* = X^*(S(t) - S_n(t))^*$ and then applying (68). \square

APPENDIX B. ERROR ESTIMATES FOR FINITE ELEMENT APPROXIMATION OF SEMIGROUPS

In this section, we will present results on the error estimates for finite element methods for the heat and the weakly damped wave equation for when the solution operator of these equations are represented as a semigroup. We will begin by analyzing the heat semigroup approximation error and then move on to analyze the weakly damped wave semigroup approximation error. For simplicity, we will consider only the one-dimensional case to avoid the theoretical technicalities regarding geometric approximation. See [40] for a discussion on how curved domains can be theoretically addressed. We remark that the majority of the analysis presented here can likely be extended to the case where the domain of the partial differential equation is curved without serious issues. The notation used in §5.3 and §5.2 will be used in the following discussion.

B.1. Finite Element Approximation of the Thermal Semigroup. In this analysis, we will carry over the notation used in §5.2. Recall that we have defined $H := L^2(\Omega)$ for this test problem, where $\Omega := (0, 1)$. It is known that $A : \mathcal{D}(A) \rightarrow H$ generates an exponentially stable semigroup $S(t) \in \mathcal{L}(H)$ [25, §7.4]. Letting $z(t) = S(t)g$, for any $g \in H$, we have that $z \in H$ is the solution of the following equation

$$(70) \quad \begin{cases} \partial_t z(x, t) = \alpha \partial_x^2 z(x, t) - \beta z(x, t) & \text{in } \Omega \times I \\ \partial_x z = 0 & \text{on } \Gamma \\ z(x, 0) = g(x) & \text{in } \Omega. \end{cases}$$

Additionally, it is known that $A_n : \mathcal{D}(A_n) \rightarrow V_n^k$ also generates an exponentially stable semigroup $\widehat{S}_n(t) \in \mathcal{L}(V_n^k)$. We extend the domain and range of $\widehat{S}_n(t)$ through an injection and projection process, i.e., $S_n(t) := \iota_H \widehat{S}_n(t) \pi_n$. Letting $z_n(t) = S_n(t)g$, for any $g \in H$, we have that $z \in H$ is the solution of the following weak equation

$$\begin{cases} \frac{d}{dt} \langle z_n(t), r_n \rangle = -a(z_n(t), r_n) \\ \langle z_n(0), r_n \rangle = \langle g, r_n \rangle \end{cases}$$

for all $r_n \in V_n^k$ and $t \in I$.

With these notions defined, we are now ready to begin deriving an error bound on $S_n(t) \in \mathcal{L}(H)$. We start with the following necessary result.

Lemma 9. *Let $S(t) \in \mathcal{L}(H)$ be the parabolic semigroup generated by $A : \mathcal{D}(A) \rightarrow H$, then we have that*

$$\partial_x^k S(t)g = S(t)\partial_x^k g$$

for all $g \in H^k(\Omega)$.

Proof. Taking the k -th order partial derivative with respect to x on both sides of (71) results in

$$\begin{cases} \partial_x^k \partial_t z(x, t) = \alpha \partial_x^k \partial_x^2 z(x, t) - \beta z(x, t) & \text{in } \Omega \times I \\ \partial_x^k \partial_x z = 0 & \text{on } \Gamma \\ \partial_x^k z(x, 0) = \partial_x^k g(x) & \text{in } \Omega. \end{cases}$$

Switching the order of differentiation then allows us to see that

$$(71) \quad \begin{cases} \partial_t \xi(x, t) = \alpha \partial_x^2 \xi(x, t) - \beta \xi(x, t) & \text{in } \Omega \times I \\ \partial_x \xi(x, t) = 0 & \text{on } \Gamma \\ \xi(x, 0) = \partial_x^k g(x) & \text{in } \Omega, \end{cases}$$

where we have denoted $\xi(x, t) = \partial_x^k z(x, t)$. It then follows that

$$\partial_x^k S(t)g = \partial_x^k z(x, t) = \xi(x, t) = S(t)\partial_x^k g,$$

which proves the result of this Lemma. \square

We now move on to derive the main result of this analysis in the following.

Lemma 10. *Let $S(t) \in \mathcal{L}(H)$ be the parabolic semigroup generated by $A : \mathcal{D}(A) \rightarrow H$, and $S_n(t) \in \mathcal{L}(H)$ be its finite element approximation, then we have that there exists a constant $C \in \mathbb{R}_+$ so that*

$$\|S(t) - S_n(t)\|_{\mathcal{L}(H^{k+3}(\Omega), L^2(\Omega))} \leq Ch^{k+1} (1+t) e^{-\alpha t},$$

where $\alpha \in \mathbb{R}_+$ is the fundamental rate of dissipation of the parabolic semigroup and $k \in \mathbb{N}_+$ is the polynomial order of the finite element approximation space.

Proof. Following the analysis presented in [40, Theorem 7.1], we have that

$$\|z(t) - z_n(t)\|_{L^2(\Omega)} \leq Ch^{k+1} \left(\|z(t)\|_{H^{k+1}(\Omega)} + e^{-\alpha t} \|g\|_{H^{k+1}(\Omega)} + \int_0^t e^{\alpha(s-t)} \|\partial_s z(x, s)\|_{H^{k+1}(\Omega)} ds \right).$$

We begin by seeing that

$$\|z(t)\|_{H^{k+1}(\Omega)} = \|S(t)g\|_{H^{k+1}(\Omega)} \leq e^{-\alpha t} \|g\|_{H^{k+1}(\Omega)},$$

as a consequence of applying Lemma 9 to the definition of the $H^{k+1}(\Omega)$ norm. We then see that

$$\begin{aligned} \|\partial_s z(x, s)\|_{H^{k+1}(\Omega)} &= \|\alpha \partial_x^2 z - \beta z\|_{H^{k+1}(\Omega)} \\ &= \|\alpha \partial_x^2 S(s)g - \beta S(s)g\|_{H^{k+1}(\Omega)} \\ &\leq Ce^{-\alpha s} \|g\|_{H^{k+3}(\Omega)}, \end{aligned}$$

which follows again from applying Lemma 9, and equation (71). It then follows that

$$\|z(t) - z_n(t)\|_{L^2(\Omega)} \leq Ch^{k+1} (1+t) e^{-\alpha t} \|g\|_{H^{k+3}(\Omega)}.$$

We then arrive at the result of this Lemma by recalling that $z(t) = S(t)g$ and that $z_n(t) = S_n(t)g$, and then finally applying the definition of the operator norm. \square

We have shown above that the classical finite element error estimate for parabolic equations can be used to derive uniform error estimates for the approximate semigroup in the operator norm. We will derive a similar estimate for the approximation of hyperbolic semigroups in the following subsection.

B.2. Finite Element Approximation of the Weakly Damped Wave Semigroup. Here, we present results pertaining to the finite element approximation error estimates for the weakly damped wave semigroup. The notation used here will be carried over from §5.3. Recall that we have set $H := H^1(\Omega) \times L^2(\Omega)$ with $\Omega : (0, 1)$. It is known that $\mathcal{A} : \mathcal{D}(\mathcal{A}) \rightarrow H$ generates an exponentially stable semigroup [19] which we denote $S(t) \in \mathcal{L}(H)$. Letting $\mathbf{z} = S(t)\mathbf{q}$ for any $\mathbf{q} \in H$, we have that $\mathbf{z}(t) = [v(t), w(t)]$ is the solution of the following weakly damped wave equation

$$(72) \quad \begin{cases} \partial_t v(x, t) = w & \text{in } \Omega \times \mathbb{R}_+ \\ \partial_t w(x, t) = c^2 \partial_x^2 v(x, t) - \gamma w(x, t) & \text{in } \Omega \times \mathbb{R}_+ \\ v(x, t) = 0 & \text{on } \Gamma \times \mathbb{R}_+ \\ v(x, 0) = q(x) & \text{in } \Omega \\ w(x, 0) = r(x) & \text{in } \Omega, \end{cases}$$

where we have denoted $\mathbf{q} := [q, r]$. Additionally, it is known that $A_n : \mathcal{D}(A_n) \rightarrow H_n$ also generates an exponentially stable semigroup $\widehat{S}_n(t) \in \mathcal{L}(H_n)$. The domain and range of $\widehat{S}_n(t)$ can then be extended through an injection and projection process, i.e., $S_n(t) := \iota_H \widehat{S}_n(t) \pi_n$. Setting $\mathbf{z}_n = S_n(t)\mathbf{q}$, for any $\mathbf{q} \in H$, we have that $\mathbf{z}_n \in H$ satisfies the following set of weak equations

$$\begin{cases} \frac{d}{dt} \langle v_n(t), \phi_n \rangle = \langle w_n, \phi_n \rangle & \forall \phi_n \in V_n^k \\ \frac{d}{dt} \langle w_n(t), \psi_n \rangle = -a(v_n, \psi_n) - \gamma \langle w_n, \psi_n \rangle & \forall \psi_n \in V_n^k \\ \langle v_n(0), \phi_n \rangle = \langle q, \phi_n \rangle & \forall \phi_n \in V_n^k \\ \langle w_n(0), \psi_n \rangle = \langle r, \psi_n \rangle & \forall \psi_n \in V_n^k \end{cases}$$

for all $t \in \mathbb{R}_+$. We now define the following differential operator for notational convenience

$$\mathbf{D}_{j,k} \mathbf{z} := \begin{bmatrix} \partial_x^j & 0 \\ 0 & \partial_x^k \end{bmatrix} \begin{bmatrix} v(x) \\ w(x) \end{bmatrix}$$

for any $\mathbf{z} := [v(x), w(x)]^T$ with $v(x)$ and $w(x)$ possessing at least l and m weak derivatives respectively. We now move forward to derive the first result of this section.

Lemma 11. *Let $S(t) \in \mathcal{L}(H)$ be the weakly damped wave semigroup, then we have that*

$$(73) \quad \mathbf{D}_{k,k} S(t) \mathbf{q} := S(t) \mathbf{D}_{k,k} \mathbf{q}$$

for all $\mathbf{q} \in H^{k+1}(\Omega) \times H^k(\Omega)$.

Proof. First, we see that $S(t) \mathbf{D}_{k,k} \mathbf{q}$ is well defined since $\mathbf{D}_{k,k} \mathbf{q} \in H$ for any $\mathbf{q} \in H^{k+1}(\Omega) \times H^k(\Omega)$ from the definition of Sobolev spaces. This is necessary since $S(t) \in \mathcal{L}(H)$. The remainder of the proof follows using the same argument as in the proof of Lemma 9.

Next, taking the k -th order partial derivative with respect to x on both sides of (72) results in

$$\begin{cases} \partial_t \partial_x^k v(x, t) = \partial_x^k w & \text{in } \Omega \times \mathbb{R}_+ \\ \partial_t \partial_x^k w(x, t) = c^2 \partial_x^2 \partial_x^k v(x, t) - \gamma \partial_x^k w(x, t) & \text{in } \Omega \times \mathbb{R}_+ \\ \partial_x^k v(x, t) = 0 & \text{on } \Gamma \times \mathbb{R}_+ \\ \partial_x^k v(x, 0) = \partial_x^k q(x) & \text{in } \Omega \\ \partial_x^k w(x, 0) = \partial_x^k r(x) & \text{in } \Omega, \end{cases}$$

after interchanging the order of partial differentiation. This then allows to see that

$$S(t) \mathbf{D}_{k,k} \mathbf{q} = \mathbf{D}_{k,k} \mathbf{z}(t) = \mathbf{D}_{k,k} S(t) \mathbf{q}$$

for any $\mathbf{q} \in H^{k+1}(\Omega) \times H^k(\Omega)$. This concludes the proof. \square

We now move on to derive an error estimate on the finite element approximation of the weakly damped wave semigroup in the following.

Lemma 12. *Let $S(t) \in \mathcal{L}(H)$ be the weakly damped wave semigroup generated by $\mathcal{A} : \mathcal{D}(\mathcal{A}) \rightarrow H$, and $S_n(t) \in \mathcal{L}(H)$ be its finite element approximation, then we have that there exists a constant $C \in \mathbb{R}_+$ so that*

$$\|S(t) - S_n(t)\|_{\mathcal{L}(V, H^1(\Omega) \times L^2(\Omega))} \leq Ch^k,$$

where $\alpha \in \mathbb{R}_+$ is the fundamental rate of dissipation of the parabolic semigroup and $V := H^{k+3}(\Omega) \cap H^1(\Omega) \times H^{k+2}(\Omega)$.

Proof. In this analysis, we take $\mathbf{q} \in H^{k+3}(\Omega) \times H^{k+2}(\Omega)$ as any arbitrary vector and $\mathbf{z}(t) = S(t)\mathbf{q}$ with $\mathbf{z}(t) = [v(t), w(t)]$. Lemma 11 then implies that $\mathbf{z}(t) \in H^{k+3}(\Omega) \times H^{k+2}(\Omega)$.

From the analysis presented in [23], we have that

$$\begin{aligned} \|v - v_n\|_{H^1(\Omega)} + \|w - w_n\|_{L^2(\Omega)} &\leq Ch^k \left(\|v\|_{H^{k+1}(\Omega)} + \|w\|_{H^{k+1}(\Omega)} \right) \\ &\quad + C_\gamma h^{k+1} \int_0^t \|\partial_s w(s)\|_{H^{k+1}(\Omega)} ds. \end{aligned}$$

Seeing that $\partial_t w = c^2 \partial_x^2 v - \gamma w$, we observe that

$$\|\partial_s w(s)\|_{H^{k+1}(\Omega)} \leq C \left(\|v\|_{H^{k+3}(\Omega)} + \|w\|_{H^{k+2}(\Omega)} \right),$$

after applying the embedding inequality $\|v\|_{H^{k+1}(\Omega)} \leq \|v\|_{H^{k+2}(\Omega)}$. Applying Lemma 11 and the exponential stability of $S(t) \in \mathcal{L}(H)$ allows us to see that

$$\|v\|_{H^{k+3}(\Omega)} + \|w\|_{H^{k+2}(\Omega)} \leq C e^{-\alpha t} \left(\|p\|_{H^{k+3}(\Omega)} + \|q\|_{H^{k+2}(\Omega)} \right).$$

Putting this all together, we observe that

$$\|v - v_n\|_{H^1(\Omega)} + \|w - w_n\|_{L^2(\Omega)} \leq C h^k \left(\|p\|_{H^{k+3}(\Omega)} + \|q\|_{H^{k+2}(\Omega)} \right).$$

We conclude the proof by seeing that

$$\|S(t)\mathbf{q} - S_n(t)\mathbf{q}\|_{H^1(\Omega) \times L^2(\Omega)} = \|v - v_n\|_{H^1(\Omega)} + \|w - w_n\|_{L^2(\Omega)}$$

and applying the definition of the operator norm. □





FIGURE 2. Approximation error in $\|\kappa - \kappa_n\|_H$ for the finite element approximation of the weakly damped wave control system, where $H = H_0^1(\Omega) \times L^2(\Omega)$ in the top plot and $H = L^2(\Omega) \times L^2(\Omega)$ in the bottom figure.