

A quantum neural network framework for scalable quantum circuit approximation of unitary matrices ^{*}

Rohit Sarma Sarkar[†] and Bibhas Adhikari^{‡§}

Abstract. In this paper, we develop a Lie group theoretic approach for parametric representation of unitary matrices. This leads to develop a quantum neural network framework for quantum circuit approximation of multi-qubit unitary gates. Layers of the neural networks are defined by product of exponential of certain elements of the Standard Recursive Block Basis, which we introduce as an alternative to Pauli string basis for matrix algebra of complex matrices of order 2^n . The recursive construction of the neural networks implies that the quantum circuit approximation is scalable i.e. quantum circuit for an $(n + 1)$ -qubit unitary can be constructed from the circuit of n -qubit system by adding a few CNOT gates and single-qubit gates.

Key words. Quantum neural network, parametrized quantum circuit, quantum compilation, multi-controlled rotation gates, Lie algebra, special unitary matrices

1 Introduction

Decomposing dense unitary matrices into product of sparse unitaries is a subject of interest for mathematicians, physicists and computer scientists. Specifically in quantum computing, the problem is reiterated in the form of constructing any n -qubit quantum gate or a circuit using only one and two qubit gates i.e. writing a $2^n \times 2^n$ unitary matrix as a product of permutations and Kronecker products of rotation gates belonging to $SU(2)$, the *special linear group* of 2×2 complex matrices. This problem is often referred to as *quantum compilation problem* [16, 35].

The existence of such a construction is validated by the Solovay-Kitaev algorithm, which shows that any n -qubit quantum circuit can be approximated using a sequence of just one qubit rotation gates and CNOT gates. Hence, these gates form *universal model of computation* and can represent unitaries for multi-qubit systems [16, 2]. However, in Solovay-Kitaev algorithm, the approximation of unitary matrices and length of the sequence are directly correlated, which shows that longer sequences yield better approximations. Hence, one needs to do an exhaustive search over sequences of a particular length in order to find the minimal distance from the given unitary matrix, known as Solovay-Kitaev approximation algorithms [23]. Since the search covers only a sparse region of the entire space of possible approximation sequences, several methods are proposed for optimization of the Solovay-Kitaev algorithm that finds application in *fault-tolerant quantum computation* [36, 52].

^{*}This is an extended version of a conference paper titled “Scalable approximation of n -qubit unitaries”, IEEE International conference on Quantum Computing and Engineering (QCE 23).

[†]Department of Mathematics, IIT Kharagpur, India, E-mail: rohit15sarkar@yahoo.com

[‡]Corresponding author, Department of Mathematics, Indian Institute of Technology Kharagpur, bibhas@maths.iitkgp.ac.in, bibhas.adhikari@gmail.com

[§]The author currently works at Fujitsu Research of America, Inc., Santa Clara, CA, USA

There have been advancements for efficiently approximating n -qubit unitaries using various methods such as recursive CS decomposition and Quantum Shannon-decomposition [31, 26]. However, the algorithms developed, though aimed at minimizing number of CNOT and one-qubit gates, rely on numerical algorithms to find SVD and eigen-decomposition of a matrix, which are itself challenging computational problems for large matrices. Recently, an optimization based viewpoint for the compilation problem has generated a lot of interest [28, 27, 32]. In this approach, a unitary matrix is found that can be realized in hardware with constraints that is the closest to a target unitary with respect to a metric. Various cost functions are defined in these optimization-based approaches to achieve a good implementation of the target unitary. For example, optimizing the structure (i.e., where to place a CNOT gate), optimizing the rotation angles of the rotation gates, optimizing the number of CNOT count etc. after writing a parametric representation using matrix decomposition of the target unitary [43, 42].

Other methods like QFAST [50, 51] makes use of geometry of the unitary manifold by approximating a target unitary with help of the tangent space around the identity matrix. It is evident that the Pauli strings (Kronecker products of Pauli matrices) form a basis for the vector space of all $2^n \times 2^n$ complex matrices $M_{2^n}(\mathbb{C})$. Further the Pauli strings are Hermitian and traceless, making them basis elements that are ι -times the Pauli strings for the Lie algebra of the unitary manifold, where $\iota = \sqrt{-1}$. Hence, in this method one can approximate a $2^n \times 2^n$ unitary matrix using exponential of scaling of Pauli strings.

Similar to QFAST, in this paper, we present an optimization-based approach to approximate a given unitary matrix comparing with it with a generic parametrized unitary matrix. This leads to the development of a quantum neural network framework for implementing n -qubit unitaries using quantum circuits of CNOT and one-qubit gates. To obtain a generic parametrized representation for unitaries, a new Hermitian unitary basis for matrix algebra of $d \times d$ complex matrices is introduced, with the aim of expressing any unitary through product of exponential of ι -times the proposed basis elements. The new bases have Hermitian and unitary elements, with diagonal or 2-sparse matrices, alike the Pauli string basis. The proposed bases have an advantage over the Pauli string basis as the method of constructing such basis elements is recursive. Further the matrices are permutation similar to block diagonal matrices and making it easier to compute the exponential of the basis elements.

First, we introduce a recursive approach for construction of a basis comprises of Hermitian unitary 1-sparse matrices for the matrix algebra of $d \times d$ complex matrices, $d > 2$. For $d = 2$, the basis is the Pauli basis, and hence the proposed construction may be regarded as a generalization of the Pauli basis of 2×2 complex matrices. Then altering some of the basis elements, replacing them by Pauli strings formed by Kronecker product of the identity matrix of order 2 and Pauli Z matrix of order 2, we propose a Hermitian unitary trace-less basis for algebra of $2^n \times 2^n$ complex matrices. We call this basis as *Standard Recursive Block Basis* (SRBB), inspired by the recursive construction of the basis elements with have certain block structure. Then we provide a direct computable expression for the exponential of these basis elements, which is further employed for exact synthesis of any 2-level unitary matrix (a matrix obtained from the identity matrix by replacing a 2×2 principal submatrix with a unitary block) of order 2^n and block-unitary matrices that correspond to multi-controlled rotation gates. It is needless to mention that any unitary matrix can be written as a product of 2-level matrices [33].

Then utilizing the obtained basis for the Lie algebra of skew-Hermitian matrices and considering the unitary matrices as its corresponding Lie group, we develop algorithms for approximation of any unitary matrix as product of exponential of the basis elements, which form one-parameter subgroup of unitary matrices. This formulation of the approximation can be interpreted as a quan-

tum neural network, in which the unitary matrices represent the quantum evolution of an n -qubit system that can be compiled using quantum circuits of parametrized elementary gates for practical implementation in *Noisy Intermediate Scale Quantum* (NISQ) computers. Consequently, we formulate the optimization problem of estimating the values of these parameters for approximation of any target unitary matrix, very much like variational quantum algorithms (VQAs). The objective function of the optimization problem is defined as the Frobenius distance of the parametrized unitary approximation and the target unitary.

It may be emphasized here that due to the exponential dimension of the concerned matrices, which increases with n , (which corresponds to the n -qubit system), it is a classically hard optimization problem for exponentially large number of parameters, in the generic case, when all the basis elements are employed to approximate the target unitary. Obviously, several basis elements need not be considered for the approximation when the target unitary is sparse and has certain sparsity pattern. Besides, the execution time may be reduced for small number of parameters, when standard classical optimization algorithms are used. The classical optimization algorithms, such as Nelder-Mead and Powell’s method are usually applied as classical optimization algorithms for VQAs. In this paper, we employ Nelder-Mead method to perform the simulation for various target unitaries which appear in quantum computation. Note that the improvement of the execution time in compiling standard quantum gates using this approach in Table 1 than the same using all the basis elements in our previous simulation reported in ¹.

It may further be noted that ordering of the basis elements play a crucial role for the approximation which we address while constructing quantum circuits for unitaries that are product of exponential of certain basis elements. Indeed, we identify and determine the basis elements such that products of their exponential have suitable existing quantum circuit representation such as multi-controlled rotation gates. We also develop quantum circuits for exponential of basis elements that are diagonal matrices, and of the permutations which are product of certain type of transpositions that arise during the approximation. Thus we develop a framework of a multi layered quantum neural network defined by quantum circuit of parametrized rotation gates and CNOT gates for approximating a target unitary matrix, applicable for implementation in NISQ computers. Indeed, we decide on the choice of the ordering of the basis elements such that it reduces the number of CNOT gates in the quantum circuit implementation of the approximation algorithm.

Moreover, we show that the proposed recursive approach for the basis has the advantage that the proposed quantum circuit representation of the approximation for n -qubit systems is scalable. Thus, given the circuit for n -qubits, the circuit for $(n + 1)$ -qubits can be implemented using the current circuit with the addition of new CNOT gates and one-qubit rotation gates. We prove that the proposed quantum circuit of one layer of approximation has the use of at most $2 \cdot 4^n + (n - 5)2^n$ CNOT gates, and at most $\frac{3}{2} \cdot 4^n - \frac{5}{2} \cdot 2^n + 1$ one-qubit rotation gates corresponding to Y and Z axes.

We examine various scenarios to evaluate the effectiveness of our approximation algorithms in approximating standard and random unitary matrices for 2-qubit, 3-qubit, and 4-qubit systems, and unitary matrices of order $d = 3, 5$. Our results indicate that the proposed algorithms perform better when the target unitaries are sparse when only one layer of approximation is used, and the error of the approximation reduces with the increase of number of layers for the approximation. It is evident that the performance of the algorithm is influenced by the initial parameter values and the optimization technique utilized to obtain the optimal parameter values. Thus we randomize for the choice of the initialization of the optimization algorithm. Lastly, we present an algorithm

¹“Scalable approximation of n -qubit unitaries”, IEEE International conference on Quantum Computing and Engineering (QCE 23)

that enables the implementation of the proposed quantum circuits from n -qubit to $(n + 1)$ -qubit systems.

The remainder of the paper is structured as follows. In Section 2, recursive methods for construction of a basis consists of Hermitian unitary matrices for complex matrices of size $d \times d$ is given, which is further modified to obtain a suitable basis for algebra of $2^n \times 2^n$ complex matrices. In Section 3, we propose a Lie group theoretic approach for approximation of unitary matrices through proposed basis elements. Exact representation of 2-level matrices and unitary matrices corresponding to multi-controlled rotation gates through product exponential of certain proposed basis elements are also given. Section 4 presents methods for approximating unitary matrices of order 2^n i.e. n -qubit unitaries through the elements of SRBB are described. A quantum neural network framework for developing a generic parametric representation of n -qubit unitaries is provided via an optimization-based approximation algorithm. Numerical simulation results for examples of Haar random unitaries are given. In Section 5, a scalable quantum circuit for the proposed approximation algorithm is established, providing a quantum circuit representation and implementation of n -qubit unitaries. Finally, the paper concludes with a discussion of future research directions.

2 Recursive construction of Hermitian unitary basis

In this section we provide a recursive method for generation of a basis consisting of Hermitian, unitary matrices for the matrix algebra of $d \times d$, $d \geq 3$ matrices. Then this basis is employed to define a parametric representation of unitary matrices of order $d \times d$. We denote the identity matrix of order k as I_k , $k \geq 0$ where $I_1 = [1]$, and I_0 is just void which means to ignore the index from the construction. We denote the Pauli basis by σ whose elements are given by

$$\sigma_1 = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}, \sigma_2 = \begin{bmatrix} 0 & -i \\ i & 0 \end{bmatrix}, \sigma_3 = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}, \sigma_4 = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix},$$

called Pauli matrices. Then we define a new basis of Hermitian unitary trace-less matrices for the algebra of 2^n complex matrices by changing some of the elements of the former basis.

2.1 A recursive construction of Hermitian unitary basis for $d \times d$ complex matrices

The following theorem describes a recursive approach for construction of Hermitian unitary basis of $\mathbb{C}^{d \times d}$, with $d^2 - 1$ of them having trace zero when d is even. The proof of the theorem is given in the Appendix.

Theorem 2.1. *Let $\mathcal{B}^{(d)} = \{B_j^{(d)} : 1 \leq j \leq d^2\}$, $d > 2$ denote the desired ordered basis for the matrix algebra of $d \times d$ complex matrices. Then setting $\mathcal{B}^{(2)}$ as the Pauli basis, the elements of*

$\mathcal{B}^{(d)}$ can be constructed from the elements of $\mathcal{B}^{(d-1)}$ using the following recursive procedure

$$B_j^{(d)} = \begin{cases} \left[\begin{array}{c|c} B_j^{(d-1)} & 0 \\ \hline 0 & (-1)^{d-1} \end{array} \right]; & \text{if } j \in \{1, \dots, (d-1)^2 - 1\}, \\ P_{(k,d-1)} \left[\begin{array}{c|c} D & 0 \\ \hline 0 & \sigma_1 \end{array} \right] P_{(k,d-1)}; & \text{if } j = (d-1)^2 + (k-1), k \in \{1, \dots, d-1\} \\ P_{(k,d-1)} \left[\begin{array}{c|c} D & 0 \\ \hline 0 & \sigma_2 \end{array} \right] P_{(k,d-1)}; & \text{if } j = (d-1)^2 + (d-1) + (k-1), k \in \{1, \dots, d-1\} \\ \left[\begin{array}{c|c} I_{\lfloor d/2 \rfloor + 1} & 0 \\ \hline 0 & -I_{\lfloor d/2 \rfloor} \end{array} \right]; & \text{if } j = d^2 - 1 \text{ and } d \text{ is odd} \\ \left[\begin{array}{c|c} \Sigma & 0 \\ \hline 0 & \sigma_3 \end{array} \right]; & \text{if } j = d^2 - 1 \text{ and } d \text{ is even} \\ I_d & \text{if } j = d^2 \end{cases},$$

where $P_{k,(d-1)}$ is the permutation matrix of order $d \times d$ corresponding to the 2-cycle $(k, d-1)$, $D = \text{diag}\{d_l : 1 \leq l \leq d-2\}$, $d_l = (-1)^{l-1}$, and $\Sigma = \begin{bmatrix} I_{\lfloor d/2 \rfloor - 1} & 0 \\ 0 & -I_{\lfloor d/2 \rfloor - 1} \end{bmatrix}$. Besides,

$$\text{Tr}(B_j^{(d)}) = \begin{cases} 1 & \text{if } d \text{ is odd} \\ 0 & \text{if } d \text{ is even,} \end{cases},$$

$1 \leq j \leq d^2 - 1$, $(B_j^{(d)})^2 = I_d$, and $\{B_j^{(d)} : 1 \leq j \leq d^2 - 1\}$ forms a basis for $\mathfrak{su}(d)$ when d is even. The basis elements that are diagonal matrices are given by $B_j^{(n)}$ where $j = m^2 - 1$, $2 \leq m \leq d$ and $B_{d^2}^{(d)} = I_d$.

Remark 2.2. (a) Note that any of the basis elements described by the above theorem that is a non diagonal matrix, is one of the form

$$P \begin{bmatrix} D_1 & 0 & 0 \\ 0 & \sigma & 0 \\ 0 & 0 & D_2 \end{bmatrix} P, \quad P \begin{bmatrix} \sigma & 0 \\ 0 & D \end{bmatrix} P, \quad P \begin{bmatrix} D & 0 \\ 0 & \sigma \end{bmatrix} P$$

where D, D_1, D_2 are diagonal matrices with entries from $\{1, -1\}$, $\sigma \in \{\sigma_1, \sigma_2\}$ and P is a 2-cycle. Thus the basis elements are unitary, Hermitian, and 1-sparse matrices (alike Pauli string basis elements).

(b) Then exponential of these matrices are of the form

$$P \begin{bmatrix} \exp(D_1) & 0 & \\ 0 & \exp(\sigma) & 0 \\ 0 & 0 & \exp(D_2) \end{bmatrix} P, \quad P \begin{bmatrix} \exp(\sigma) & 0 \\ 0 & \exp(D) \end{bmatrix} P, \quad P \begin{bmatrix} \exp(D) & 0 \\ 0 & \exp(\sigma) \end{bmatrix} P.$$

(c) The indices j for which the permutation matrix $P = I_d$, and the basis elements are of the form

$$\begin{bmatrix} D_1 & 0 & 0 \\ 0 & \sigma & 0 \\ 0 & 0 & D_2 \end{bmatrix}, \quad \begin{bmatrix} \sigma & 0 \\ 0 & D \end{bmatrix} \text{ or } \begin{bmatrix} D & 0 \\ 0 & \sigma \end{bmatrix}$$

with $\sigma = \sigma_1$ when $j \in \mathcal{J}_{\sigma_1} = \{(j-1)^2 | 2 \leq l \leq d\}$, and $\sigma = \sigma_2$ when $j \in \mathcal{J}_{\sigma_2} = \{l^2 - l | 2 \leq l \leq d\}$.

- (d) The basis elements with indices $j \in \mathcal{J} = \{l^2 - 1 : 2 \leq l \leq d\} \cup \{d^2\}$ are diagonal matrices, which are orthogonal to each other. Obviously, $|\mathcal{J}| = d - 1$.

2.1.1 Hermitian unitary basis for $2^n \times 2^n$ complex matrices

Now we present another Hermitian unitary basis of $\mathbb{C}^{2^n \times 2^n}$ which we will play a crucial role in the remainder of the paper. The idea is that we now replace the diagonal basis elements of $\mathcal{B}^{(2^n)}$ described in Theorem 2.1 by another set of diagonal matrices keeping invariance of the linearly independent property of the basis. First note that the set of matrices

$$\mathcal{D}_{IZ} = \{A_1 \otimes \dots \otimes A_n : A_j \in \{I_2, \sigma_3\}, 1 \leq j \leq n\} \quad (1)$$

is a set of 2^n linearly independent diagonal matrices with trace zero except when $A_j = I_2$ for all j i.e. $A_1 \otimes \dots \otimes A_n = I_{2^n}$. We call this as the **Standard Recursive Block Basis** (SRBB).

Corollary 2.3. (SRBB) Let $\mathcal{B}^{(2^n)} = \{B_j^{(2^n)} : 1 \leq j \leq 2^{2^n}\}$ denote the basis described in Theorem 2.1, and \mathcal{D}_{IZ} is given by equation (1). Then the set $\mathcal{U}^{(2^n)} = \{U_j^{(2^n)} : 1 \leq j \leq 2^{2^n}\}$, where

$$U_j^{(2^n)} = \begin{cases} D \in \mathcal{D}_{IZ} & \text{if } j \in \mathcal{J} = \{l^2 - 1 : 2 \leq l \leq 2^n\} \cup \{2^{2^n}\} \\ B_j^{(2^n)}, & \text{otherwise} \end{cases}$$

forms a Hermitian unitary basis for $\mathbb{C}^{2^n \times 2^n}$. Besides, $\text{Tr}(U_j^{(2^n)}) = 0$ when $U_j^{(2^n)} \neq I_{2^n}$.

Observe that the non-diagonal basis matrices as defined in Corollary 2.3 are of two types as described below.

$$[U]_{kl} = \begin{cases} (-1)^{l-1} & \text{if } k = l \notin \{p, q\} \\ 1 & \text{if } k = p, l = q \\ 1 & \text{if } k = q, l = p \\ 0 & \text{otherwise} \end{cases} \quad \text{and} \quad [U]_{kl} = \begin{cases} (-1)^{l-1} & \text{if } k = l \notin \{p, q\} \\ -i & \text{if } k = p, l = q \\ i & \text{if } k = q, l = p \\ 0 & \text{otherwise.} \end{cases} \quad (2)$$

$1 \leq k, l \leq 2^n$.

Now we prove certain results which will be used in sequel. First we introduce a function which provides an ordering of the diagonal basis elements of $\mathcal{U}^{(2^n)}$. From now onward, we denote $A_1 \otimes A_2 \otimes \dots \otimes A_m = \otimes_{i=1}^m A_i$ for some matrices or vectors A_i . If $A_i = A$ for all i then we denote $\otimes_{i=1}^m A_i = \otimes^m A$.

Definition 2.4. Define $\chi : \{I, Z\} \rightarrow \{0, 1\}$ such that $\chi(I) = 0, \chi(Z) = 1$. For any positive integer m , define $\chi_m : \{\otimes_{i=1}^m A_i \mid A_i \in \{I, Z\}, 1 \leq i \leq m\} \rightarrow \{0, 1, \dots, 2^m - 1\}$ such that

$$\chi_m(\otimes_{i=1}^m A_i) = \sum_{i=1}^m 2^{i-1} \chi(A_i).$$

The above definition is inspired from the fact that for any matrix $A = [A_0 \ A_1] \in \mathbb{C}^{2 \times 2}$, the columns of $\otimes^n A$ are ordered according to the lexicographic ordering of binary strings, where the bits 0 and 1 represent the first column A_0 and the second column A_1 of A . The k -th column of

$\otimes^n A$ corresponds to the binary string representation of k , say $k_1 k_2 \dots k_n, k_j \in \{0, 1\}$, and hence it is given by $A_{k_1} \otimes A_{k_2} \otimes \dots \otimes A_{k_n}$, $0 \leq k \leq 2^n - 1$. In particular, for the Hadamard matrix H_2 , we can write

$$H_2 = \frac{1}{\sqrt{2}} [\text{diag}(I_2) \quad \text{diag}(\sigma_3)].$$

Hence the k -th column of $2^{n/2} H_{2^n} := 2^{n/2} (\otimes^n H_2)$ is given by $\text{diag}(A_{k_1}) \otimes \text{diag}(A_{k_2}) \otimes \dots \otimes \text{diag}(A_{k_n}) = \text{diag}(A_{k_1} \otimes A_{k_2} \otimes \dots \otimes A_{k_n})$, where $k = k_1 k_2 \dots k_n$ is the binary representation of k and $A_{k_l} \in \{I_2, \sigma_3\}$, $1 \leq l \leq n$. Thus there is a one-to-one correspondence between the columns of $2^{n/2} H_{2^n}$ and the diagonal basis elements of $\mathcal{U}^{(2^n)}$, through the diag operation.

Now we provide parametric representations of unitary matrices of order d .

3 Lie group theoretic approach for parametric representation of unitary matrices

It is well-known that the set of all unitary matrices of order d , denoted by $\mathbf{U}(d)$ forms a Lie group and the corresponding Lie algebra is the real vector space of all skew-Hermitian matrices of order d which we denote as $\mathfrak{u}(d)$. A classification of unitary matrices is that: any unitary matrix can be expressed as exponential of a skew-Hermitian matrix i.e. the map $\exp : \mathfrak{u}(d) \rightarrow \mathbf{U}(d)$ is surjective [Theorem 3.2, [11]]. Now we develop a parametric representation of unitary matrices of order d .

We recall from [Chapter 2, [44]] that if $\{X_1, \dots, X_k\}$ is a basis of the Lie algebra of a Lie group G then for some $\theta > 0$, the map

$$\psi : (\theta_1, \theta_2, \dots, \theta_k) \mapsto \exp(\theta_1 X_1) \exp(\theta_2 X_2) \dots \exp(\theta_k X_k)$$

from \mathbb{R}^k into G is an analytic diffeomorphism of the cube $I_\theta^k = \{(\theta_1, \dots, \theta_k) : |\theta_j| < \theta, 1 \leq j \leq k\}$ of \mathbb{R}^k onto an open subset U of G containing the identity element I of G . If x_1, \dots, x_k are the analytic functions on U such that the map $y \mapsto (x_1(y), \dots, x_k(y))$ inverts ψ , then for $1 \leq j \leq k$,

$$x_j(\exp \theta_1 X_1, \exp \theta_2 X_2, \dots, \exp \theta_k X_k) = \theta_j, (\theta_1, \dots, \theta_k) \in I_\theta^k.$$

Then x_1, \dots, x_k are called the canonical coordinates of the second kind around I with respect to the basis $\{X_1, \dots, X_k\}$.

Setting $G = \mathbf{U}(d)$, the (real) dimension of $\mathfrak{u}(d)$ is d^2 and if $\{B_j^{(d)} : 1 \leq j \leq d^2\}$ denotes a basis of $\mathfrak{u}(d)$ then we have the following theorem.

Theorem 3.1. *There exists a $\theta > 0$ such that $\left\{ \prod_{j=1}^{d^2} \exp(i\theta_j B_j^{(d)}) : (\theta_1, \dots, \theta_{d^2}) \in I_\theta^{d^2} \right\}$ generates $\mathbf{U}(d)$.*

Proof: With the standard subspace topology of the matrix algebra of complex matrices, $\mathbf{U}(d)$ is a connected topological space. Then there exists $\theta > 0$ such that the map $\psi : (\theta_1, \dots, \theta_{d^2}) \mapsto \exp(\theta_1 B_1^{(d)}), \dots, \exp(\theta_{d^2} B_{d^2}^{(d)})$ is a diffeomorphism from $I_\theta^{d^2}$ onto an open neighborhood U of \mathbf{U} containing the identity matrix. Since \mathbf{U} is connected, then the desired result follows from Corollary 2.9, [21]. \square

Now we have the following proposition.

Proposition 3.2. *Let $\mathcal{B}^{(d)} = \{B_j^{(d)} : 1 \leq j \leq d^2\}$ denote a basis of Hermitian unitary matrices for $\mathbb{C}^{d \times d}$ as described in Theorem 2.1 or Corollary 2.3. Then*

$$\exp(\pm i\theta_j B_j^{(d)}) = \cos \theta_j I_d \pm i \sin \theta_j B_j^{(d)},$$

for any $\theta_j \in \mathbb{R}$, $1 \leq j \leq d^2$.

Proof: The proof follows from the fact that $\exp(\pm i t \sigma_j) = \cos t \pm i \sin t \sigma_j$, $j = 0, 1, 2, 3$, $t \in \mathbb{R}$, and $P_{(k,d-1)}$ is a symmetric unitary matrix, as described in Theorem 2.1 and Corollary 2.3. \square

Thus it follows from Proposition 3.2 that exponential of basis elements given in Corollary 2.3 is either a 2-level matrix or a diagonal matrix since the basis elements $U_j^{(2^n)}$, $1 \leq j \leq 2^n$ are either a 2-level or a diagonal matrix. As mentioned above, it is a well-known result that any unitary matrix can always be written as a product of 2-level matrices [33]. On the other hand, due to Theorem 3.1 and Proposition 3.2, it is clear that as a byproduct of the construction of the proposed basis, it provides such a decomposition.

3.1 Exact parametric representation of certain unitary matrices

In the next section we provide parametric representation of certain unitaries for n -qubit systems by employing the basis $\mathbf{U}^{(d)}$, $d = 2^n$ proposed in Corollary 2.3.

Theorem 3.3. *Any 2-level unitary matrix $U \in \text{SU}(2^n)$ can be represented as*

$$\left(\prod_{j \in \mathcal{J}} \exp \left(i t_j U_j^{(2^n)} \right) \right) \exp \left(i t_l U_l^{(2^n)} \right) \left(\prod_{j \in \mathcal{J}} \exp \left(i t'_j U_j^{(2^n)} \right) \right),$$

where $l = (d-1)^2 + d - 1, \dots, (d-1)^2 + 2(d-1) - 1$ for some $d \in \{2, \dots, 2^n\}$, $U_l^{(2^n)}, U_j^{(2^n)} \in \mathbf{U}^{(2^n)}$, and $t_j, t'_j \in \mathbb{R}$, $j \in \mathcal{J}$.

Remark 3.4. (a) It is well known that any matrix $U \in \text{SU}(2)$ has a ZYZ decomposition $U = \exp(i\alpha\sigma_3) \exp(i\beta\sigma_2) \exp(i\gamma\sigma_3)$. The Theorem 3.3 provides a ZYZ like decomposition for matrices in $\text{SU}(2^n)$. Indeed, the matrix $\prod_{j \in \mathcal{J}} \exp \left(i t_j U_j^{(2^n)} \right)$ and $\prod_{j \in \mathcal{J}} \exp \left(i t'_j U_j^{(2^n)} \right)$ act as the diagonal matrix which represents for the ‘Z’ defined by σ_3 , and the matrix $\exp \left(i t_l U_l^{(2^n)} \right)$ and as ‘Y’ which is defined by σ_2 .

(b) Note that the proof is valid for 2-level special unitary matrix of any order d . We write it for $d = 2^n$ just to correspond to a quantum circuit representation of such matrices for n -qubit systems.

Then we have the following corollary.

Corollary 3.5. *Any 2-level unitary matrix $U \in \text{U}(2^n)$ can be represented using*


$$e^{i\alpha} \left(\prod_{j \in \mathcal{J}} \exp \left(i t_j U_j^{(2^n)} \right) \right) \exp \left(i t_l U_l^{(2^n)} \right) \left(\prod_{j \in \mathcal{J}} \exp \left(i t'_j U_j^{(2^n)} \right) \right),$$

where $l = (d-1)^2 + d - 1, \dots, (d-1)^2 + 2(d-1) - 1$ for some $d \in \{2, \dots, 2^n\}$, $U_l^{(2^n)}, U_j^{(2^n)} \in \mathbf{U}^{(2^n)}$, and $\alpha, t_j, t'_j \in \mathbb{R}$, $j \in \mathcal{J}$.

Now we consider 2-sparse unitary matrices that are block diagonal matrices, each block is a special unitary matrix. Let $R_a(\theta)$ denote a rotation gate around an axis a with an angle $\theta \in \mathbb{R}$. In particular, when the rotation matrices around the axes X, Y, Z are defined as

$$R_z(\theta) = \begin{bmatrix} e^{i\theta} & 0 \\ 0 & e^{-i\theta} \end{bmatrix}, R_y(\theta) = \begin{bmatrix} \cos \theta & \sin \theta \\ -\sin \theta & \cos \theta \end{bmatrix}, R_x(\theta) = \begin{bmatrix} \cos \theta & i \sin \theta \\ i \sin \theta & \cos \theta \end{bmatrix}.$$


Definition 3.6. [26] For n -qubit systems, a multi-controlled rotation gate around an axis a is defined as




where $\square \in \{ \text{---}\bullet\text{---}, \text{---}\circ\text{---} \}$, and $\theta_j, 1 \leq j \leq 2^{n-1} \in \mathbb{R}$. Then the unitary matrix corresponding to the above circuit is given by

$$F_n(R_a(\theta_1, \theta_2, \dots, \theta_{2^{n-1}})) := F_n(R_a) = \begin{bmatrix} R_a(\theta_1) & 0 & 0 & 0 \\ 0 & 0 & \ddots & 0 \\ \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & R_a(\theta_{2^{n-1}}) \end{bmatrix}$$

In short, we use the circuit in Definition 3.6 as




For example, setting $n = 4$, the circuit corresponding to $F_4(R_a)$ is given by



Further, it can be shown that that the multi-controlled rotation gates can be decomposed and implemented through CNOT and single qubit gates [26]. Indeed, the multi-controlled rotation gate on an n qubit system given by

$$\begin{array}{c} 1 \\ 2 \\ \vdots \\ n-1 \\ n \end{array} \begin{array}{l} \text{---} \square \text{---} \\ \text{---} \square \text{---} \\ \text{---} \square \text{---} \\ \text{---} \square \text{---} \\ \text{---} F_n(R_a(\psi_1, \dots, \psi_{2^{n-1}})) \text{---} \end{array} \quad (3)$$

can be written as



where

$$\psi_j = \begin{cases} \theta_j + \phi_j & \text{where } 1 \leq j \leq 2^{n-2} \\ \theta_j - \phi_j & \text{where } 2^{n-2} + 1 \leq j \leq 2^{n-1}. \end{cases}$$

Lemma 3.7. *The quantum circuits in equation (3) and Equation (4) are equivalent.*

Proof: The proof is computational and easy to verify. \square


Now with the help of the multi-controlled rotation gates, we consider writing 2-sparse block diagonal matrix of the form

$$\begin{bmatrix} U_1(\alpha_1, \beta_1, \gamma_1) & & & \\ & U_2(\alpha_2, \beta_2, \gamma_2) & & \\ & & \ddots & \\ & & & U_{2^{k-1}}(\alpha_{2^{n-1}}, \beta_{2^{n-1}}, \gamma_{2^{n-1}}) \end{bmatrix} \quad (5)$$

in terms of the proposed basis elements, where $U_j(\Theta_j) \in \text{SU}(2)$, $\Theta_j := (\alpha_j, \beta_j, \gamma_j)$, $1 \leq j \leq 2^{n-1}$ is a 2×2 special unitary matrix such that

$$U_j(\Theta_j) = \begin{bmatrix} e^{i(\alpha_j + \beta_j)} \cos \gamma_j & e^{i(\alpha_j - \beta_j)} \sin \gamma_j \\ -e^{-i(\alpha_j - \beta_j)} \sin \gamma_j & e^{-i(\alpha_j + \beta_j)} \cos \gamma_j \end{bmatrix}. \quad (6)$$

Since any 2×2 special unitary matrix has a ZYZ decomposition, the matrices in equation (5) have circuit from using the multi-controlled rotation gates as



which we denote as $M_n ZYZ$.

Now we introduce a handy notation for extracting diagonal entry of a diagonal matrix. Define

$$\eta_M^{(j)} = M_{jj}, 1 \leq j \leq k \quad (8)$$

for any diagonal matrix $M \in \{1, -1\}^{k \times k}$.

Lemma 3.8. *The set of vectors $\left\{ \left[\eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(1)} \quad \eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(3)} \quad \dots \quad \eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(2^{n+1}-1)} \right]^T \mid 0 \leq k \leq 2^n - 1 \right\}$ is equal to the set of column vectors of the matrix $2^{n/2} H_n$ where η is defined in equation 8 and χ is defined in equation 2.4.*

Proof: The proof follows from the fact that

$$\left[\eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(1)} \quad \eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(3)} \quad \cdots \quad \eta_{\chi_n^{-1}(k) \otimes \sigma_3}^{(2^{n+1}-1)} \right]^T = \text{diag}(\chi_n^{-1}(k)),$$

where $0 \leq k \leq 2^n - 1$. \square

Theorem 3.9. *The unitary matrix corresponding to an $M_n ZYZ$ given by equation (5) can be written as*

$$\left(\prod_{j \in \mathcal{J}} \exp(it_j \chi_{n-1}^{-1}(j)) \times \sigma_3 \right) \left(\prod_{j=1}^{2^{n-1}} \exp(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)}) \right) \left(\prod_{j \in \mathcal{J}} \exp(it'_j \chi_{n-1}^{-1}(j)) \times \sigma_3 \right)$$

where $\theta_{4j^2-2j} = \gamma_j \in \mathbb{R}$, $1 \leq j \leq 2^{n-1}$, $t_j, t'_j \in \mathbb{R}$.

Proof: We know that $R_y(\theta) = \exp(i\theta\sigma_2) = \cos\theta I_2 + i\sin\theta\sigma_2 = \begin{bmatrix} \cos\theta & \sin\theta \\ -\sin\theta & \cos\theta \end{bmatrix}$. From the proposed traceless basis elements, we have

$$U_j^{(2^n)} \in \left\{ \begin{bmatrix} D_1 & 0 & 0 \\ 0 & \sigma_2 & 0 \\ 0 & 0 & D_2 \end{bmatrix}, \begin{bmatrix} \sigma_2 & 0 \\ 0 & D \end{bmatrix}, \begin{bmatrix} D & 0 \\ 0 & \sigma_2 \end{bmatrix} \right\}$$

when $j \in \mathcal{J}_{\sigma_2} = \{l^2 - l : 2 \leq l \leq 2^n\}$ and D_1, D_2, D are diagonal matrices with entries from $\{1, -1\}$. In particular, the i -th diagonal entry of D, D_1 , and D_2 is 1 if i is even and -1 otherwise. Further, choosing $j = 4l^2 - 2l$, $1 \leq l \leq 2^{n-1}$ it is evident that the block diagonal matrices $U_j^{(2^n)}$ will have non-overlapping positions of σ_2 in the diagonal.

Thus we obtain

$$\prod_{l=1}^{2^{n-1}} \exp(i\theta_{4l^2-2l} U_{4l^2-2l}^{(2^n)}) = \begin{bmatrix} V_2 & & & \\ & V_4 & & \\ & & \ddots & \\ & & & V_{2^n} \end{bmatrix},$$

where

$$\begin{aligned} V_{2l} &= \left(\prod_{j < l} \begin{bmatrix} e^{i\theta_{4j^2-2j}} & 0 \\ 0 & e^{-i\theta_{4j^2-2j}} \end{bmatrix} \right) \begin{bmatrix} \cos \theta_{4l^2-2l} & \sin \theta_{4l^2-2l} \\ \sin \theta_{4l^2-2l} & \cos \theta_{4l^2-2l} \end{bmatrix} \left(\prod_{j > l} \begin{bmatrix} e^{i\theta_{4j^2-2j}} & 0 \\ 0 & e^{-i\theta_{4j^2-2j}} \end{bmatrix} \right) \\ &= \begin{bmatrix} e^{i \sum_{j \neq l} \theta_{4j^2-2j}} \cos \theta_{4l^2-2l} & e^{i(\sum_{j < l} \theta_{4j^2-2j} - \sum_{j > l} \theta_{4j^2-2j})} \sin \theta_{4l^2-2l} \\ -e^{-i(\sum_{j < l} \theta_{4j^2-2j} - \sum_{j > l} \theta_{4j^2-2j})} \sin \theta_{4l^2-2l} & e^{-i \sum_{j \neq l} \theta_{4j^2-2j}} \cos \theta_{4l^2-2l} \end{bmatrix}, \end{aligned}$$

$1 \leq l \leq 2^{n-1}$.

Now setting $\theta_{4l^2-2l} = \gamma_l$, $1 \leq l \leq 2^{n-1}$ for the representation of a $M_n ZYZ$ unitary matrix given by equation (5) with each diagonal block given by equation (6) through the proposed basis elements, the next is to find parameters that can provide the values of the remaining parameters α_l, β_l . Setting $x_l = \sum_{j \neq l} \theta_{4j^2-2j}$ and $y_l = \sum_{j < l} \theta_{4j^2-2j} - \sum_{j > l} \theta_{4j^2-2j}$, we obtain

$$V_{2l} = \begin{bmatrix} e^{ix_l} \cos \gamma_l & e^{iy_l} \sin \gamma_l \\ -e^{-iy_l} \sin \gamma_l & e^{-ix_l} \cos \gamma_l \end{bmatrix}.$$

Now let $A_{2l} = \begin{bmatrix} e^{ia_l} & 0 \\ 0 & e^{-ia_l} \end{bmatrix}$ and $B_{2l} = \begin{bmatrix} e^{ib_l} & 0 \\ 0 & e^{-ib_l} \end{bmatrix}$, $a_l, b_l \in \mathbb{R}$ such that

$$U_l(\alpha_l, \beta_l, \gamma_l) = A_{2l}V_{2l}B_{2l} = \begin{bmatrix} e^{i(\alpha_l+\beta_l)} \cos \gamma_l & e^{i(\alpha_l-\beta_l)} \sin \gamma_l \\ -e^{-i(\alpha_l-\beta_l)} \sin \gamma_l & e^{-i(\alpha_l+\beta_l)} \cos \gamma_l \end{bmatrix},$$

and $U = AVB$, where

$$A = \begin{bmatrix} A_2 & & \\ & \ddots & \\ & & A_{2^n} \end{bmatrix}, V = \begin{bmatrix} V_2 & & \\ & \ddots & \\ & & V_{2^n} \end{bmatrix}, B = \begin{bmatrix} B_2 & & \\ & \ddots & \\ & & B_{2^n} \end{bmatrix}.$$

Then setting

$$A_{2l} = \begin{bmatrix} \exp(i \sum_{j=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(j) \otimes \sigma_3}^{(2l-1)} t_j) & 0 \\ 0 & \exp(-i \sum_{j=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(j) \otimes \sigma_3}^{(2l-1)} t_j) \end{bmatrix}$$

where

$$B_{2l} = \begin{bmatrix} \exp(i \sum_{j=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(j) \otimes \sigma_3}^{(2l-1)} t'_j) & 0 \\ 0 & \exp(-i \sum_{j=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(j) \otimes \sigma_3}^{(2l-1)} t'_j) \end{bmatrix}$$

This is obtained by applying all l -th blocks of $\exp(i \otimes_{k=1}^{n-1} A_k \otimes \sigma_3)$ where $A_k \in \{I, \sigma_3\}$ so that A_{2l}, B_{2l} are of the desired forms. Then equating the entries of the both sides of the equation $U = AVA$ provides a system of linear equation of the form $Hx = b$, where $b_{2l-1} = -(x_l - \alpha_l - \beta_l)$ and $b_{2l} = -(y_l - \beta_l + \alpha_l)$, and η defined in equation (8), $1 \leq l \leq 2^{n-1}$ and $x = [t_0 \ t_1 \ \dots \ t_{2^{n-1}-1} \ t'_0 \ \dots \ t'_{2^{n-1}-1}]^T$ and

$$H = \begin{bmatrix} \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} \end{bmatrix}_{2^n \times 2^n}$$

Now H is nonsingular since H can also be written in the following form.

$$H = P \begin{bmatrix} \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(3)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(3)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(3)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(3)} \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2l-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2l-1)} \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} & \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(1)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(1)} \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(3)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(3)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(3)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(3)} \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots \\ \eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & \eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} & -\eta_{\chi_{n-1}^{-1}(0) \otimes \sigma_3}^{(2^n-1)} & \cdots & -\eta_{\chi_{n-1}^{-1}(2^{n-1}-1) \otimes \sigma_3}^{(2^n-1)} \end{bmatrix}$$

Note that

$$A = P \begin{bmatrix} 2^{(n-1)/2} H_{n-1} & 2^{(n-1)/2} H_{n-1} \\ 2^{(n-1)/2} H_{n-1} & -2^{(n-1)/2} H_{n-1} \end{bmatrix}' = 2^{n/2} H_n$$

follows from Lemma 3.8 and $(\text{diag}(\otimes_{k=1}^{n-1} M_k \otimes \sigma_3) = 2^{(n-1)/2} H_{2^{n-1}}$, where P is a permutation matrix. This completes the proof. \square

Remark 3.10. (a) As Givens rotation matrices, which are 2-level unitary matrices, can be used to construct any unitary matrix through matrix multiplication [14], it follows that any unitary matrix can be expressed as a product of exponential of the RBB elements. It is worth noting that the computing the exponential of RBB elements can be performed in $O(1)$ time. Therefore, if the Givens rotation corresponding to a given unitary matrix is known, expressing that matrix in terms of the proposed basis elements becomes a straightforward task.

(b) It can be noted that using Pauli string basis to form matrices of dimensions 2^n is not ideal when compared to the proposed basis, due to two main reasons. Firstly, computing the exponential of Pauli string matrices is a difficult task because the fundamental Pauli matrices do not commute. Secondly, in the worst-case scenario, generating a Pauli string for an n -qubit system would require $O(n2^{2n})$ operations using generic Kronecker product algorithms [37]. On the contrary, the construction of the proposed basis matrices do not require any operation as the construction is completely prescribed by the pattern of the non-zero entries of the basis elements.

3.2 Algorithmic approximation of special unitary matrices

We can utilize Theorem 3.1 to find a value $\theta > 0$ such that the set $\left\{ \prod_{j=1}^{d^2} \exp\left(i\theta_j B_j^{(d)}\right) \right\}$, where $(\theta_1, \dots, \theta_{d^2}) \in I_\theta^{d^2}$, generates the unitary group $U(d)$. As a result, any unitary matrix U up to permutation of indices of the basis elements can be represented as

$$U = \underbrace{\left(\prod_{j=1}^{d^2} \exp\left(i\theta_j B_j^{(d)}\right) \right) \cdots \left(\prod_{j=1}^{d^2} \exp\left(i\theta_j B_j^{(d)}\right) \right)}_{L \text{ times}} := \prod_{l=1}^L \left(\prod_{j=1}^{d^2} \exp\left(i\theta_{lj} B_j^{(d)}\right) \right) \quad (9)$$

for some positive integer L , which we call the number of layers or iterations for approximating U . However, determining the appropriate value of L for a given $U \in \mathbf{U}(d)$ is challenging in practice. Further, the ordering of the basis elements in Corollary 2.3 given by $\mathcal{U}^{(2^n)}$ is fixed to ensure that the recursive construction method works.

Indeed, we propose to find a parametric representation of a given unitary through solving the following optimization problem

$$\min_{\theta_{l_j} \in I_\theta^{Kd^2}} \left\| U - \prod_{l=1}^L \left(\prod_{j=1}^{d^2} \exp \left(i\theta_{l_j} B_j^{(d)} \right) \right) \right\|$$

for some $\theta > 0$, where $\|\cdot\|$ is a desired matrix norm. In this section, we explore approximating unitaries that are dominant in quantum computing and perform an accuracy analysis of this approximation corresponding to Frobenius norm. The optimization problem is solved using Nelder-Mead method in the numerical simulation. We also explore whether altering the ordering impact the accuracy of approximating a unitary U through parameter optimization.

Employing the basis described in Theorem 2.1 the Algorithm 1 describes how to approximate a unitary $U \in \mathbf{SU}(d)$.

One draw back of Algorithm 1 lies in the fact that the optimization may end at a local minima since the objective function is not convex. Further, the initial condition i.e. the choice of of the parameters involved can have adverse effect on the efficiency of the algorithm. A procedure to decide on the choice of the parameters can possibly be overcome by generating several values of parameters in the initial stage of the algorithm and then apply the optimization method. For n -qubit system the algorithm faces another significant problem for implementation of the unitary matrices through elementary gates, since the ultimate goal is to implement any unitary through strings of elementary gates. Indeed, for unitary matrices of order $d = 2^n$, the problem with Algorithm 1, lies in the fact that in order to construct a quantum circuit for the proposed ordering of the basis elements while approximating any unitary from $\mathbf{SU}(2^n)$, the number of *CNOT* gates required for a single iteration becomes $O(2^{3n})$ as follows from equation (9) setting $L = 1$. This is due to the fact all non-diagonal RBB matrices generate 2-level unitary matrices and a single 2-level unitary matrix requires at least 2^{n-1} *CNOT* gates from this ordering of the basis elements and there are $2^{2n} - 2^n$ non-diagonal basis matrices.

Thus the question is: how to choose a suitable ordering of the basis elements? One motivation for a suitable choice is to reduce the number of *CNOT* gates in a quantum circuit implementation of a given unitary matrix using equation (9). First we introduce two functions through which we like to call the proposed basis elements of particular index. For a given integer $d \geq 2$, we define the functions:

$$\begin{cases} f : \mathbb{N} \times \mathbb{Z} \rightarrow \mathbb{Z} \text{ such that } f(n, k) := f_n(k) = (n-1)^2 + (n-1) + (k \bmod (n-1)) \\ h : \mathbb{N} \times \mathbb{Z} \rightarrow \mathbb{Z} \text{ such that } h(n, k) := h_n(k) = (n-1)^2 + (k \bmod (n-1)). \end{cases} \quad (10)$$

Now in the next section we propose a new ordering for the SRBB that can give an optimal number of *CNOT* gates in the corresponding quantum circuit implementation using equation (9), setting $L = 1$.

Algorithm 1 Approximating $d \times d$ special unitary matrix

Provided: Consider the basis $\mathcal{B}^{(d)}$ of $SU(d)$ from Theorem 2.1 and set

$$\psi(a_1, a_2, \dots, a_{d^2-1}) = \prod_{j=1}^{d^2-1} \exp(ia_j B_j^{(d)})$$

Input: $U_1 \in SU(d)$, $d^2 - 1$ real parameters $(a_1^{(1)}, \dots, a_{d^2-1}^{(1)})$, $\epsilon > 0$

Output: A unitary matrix A such that $\|U - A\|_F \leq \epsilon$ where

$$A = \prod_{l=1}^L \left(\prod_{j=1}^{d^2-1} \exp(ia_j^{(l)} B_j^{(d)}) \right)$$

procedure (Unitary Matrix U) ▷

$A \rightarrow I$

for $t = 1; t++$ **do**

Use optimization methods like Nelder-Mead/Powell's or Gradient descent to determine $U_t = \psi(a_1^{(t)}, \dots, a_{n^2-1}^{(t)})$ such that $\|U - U_t\|_F$ is minimum. Set $\|U - U_t\| = \epsilon_t$.

if $\epsilon_t \leq \epsilon$ **then**

Break

$A \rightarrow A\psi(a_1^{(t)}, a_2^{(t)}, \dots, a_{n^2-1}^{(t)})$

else

$U_{t+1} \rightarrow U_t A^*$

end if

End

end for

End

End Procedure

end procedure

4 Approximation of n -qubit unitaries

First observe that a SRBB element $U_j^{(2^n)} \in \mathbf{U}^{(2^n)}$, $\exp(i\theta U_j^{(2^n)})$, $j = h_q(p)$, $p < q$, $q \in \{2, \dots, 2^n\}$, can be written as

$$\left(\prod_{l=0}^{2^{n-1}-1} \exp(it_l(\chi_{n-1}^{-1}(l) \otimes \sigma_3)) \right) \exp(i\theta U_{j'}^{(2^n)}) \left(\prod_{l=0}^{2^{n-1}-1} \exp(it'_l(\chi_{n-1}^{-1}(l) \otimes \sigma_3)) \right)$$

where $j' = f_q(p)$, $p < q$, $q \in \{2, \dots, 2^n\}$ for some $t_l, t'_l \in \mathbb{R}$. Moreover, we would like to consider the ordering of the SRB such that products of the exponential certain non-diagonal SRBB elements in that order should generate $M_n ZYZ$ type matrix or permutation of a $M_n ZYZ$ type matrix. For example, note from Theorem 3.9 that in the original ordering of the non-diagonal SRBB basis matrices with indices $4j^2 - 2j$ and diagonal SRB matrices, the matrix

$$\left(\prod_{l=0}^{2^{n-1}-1} \exp(it_l(\chi_{n-1}^{-1}(l) \otimes \sigma_3)) \right) \left(\prod_{j=1}^{2^{n-1}} \theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \left(\prod_{l=0}^{2^{n-1}-1} \exp(it'_l(\chi_{n-1}^{-1}(l) \otimes \sigma_3)) \right)$$

is a $M_n ZYZ$ type matrix. Besides, it is well known that quantum circuit for $M_n ZYZ$ is prevalent in literature [26].

From Corollary 2.3, note that any non-diagonal element of the SRBB is given by $U_j^{(2^n)} = PMP$, where M is a block diagonal matrix with a maximum 3 blocks, two of which are diagonal matrices and one block is $\sigma \in \{\sigma_1, \sigma_3\}$, and $P = P_{(\alpha, \beta)}$ is a trasposition with $0 < \alpha \leq \beta \leq 2^n$. Moreover, the permutation matrix $P_{(\alpha, \beta)}$ is uniquely identified with the SRBB element index j , except when it is identity. We shall see now another interesting aspect of the SRBB elements. First we consider the following example.

Example 4.1. The exponential of SRBB elements for $\mathbb{C}^{4 \times 4}$ are as follows.

$$\begin{aligned}
\exp(i\theta_1 U_1^{(4)}) &= \begin{bmatrix} \cos \theta_1 & i \sin \theta_1 & 0 & 0 \\ i \sin \theta_1 & \cos \theta_1 & 0 & 0 \\ 0 & 0 & e^{i\theta_1} & 0 \\ 0 & 0 & 0 & e^{-i\theta_1} \end{bmatrix}, \quad \exp(i\theta_2 U_2^{(4)}) = \begin{bmatrix} \cos \theta_2 & \sin \theta_1 & 0 & 0 \\ -\sin \theta_2 & \cos \theta_2 & 0 & 0 \\ 0 & 0 & e^{i\theta_2} & 0 \\ 0 & 0 & 0 & e^{-i\theta_2} \end{bmatrix} \\
\exp(i\theta_3 U_3^{(4)}) &= \begin{bmatrix} e^{i\theta_3} & 0 & 0 & 0 \\ 0 & e^{-i\theta_3} & 0 & 0 \\ 0 & 0 & e^{i\theta_3} & 0 \\ 0 & 0 & 0 & e^{-i\theta_3} \end{bmatrix}, \quad \exp(i\theta_4 U_4^{(4)}) = \begin{bmatrix} e^{i\theta_4} & 0 & 0 & 0 \\ 0 & \cos \theta_4 & i \sin \theta_4 & 0 \\ 0 & i \sin \theta_4 & \cos \theta_4 & 0 \\ 0 & 0 & 0 & e^{-i\theta_4} \end{bmatrix} \\
\exp(i\theta_5 U_5^{(4)}) &= \begin{bmatrix} \cos \theta_4 & 0 & i \sin \theta_5 & 0 \\ 0 & e^{i\theta_5} & 0 & 0 \\ i \sin \theta_5 & 0 & \cos \theta_5 & 0 \\ 0 & 0 & 0 & e^{-i\theta_5} \end{bmatrix}, \quad \exp(i\theta_6 U_6^{(4)}) = \begin{bmatrix} e^{i\theta_6} & 0 & 0 & 0 \\ 0 & \cos \theta_6 & \sin \theta_6 & 0 \\ 0 & -\sin \theta_6 & \cos \theta_6 & 0 \\ 0 & 0 & 0 & e^{-i\theta_6} \end{bmatrix}, \\
\exp(i\theta_7 U_7^{(4)}) &= \begin{bmatrix} \cos \theta_4 & 0 & \sin \theta_5 & 0 \\ 0 & e^{i\theta_7} & 0 & 0 \\ -\sin \theta_7 & 0 & \cos \theta_7 & 0 \\ 0 & 0 & 0 & e^{-i\theta_7} \end{bmatrix}, \quad \exp(i\theta_8 U_8^{(4)}) = \begin{bmatrix} e^{i\theta_8} & 0 & 0 & 0 \\ 0 & e^{i\theta_8} & 0 & 0 \\ 0 & 0 & e^{-i\theta_8} & 0 \\ 0 & 0 & 0 & e^{-i\theta_8} \end{bmatrix}, \\
\exp(i\theta_9 U_9^{(4)}) &= \begin{bmatrix} e^{i\theta_9} & 0 & 0 & 0 \\ 0 & e^{-i\theta_9} & 0 & 0 \\ 0 & 0 & \cos \theta_9 & i \sin \theta_9 \\ 0 & 0 & i \sin \theta_9 & \cos \theta_9 \end{bmatrix}, \quad \exp(i\theta_{10} U_{10}^{(4)}) = \begin{bmatrix} \cos \theta_{10} & 0 & 0 & i \sin \theta_{10} \\ 0 & e^{-i\theta_{10}} & 0 & 0 \\ 0 & 0 & e^{i\theta_{10}} & 0 \\ i \sin \theta_{10} & 0 & 0 & \cos \theta_{10} \end{bmatrix}, \\
\exp(i\theta_{11} U_{11}^{(4)}) &= \begin{bmatrix} e^{i\theta_{11}} & 0 & 0 & 0 \\ 0 & \cos \theta_{11} & 0 & i \sin \theta_{11} \\ 0 & 0 & e^{-i\theta_{11}} & 0 \\ 0 & i \sin \theta_{11} & 0 & \cos \theta_{11} \end{bmatrix}, \quad \exp(i\theta_{12} U_{12}^{(4)}) = \begin{bmatrix} e^{i\theta_{12}} & 0 & 0 & 0 \\ 0 & e^{-i\theta_{12}} & 0 & 0 \\ 0 & 0 & \cos \theta_{12} & \sin \theta_{12} \\ 0 & 0 & -\sin \theta_{12} & \cos \theta_{12} \end{bmatrix}, \\
\exp(i\theta_{13} U_{13}^{(4)}) &= \begin{bmatrix} \cos \theta_{13} & 0 & 0 & \sin \theta_{13} \\ 0 & e^{-i\theta_{13}} & 0 & 0 \\ 0 & 0 & e^{i\theta_{13}} & 0 \\ -\sin \theta_{13} & 0 & 0 & \cos \theta_{13} \end{bmatrix}, \quad \exp(i\theta_{14} U_{14}^{(4)}) = \begin{bmatrix} e^{i\theta_{14}} & 0 & 0 & 0 \\ 0 & \cos \theta_{14} & 0 & \sin \theta_{14} \\ 0 & 0 & e^{-i\theta_{14}} & 0 \\ 0 & -\sin \theta_{14} & 0 & \cos \theta_{14} \end{bmatrix}, \\
\exp(i\theta_{15} U_{15}^{(4)}) &= \begin{bmatrix} e^{i\theta_{15}} & 0 & 0 & 0 \\ 0 & e^{-i\theta_{15}} & 0 & 0 \\ 0 & 0 & e^{-i\theta_{15}} & 0 \\ 0 & 0 & 0 & e^{i\theta_{15}} \end{bmatrix}
\end{aligned}$$

Then note that $\exp(i\theta_1 U_1^{(4)}) \exp(i\theta_2 U_2^{(4)}) \exp(i\theta_9 U_9^{(4)}) \exp(i\theta_{12} U_{12}^{(4)})$ forms a $M_2 Z Y Z$ matrix. Further, the product

$$P_{(2,4)} \exp(i\theta_4 U_4^{(4)}) \exp(i\theta_6 U_6^{(4)}) \exp(i\theta_{10} U_{10}^{(4)}) \exp(i\theta_{13} U_{13}^{(4)}) P_{(2,4)}$$

is of the form $M_2 Z Y Z$, and

$$P_{(2,3)} \exp(i\theta_5 U_5^{(4)}) \exp(i\theta_7 U_7^{(4)}) \exp(i\theta_{11} U_{11}^{(4)}) \exp(i\theta_{14} U_{14}^{(4)}) P_{(2,3)}$$

is a block diagonal matrix. Thus we conclude that product of exponential of certain non-diagonal SRBB elements is permutation similar to either a $M_2 Z Y Z$ type matrix or a block-diagonal matrix.

Now we show that the above observation is true for non-diagonal SRBB elements of $SU(2^n)$.

Indeed, for a pair $1 \leq \alpha < \beta \leq 2^n$ with β is even and α is odd, we have

$$\exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right) = \begin{bmatrix} \exp(i\theta D_{\alpha-1}) & & & & & \\ & \cos\theta & & & \sin\theta & \\ & \vdots & & \exp(i\theta D_{\beta-\alpha-1}) & & \\ & & -\sin\theta & & \cos\theta & \\ & & & & & \exp(i\theta D_{2^n-\beta}) \end{bmatrix}, \quad (11)$$

where D_x is a diagonal matrix of order x with l -th diagonal entry is 1 if l is odd and it is -1 if l is even. Then clearly $P_{(\alpha+1,\beta)} \exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right) P_{(\alpha+1,\beta)}$ gives a $M_n ZY Z$ type matrix. Similarly, if β is odd and α is even then $P_{(\alpha,\beta+1)} \exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right) P_{(\alpha,\beta+1)}$ is a $M_n ZY Z$ type matrix. Next if α and β are both odd then for the non-diagonal basis element $\exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right)$ will have same pattern as equation (11) but $P_{(\alpha+1,\beta)} \exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right) P_{(\alpha+1,\beta)}$ will be a block-diagonal matrix consists of blocks are of size 2 belonging to $\mathfrak{u}(2)$ with at least one block of the form $\begin{bmatrix} \exp(i\theta) & 0 \\ 0 & \exp(i\theta) \end{bmatrix}$. Similarly, if α, β are even then $P_{(\alpha,\beta-1)} \exp\left(i\theta U_{f_\beta(\alpha)}^{(2^n)}\right) P_{(\alpha,\beta-1)}$ is a special unitary block diagonal matrix with at least one block is from $\mathfrak{U}(2)$. Similar observations also hold for the function h .

Finally observe that all the transpositions $P_{(\alpha,\beta)}$ whose pre and pro multiplication make a matrix $U_j^{(2^n)} \in \mathcal{U}^{(2^n)}$ a matrix of type $M_n ZY Z$ or a special unitary block diagonal matrix, have the values of α, β both to be even or α is even and β is odd, where $1 \leq \alpha < \beta \leq 2^n$. Thus we consider two sets of permutation matrices

$$\begin{aligned} \mathcal{P}_{2^n, \text{even}} &= \{P_{(\alpha,\beta)} \in \mathcal{P}_{2^n} \mid \alpha, \beta \text{ are even}\} \\ \mathcal{P}_{2^n, \text{odd}} &= \{P_{(\alpha,\beta)} \in \mathcal{P}_{2^n} \mid \alpha \text{ is even, } \beta \text{ is odd}\} \end{aligned}$$

which we will use in order to approximate a unitary matrix as a product of $M_n ZY Z$ or unitary block diagonal matrices and its permutations. Then it follows that $|\mathcal{P}_{2^n, \text{even}}| = 2^{2^n-3} - 2^{n-2} = |\mathcal{P}_{2^n, \text{odd}}|$.

We will see in Theorem 4.8 that the product of exponential of certain SRBB elements create a matrix which is permutation similar to a $M_n ZY Z$ matrix or a special unitary block diagonal matrix, and the corresponding permutation matrix is a product of 2^{n-2} disjoint transpositions either from $\mathcal{P}_{2^n, \text{even}}$ or $\mathcal{P}_{2^n, \text{odd}}$ and total number of such permutation matrices is $(2^{n-1} - 1)$ which makes the total number of elements in $\mathcal{P}_{2^n, \text{even}}$ and $\mathcal{P}_{2^n, \text{odd}}$ to be $2^{n-2} \times (2^{n-1} - 1) = 2^{2^n-3} - 2^{n-2}$. Let T_x^e and T_x^o be sets of 2^{n-2} disjoint transpositions from $\mathcal{P}_{2^n, \text{even}}$ and $\mathcal{P}_{2^n, \text{odd}}$ respectively, $1 \leq x \leq 2^{n-1} - 1$ such that $\cup_x T_x^e = \mathcal{P}_{2^n, \text{even}}$ and $\cup_x T_x^o = \mathcal{P}_{2^n, \text{odd}}$, where \cup denotes disjoint union. Define

$$\Pi T_x^e = \prod_{(\alpha,\beta) \in T_x^e} P_{(\alpha,\beta)} \quad \text{and} \quad \Pi T_x^o = \prod_{(\alpha,\beta) \in T_x^o} P_{(\alpha,\beta)}, \quad (12)$$

$1 \leq x \leq 2^{n-1} - 1$.

The motivation behind creating unitary block diagonal or $M_n ZY Z$ matrices lies in the fact that the quantum circuits for such matrices are easy to implement. The quantum circuit for $M_n ZY Z$ matrices can be found in [26]. We shall see later that adding a few $CNOT$ and R_z gates it is possible to define a circuit for a block diagonal matrix with 2×2 blocks from a circuit that represents a $M_n ZY Z$ matrix.

Now we prove certain results which will be used to approximate a unitary matrix through product of exponential of SRBB elements in certain order.

Lemma 4.2. A block diagonal matrix $U \in \text{SU}(2^n)$ consisting of 2×2 blocks is of the form

$$\left(\prod_{t=2}^{2^n} \exp \left(i\theta_{t^2-1} U_{t^2-1}^{(2^n)} \right) \right) \left(\prod_{j=1}^{2^{n-1}} \exp \left(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \right) \left(\prod_{t=2}^{2^n} \exp \left(i\theta_{t^2-1} U_{t^2-1}^{(2^n)} \right) \right)$$

where $\theta_{4j^2-2j} \in \mathbb{R}$, $1 \leq j \leq 2^{n-1}$, $\theta_{t^2-1}, \theta'_{t^2-1}$ are obtained from Theorem 3.3 and Theorem 3.9.

Proof: The matrices $U_{t^2-1}^{(2^n)}$, $2 \leq t \leq 2^n$ are used to construct diagonal unitary matrices. Thus the proof follows from how to get a $M_n ZY Z$ matrix and finally we apply the same procedure used in theorem 3.3. \square

Lemma 4.3. Suppose $U(\alpha, \beta, \gamma)$ is a unitary matrix given by equation (5), where $\alpha = \{\alpha_j\}_{j=1}^{2^{n-1}}$, $\beta = \{\beta_j\}_{j=1}^{2^{n-1}}$, $\gamma = \{\gamma_j\}_{j=1}^{2^{n-1}}$. Then

$$\left(\prod_{p=0}^{2^{n-1}-1} \exp \left(it_p (\chi_{n-1}^{-1}(p) \otimes \sigma_3) \right) \right) U(\alpha, \beta, \gamma) \left(\prod_{p=0}^{2^{n-1}-1} \exp \left(it'_p (\chi_{n-1}^{-1}(p) \otimes \sigma_3) \right) \right) = \tilde{U}(\tilde{\alpha}, \tilde{\beta}, \tilde{\gamma}),$$

which is of the form $M_n YZY$, where $\tilde{\alpha} = \{\tilde{\alpha}_j\}_{j=1}^{2^{n-1}}$, $\tilde{\beta} = \{\tilde{\beta}_j\}_{j=1}^{2^{n-1}}$, $\tilde{\gamma} = \{\tilde{\gamma}_j\}_{j=1}^{2^{n-1}}$ with

$$\begin{aligned} \tilde{\alpha}_j &= \left(\alpha_j + \left(\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes Z}^{(2j-1)} t_p + \sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes Z}^{(2j-1)} t'_p \right) \right) \\ \tilde{\beta}_j &= \left(\beta_j + \left(\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes Z}^{(2j-1)} t_p - \sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes Z}^{(2j-1)} t'_p \right) \right), \end{aligned}$$

$\tilde{\gamma}_j = \gamma_j$, $1 \leq j \leq 2^{n-1}$, $t_p, t'_p \in \mathbb{R}$.

Proof: The proof follows adapting a similar procedure as described in Theorem 3.9 \square .

Lemma 4.4 (Product of exponential of certain basis elements makes a $M_n ZY Z$ matrix).
The matrix

$$\prod_{q=1}^{2^{n-1}} \left(\exp \left(i\theta_{h_{2q}(0)} U_{h_{2q}(0)}^{(2^n)} \right) \right) \left(\exp \left(i\theta_{f_{2q}(0)} U_{f_{2q}(0)}^{(2^n)} \right) \right) = \prod_{j=1}^{2^{n-1}} \left(\exp \left(i\theta_{(2j-1)^2} U_{(2j-1)^2}^{(2^n)} \right) \right) \left(\exp \left(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \right)$$

is of the form of a $M_n ZY Z$ matrix. Besides this matrix can also be expressed alternatively as

$$\left(\prod_{p=0}^{2^{n-1}-1} \exp \left(it_p (\chi_{n-1}^{-1}(p) \otimes \sigma_3) \right) \right) \left(\prod_{j=1}^{2^{n-1}} \exp \left(i\phi_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \right) \left(\prod_{p=1}^{2^{n-1}} \exp \left(it'_p (\chi_{n-1}^{-1}(p) \otimes \sigma_3) \right) \right),$$

where $\theta_{4j^2-2j}, \theta_{(2j-1)^2} \in \mathbb{R}$, $1 \leq j \leq 2^{n-1}$,

$$\phi_{4j^2-2j} = \arccos \sqrt{(\cos \theta_{(2j-1)^2} \cos \theta_{(4j^2-2j)})^2 + (\sin \theta_{(2j-1)^2} \sin \theta_{(4j^2-2j)})^2},$$

and t_p, t'_p , $0 \leq p \leq 2^{n-1} - 1$ can be obtained by solving a linear system.

Proof: The first identity follows from the writing the value $h_{2q}(0)$ and $f_{2q}(0)$. From the definition of $U_j^{(2^n)}$, observe that

$$\begin{aligned} \exp\left(i\theta_{4j^2-2j}U_{4j^2-2j}^{(2^n)}\right) &= \left[\begin{array}{c|cc} D_{(2j-2)\times(2j-2)} & 0 & 0 \\ \hline 0 & \begin{bmatrix} \cos \theta_{4j^2-2j} & \sin \theta_{4j^2-2j} \\ -\sin \theta_{4j^2-2j} & \cos \theta_{4j^2-2j} \end{bmatrix} & 0 \\ \hline 0 & 0 & D_{(2^n-2j)\times(2^n-2j)} \end{array} \right] \\ \exp\left(i\theta_{(2j-1)^2}B_{(2j-1)^2}^{(2^n)}\right) &= \left[\begin{array}{c|cc} D_{(2j-2)\times(2j-2)} & 0 & 0 \\ \hline 0 & \begin{bmatrix} \cos \theta_{(2j-1)^2} & i \sin \theta_{(2j-1)^2} \\ i \sin \theta_{(2j-1)^2} & \cos \theta_{(2j-1)^2} \end{bmatrix} & 0 \\ \hline 0 & 0 & D_{(2^n-2j)\times(2^n-2j)} \end{array} \right] \end{aligned}$$

where D is a diagonal matrix with k -th diagonal entry is given by

$$D_{kk} = \begin{cases} \exp(i\theta_{4j^2-2j}), & \text{if } k \text{ is odd} \\ \exp(-i\theta_{4j^2-2j}), & \text{if } k \text{ is even} \end{cases},$$

$$1 \leq k \leq 2^{n-1}.$$

Now

$$\begin{aligned} & \begin{bmatrix} \cos \theta_{(2j-1)^2} & i \sin \theta_{(2j-1)^2} \\ i \sin \theta_{(2j-1)^2} & \cos \theta_{(2j-1)^2} \end{bmatrix} \begin{bmatrix} \cos \theta_{4j^2-2j} & \sin \theta_{4j^2-2j} \\ -\sin \theta_{4j^2-2j} & \cos \theta_{4j^2-2j} \end{bmatrix} \\ &= \begin{bmatrix} \cos \theta_{(2j-1)^2} \cos \theta_{4j^2-2j} - i \sin \theta_{(2j-1)^2} \sin \theta_{4j^2-2j} & \sin \theta_{4j^2-2j} \cos \theta_{(2j-1)^2} + i \cos \theta_{4j^2-2j} \sin \theta_{(2j-1)^2} \\ -\sin \theta_{4j^2-2j} \cos \theta_{(2j-1)^2} + i \cos \theta_{4j^2-2j} \sin \theta_{(2j-1)^2} & \cos \theta_{(2j-1)^2} \cos \theta_{4j^2-2j} + i \sin \theta_{(2j-1)^2} \sin \theta_{4j^2-2j} \end{bmatrix} \\ &= \begin{bmatrix} \cos \phi_{4j^2-2j} \exp(-i\beta_{4j^2-2j}) & \sin \phi_{4j^2-2j} \exp(i\gamma_{4j^2-2j}) \\ -\sin \phi_{4j^2-2j} \exp(-i\gamma_{4j^2-2j}) & \cos \phi_{4j^2-2j} \exp(i\beta_{4j^2-2j}) \end{bmatrix} \end{aligned}$$

utilizing

$$(\cos \theta_{(2j-1)^2} \cos \theta_{4j^2-2j})^2 + (\sin \theta_{(2j-1)^2} \sin \theta_{4j^2-2j})^2 + (\sin \theta_{4j^2-2j} \cos \theta_{(2j-1)^2})^2 + (\cos \theta_{4j^2-2j} \sin \theta_{(2j-1)^2})^2 = 1$$

with

$$\begin{aligned} \cos \phi_{4j^2-2j} &= \sqrt{(\cos \theta_{(2j-1)^2} \cos \theta_{4j^2-2j})^2 + (\sin \theta_{(2j-1)^2} \sin \theta_{4j^2-2j})^2}, \\ \sin \phi_{4j^2-2j} &= \sqrt{(\sin \theta_{4j^2-2j} \cos \theta_{(2j-1)^2})^2 + (\cos \theta_{4j^2-2j} \sin \theta_{(2j-1)^2})^2}, \\ \beta_{4j^2-2j} &= \arcsin \frac{\sin \theta_{(2j-1)^2} \sin \theta_{4j^2-2j}}{\cos \phi_{4j^2-2j}}, \\ \gamma_{4j^2-2j} &= \arcsin \frac{\cos \theta_{4j^2-2j} \sin \theta_{(2j-1)^2}}{\sin \phi_{4j^2-2j}}. \end{aligned}$$

Therefore,

$$\prod_{j=1}^{2^{n-1}} \exp\left(i\theta_{(2j-1)^2}U_{(2j-1)^2}^{(2^n)}\right) \exp\left(i\theta_{4j^2-2j}B_{4j^2-2j}^{(2^n)}\right) := V = \left[\begin{array}{c|ccc} V_2 & 0 & 0 & 0 \\ \hline 0 & V_4 & 0 & 0 \\ \hline 0 & 0 & \ddots & 0 \\ \hline 0 & 0 & 0 & V_{2^n} \end{array} \right]$$

where

$$V_{2j} = \begin{bmatrix} e^{i(\sum_{l<j}(\theta_{4l^2-4l}+\theta_{(2l-1)^2}))} & 0 \\ 0 & e^{(-i\sum_{l<j}(\theta_{4l^2-4l}+\theta_{(2l-1)^2}))} \end{bmatrix} \begin{bmatrix} e^{(-i\beta_{4j^2-2j})} \cos \phi_{4j^2-2j} & e^{(i\gamma_{4j^2-2j})} \sin \phi_{4j^2-2j} \\ -e^{(-i\gamma_{4j^2-2j})} \sin \phi_{4j^2-2j} & e^{(i\beta_{4j^2-2j})} \cos \phi_{4j^2-2j} \end{bmatrix} \\ \begin{bmatrix} e^{(i(\sum_{l=j+1}^{2^{n-1}}(\theta_{4l^2-4l}+\theta_{(2l-1)^2}))} & 0 \\ 0 & e^{(-i(\sum_{l=j+1}^{2^{n-1}}(\theta_{4l^2-4l}+\theta_{(2l-1)^2}))} \end{bmatrix}$$

Finally, from Theorem 3.9, we have

$$\prod_{j=1}^{2^{n-1}} \exp\left(i\phi_{4j^2-2j}U_{4j^2-2j}^{(2^n)}\right) = \begin{bmatrix} W_2 & 0 & 0 & 0 \\ 0 & 0 & \ddots & 0 \\ 0 & 0 & 0 & W_{2^n} \end{bmatrix}$$

with

$$W_{2j} = \begin{bmatrix} e^{i\sum_{l\neq j} \phi_{4l^2-2l}} \cos \phi_{4j^2-2j} & e^{i(\sum_{l<j} \phi_{4l^2-2l} - \sum_{l>j} \phi_{4l^2-2l})} \sin \phi_{4j^2-2j} \\ -e^{-i(\sum_{l<j} \phi_{4l^2-2l} - \sum_{l>j} \phi_{4l^2-2l})} \sin \phi_{4j^2-2j} & e^{-i(\sum_{l\neq j} \phi_{4l^2-2l})} \cos \phi_{4j^2-2j} \end{bmatrix},$$

$1 \leq j \leq 2^{n-1}$.

Thus

$$\left(\prod_{p=0}^{2^{n-1}-1} \exp(it_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right) \left(\prod_{j=1}^{2^{n-1}} \exp(i\phi_{4j^2-2j}U_{4j^2-2j}^{(2^n)}) \right) \left(\prod_{p=0}^{2^{n-1}-1} \exp(it'_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right) = V,$$

which is equivalent to $V_{2j} = M_{2j}W_{2j}M'_{2j}$, such that

$$M_{2j} = \begin{bmatrix} \exp\left(i\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes \sigma_3}^{(2j-1)} t_p\right) & 0 \\ 0 & \exp\left(-i\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes \sigma_3}^{(2j-1)} t_p\right) \end{bmatrix} \\ M'_{2j} = \begin{bmatrix} \exp\left(i\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes \sigma_3}^{(2j-1)} t'_p\right) & 0 \\ 0 & \exp\left(-i\sum_{p=0}^{2^{n-1}-1} \eta_{\chi_{n-1}^{-1}(p) \otimes \sigma_3}^{(2j-1)} t'_p\right) \end{bmatrix}$$

will hold for certain values of $t_p, t'_p \in \mathbb{R}$ that can be obtained by solving a linear system as described in Theorem 3.9. This completes the proof. \square

Remark 4.5. In the above lemma we see how to select certain basis elements to obtain $M_n ZYZ$ matrices, and the number of non-diagonal basis elements used to create such a matrix is 2^n . Total number of non-diagonal basis elements is $2^{2^n} - 2^n$. Hence, we need to allocate these matrices into $(2^n - 1)$ bundles each of which contains 2^n matrix multiplications such that each bundle gives us a matrix which is permutationally similar to $M_n ZYZ$ matrices i.e. the matrix multiplication in the bundle is of the form PUP^{-1} where U is a $M_n ZYZ$ matrix. In order to find what basis we shall use for multiplication and what permutation matrices are allowed, we first look at a theorem that tells us about the effect of permutation matrix on the exponentiation of non-diagonal basis elements.

Lemma 4.6. *Let $0 < \alpha \leq \beta \leq 2^n$ be a pair of even integers, and $P_{(\alpha,\beta)}$ denote a 2-cycle permutation on 2^n elements. Then*

$$P_{(\alpha,\beta)} \exp\left(i\theta_{h_\beta(\alpha-1)}U_{h_\beta(\alpha-1)}^{(2^n)}\right) \exp\left(i\theta_{f_\beta(\alpha-1)}U_{f_\beta(\alpha-1)}^{(2^n)}\right) \exp\left(i\theta_{h_{\beta-1}(\alpha)}U_{h_{\beta-1}(\alpha)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta-1}(\alpha)}U_{f_{\beta-1}(\alpha)}^{(2^n)}\right) P_{(\alpha,\beta)}$$

is a block diagonal matrix of the form $M_n Y Z Y$ given by

$$\left[\begin{array}{c|c|c|c} U_2 & 0 & 0 & 0 \\ \hline 0 & U_4 & 0 & 0 \\ \hline 0 & 0 & \ddots & 0 \\ \hline 0 & 0 & 0 & U_{2^n} \end{array} \right]$$

such that

$$\begin{aligned} U_\alpha &= \exp(i\theta_{h_\beta(\alpha-1)}\sigma_1) \exp(i\theta_{f_\beta(\alpha-1)}\sigma_2) \exp(i(\theta_{f_{\beta-1}(\alpha)} + \theta_{h_{\beta-1}(\alpha)})\sigma_3) \\ U_\beta &= \exp(i(\theta_{f_\beta(\alpha-1)} + \theta_{h_\beta(\alpha-1)})\sigma_3) \exp(i\theta_{h_{\beta-1}(\alpha)}\sigma_1) \exp(-i\theta_{f_{\beta-1}(\alpha)}\sigma_2) \\ U_{2l} &= \exp(i(\theta_{f_{\beta-1}(\alpha)} + \theta_{h_{\beta-1}(\alpha)} + \theta_{f_\beta(\alpha-1)} + \theta_{h_\beta(\alpha-1)})\sigma_3), \quad l \in \{1, 2, \dots, 2^{n-1}\} \setminus \{\alpha/2, \beta/2\}. \end{aligned}$$

Proof: Note that

$$\begin{aligned} \exp(i\theta_{h_\beta(\alpha-1)}U_{h_\beta(\alpha-1)}^{(2^n)}) &= \left[\begin{array}{ccc|c} e^{i(\theta_{h_\beta(\alpha-1)})D_{\alpha-2}} & & & \\ & \cos(\theta_{h_\beta(\alpha-1)}) & & i \sin(\theta_{h_\beta(\alpha-1)}) \\ & i \sin(\theta_{h_\beta(\alpha-1)}) & e^{i(\theta_{h_\beta(\alpha-1)})D_{\beta-\alpha+1}} & \cos(\theta_{h_\beta(\alpha-1)}) \\ & & & e^{i(\theta_{h_\beta(\alpha-1)})D_{2^n-\beta}} \end{array} \right], \\ \exp(i\theta_{f_\beta(\alpha-1)}U_{f_\beta(\alpha-1)}^{(2^n)}) &= \left[\begin{array}{ccc|c} e^{i(\theta_{f_\beta(\alpha-1)})D_{\alpha-2}} & & & \\ & \cos(\theta_{f_\beta(\alpha-1)}) & & \sin(\theta_{f_\beta(\alpha-1)}) \\ & -\sin(\theta_{f_\beta(\alpha-1)}) & e^{i(\theta_{f_\beta(\alpha-1)})D_{\beta-\alpha+1}} & \cos(\theta_{f_\beta(\alpha-1)}) \\ & & & e^{i(\theta_{f_\beta(\alpha-1)})D_{2^n-\beta}} \end{array} \right], \end{aligned}$$

where $D_{\alpha-2}$, $D_{\beta-\alpha+1}$ and $D_{2^n-\beta}$ are diagonal matrices of order $\alpha-2$, $\beta-\alpha+1$ and $2^n-\beta$ respectively with the k -th diagonal entry is 1 if k is odd and -1 otherwise. Therefore,

$$\begin{aligned} P_{(\alpha,\beta)} \exp(i\theta_{h_\beta(\alpha-1)}U_{h_\beta(\alpha-1)}^{(2^n)}) \exp(i\theta_{f_\beta(\alpha-1)}U_{f_\beta(\alpha-1)}^{(2^n)}) P_{(\alpha,\beta)} &= \left[\begin{array}{c|c|c} V_2 & 0 & 0 \\ \hline 0 & \ddots & 0 \\ \hline 0 & 0 & V_{2^n} \end{array} \right], \\ P_{(\alpha,\beta)} \exp(i\theta_{h_{\beta-1}(\alpha)}U_{h_{\beta-1}(\alpha)}^{(2^n)}) \exp(i\theta_{f_{\beta-1}(\alpha)}B_{f_{\beta-1}(\alpha)}^{(2^n)}) P_{(\alpha,\beta)} &= \left[\begin{array}{c|c|c} W_2 & 0 & 0 \\ \hline 0 & \ddots & 0 \\ \hline 0 & 0 & W_{2^n} \end{array} \right], \end{aligned}$$

where

$$\begin{aligned} V_\alpha &= \exp(i\theta_{h_\beta(\alpha-1)}\sigma_1) \exp(i\theta_{f_\beta(\alpha-1)}\sigma_2) \\ V_{2l} &= \exp(i\theta_{h_\beta(\alpha-1)}\sigma_3) \exp(i\theta_{f_\beta(\alpha-1)}\sigma_3), \quad \forall l \in \{1, 2, \dots, 2^{n-1}\} \setminus \{\alpha/2\} \\ W_\beta &= \exp(i\theta_{h_{\beta-1}(\alpha)}\sigma_1) \exp(-i\theta_{f_{\beta-1}(\alpha)}\sigma_2) \\ W_{2l} &= \exp(i\theta_{h_{\beta-1}(\alpha)}\sigma_3) \exp(i\theta_{f_{\beta-1}(\alpha)}\sigma_3), \quad \forall l \in \{1, 2, \dots, 2^{n-1}\} \setminus \{\beta/2\}. \end{aligned}$$

Thus the desired result follows. \square

Corollary 4.7. Let $0 < \alpha \leq \beta \leq 2^n$ and $0 < \delta \leq \gamma \leq 2^n$ be two distinct pairs of even integers, and $P_{(\alpha,\beta)}$, $P_{(\delta,\gamma)}$ denote the permutation matrices of order 2^n corresponding to the transpositions (α, β) and (δ, γ) respectively. Then $P_{(\delta,\gamma)}AP_{(\delta,\gamma)} = A$, where

$$A = \exp\left(i\theta_{h_\beta(\alpha-1)}U_{h_\beta(\alpha-1)}^{(2^n)}\right) \exp\left(i\theta_{f_\beta(\alpha-1)}U_{f_\beta(\alpha-1)}^{(2^n)}\right) \exp\left(\theta_{h_{\beta-1}(\alpha)}U_{h_{\beta-1}(\alpha)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta-1}(\alpha)}U_{f_{\beta-1}(\alpha)}^{(2^n)}\right).$$

Proof: The proof is computational and follows from Theorem 4.6. \square

Theorem 4.8 (Product of exponential of certain basis elements make a matrix permutationally similar to a M_nZYZ matrix). Let $P = \prod_{j=1}^{2^{n-2}} P_{(\alpha_j,\beta_j)}$ be a product of 2^{n-2} permutation matrices of order 2^n corresponding to transposition (α_j, β_j) , where $0 < \alpha_j \leq \beta_j \leq 2^n$, $1 \leq j \leq 2^{n-2}$ are distinct pairs of even integers. Then

$$P \left[\prod_{j=1}^{2^{n-2}} \exp\left(i\theta_{h_{\beta_j}(\alpha_j-1)}U_{h_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j}(\alpha_j-1)}U_{f_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \exp\left(i\theta_{h_{\beta_j-1}(\alpha_j)}U_{h_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j-1}(\alpha_j)}U_{f_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \right] P,$$

is a block diagonal matrix of the form M_nYZY , where the diagonal blocks are given by

$$\begin{aligned} U_{\alpha_j} &= \exp\left(i \sum_{m < j} (\theta_{h_{\beta_m}(\alpha_m-1)} + \theta_{f_{\beta_m}(\alpha_m-1)} + \theta_{h_{\beta_m-1}(\alpha_m)} + \theta_{f_{\beta_m-1}(\alpha_m)})\sigma_3\right) \exp\left(i\theta_{h_{\beta_j}(\alpha_j-1)}\sigma_1\right) \\ &\quad \exp\left(i\theta_{f_{\beta_j}(\alpha_j-1)}\sigma_2\right) \exp\left(i(\theta_{f_{\beta_j-1}(\alpha_j)} + \theta_{h_{\beta_j-1}(\alpha_j)})\sigma_3\right) \\ &\quad \exp\left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l-1)} + \theta_{f_{\beta_l}(\alpha_l-1)} + \theta_{h_{\beta_l-1}(\alpha_l)} + \theta_{f_{\beta_l-1}(\alpha_l)})\sigma_3\right) \\ U_{\beta_j} &= \exp\left(i \sum_{m < j} (\theta_{h_{\beta_m-1}(\alpha_m)} + \theta_{f_{\beta_m-1}(\alpha_m)} + \theta_{h_{\beta_m}(\alpha_m-1)} + \theta_{f_{\beta_m}(\alpha_m-1)})\sigma_3\right) \exp\left(i\theta_{h_{\beta_j-1}(\alpha_j)}\sigma_1\right) \\ &\quad \exp\left(-i\theta_{f_{\beta_j-1}(\alpha_j)}\sigma_2\right) \exp\left(i(\theta_{f_{\beta_j}(\alpha_j-1)} + \theta_{h_{\beta_j}(\alpha_j-1)})\sigma_3\right) \\ &\quad \exp\left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l-1)} + \theta_{f_{\beta_l}(\alpha_l-1)} + \theta_{h_{\beta_l-1}(\alpha_l)} + \theta_{f_{\beta_l-1}(\alpha_l)})\sigma_3\right), \end{aligned}$$

$1 \leq j \leq 2^{n-2}$.

Proof: From Lemma 4.7,

$$\begin{aligned} &\prod_{j=1}^{2^{n-2}} P \left[\exp\left(i\theta_{h_{\beta_j}(\alpha_j-1)}U_{h_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j}(\alpha_j-1)}U_{f_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \right. \\ &\quad \left. \exp\left(i\theta_{h_{\beta_j-1}(\alpha_j)}U_{h_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j-1}(\alpha_j)}U_{f_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \right] P \\ &= \prod_{j=1}^{2^{n-2}} P_{(\alpha_j,\beta_j)} \left[\exp\left(i\theta_{h_{\beta_j}(\alpha_j-1)}U_{h_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j}(\alpha_j-1)}U_{f_{\beta_j}(\alpha_j-1)}^{(2^n)}\right) \right. \\ &\quad \left. \exp\left(i\theta_{h_{\beta_j-1}(\alpha_j)}U_{h_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \exp\left(i\theta_{f_{\beta_j-1}(\alpha_j)}U_{f_{\beta_j-1}(\alpha_j)}^{(2^n)}\right) \right] P_{(\alpha_j,\beta_j)} \end{aligned}$$

Then the proof follows from Lemma4.3, Lemma4.6 and theorem 3.9. \square

Remark 4.9. The theorem above deals with the cases when the product is permutationally similar to $M_n ZYZ$ matrices where the permutation matrix P is a product of 2^{n-2} disjoint transpositions of the form $P_{(2m,2n)}$, $m < n$.

Lemma 4.10. Let $1 \leq \alpha < \beta \leq 2^n$ with α is even and β is odd, and $P_{(\alpha,\beta)}$ denote the permutation matrix corresponding to the transposition (α, β) . Then

$$P_{(\alpha,\beta)} \left[\exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha-1)} U_{f_\beta(\alpha-1)}^{(2^n)} \right) \right. \\ \left. \exp \left(i\theta_{h_{\beta+1}(\alpha)} U_{h_{\beta+1}(\alpha)}^{(2^n)} \right) \exp \left(i\theta_{f_{\beta+1}(\alpha)} U_{f_{\beta+1}(\alpha)}^{(2^n)} \right) \right] P_{(\alpha,\beta)}$$

is a block diagonal matrix $U = \left[\begin{array}{c|c|c} U_2 & 0 & 0 \\ \hline 0 & \ddots & 0 \\ \hline 0 & 0 & U_{2^n} \end{array} \right] \in \text{SU}(2^n)$ where

$$U_\alpha = \exp \left(i\theta_{h_\beta(\alpha-1)} \sigma_1 \right) \exp \left(i\theta_{f_\beta(\alpha-1)} \sigma_2 \right) \exp \left(i(\theta_{f_{\beta+1}(\alpha)} + \theta_{h_{\beta+1}(\alpha)}) \sigma_3 \right) \\ U_{\beta+1} = \exp \left(-i(\theta_{f_\beta(\alpha-1)} + \theta_{h_\beta(\alpha-1)}) I_2 \right) \exp \left(i\theta_{h_{\beta+1}(\alpha)} \sigma_1 \right) \exp \left(i\theta_{f_{\beta+1}(\alpha)} \sigma_2 \right) \\ U_{\beta-1} = \exp \left(i(\theta_{f_\beta(\alpha-1)} + \theta_{h_\beta(\alpha-1)}) I_2 \right) \exp \left(i(\theta_{f_{\beta+1}(\alpha)} + \theta_{h_{\beta+1}(\alpha)}) \sigma_3 \right) \\ U_{2l} = \exp \left(i(\theta_{f_{\beta+1}(\alpha)} + \theta_{h_{\beta+1}(\alpha)} + \theta_{f_\beta(\alpha-1)} + \theta_{h_\beta(\alpha-1)}) \sigma_3 \right),$$

where $l \in \{1, 2, \dots, 2^{n-1}\} \setminus \{(\alpha+1)/2, (\beta-1)/2, (\beta+1)/2\}$.

Proof: The proof follows similar to the proof of Lemma4.6. \square

Remark 4.11. It is easy to see that the matrix U in the above lemma is not in the form $M_n ZYZ$ but a special unitary block diagonal matrix consisting of 2×2 unitary blocks.

Theorem 4.12. Let $P = \prod_{j=1}^{2^{n-2}} P_{(\alpha_j, \beta_j)}$ be the product of 2^{n-2} disjoint transpositions where $1 < \alpha_j < \beta_j \leq 2^n$ with α_j is even and β_j is odd, $1 \leq j \leq 2^{n-2}$. Then

$$P \left[\prod_{j=1}^{2^{n-2}} \exp \left(i\theta_{h_{\beta_j}(\alpha_j-1)} U_{h_{\beta_j}(\alpha_j-1)}^{(2^n)} \right) \exp \left(i\theta_{f_{\beta_j}(\alpha_j-1)} U_{f_{\beta_j}(\alpha_j-1)}^{(2^n)} \right) \right. \\ \left. \exp \left(i\theta_{h_{\beta_j+1}(\alpha_j)} U_{h_{\beta_j+1}(\alpha_j)}^{(2^n)} \right) \exp \left(i\theta_{f_{\beta_j+1}(\alpha_j)} U_{f_{\beta_j+1}(\alpha_j)}^{(2^n)} \right) \right] P$$

is equal to $U = \left[\begin{array}{c|c|c} U_2 & 0 & 0 \\ \hline 0 & \cdot & 0 \\ \hline 0 & 0 & U_{2^n} \end{array} \right] \in \text{SU}(2^n)$, where

$$U_{\alpha_j} = \begin{cases} \exp \left(i \sum_{m < j} (\theta_{h_{\beta_m}(\alpha_m - 1)} + \theta_{f_{\beta_m}(\alpha_m - 1)} + \theta_{h_{\beta_m + 1}(\alpha_m)} + \theta_{f_{\beta_m + 1}(\alpha_m)}) \sigma_3 \right) \\ \exp \left(i \theta_{h_{\beta_j}(\alpha_j - 1)} \sigma_1 \right) \exp \left(i \theta_{f_{\beta_j}(\alpha_j - 1)} \sigma_2 \right) \exp \left(i (\theta_{f_{\beta_j + 1}(\alpha_j)} + \theta_{h_{\beta_j + 1}(\alpha_j)}) \sigma_3 \right) \\ \exp \left(i \sum_{l=j+1, l \neq k}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l - 1)} + \theta_{f_{\beta_l}(\alpha_l - 1)} + \theta_{h_{\beta_l + 1}(\alpha_l)} + \theta_{f_{\beta_l + 1}(\alpha_l)}) \sigma_3 \right) \\ \exp \left(i (\theta_{f_{\beta_k}(\alpha_k - 1)} + \theta_{h_{\beta_k}(\alpha_k - 1)}) I_2 \right) \text{ if } \beta_k - 1 = \alpha_j, k \geq j \\ \\ \exp \left(i (\theta_{f_{\beta_k}(\alpha_k - 1)} + \theta_{h_{\beta_k}(\alpha_k - 1)}) I_2 \right) \\ \exp \left(i \sum_{0 < m \neq k < j} (\theta_{h_{\beta_m}(\alpha_m - 1)} + \theta_{f_{\beta_m}(\alpha_m - 1)} + \theta_{h_{\beta_m + 1}(\alpha_m)} + \theta_{f_{\beta_m + 1}(\alpha_m)}) \sigma_3 \right) \\ \exp \left(i \theta_{h_{\beta_j}(\alpha_j - 1)} \sigma_1 \right) \exp \left(i \theta_{f_{\beta_j}(\alpha_j - 1)} \sigma_2 \right) \exp \left(i (\theta_{f_{\beta_j + 1}(\alpha_j)} + \theta_{h_{\beta_j + 1}(\alpha_j)}) \sigma_3 \right) \\ \exp \left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l - 1)} + \theta_{f_{\beta_l}(\alpha_l - 1)} + \theta_{h_{\beta_l + 1}(\alpha_l)} + \theta_{f_{\beta_l + 1}(\alpha_l)}) \sigma_3 \right) \text{ if } \beta_k - 1 = \alpha_j, k \leq j \\ \\ \exp \left(i \sum_{0 < m \neq k < j} (\theta_{h_{\beta_m}(\alpha_m - 1)} + \theta_{f_{\beta_m}(\alpha_m - 1)} + \theta_{h_{\beta_m + 1}(\alpha_m)} + \theta_{f_{\beta_m + 1}(\alpha_m)}) \sigma_3 \right) \\ \exp \left(i \theta_{h_{\beta_j}(\alpha_j - 1)} \sigma_1 \right) \exp \left(i \theta_{f_{\beta_j}(\alpha_j - 1)} \sigma_2 \right) \exp \left(i (\theta_{f_{\beta_j + 1}(\alpha_j)} + \theta_{h_{\beta_j + 1}(\alpha_j)}) \sigma_3 \right) \\ \exp \left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l - 1)} + \theta_{f_{\beta_l}(\alpha_l - 1)} + \theta_{h_{\beta_l + 1}(\alpha_l)} + \theta_{f_{\beta_l + 1}(\alpha_l)}) \sigma_3 \right), \text{ otherwise} \end{cases}$$

and

$$U_{\beta_j + 1} = \begin{cases} \exp \left(i (\theta_{f_{\beta_k}(\alpha_k - 1)} + \theta_{h_{\beta_k}(\alpha_k - 1)}) I_2 \right) \exp \left(i \sum_{0 < m \neq k < j} (\theta_{h_{\beta_m + 1}(\alpha_m)} + \theta_{f_{\beta_m + 1}(\alpha_m)} + \theta_{h_{\beta_m}(\alpha_m - 1)} + \theta_{f_{\beta_m}(\alpha_m - 1)}) \sigma_3 \right) \\ \exp \left(-i (\theta_{f_{\beta_j}(\alpha_j - 1)} + \theta_{h_{\beta_j}(\alpha_j - 1)}) I_2 \right) \exp \left(i \theta_{h_{\beta_j + 1}(\alpha_j)} \sigma_1 \right) \exp \left(i \theta_{f_{\beta_j + 1}(\alpha_j)} \sigma_2 \right) \\ \exp \left(i (\theta_{f_{\beta_j}(\alpha_j - 1)} + \theta_{h_{\beta_j}(\alpha_j - 1)}) \sigma_3 \right) \\ \exp \left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l - 1)} + \theta_{f_{\beta_l}(\alpha_l - 1)} + \theta_{h_{\beta_l + 1}(\alpha_l)} + \theta_{f_{\beta_l + 1}(\alpha_l)}) \sigma_3 \right) \text{ if } \beta_k - 1 = \beta_j + 1, k < j \\ \\ \exp \left(i \sum_{0 < m < j} (\theta_{h_{\beta_m + 1}(\alpha_m)} + \theta_{f_{\beta_m + 1}(\alpha_m)} + \theta_{h_{\beta_m}(\alpha_m - 1)} + \theta_{f_{\beta_m}(\alpha_m - 1)}) \sigma_3 \right) \\ \exp \left(-i (\theta_{f_{\beta_j}(\alpha_j - 1)} + \theta_{h_{\beta_j}(\alpha_j - 1)}) I_2 \right) \exp \left(i \theta_{h_{\beta_j + 1}(\alpha_j)} \sigma_1 \right) \exp \left(i \theta_{f_{\beta_j + 1}(\alpha_j)} \sigma_2 \right) \\ \exp \left(i (\theta_{f_{\beta_j}(\alpha_j - 1)} + \theta_{h_{\beta_j}(\alpha_j - 1)}) \sigma_3 \right) \exp \left(i \sum_{l=j+1}^{2^{n-2}} (\theta_{h_{\beta_l}(\alpha_l - 1)} + \theta_{f_{\beta_l}(\alpha_l - 1)} + \theta_{h_{\beta_l + 1}(\alpha_l)} + \theta_{f_{\beta_l + 1}(\alpha_l)}) \sigma_3 \right) \\ \exp \left(i (\theta_{f_{\beta_k}(\alpha_k - 1)} + \theta_{h_{\beta_k}(\alpha_k - 1)}) I_2 \right) \text{ if } \beta_k - 1 = \beta_j + 1, k \geq j \end{cases}$$

$$1 \leq j \leq 2^{n-2}$$

Proof: Follows from 4.10 and follows similar to Theorem 4.8 \square

Remark 4.13. (a) The theorem above deals with the cases when the product of exponential of certain SRBB elements is permutationally similar to $M_n ZYZ$ matrices, where the corresponding permutation matrix is a product of 2^{n-2} disjoint transpositions that are of the form $P_{(\alpha, \beta)}$, α is even and β is odd.

- (b) Besides, from the above theorem we see that when α is even and β is odd, the for any trasposition $P_{(\delta,\gamma)}$ with $(\delta,\gamma) \neq (\alpha,\beta)$ and δ is even and γ is odd then like Corollary 4.7

$$P_{(\delta,\gamma)} \left[\exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha-1)} U_{f_\beta(\alpha-1)}^{(2^n)} \right) \right. \\ \left. \exp \left(i\theta_{h_{\beta+1}(\alpha)} U_{h_{\beta+1}(\alpha)}^{(2^n)} \right) \exp \left(i\theta_{f_{\beta+1}(\alpha)} U_{f_{\beta+1}(\alpha)}^{(2^n)} \right) \right] P_{(\delta,\gamma)}$$

does not give back

$$\exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha+1)} U_{f_\beta(\alpha+1)}^{(2^n)} \right) \exp \left(i\theta_{h_{\beta+1}(\alpha)} U_{h_{\beta+1}(\alpha)}^{(2^n)} \right) \exp \left(i\theta_{f_{\beta+1}(\alpha)} U_{f_{\beta+1}(\alpha)}^{(2^n)} \right)$$

but it gives back

$$\left[\prod_{t=2}^{2^n} \exp \left(i\theta_{t^2-1} U_{t^2-1}^{(2^n)} \right) \right] \exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha-1)} U_{f_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{h_{\beta+1}(\alpha)} U_{h_{\beta+1}(\alpha)}^{(2^n)} \right) \\ \exp \left(i\theta_{f_{\beta+1}(\alpha)} U_{f_{\beta+1}(\alpha)}^{(2^n)} \right) \left[\prod_{t=2}^{2^n} \exp \left(i\theta'_{t^2-1} B_{t^2-1}^{(2^n)} \right) \right]$$

for some $\theta'_{t^2-1}, \theta_{t^2-1}, 2 \leq t \leq 2^n$. Hence the product of exponential of certain SRBB elements scaled with some permutation matrix in Theorem 4.12 does not give a $M_n ZYZ$ matrix but rather a unitary block-diagonal matrix consisting of 2×2 blocks.

Now from equation (12), Theorem 4.8, and Theorem 4.12, for any $1 \leq x \leq 2^{n-1} - 1$, define

$$M_x^e = \Pi \Gamma_x^e \left[\prod_{(\alpha,\beta) \in T_x^e} \exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha-1)} U_{f_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{h_{\beta-1}(\alpha)} U_{h_{\beta-1}(\alpha)}^{(2^n)} \right) \right. \\ \left. \exp \left(i\theta_{f_{\beta-1}(\alpha)} U_{f_{\beta-1}(\alpha)}^{(2^n)} \right) \right] \Pi \Gamma_x^e, \quad (13)$$

$$M_x^o = \Pi \Gamma_x^o \left[\prod_{(\alpha,\beta) \in T_x^o} \exp \left(i\theta_{h_\beta(\alpha-1)} U_{h_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{f_\beta(\alpha-1)} U_{f_\beta(\alpha-1)}^{(2^n)} \right) \exp \left(i\theta_{h_{\beta+1}(\alpha)} U_{h_{\beta+1}(\alpha)}^{(2^n)} \right) \right. \\ \left. \exp \left(i\theta_{f_{\beta+1}(\alpha)} U_{f_{\beta+1}(\alpha)}^{(2^n)} \right) \right] \Pi \Gamma_x^o, \quad (14)$$

where $\Pi \Gamma_x^e$ and $\Pi \Gamma_x^o$ are defined in equation (12). Then it can be seen that $M_x^o \in \text{SU}(2^n)$ is a unitary block diagonal matrix with 2×2 blocks and $M_x^e \in \text{SU}(2^n)$ is a $M_n ZYZ$ matrix, $1 \leq x \leq 2^{n-1} - 1$. Now note that for each x , M_x^e and M_x^o include $4 \times 2^{n-2} = 2^n$ non-diagonal SRBB elements, and a total of $2 \times (2^{n-1} - 1) \times 2^n = 2^{2n} - 2^{n+1}$ SRBB elements. Further, from Lemma 4.4, note that there are $2 \times 2^{n-1} = 2^n$ non-diagonal SRBB elements whose product gives us a matrix of the form $M_n ZYZ$. Thus the total number of non-diagonal basis elements $2^{2n} - 2^n = 2^{2n} - 2^{n+1} + 2^n$ SRBB elements which contribute to unitary block diagonal matrices of matrices of type $M_n ZYZ$ which we will now employ to redefine an approximation for any unitary matrix of order 2^n .

Approximation of unitary matrices of order 2^n with optimal ordering of the SRRB:

Define

$$\zeta(\Theta_\zeta) = \prod_{j=2}^{2^n} \exp\left(i\theta_{j^2-1} U_{j^2-1}^{(2^n)}\right) \quad (15)$$

$$\Psi(\Theta_\psi) = \left(\prod_{j=1}^{2^{n-1}} \exp\left(i\theta_{(2j-1)^2} U_{(2j-1)^2}^{(2^n)}\right) \exp\left(i\theta_{(4j^2-2j)} U_{(4j^2-2j)}^{(2^n)}\right) \right) \left(\prod_{x=1}^{2^{n-1}-1} (\Pi\Gamma_x^e) M_x^e (\Pi\Gamma_x^e) \right) \quad (16)$$

$$\Phi(\Theta_\phi) = \left(\prod_{x=1}^{2^{n-1}-1} (\Pi\Gamma_x^o) M_x^o (\Pi\Gamma_x^o) \right). \quad (17)$$

Then note that $\zeta(\Theta_\zeta)$ is the product of exponential of all diagonal SRBB elements, $\Psi(\Theta_\psi)$ is the product of matrices of type $M_n ZY Z$ and permutation scaling of $M_n ZY Z$ type matrices, and $\Phi(\Theta_\phi) \in \mathfrak{su}(2^n)$ is product of unitary block diagonal matrices, which we will use in the construction of the circuits for these matrices in Section 5. Then we propose a quantum neural network framework [3] for approximating a unitary matrix as follows. Given $U \in \text{SU}(2^n)$ approximate U as

$$U = \prod_{l=1}^L \zeta(\Theta_\zeta^{(l)}) \Psi(\Theta_\psi^{(l)}) \Phi(\Theta_\phi^{(l)}) \quad (18)$$

where l is called the layer and we call the equation (18) is called the L -layer approximation of U with

$$\Theta_\zeta^{(l)} = \left\{ \theta_{j^2-1}^{(l)} \mid 2 \leq j \leq 2^n \right\}, \quad (19)$$

$$\Theta_\psi^{(l)} = \left\{ \theta_{h_\beta(\alpha-1)}^{(l)}, \theta_{f_\beta(\alpha-1)}^{(l)}, \theta_{h_{\beta-1}(\alpha)}^{(l)}, \theta_{f_{\beta-1}(\alpha)}^{(l)}, \theta_{(2j-1)^2}^{(l)}, \theta_{4j^2-2j}^{(l)} \mid 1 \leq j \leq 2^{n-1}, \right. \\ \left. (\alpha, \beta) \in T_x^e, 1 \leq x \leq 2^{n-1} - 1 \right\}, \quad (20)$$

$$\Theta_\phi^{(l)} = \left\{ \theta_{h_\beta(\alpha-1)}^{(l)}, \theta_{f_\beta(\alpha-1)}^{(l)}, \theta_{h_{\beta+1}(\alpha)}^{(l)}, \theta_{f_{\beta+1}(\alpha)}^{(l)} \mid (\alpha, \beta) \in T_x^o, 1 \leq x \leq 2^{n-1} - 1 \right\}. \quad (21)$$

It may seem from the equation (18) that we can change the ordering of making the product of the matrices $\zeta(\Theta_\zeta^{(l)})$, $\Psi(\Theta_\psi^{(l)})$, $\Phi(\Theta_\phi^{(l)})$, which is indeed possible. However, from the perspective of design of quantum circuits for U in order to reduce the count of $CNOT$ gates, this choice of ordering facilitates the nullification of effects of certain $CNOT$ gates while considering this ordering. For instance, see Section 5.6.

4.1 Numerical simulations

In this section we report the performance of the proposed algorithms for approximating unitary matrices through product of exponential of the proposed RB basis elements in optimal ordering. We have considered several unitary matrices sampled from the Haar distribution and the standard well-known unitaries for two, three and four qubits. Given a target unitary matrix, the initial choice of the parameters can influence the output unitary matrix and since the objective function is non-convex, the optimal approximated values of the parameters may lead to a local minimum. Thus we generate multiple random points from uniform distribution and normal distribution for the set of parameters $\Theta = \{\theta_1, \dots, \theta_{2^{2n}-1}\}$, where $0 \leq \theta_j \leq 2\pi, 1 \leq j \leq 2^{2n} - 1$ and execute the proposed algorithms. Finally, we report the error that is least among all those initial parameter

Algorithm 2 Modified Algorithm for Approximating $2^n \times 2^n$ special unitary matrix

Provided: $U_1 \in \text{SU}(2^n)$, $U_j^{(2^n)} \in \mathcal{U}(2^n)$, $1 \leq j \leq 2^{2n} - 1$, $\zeta(\Theta_\zeta)$, $\Psi(\Theta_\psi)$, $\Phi(\Theta_\phi)$ given by equation (15) - (17).

Input: $\Theta_\zeta^{(0)}$, $\Theta_\psi^{(0)}$, $\Theta_\phi^{(0)}$, $\epsilon > 0$

Output: $A = \prod_t \zeta(\Theta_\zeta^{(t)})\Psi(\Theta_\psi^{(t)})\Phi(\Theta_\phi^{(t)})$ such that $\|U - A\|_F \leq \epsilon$

procedure (Unitary Matrix U) ▷

$A \rightarrow I$

for $t = 1; t++$ **do**

Use an optimization method like Nelder-Mead/Powell's or Gradient descent method to find $\Theta_\zeta^{(t)}$, $\Theta_\psi^{(t)}$, $\Theta_\phi^{(t)}$ such that

$$\min_{\Theta_\zeta^{(t)}, \Theta_\psi^{(t)}, \Theta_\phi^{(t)}} \left\| U - \zeta(\Theta_\zeta^{(t)})\Psi(\Theta_\psi^{(t)})\Phi(\Theta_\phi^{(t)}) \right\|_F = \epsilon_t$$

if $\epsilon_t \leq \epsilon$ **then**

Break

$A \rightarrow A\zeta(\Theta_\zeta^{(t)})\Psi(\Theta_\psi^{(t)})\Phi(\Theta_\phi^{(t)})$

else

$U_{t+1} \rightarrow U_t A^*$

end if

End

end for

End

End Procedure

end procedure

values. From our simulations, we sampled 600 random unitary matrices and we observe that the error lies mostly between 10^{-12} to 10^{-15} except at a few cases where the error is of the order 10^{-4} .

We compare our findings with the results found in [26, 46, 25] and see that our method for 2-qubits is faster as it does not need to perform singular value decomposition. Like [46, 25], we don't need to convert the target matrices into magic basis/states and perform Schmidt decomposition in order to check for separable states which is non-trivial and time consuming. We have also seen that employing the modified ordering of the proposed basis elements and decomposing a 2-qubit gate using the original ordering of the basis elements with $(\prod_{j=1}^{15} \exp(i\theta_j U_j^{(4)}))^L$ with $L = 1$ and applying Algorithm 2, the error is same. We have performed Algorithm 2 on MATLAB and Python 3.0 on a system with 16GB RAM, Intel(R) Core(TM) i5 – 1035G1 CPU @1.00GHz/1.19GHz for 2-qubit and 3-qubit examples. For 4-qubit examples, we have performed the simulations using supercomputer PARAM Shakti of IIT Kharagpur.

We mention that the issue with the methods described in [26, 25] lies in the fact that calculating ζ_k, U_A, U_B such that $U_A \otimes U_B e^{i\zeta_k} |\psi_k\rangle = |\phi_k\rangle$ is a non-trivial process and we have verified the calculation for a handful of 'easy' matrices. However, for generic matrices, the process is difficult. Among the synthesized 600 2-qubit Haar random unitary matrices, 300 are used for simulating with original ordering and 300 using modified ordering of the SRBB elements. We have used Nelder-Mead method of minimization in our algorithm. The method proposed in [46, 25] gives us results with errors of order 10^{-15} however, it is more time consuming than our method since, one has to be aware of the unitary matrix in order to convert its eigenvalues into magic basis states. So the problem has to be tackled individually for each unitary matrix. For our proposed method however, one need not even know about the unitary matrix and we can reach our result.

We report the error and time taken for simulating certain standard 2-qubit unitaries in Table 1, the errors for simulating random 600 unitary matrices are provided in Figure 1, both are obtained by setting $L = 1$. We consider several standard unitaries and 100 random unitaries sampled from Haar distribution for 3-qubit systems. In table 3 we report the error for the standard unitaries, and the errors for random unitaries are plotted in Figure 2 considering one, two and three iterations. Further, we generate 100 3-qubit Haar random unitaries that are 4-sparse and 6-sparse. The 4-sparse unitaries contain two blocks of order 4 and their permutations whereas the 6-sparse unitaries contain two blocks of order 6 and 2 and their permutations. The errors for these unitaries using Algorithm 2 lies between 10^{-12} and 10^{-7} for up to one iteration/layer. Next we consider certain standard 4-qubit unitaries and report the error in Table 4. It is to be noted that our algorithm works better if the unitary matrix is sparse. We speculate that this is due to the performance of the optimization algorithms which need not perform well for large search spaces.

Finally we perform simulation for 100 unitaries of order three and five i.e. for unitaries which define evolution of three and five dimensional quantum states. The error are obtained after approximating the Haar random unitaries and employing Algorithm 1 in Figure 4.

The execution time for approximating the target unitaries described in Table 1 are significantly improved compared to our previous simulation that we reported in the earlier (conference) version of this paper. The algorithm are implemented in Python 3.0 and the run time for approximating several unitary matrices of order 2^2 given by $XX, YY, ZZ, ZX, CNOT(2, 1)$ and the phase gates are extremely fast. The justification of this phenomena lies in the fact that we have exploited the sparsity pattern of these matrices mentioned and selected a list of basis elements for the approximation as given by Table 2. We employ the Nelder-Mead method as the optimization methods to determine the values of the parameters, however, we observe that using Powell's method also produces a similar result. The choice of the initial values of the parameters is decided by a randomization techniques as follows. We generate multiple random points (10 to 100) from normal

| Matrix | Time taken in seconds in our method | Error from our Method | Error from[46] circuit + our method |
|----------------------------|---|------------------------------|--|
| CNOT | 24 | $7.03793017 \times 10^{-14}$ | 3.9×10^{-15} |
| <i>Grover</i> ₂ | 13 | $9.87612962 \times 10^{-14}$ | 1.72×10^{-14} |
| XX | 12 | $7.33016345 \times 10^{-15}$ | 9.4×10^{-13} |
| YY | 39 | $6.24698228 \times 10^{-14}$ | 3.5×10^{-14} |
| ZZ | 13 | $6.22407276 \times 10^{-14}$ | 8.34×10^{-14} |
| SWAP | 23 | $6.15361435 \times 10^{-13}$ | 3.6×10^{-15} |
| XZ | 28 | $8.07143891 \times 10^{-14}$ | 7.62×10^{-13} |
| ZX | 14 | $3.40555621 \times 10^{-14}$ | 6.91×10^{-13} |
| ZY | 28 | $3.36666967 \times 10^{-13}$ | 5.32×10^{-14} |
| CNOT(2,1) | 04 | $2.12476637 \times 10^{-14}$ | 1.36×10^{-13} |
| DCNOT | 24 | $4.31202055 \times 10^{-14}$ | 8.2×10^{-14} |
| XNOR | 15 | $5.70538776 \times 10^{-14}$ | 6.22×10^{-14} |
| iSWAP | 36 | $9.73113534 \times 10^{-14}$ | 4.78×10^{-13} |
| fSWAP | 26 | $1.64656376 \times 10^{-13}$ | 5.83×10^{-13} |
| C-Phase | 10 | $3.17597256 \times 10^{-13}$ | 7.1×10^{-14} |
| XY | 22 | $2.14722235 \times 10^{-14}$ | 6.65×10^{-13} |
| \sqrt{SWAP} | 22 | $2.24302075 \times 10^{-13}$ | 8.51×10^{-13} |
| \sqrt{iSWAP} | 28 | $8.22872467 \times 10^{-15}$ | 6.18×10^{-14} |
| <i>QFT</i> ₂ | 42 | $5.11674305 \times 10^{-13}$ | 7.83×10^{-13} |

Table 1: Error and time for simulating standard 2-qubit unitaries

| Matrix | 2-qubit Basis elements chosen from SRBB along with identity matrix I_4 |
|----------------|---|
| CNOT | $I_4, U_3^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{12}^{(4)}, U_{15}^{(4)}$ |
| $Grover_2$ | all |
| XX | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{10}^{(4)}, U_{12}^{(4)}, U_{13}^{(4)}, U_{15}^{(4)}$ |
| YY | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{10}^{(4)}, U_{12}^{(4)}, U_{13}^{(4)}, U_{15}^{(4)}$ |
| ZZ | $U_3^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| SWAP | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| XZ | $I_4, U_3^{(4)}, U_4^{(4)}, U_5^{(4)}, U_7^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{11}^{(4)}, U_{12}^{(4)}, U_{14}^{(4)}, U_{15}^{(4)}$ |
| ZX | $I_4, U_1^{(4)}, U_2^{(4)}, U_3^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{12}^{(4)}, U_{15}^{(4)}$ |
| ZY | $I_4, U_1^{(4)}, U_2^{(4)}, U_3^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{12}^{(4)}, U_{15}^{(4)}$ |
| CNOT(2,1) | $I_4, U_3^{(4)}, U_8^{(4)}, U_{11}^{(4)}, U_{14}^{(4)}, U_{15}^{(4)}$ |
| DCNOT | $U_1^{(4)}, U_2^{(4)}, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{11}^{(4)}, U_{12}^{(4)}, U_{14}^{(4)}, U_{15}^{(4)}$ |
| XNOR | $U_1^{(4)}, U_2^{(4)}, U_3^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| iSWAP | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| fSWAP | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| C-Phase | $I_4, U_3^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| XY | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_9^{(4)}, U_{10}^{(4)}, U_{12}^{(4)}, U_{13}^{(4)}, U_{15}^{(4)}$ |
| \sqrt{SWAP} | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| \sqrt{iSWAP} | $I_4, U_3^{(4)}, U_4^{(4)}, U_6^{(4)}, U_8^{(4)}, U_{15}^{(4)}$ |
| QFT_2 | all |

Table 2: List of SRBB elements that are used for implementing the approximation algorithms

distribution for the set of parameters lie in the interval $[0, 2\pi)$. Further, The algorithm is stopped immediately when the objective function goes below our specified threshold for the error bound ($\epsilon \leq 5 \times 10^{-12}$) in order to account for fast run time. We speculate that the run time can be improved further in a system with a better configuration than ours.

5 Quantum circuit representation of unitary matrices of order 2^n

In the previous section we have introduced a modified ordering while multiplying for approximation of unitary matrices for n -qubit systems. The modified ordering is introduced to incorporate a structure for approximating a target unitary through product of permutation matrices, $M_n ZYZ$ type matrices, and block diagonal matrices when we write a given target unitary as product of exponential of SRBB elements. Further, we provided a neural network framework for bettering the approximation, where a layer is one iteration of the Algorithm 1. Thus, in order to provide a quantum circuit representation of the unitary matrices, we need to provide quantum circuit representation of permutation matrices, which are product of transpositions of particular type, and $M_n ZYZ$ matrices, which are block matrices with each block is a special unitary matrix of order 2, and block diagonal unitary matrices with blocks are of size 2. Below we discuss circuit construction for each of these structured matrices.

| Matrix | 1st iteration Error from our method | QFAST + KAK [50] | UniversalQ [50] | Search Compiler [50] |
|------------|-------------------------------------|----------------------|----------------------|----------------------|
| Toffoli | 4.48×10^{-9} | 1.5×10^{-6} | 2.6×10^{-8} | 2.4×10^{-7} |
| Fredkin | 1.6×10^{-8} | 2.2×10^{-6} | 0 | 5.8×10^{-6} |
| $Grover_3$ | 4.602×10^{-9} | 8.1×10^{-7} | 0 | 5.5×10^{-7} |
| Peres | 2×10^{-8} | 6.8×10^{-7} | 2.1×10^{-8} | 2.3×10^{-7} |
| QFT_3 | 3.1×10^{-9} | 3×10^{-7} | 3×10^{-8} | 4.9×10^{-7} |


Table 3: Error in the Frobenius norm after simulation using one iteration/Layer for 3-qubit standard unitaries

| Matrix | 1st iteration Error from our method | QFAST + KAK [50] | QFAST + UQ [50] | UniversalQ [50] |
|------------|-------------------------------------|----------------------|----------------------|----------------------|
| CCCX | 1.97×10^{-8} | 2.2×10^{-5} | 1.3×10^{-6} | 2.1×10^{-8} |
| $Grover_4$ | 2.12×10^{-9} | – | – | – |
| QFT_4 | 9.331×10^{-8} | 7.9×10^{-7} | 8.5×10^{-7} | 3.9×10^{-8} |


Table 4: Error in the Frobenius norm after simulation using one iteration/Layer for 4-qubit standard unitaries

5.1 Quantum circuits for product of transpositions

Now we construct quantum circuit for the matrix ΠT_x^e , $1 \leq x \leq 2^{n-1} - 1$. First consider an n -qubit quantum circuit consisting of only $(CNOT)_{(n,i)}$, $1 \leq i \leq n - 1$ gates as follows. Let $x \equiv (x_1 x_2 x_3, \dots, x_{n-1})$ denote the binary representation of $0 \leq x \leq 2^{n-1}$ i.e. $x = \sum_{i=1}^{n-1} 2^{n-i-1} x_i$ where $x_i \in \{0, 1\}$. Then for a given x with its binary representation define a circuit with the property that for each $1 \leq i \leq n - 1$ the circuit contains a $(CNOT)_{(n,i)}$ gate if the $x_i = 1$, where $(CNOT)_{(n,i)}$ means a $CNOT$ gate with n -th qubit as the control and i -th qubit as target. Obviously, if $x = 0$ then the corresponding quantum circuit represents the identity matrix, otherwise there is at least one $CNOT$ gate in the circuit. For example, if $n = 2$ and $x = 1$ then the corresponding circuit is



For $n = 3$, the circuits corresponding to $x = 1, 2, 3$ are given by respectively.



Now since $(CNOT)_{(n,i)}$ is a permutation matrix, corresponding to each $0 \leq x \leq 2^{n-1}$, the matrix representation corresponding to each of the quantum circuit is a product of permutation matrices. If $x \equiv (x_1, \dots, x_{n-1})$, the unitary matrix corresponding to the circuit is given by

$$Q_x = A_1 A_2 \dots A_{n-1}, \text{ where } A_i = \begin{cases} I_{2^n}, & \text{if } x_i = 0 \\ (CNOT)_{(n,i)}, & \text{if } x_i = 1. \end{cases}$$




Figure 1: Errors in the Frobenius norm using Algorithm 2, considering original and modified RB basis elements for the decomposition of 2-qubit unitary matrices sampled from Haar distribution.





Figure 2: The errors obtained from up to three iterations (layers) for 3-qubit Haar random unitaries. The error after 3rd iteration lies between 10^{-4} to 10^{-6} .

Then we show that $Q_x = \Pi T_x^e$ for some $1 \leq x \leq 2^{n-1} - 1$. In particular, for $n = 3$, we have


$$\Pi T_1^e = P_{(2,4)} P_{(6,8)}, \Pi T_2^e = P_{(2,6)} P_{(4,8)}, \Pi T_3^e = P_{(2,8)} P_{(4,6)}.$$

Obviously, if $x \neq y$ then $C_x \neq C_y$.

Further, we show that ΠT_x^o can be defined as follows. Suppose $x \equiv (x_1 x_2 x_4 \dots x_{n-1})$ is the binary representation of $0 \leq x \leq n - 1$. Let k be a number between 1 and $n - 1$ such that k is the lowest index for which $x_k = 1$ i.e. for all $i < k, x_i = 0, x_k = 1$. Then $\Pi T_x^o = (CNOT)_{(k,n)} \Pi T_1^e (CNOT)_{(k,n)}$. For example, in a 3-qubit system $\Pi T_1^o, \Pi T_2^o$ and ΠT_3^o are given by respectively




Now we prove the above facts in the following theorems. Note that binary strings $(x_1, x_2, \dots, x_{n-1})$ and non-empty subsets of $[n - 1] = \{1, \dots, n - 1\}$ have a one-one correspondence. Indeed, for a subset Λ of $[n - 1]$, define a binary string $(x_1, x_2, \dots, x_{n-1})$ with $x_i = 1$ if $i \in \Lambda$ and $x_i = 0$



(a) Errors for 4-sparse unitaries wrt original ordering (b) Errors for 4-sparse unitaries wrt modified ordering

Figure 3: Errors in Frobenius norm for simulating random 4-sparse and 6-sparse 3-qubit unitaries with two ordering of the SRBB, considering only one iteration of the algorithm.



(a) Errors for unitaries of order 3

(b) Errors for unitaries of order 5

Figure 4: Error for approximating unitaries of order 3 and 5 using Algorithm 1 up to one iteration. The unitary matrices are sampled at random from Haar distribution and Nelder-Mead is employed for optimization.

otherwise. We denote this function as $\chi : \{0, 1\}^{n-1} \rightarrow 2^{[n-1]}$, which assigns x to Λ . Thus each position of the string represents a characteristic function for Λ .

Theorem 5.1. *Let $\chi : \{0, 1\}^{n-1} \rightarrow 2^{[n-1]}$ be the bijective function as defined above. Then*


$$\Pi\Gamma_x^e = \prod_{\Lambda \in 2^{[n-1]}} P_{(\alpha_\Lambda, \beta_\Lambda)},$$

where $x \equiv (x_1, x_2, \dots, x_{n-1})$, and

$$\begin{aligned} \alpha_\Lambda &= \sum_{i \in \Lambda} x_i 2^{n-i} + \sum_{j \notin \Lambda} x_j 2^{n-j} + 2, \\ \beta_\Lambda &= \sum_{i \in \Lambda} \bar{x}_i 2^{n-i} + \sum_{j \notin \Lambda} x_j 2^{n-j} + 2, \end{aligned}$$

If $\Lambda_1 \neq \Lambda_2 \in [n-1]$ then $(\alpha_{\Lambda_1}, \beta_{\Lambda_1}) \neq (\alpha_{\Lambda_2}, \beta_{\Lambda_2})$, and $\Pi\Gamma_x^e \neq \Pi\Gamma_y^e$ if $x \neq y$.

Proof: First consider the n -qubit quantum circuit corresponding given by



Then the unitary matrix corresponding to the circuit is

$$\prod_{j=1}^k (CNOT)_{(n, m_{k-j+1})},$$

where $m_1 < m_2 < \dots < m_k$, $1 \leq k \leq n - 2$ and $\Lambda = \{m_1, m_2, \dots, m_k\}$ and $x = \sum_{j=1}^k 2^{n-m_j-1} x_{m_j}$.

Now consider the canonical basis of \mathbb{C}^{2^n} denoted as $\{|x_1, x_2, \dots, x_n\rangle | z_i \in \{0, 1\}\}$. Then the output of the above circuit corresponding to the basis elements of \mathbb{C}^{2^n} as inputs are given by


$$|x_1, x_2, \dots, x_{n-1}, 1\rangle \rightarrow |x_1, x_2, \dots, x_{m_1} + 1, \dots, x_{m_2} + 1, \dots, x_{m_k} + 1, \dots, x_{n-1}, 1\rangle$$

and $|x_1, x_2, \dots, x_{n-1}, 0\rangle \rightarrow |x_1, x_2, \dots, x_{n-1}, 0\rangle$. Thus $x_{m_i} \rightarrow \bar{x}_{m_i}$, $1 \leq i \leq k$ and $x_j \rightarrow x_j$, $j \in [n-1] \setminus \{m_1, \dots, m_k\}$.

Let $T : V \rightarrow V$ be a linear transformation on vector space of dimension $2m$ (even integer) such that $T^2 = I$. Let $B = \{v_1, v_2, \dots, v_{2m}\}$ be a basis of V . Then considering B as the basis for both the domain and range spaces of T , and assuming that $T(v_i) = v_j, T(v_j) = v_i, T(v_k) = v_k, k \in \{1, 2, \dots, 2m\} \setminus \{i, j\}$ gives the transposition $P_{(k,j)}$.

Now, in the circuit, the bits are not flipped at p -th position where $p \in [n-1] \setminus \{m_1, m_2, \dots, m_k\}$ and the bits are flipped for x_{m_i} , $1 \leq i \leq k$. Thus, fixing x_{m_i} 's for $1 \leq i \leq k$, we have 2^{n-k-1} transposition permutation matrices. Now these x_{m_i} 's can vary among themselves and have total 2^{k-1} choices (barring the choice where all x_{m_i} 's are 0). Hence, the circuit is a product of $2^{k-1} 2^{n-k-1} = 2^{n-2}$ disjoint transposition permutations. Further since, $(CNOT)_{(n,j)} = I_2^{(\otimes j-1)} (CNOT)_{(n,j)} = I_2^{(\otimes j-1)} \otimes (\prod_{i=1}^{2^{n-j-1}} P_{(2i, 2i+2^{n-j})})$. Hence, the circuit can be written as $\prod_{i=1}^{2^{n-2}} P_{(\alpha_i, \beta_i)}$, $\alpha_i < \beta_i \leq 2^n$, α_i, β_i are even, $1 \leq i \leq 2^{n-2}$. Further $(CNOT)_{(n,j)} = I_2^{\otimes j-1} \otimes \prod_{i=1}^{2^{n-j-1}} P_{(2i, 2i+2^{n-j})}$ Hence the desired result follows.

Now let us take another circuit



such that there exists α_i such that $\alpha_i \neq m_i$, $1 \leq i \leq k$. Hence there exist $\Lambda_1 \neq \Lambda_2 \subset [n-1]$ such that $(\alpha_{\Lambda_1}, \beta_{\Lambda_1}) \neq (\alpha_{\Lambda_2}, \beta_{\Lambda_2})$ if and only if there exists some basis element $|x_1, x_2, \dots, x_{n-1}, 1\rangle$ of \mathbb{C}^{2^n} such that the image of $|x_1, x_2, \dots, x_{n-1}, 1\rangle$ via the former circuit coincides with the image of the later circuit i.e.

$$|x_1, \dots, x_{\alpha_1} + 1, x_{\alpha_1+1}, \dots, x_{\alpha_p} + 1, \dots, x_{n-1}, 1\rangle = |x_1, \dots, x_{m_1} + 1, x_{m_2+1}, \dots, x_{m_k} + 1, \dots, x_{n-1}, 1\rangle.$$

This can happen if and only if $x_{\alpha_1} + 1 = x_{\alpha_1}$ which is impossible. Thus the desired result follows. \square

Then we have the following corollary.

Theorem 5.2. *Let $\chi : \{0, 1\}^{n-1} \rightarrow 2^{[n-1]}$ be the bijective function as defined above. Then*


$$\Pi\Gamma_x^o = \prod_{\Lambda \in 2^{[n-1]}} P_{(\alpha_\Lambda, \beta_\Lambda)},$$

where $x \equiv (x_1, x_2, \dots, x_{n-1})$, and

$$\begin{aligned} \alpha_\Lambda &= \sum_{i \in \Lambda} x_i 2^{n-i} + \sum_{j \notin \Lambda \cup \{n\}} x_j 2^{n-j} + 2, \\ \beta_\Lambda &= \sum_{i \in \Lambda} \bar{x}_i 2^{n-i} + \sum_{j \notin \Lambda} x_j 2^{n-j} + 1. \end{aligned}$$

If $\Lambda_1 \neq \Lambda_2 \in [n-1]$ then $(\alpha_{\Lambda_1}, \beta_{\Lambda_1}) \neq (\alpha_{\Lambda_2}, \beta_{\Lambda_2})$, and $\Pi\Gamma_x^o \neq \Pi\Gamma_y^o$ if $x \neq y$.


Proof: Consider the n -qubit quantum circuit corresponding to $\Pi\Gamma_x^e$, where $x = \sum_{j=1}^k 2^{n-m_j-1} x_{m_j}$ considered in Theorem 5.1. Then $\Pi\Gamma_x^o = (CNOT)_{(m_1, n)} \Pi\Gamma_x^e (CNOT)_{(m_1, n)}$ i.e. the circuit



The rest of the proof is similar to that described in Theorem 5.1. \square

5.2 Quantum circuit for diagonal unitaries

The SRBB basis elements that are diagonal matrices, are given by $U_{j^2-1}^{(2^n)}$, $2 \leq j \leq 2^n$, which are of the form $\otimes_{j=1}^n A_j$, $A_j \in \{I_2, \sigma_3\}$. Given such a basis element for some j , let m be the greatest number such that $A_p = I_2$ for all $p > m$, and let $A_{m_1} = A_{m_2} = \dots, A_{m_k} = \sigma_3$ for some k with $m_1 < m_2 < \dots < m_k < m$. Then a quantum circuit representation of $\exp(i\theta U_{j^2-1}^{(2^n)})$ is given by



which represents the unitary matrix

$$\left(\prod_{l=1}^k (I_2^{\otimes m_l - 1} \otimes (CNOT)_{(m_l, m)} \otimes I_2^{\otimes n - m}) \right) (I_2^{\otimes m - 1} \otimes R_z(\theta) \otimes I_2^{\otimes n - m}) \left(\prod_{l=1}^k (I_2^{\otimes m_l - 1} \otimes (CNOT)_{(m_l, m)} \otimes I_2^{\otimes n - m}) \right)$$


$$\Pi_{i=1}^k (I_2^{\otimes m_i - 1} \otimes (CNOT)_{(m_i, m)} \otimes I_2^{\otimes n - m}) (I_2^{\otimes m - 1} \otimes R_z(\theta) \otimes I_2^{\otimes n - m}) \Pi_{i=1}^k (I_2^{\otimes m_i - 1} \otimes (CNOT)_{(m_i, m)} \otimes I_2^{\otimes n - m}).$$

5.3 Quantum circuit for multi-controlled rotation gates


In this section we propose and analyze quantum circuit for $M_n ZYZ$ matrices. First we have the following theorem.

Theorem 5.3. *A quantum circuit for a $M_n ZYZ$ matrix requires at most $(3 \cdot 2^{n-1} - 2)$ CNOT, and $3 \cdot 2^{n-1}$ rotation gates.*


Proof: From equation (7), the circuit representation of a matrix in the $M_n ZYZ$ form can be written as




Further, from Lemma 3.7,




can be decomposed as




where $\psi_i = \begin{cases} \theta_i + \phi_i & \text{where } 1 \leq i \leq 2^{n-2} \\ \theta_i - \phi_i & \text{where } 2^{n-2} + 1 \leq i \leq 2^{n-1} \end{cases}$ or




where $\psi_i = \begin{cases} \theta_i + \phi_i & \text{where } 1 \leq i \leq 2^{n-2} \\ -\theta_i + \phi_i & \text{where } 2^{n-2} + 1 \leq i \leq 2^{n-1} \end{cases}$. Hence




can be written as




Further, each circuit of the form




at least requires 2^{n-1} gates [26]. Thus the number of *CNOT*s in the circuit given by equation (26) is $6 \cdot 2^{n-2} + 4 = 3 \cdot 2^{n-1} + 4$. Now in section of the circuit




the right most *CNOT* gate of




by decomposing it into



and the leftmost *CNOT* gate of




by decomposing into



cancels each other out after further decomposition. This is because

$$(CNOT)_{(2,n)}(CNOT)_{(1,n)}(CNOT)_{(2,n)} = (CNOT)_{(1,n)}.$$

The similar cancellation happens for the part of the circuit given by



Therefore, the total number of $CNOT$ gates that cancels out each other is 6. Hence, there are at most $3 \cdot 2^{n-1} - 2$ $CNOT$ gates. \square

5.4 Quantum circuit for unitary block diagonal matrices

Now we consider circuit implementation of block diagonal unitary matrices, each block of which is a special unitary matrix of order 2.

Corollary 5.4. *A quantum circuit for a block diagonal matrix $U \in \text{SU}(2^n)$ of the form*

$$\left[\begin{array}{c|c|c|c|c} U_2 & 0 & 0 & 0 & 0 \\ \hline 0 & U_4 & 0 & 0 & 0 \\ \hline 0 & 0 & 0 & \ddots & 0 \\ \hline 0 & 0 & 0 & 0 & U_{2^n} \end{array} \right],$$

where $U_{2^j} \in \text{U}(2)$, $1 \leq j \leq 2^{n-1}$, requires at most $5 \cdot 2^{n-1} - 6$ $CNOT$ gates.

Proof: From Theorem 4.2, any block diagonal matrix $U \in \text{SU}(2^n)$ consisting of 2×2 blocks is of the form

$$\left(\prod_{t=2}^{2^n} \exp \left(i\theta_{t^2-1} U_{t^2-1}^{(2^n)} \right) \right) \left(\prod_{j=1}^{2^{n-1}} \exp \left(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \right) \left(\prod_{t=2}^{2^n} \exp \left(i\theta'_{t^2-1} U_{t^2-1}^{(2^n)} \right) \right) \quad (27)$$

where $\theta_{4j^2-2j} \in \mathbb{R}$, $1 \leq j \leq 2^{n-1}$, $\theta_{t^2-1}, \theta'_{t^2-1} \in \mathbb{R}$ can be obtained by employing the methods from the proofs of Theorem 3.3 and Theorem 3.9. This means that exponential of all diagonal matrices in the basis of $\mathfrak{su}(2^n)$ needs to be multiplied on both sides. i.e. we are using the product

$$\left(\prod_{p=1}^{2^{n-1}} \exp \left(it_p (\chi_n^{-1}(p)) \right) \right) \left(\prod_{j=1}^{2^{n-1}} \exp \left(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)} \right) \right) \left(\prod_{p=1}^{2^{n-1}} \exp \left(it'_p (\chi_n^{-1}(p)) \right) \right)$$

i.e. we are multiplying all diagonal matrices of the form $\bigotimes_{i=1}^n A_i$, $A_i \in \{I, \sigma_3\}$ barring the identity matrix. Now the set $\{\bigotimes_{i=1}^n A_i \mid A_i \in \{I, \sigma_3\}, 1 \leq i \leq n\} \setminus \{I_{2^n}\} = \left\{ \bigotimes_{i=1}^{n-1} A_i \otimes I_2 \mid A_i \in \{I, \sigma_3\}, 1 \leq i \leq n-1 \right\} \cup \left\{ \bigotimes_{i=1}^{n-1} A_i \otimes Z \mid A_i \in \{I, \sigma_3\}, 1 \leq i \leq n-1 \right\} \setminus \{I_{2^n}\}$.

Hence using Theorem 3.9 the product in equation (27) this product can alternatively be written as

$$\left(\prod_{p=1}^{2^{n-1}-1} \exp(it_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right) \tilde{U} \left(\prod_{p=1}^{2^{n-1}-1} \exp(it'_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right)$$


for some $t_p, t'_p \in \mathbb{R}$ where \tilde{U} is a $M_n ZYZ$ matrix, χ_{n-1} is discussed in Definition 2.4. This is because by Theorem 3.9

$$\tilde{U} = \left(\prod_{p=0}^{2^{n-1}-1} \exp(i\tilde{t}_p(\chi_{n-1}^{-1}(p) \otimes Z)) \right) \left(\prod_{j=1}^{2^{n-1}} \exp(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)}) \right) \left(\prod_{p=0}^{2^{n-1}-1} \exp(it'_p(\chi_{n-1}^{-1}(p) \otimes Z)) \right)$$

for some real \tilde{t}_p, t'_p

Moreover, we have shown how to define a quantum circuit for the exponential of matrices of the form $\bigotimes_{i=1}^{n-1} A_i \otimes I$, $A_i \in \{I_2, \sigma_3\}$. For each $A_i = \sigma_3$, we apply 2 *CNOT* gates. Also the exponential of the matrix $\sigma_3 \otimes I_2^{(\otimes n-1)}$ does not require *CNOT* gates. Hence the number of *CNOT* gates for a given $\bigotimes_{i=1}^{n-1} A_i \otimes I_2$, $A_i \in \{I_2, \sigma_3\}$ is $2 + 4 + \dots + 2^{n-2} = 2^{n-1} - 2$. This is because the product $\left(\prod_{p=1}^{2^{n-k}-1} \exp(it_p(\chi_{n-k}^{-1}(p) \otimes I_2^{(\otimes k)})) \right)$ requires 2^{n-k} *CNOT* gates from [26] and Theorem 5.3. Therefore the total number of *CNOT* gates for the product $\left(\prod_{p=1}^{2^{n-1}-1} \exp(it_p(\chi_{n-1}^{-1}(p) \otimes I_2)) \right)$ is $2^n - 4$. Since the product is applied on both sides of a $M_n ZYZ$ matrix, the total number of *CNOT* gates becomes $2^{n+1} - 4$. The rest of the proof follows from Theorem 5.3 since $3 \cdot 2^{n-1} - 2 + 2^{n+1} - 4$ gives us the result. \square

Now we provide a quantum circuit corresponding to the above block diagonal matrix in $\mathfrak{su}(2^n)$ is given by



The circuit represents a block diagonal matrix since it represents the product

$$\left(\prod_{k=2}^{n-1} \left(\prod_{p=1}^{2^{n-k}-1} \exp(it_p(\chi_{n-k}^{-1}(p) \otimes I_2^{\otimes k})) \right) \right) V \left(\prod_{k=2}^{n-1} \left(\prod_{p=1}^{2^{n-k}-1} \exp(it'_p(\chi_{n-k}^{-1}(p) \otimes I_2^{\otimes k})) \right) \right)$$


where

$$V = \left(\prod_{p=0}^{2^{n-1}-1} \exp(it_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right) \left(\prod_{j=1}^{2^{n-1}} \exp(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)}) \right) \left(\prod_{p=0}^{2^{n-1}-1} \exp(it'_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right),$$


which gives us the form described in Theorem 4.2

5.5 Scalable quantum circuits for approximating special unitary matrices


From Algorithm 2, we see that we a special unitary matrix $U \in \text{SU}(2^n)$ can be approximated in the circuit form with one layer is given by




where writing $\zeta(\Theta_\zeta)$, $\Psi(\Theta_\psi)$ and $\Phi(\Theta_\phi)$ as quantum circuits respectively are given by




Recall that $M_x^o \in \text{SU}(2^n)$ is a block diagonal matrix with 2×2 blocks and $M_x^e, 1 \leq x \leq 2^{n-1} - 1$ is a $M_n ZY Z$ matrix. Further, since $\prod_{j=1}^{2^{n-1}} \exp(i\theta_{(2j-1)^2} U_{(2j-1)^2}^{(2^n)}) \exp(i\theta_{(4j^2-2j)} U_{(4j^2-2j)}^{(2^n)})$ is $M_n ZY Z$ type matrix, a quantum circuit representation is given by



Next, for $1 \leq x \leq 2^{n-1} - 1$, $\Pi \Pi_x^e M_x^e \Pi \Pi_x^e$ can have the quantum circuit representation as




Finally, for $1 \leq x \leq 2^{n-1} - 1$ a quantum circuit representation of $\Pi \Pi_x^o M_x^o \Pi \Pi_x^o$ is given by




where the circuit representation of M_x^o is of the form mentioned in equation (28). Finally the circuits for $\Pi \Pi_x^o$ and $\Pi \Pi_x^e$ can be determined by Theorem 5.2 and Theorem 5.1.

Now we consider scaling the proposed n -qubit circuit into an $(n + 1)$ -qubit circuit for approximating special unitary matrices. Since the proposed circuit consists of mainly three types of circuits: circuits for product of transpositions, $M_n ZYZ$ circuit, and circuit for block diagonal unitary matrices, it is enough to describe the techniques for extending these circuits from n -qubit to $(n + 1)$ -qubit systems as follows. We denote $\Pi\Gamma_{m,y}^s$ for $\Pi\Gamma_y^s$ with m -qubit systems, $s \in \{e, o\}$. $(CNOT)_{(i,j)}$ represents a $CNOT$ gate with i -th qubit as control qubit and j -th qubit is the target qubit.

- Construction of scalable circuits for $\Pi\Gamma_x^e$: If the circuit representation of $\Pi\Gamma_x^e$ for n -qubit system given in Theorem 5.1 as $\boxed{\Pi\Gamma_{n,x}^e}$ for some $x \in \{0, \dots, 2^{n-1} - 1\}$ then the circuit for $\Pi\Gamma_{n+1,y}^e$, $1 \leq y \leq 2^n - 1$ is given by




if $y = x$, and




if $y = 2^{n-1} + x$.

- Construction of scalable circuits for $\Pi\Gamma_x^o$: As above, the circuit for $\Pi\Gamma_{n+1,y}^o$, $1 \leq y \leq 2^n - 1$ is given by




if $y = x$, and




if $y = 2^{n-1} + x$, $x \in \{0, \dots, 2^{n-1} - 1\}$.


- Construction of scalable circuits for $M_n ZYZ$: This follows from equivalence of circuits given in equation (3) and equation (4). Indeed, $M_{n+1} ZYZ$ is of the form



and



is equivalent to



where

$$\psi_j = \begin{cases} \theta_j + \phi_j & \text{where } 1 \leq j \leq 2^{n-1} \\ \theta_j - \phi_j & \text{where } 2^{n-2} + 1 \leq j \leq 2^n. \end{cases}$$

- Construction of scalable circuits for block diagonal matrices: This follows similarly due to the above property of $M_n ZYZ$, $1 \leq n$ which define the quantum circuit for a block diagonal unitary matrix given by equation (28).

Theorem 5.5. *The circuit implementation of a special unitary matrix on n -qubits with L layers using Algorithm 2 requires at most $L(2 \cdot 4^n + (n-5)2^{n-1})$ CNOT gates, $L(\frac{3}{2} \cdot 4^n - \frac{5}{2} 2^n + 1)$ R_z gates where L is the number of iterations/layers.*

Proof: Obviously, we to consider the matrices the number of rotation gates and CNOT gates for circuit implementation of $\zeta(\Theta_\zeta)$, $\Psi(\Theta_\psi)$, and $\Phi(\Theta_\phi)$. From equations (15), (16) and (17), we have

$$\zeta(\Theta_\zeta) = \prod_{j=1}^{2^n} \exp\left(i\theta_{j^2-1} U_{j^2-1}^{(2^n)}\right), \quad \Psi(\Theta_\psi) = M_0^e \left(\prod_{x=1}^{2^{n-1}-1} (\Pi \Gamma_x^e) M_x^e (\Pi \Gamma_x^e) \right), \quad \Phi(\Theta_\phi) = \prod_{x=1}^{2^{n-1}-1} (\Pi \Gamma_x^o) M_x^o (\Pi \Gamma_x^o),$$

where $M_0^e = \left(\prod_{j=1}^{2^{n-1}} \exp\left(i\theta_{(2j-1)^2} U_{(2j-1)^2}^{(2^n)}\right) \exp\left(i\theta_{(4j^2-2j)} U_{(4j^2-2j)}^{(2^n)}\right) \right)$

Using Lemma 4.4, Theorem 5.3 and from [31, 26], a $M_n ZYZ$ matrix takes $3 \cdot 2^{n-1} - 2$ $CNOT$ gates and $3 \cdot 2^{n-1}$ R_z, R_y gates. Now M_x^e, M_0^e are $M_n ZYZ$ matrices and $M_x^o \in \mathfrak{su}(2^n)$ is a block diagonal matrix for $1 \leq x \leq 2^{n-1} - 1$. Then

$$\zeta(\Theta_\zeta) = \left(\prod_{p=1}^{2^{n-1}-1} \exp(i\theta_p(\chi_{n-1}^{-1}(p) \otimes I_2)) \right) \left(\prod_{q=0}^{2^{n-1}-1} \exp(i\theta_q(\chi_{n-k}^{-1}(p) \otimes \sigma_3)) \right)$$

where χ is described in Definition 2.4.

Further the term M_0^e in $\Psi(\Theta_\psi)$ is a $M_n ZYZ$ matrix and from Theorem 3.9 can be written as

$$\left(\prod_{p=0}^{2^{n-1}-1} \exp(i\theta_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right) \left(\prod_{j=1}^{2^{n-1}} \exp(i\theta_{4j^2-2j} U_{4j^2-2j}^{(2^n)}) \right) \left(\prod_{p=1}^{2^{n-1}} \exp(i\theta'_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right)$$


where all necessary terms have been defined in Theorem 3.9. Hence the term $\left(\prod_{p=0}^{2^{n-1}-1} \exp(i\theta_p(\chi_{n-1}^{-1}(p) \otimes \sigma_3)) \right)$ from M_0^e and the term $\left(\prod_{q=0}^{2^{n-1}-1} \exp(i\theta_q(\chi_{n-k}^{-1}(p) \otimes \sigma_3)) \right)$ from $\zeta(\Theta_\zeta)$ are multiplied to form the product $\left(\prod_{p=1}^{2^{n-1}-1} \exp(i\theta_p(\chi_{n-1}^{-1}(p) \otimes I_2)) \right) \tilde{M}_0^e$ where \tilde{M}_0^e is a $M_n ZYZ$ matrix such that \tilde{M}_0^e is equal to $\left(\prod_{q=0}^{2^{n-1}-1} \exp(i\theta_q(\chi_{n-k}^{-1}(p) \otimes \sigma_3)) \right) M_0^e$.

Next, $\Phi(\Theta_\phi) = \prod_{x=1}^{2^{n-1}-1} \Pi \Gamma_x^o M_x^o \Pi \Gamma_x^o$ where M_x^e is a block diagonal matrix, which requires $(5 \cdot 2^{n-1} - 6)$ $CNOT$ gates and $2(2^n - 1)$ R_z gates and 2^{n-1} number of R_y gates from Corollary 5.4.


Finally, from the construction of $\Pi \Gamma_x^e$, $1 \leq x \leq 2^{n-1} - 1$ from Theorem 5.1, it can be seen that for different values of x , we get a quantum circuit which consists of k (depending on x) ($CNOT$)-gates having control at the n -th qubit and target is at i -th qubit for $1 \leq i \leq n-1$. Thus the number of $(CNOT)_{(n,i)}$ gates present in the construction of $\Pi \Gamma_x^e$ is at most 1 for a fixed i . Hence, one can either choose one target qubit from $\{1, 2, \dots, n-1\}$ and in this case total number of $CNOT$ gates will be $\binom{n-1}{1}$. One can also choose 2 target qubits from $\{1, 2, \dots, n-1\}$, in this case total number of $CNOT$ gates will be $2 \binom{n-1}{2}$. Continuing in this way, the number of $CNOT$ gates that is required for the permutation matrices is $\sum_{l=1}^{n-1} l \binom{n-1}{l}$ for all the permutation matrices in the set $\mathcal{P}_{2^n, \text{even}}$. On the other hand, $\Pi \Gamma_x^o$ for each $1 \leq x \leq 2^{n-1} - 1$ requires two more ($CNOT$) gates than $\Pi \Gamma_x^e$ from our construction. Hence the total $\sum_{l=1}^{n-1} (l+2) \binom{n-1}{l}$ number of $CNOT$ gates are required for all the permutation matrices in the set $\mathcal{P}_{2^n, \text{odd}}$. Now $\sum_{l=1}^{n-1} i \binom{n-1}{l} = \sum_{l=1}^{n-1} (n-1) \binom{n-2}{l-1} = 2^{n-2} (n-1)$, which gives us the total $CNOT$ gates for permutation matrices required to construct elements from $\mathcal{P}_{2^n, \text{odd}}$ and $\mathcal{P}_{2^n, \text{even}}$ to be $2(2^{n-1} - 1) + (n-1)2^{n-1}$. Since permutation matrices are multiplied on both sides, the number of $CNOT$ gates becomes $4(2^{n-1} - 1) + (n-1)2^n$. Including the $CNOT$ gates used for the construction of unitary diagonal matrices in the circuit in 5.4, total number of $CNOT$ gates for constructing product of all unitary diagonal matrices is $2^n - 2$.

However, looking at $\zeta(\Theta)\Psi(\Theta)\Phi(\Theta)$, we see that the diagonal matrices of the form $\bigotimes_{l=1}^{n-1} A_l \otimes \sigma_3$ gets multiplied with the first $M_n ZYZ$ matrix in $\Psi(\Theta_\psi)$ where $A_l \in \{I_2, \sigma_3\}$. Hence only diagonal matrices of the form $\bigotimes_{l=1}^{n-1} A_l \otimes I_2$ remain from $\zeta(\Theta_\zeta)$. Consequently, the total number of $CNOT$ gates for constructing the product of diagonal unitary matrices i.e. $\zeta(\Theta_\zeta) = 2^{n-1} - 2$. The same result holds true for number of R_z gates. Hence the desired result follows. \square

In order to construct a $(n+1)$ -qubit circuit from an n -qubit circuit, we add one more qubit at the top of the current circuit. i.e.



to



Now we present the following algorithms based on the above discussion that will help us to create an algorithm for constructing scalable quantum circuits.

Algorithm 3 Creating circuit for $\Pi\Gamma_{n+1,y}^e, 0 \leq y \leq 2^n - 1$ from circuit $\Pi\Gamma_{n,x}^e, 0 \leq x \leq 2^{n-1} - 1$

Provided: *CNOT* gates, circuits $\Pi\Gamma_{n,x}^e, 0 \leq x \leq 2^{n-1} - 1$.

Input: $y \in \{0, \dots, 2^n - 1\}$

Output: $\eta(y, 2^{n+1}, \text{even})$ gives a circuit of $I_2 \otimes \Pi\Gamma_{n+1,y}^e$

for $y = 0 : 2^n - 1; y++$ **do**

if $y < 2^{n-1}$ **then**

$x = y$

$\eta(y, 2^{n+1}, \text{even}) \rightarrow$ Add one qubit layer at the top. See equation (30)

else

$x = y - 2^{n-1}$

$\eta(y, 2^{n+1}, \text{even}) \rightarrow$ Add one qubit layer at the top and add a $(\text{CNOT})_{(n+1,1)}$ to left of $\Pi\Gamma_{n,x}^e$. See equation (31)

end if

end for

Now we give Algorithm 7, combining all the Algorithms 3-6 for the generation of $(n + 1)$ -qubit circuit from n -qubit circuit.

In Figure 5 we plot the growth of *CNOT* gate count as the number of qubits increases while approximating special unitary matrices through Algorithm 2.

5.6 Quantum circuit for two-qubit unitaries

Now we provide a parametric quantum circuit for approximating 2-qubit special unitaries following Algorithm 2. The circuit given in Figure consists of 14 *CNOT* gates and 16 1-qubit gates. Our circuit does not give minimum number of *CNOT* gates however, our results coincide with number of *CNOT* gates found in CS Decomposition [26]. The Table 5 gives the counts of *CNOT* gates that are required to represent a special unitary matrix of order 4.

Algorithm 4 Creating circuit for $\Pi\Gamma_{n+1,y}^o, 0 \leq y \leq 2^n - 1$ from circuit $\Pi\Gamma_{n,x}^o, 0 \leq x \leq 2^{n-1} - 1$

Provided: $CNOT$ gates, circuits $\Pi\Gamma_{n,x}^e, \Pi\Gamma_{n,x}^o, 0 \leq x \leq 2^{n-1} - 1$.

Input: $y \in \{0, \dots, 2^n - 1\}$

Output: $\eta(y, 2^{n+1}, odd)$ gives a circuit of $\Pi\Gamma_{n+1,x}^o$

for $y = 0 : 2^n - 1; y ++$ **do**

if $y < 2^{n-1}$ **then**

$x = y$

$\eta(y, 2^{n+1}, odd) \rightarrow$ Add one qubit layer at the top. See equation (32)

else

$x = y - 2^{n-1}$

$\eta(y, 2^{n+1}, odd) \rightarrow$ Add one qubit layer at the top and add a $(CNOT)_{(n+1,1)}$ gate, $(CNOT)_{(1,n+1)}$ gate to the left of $I_2 \otimes \Pi\Gamma_{n,x}^e$. Add another $(CNOT)_{(n+1,1)}$ gate to the right of $\Pi\Gamma_{n,x}^e$. See equation (33)

 End If

end if

 End For

end for

End

Algorithm 5 Creating circuit for $(n+1)$ -qubit rotation gates $F_{(n+1)}(R_z)$ from multi-qubit rotation gates $F_{(n)}(R_z)$

Provided: $CNOT$ gates, circuits $F_n(R_z)$.

Input: $a_1, a_2, a_4 \dots, a_{2^{n-1}}$ for $F_n(R_z) := F_n(R_z(a_1, a_2 \dots, a_{2^{n-1}}))$ and $b_1, b_2, b_3 \dots, b_{2^{n-1}}$ for $F_n(R_z) := F_n(R_z(b_1, b_2 \dots, b_{2^{n-1}}))$

Output: $\xi(F_n(R_z(a_1, \dots, a_{2^{n-1}})), F_n(R_z(b_1, \dots, b_{2^{n-1}}))) := \xi(F_n(R_z), F_n(R_z))$ gives a circuit of $F_{n+1}(R_z)$

 Add one layer of qubit at the top. Add a $(CNOT)_{(1,n+1)}$ to the left of $I_2 \otimes F_n(R_z)$. Then add another $(CNOT)_{(1,n+1)}$ and a $I_2 \otimes F_n(R_z)$. See equation (34) and equation (35).

 End

Algorithm 6 Creating circuit for $(n+1)$ -qubit rotation gates $F_{(n+1)}(R_y)$ from multi-qubit rotation gates $F_{(n)}(R_y)$

Provided: $CNOT$ gates, circuits $F_n(R_y)$.

Input: $a_1, a_2, a_4 \dots, a_{2^{n-1}}$ for $F_n(R_y) := F_n(R_y(a_1, a_2 \dots, a_{2^{n-1}}))$ and $b_1, b_2, b_3 \dots, b_{2^{n-1}}$ for $F_n(R_y) := F_n(R_y(b_1, b_2 \dots, b_{2^{n-1}}))$

Output: $\xi(F_n(R_y(a_1, \dots, a_{2^{n-1}})), F_n(R_y(b_1, \dots, b_{2^{n-1}}))) := \xi(F_n(R_y), F_n(R_y))$ gives a circuit of $F_{n+1}(R_z)$

 Add one layer of qubit at the top. Add a $(CNOT)_{(1,n+1)}$ to the left of $I_2 \otimes F_n(R_y)$. Then add another $(CNOT)_{(1,n+1)}$ and a $I_2 \otimes F_n(R_y)$. See equation (3) and equation (4).

 End

Algorithm 7 Creating a $(n + 1)$ -qubit circuit to approximate any $U \in \text{SU}(2^{n+1})$ from a n -qubit circuit that approximates any $\hat{U} \in \text{SU}(2^n)$

Provided: *CNOT* gates and 1 qubit rotation gates.

Input: n -qubit circuit that approximates any $\hat{U} \in \text{SU}(2^n)$ and of the form mentioned in equation 29 i.e. $\zeta(\Theta)\Psi(\Theta)\psi(\Theta)$ where all the terms have been defined in equation 29

Output: $(n + 1)$ -qubit circuit that approximates any $U \in \text{SU}(2^{n+1})$

procedure ▷

Add a qubit layer at the top/beginning of the circuit.

Create product of all 2^{n+1} special unitary diagonal matrices from product of all 2^n special unitary diagonal matrices using $\xi(F_i(R_z), F_i(R_z)), 1 \leq i \leq n$ in Algorithm 5.

for $y = 1 : 2^n - 1; y++$ **do**

Use Algorithm 3 create $\Pi\Gamma_{n+1,y}^e$ using the function $\eta(y, 2^{n+1}, \text{even})$

Use Algorithm 4 create $\Pi\Gamma_{n+1,y}^o$ using the function $\eta(y, 2^{n+1}, \text{odd})$

Add CNOT gates to convert $\Pi\Gamma_{n,y}^o \rightarrow \Pi\Gamma_{n+1,y}^o$

End

end for

$\zeta(\Theta) \rightarrow \prod_{i=1}^{(2^{n+1}-1)} \exp(\iota\theta_a \chi_{n+1}^{-1}(a))$, (see definition of χ at equation 2.4)

Create a $(n + 1)$ -qubit MZYZ matrix M_0^e from a n qubit MZYZ matrix using $\xi(F_n(R_z), F_n(R_z)), \xi(F_n(R_y), F_n(R_y))$ in Algorithm 5 and Algorithm 6

for $y = 1 : 2^n - 1; y++$ **do**

Create a $(n + 1)$ -qubit MZYZ matrix M_y^e from a n qubit MZYZ matrix using $\xi(F_n(R_z), F_n(R_z)), \xi(F_n(R_y), F_n(R_y))$ in Algorithm 5 and Algorithm 6

Create a $(n + 1)$ -qubit block diagonal special unitary matrix M_y^o from a n qubit block diagonal special unitary matrix using $\xi(F_i(R_z), F_i(R_z)), 1 \leq i \leq n$ in Algorithm 5. and $\xi(F_n(R_y), F_n(R_y))$ in Algorithm 6

End

end for

for $y = 1 : 2^n - 1; y++$ **do**

$\psi(\Theta) \rightarrow M_0^e \Pi\Gamma_{n+1,y}^e M_y^e P_{(y, 2^{n+1}, \text{even})}$

$\psi(\Theta) \rightarrow \psi(\Theta)$

$\Phi(\Theta) \rightarrow \Pi\Gamma_{n+1,x}^o M_x^o \Pi\Gamma_{n+1,x}^o$

$\Phi(\Theta) \rightarrow \Phi(\Theta)$

End

end for

$\zeta(\Theta)\psi(\Theta)\Phi(\Theta)$

End Procedure

end procedure





Figure 5: Red colored curve denotes the total number of *CNOT* gates required for one layer of multiplication of exponential of basis matrices in n -qubit system and magenta colored curve denotes the additional number of *CNOT* gates are required with the increase of number of qubits

| Implementation | CNOT gates required |
|---------------------------|---------------------|
| Theoretical lower bounds | 3 |
| Iterative unentangling | 8 |
| Givens rotation | 4 |
| Recursive CSD | 14 |
| Recursive CSD (optimized) | 4 |
| QSD | 6 |
| QSD(optimized) | 3 |
| Our Method | 14 |
| Vidal et al.'s Method | 3 |

Table 5: Count of *CNOT* gates for different methods



The circuit given by equation (36) with layer 1 represents the any unitary matrix represented as a product of exponential of SRBB elements in the following order according to Algorithm 2.

$$\begin{aligned}
\zeta(\theta_3, \theta_8, \theta_{15}) &= \exp(i\theta_3 U_3^{(4)}) \exp(i\theta_8 U_8^{(4)}) \exp(i\theta_{15} U_{15}^{(4)}) \\
\Psi(\theta_1, \theta_2, \theta_9, \theta_{12}, \theta_{10}, \theta_{13}, \theta_4, \theta_6) &= \exp(i\theta_1 U_1^{(4)}) \exp(i\theta_2 U_2^{(4)}) \exp(i\theta_9 U_9^{(4)}) \exp(i\theta_{12} U_{12}^{(4)}) \\
&\quad \exp(i\theta_4 U_4^{(4)}) \exp(i\theta_6 U_6^{(4)}) \exp(i\theta_{10} U_{10}^{(4)}) \exp(i\theta_{13} U_{13}^{(4)}) \\
\Phi(\theta_5, \theta_7, \theta_{11}, \theta_{14}) &= \exp(i\theta_5 U_5^{(4)}) \exp(i\theta_7 U_7^{(4)}) \exp(i\theta_{11} U_{11}^{(4)}) \exp(i\theta_{14} U_{14}^{(4)}),
\end{aligned}$$

where $U_j^{(4)}$, $1 \leq j \leq 15$ are the SRBB elements of $\mathbb{C}^{2^2 \times 2^2}$.

The parametric quantum circuit representation of the circuit equation (36) is as follows:

The quantum circuit for $\zeta(\Theta)$ is given by equation (37)

$$(37)$$

Hence, circuit for $\Psi(\Theta)$ in equation (38)

$$(38)$$

The circuit of $\exp(i\theta_1 B_1^{(4)}) \exp(i\theta_2 B_2^{(4)}) \exp(i\theta_9 B_9^{(4)}) \exp(i\theta_{12} B_{12}^{(4)})$ is

$$(39)$$

where

$$\alpha' = \frac{2\theta_9 + 2\theta_{12} - \kappa_2 - \kappa_1 - \gamma_2 - \gamma_1}{4}, \quad \beta' = \frac{2\theta_9 + 2\theta_{12} + \kappa_2 + \kappa_1 - \gamma_2 - \gamma_1}{4}$$

$$\alpha = \frac{2\theta_1 + 2\theta_2 + \kappa_2 - \kappa_1 + \gamma_2 - \gamma_1}{4}, \quad \beta = \frac{-2\theta_1 - 2\theta_2 - \kappa_2 + \kappa_1 + \gamma_2 - \gamma_1}{4}$$

with

$$\mu_1 = \arccos \sqrt{(\cos \theta_1 \cos \theta_2)^2 + (\sin \theta_1 \sin \theta_2)^2}, \quad \mu_9 = \arccos \sqrt{(\cos \theta_9 \cos \theta_{12})^2 + (\sin \theta_9 \sin \theta_{12})^2}$$

$$\gamma_1 = \arccos \frac{\cos \theta_1 \cos \theta_2}{\cos \mu_1}, \quad \gamma_2 = \arccos \frac{\cos \theta_1 \sin \theta_2}{\sin \mu_1}$$

$$\kappa_1 = \arccos \frac{\cos \theta_9 \cos \theta_{12}}{\cos \mu_9}, \quad \kappa_2 = \arccos \frac{\cos \theta_9 \sin \theta_{12}}{\sin \mu_9}.$$

The circuit of $\exp(i\theta_4 B_4^{(4)}) \exp(i\theta_6 B_6^{(4)}) \exp(i\theta_{10} B_{10}^{(4)}) \exp(i\theta_{13} B_{13}^{(4)})$ is in equation (40).

$$(40)$$

where

$$a = \frac{2\theta_4 + 2\theta_6 + g_1 - g_2 + p_2 - p_1}{4}, \quad b = \frac{2\theta_4 + 2\theta_6 - g_1 + g_2 + p_2 - p_1}{4}$$

$$a' = \frac{2\theta_{10} + 2\theta_{13} + g_1 + g_2 - p_2 - p_1}{4}, \quad b' = \frac{-2\theta_{10} - 2\theta_{13} - g_1 - g_2 - p_2 - p_1}{4}$$


with

$$m_4 = \arccos \sqrt{(\cos \theta_4 \cos \theta_6)^2 + (\sin \theta_4 \sin \theta_6)^2}, \quad m_{10} = \arccos \sqrt{(\cos \theta_{10} \cos \theta_{13})^2 + (\sin \theta_{10} \sin \theta_{13})^2},$$

$$g_1 = \arccos \frac{\cos \theta_4 \cos \theta_6}{\cos m_4}, \quad g_2 = \arccos \frac{\cos \theta_4 \sin \theta_6}{\sin m_4}$$

$$p_1 = \arccos \frac{\cos \theta_{10} \cos \theta_{13}}{\cos m_{10}}, \quad p_2 = \arccos \frac{\cos \theta_{10} \sin \theta_{13}}{\sin m_{10}}.$$

The quantum circuit for $\Phi(\Theta_\phi)$ is given by equation (41).



where

$$\tilde{\alpha}' = \frac{2\theta_{11} + 2\theta_{14} - \tilde{\kappa}_2 - \tilde{\kappa}_1 - \tilde{\gamma}_2 - \tilde{\gamma}_1}{4}, \quad \tilde{\beta}' = \frac{2\theta_{11} + 2\theta_{14} + \tilde{\kappa}_2 + \tilde{\kappa}_1 - \tilde{\gamma}_2 - \tilde{\gamma}_1}{4},$$

$$\tilde{\alpha} = \frac{2\theta_5 + 2\theta_7 + \tilde{\kappa}_2 - \tilde{\kappa}_1 + \tilde{\gamma}_2 - \tilde{\gamma}_1}{4}, \quad \tilde{\beta} = \frac{-2\theta_5 - 2\theta_7 - \tilde{\kappa}_2 + \tilde{\kappa}_1 + \tilde{\gamma}_2 - \tilde{\gamma}_1}{4}$$

with

$$u_5 = \arccos \sqrt{(\cos \theta_5 \cos \theta_7)^2 + (\sin \theta_5 \sin \theta_7)^2}, \quad u_{11} = \arccos \sqrt{(\cos \theta_{11} \cos \theta_{14})^2 + (\sin \theta_{11} \sin \theta_{14})^2}$$

$$\tilde{\gamma}_1 = \arccos \frac{\cos \theta_5 \cos \theta_7}{\cos u_5}, \quad \tilde{\gamma}_2 = \arccos \frac{\cos \theta_5 \sin \theta_7}{\sin u_5},$$

$$\tilde{\kappa}_1 = \arccos \frac{\cos \theta_{11} \cos \theta_{14}}{\cos u_{11}}, \quad \tilde{\kappa}_2 = \arccos \frac{\cos \theta_{11} \sin \theta_{14}}{\sin u_{11}}.$$

Remark 5.6. From Table 5 it is clear that the proposed method does not build a quantum circuit with optimal number of CNOT gates for 2-qubit unitaries compared to most of the methods in literature. However, most of these methods such as Vidal et al. are not scalable i.e. one cannot construct a quantum circuit for a generic unitary for $(n+1)$ -qubit system from the quantum circuit for unitary matrices of n -qubit systems, $n \geq 2$. Thus we emphasize that existing methods for scalable circuit design for unitaries are adhoc. On the contrary, the proposed method for quantum circuit design of $(n+1)$ -qubit systems can be designed just by adding a few CNOT and single-qubit gates to the existing circuit for n -qubit systems, which is a byproduct of the proposed recursive Hermitian unitary basis for the algebras of matrices of order 2^n .

Conclusion: We have introduced a recursive method for generation of a basis for the algebra of complex matrices of order $d \geq 2$ with basis elements as Hermitian unitary 1-sparse matrices. This basis is used to develop parametric representation of unitary matrices employing a Lie group theoretic approach. Further, optimized-based algorithms are proposed to approximate any target unitary matrix by determining optimal values of the parameters. Then the above results are applied to determine parametric representation of unitary matrices of order $d = 2^n$, which represent unitary evolution of n -qubit systems, by defining a new basis, which we call Standard Recursive Block Basis for the algebra of complex matrices of order 2^n obtained by changing certain elements of the above basis. Consequently, a scalable quantum circuit model is implemented using the approximation algorithm in a quantum neural network framework for unitary evolution of n -qubit systems. The performance of the approximation algorithms is investigated through several examples for standard and random 2-qubit, 3-qubit and 4-qubit unitaries. It is observed that the error of approximation reduces with the increase of iteration or layer of the approximation algorithm.

In future, we plan to explore finding a connection between the optimal number of layers for the approximation algorithm with the error of accuracy of the algorithm for a given target unitary matrix. Besides, the performance of the proposed approximation algorithm can be investigated by implementing the proposed scalable quantum circuits in available NISQ computers with large number of qubits. Finding the efficiency of the parametrized quantum circuit with the available

restricted set of quantum gates with specific quantum hardware architecture is another problem that should be explored in the future.

Acknowledgement: The authors thank Sabyasachi Chakraborty for his help with the numerical simulations using PARAM Shakti HPC at IIT Kharagpur. Rohit Sarma Sarkar acknowledges support through Prime Minister Research Fellowship (PMRF), Government of India.

References

- [1] G. AMMAR, W. GRAGG, AND L. REICHEL, *Constructing a unitary hessenberg matrix from spectral data*, In Numerical linear algebra, digital signal processing and parallel algorithms, NATO ASI Subseries F, 20(1), G. H. Golub and P. Dooren, eds., Springer Berlin, Heidelberg, 1991, pp. 385–395.
- [2] A. BARENCO, C. H. BENNETT, R. CLEVE, D. P. DIVINCENZO, N. MARGOLUS, P. SHOR, T. SLEATOR, J. A. SMOLIN, AND H. WEINFURTER, *Elementary gates for quantum computation*, Phys. Rev. A, 52 (1995), pp. 3457.
- [3] M. BENEDETTI, E. LLOYD, S. SACK, AND M. FIORENTINI, *Parameterized quantum circuits as machine learning models*, Quantum Sci. Technol., 4 (2019), pp. 043001.
- [4] S. BILEK AND K. WOLD, *Recursive variational quantum compiling*, arXiv preprint, arXiv:2203.08514, 2022.
- [5] A. BOCHAROV, M. ROETTELER, AND K. M. SVORE, *Efficient synthesis of probabilistic quantum circuits with fallback*, Phys. Rev. A, 91 (2015), pp. 052317.
- [6] R. COURTLAND, *Google aims for quantum computing supremacy [news]*, IEEE Spectrum, 54 (2017), pp. 9–10.
- [7] C. M. DAWSON AND M. A. NIELSEN, *The solovay-kitaev algorithm*, arXiv preprint quant-ph/0505030, 2005.
- [8] P. DITA, *On the parametrisation of unitary matrices by the moduli of their elements*, Comm. Math. Phys, 159 (1994), pp. 581–591.
- [9] P. DITA, *Factorization of unitary matrices*, J. Phys. A., 36 (2003), pp. 2781.
- [10] K. FUJII, K. FUNAHASHI, AND T. KOBAYASHI, *Jarlskog’s parametrization of unitary matrices and qudit theory*, Int. J. Geom. Methods Mod. Phys, 3 (2006), pp. 69–283.
- [11] J. GALLIER AND J. QUAINANC, *Differential geometry and Lie groups: a computational perspective*, 12, Springer Nature, Switzerland, 2020.
- [12] V. GHEORGHIU, J. HUANG, S. M. LI, M. MOSCA, AND P. MUKHOPADHYAY, *Reducing the CNOT count for Clifford+ T circuits on NISQ architectures*, IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems, 42 (2022), pp. 1873-1884.
- [13] B. GILES AND P. SELINGER, *Exact synthesis of multiqubit Clifford+ T circuits*, Phys. Rev. A, 87 (2013), pp. 032332.
- [14] G. H. GOLUB AND C. F. VAN LOAN, *Matrix computations*, 3, JHU press, 2013.

- [15] L. GOMES, *Quantum computing: Both here and not here*, IEEE Spectrum, 55 (2018), pp. 42–47.
- [16] A. HARROW, *Quantum compiling*, PhD thesis, Massachusetts Institute of Technology, Department of Physics, 2001.
- [17] L. E. HEYFRON AND E. T. CAMPBELL, *An efficient quantum compiler that reduces T count*, Quantum Sci. Technol., 4 (2018), pp. 015004.
- [18] J. HSU, *Ces 2018: Intel’s 49-qubit chip shoots for quantum supremacy*, IEEE Spectrum Tech Talk, 2018, pp. 1–6.
- [19] C. JARLSKOG, *A recursive parametrization of unitary matrices*, J. Math. Phys, 46 (2005), pp. 103508.
- [20] S. KHATRI, R. LAROSE, A. POREMBA, L. CINCIO, A. T. SORNBORGER, AND P. J. COLES, *Quantum-assisted quantum compiling*, Quantum, 3 (2019), pp. 140.
- [21] A. A. KIRILLOV, *An introduction to Lie groups and Lie algebras*, 113, Cambridge University Press, 2008.
- [22] A. Y. KITAEV, *Quantum computations: algorithms and error correction*, Russian Math. Surveys, 52 (1997), pp. 1191.
- [23] A. Y. KITAEV, A. YU, A. H. SHEN, AND M. N. VYALI, *Classical and Quantum Computation*, American Mathematical Society, 2002.
- [24] V. KLIUCHNIKOV, D. MASLOV, AND M. MOSCA, *Fast and efficient exact synthesis of single qubit unitaries generated by Clifford and T gates*, arXiv preprint arXiv:1206.5236, 2012.
- [25] B. KRAUS AND J. I. CIRAC, *Optimal creation of entanglement using a two-qubit gate*, Phys. Rev. A, 63 (2001), pp. 062309.
- [26] A. M. KROL, A. SARKAR, I. ASHRAF, Z. AL-ARS, AND K. BERTELS, *Efficient decomposition of unitary matrices in quantum circuit compilers*, Applied Sciences, 12 (2022), pp. 759.
- [27] L. MADDEN, A. AKHRIEV, AND A. SIMONETTO, *Sketching the best approximate quantum compiling problem*, arXiv preprint arXiv:2205.04025, 2022.
- [28] L. MADDEN AND A. SIMONETTO, *Best approximate quantum compiling problems*, ACM Trans. Quantum Comput., 3 (2022), pp. 1–29.
- [29] K. MATSUMOTO AND K. AMANO, *Representation of quantum circuits with clifford and pi/8 gates*, arXiv preprint arXiv:0806.3834, 2008.
- [30] G. J. MOONEY, C. D. HILL, AND L. C. HOLLENBERG, *Cost-optimal single-qubit gate synthesis in the clifford hierarchy*, Quantum, 5 (2021), pp. 396.
- [31] M. MÖTTÖNEN, J. J. VARTIAINEN, V. BERGHOLM, AND M. M. SALOMAA *Quantum circuits for general multiqubit gates* Phys. Rev. Lett., 93 (2004), pp. 130502.
- [32] Y. NAKAJIMA, Y. KAWANO, AND H. SEKIGAWA, *A new algorithm for producing quantum circuits using kak decompositions*, arXiv preprint quant-ph/0509196, 2005.

- [33] M. A. NIELSEN AND I. CHUANG, *Quantum computation and quantum information*, Cambridge University Press, 2002.
- [34] B. OWREN AND A. MARTHINSEN, *Integration methods based on canonical coordinates of the second kind*, Numer. Math., 87 (2001), pp. 763–790.
- [35] A. PALER, I. POLIAN, K. NEMOTO, AND S. J. DEVITT, *Fault-tolerant, high-level quantum circuits: form, compilation and description*, Quantum Sci. Technol., 2 (2017), pp. 025003.
- [36] T. T. PHAM, R. VAN METER, AND C. HORSMAN, *Optimization of the solovay-kitaev algorithm*, Phys. Rev. A, 87 (2013), pp. 052332.
- [37] S. V. ROMERO AND J. SANTOS-SUÁREZ, *Paulicomposer: Compute tensor products of pauli matrices efficiently*, arXiv preprint arXiv:2301.00560, 2023.
- [38] N. J. ROSS AND P. SELINGER, *Optimal ancilla-free Clifford+ T approximation of Z-rotations*, Quantum Inf. Comput., 16 (2016), pp. 901–953.
- [39] J. SCHWINGER, *Unitary operator bases*, Proc. Nat. Acad. Sci., 46 (1960), pp. 570–579.
- [40] P. SELINGER, *Quantum circuits of t-depth one*, Phys. Rev. A, 87 (2013), pp. 042302.
- [41] E. A. SETE, W. J. ZENG, AND C. T. RIGETTI, *A functional architecture for scalable quantum computing*, In 2016 IEEE International Conference on Rebooting Computing (ICRC), IEEE, 2016, pp. 1–6.
- [42] V. V. SHENDE, I. L. MARKOV, AND S. S. BULLOCK, *Minimal universal two-qubit controlled-not-based circuits*, Phys. Rev. A, 69 (2004), pp. 062321.
- [43] V. V. SHENDE, S. S. BULLOCK, AND I. L. MARKOV, *Synthesis of quantum logic circuits*, In Proceedings of the 2005 Asia and South Pacific Design Automation Conference, 2005, pp. 272–275.
- [44] V. S. VARADARAJAN, *Lie groups, Lie algebras, and their representations*, 102, Springer Science & Business Media, 2013.
- [45] D. VENTURELLI, M. DO, E. RIEFFEL, AND J. FRANK, *Compiling quantum circuits to realistic hardware architectures using temporal planners*, Quantum Sci. Technol., 3 (2018), pp. 025004.
- [46] G. VIDAL AND C. M. DAWSON, *Universal quantum circuit for two-qubit transformations with three controlled-not gates*, Phys. Rev. A, 69 (2004), pp. 010301.
- [47] D. S. WANG, A. G. FOWLER, AND L. C. HOLLENBERG, *Surface code quantum computing with error rates over 1%*, Phys. Rev. A, 83 (2011), pp. 020302.
- [48] R. F. WERNER, *All teleportation and dense coding schemes*, J. Phys. A, 34 (2001), pp. 7081.
- [49] H. WEYL, *Quantenmechanik und gruppentheorie*, Z. Phys, 46 (1927), pp. 1–46.
- [50] E. YOUNIS, K. SEN, K. YELICK, C. IANCU, *Qfast: Quantum synthesis using a hierarchical continuous circuit space*, arXiv preprint, arXiv:2003.04462, 2020

- [51] E. YOUNIS, K. SEN, K. YELICK, AND C. IANCU, *QFAST: Conflating Search and Numerical Optimization for Scalable Quantum Circuit Synthesis*, In 2021 IEEE International Conference on Quantum Computing and Engineering (QCE), IEEE, 2021, pp. 232–243.
- [52] Y. ZHIYENBAYEV, V. AKULIN, AND A. MANDILARA, *Quantum compiling with diffusive sets of gates*, Phys. Rev. A, 98 (2018), pp. 012325.
- [53] X. ZHOU, D. W. LEUNG, AND I. L. CHUANG, *Methodology for quantum logic gate construction*, Phys. Rev. A, 62 (2000), pp. 052316.

6 Appendix

Proof of Theorem 2.1. First observe that the matrices $B_j^{(d)}$, $1 \leq j \leq d^2$ are Hermitian and unitary due to the construction. Also, $\text{Tr}(B_j^{(d)}) = 0$ when d is even and $\text{Tr}(B_j^{(d)}) = 1$ when d is odd. Now we show that these matrices form a linearly independent subset of $\mathbb{C}^{d \times d}$. Suppose d is even. Then setting

$$\begin{aligned}
0 &= \sum_{m=1}^{(d-1)^2-1} c_{1m} \begin{bmatrix} B_m^{(d-1)} & 0 \\ 0 & -1 \end{bmatrix} + \sum_{m=1}^{(d-1)} c_{2m} P_{(m(d-1))} \begin{bmatrix} D & 0 \\ 0 & \sigma_1 \end{bmatrix} P_{(m(d-1))} \\
&+ \sum_{m=1}^{(d-1)} c_{3m} P_{(m(d-1))} \begin{bmatrix} D & 0 \\ 0 & \sigma_2 \end{bmatrix} P_{(m(d-1))} + c_{44} \begin{bmatrix} \Sigma & 0 \\ 0 & -\sigma_3 \end{bmatrix} + c_{55} I_d \\
&= \sum_{m=1}^{(d-1)^2-1} \underbrace{\begin{bmatrix} c_{1m} B_m^{(d-1)} & 0 \\ 0 & -c_{1m} \end{bmatrix}}_A + \sum_{m=1}^{(d-1)} \underbrace{P_{(m(d-1))} \begin{bmatrix} (c_{2m} + c_{3m})D & 0 \\ 0 & c_{2m}\sigma_1 + c_{3m}\sigma_2 \end{bmatrix} P_{(m(d-1))}}_B \\
&+ \underbrace{\begin{bmatrix} c_{44}\Sigma + c_{55}I_{d-2} & 0 \\ 0 & -c_{44}\sigma_3 + c_{55}I_2 \end{bmatrix}}_C. \tag{42}
\end{aligned}$$

It can be seen from equation (42) that the first $d - 1$ entries of the last column of B are given by $c_{2m} - ic_{3m}$, $1 \leq m \leq d - 1$, whereas these corresponding entries in A and C are zero. Also first $n - 1$ entries (left to right) of the last row of B are given by $c_{2m} + ic_{3m}$, $1 \leq m \leq d - 1$, whereas these corresponding entries in A and C are zero. Then it immediately follows that $c_{2m} = c_{3m} = 0$, $1 \leq m \leq d - 1$. Then the equation (42) becomes

$$0 = \sum_{m=1}^{(d-1)^2-1} \begin{bmatrix} c_{1m} B_m^{(d-1)} & 0 \\ 0 & -c_{1m} \end{bmatrix} + \begin{bmatrix} c_{44}\Sigma + c_{55}I_{d-2} & 0 \\ 0 & -c_{44}\sigma_3 + c_{55}I_2 \end{bmatrix}. \tag{43}$$

Further, since $\{B_m^{(d-1)} : 1 \leq m \leq (d-1)^2 - 1\} \cup I_{d-1}$ is linearly independent, then using the same method described above, the matrix $\sum_{m=1}^{(d-1)^2-1} c_{1m} B_j^{(d-1)}$ has all non-diagonal entries 0. Thus the

only terms remain are diagonal matrices i.e. the equation reduces to

$$\begin{aligned}
0 &= \sum_{m=2}^{(d-1)} \begin{bmatrix} c_{1(m^2-1)}B_{(m^2-1)}^{(d-1)} & & 0 \\ & & -c_{1(m^2-1)} \\ & 0 & \end{bmatrix} + \begin{bmatrix} c_{44}\Sigma + c_{55}I_{d-2} & & 0 \\ & & -c_{44}\sigma_3 + c_{55}I_2 \\ 0 & & \end{bmatrix} \\
&= \begin{bmatrix} \sum_{m=2}^{(d-1)} c_{1(m^2-1)}B_{(m^2-1)}^{(d-1)} + c_{44} \begin{bmatrix} \Sigma & 0 \\ 0 & -1 \end{bmatrix} + c_{55}I_{d-1} & & 0 \\ & & & (-\sum_{m=2}^{(d-1)} c_{1(m^2-1)} + c_{44} + c_{55}) \end{bmatrix} \quad (44)
\end{aligned}$$

where $B_{m^2-1}^{(d-1)}$ and $I_{d-1} = B_{(d-1)^2}^{(d-1)}$, $2 \leq m \leq d-1$ are proposed basis elements of $\mathbb{C}^{(d-1) \times (d-1)}$.

For a diagonal matrix M of order d with diagonal entries $m_{jj}, 1 \leq j \leq d$, set $\text{diag}(M) = [m_{11} m_{22} \dots m_{dd}]^T$ as the column vector. Then observe that equation (44) can be described as a linear system $Ax = 0$, where $x = [c_{13} \dots c_{1((d-1)^2-1)} \ c_{44} \ c_{55}]^T$ and

$$A = \left[\text{diag}(B_3^{(d)}) \ \text{diag}(B_8^{(d)}) \ \dots \ \text{diag}(B_{(d-1)^2-1}^{(d)}) \ \text{diag}\left(\begin{bmatrix} \Sigma & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & 1 \end{bmatrix}\right) \ \text{diag}(I_d) \right].$$

Next we show that A is non-singular i.e. the columns of A form a linearly independent set. Suppose

$$\sum_{m=2}^{d-1} \alpha_m \begin{bmatrix} \text{diag}(B_{m^2-1}^{(d)}) \\ -1 \end{bmatrix} + \beta \begin{bmatrix} \text{diag}\left(\begin{bmatrix} \Sigma & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & 1 \end{bmatrix}\right) \\ + \gamma [\text{diag}(I_{d-1})] \end{bmatrix} = 0.$$

Then multiplying the all-one vector $\mathbf{1}_d^T$ from left at the above equation, we obtain $n\gamma = 0$ since sum of entries of all other vectors are zero. This further implies $\gamma = 0$. Thus we have

$$\sum_{m=2}^{d-1} \alpha_m \begin{bmatrix} \text{diag}(B_{m^2-1}^{(d)}) \\ -1 \end{bmatrix} + \beta \begin{bmatrix} \text{diag}\left(\begin{bmatrix} \Sigma & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & 1 \end{bmatrix}\right) \end{bmatrix} = 0.$$

Now note that the first entry of all the vectors in the above vectors are 1. Then considering the first and last entries of the above vectors, we obtain

$$\beta + \sum_{m=2}^{d-1} \alpha_m = 0 \text{ and } \beta - \sum_{m=2}^{d-1} \alpha_m = 0,$$

whose only solution is $\beta = \alpha_m = 0$ for all m . Hence the desired result follows when m is even. The proof for odd m follows similarly. \square

Proof of Theorem 3.3. Any 2-level matrix $U = [U_{\alpha\beta}] \in \text{SU}(2^n)$ of order 2^n is of the form

$$u_{\alpha\beta} = \begin{cases} 1 & \text{if } \alpha = \beta, \alpha, \beta \notin \{p, q\} \\ ae^{i\theta_a} & \text{if } \alpha = p = \beta \\ ae^{-i\theta_a} & \text{if } \alpha = q = \beta \\ -be^{i\theta_b} & \text{if } \alpha = p, \beta = q \\ be^{-i\theta_b} & \text{if } \alpha = q, \beta = p \\ 0 & \text{otherwise} \end{cases} \quad \text{i.e. } U = \begin{bmatrix} I_{p-1} & & & & & & & & & & \\ & ae^{i\theta_a} & & & & & & & & -be^{i\theta_b} & & \\ & & I_{q-p-1} & & & & & & & & & \\ & & & be^{-i\theta_b} & & & & & & ae^{-i\theta_a} & & \\ & & & & & & & & & & & I_{2^n-q} \end{bmatrix}$$

for some $1 \leq p < q \leq 2^n$, $a^2 + b^2 = 1$, $a, b, \theta_a, \theta_b \in \mathbb{R}$. Now from the Hermitian unitary basis from Corollary 2.3 we have $B_q^{(2^n)} = P_{(p, 2^{n-1})} \begin{bmatrix} D & \\ & \sigma_2 \end{bmatrix} P_{(p, 2^{n-1})}$, $D = \text{diag}\{(-1)^{j-1} : 1 \leq j \leq 2^n - 2\} = \text{diag}\{D_{q-1}, D_{q-p-1}, D_{2^n-q}\}$ for which

$$\begin{aligned} \exp(it_q B_q^{(2^n)}) &= \cos t_q I_{2^n} + i \sin t_q B_q^{(2^n)} \\ &= \begin{bmatrix} \exp(it_q D_{p-1}) & & & & \\ & \cos t_q & & \sin t_q & \\ & & \exp(it_q D_{q-p-1}) & & \\ & & -\sin t_q & \cos t_q & \\ & & & & \exp(it_q D_{2^n-q}) \end{bmatrix}, \end{aligned}$$

when p is odd and q is even, or p is even and q is odd.

Now the matrix U can be obtained from $\exp(it_q B_q^{(2^n)})$ by the following transformation. Set

$$D_L = \begin{bmatrix} D_1^{(\alpha_a)} & & & & \\ & e^{i\alpha_a} & & & \\ & & D_2^{(\alpha_a)} & & \\ & & & e^{-i\alpha_a} & \\ & & & & D_3^{(\alpha_a)} \end{bmatrix}, \quad D_R = \begin{bmatrix} D_1^{(\alpha_b)} & & & & \\ & e^{-i\alpha_b} & & & \\ & & D_2^{(\alpha_b)} & & \\ & & & e^{i\alpha_b} & \\ & & & & D_3^{(\alpha_b)} \end{bmatrix}$$

as the diagonal unitary matrices of order 2^n , where $D_1^{(\alpha_a)}, D_1^{(\alpha_b)}$ are order $p-1$, $D_2^{(\alpha_a)}, D_2^{(\alpha_b)}$ are of order $q-p-1$, $D_3^{(\alpha_a)}, D_3^{(\alpha_b)}$ are of order 2^n-q , and $\alpha_a, \alpha_b \in \mathbb{R}$ such that $\alpha_a + \alpha_b = \theta_b$, $\alpha_a - \alpha_b = \theta_a$. Further if the diagonal blocks can be chosen such that $D_1^{(\alpha_a)} \exp(it_q D_{p-1}) D_1^{(\alpha_b)} = I_{p-1}$, $D_2^{(\alpha_a)} \exp(it_q D_{q-p-1}) D_2^{(\alpha_b)} = I_{q-p-1}$, and $D_3^{(\alpha_a)} \exp(it_q D_{2^n-q}) D_3^{(\alpha_b)} = I_{2^n-q}$ then

$$D_L \exp(it_q B_q^{(2^n)}) D_R = U$$

with $a = \cos t_q$, $b = -\sin t_q$.

Now since $\mathcal{D}_{IZ} = \{U_j^{(2^n)} : j \in \mathcal{J}\}$ from equation (1) form a basis for the (real) linear space of diagonal traceless matrices of order 2^n , there must exist c_j and c'_j such that

$$\begin{aligned} \sum_{j \in \mathcal{J}} c_j U_j^{(2^n)} &= \begin{bmatrix} -\frac{1}{2} t_q D_{q-1} & & & & \\ & \alpha_a & & & \\ & & -\frac{1}{2} t_q D_{q-p-1} & & \\ & & & -\alpha_a & \\ & & & & -\frac{1}{2} t_q D_{2^n-q} \end{bmatrix} \\ \sum_{j \in \mathcal{J}} c'_j U_j^{(2^n)} &= \begin{bmatrix} -\frac{1}{2} t_q D_{q-1} & & & & \\ & -\alpha_b & & & \\ & & -\frac{1}{2} t_q D_{q-p-1} & & \\ & & & \alpha_b & \\ & & & & -\frac{1}{2} t_q D_{2^n-q} \end{bmatrix}. \end{aligned}$$

Moreover,

$$\begin{aligned} \exp\left(\sum_{j \in \mathcal{J}} i c_j U_j^{(2^n)}\right) &= \prod_{j \in \mathcal{J}} \exp\left(i c_j U_j^{(2^n)}\right) = D_L \text{ and} \\ \exp\left(\sum_{j \in \mathcal{J}} i c'_j U_j^{(2^n)}\right) &= \prod_{j \in \mathcal{J}} \exp\left(i c'_j U_j^{(2^n)}\right) = D_R. \end{aligned}$$

When both p and q are odd or even, the desired result follows similarly. \square

Proof of Corollary 3.5. Suppose p is odd and q is even, or p is even and q is odd. Then any 2-level matrix $U = [U_{\alpha\beta}] \in \mathbf{U}(d)$ of order 2^n is of the form

$$U = \begin{bmatrix} I_{p-1} & & & \\ e^{i(\alpha - \frac{\beta}{2} - \frac{\delta}{2})} \cos \frac{\theta}{2} & & -e^{i(\alpha - \frac{\beta}{2} + \frac{\delta}{2})} \sin \frac{\theta}{2} & \\ & I_{q-p-1} & & \\ e^{i(\alpha + \frac{\beta}{2} - \frac{\delta}{2})} \sin \frac{\theta}{2} & & e^{i(\alpha + \frac{\beta}{2} + \frac{\delta}{2})} \cos \frac{\theta}{2} & \\ & & & I_{2^n - q} \end{bmatrix}$$

for some $1 \leq p < q \leq 2^n$, $\alpha, \beta, \delta, \theta \in \mathbb{R}$. Then $U = e^{i\alpha} U'$, where

$$U' = \begin{bmatrix} e^{-i\alpha} I_{p-1} & & & \\ e^{i(-\frac{\beta}{2} - \frac{\delta}{2})} \cos \frac{\theta}{2} & & -e^{i(-\frac{\beta}{2} + \frac{\delta}{2})} \sin \frac{\theta}{2} & \\ & e^{-i\alpha} I_{q-p-1} & & \\ e^{i(\frac{\beta}{2} - \frac{\delta}{2})} \sin \frac{\theta}{2} & & e^{i(\frac{\beta}{2} + \frac{\delta}{2})} \cos \frac{\theta}{2} & \\ & & & e^{-i\alpha} I_{2^n - q} \end{bmatrix}.$$

Now there exists a basis element $U_l^{(2^n)}$ as described in Corollary 2.3 such that

$$\exp\left(-i\frac{\theta}{2} U_l^{(2^n)}\right) = \begin{bmatrix} \exp(-i\frac{\theta}{2} D_{p-1}) & & & \\ & \cos \frac{\theta}{2} & & -\sin \frac{\theta}{2} \\ & & \exp(-i\frac{\theta}{2} D_{q-p-1}) & \\ & \sin \frac{\theta}{2} & & \cos \frac{\theta}{2} \\ & & & & \exp(-i\frac{\theta}{2} D_{2^n - q}) \end{bmatrix},$$

where where $l = (d-1)^2 + d - 1, \dots, (d-1)^2 + 2(d-1) - 1$ for some $d \in \{2, \dots, 2^n\}$. Define the diagonal matrices

$$\begin{aligned} \sum_{j \in \mathcal{J}} c_j U_j^{(2^n)} &= \begin{bmatrix} -\frac{\alpha}{2} I_{p-1} + \frac{\theta}{4} D_{p-1} & & & \\ & \frac{-\beta}{2} & & \\ & & -\frac{\alpha}{2} I_{q-p-1} + \frac{\theta}{4} D_{q-p-1} & \\ & & & \frac{\beta}{2} \\ & & & & -\frac{\alpha}{2} I_{2^n - q} + \frac{\theta}{4} D_{2^n - q} \end{bmatrix} \\ \sum_{j \in \mathcal{J}} c'_j U_j^{(2^n)} &= \begin{bmatrix} -\frac{\alpha}{2} I_{p-1} + \frac{\theta}{4} D_{p-1} & & & \\ & \frac{-\delta}{2} & & \\ & & -\frac{\alpha}{2} I_{q-p-1} + \frac{\theta}{4} D_{q-p-1} & \\ & & & \frac{\delta}{2} \\ & & & & -\frac{\alpha}{2} I_{2^n - q} + \frac{\theta}{4} D_{2^n - q} \end{bmatrix} \end{aligned}$$

where $U_j^{(2^n)} \in D_{IZ}, j \in \mathcal{J}$. Then it can be easily checked that

$$U' = \exp\left(\sum_{j \in \mathcal{J}} c_j U_j^{(2^n)}\right) \exp\left(-i\frac{\theta}{2} U_l^{(2^n)}\right) \exp\left(\sum_{j \in \mathcal{J}} c'_j U_j^{(2^n)}\right).$$

When both p and q are odd or even, the desired result follows similarly. \square