

Factorization of the R-matrix. I.

S.E. DERKACHOV

Department of Mathematics, St Petersburg Technology Institute
St.Petersburg, Russia.
E-mail: S.Derkachov@pobox.spbu.ru

Abstract. We study the general rational solution of the Yang-Baxter equation with the symmetry algebra $sl(3)$. The R-operator acting in the tensor product of two arbitrary representations of the symmetry algebra can be represented as the product of the simpler "building blocks" – \mathcal{R} -operators. The \mathcal{R} -operators are constructed explicitly and have simple structure. We construct in a such way the general rational solution of the Yang-Baxter equation with the symmetry algebra $sl(3)$. To illustrate the factorization in the simplest situation we treat also the $sl(2)$ case.

arXiv:math/0503396v1 [math.QA] 19 Mar 2005

Contents

1	Introduction	2
2	The general $sl(2)$-invariant R-matrix	4
2.1	$sl(2)$ lowest weight modules	4
2.2	Yang-Baxter equation and Lax operator	5
2.3	The general R-matrix	6
3	The general $sl(3)$-invariant R-matrix	10
3.1	$sl(3)$ lowest weight modules	10
3.2	Yang-Baxter equation and Lax operator	12
3.3	The general R-matrix	14
4	Conclusions	20
5	Acknowledgments	21

1 Introduction

The Yang-Baxter equation and its solutions play a key role in the theory of the completely integrable quantum models [1, 2, 3, 6]. The general solution of the Yang-Baxter equation (R-matrix) is the operator $\mathbb{R}(u)$ acting in a tensor product $\mathbf{V}_1 \otimes \mathbf{V}_2$ of two linear spaces. The explicit expression for the R-matrix can be obtained by the following method [7, 8]. The Yang-Baxter equation is reduced to the simpler defining equation for the R-matrix [7]

$$\mathbb{R}_{12}(u - v)L_1(u)L_2(v) = L_2(v)L_1(u)\mathbb{R}_{12}(u - v)$$

where $L(u)$ is the Lax operator and by some conditions the defining equation is reduced to the recurrence relation for the function of one variable. Let us consider the $sl(2)$ -invariant R-matrix [7] for example. The tensor product of two $sl(2)$ -modules has the simple direct sum decomposition

$$V_{\ell_1} \otimes V_{\ell_2} = \sum_{n=0}^{\infty} V_{\ell_1 + \ell_2 + n}$$

so that one obtains the spectral decomposition of R-matrix in the following general form

$$\mathbb{R}_{\ell_1 \ell_2}(u) \sim \sum_{n=0}^{\infty} R_n(u) \cdot \mathbb{P}_n$$

where operator \mathbb{P}_n is the projector on the space $V_{\ell_1 + \ell_2 + n}$ in the tensor product $V_{\ell_1} \otimes V_{\ell_2}$. The defining equation results in the recurrence relation for the function $R_n(u)$

$$(-u + \ell_1 + \ell_2 + n) \cdot R_{n+1}(u) = -(u + \ell_1 + \ell_2 + n) \cdot R_n(u)$$

which has the solution [6]

$$R_n(u) = (-1)^n \frac{\Gamma(u + \ell_1 + \ell_2 + n)}{\Gamma(-u + \ell_1 + \ell_2 + n)}. \tag{1.0.1}$$

This method is generally applicable provided the direct sum decomposition of the tensor product $\mathbf{V}_1 \otimes \mathbf{V}_2$ has no multiplicities [8]. In generic situation for the algebras of higher rank ($sl(3)$ is the first nontrivial example) one obtains the system of complicated recurrence relations for the function of several variables [7, 17, 13] which is difficult to solve.

We suggest the natural factorized expression for the general R-matrix. It can be represented as the product of the simple "building blocks" – \mathcal{R} -operators. The main idea is very simple and can be illustrated on the $sl(2)$ -example. The Lax operator depends on two parameters: spin of representation ℓ and spectral parameter u . It is useful to switch to another two parameters $u_1 = u + \ell$ and $u_2 = u - \ell$ and extract the operator of permutation \mathbb{P}_{12} from the R-matrix $\mathbb{R}_{12} = \mathbb{P}_{12}\check{\mathbb{R}}_{12}$. The defining equation for the operator $\check{\mathbb{R}}_{12}$ has the form

$$\check{\mathbb{R}}_{12} \cdot L_1(u_1, u_2)L_2(v_1, v_2) = L_1(v_1, v_2)L_2(u_1, u_2) \cdot \check{\mathbb{R}}_{12}.$$

The operator $\check{\mathbb{R}}_{12}$ interchanges u_1 with v_1 and u_2 with v_2 in the product of two Lax-operators. Let us perform this operation in two stages. In the first stage we interchange the parameters u_1 with v_1 only. The parameters u_2 and v_2 remain the same. In this way one obtains the natural defining equation for the \mathcal{R}_1 -operator

$$\mathcal{R}_1 \cdot L_1(u_1, u_2)L_2(v_1, v_2) = L_1(v_1, u_2)L_2(u_1, v_2) \cdot \mathcal{R}_1$$

In the second stage we interchange u_2 with v_2 but the parameters u_1 and v_1 remain the same. The defining equation for the \mathcal{R}_2 -operator is

$$\mathcal{R}_2 \cdot L_1(u_1, u_2)L_2(v_1, v_2) = L_1(u_1, v_2)L_2(v_1, u_2) \cdot \mathcal{R}_2$$

These equations appear much simpler than initial defining equation for the R-operator and the solution can be obtained in a closed form. Finally we construct the "composite object" R-matrix from the simplest "building blocks" – \mathcal{R} -operators $\mathbb{R}_{12} = \mathbb{P}_{12}\mathcal{R}_1\mathcal{R}_2$. Note this factorization is different from the ones used by V.Drinfeld [4] and the \mathcal{R} -operator is different from the Drinfeld twist \mathcal{F} [4, 5]. In the present paper we shall consider two examples of such factorization. As an illustrative example we derive the factorized expression for the R-matrix with symmetry algebra $sl(2)$. Next we work out in details the first nontrivial example of the R-matrix with symmetry algebra $sl(3)$. It seems that the whole construction can be generalized to the case of the R-matrix with symmetry algebra $sl(n)$. There exist operators $\mathcal{R}_1, \mathcal{R}_2, \dots, \mathcal{R}_n$ and the general R-matrix can be expressed in the factorized form $\mathbb{R}_{12} = \mathbb{P}_{12}\mathcal{R}_1\mathcal{R}_2 \dots \mathcal{R}_n$.

The presentation is organized as follows. In Section 2 we collect the standard facts about the algebra $sl(2)$ and its representations. We represent the lowest weight modules by polynomials in one variable (z) and the $sl(2)$ -generators as first order differential operators. We derive the defining relation for the general R-matrix, i.e. the solution of the Yang-Baxter equation acting on tensor products of two arbitrary representations, the elements of which are polynomials in z_1 and z_2 . Next we introduce the natural defining equations for the \mathcal{R} -operators and show that the general R-matrix can be represented as the product of such much more simple operators. In the Section 3 we follow the same strategy for the algebra $sl(3)$. We represent the $sl(3)$ lowest weight modules by polynomials in three variables (x, y, z) and the $sl(3)$ -generators as first order differential operators. Next we derive the defining relation for the general R-matrix and show how it can be solved using the \mathcal{R} -operators. Finally, in Section 4 we summarize.

2 The general $sl(2)$ -invariant R-matrix

In this section we consider the simplest situation when the symmetry algebra of the Yang-Baxter equation is $sl(2)$. We serve it as the illustrative example and present all calculations in the great details.

2.1 $sl(2)$ lowest weight modules

In this, preparatory, section we collect some facts about $sl(2)$ lowest weight modules and fix the notations. The Lie algebra $sl(2)$ has three generators \mathbf{S} , \mathbf{S}_\pm

$$[\mathbf{S}, \mathbf{S}_\pm] = \pm \mathbf{S}_\pm, \quad [\mathbf{S}_+, \mathbf{S}_-] = 2\mathbf{S}$$

the central element (Casimir operator \mathbf{C}_2) being

$$\mathbf{C}_2 = \mathbf{S}^2 - \mathbf{S} + \mathbf{S}_+ \mathbf{S}_-, \quad [\mathbf{C}_2, \mathbf{S}_\pm] = [\mathbf{C}_2, \mathbf{S}] = 0.$$

The Verma module \mathbf{V}_ℓ is the generic lowest weight $sl(2)$ -module with the lowest weight $\ell \in \mathbb{C}$ and Casimir $\mathbf{C}_2 = \ell(\ell - 1)$. As a linear space \mathbf{V}_ℓ is spanned by the basis $\{\mathbf{v}_k\}_{k=0}^\infty$

$$\mathbf{v}_k = \mathbf{S}_+^k \mathbf{v}_0, \quad \mathbf{S} \mathbf{v}_k = (\ell + k) \mathbf{v}_k, \quad \mathbf{S}_- \mathbf{v}_k = -k(2\ell + k - 1) \mathbf{v}_k$$

where the vector \mathbf{v}_0 is the lowest weight vector: $\mathbf{S}_- \mathbf{v}_0 = 0$, $\mathbf{S} \mathbf{v}_0 = \ell \mathbf{v}_0$. The module \mathbf{V}_ℓ is irreducible, except for $\ell = -\frac{n}{2}$ where $n \in \{0, 1, 2, 3, \dots\}$, when there exists an $(n+1)$ -dimensional invariant subspace $\mathbf{V}_n \subset \mathbf{V}_\ell$ spanned by $\{\mathbf{v}_k\}_{k=0}^n$. We shall extensively use the representation V_ℓ of $sl(2)$ in the infinite-dimensional space $\mathbb{C}[z]$ of polynomials in variable z with the standard monomial basis $\{z^k\}_{k=0}^\infty$ and lowest weight vector $v_0 = 1$. The action of $sl(2)$ in V_ℓ is given by the first-order differential operators:

$$\mathbf{S} = z\partial + \ell, \quad \mathbf{S}_- = -\partial, \quad \mathbf{S}_+ = z^2\partial + 2\ell z \quad (2.1.1)$$

or the group-like elements(global transformations)

$$\lambda^{\mathbf{S}} \Phi(z) = \lambda^\ell \Phi(\lambda z), \quad e^{\lambda \mathbf{S}_-} \Phi(z) = \Phi(z - \lambda), \quad e^{\lambda \mathbf{S}_+} \Phi(z) = (1 - \lambda z)^{-2\ell} \Phi\left(\frac{z}{1 - \lambda z}\right) \quad (2.1.2)$$

The generating function for the basis vectors of Verma module \mathbf{V}_ℓ

$$e^{\lambda \mathbf{S}_+} \cdot \mathbf{v}_0 = \sum_{k=0}^{\infty} \frac{\lambda^k}{k!} \cdot \mathbf{S}_+^k \mathbf{v}_0 = \sum_{k=0}^{\infty} \frac{\lambda^k}{k!} \cdot \mathbf{v}_k$$

can be calculated in closed form in the functional representation V_ℓ using (2.1.2)

$$e^{\lambda \mathbf{S}_+} \cdot 1 = (1 - \lambda z)^{-2\ell} = \sum_{k=0}^{\infty} \frac{\lambda^k}{k!} \cdot (2\ell)_k z^k; \quad (2\ell)_k \equiv \frac{\Gamma(2\ell + k)}{\Gamma(2\ell)}$$

This expression clearly shows that for generic $\ell \neq -\frac{n}{2}$ the module V_ℓ is an irreducible $sl(2)$ -module isomorphic to \mathbf{V}_ℓ , the isomorphism being given by $\mathbf{v}_k \leftrightarrow (2\ell)_k \cdot z^k$. For $\ell = -\frac{n}{2}$ where $n \in \{0, 1, 2, 3, \dots\}$, we have the finite sum instead of infinite series

$$e^{\lambda S_+} \cdot 1 = (1 - \lambda z)^n = \sum_{k=0}^n (-1)^k C_k^n \lambda^k z^k ; C_k^n = \frac{n!}{k!(n-k)!}$$

so that there exists an invariant subspace $V_n \subset V_\ell$ spanned by $\{z^k\}_{k=0}^n$ which is isomorphic to \mathbf{V}_n . For $\ell = -\frac{1}{2}$ one obtains the two-dimensional invariant subspace $V_1 \sim \mathbb{C}^2$ and the matrices of operators S, S^\pm in the basis

$$\mathbf{e}_1 = S_+ \cdot 1 = -z, \quad \mathbf{e}_2 = 1$$

have the standard form of generators $\mathbf{s}, \mathbf{s}_\pm$ in the fundamental representation

$$\mathbf{s}_+ = \begin{pmatrix} 0 & 1 \\ 0 & 0 \end{pmatrix}, \quad \mathbf{s}_- = \begin{pmatrix} 0 & 0 \\ 1 & 0 \end{pmatrix}, \quad \mathbf{s} = \frac{1}{2} \cdot \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} \quad (2.1.3)$$

2.2 Yang-Baxter equation and Lax operator

Let V_{ℓ_1}, V_{ℓ_2} and V_{ℓ_3} be lowest weight $sl(2)$ -modules and consider the three operators $\mathbb{R}_{\ell_i \ell_j}(u)$ which are acting in $V_{\ell_i} \otimes V_{\ell_j}$. The Yang-Baxter equation is the following three term relation

$$\mathbb{R}_{\ell_1 \ell_2}(u-v) \mathbb{R}_{\ell_1 \ell_3}(u) \mathbb{R}_{\ell_2 \ell_3}(v) = \mathbb{R}_{\ell_2 \ell_3}(v) \mathbb{R}_{\ell_1 \ell_3}(u) \mathbb{R}_{\ell_1 \ell_2}(u-v) \quad (2.2.1)$$

We seek the general $sl(2)$ -invariant solution $\mathbb{R}_{\ell_1 \ell_2}(u)$ of this equation. The natural way is to start from the simplest solutions of Yang-Baxter equation and derive the defining equation for the general \mathbb{R} -operator [7]. First we put $\ell_1 = \ell_2 = \ell_3 = -\frac{1}{2}$ in (2.2.1), consider the restriction to the invariant subspace $\mathbb{C}^2 \otimes \mathbb{C}^2 \otimes \mathbb{C}^2$ and obtain the equation

$$\mathbb{R}_{12}(u-v) \mathbb{R}_{13}(u) \mathbb{R}_{23}(v) = \mathbb{R}_{23}(v) \mathbb{R}_{13}(u) \mathbb{R}_{12}(u-v)$$

where the operator $\mathbb{R}_{12}(u)$ acts on the first and second copy of \mathbb{C}^2 in the tensor product $\mathbb{C}^2 \otimes \mathbb{C}^2 \otimes \mathbb{C}^2$ and similarly for the other \mathbb{R} -operators. The solution is the Yang's $sl(2)$ -invariant R-matrix [23]

$$\mathbb{R}_{12}(u) = u + P_{12}$$

where P_{12} is the permutation operator in $\mathbb{C}^2 \otimes \mathbb{C}^2$. Next we choose $\ell_1 = \ell$; $\ell_2 = \ell_3 = -\frac{1}{2}$ and consider the restriction to the invariant subspace $V_\ell \otimes \mathbb{C}^2 \otimes \mathbb{C}^2$. The restriction of the operator $\mathbb{R}_{\ell, -\frac{1}{2}}(u)$ to the space $V_\ell \otimes \mathbb{C}^2$ coincides up to normalization and the shift of the spectral parameter with the fundamental Lax-operator

$$L(u) : V_\ell \otimes \mathbb{C}^2 \rightarrow V_\ell \otimes \mathbb{C}^2$$

and the Yang-Baxter equation defines the commutation relations for the Lax-operators [6]

$$L^{(1)}(u-v) L^{(2)}(u) \mathbb{R}_{12}(v) = \mathbb{R}_{12}(v) L^{(2)}(u) L^{(1)}(u-v)$$

where $L^{(1)}(u)$ is the operator which acts nontrivially on the space V_ℓ and the first copy of \mathbb{C}^2 in the tensor product $V_\ell \otimes \mathbb{C}^2 \otimes \mathbb{C}^2$ and $L^{(2)}(u)$ is the operator which acts nontrivially on the V_ℓ and the second copy of \mathbb{C}^2 . The solution is given (up to additive constant) by the Casimir operator \mathbf{C}_2 for the tensor product of representations $V_\ell \otimes \mathbb{C}^2$ [7]

$$L(u) \equiv u + 2S \otimes \mathbf{s} + S_- \otimes \mathbf{s}_+ + S_+ \otimes \mathbf{s}_- = \begin{pmatrix} u + S & S_- \\ S_+ & u - S \end{pmatrix} = \begin{pmatrix} u + \ell + z\partial & -\partial \\ z^2\partial + 2\ell z & u - \ell - z\partial \end{pmatrix}$$

where $\mathbf{s}, \mathbf{s}^\pm$ are the generators in the fundamental representation (2.1.3) and S, S_\pm are generators (2.1.1) in the generic representation V_ℓ . The Lax operator acts in the space $\mathbb{C}[z] \otimes \mathbb{C}^2$ and despite the compact notation $L(u)$ depends really on two parameters: spin ℓ and spectral parameter u . We shall use extensively the parametrization $u_1 \equiv u + \ell, u_2 \equiv u - \ell$ and show all parameters explicitly. There exists very useful factorized representation for the L-operator [9]

$$L(u_1, u_2) \equiv \begin{pmatrix} u_1 + z\partial & -\partial \\ z^2\partial + (u_1 - u_2)z & u_2 - z\partial \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ z & 1 \end{pmatrix} \begin{pmatrix} u_1 - 1 & -\partial \\ 0 & u_2 \end{pmatrix} \begin{pmatrix} 1 & 0 \\ -z & 1 \end{pmatrix} \quad (2.2.2)$$

The L-operator is $sl(2)$ invariant by construction and as consequence we obtain the useful equality

$$\begin{pmatrix} 1 & 0 \\ -\lambda & 1 \end{pmatrix} \cdot L(u) \cdot \begin{pmatrix} 1 & 0 \\ \lambda & 1 \end{pmatrix} = e^{\lambda S_-} \cdot L(u) \cdot e^{-\lambda S_-} = e^{-\lambda\partial} \cdot L(u) \cdot e^{\lambda\partial} \quad (2.2.3)$$

Indeed, we have

$$(\mathbf{s}_- + S_-) \cdot L(u) = L(u) \cdot (\mathbf{s}_- + S_-) \Rightarrow e^{-\lambda S_-} \cdot L(u) \cdot e^{\lambda S_-} = e^{\lambda S_-} \cdot L(u) \cdot e^{-\lambda S_-} ; e^{\lambda S_-} = \begin{pmatrix} 1 & 0 \\ \lambda & 1 \end{pmatrix}$$

Finally we put $\ell_3 = -\frac{1}{2}$ in (2.2.1) and consider the restriction on the invariant subspace $V_{\ell_1} \otimes V_{\ell_2} \otimes \mathbb{C}^2$. In this way one obtains the defining equation for the operator $\mathbb{R}_{\ell_1\ell_2}(u)$ [7, 18]

$$\mathbb{R}_{\ell_1\ell_2}(u - v)L_1(u)L_2(v) = L_2(v)L_1(u)\mathbb{R}_{\ell_1\ell_2}(u - v)$$

The operator L_k acts nontrivially on the tensor product $V_{\ell_k} \otimes \mathbb{C}^2$ which is isomorphic to $\mathbb{C}[z_k] \otimes \mathbb{C}^2$ and the operator $\mathbb{R}_{\ell_1\ell_2}(u)$ acts nontrivially on the tensor product $V_{\ell_1} \otimes V_{\ell_2}$ which is isomorphic to $\mathbb{C}[z_1] \otimes \mathbb{C}[z_2] = \mathbb{C}[z_1, z_2]$.

2.3 The general R-matrix

Now we are going to the solution of the defining equation for the general R-matrix. It is useful to extract the operator of permutation \mathbb{P}_{12}

$$\mathbb{P}_{12}\Psi(z_1, z_2) = \Psi(z_2, z_1) ; \Psi(z_1, z_2) \in \mathbb{C}[z_1, z_2]$$

from the \mathbb{R} -operator $\mathbb{R}_{\ell_1\ell_2}(u) = \mathbb{P}_{12}\check{\mathbb{R}}_{\ell_1\ell_2}(u)$ and solve the defining equation for the $\check{\mathbb{R}}$ -operator

$$\check{\mathbb{R}}(u_1, u_2|v_1, v_2)L_1(u_1, u_2)L_2(v_1, v_2) = L_1(v_1, v_2)L_2(u_1, u_2)\check{\mathbb{R}}(u_1, u_2|v_1, v_2).$$

To avoid misunderstanding we present this equation in explicit form

$$\check{\mathbb{R}}(u_1, u_2|v_1, v_2) \begin{pmatrix} u_1 + z_1\partial_1 & -\partial_1 \\ z_1^2\partial_1 + (u_1 - u_2)z_1 & u_2 - z_1\partial_1 \end{pmatrix} \cdot \begin{pmatrix} v_1 + z_2\partial_2 & -\partial_2 \\ z_2^2\partial_2 + (v_1 - v_2)z_2 & v_2 - z_2\partial_2 \end{pmatrix} =$$

$$= \begin{pmatrix} v_1 + z_1 \partial_1 & -\partial_1 \\ z_1^2 \partial_1 + (v_1 - v_2) z_1 & v_2 - z_1 \partial_1 \end{pmatrix} \cdot \begin{pmatrix} u_1 + z_2 \partial_2 & -\partial_2 \\ z_2^2 \partial_2 + (u_1 - u_2) z_2 & u_2 - z_2 \partial_2 \end{pmatrix} \check{\mathbb{R}}(u_1, u_2 | v_1, v_2)$$

where $u_1 = u + \ell_1$, $u_2 = u - \ell_1$, $v_1 = v + \ell_2$, $v_2 = v - \ell_2$. The $\check{\mathbb{R}}$ -operator can be factorized on the product of the simpler "elementary building blocks" - \mathcal{R} -operators.

Proposition 1 *There exists operator \mathcal{R}_1 which is the solution of defining equations*

$$\mathcal{R}_1 L_1(u_1, u_2) L_2(v_1, v_2) = L_1(v_1, u_2) L_2(u_1, v_2) \mathcal{R}_1 \quad (2.3.1)$$

$$\mathcal{R}_1 = \mathcal{R}_1(u_1 | v_1, v_2) ; \mathcal{R}_1(u_1 | v_1, v_2) = \mathcal{R}_1(u_1 + \lambda | v_1 + \lambda, v_2 + \lambda)$$

and these requirements fix the operator \mathcal{R}_1 up to overall normalization constant

$$\mathcal{R}_1(u_1 | v_1, v_2) \sim \frac{\Gamma(z_{21} \partial_2 + u_1 - v_2)}{\Gamma(z_{21} \partial_2 + v_1 - v_2)} ; z_{21} = z_2 - z_1$$

Proposition 2 *There exists operator \mathcal{R}_2 which is the solution of defining equations*

$$\mathcal{R}_2 L_1(u_1, u_2) L_2(v_1, v_2) = L_1(u_1, v_2) L_2(v_1, u_2) \mathcal{R}_2 \quad (2.3.2)$$

$$\mathcal{R}_2 = \mathcal{R}_2(u_1, u_2 | v_2) ; \mathcal{R}_2(u_1, u_2 | v_2) = \mathcal{R}_2(u_1 + \lambda, u_2 + \lambda | v_2 + \lambda)$$

and these requirements fix the operator \mathcal{R}_2 up to overall normalization constant

$$\mathcal{R}_2(u_1, u_2 | v_2) \sim \frac{\Gamma(z_{12} \partial_1 + u_1 - v_2)}{\Gamma(z_{12} \partial_1 + u_1 - u_2)} ; z_{12} = z_1 - z_2$$

Proposition 3 *The operator $\check{\mathbb{R}}$ can be factorized in a following way*

$$\check{\mathbb{R}}(u_1, u_2 | v_1, v_2) = \mathcal{R}_1(u_1 | v_1, u_2) \mathcal{R}_2(u_1, u_2 | v_2) = \mathcal{R}_2(v_1, u_2 | v_2) \mathcal{R}_1(u_1 | v_1, v_2) \quad (2.3.3)$$

Note that the \mathcal{R} -operators change the spins of $sl(2)$ -representations

$$\mathcal{R}_1 : V_{\ell_1} \otimes V_{\ell_2} \rightarrow V_{\ell_1 - \xi_1} \otimes V_{\ell_2 + \xi_1} ; \xi_1 = \frac{u_1 - v_1}{2} \quad (2.3.4)$$

$$\mathcal{R}_2 : V_{\ell_1} \otimes V_{\ell_2} \rightarrow V_{\ell_1 + \xi_2} \otimes V_{\ell_2 - \xi_2} ; \xi_2 = \frac{u_2 - v_2}{2} \quad (2.3.5)$$

but the general R-matrix $\mathbb{R}_{\ell_1 \ell_2}(u) = \mathbb{P}_{12} \mathcal{R}_1(u_1 | v_1, u_2) \mathcal{R}_2(u_1, u_2 | v_2)$ appears automatically $sl(2)$ -invariant.

The factorization of the $\check{\mathbb{R}}$ -operator can be proven using the simple pictures. The operator $\check{\mathbb{R}}$ interchanges all parameters in the product of two L-operators. The operator \mathcal{R}_2 interchanges the parameters u_2 and v_2 only and the operator \mathcal{R}_1 interchanges the parameters u_1 and v_1 . Using the operator $\mathcal{R}_1 \mathcal{R}_2$ it is possible to interchange parameters u_1, v_1 and u_2, v_2 in two steps so that we obtain the first equality in (2.3.3) as the condition of commutativity for the diagram

$$\begin{array}{ccc} & L_1(u_1, v_2) L_2(v_1, u_2) & \\ & \nearrow & \searrow \\ \mathcal{R}_2(u_1, u_2 | v_2) & & \mathcal{R}_1(u_1 | v_1, u_2) \\ L_1(u_1, u_2) L_2(v_1, v_2) & \xrightarrow{\check{\mathbb{R}}(u_1, u_2 | v_1, v_2)} & L_1(v_1, v_2) L_2(u_1, u_2) \end{array}$$

It is possible to exchange the parameters in the opposite order so that the second equality in (2.3.3) is the condition of commutativity for the diagram

$$\begin{array}{ccc}
& L_1(v_1, u_2)L_2(u_1, v_2) & \\
\mathcal{R}_1(u_1|v_1, v_2) & \nearrow & \mathcal{R}_2(v_1, u_2|v_2) \\
L_1(u_1, u_2)L_2(v_1, v_2) & \xrightarrow{\tilde{\mathbb{R}}(u_1, u_2; |v_1, v_2)} & L_1(v_1, v_2)L_2(u_1, u_2)
\end{array}$$

The defining system of equations for the \mathcal{R} -operator is the system of differential equations of the second order. It can be reduced to the simpler system of equations of the first order which clearly shows the $sl(2)$ -covariance of the \mathcal{R} -operator.

Lemma 1 *The system of equations (2.3.1) for the operator \mathcal{R}_1 is equivalent to the system*

$$\mathcal{R}_1 \cdot [L_1(u_1, u_2) + L_2(v_1, v_2)] = [L_1(v_1, u_2) + L_2(u_1, v_2)] \cdot \mathcal{R}_1 ; \mathcal{R}_1 \cdot z_1 = z_1 \cdot \mathcal{R}_1 \quad (2.3.6)$$

Lemma 2 *The system of equations (2.3.2) for the operator \mathcal{R}_2 is equivalent to the system*

$$\mathcal{R}_2 \cdot [L_1(u_1, u_2) + L_2(v_1, v_2)] = [L_1(u_1, v_2) + L_2(v_1, u_2)] \cdot \mathcal{R}_2 ; \mathcal{R}_2 \cdot z_2 = z_2 \cdot \mathcal{R}_2 \quad (2.3.7)$$

Note that the relations in the first place are simply the rules of commutation of \mathcal{R} -operators with $sl(2)$ -generators written in a compact form. In explicit notations it is exactly the relations (2.3.4), (2.3.5). The $sl(2)$ -invariance of \mathbb{R} -matrix follows directly from the properties of \mathcal{R} -operators.

Proof of the Lemma 2 and the Proposition 2. As an example we shall consider the operator \mathcal{R}_2 and all calculations for the operator \mathcal{R}_1 are very similar. We are going to prove that the defining equation (2.3.2) is equivalent to the system (2.3.7) and derive the explicit formula for the operator \mathcal{R}_2 . First we show that the system (2.3.7) is the direct consequence of the eq. (2.3.2). Let us make the shift $u_1 \rightarrow u_1 + \lambda$, $u_2 \rightarrow u_2 + \lambda$, $v_1 \rightarrow v_1 + \mu$, $v_2 \rightarrow v_2 + \lambda$ in the defining equation (2.3.2). The \mathcal{R} -operator is invariant under this shift, L-operators transform simply

$$L_1 \rightarrow L_1 + \lambda \cdot \mathbb{1}, \quad L_2 \rightarrow L_2 + \lambda \cdot \mathbb{1} + (\mu - \lambda) \begin{pmatrix} 1 & 0 \\ z_2 & 0 \end{pmatrix}$$

so that we derive as consequence of eq. (2.3.2)

$$\begin{aligned}
& \mathcal{R}_2 \cdot \left[\lambda \cdot [L_1(u_1, u_2) + L_2(v_1, v_2)] + (\mu - \lambda)L_1(u_1, u_2) \begin{pmatrix} 1 & 0 \\ z_2 & 0 \end{pmatrix} + \lambda(\mu - \lambda) \begin{pmatrix} 1 & 0 \\ z_2 & 0 \end{pmatrix} \right] = \\
& = \left[\lambda \cdot [L_1(u_1, v_2) + L_2(v_1, u_2)] + (\mu - \lambda)L_1(u_1, v_2) \begin{pmatrix} 1 & 0 \\ z_2 & 0 \end{pmatrix} + \lambda(\mu - \lambda) \begin{pmatrix} 1 & 0 \\ z_2 & 0 \end{pmatrix} \right] \cdot \mathcal{R}_2
\end{aligned}$$

The parameters λ and μ are arbitrary so that we obtain the equations

$$\mathcal{R}_2(u_1, u_2|v_2) \cdot [L_1(u_1, u_2) + L_2(v_1, v_2)] = [L_1(u_1, v_2) + L_2(v_1, u_2)] \cdot \mathcal{R}_2(u_1, u_2|v_2) ; \mathcal{R}_2 \cdot z_2 = z_2 \cdot \mathcal{R}_2$$

$$\mathcal{R}_2 \cdot L_1(u_1, u_2) \begin{pmatrix} 1 \\ z_2 \end{pmatrix} = L_1(u_1, v_2) \begin{pmatrix} 1 \\ z_2 \end{pmatrix} \cdot \mathcal{R}_2$$

It is easy to prove that the last equation is the direct consequence of the first and the second ones. Next we show that from the systems of equations (2.3.7) follows eq. (2.3.2). This will be almost trivial if we rewrite the equations (2.3.7) and (2.3.2) in equivalent form using the $sl(2)$ -invariance of the L-operator and the commutativity of \mathcal{R}_2 and z_2 . We start from the equation (2.3.2) for the operator \mathcal{R}_2 and use the factorized expression (2.2.2) for the L₂-operator

$$\mathcal{R}_2 \cdot L_1(u_1, u_2) \mathbf{M} \begin{pmatrix} v_1 - 1 & -\partial_2 \\ 0 & v_2 \end{pmatrix} \mathbf{M}^{-1} = L_1(u_1, v_2) \mathbf{M} \begin{pmatrix} v_1 - 1 & -\partial_2 \\ 0 & u_2 \end{pmatrix} \mathbf{M}^{-1} \cdot \mathcal{R}_2 ; \mathbf{M} = \begin{pmatrix} 1 & 0 \\ z_2 & 1 \end{pmatrix}$$

Next we perform the similarity transformation $\mathbf{M}^{-1} \cdots \mathbf{M}$ of this matrix equation

$$\mathcal{R}_2 \cdot \mathbf{M}^{-1} L_1(u_1, u_2) \mathbf{M} \cdot \begin{pmatrix} v_1 - 1 & -\partial_2 \\ 0 & v_2 \end{pmatrix} = \mathbf{M}^{-1} L_1(u_1, v_2) \mathbf{M} \cdot \begin{pmatrix} v_1 - 1 & -\partial_2 \\ 0 & u_2 \end{pmatrix} \cdot \mathcal{R}_2$$

The $sl(2)$ -invariance of L-operator allows to rewrite the matrix $\mathbf{M}^{-1} \mathbf{L} \mathbf{M}$ in the form (2.2.3)

$$\mathbf{M}^{-1} L_1(u_1, u_2) \mathbf{M} = e^{-z_2 \partial_1} L_1(u_1, u_2) e^{+z_2 \partial_1}$$

so that we have the simple equation for the operator $\mathbf{r} \equiv e^{z_2 \partial_1} \cdot \mathcal{R}_2 \cdot e^{-z_2 \partial_1}$ (note that $\mathbf{r} z_2 = z_2 \mathbf{r}$)

$$\mathbf{r} \cdot L_1(u_1, u_2) \begin{pmatrix} v_1 - 1 & -\partial_2 + \partial_1 \\ 0 & v_2 \end{pmatrix} = L_1(u_1, v_2) \begin{pmatrix} v_1 - 1 & -\partial_2 + \partial_1 \\ 0 & u_2 \end{pmatrix} \cdot \mathbf{r} \quad (2.3.8)$$

This system of equations is equivalent to the system (2.3.2) written in terms of \mathbf{r} . To derive the system of equations which is equivalent to the system (2.3.7) written in terms of \mathbf{r} we repeat the same trick with the shift of parameters and obtain the equations

$$\mathbf{r} \left[L_1(u_1, u_2) + \begin{pmatrix} v_1 - 1 & -\partial_2 + \partial_1 \\ 0 & v_2 \end{pmatrix} \right] = \left[L_1(u_1, v_2) + \begin{pmatrix} v_1 - 1 & -\partial_2 + \partial_1 \\ 0 & u_2 \end{pmatrix} \right] \mathbf{r} \quad (2.3.9)$$

$$\mathbf{r} \cdot L_1(u_1, u_2) \begin{pmatrix} 1 \\ 0 \end{pmatrix} = L_1(u_1, v_2) \begin{pmatrix} 1 \\ 0 \end{pmatrix} \cdot \mathbf{r}$$

The second equation is the evident consequence of the first one. We must prove that the system (2.3.8) is equivalent to the system (2.3.9). First step we factorize in (2.3.8) the matrix $diag(v_1 - 1 ; 1)$ from the right so that the parameter v_1 disappears from the equation

$$\mathbf{r} \cdot L_1(u_1, u_2) \begin{pmatrix} 1 & -\partial_2 + \partial_1 \\ 0 & v_2 \end{pmatrix} = L_1(u_1, v_2) \begin{pmatrix} 1 & -\partial_2 + \partial_1 \\ 0 & u_2 \end{pmatrix} \cdot \mathbf{r}$$

It is easy to see that there are two new equations in comparison with (2.3.9)

$$\mathbf{r} \cdot L_1(u_1, u_2) \begin{pmatrix} \partial_1 \\ v_2 \end{pmatrix} = L_1(u_1, v_2) \begin{pmatrix} \partial_1 \\ u_2 \end{pmatrix} \cdot \mathbf{r} \quad (2.3.10)$$

In explicit form the defining system (2.3.9) contains three equations

$$\mathbf{r} z_1 \partial_1 = z_1 \partial_1 \mathbf{r} ; \mathbf{r} \partial_2 = \partial_2 \mathbf{r} ; \mathbf{r} z_1 (z_1 \partial_1 + u_1 - u_2) = z_1 (z_1 \partial_1 + u_1 - v_2) \mathbf{r} \quad (2.3.11)$$

The "down"-equation in (2.3.10) is the simple consequence of equation $\mathbf{r} \cdot z_1 \partial_1 = z_1 \partial_1 \cdot \mathbf{r}$ from the system (2.3.11) and the "up"-equation

$$\mathbf{r}(z_1 \partial_1 + u_1 - v_2) \partial_1 = (z_1 \partial_1 + u_1 - v_2) \partial_1 \mathbf{r}$$

is equivalent to the last equation from the system (2.3.11). Indeed we have

$$\begin{aligned} \mathbf{r} z_1 (z_1 \partial_1 + u_1 - v_2) &= z_1 (z_1 \partial_1 + u_1 - v_2) \mathbf{r} \rightarrow \mathbf{r} z_1 (z_1 \partial_1 + u_1 - v_2) \partial_1 = z_1 (z_1 \partial_1 + u_1 - v_2) \mathbf{r} \partial_1 \rightarrow \\ &\rightarrow z_1 (z_1 \partial_1 + u_1 - v_2) \partial_1 \mathbf{r} = z_1 (z_1 \partial_1 + u_1 - v_2) \partial_1 \rightarrow (z_1 \partial_1 + u_1 - v_2) \partial_1 \mathbf{r} = \mathbf{r} (z_1 \partial_1 + u_1 - v_2) \partial_1 \end{aligned}$$

We have proved the equivalence of the systems (2.3.8) and (2.3.9) and therefore the equivalence of the systems (2.3.7) and (2.3.2). It remains to find the solution. First we solve the equations (2.3.11) for operator \mathbf{r} . The solution of equation $\mathbf{r} z_2 = z_2 \mathbf{r}$ and the first two equations from the system (2.3.11) is $\mathbf{r} = \mathbf{r}[z_1 \partial_1]$. Then the last equation leads to the recurrence relation which has the simple solution

$$\mathbf{r}[z_1 \partial_1 + 1](z_1 \partial_1 + u_1 - v_2) = \mathbf{r}[z_1 \partial_1](z_1 \partial_1 + u_1 - v_2) \implies \mathbf{r}[z_1 \partial_1] \sim \frac{\Gamma(z_1 \partial_1 + u_1 - v_2)}{\Gamma(z_1 \partial_1 + u_1 - u_2)}$$

Finally we derive the expression for the operator \mathcal{R}_2 from the Proposition

$$\mathcal{R}_2 = e^{-z_2 \partial_1} \mathbf{r} e^{z_2 \partial_1} \sim \frac{\Gamma(z_{12} \partial_1 + u_1 - v_2)}{\Gamma(z_{12} \partial_1 + u_1 - u_2)}.$$

3 The general $sl(3)$ -invariant R-matrix

In the previous section we have constructed the general solution of the Yang-Baxter equation with symmetry algebra $sl(2)$ and proved that it has simple factorized structure. Next we shall consider the first nontrivial example of the symmetry algebra of the rank two. In fact, we repeat step by step all calculations from the previous section and show that the general solution of the Yang-Baxter equation with the symmetry algebra $sl(3)$ has the very similar structure.

3.1 $sl(3)$ lowest weight modules

The algebra $sl(3)$ has eight generators \mathbf{T}_{ab} , $a, b = 1, 2, 3$ with condition $\mathbf{T}_{11} + \mathbf{T}_{22} + \mathbf{T}_{33} = 0$. The commutation relations have the standard form [10, 11]

$$[\mathbf{T}_{ab}, \mathbf{T}_{cd}] = \delta_{cb} \mathbf{T}_{ad} - \delta_{ad} \mathbf{T}_{cb}$$

We shall use the following generators of the Cartan subalgebra

$$\mathbf{H}_1 = \mathbf{T}_{11} - \mathbf{T}_{22}; \quad \mathbf{H}_2 = \mathbf{T}_{22} - \mathbf{T}_{33}; \quad \mathbf{T}_{11} = \frac{2}{3} \mathbf{H}_1 + \frac{1}{3} \mathbf{H}_2; \quad \mathbf{T}_{22} = \frac{1}{3} \mathbf{H}_2 - \frac{1}{3} \mathbf{H}_1; \quad \mathbf{T}_{33} = -\frac{1}{3} \mathbf{H}_1 - \frac{2}{3} \mathbf{H}_2$$

There are two central elements $\mathbf{C}_2 = \sum_{ab} \mathbf{T}_{ab} \mathbf{T}_{ba}$ and $\mathbf{C}_3 = \sum_{abc} \mathbf{T}_{ab} \mathbf{T}_{bc} \mathbf{T}_{ca}$. The Verma module is the generic lowest weight $sl(3)$ -module \mathbf{V}_Λ ; $\Lambda = (m, n)$. As a linear space \mathbf{V}_Λ is obtained by application of operators $\mathbf{T}_{12}, \mathbf{T}_{13}, \mathbf{T}_{23}$ to the lowest weight vector \mathbf{a}_0

$$\mathbf{T}_{21} \mathbf{a}_0 = \mathbf{T}_{31} \mathbf{a}_0 = \mathbf{T}_{32} \mathbf{a}_0 = 0; \quad \mathbf{H}_1 \mathbf{a}_0 = -m \cdot \mathbf{a}_0; \quad \mathbf{H}_2 \mathbf{a}_0 = -n \cdot \mathbf{a}_0$$

We shall use the representation V_Λ of $sl(3)$ in the infinite-dimensional space $\mathbb{C}[x, y, z]$ of polynomials in variables x, y, z and lowest weight vector $a_0 = 1$ [10, 12]. The action of $sl(3)$ in V_Λ is given by the first-order differential operators. Lowering (decreasing the polynomial degree) operators have the form

$$T_{21} = \partial_x ; T_{31} = \partial_y ; T_{32} = \partial_z - x\partial_y \quad (3.1.1)$$

and generate the following global transformations

$$\begin{aligned} e^{\lambda T_{21}} \Phi(x, y, z) &= \Phi(x + \lambda, y, z) ; e^{\lambda T_{31}} \Phi(x, y, z) = \Phi(x, y + \lambda, z) \\ e^{\lambda T_{32}} \Phi(x, y, z) &= \Phi(x, y - \lambda x, z + \lambda) . \end{aligned}$$

Rising (increasing the polynomial degree) operators

$$\begin{aligned} T_{12} &= -x^2 \partial_x - xy \partial_y + xz \partial_z + y \partial_z + nx , T_{23} = -z^2 \partial_z - y \partial_x + mz \\ T_{13} &= -y^2 \partial_y - xy \partial_x - z(y + xz) \partial_z + (m + n)y + mxz \end{aligned} \quad (3.1.2)$$

generate the global transformations

$$\begin{aligned} e^{\lambda T_{12}} \Phi(x, y, z) &= [1 + \lambda x]^n \Phi \left(\frac{x}{1 + \lambda x}, \frac{y}{1 + \lambda x}, z + \lambda(y + xz) \right) \\ e^{\lambda T_{23}} \Phi(x, y, z) &= [1 + \lambda z]^m \Phi \left(x - \lambda y, y, \frac{z}{1 + \lambda z} \right) , \\ e^{\lambda T_{13}} \Phi(x, y, z) &= [1 + \lambda y]^n [1 + \lambda(y + xz)]^m \Phi \left(\frac{x}{1 + \lambda y}, \frac{y}{1 + \lambda y}, \frac{z}{1 + \lambda(y + xz)} \right) . \end{aligned}$$

Two remaining elements of the Cartan subalgebra:

$$H_1 = 2x\partial_x + y\partial_y - z\partial_z - n ; H_2 = 2z\partial_z + y\partial_y - x\partial_x - m$$

generate the transformations:

$$\lambda^{H_1} \Phi(x, y, z) = \lambda^{-n} \Phi \left(\lambda^2 x, \lambda y, \frac{z}{\lambda} \right) ; \lambda^{H_2} \Phi(x, y, z) = \lambda^{-m} \Phi \left(\frac{z}{\lambda}, \lambda y, \lambda^2 z \right)$$

Using these formulae it is possible to derive the closed expression for the generating functions of the basis vectors

$$e^{\mu T_{12}} e^{\nu T_{23}} e^{\lambda T_{13}} \cdot 1 = [1 + \mu x + \lambda y]^n \cdot [1 + \nu z + (\lambda + \mu\nu)(y + xz)]^m$$

The power expansion of these generating functions in μ, ν, λ gives the elements of the basis. It is evident that for the generic $m \neq M$, $n \neq N$; $M, N \in \{0, 1, 2, 3 \dots\}$ the module V_Λ is an irreducible lowest weight $sl(3)$ -module isomorphic to \mathbf{V}_Λ but for the special values of the spin $m = M$, $n = N$ there exists the finite dimensional invariant subspace $V_{M,N}$ with dimension $\dim V_{M,N} = \frac{1}{2}(M+1)(N+1)(M+N+2)$ [10, 11]. For generic $M, N \neq 0$ the space $V_{M,N}$ is invariant subspace in the space of polynomials in three variables $\mathbb{C}[x, y, z]$. In the case $N = 0$ we have

$$e^{\mu T_{12}} e^{\nu T_{23}} e^{\lambda T_{13}} \cdot 1 = [1 + \nu z + (\lambda + \mu\nu)(y + xz)]^M$$

so that one obtains the invariant subspace $V_{M,0}$ with dimension $\dim V_{M,0} = \frac{1}{2}(M+1)(M+2)$ in the space of polynomials in two variables $\mathbb{C}[y+xz, z]$. In the case $M=0$ we have

$$e^{\mu T_{12}} e^{\nu T_{23}} e^{\lambda T_{13}} \cdot 1 = [1 + \mu x + \lambda y]^N$$

so that one obtains the invariant subspace $V_{0,N}$ with dimension $\dim V_{0,N} = \frac{1}{2}(N+1)(N+2)$ in the space of polynomials in two variables $\mathbb{C}[x, y]$. We shall use the three-dimensional representation $V_{(1,0)} \sim \mathbb{C}^3$. In the basis

$$\mathbf{e}_1 = T_{13} \cdot 1 = y + xz, \quad \mathbf{e}_2 = T_{23} \cdot 1 = z, \quad \mathbf{e}_3 = 1$$

the $sl(3)$ -generators take the form

$$\begin{aligned} \mathbf{t}_{31} &= \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 1 & 0 & 0 \end{pmatrix}; \quad \mathbf{t}_{21} = \begin{pmatrix} 0 & 0 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}; \quad \mathbf{t}_{32} = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 1 & 0 \end{pmatrix}; \quad \mathbf{h}_1 = \begin{pmatrix} 1 & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & 0 \end{pmatrix} \\ \mathbf{t}_{13} &= \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}; \quad \mathbf{t}_{23} = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \end{pmatrix}; \quad \mathbf{t}_{12} = \begin{pmatrix} 0 & 1 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}; \quad \mathbf{h}_2 = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & -1 \end{pmatrix} \end{aligned} \quad (3.1.3)$$

There exists the second three-dimensional representation $V_{(0,1)} \sim \mathbb{C}^3$. In the basis

$$\mathbf{e}_1 = -1; \quad \mathbf{e}_2 = T_{12} \cdot 1 = x, \quad \mathbf{e}_3 = T_{13} \cdot 1 = y$$

the $sl(3)$ -generators take the similar form but $\mathbf{t}_{ik} \rightarrow -\mathbf{t}_{ki}$; $\mathbf{h}_1 \rightarrow -\mathbf{h}_1$; $\mathbf{h}_2 \rightarrow -\mathbf{h}_2$.

3.2 Yang-Baxter equation and Lax operator

The Yang-Baxter equation is the following three term relation

$$\mathbb{R}_{\Lambda_1 \Lambda_2}(u-v) \mathbb{R}_{\Lambda_1 \Lambda_3}(u) \mathbb{R}_{\Lambda_2 \Lambda_3}(v) = \mathbb{R}_{\Lambda_2 \Lambda_3}(v) \mathbb{R}_{\Lambda_1 \Lambda_3}(u) \mathbb{R}_{\Lambda_1 \Lambda_2}(u-v)$$

for the operators $\mathbb{R}_{\Lambda_i \Lambda_j}(u) : V_{\Lambda_i} \otimes V_{\Lambda_j} \rightarrow V_{\Lambda_i} \otimes V_{\Lambda_j}$. As in the $sl(2)$ -case we start from the simplest solutions of Yang-Baxter equation and derive the defining equation for the general \mathbb{R} -operator. First we put $\Lambda_1 = \Lambda_2 = \Lambda_3 = (1, 0)$ in Yang-Baxter equation and consider the restriction to the invariant subspace $\mathbb{C}^3 \otimes \mathbb{C}^3 \otimes \mathbb{C}^3$. We obtain the equation

$$\mathbb{R}_{12}(u-v) \mathbb{R}_{13}(u) \mathbb{R}_{23}(v) = \mathbb{R}_{23}(v) \mathbb{R}_{13}(u) \mathbb{R}_{12}(u-v) \quad (3.2.1)$$

where the operator $\mathbb{R}_{12}(u)$ acts on the first and second copy of \mathbb{C}^3 in the tensor product $\mathbb{C}^3 \otimes \mathbb{C}^3 \otimes \mathbb{C}^3$ and similarly for the other \mathbb{R} -operators. The solution is well known [1, 13]

$$\mathbb{R}_{12}(u) = u + P_{12}$$

where P_{12} is the permutation operator in $\mathbb{C}^3 \otimes \mathbb{C}^3$. Secondly we choose $\Lambda_1 = \Lambda_2 = (1, 0)$; $\Lambda_3 = \Lambda = (m, n)$ and consider the restriction to the invariant subspace $\mathbb{C}^3 \otimes \mathbb{C}^3 \otimes V_{\Lambda}$. The restriction

of the operator $\mathbb{R}_{\Lambda_1\Lambda}(u)$ to the space $\mathbb{C}^3 \otimes V_\Lambda$ coincides up to normalization and shift of spectral parameter with the Lax-operator

$$L(u) : \mathbb{C}^3 \otimes V_\Lambda \rightarrow \mathbb{C}^3 \otimes V_\Lambda$$

and the Yang-Baxter equation coincides with the fundamental commutation relations for the Lax-operator [1, 13, 14, 15]

$$\mathbb{R}_{12}(u-v)L^{(1)}(u)L^{(2)}(v) = L^{(2)}(v)L^{(1)}(u)\mathbb{R}_{12}(u-v)$$

where $L^{(1)}(u)$ is the operator which acts nontrivially on the first copy of \mathbb{C}^3 and V_Λ in the tensor product $\mathbb{C}^3 \otimes \mathbb{C}^{\otimes} V_\Lambda$ and $L^{(2)}(u)$ is the operator which acts nontrivially on the second copy of \mathbb{C}^3 and V_Λ . The solution coincides up to additive constant with the Casimir operator \mathbf{C}_2 for the representation $\mathbb{C}^3 \otimes V_\Lambda$

$$L(u) \equiv u + \frac{1}{3} \cdot (2\mathbf{h}_1 + \mathbf{h}_2) \otimes H_1 + \frac{1}{3} \cdot (\mathbf{h}_1 + 2\mathbf{h}_2) \otimes H_2 + \sum_{i \neq k} \mathbf{t}_{ik} \otimes T_{ki}$$

where $\mathbf{h}_1, \mathbf{h}_2, \mathbf{t}_{ik}$ are $sl(3)$ -generators in the fundamental representation and H_1, H_2, T_{ik} are generators in the generic representation. The algebra $sl(3)$ has two three-dimensional representations - $V_{(1,0)}$ and $V_{(0,1)}$ so that there exists the second Lax-operator

$$\bar{L}(u) : \mathbb{C}^3 \otimes V_\Lambda \rightarrow \mathbb{C}^3 \otimes V_\Lambda ; \mathbb{R}_{12}(u-v)\bar{L}^{(1)}(u)\bar{L}^{(2)}(v) = \bar{L}^{(2)}(v)\bar{L}^{(1)}(u)\mathbb{R}_{12}(u-v)$$

The explicit expression for the second Lax-operator is the same but now $\mathbf{t}_{ik} \rightarrow -\mathbf{t}_{ki}$; $\mathbf{h}_1 \rightarrow -\mathbf{h}_1$; $\mathbf{h}_2 \rightarrow -\mathbf{h}_2$. We shall use the Lax-operator $L(u)$

$$L(u) = \begin{pmatrix} \frac{2}{3}H_1 + \frac{1}{3}H_2 + u & T_{21} & T_{31} \\ T_{12} & \frac{1}{3}H_2 - \frac{1}{3}H_1 + u & T_{32} \\ T_{13} & T_{23} & -\frac{1}{3}H_1 - \frac{2}{3}H_2 + u \end{pmatrix}$$

in defining equation for the general \mathbb{R} -operator. The Lax-operator $L(u)$ depends on three parameters u, m, n . We shall use the parametrization

$$u_1 = u - 2 - \frac{m+2n}{3}, \quad u_2 = u - 1 + \frac{n-m}{3}, \quad u_3 = u + \frac{n+2m}{3}; \quad m = u_3 - u_2 - 1, \quad n = u_2 - u_1 - 1$$

and show this parameters explicitly. The Lax operator $L(u_1, u_2, u_3)$ in the functional representation V_Λ has the form

$$L(u_1, u_2, u_3) = \begin{pmatrix} x\partial_x + y\partial_y + u_1 + 2 & \partial_x & \partial_y \\ L_{21} & -x\partial_x + z\partial_z + u_2 + 1 & \partial_z - x\partial_y \\ L_{31} & L_{32} & -y\partial_y - z\partial_z + u_3 \end{pmatrix} \quad (3.2.2)$$

$$L_{21} = -x^2\partial_x - xy\partial_y + (xz + y)\partial_z + (u_2 - u_1 - 1)x ; \quad L_{32} = -y\partial_x - z^2\partial_z + (u_3 - u_2 - 1)z$$

$$L_{31} = -xy\partial_x - y^2\partial_y - z(xz + y)\partial_z + (u_3 - u_2 - 1)xz + (u_3 - u_1 - 2)y$$

and similar to $sl(2)$ -case there exists the factorized representation for the Lax-operator

$$L(u_1, u_2, u_3) \equiv \begin{pmatrix} 1 & 0 & 0 \\ -x & 1 & 0 \\ -y & -z & 1 \end{pmatrix} \begin{pmatrix} u_1 & \partial_x - z\partial_y & \partial_y \\ 0 & u_2 & \partial_z \\ 0 & 0 & u_3 \end{pmatrix} \begin{pmatrix} 1 & 0 & 0 \\ x & 1 & 0 \\ y + xz & z & 1 \end{pmatrix} \quad (3.2.3)$$

The L-operator is $sl(3)$ -invariant by construction and as consequence one obtains the useful equality

$$\mathbf{M}^{-1} \cdot L(u) \cdot \mathbf{M} = \mathbb{S}^{-1} \cdot L(u) \cdot \mathbb{S} ; \quad \mathbb{S} = e^{c(\partial_z - x\partial_y)} \cdot e^{b\partial_y} \cdot e^{a\partial_x} ; \quad \mathbf{M} = \begin{pmatrix} 1 & 0 & 0 \\ -a & 1 & 0 \\ -b & -c & 1 \end{pmatrix} \quad (3.2.4)$$

Finally we put $\Lambda_1 = (1, 0)$ in Yang-Baxter equation

$$\mathbb{R}_{\Lambda_1\Lambda_2}(u-v)\mathbb{R}_{\Lambda_1\Lambda_3}(u)\mathbb{R}_{\Lambda_2\Lambda_3}(v) = \mathbb{R}_{\Lambda_2\Lambda_3}(v)\mathbb{R}_{\Lambda_1\Lambda_3}(u)\mathbb{R}_{\Lambda_1\Lambda_2}(u-v)$$

change the numeration of the representation spaces $\Lambda_2 \rightarrow \Lambda_1 = (m_1, n_1)$; $\Lambda_3 \rightarrow \Lambda_2 = (m_2, n_2)$ and consider the restriction to the invariant subspace $\mathbb{C}^3 \otimes V_{\Lambda_1} \otimes V_{\Lambda_2}$. In this way one obtains the defining equation for the \mathbb{R} -operator

$$L_1(u-v)L_2(u)\mathbb{R}_{\Lambda_1\Lambda_2}(v) = \mathbb{R}_{\Lambda_1\Lambda_2}(v)L_2(u)L_1(u-v)$$

The operator L_k acts nontrivially on the tensor product $\mathbb{C}^3 \otimes V_{\Lambda_k}$ which is isomorphic to $\mathbb{C}^3 \otimes \mathbb{C}[x_k, y_k, z_k]$ and the operator $\mathbb{R}_{\Lambda_1\Lambda_2}(u)$ acts nontrivially on the tensor product $V_{\Lambda_1} \otimes V_{\Lambda_2}$ which is isomorphic to $\mathbb{C}[x_1, y_1, z_1] \otimes \mathbb{C}[x_2, y_2, z_2]$. Note that obtained defining equation is slightly different from the ones we have used in $sl(2)$ -case. The defining equation which is similar to $sl(2)$ case is

$$\mathbb{R}_{\Lambda_1\Lambda_2}^{-1}(v-u)L_1(u)L_2(v) = L_2(v)L_1(u)\mathbb{R}_{\Lambda_1\Lambda_2}^{-1}(v-u) \quad (3.2.5)$$

There exists the well known automorphism [14, 15] of the Yang-Baxter equation $\mathbb{R}_{\Lambda_1\Lambda_2}(u) \rightarrow \mathbb{R}_{\Lambda_1\Lambda_2}^{-1}(-u)$. In the simplest $sl(2)$ case we have $\mathbb{R}_{\ell_1\ell_2}(u) \sim \mathbb{R}_{\ell_1\ell_2}^{-1}(-u)$ but for the more complicated algebras the action of this automorphism is nontrivial. To proceed in close analogy with $sl(2)$ case we shall use the defining equation (3.2.5) so that we derive the expression for the operator $\mathbb{R}_{\Lambda_1\Lambda_2}^{-1}(v-u)$.

3.3 The general R-matrix

Now we are going to the solution of the defining equation for the general R-matrix. It is useful to extract the operator of permutation

$$\mathbb{P}_{12} : \mathbb{C}[x_1, y_1, z_1] \otimes \mathbb{C}[x_2, y_2, z_2] \rightarrow \mathbb{C}[x_2, y_2, z_2] \otimes \mathbb{C}[x_1, y_1, z_1]$$

$$\mathbb{P}_{12}\Psi(x_1, y_1, z_1|x_2, y_2, z_2) = \Psi(x_2, y_2, z_2|x_1, y_1, z_1)$$

from the \mathbb{R} -operator $\mathbb{R}_{\Lambda_1\Lambda_2}^{-1}(v-u) = \mathbb{P}_{12}\check{\mathbb{R}}(u;v)$ and solve the defining equation for the $\check{\mathbb{R}}$ -operator. The main defining equation for the $\check{\mathbb{R}}$ -operator is

$$\check{\mathbb{R}}(u;v)L_1(u_1, u_2, u_3)L_2(v_1, v_2, v_3) = L_1(v_1, v_2, v_3)L_2(u_1, u_2, u_3)\check{\mathbb{R}}(u;v) \quad (3.3.1)$$

$$u_1 = u - 2 - \frac{m_1 + 2n_1}{3}, \quad u_2 = u - 1 + \frac{n_1 - m_1}{3}, \quad u_3 = u + \frac{n_1 + 2m_1}{3}$$

$$v_1 = v - 2 - \frac{m_2 + 2n_2}{3}, \quad v_2 = v - 1 + \frac{n_2 - m_2}{3}, \quad v_3 = v + \frac{n_2 + 2m_2}{3}$$

The operator $\check{\mathbb{R}}$ can be represented as the product of the simpler "elementary building blocks" - \mathcal{R} -operators.

Proposition 4 *There exists operator \mathcal{R}_1 which is the solution of the defining equations*

$$\mathcal{R}_1 L_1(u_1, u_2, u_3) L_2(v_1, v_2, v_3) = L_1(v_1, u_2, u_3) L_2(u_1, v_2, v_3) \mathcal{R}_1 \quad (3.3.2)$$

$$\mathcal{R}_1 = \mathcal{R}_1(u_1 | v_1, v_2, v_3); \quad \mathcal{R}_1(u_1 | v_1, v_2, v_3) = \mathcal{R}_1(u_1 + \lambda | v_1 + \lambda, v_2 + \lambda, v_3 + \lambda)$$

and these requirements fix the operator \mathcal{R}_1 up to overall normalization constant

$$\mathcal{R}_1 \sim \mathbb{S}_1^{-1} \cdot \frac{\Gamma(x\partial_x + u_1 - v_2 + 1)}{\Gamma(x\partial_x + 1)} \cdot e^{-\frac{y}{x}\partial_z} \cdot \frac{\Gamma(y\partial_y + u_1 - v_3 + 1)}{\Gamma(y\partial_y + v_1 - v_3 + 1)} \cdot e^{\frac{y}{x}\partial_z} \cdot \frac{\Gamma(x\partial_x + 1)}{\Gamma(x\partial_x + v_1 - v_2 + 1)} \cdot \mathbb{S}_1$$

$$\mathbb{S}_1 = e^{(y_1 - z_1 x_2)\partial_{y_2}} \cdot e^{z_1 \partial_{z_2}} \cdot e^{x_1 \partial_{x_2}}$$

$$x = x_2, \quad y = y_2 + x_2 z_2, \quad z = z_2; \quad \partial_x = \partial_{x_2} - z_2 \partial_{y_2}, \quad \partial_y = \partial_{y_2}, \quad \partial_z = \partial_{z_2} - x_2 \partial_{y_2}$$

Proposition 5 *There exists operator \mathcal{R}_2 which is the solution of the defining equations*

$$\mathcal{R}_2 L_1(u_1, u_2, u_3) L_2(v_1, v_2, v_3) = L_1(u_1, v_2, u_3) L_2(v_1, u_2, v_3) \mathcal{R}_2 \quad (3.3.3)$$

$$\mathcal{R}_2 = \mathcal{R}_2(u_1, u_2 | v_2, v_3); \quad \mathcal{R}_2(u_1, u_2 | v_2, v_3) = \mathcal{R}_2(u_1 + \lambda, u_2 + \lambda | v_2 + \lambda, v_3 + \lambda)$$

and these requirements fix the operator \mathcal{R}_2 up to overall normalization constant

$$\mathcal{R}_2 \sim \mathbb{S}_2^{-1} \cdot \frac{\Gamma(z_2 \partial_{z_2} + u_2 - v_3 + 1)}{\Gamma(z_2 \partial_{z_2} + 1)} \cdot e^{\frac{y_1}{z_2} \partial_{x_1}} \cdot \frac{\Gamma(x_1 \partial_{x_1} + u_1 - v_2 + 1)}{\Gamma(x_1 \partial_{x_1} + u_1 - u_2 + 1)} \cdot e^{-\frac{y_1}{z_2} \partial_{x_1}} \cdot \frac{\Gamma(z_2 \partial_{z_2} + 1)}{\Gamma(z_2 \partial_{z_2} + v_2 - v_3 + 1)} \cdot \mathbb{S}_2$$

$$\mathbb{S}_2 = e^{(y_2 - x_1 z_1)\partial_{y_1}} \cdot e^{z_1 \partial_{z_2}} \cdot e^{x_2 \partial_{x_1}}$$

Proposition 6 *There exists operator \mathcal{R}_3 which is the solution of the defining equations*

$$\mathcal{R}_3 L_1(u_1, u_2, u_3) L_2(v_1, v_2, v_3) = L_1(u_1, u_2, v_3) L_2(v_1, v_2, u_3) \mathcal{R}_3 \quad (3.3.4)$$

$$\mathcal{R}_3 = \mathcal{R}_3(u_1, u_2, u_3 | v_3); \quad \mathcal{R}_3(u_1, u_2, u_3 | v_3) = \mathcal{R}_3(u_1 + \lambda, u_2 + \lambda, u_3 + \lambda | v_3 + \lambda)$$

and these requirements fix the operator \mathcal{R}_3 up to overall normalization constant

$$\mathcal{R}_3 \sim \mathbb{S}_3^{-1} \cdot \frac{\Gamma(z_1 \partial_{z_1} + u_2 - v_3 + 1)}{\Gamma(z_1 \partial_{z_1} + 1)} \cdot e^{\frac{y_1}{z_1} \partial_{x_1}} \cdot \frac{\Gamma(y_1 \partial_{y_1} + u_1 - v_3 + 1)}{\Gamma(y_1 \partial_{y_1} + u_1 - u_3 + 1)} \cdot e^{-\frac{y_1}{z_1} \partial_{x_1}} \cdot \frac{\Gamma(z_1 \partial_{z_1} + 1)}{\Gamma(z_1 \partial_{z_1} + u_2 - u_3 + 1)} \cdot \mathbb{S}_3$$

$$\mathbb{S}_3 = e^{(y_2 - x_1 z_2)\partial_{y_1}} \cdot e^{z_2 \partial_{z_1}} \cdot e^{x_2 \partial_{x_1}}$$

Proposition 7 *The $\check{\mathbb{R}}$ -operator can be factorized as follows*

$$\check{\mathbb{R}}(u; v) = \mathcal{R}_1(u_1; v_1, u_2, u_3) \mathcal{R}_2(u_1, u_2; v_2, u_3) \mathcal{R}_3(u_1, u_2, u_3; v_3) \quad (3.3.5)$$

There exist six equivalent ways to represent $\check{\mathbb{R}}$ in an factorized form which differ by the order of \mathcal{R} -operators and their parameters. All these expressions and the proof of the factorization of the $\check{\mathbb{R}}$ -operator can be obtained using the pictures similar to $sl(2)$ -case.

The defining systems of equations for the \mathcal{R} -operator can be reduced to the simpler system which clearly shows the property of $sl(3)$ -covariance of the \mathcal{R} -operator.

Lemma 3 *The defining equation (3.3.2) for the operator \mathcal{R}_1 is equivalent to the system of equations*

$$\mathcal{R}_1 [\mathbb{L}_1(u_1, u_2, u_3) + \mathbb{L}_2(v_1, v_2, v_3)] = [\mathbb{L}_1(v_1, u_2, u_3) + \mathbb{L}_2(u_1, v_2, v_3)] \mathcal{R}_1 \quad (3.3.6)$$

$$\mathcal{R}_1 x_1 = x_1 \mathcal{R}_1, \quad \mathcal{R}_1 y_1 = y_1 \mathcal{R}_1, \quad \mathcal{R}_1 z_1 = z_1 \mathcal{R}_1$$

$$\mathcal{R}_1 \cdot (\partial_{z_2} - x_{21} \partial_{y_2}) = (\partial_{z_2} - x_{21} \partial_{y_2}) \cdot \mathcal{R}_1 \quad (3.3.7)$$

Lemma 4 *The defining equation (3.3.3) for the operator \mathcal{R}_2 is equivalent to the system of equations*

$$\mathcal{R}_2 [\mathbb{L}_1(u_1, u_2, u_3) + \mathbb{L}_2(v_1, v_2, v_3)] = [\mathbb{L}_1(u_1, v_2, u_3) + \mathbb{L}_2(v_1, u_2, v_3)] \mathcal{R}_2 \quad (3.3.8)$$

$$\mathcal{R}_2 (y_1 + x_1 z_1) = (y_1 + x_1 z_1) \mathcal{R}_2, \quad \mathcal{R}_2 z_1 = z_1 \mathcal{R}_2; \quad \mathcal{R}_2 x_2 = x_2 \mathcal{R}_2, \quad \mathcal{R}_2 y_2 = y_2 \mathcal{R}_2$$

Lemma 5 *The defining equation (3.3.4) for the operator \mathcal{R}_3 is equivalent to the system of equations*

$$\mathcal{R}_3 [\mathbb{L}_1(u_1, u_2, u_3) + \mathbb{L}_2(v_1, v_2, v_3)] = [\mathbb{L}_1(u_1, u_2, v_3) + \mathbb{L}_2(v_1, v_2, u_3)] \mathcal{R}_3 \quad (3.3.9)$$

$$\mathcal{R}_3 x_2 = x_2 \mathcal{R}_3, \quad \mathcal{R}_3 y_2 = y_2 \mathcal{R}_3, \quad \mathcal{R}_3 z_2 = z_2 \mathcal{R}_3$$

$$\mathcal{R}_3 \cdot (\partial_{x_1} - z_2 \partial_{y_1}) = (\partial_{x_1} - z_2 \partial_{y_1}) \cdot \mathcal{R}_3 \quad (3.3.10)$$

The relations in the first line are simply the rules of commutation of \mathcal{R} -operators with $sl(3)$ -generators written in a compact form. In explicit notations we have for $\Lambda_1 = (m_1, n_1)$ and $\Lambda_2 = (m_2, n_2)$

$$\mathcal{R} : V_{\Lambda_1} \otimes V_{\Lambda_2} \rightarrow V_{\Lambda'_1} \otimes V_{\Lambda'_2}$$

$$\mathcal{R}_1 : \Lambda'_1 = (m_1, n_1 + \xi_1); \quad \Lambda'_2 = (m_2, n_2 - \xi_1); \quad \xi_1 = u_1 - v_1$$

$$\mathcal{R}_2 : \Lambda'_1 = (m_1 + \xi_2, n_1 - \xi_2); \quad \Lambda'_2 = (m_2 - \xi_2, n_2 + \xi_2); \quad \xi_2 = u_2 - v_2$$

$$\mathcal{R}_3 : \Lambda'_1 = (m_1 - \xi_3, n_1); \quad \Lambda'_2 = (m_2 + \xi_3, n_2); \quad \xi_3 = u_3 - v_3$$

The $sl(3)$ -invariance of \mathbb{R} -matrix follows directly from the properties of \mathcal{R} -operators so that the general \mathbb{R} -matrix $\mathbb{R}_{\Lambda_1 \Lambda_2}^{-1}(v - u) = \mathbb{P}_{12} \check{\mathbb{R}}(u; v)$ is automatically $sl(3)$ -invariant.

Proof. We shall consider the operators \mathcal{R}_3 and \mathcal{R}_2 . All calculations for the operator \mathcal{R}_1 are very similar to the \mathcal{R}_3 -case. Now we are going to the proof of equivalence of defining equation (3.3.4) to the system (3.3.9) and derivation of explicit formula for the operator \mathcal{R}_3 . First we show that the system (3.3.9) is the direct consequence of the eq. (3.3.4). Let us make the shift $u_k \rightarrow u_k + \lambda$, $v_1 \rightarrow v_1 + \mu$, $v_2 \rightarrow v_2 + \nu$, $v_3 \rightarrow v_3 + \lambda$ in the defining equation (3.3.4). The \mathcal{R} -operator is invariant under this shift and L-operators transform as follows

$$\mathbb{L}_1 \rightarrow \mathbb{L}_1 + \lambda \cdot \mathbb{1}; \quad \mathbb{L}_2 \rightarrow \mathbb{L}_2 + \lambda \cdot \mathbb{1} + (\mu - \lambda) \begin{pmatrix} 1 & 0 & 0 \\ -x_2 & 0 & 0 \\ -y_2 & 0 & 0 \end{pmatrix} + (\nu - \lambda) \begin{pmatrix} 0 & 0 & 0 \\ x_2 & 1 & 0 \\ -x_2 z_2 & -z_2 & 0 \end{pmatrix}$$

The obtained after all equation is valid for arbitrary parameters λ , μ and ν and as consequence we derive the system (3.3.9) and equation (3.3.10). Next we show that from the system of equations (3.3.9), (3.3.10) follows eq. (3.3.4). This will be almost evident if we rewrite these equations in equivalent form using the $sl(3)$ -invariance of the L-operator and the commutativity of \mathcal{R}_3 and x_2, y_2, z_2 . We substitute the factorized representation (3.2.3) for the operator L_2 in the equation (3.3.4) for the operator \mathcal{R}_3 ($D_{x_2} = \partial_{x_2} - z_2 \partial_{y_2}$)

$$\mathcal{R}_3 L_1(u_1, u_2, u_3) \mathbf{M} \begin{pmatrix} v_1 & D_{x_2} & \partial_{y_2} \\ 0 & v_2 & \partial_{z_2} \\ 0 & 0 & v_3 \end{pmatrix} \mathbf{M}^{-1} = L_1(u_1, u_2, v_3) \mathbf{M} \begin{pmatrix} v_1 & D_{x_2} & \partial_{y_2} \\ 0 & v_2 & \partial_{z_2} \\ 0 & 0 & u_3 \end{pmatrix} \mathbf{M}^{-1} \mathcal{R}_3$$

and perform the similarity transformation $\mathbf{M}^{-1} \dots \mathbf{M}$ of this matrix equation using the commutativity \mathcal{R}_3 and x_2, y_2, z_2 . Then using the $sl(3)$ -invariance of L-operator (3.2.4)

$$\mathbf{M}^{-1} \cdot L_1 \cdot \mathbf{M} = \mathbb{S}^{-1} \cdot L_1 \cdot \mathbb{S} ; \mathbb{S} = e^{z_2(\partial_{z_1} - x_1 \partial_{y_1})} \cdot e^{y_2 \partial_{y_1}} \cdot e^{x_2 \partial_{x_1}} ; \mathbf{M} = \begin{pmatrix} 1 & 0 & 0 \\ -x_2 & 1 & 0 \\ -y_2 & -z_2 & 1 \end{pmatrix}$$

we derive the equation for the transformed operator $\mathbf{r} = \mathbb{S} \cdot \mathcal{R}_3 \cdot \mathbb{S}^{-1}$

$$\mathbf{r} \cdot L_1(u_1, u_2, u_3) \mathbf{L}(v_1, v_2, v_3) = L_1(u_1, u_2, v_3) \mathbf{L}(v_1, v_2, u_3) \cdot \mathbf{r} \quad (3.3.11)$$

where

$$\mathbf{L}(v_1, v_2, v_3) \equiv \mathbb{S} \cdot \begin{pmatrix} v_1 & D_{x_2} & \partial_{y_2} \\ 0 & v_2 & \partial_{z_2} \\ 0 & 0 & v_3 \end{pmatrix} \cdot \mathbb{S}^{-1} = \begin{pmatrix} v_1 & D_{x_2} - \partial_{x_1} & \partial_{y_2} - \partial_{y_1} \\ 0 & v_2 & \partial_{z_2} - D_{z_1} \\ 0 & 0 & v_3 \end{pmatrix} ; D_{z_1} = \partial_{z_1} - x_1 \partial_{y_1}$$

To derive the system of equations which is equivalent to the system (3.3.9), (3.3.10) written in terms of \mathbf{r} we repeat the same trick with the shift of parameters and obtain the system of equations

$$\mathbf{r} \cdot [L_1(u_1, u_2, u_3) + \mathbf{L}(v_1, v_2, v_3)] = [L_1(u_1, u_2, v_3) + \mathbf{L}(v_1, v_2, u_3)] \cdot \mathbf{r} \quad (3.3.12)$$

$$\mathbf{r} \cdot L_1(u_1, u_2, u_3) \begin{pmatrix} 1 & 0 \\ 0 & 1 \\ 0 & 0 \end{pmatrix} = L_1(u_1, u_2, v_3) \begin{pmatrix} 1 & 0 \\ 0 & 1 \\ 0 & 0 \end{pmatrix} \mathbf{r} \quad (3.3.13)$$

It is evident that all equations of the system (3.3.13) contained in the equation (3.3.12) except only one (12)-equation $\mathbf{r} \partial_{x_1} = \partial_{x_1} \mathbf{r}$. We use the system of equation

$$\mathbf{r} \cdot [L_1(u_1, u_2, u_3) + \mathbf{L}(v_1, v_2, v_3)] = [L_1(u_1, u_2, v_3) + \mathbf{L}(v_1, v_2, u_3)] \cdot \mathbf{r} ; \mathbf{r} \partial_{x_1} = \partial_{x_1} \mathbf{r} \quad (3.3.14)$$

as defining system for operator \mathbf{r} . It is the system of equations (3.3.9), (3.3.10) written in terms of operator \mathbf{r} . Returning to the system (3.3.11)(which is (3.3.4) written in terms of \mathbf{r}) we note that it is possible to factorize the matrix $diag(v_1 ; v_2 ; 1)$ from the right

$$\mathbf{r} \cdot L_1(u_1, u_2, u_3) \begin{pmatrix} 1 & \frac{D_{x_2} - \partial_{x_1}}{v_2} & \partial_{y_2} - \partial_{y_1} \\ 0 & 1 & \partial_{z_2} - D_{z_1} \\ 0 & 0 & v_3 \end{pmatrix} = L_1(u_1, u_2, v_3) \begin{pmatrix} 1 & \frac{D_{x_2} - \partial_{x_1}}{v_2} & \partial_{y_2} - \partial_{y_1} \\ 0 & 1 & \partial_{z_2} - D_{z_1} \\ 0 & 0 & u_3 \end{pmatrix} \mathbf{r}$$

In comparison with (3.3.14) there are three new equations only

$$\mathbf{r} \cdot L_1(u_1, u_2, u_3) \begin{pmatrix} -\partial_{y_1} \\ -\partial_{z_1} + x_1 \partial_{y_1} \\ v_3 \end{pmatrix} = L_1(u_1, u_2, v_3) \begin{pmatrix} -\partial_{y_1} \\ -\partial_{z_1} + x_1 \partial_{y_1} \\ u_3 \end{pmatrix} \mathbf{r}$$

Indeed the system (3.3.14) contains the equations $[\mathbf{r}, \partial_{x_2}] = [\mathbf{r}, \partial_{y_2}] = [\mathbf{r}, \partial_{z_2}] = [\mathbf{r}, \partial_{x_1}] = 0$ and by conditions (3.3.13) we obtain only three new equations. It is possible to show that these equations follow from the system (3.3.14) so that it remains to find the solution of the system of equations (3.3.14). First of all $[\mathbf{r}, x_2] = [\mathbf{r}, y_2] = [\mathbf{r}, z_2] = [\mathbf{r}, \partial_{x_2}] = [\mathbf{r}, \partial_{y_2}] = [\mathbf{r}, \partial_{z_2}] = 0$ and therefore the operator \mathbf{r} depends on the variables x_1, y_1, z_1 only. There are six equations and for simplicity we change $z_1, y_1, z_1 \rightarrow x, y, z$

$$\mathbf{r} (x \partial_x + y \partial_y) = (x \partial_x + y \partial_y) \mathbf{r} ; \mathbf{r} \partial_x = \partial_x \mathbf{r} ; \mathbf{r} (-x \partial_x + z \partial_z) = (-x \partial_x + z \partial_z) \mathbf{r} \quad (3.3.15)$$

$$\mathbf{r} (y \partial_x + z^2 \partial_z + (u_2 - u_3 + 1)z) = (y \partial_x + z^2 \partial_z + (u_2 - v_3 + 1)z) \mathbf{r} \quad (3.3.16)$$

$$\begin{aligned} \mathbf{r} (x^2 \partial_x + xy \partial_y - xz \partial_z - y \partial_z + (u_1 - u_2 + 1)x) = \\ = (x^2 \partial_x + xy \partial_y - xz \partial_z - y \partial_z + (u_1 - u_2 + 1)x) \mathbf{r} \end{aligned} \quad (3.3.17)$$

$$\begin{aligned} \mathbf{r} (x (y \partial_x + z^2 \partial_z + (u_2 - u_3 + 1)z) + y (y \partial_y + z \partial_z + u_1 - u_3 + 2)) = \\ = (x (y \partial_x + z^2 \partial_z + (u_2 - v_3 + 1)z) + y (y \partial_y + z \partial_z + u_1 - v_3 + 2)) \mathbf{r} \end{aligned} \quad (3.3.18)$$

We look the general solution in the form

$$\mathbf{r} = \mathbf{a}[z \partial_z] \cdot e^{\frac{y}{z} \partial_x} \cdot \mathbf{b}[y \partial_y] \cdot e^{-\frac{y}{z} \partial_x} \cdot \mathbf{c}[z \partial_z]$$

where

$$\mathbf{c}[z \partial_z] = \frac{\Gamma(z \partial_z + 1)}{\Gamma(z \partial_z + u_2 - u_3 + 1)}.$$

It is the evident solution of the equations (3.3.15). The equations (3.3.16)-(3.3.18) lead to the recurrence relations for the functions $\mathbf{a}[z \partial_z]$ and $\mathbf{b}[y \partial_y]$

$$\mathbf{a}[z \partial_z + 1] \cdot (z \partial_z + 1) = (z \partial_z + u_2 - v_3 + 1) \cdot \mathbf{a}[z \partial_z]$$

$$\mathbf{b}[y \partial_y + 1] \cdot (y \partial_y + u_1 - u_3 + 1) = (y \partial_y + u_1 - v_3 + 1) \cdot \mathbf{b}[y \partial_y]$$

The solution of these equations is

$$\mathbf{a}[z \partial_z] = \frac{\Gamma(z \partial_z + u_2 - v_3 + 1)}{\Gamma(z \partial_z + 1)} ; \mathbf{b}[y \partial_y] = \frac{\Gamma(y \partial_y + u_1 - v_3 + 1)}{\Gamma(y \partial_y + u_1 - u_3 + 1)}.$$

Collecting everything together we obtain the expression for the operator \mathcal{R}_3 from the Proposition. All calculations for the operator \mathcal{R}_1 are very similar and finally one arrives to the system which coincides with the system (3.3.15), (3.3.18) after the change of variables and parameters. In a such way one obtains the expression for the operator \mathcal{R}_1 from the Proposition. It remains to prove the equivalence of defining equation (3.3.3) to the system (3.3.8) and derive the explicit formula for the operator \mathcal{R}_2 . First we show that the system (3.3.8) is the direct consequence of the eq. (3.3.3). Let us make the shift $u_1 \rightarrow u_1 + \lambda$, $u_2 \rightarrow u_2 + \lambda$, $u_3 \rightarrow u_3 + \mu$, $v_1 \rightarrow$

$v_1 + \nu$, $v_2 \rightarrow v_2 + \lambda$, $v_3 \rightarrow v_3 + \lambda$ in the defining equation (3.3.3) for the operator \mathcal{R}_2 . The \mathcal{R} -operator is invariant under this shift and L-operators transform as follows

$$\mathbf{L}_1 \rightarrow \mathbf{L}_1 + \lambda \cdot \mathbb{1} + (\mu - \lambda) \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ y_1 + x_1 z_1 & z_1 & 1 \end{pmatrix} ; \mathbf{L}_2 \rightarrow \mathbf{L}_2 + \lambda \cdot \mathbb{1} + (\nu - \lambda) \begin{pmatrix} 1 & 0 & 0 \\ -x_2 & \lambda & 0 \\ y_2 & 0 & 0 \end{pmatrix}$$

The obtained after all equation has to be satisfied for arbitrary λ , μ and ν and as consequence we derive the system (3.3.8). Next we show that from the systems of equations (3.3.8) follows eq. (3.3.3). This will be almost evident if we rewrite these equations in equivalent form using the $sl(3)$ -invariance of the L-operator and the commutativity of \mathcal{R}_2 and $z_1, y_1 + x_1 z_1, x_2, y_2$. We start from the equation (3.3.3) and make the two similarity transformations of the defining equation (3.3.3) using simple matrices which commute with operator \mathcal{R}_2 . After all these transformations the defining equation (3.3.3) for the \mathcal{R}_2 -operator in factorized form looks as follows

$$\mathcal{R}_2 \cdot \mathbf{l}_1(u_1, u_2, u_3) \cdot \mathbf{M} \cdot \mathbf{l}_2(v_1, v_2, v_3) = \mathbf{l}_1(u_1, v_2, u_3) \cdot \mathbf{M} \cdot \mathbf{l}_2(v_1, u_2, v_3) \cdot \mathcal{R}_2 ; \mathbf{M} \equiv \begin{pmatrix} 1 & 0 & 0 \\ -x_2 & 1 & 0 \\ y_{12} + z_1 x_{12} & z_1 & 1 \end{pmatrix}$$

$$\mathbf{l}_1(u_1, u_2, u_3) \equiv \begin{pmatrix} 1 & 0 & 0 \\ -x_1 & 1 & 0 \\ 0 & 0 & 1 \end{pmatrix} \begin{pmatrix} u_1 & \partial_{x_1} - z_1 \partial_{y_1} & \partial_{y_1} \\ 0 & u_2 & \partial_{z_1} \\ 0 & 0 & u_3 \end{pmatrix} \begin{pmatrix} 1 & 0 & 0 \\ x_1 & 1 & 0 \\ 0 & 0 & 1 \end{pmatrix}$$

$$\mathbf{l}_2(v_1, v_2, v_3) \equiv \begin{pmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & -z_2 & 1 \end{pmatrix} \begin{pmatrix} v_1 & \partial_{x_2} - z_2 \partial_{y_2} & \partial_{y_2} \\ 0 & v_2 & \partial_{z_2} \\ 0 & 0 & v_3 \end{pmatrix} \begin{pmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & z_2 & 1 \end{pmatrix}$$

Next step we rewrite this equation in terms of the transformed operator \mathbf{r}

$$\mathcal{R}_2 = \mathbb{S}^{-1} \cdot \mathbf{r} \cdot \mathbb{S} ; \mathbb{S} = e^{(y_2 - x_1 z_1) \partial_{y_1}} \cdot e^{z_1 \partial_{z_2}} \cdot e^{x_2 \partial_{x_1}}$$

$$\mathbf{r} \cdot \mathbf{L}_1(u_1, u_2, u_3) \mathbf{m} \mathbf{L}_2(v_1, v_2, v_3) = \mathbf{L}_1(u_1, v_2, u_3) \mathbf{m} \mathbf{L}_2(v_1, u_2, v_3) \cdot \mathbf{r} ; \mathbf{m} = \begin{pmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ y_1 & 0 & 1 \end{pmatrix} \quad (3.3.19)$$

where

$$\mathbf{L}_1(u_1, u_2, u_3) = \begin{pmatrix} u_1 + 1 + x_1 \partial_{x_1} & \partial_{x_1} & \partial_{y_1} \\ -x_1^2 \partial_{x_1} + (u_2 - u_1 - 1)x_1 & u_2 - x_1 \partial_{x_1} & \partial_{z_1} - \partial_{z_2} \\ 0 & 0 & u_3 \end{pmatrix}$$

$$\mathbf{L}_2(v_1, v_2, v_3) = \begin{pmatrix} v_1 & \partial_{x_2} - \partial_{x_1} - z_1 \partial_{y_2} & \partial_{y_2} - \partial_{y_1} \\ 0 & v_2 + 1 + z_2 \partial_{z_2} & \partial_{z_2} \\ 0 & -z_2^2 \partial_{z_2} + (v_3 - v_2 - 1)z_2 & v_3 - z_2 \partial_{z_2} \end{pmatrix}$$

To derive the system of equations which is equivalent to the system (3.3.8) written in terms of \mathbf{r} we repeat the same trick with the shift of parameters and obtain

$$\mathbf{r} \cdot [\mathbf{L}_1(u_1, u_2, u_3) \mathbf{m} + \mathbf{m} \mathbf{L}_2(v_1, v_2, v_3)] = [\mathbf{L}_1(u_1, v_2, u_3) \mathbf{m} + \mathbf{m} \mathbf{L}_2(v_1, u_2, v_3)] \cdot \mathbf{r} \quad (3.3.20)$$

This system results in a simple equations. First of all we have $[\mathbf{r}, y_1] = [\mathbf{r}, z_1] = [\mathbf{r}, x_2] = [\mathbf{r}, y_2] = 0$ from the very beginning and the system contain the equations

$$[\mathbf{r}, \partial_{y_2}] = [\mathbf{r}, \partial_{z_1}] = [\mathbf{r}, \partial_{x_2} - z_1 \partial_{y_2}] = 0 \quad (3.3.21)$$

$$\mathbf{r}(x_1 \partial_{x_1} + y_1 \partial_{y_1}) = (x_1 \partial_{x_1} + y_1 \partial_{y_1}) \mathbf{r} ; \mathbf{r}(x_1 \partial_{x_1} - z_2 \partial_{z_2}) = (x_1 \partial_{x_1} - z_2 \partial_{z_2}) \mathbf{r} \quad (3.3.22)$$

$$\mathbf{r}(-x_1^2 \partial_{x_1} + (u_2 - u_1 - 1)x_1 - y_1 \partial_{z_2}) = (-x_1^2 \partial_{x_1} + (v_2 - u_1 - 1)x_1 - y_1 \partial_{z_2}) \mathbf{r} \quad (3.3.23)$$

$$\mathbf{r}(-z_2^2 \partial_{z_2} + (v_3 - v_2 - 1)z_2 - y_1 \partial_{x_1}) = (-z_2^2 \partial_{z_2} + (v_3 - u_2 - 1)z_2 - y_1 \partial_{x_1}) \mathbf{r} \quad (3.3.24)$$

Returning to the system (3.3.19) which is equivalent to the system (3.3.3) written in terms of \mathbf{r} we note that it is possible to factorize the matrix $diag(v_1; 1; 1)$ from the right and the matrix $diag(1; 1; u_3)$ from the left so that the parameters v_1 and u_3 disappear from equation. The equivalence obtained system of equations to the system (3.3.21)-(3.3.24) can be proven by straightforward calculations. Now we are going to the solution of the defining system of equations. We look the general solution in the form

$$\mathbf{r} = \mathbf{a}[z_2 \partial_{z_2}] \cdot e^{\frac{y_1}{z_2} \partial_{x_1}} \cdot \mathbf{b}[x_1 \partial_{x_1}] \cdot e^{-\frac{y_1}{z_2} \partial_{x_1}} \cdot \mathbf{c}[z_2 \partial_{z_2}]$$

where

$$\mathbf{c}[z_2 \partial_{z_2}] = \frac{\Gamma(z_2 \partial_{z_2} + 1)}{\Gamma(z_2 \partial_{z_2} + v_2 - v_3 + 1)}.$$

It is the evident solution of the equations (3.3.21), (3.3.22). The equations (3.3.17) and (3.3.18) lead to the recurrence relations for the functions $\mathbf{a}[z_2 \partial_{z_2}]$ and $\mathbf{b}[x_1 \partial_{x_1}]$

$$\mathbf{a}[z_2 \partial_{z_2} + 1] \cdot (z_2 \partial_{z_2} + 1) = (z_2 \partial_{z_2} + u_2 - v_3 + 1) \cdot \mathbf{a}[z_2 \partial_{z_2}]$$

$$\mathbf{b}[x_1 \partial_{x_1} + 1] \cdot (x_1 \partial_{x_1} + u_1 - u_2 + 1) = (x_1 \partial_{x_1} + u_1 - v_2 + 1) \cdot \mathbf{b}[x_1 \partial_{x_1}]$$

The solution of these equations is

$$\mathbf{a}[z_2 \partial_{z_2}] = \frac{\Gamma(z_2 \partial_{z_2} + u_2 - v_3 + 1)}{\Gamma(z_2 \partial_{z_2} + 1)} ; \mathbf{b}[x_1 \partial_{x_1}] = \frac{\Gamma(x_1 \partial_{x_1} + u_1 - v_2 + 1)}{\Gamma(x_1 \partial_{x_1} + u_1 - u_2 + 1)}$$

and collecting everything together we obtain the expression for the operator \mathcal{R}_2 from the proposition.

4 Conclusions

We have shown that the general R-matrix can be represented as the product of the simple "building blocks" – \mathcal{R} -operators. In the present paper we have demonstrated how this factorization arises in the simplest situations of the symmetry algebra $sl(2)$ and $sl(3)$. As a byproduct we derived useful representation for the $sl(2)$ -invariant R-matrix

$$\mathbb{R}_{\ell_1 \ell_2}(u) = \mathbb{P}_{12} \mathcal{R}_1(u_1 | v_1, u_2) \mathcal{R}_2(u_1, u_2 | v_2) \sim \mathbb{P}_{12} \cdot \frac{\Gamma(z_{21} \partial_2 + 2\ell_1)}{\Gamma(z_{21} \partial_2 + \ell_1 + \ell_2 - u)} \cdot \frac{\Gamma(z_{12} \partial_1 + \ell_1 + \ell_2 + u)}{\Gamma(z_{12} \partial_1 + 2\ell_1)}$$

It is possible to represent the general $sl(2)$ -invariant R-matrix in many equivalent forms. The spectral decomposition of R-matrix (1.0.1) was obtained in the paper [7]. In functional representation R-matrix is some integral operator acting on the space of polynomials. The symbol and kernel of this integral operator was calculated in [18] and in [19] correspondingly. Here we obtain the representation for the R-matrix in the operator form. The similar operator expression for the Hamiltonian of the XXX spin chain was used in [20, 21, 22].

In the $sl(3)$ case we have derived the explicit expression for the general R-matrix in the factorized form

$$\mathbb{R}_{\Lambda_1 \Lambda_2}^{-1}(v - u) \sim \mathbb{P}_{12} \mathcal{R}_1(u_1; v_1, u_2, u_3) \mathcal{R}_2(u_1, u_2; v_2, u_3) \mathcal{R}_3(u_1, u_2, u_3; v_3).$$

The \mathcal{R} -operators in many respects are very similar to the general R-matrix but are much more simpler. In some sense the R-matrix is composite object and \mathcal{R} -operators are elementary building blocks. Using the simple pictures it is possible to derive the general system of defining relations for the \mathcal{R} -operators. First, there exist nontrivial commutation relations for the \mathcal{R} -operators acting in different spaces. Second, there are three term relations for the \mathcal{R} -operators which play the same role as Yang-Baxter relation for the R-matrix. Using defining relations for \mathcal{R} -operators it is possible to derive all relations for the general R-matrix including the Yang-Baxter equation. All this will be discussed elsewhere.

It seems that all these results can be generalized to the symmetry algebra $sl(n)$ where should exist the factorization of the general R-matrix on the product of n simple \mathcal{R} -operators. In the second part of this work we shall show that the same factorization take place for the general rational solution of the Yang-Baxter equation with the supersymmetry algebra $sl(2|1)$.

5 Acknowledgments

I would like to thank R.Kirschner, G.Korchemsky, P.Kulish, A.Manashov, E.Sklyanin and V.Tarasov for the stimulating discussions and critical remarks on the different stages of this work. This work was supported by the grant 03-01-00837 of the Russian Foundation for Fundamental Research.

References.

- [1] P.P. Kulish and E.K.Sklyanin , "On the solutions of the Yang-Baxter equation" Zap.Nauchn.Sem. LOMI **95** (1980) 129
- [2] M.Jimbo , "Introduction to the Yang-Baxter equation", Int.J.Mod.Phys **A 4**, (1983) 3759
"Yang-Baxter equation in integrable systems", M.Jimbo ed., Adv.Ser.Math.Phys., 10 , World Scientific(Singapore) 1990
- [3] V.G.Drinfeld, "Hopf algebras and Yang-Baxter equation", Soviet Math.Dokl. **32**(1985), 254
V.G.Drinfeld, "Quantum Groups" in "Proc.Int.Congress Math., Berkeley, 1986", AMS, Providence RI (1987), p 798
- [4] V.G.Drinfeld, "Quasi-Hopf algebras", Leningrad.Math.J. **1**(1990) 1419

- [5] V.Terras, "Drinfel'd twists and Functional Bethe Ansatz", Lett.Math.Phys.**48**(1999) 263
H.Pfeiffer, "Factorizing twists and the universal R-matrix of the Yangian $Y(sl_2)$ ",
J.Phys.A:Math.Gen **33**(2000), 8929
- [6] P.P. Kulish and E.K. Sklyanin , "Quantum spectral transform method. Recent developments",
Lect. Notes in Physics, v **151**, (1982) , 61,
L.D. Faddeev, "How Algebraic Bethe Ansatz works for integrable model", Les-Houches lectures
1995, hep-th/9605187,
E.K.Sklyanin, "Quantum Inverse Scattering Method.Selected Topics", in "Quantum Group
and Quantum Integrable Systems" (Nankai Lectures in Mathematical Physics), ed. Mo-Lin
Ge,Singapore:World Scientific,1992,pp.63-97; hep-th/9211111
- [7] P.P. Kulish, N.Yu.Reshetikhin and E.K.Sklyanin, "Yang-Baxter equation and representation
theory", Lett.Math.Phys. **5** (1981) 393-403
- [8] N. MacKay, "Rational R-matrices in irreducible representations", J.Phys. **A 24** (1991) 4017
R-B. Zhang, M.Gould and A.Bracken, "From the representation of the braid group to
solutions of the Yang-Baxter equation",Nucl.Phys. **B 354**, (1991) 625
M.Gould and Y-Z. Zhang, "R-matrices and the tensor product graph
method",hep-th/0205071
- [9] E.K. Sklyanin, *private communication*
- [10] D.P.Zhelobenko, "Compact Lie Groups and their Representations", AMS , Providence,
Rhode Island (1973)
- [11] J.J. de Swart, "The Octet Model and its Clebsch-Gordan Coefficients", Rev.Mod.Phys.v **35**,
(1963) 916
- [12] M.Shifman, "ITEP Lectures on Particle Physics and Field Theory", (1999) v**2** pp 775-875
World.Sci.Lect.Notes Phys. **62**
- [13] P.P. Kulish and N.Yu.Reshetikhin, "On $GL(3)$ -invariant solutions to the Yang-Baxter equa-
tion and the associated quantum systems", Zap.Nauchn.Sem. LOMI **120** (1982) 92
- [14] A.Molev "Yangians and their applications"(2002) math.QA/0211288
- [15] A.Molev, M.Nazarov and G.Olshanski "Yangian and classical Lie algebras", Russian
Math.Surveys**51:2**(1996), 205-282
- [16] P.P. Kulish, "Yang-Baxter equation and reflection equations in integrable mod-
els", hep-th/9507070
- [17] S.I.Alishauskas and P.P.Kulish, "Spectral resolution of the $su(3)$ -invariant solutions to the
Yang-Baxter equation", Zap.Nauchn.Sem. LOMI **145** (1985) 3
- [18] E.K. Sklyanin "Classical limits of the Yang-Baxter equation", J.Soviet.Math. **40**, (1988) 93
- [19] S.Derkachov, D.Karakhanyan, R.Kirschner "Universal R-matrix as integral operator"
Nucl.Phys. **B 618**, (2001) 589

- [20] L.N. Lipatov, "*High-energy asymptotics of multicolor QCD and exactly solvable lattice models*", JETP.Lett. **59**(1994)596
L.N. Lipatov, "*Duality symmetry of reggeon interactions in multicolor QCD*", Nucl.Phys. **B 548**, (1999) 328.
- [21] L.D.Faddeev and G.P.Korchemsky, "*Hight-energy QCD as a completely integrable model*", Phys.Lett.**B342**(1995)311.
- [22] D.Karakhianian and R.Kirschner, "*Conserved currents of the three-reggeon interaction*", hep-th/9902147; "*High-energy scattering in gauge theories and integrable spin chains*", hep-th/9902031, Fortschr. Phys.**48**, (2000) 139
- [23] C-N.Yang "*Some exact results for the many-body problem in one dimension with repulsive delta-function interaction*", Phys.Rev.Lett. **19** (1967) , 1312