

Transverse Solutions of the Vector Laplace and Helmholtz Equations for Spherical Coordinates and Boundary Conditions with Azimuthal Symmetry

Ernesto A. MATUTE

Departamento de Física, Universidad de Santiago de Chile, Casilla 307 - Correo 2, Santiago, Chile

ABSTRACT

A scalar field method to obtain transverse solutions of the vector Laplace and Helmholtz equations in spherical coordinates for boundary-value problems with azimuthal symmetry is described. Neither scalar nor vector potentials are used. Solutions are obtained by use of separation of variables instead of dyadic Green's functions expanded in terms of vector spherical harmonics. Applications to the calculations of magnetic fields from steady and oscillating localized current distributions are presented.

Keywords: Vector Laplace and Helmholtz Equations, Spherical Coordinates, Electromagnetic Fields.

1. INTRODUCTION

In many physical applications the vector Laplace equation $\nabla^2 \vec{F} = \vec{0}$ or the vector Helmholtz equation $\nabla^2 \vec{F} + k^2 \vec{F} = \vec{0}$ for spherical coordinates and boundary conditions has to be solved. It is the case for instance with the electric and magnetic fields wherever there is no free charge and current distributions. In spherical coordinates, however, the Laplacian of the vector $\nabla^2 \vec{F}$ leads to a set of three simultaneous equations, each equation involving all three components F_r , F_θ , F_φ [1]. This complication is well known and general techniques for solving these equations have been developed, based on a dyadic Green's function involving vector spherical harmonics which transforms the boundary conditions and source densities into the vector solution [2].

In a number of cases the vector field must also have zero divergence: $\vec{\nabla} \cdot \vec{F} = 0$. This is so for example for the magnetic field and in general for transverse vector fields. With this transverse condition it can be shown that the above vector equations can be separated into an equation for F_r alone. However, this is not true for the other two scalar components of the vector field. Nevertheless, it is possible to obtain a straightforward solution for F_θ in a problem with azimuthal symmetry; here we are not concerned about those symmetry cases where only

F_φ is nonzero because a scalar technique of separation of variables is already known to obtain the solution [3]. Several problems of physical interest can then be treated with the standard mathematical methods used to solving scalar field equations, so avoiding the dyadic method [4].

The purpose of this paper is to report the use of the technique to compute the solution to instructive examples taken from the electromagnetic theory, though there are different other places where vector fields show up. Specifically, we work out magnetic field solutions from localized current distributions. The main methods which may be used for solving boundary-value problems in magnetism involve the vector potential and the scalar potential [5]. The new technique we discuss here deals with the magnetic field itself, without reference to any kind of potential. The approach can also be used to calculate electric fields from localized charge distributions since the equations to be solved are the same.

2. TRANSVERSE SOLUTIONS OF THE VECTOR LAPLACE EQUATION

In order to calculate the components of the vector $\nabla^2 \vec{F}$ along the axes of the spherical system of coordinates, the following identity must be used:

$$\nabla^2 \vec{F} = -\vec{\nabla} \times (\vec{\nabla} \times \vec{F}) + \vec{\nabla}(\vec{\nabla} \cdot \vec{F}). \quad (1)$$

By combining with the transverse condition $\vec{\nabla} \cdot \vec{F} = 0$ and requiring azimuthal symmetry, we find the equation

$$\begin{aligned} (\nabla^2 \vec{F})_r &= \frac{1}{r^2} \frac{\partial^2}{\partial r^2} (r^2 F_r) + \frac{1}{r^2 \sin \theta} \frac{\partial}{\partial \theta} (\sin \theta \frac{\partial F_r}{\partial \theta}) \\ &= 0 \end{aligned} \quad (2)$$

for the radial component of the vector Laplace equation $\nabla^2 \vec{F} = \vec{0}$. To compute F_θ is convenient to use the transverse condition:

$$\begin{aligned} \vec{\nabla} \cdot \vec{F} &= \frac{1}{r^2} \frac{\partial}{\partial r} (r^2 F_r) + \frac{1}{r \sin \theta} \frac{\partial}{\partial \theta} (\sin \theta F_\theta) \\ &= 0, \end{aligned} \quad (3)$$

where azimuthal symmetry has been demanded.

Equation (2) can be solved by the usual technique of separation of variables. If a product form for F_r is assumed, then it can be written

$$F_r(r, \theta) = \frac{u(r)}{r^2} P(\theta). \quad (4)$$

The following separate equations for $u(r)$ and $P(\theta)$ are obtained:

$$\frac{d^2 u}{dr^2} - \frac{n(n+1)}{r^2} u = 0, \quad (5)$$

$$\frac{1}{\sin \theta} \frac{d}{d\theta} \left(\sin \theta \frac{dP}{d\theta} \right) + n(n+1)P = 0, \quad (6)$$

where $n(n+1)$ is the real separation constant. The solution of Eq. (5) is

$$u(r) = a r^{n+1} + \frac{b}{r^n}. \quad (7)$$

Equation (6) is the Legendre equation of order n and the only solution which is single valued, finite and continuous over the whole interval corresponds to the Legendre polynomial $P_n(\cos \theta)$, n being a positive integer. Thus the general solution for F_r is

$$F_r(r, \theta) = \sum_{n=0}^{\infty} \left(a_n r^{n+1} + \frac{b_n}{r^{n+2}} \right) P_n(\cos \theta). \quad (8)$$

The simplest way of treating Eq. (3) is to use the series expansion

$$F_\theta(r, \theta) = \sum_{n=0}^{\infty} v_n(r) \frac{d}{d\theta} P_n(\cos \theta), \quad (9)$$

where $v_n(r)$ are functions to be determined. By replacing Eqs. (8) and (9) into Eq. (3), it is found that

$$v_n(r) = \frac{a_n}{n} r^{n-1} - \frac{b_n}{n+1} \frac{1}{r^{n+2}} \quad (10)$$

for $n \geq 1$ with $a_0 = 0$. The coefficients a_n and b_n are to be determined from the boundary conditions.

On the other hand, we note that the solution obtained from Eqs. (8), (9) and (10) satisfies the angular component of the Laplace equation for transverse vector fields and azimuthal symmetry:

$$(\nabla^2 \vec{F})_\theta = \frac{1}{r} \frac{\partial^2}{\partial r^2} (r F_\theta) - \frac{1}{r} \frac{\partial^2 F_r}{\partial r \partial \theta} = 0, \quad (11)$$

as expected by consistency. This happens because Eqs. (2) and (3) imply

$$\frac{\partial}{\partial r} (r F_\theta) - \frac{\partial F_r}{\partial \theta} = 0, \quad (12)$$

which leads to Eq. (11); clearly, the solutions given in Eqs. (8), (9) and (10) satisfy Eq. (12).

In the case of the magnetic field, we recall that the boundary conditions at a boundary separating two regions are

$$\begin{aligned} \hat{n} \cdot (\vec{B}_1 - \vec{B}_2) &= 0, \\ \hat{n} \times (\vec{H}_1 - \vec{H}_2) &= \vec{J}_S, \end{aligned} \quad (13)$$

where \vec{J}_S is the surface current density and the normal unit vector \hat{n} is drawn from the second region into the first one. For a linear medium the constitutive relation $\vec{B} = \mu \vec{H}$ holds, μ being the constant magnetic permeability. To see how the technique works out, we consider the simple, common textbook example of the magnetic field produced by the rotation of a sphere of radius a , uniformly charged with a charge Q , with constant angular velocity ω , which is usually solved with the vector potential method [2,5]. The surface current density at $r = a$ is

$$\vec{J}_S(a, \theta, \varphi) = \frac{\omega Q}{4\pi a} \sin \theta \hat{\varphi}, \quad (14)$$

where the z axis has been chosen along the rotation axis. The problem reduces to using the series solutions (8), (9) and (10) of the Laplace equation in the regions $r > a$ and $r < a$ to conform to the requirement that the magnetic field must be finite at the origin, vanish at infinity and satisfy the boundary conditions of Eq. (13) at $r = a$. Using $\vec{B} = \mu_0 \vec{H}$, where μ_0 is the vacuum magnetic permeability, the resulting magnetic field can be seen to be

$$\vec{H}(r, \theta) = \frac{\omega Q}{12\pi} \begin{cases} \frac{a^2}{r^3} (3 \cos \theta \hat{r} - \hat{z}); & r > a \\ \frac{2}{a} \hat{z}; & r < a \end{cases}. \quad (15)$$

This solution describes a uniform magnetic field inside the sphere and a dipole field outside with dipole moment $\vec{m} = \hat{z} \omega Q a^2 / 3$.

Another example is that of the magnetic field from a circular current loop of radius a lying in the x - y plane with its center at the origin and carrying a current I . In this case the surface current density at $r = a$ is

$$\vec{J}_S(a, \theta, \varphi) = \frac{I}{a} \delta(\cos \theta) \hat{\varphi}. \quad (16)$$

The radial component of the magnetic field turns out

to be now

$$H_r(r, \theta) = \frac{I}{2} \sum_{n=0}^{\infty} \frac{(-1)^n (2n+1)!!}{2^n n!} P_{2n+1}(\cos \theta) \times \begin{cases} \frac{a^{2n+2}}{r^{2n+3}}; & r > a \\ \frac{r^{2n}}{a^{2n+1}}; & r < a \end{cases}, \quad (17)$$

while the angular component becomes

$$H_\theta(r, \theta) = \frac{I}{4} \sum_{n=0}^{\infty} \frac{(-1)^n (2n+1)!!}{2^n (n+1)!} P_{2n+1}^1(\cos \theta) \times \begin{cases} -\frac{a^{2n+2}}{r^{2n+3}}; & r > a \\ \left(\frac{2n+2}{2n+1}\right) \frac{r^{2n}}{a^{2n+1}}; & r < a \end{cases}, \quad (18)$$

where $P_{2n+1}^1(\cos \theta) = (d/d\theta) P_{2n+1}(\cos \theta)$ is an associated Legendre polynomial.

3. TRANSVERSE SOLUTIONS OF THE VECTOR HELMHOLTZ EQUATION

In the case of the Helmholtz equation for transversal vector fields the radial equation becomes

$$(\nabla^2 \vec{F})_r + k^2 F_r = \frac{1}{r^2} \frac{\partial^2}{\partial r^2} (r^2 F_r) + \frac{1}{r^2 \sin \theta} \frac{\partial}{\partial \theta} (\sin \theta \frac{\partial F_r}{\partial \theta}) + k^2 F_r = 0. \quad (19)$$

Equation (3) still applies for problems possessing azimuthal symmetry; it is used to obtain F_θ from F_r .

Next, by putting

$$F_r(r, \theta) = \frac{j(r)}{r} P(\theta), \quad (20)$$

we can separate Eq. (19) into two equations:

$$\frac{d^2 j}{dr^2} + \frac{2}{r} \frac{dj}{dr} + \left[k^2 - \frac{n(n+1)}{r^2} \right] j = 0 \quad (21)$$

for $j(r)$ and Eq. (6) for $P(\theta)$, where $n(n+1)$ is the separation constant. Equation (21) is the spherical Bessel equation of order n in the variable kr . Therefore, the general solution for F_r is

$$F_r(r, \theta) = \sum_{n=0}^{\infty} \left[c_n \frac{j_n(kr)}{r} + d_n \frac{n_n(kr)}{r} \right] P_n(\cos \theta). \quad (22)$$

Depending on boundary conditions, the spherical Hankel functions $h_n^{(1,2)}$ instead of the spherical Bessel functions j_n, n_n may be used. For F_θ we again assume

$$F_\theta(r, \theta) = \sum_{n=0}^{\infty} w_n(r) \frac{d}{d\theta} P_n(\cos \theta), \quad (23)$$

where for w_n we now obtain

$$w_n(r) = \frac{c_n}{n(n+1)r} \frac{d}{dr} [r j_n(kr)] + \frac{d_n}{n(n+1)r} \frac{d}{dr} [r n_n(kr)]. \quad (24)$$

The constants c_n and d_n are computed from the requirement that the vector field has to satisfy the boundary conditions of the given problem.

On the other hand, we observe that the solution given in Eqs. (22), (23) and (24) satisfies the angular component of the Helmholtz equation for transverse vector fields and azimuthal symmetry:

$$(\nabla^2 \vec{F})_\theta + k^2 F_\theta = \frac{1}{r} \frac{\partial^2}{\partial r^2} (r F_\theta) - \frac{1}{r} \frac{\partial^2 F_r}{\partial r \partial \theta} + k^2 F_\theta = 0, \quad (25)$$

as expected, where Eq. (21) must be used.

An illustration is provided by the problem of the radiation from a vibrating current loop lying in the x - y plane. The surface density current at $r = a$ is

$$\vec{J}_S(a, \theta, \varphi, t) = \frac{I_0}{a} \delta(\cos \theta) e^{-i\omega t} \hat{\varphi}. \quad (26)$$

The series solution of the Helmholtz equation for the magnetic field, which is finite at the origin, represents outgoing waves at infinity and conforms to the boundary conditions of Eq. (13) at $r = a$, is then given by

$$H_r(r, \theta, t) = i \frac{I_0 k a}{2r} e^{-i\omega t} \sum_{n=0}^{\infty} \frac{(-1)^n (4n+3)}{2^n} \times \frac{(2n+1)!!}{n!} P_{2n+1}(\cos \theta) \begin{cases} j_{2n+1}(ka) h_{2n+1}^{(1)}(kr) \\ j_{2n+1}(kr) h_{2n+1}^{(1)}(ka) \end{cases} \quad (27)$$

and

$$\begin{aligned}
H_\theta(r, \theta, t) &= i \frac{I_0 k^2 a}{2} e^{-i\omega t} \sum_{n=0}^{\infty} \frac{(-1)^n (4n+3)}{2^{n+1} (2n+1)} \\
&\times \frac{(2n+1)!!}{(n+1)!} P_{2n+1}^1(\cos \theta) \\
&\times \begin{cases} j_{2n+1}(ka) \left[h_{2n}^{(1)}(kr) - \frac{2n+1}{kr} h_{2n+1}^{(1)}(kr) \right] \\ h_{2n+1}^{(1)}(ka) \left[j_{2n}(kr) - \frac{2n+1}{kr} j_{2n+1}(kr) \right] \end{cases} \quad (28)
\end{aligned}$$

where the upper lines hold for $r > a$ and the lower lines for $r < a$. The radiative part of the magnetic field takes on the limiting form

$$\begin{aligned}
\vec{H}(r, \theta, t) &= \hat{\theta} \frac{I_0 k a}{4r} e^{i(kr - \omega t)} \sum_{n=0}^{\infty} \frac{(4n+3)(2n+1)!!}{2^n (2n+1)(n+1)!} \\
&\times j_{2n+1}(ka) P_{2n+1}^1(\cos \theta). \quad (29)
\end{aligned}$$

The resulting magnetic field can be seen to be the same as that obtained by another more extensive methods [2].

4. CONCLUSION

The expressions for the components of $\nabla^2 \vec{F}$ in spherical coordinates are really messy, but they appear for instance in Laplace and Helmholtz equations for vector fields, such as the electromagnetic fields. We have presented a fairly simple technique of separation of variables to compute transverse solutions with $\vec{\nabla} \cdot \vec{F} = 0$ of these vector equations applied to boundary-value problems with azimuthal symmetry, so avoiding the general, more extensive method in which dyadic Green's functions and series expansions in vector spherical harmonics

are introduced. It involves scalar solutions for the spherical components of \vec{F} which resemble the ones obtained for the scalar Laplace and Helmholtz equations. No scalar or vector potentials are used. Illustrations were provided by problems concerned with the magnetic field from steady and oscillating localized currents. We finally remark that the method can also be extended to solving boundary-value problems in cylindrical coordinates possessing azimuthal symmetry, although in this case we deal with a separated equation for each scalar component of the vector field [1], so that the problem of solving the vector Laplace or Helmholtz equation reduces to that of solving the corresponding scalar equation.

5. ACKNOWLEDGMENTS

This work was partially supported by the Departamento de Investigaciones Científicas y Tecnológicas, Universidad de Santiago de Chile.

6. REFERENCES

- [1] G. Arfken and H. Weber, **Mathematical Methods for Physicists**, New York: Academic Press Inc., 2001, 5th edition, Chap. 2.
- [2] P.M. Morse and H. Feshbach, **Methods of Theoretical Physics**, New York: McGraw-Hill Book Company Inc., 1953, Vol. 2, Chap. 13.
- [3] Reference [1], Chap. 12.
- [4] E.A. Matute, "On the Superconducting Sphere in an External Magnetic Field", **American Journal of Physics**, Vol. 67, No. 9, 1999, pp. 786-788.
- [5] J.D. Jackson, **Classical Electrodynamics**, New York: John Wiley & Sons Inc., 1998, 3rd edition, Chap. 5.