

The Existence of Strongly-MDS Convolutional Codes*

Ryan Hutchinson

Department of Mathematics and Computer Science
Bemidji State University
e-mail: rhutchinson@bemidjstate.edu

November 2, 2018

Abstract

It is known that maximum distance separable and maximum distance profile convolutional codes exist over large enough finite fields of any characteristic for all parameters (n, k, δ) . It has been conjectured that the same is true for convolutional codes that are strongly maximum distance separable. Using methods from linear systems theory, we resolve this conjecture by showing that, over a large enough finite field of any characteristic, codes which are simultaneously maximum distance profile and strongly maximum distance separable exist for all parameters (n, k, δ) .

Keywords: MDS codes, convolutional codes, column distances, linear systems, minimal partial realization problem.

1 Introduction

In recent literature on convolutional codes, several new classes of codes with optimal distance properties have been introduced. These classes of codes are known as maximum distance separable (MDS) codes, maximum distance profile (MDP) codes, and strongly MDS (sMDS) codes. MDS codes are characterized by the property that they have the maximum possible free distance for a given choice of code parameters. sMDS codes are a subclass of MDS codes having the property that this maximum possible free distance is attained at the earliest possible encoding step. MDP codes are characterized by the property that their column distances grow at the maximum possible rate for a given choice of code parameters.

In [18], it is shown that MDS convolutional codes exist for all parameters (n, k, δ) over sufficiently large finite fields; in [11], a similar result is obtained for codes having the MDP property. In [8], sMDS convolutional codes are introduced and studied, and they are shown

*This work was supported in part by NSF grants DMS-00-72383 and CCR-02-05310.

to exist for parameters (n, k, δ) satisfying $(n - k) \mid \delta$. In addition, it is conjectured that convolutional codes possessing the MDP and sMDS properties together exist for all (n, k, δ) . In this work, we show that this conjecture is correct. The approach used is systems-theoretic in nature; to obtain the proof, we make use of the well-known interpretation of a convolutional code as an input-state-output linear system as well as results from partial realization theory.

The structure of this paper is as follows. In Section 2, we review relevant ideas from the theory of convolutional codes. We recall as well a connection between convolutional codes and input-state-output linear systems that we will use to obtain our results. In Section 3, we use a linear systems representation of convolutional codes to give a characterization of the sMDS property. In Section 4, we use this characterization to show the existence, for all parameters (n, k, δ) , of codes possessing both the MDP and sMDS properties.

2 Convolutional Codes and Linear Systems

In this section, we recall some facts about convolutional codes and their connection with linear systems. Throughout this paper, 0 will be understood to be the zero matrix or vector of the appropriate size. Let k and n be positive integers with $k < n$, p a prime number, \mathbb{K} the algebraic closure of the prime field \mathbb{F}_p , and \mathbb{F} a finite subfield of \mathbb{K} .

Definition 2.1 A *convolutional code* \mathcal{C} of rate k/n is a rank- k direct summand of $\mathbb{F}[s]^n$.

\mathcal{C} is a free $\mathbb{F}[s]$ -module and may thus be viewed as the column space of a full-rank matrix $G(s) \in \mathbb{F}[s]^{n \times k}$, called a *generator matrix* for \mathcal{C} . Two full-rank $n \times k$ matrices $G_1(s)$ and $G_2(s)$ generate the same code if and only if there exists a unimodular matrix $U(s) \in \mathbb{F}[s]^{k \times k}$ such that $G_1(s) = G_2(s)U(s)$.

When convenient, we will (at times with a slight abuse of notation) make use of the fact that $\mathbb{F}[s]^n$ and $\mathbb{F}^n[s]$ are isomorphic $\mathbb{F}[s]$ -modules and think of codewords as elements of $\mathbb{F}^n[s]$. For example, the columns of a generator matrix $G(s)$ may be thought of as polynomials with coefficients in \mathbb{F}^n ; we refer to the degrees of these polynomials as the *column degrees* of $G(s)$ and denote the degree of the j th column by δ_j . The *high-order coefficient matrix* of $G(s)$, G_∞ , is the matrix whose j th column is the column coefficient of s^{δ_j} in the j th column of $G(s)$. In general, G_∞ need not have full rank. It is always possible, though, to find a unimodular matrix $U(s) \in \mathbb{F}[s]^{k \times k}$ such that $G(s)U(s)$ has a full-rank high-order coefficient matrix (see [7]). If G_∞ has full rank, then $G(s)$ is called a *minimal generator matrix*.

An important invariant of a convolutional code is its degree, defined as follows:

Definition 2.2 The *degree* δ of a convolutional code \mathcal{C} is the maximal degree of a (polynomial) determinant of a $k \times k$ submatrix of a generator matrix of \mathcal{C} .

This definition makes sense, as multiplication by a unimodular matrix preserves the degrees of such determinants. We note that, if $G(s)$ is a minimal generator matrix of \mathcal{C} with column

degrees $\delta_1, \dots, \delta_k$, then $\delta = \sum_{j=1}^k \delta_j$. A code of rate k/n and degree δ will be referred to as an (n, k, δ) -code.

We turn next to notions of distance. We first recall the definition of Hamming weight:

Definition 2.3 Let $v \in \mathbb{F}^n$ and $v(t) := \sum_{t=0}^d v_t s^t \in \mathbb{F}^n[s]$. The *Hamming weight of v* , $\text{wt}(v)$, is the number of nonzero components of v . The Hamming weight of $v(t)$ is $\text{wt}(v(t)) := \sum_{t=0}^d \text{wt}(v_t)$.

For the purpose of error control coding, it is important that the minimum weight among the codewords of a code be as large as possible. This leads to the concept of free distance:

Definition 2.4 The *free distance* of a convolutional code \mathcal{C} is

$$d_{\text{free}}(\mathcal{C}) := \min\{\text{wt}(v(t)) \mid v(t) \in \mathcal{C} \setminus \{0\}\}.$$

Column distances also play an important part in what follows. They measure the minimum possible distance between truncated codewords:

Definition 2.5 Let \mathcal{C} be a convolutional code. For $j \in \mathbb{N}_0$, the *j th column distance* of \mathcal{C} is

$$d_j^c(\mathcal{C}) := \min \left\{ \sum_{t=0}^j \text{wt}(v_t) \mid v(t) \in \mathcal{C} \text{ and } v_0 \neq 0_n \right\},$$

where $v_j = 0_n$ if $j > \deg v(t)$.

The following result gives upper bounds for the column distances and the free distance of a convolutional code.

Proposition 2.6 Let \mathcal{C} be an (n, k, δ) -code.

1. For every $j \in \mathbb{N}_0$,

$$d_j^c(\mathcal{C}) \leq (n - k)(j + 1) + 1.$$

If $d_j^c(\mathcal{C}) = (n - k)(j + 1) + 1$ for some j , then $d_i^c(\mathcal{C}) = (n - k)(i + 1) + 1$ when $i \in \{0, \dots, j\}$.

- 2.

$$d_{\text{free}}(\mathcal{C}) \leq (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1.$$

Statement 1 is proved in [8], and statement 2 is proved in [18]. The bound in 2 is called the *generalized Singleton bound*.

Set $L := \left\lfloor \frac{\delta}{k} \right\rfloor + \left\lfloor \frac{\delta}{n - k} \right\rfloor$ and $M := \left\lfloor \frac{\delta}{k} \right\rfloor + \left\lceil \frac{\delta}{n - k} \right\rceil$. We are now ready to define the code properties of interest in this work:

Definition 2.7 Let \mathcal{C} be an (n, k, δ) -code. Then,

1. \mathcal{C} is called a *maximum distance profile code* (MDP code) if

$$d_L^c(\mathcal{C}) = (n - k)(L + 1) + 1.$$

2. \mathcal{C} is called a *maximum distance separable code* (MDS code) if

$$d_{free}(\mathcal{C}) = (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1.$$

3. \mathcal{C} is called a *strongly MDS code* (sMDS code) if

$$d_M^c(\mathcal{C}) = (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1.$$

Using the fact that no column distance of \mathcal{C} can exceed the generalized Singleton bound, one can show that L is the largest possible value of j for which $d_j^c(\mathcal{C})$ can attain the upper bound in statement 1 of Proposition 2.6. If \mathcal{C} is an MDP code, then, by Proposition 2.6, $d_i^c(\mathcal{C})$ attains this upper bound when $i \in \{0, \dots, L\}$. Thus, 1 says that the column distances of an MDP code are maximal until it is no longer possible. Similarly, one can show that, if $j < M$, then $d_j^c(\mathcal{C}) < (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1$. Thus, 3 says that, for an sMDS code, the sequence $\{d_j^c(\mathcal{C})\}_{j \geq 0}$ attains the generalized Singleton bound at the smallest possible value of j .

In the second part of this section, we introduce a connection between convolutional codes and linear systems that we will use to obtain our results. Background information for this discussion and applications of ideas from systems theory to the construction of convolutional codes may be found, for example, in [2, 3, 17, 19, 20].

Let $A \in \mathbb{K}^{\delta \times \delta}$, $B \in \mathbb{K}^{\delta \times k}$, $C \in \mathbb{K}^{(n-k) \times \delta}$, and $D \in \mathbb{K}^{(n-k) \times k}$. Note that, since the number of entries in the matrices (A, B, C, D) is finite, these matrices are actually defined over a finite subfield \mathbb{F} of \mathbb{K} . The matrices (A, B, C, D) describe a time-invariant linear system through the equations

$$\begin{aligned} x_{t+1} &= Ax_t + Bu_t, \\ y_t &= Cx_t + Du_t, \\ x_0 &= 0, \end{aligned} \tag{2.1}$$

where $x_t \in \mathbb{F}^\delta$, $u_t \in \mathbb{F}^k$, and $y_t \in \mathbb{F}^{n-k}$ are called the *state vector*, *input vector*, and *output vector* at time t , respectively. The matrix quadruple (A, B, C, D) is called a *realization* for the system. We recall the following well-known definition:

Definition 2.8 (A, B) is called a *reachable pair* if

$$\text{rank} \left(\begin{bmatrix} B & AB & \dots & A^{\delta-2}B & A^{\delta-1}B \end{bmatrix} \right) = \delta.$$

(A, C) is called an *observable pair* if

$$\text{rank} \left(\begin{bmatrix} C^T & (CA)^T & \dots & (CA^{\delta-2})^T & (CA^{\delta-1})^T \end{bmatrix}^T \right) = \delta.$$

$$4. H(s) \begin{bmatrix} y(s) \\ u(s) \end{bmatrix} = [-Q(s) \ P(s)] \begin{bmatrix} y(s) \\ u(s) \end{bmatrix} = 0.$$

$$5. y(s) = T(s)u(s).$$

Further, the right $\mathbb{F}[s]$ -kernel of $H(s)$ is an (n, k, δ) -code \mathcal{C} .

The code \mathcal{C} is not quite suitable for our purposes. This is due to the fact that the finite-weight sequence

$$\begin{pmatrix} y_0 \\ u_0 \end{pmatrix}, \begin{pmatrix} y_1 \\ u_1 \end{pmatrix}, \dots, \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix}, \begin{pmatrix} y_d \\ u_d \end{pmatrix}$$

corresponds with the codeword

$$\begin{pmatrix} y_d \\ u_d \end{pmatrix} + \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix} s + \dots + \begin{pmatrix} y_1 \\ u_1 \end{pmatrix} s^{d-1} + \begin{pmatrix} y_0 \\ u_0 \end{pmatrix} s^d \in \mathcal{C}.$$

Working in the systems setting, we will show there is a realization $(A, B, C, D) \in S_{k,n}^\delta$ for which any finite-weight sequence

$$\begin{pmatrix} y_0 \\ u_0 \end{pmatrix}, \begin{pmatrix} y_1 \\ u_1 \end{pmatrix}, \dots, \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix}, \begin{pmatrix} y_d \\ u_d \end{pmatrix}$$

(with $u_0 \neq 0$) formed using (2.1) has the properties that

$$\sum_{t=0}^L \text{wt} \left(\begin{pmatrix} y_t \\ u_t \end{pmatrix} \right) = (L+1)(n-k) + 1$$

and

$$\sum_{t=0}^M \text{wt} \left(\begin{pmatrix} y_t \\ u_t \end{pmatrix} \right) \geq (n-k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1.$$

Due to the order reversal noted above, it will not necessarily be true that $d_L^c(\mathcal{C}) = (L+1)(n-k) + 1$. The next result shows how to overcome this problem:

Proposition 2.9 *Let \mathcal{C} be an (n, k, δ) -code with minimal generator matrix $G(s)$. Let $\overline{G(s)}$ be the matrix obtained by replacing each entry $p_{ij}(s)$ of $G(s)$ by $\overline{p_{ij}(s)} := s^{\delta_j} p_{ij}(s^{-1})$, where δ_j is the j th column degree of $G(s)$. Then, $\overline{G(s)}$ is a minimal generator matrix of an (n, k, δ) -code $\overline{\mathcal{C}}$, and*

$$\begin{pmatrix} y_0 \\ u_0 \end{pmatrix} + \begin{pmatrix} y_1 \\ u_1 \end{pmatrix} s + \dots + \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix} s^{d-1} + \begin{pmatrix} y_d \\ u_d \end{pmatrix} s^d \in \overline{\mathcal{C}}$$

if and only if

$$\begin{pmatrix} y_d \\ u_d \end{pmatrix} + \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix} s + \dots + \begin{pmatrix} y_1 \\ u_1 \end{pmatrix} s^{d-1} + \begin{pmatrix} y_0 \\ u_0 \end{pmatrix} s^d \in \mathcal{C}.$$

PROOF: First, $\overline{G(s)}$ has rank k , since a $k \times k$ minor of $\overline{G(s)}$ is zero if and only if the corresponding minor of $G(s)$ is.

Next, let G_0 denote the $n \times k$ matrix whose ij th entry is $p_{ij}(0)$ and $\overline{G_0}$ the $n \times k$ matrix whose ij th entry is $\overline{p_{ij}(0)}$. Because \mathcal{C} is a summand of $\mathbb{F}[s]^n$, G_0 has full rank, so that each column of G_0 has at least one nonzero entry. This means that $G_0 = \overline{G_\infty}$, $\overline{G_\infty}$ has full rank, corresponding columns of $G(s)$ and $\overline{G(s)}$ have the same column degrees, and $\overline{\overline{G(s)}} = G(s)$. From the definition of $\overline{G(s)}$, we have that $G_\infty = \overline{G_0}$; since $G(s)$ is minimal, $\overline{G_0}$ also has full rank.

Suppose $p(s) \in \mathbb{F}[s]$ has degree d and is a common divisor of the $k \times k$ minors of $\overline{G(s)}$. Since $\overline{G_0}$ has full rank, $p(0) \neq 0$, so that $s^d p(s^{-1})$ has degree d . Since $\overline{\overline{G(s)}} = G(s)$, $s^d p(s^{-1})$ is a common divisor of the $k \times k$ minors of $G(s)$. As \mathcal{C} is a summand of $\mathbb{F}[s]^n$, it follows that $d = 0$, so that the only common divisors of the $k \times k$ minors of $\overline{G(s)}$ are the nonzero elements of \mathbb{F} . Thus, the column space of $\overline{G(s)}$ is a summand of $\mathbb{F}[s]^n$, which means that it is a rate k/n convolutional code $\overline{\mathcal{C}}$. It follows from the remarks in the preceding paragraph that $\overline{G(s)}$ is a minimal generator matrix of $\overline{\mathcal{C}}$ and that $\overline{\mathcal{C}}$ has degree δ .

Consider the vector polynomials

$$v(s) := v_d + v_{d-1}s + \cdots + v_1s^{d-1} + v_0s^d$$

and

$$\overline{v(s)} := v_0 + v_1s + \cdots + v_{d-1}s^{d-1} + v_ds^d$$

in $\mathbb{F}^n[s]$, and note that $\overline{\overline{v(s)}} = s^d v(s^{-1})$. Thinking of $v(s)$ and $\overline{v(s)}$ as column vectors in $\mathbb{F}[s]^n$, we observe that a $(k+1) \times (k+1)$ minor of $\begin{bmatrix} G(s) & v(s) \end{bmatrix}$ is zero if and only if the corresponding minor of $\begin{bmatrix} \overline{G(s)} & \overline{v(s)} \end{bmatrix}$ is. Since \mathcal{C} and $\overline{\mathcal{C}}$ are summands of $\mathbb{F}[s]^n$, this means that $v(s) \in \mathcal{C}$ if and only if $\overline{v(s)} \in \overline{\mathcal{C}}$. \square

This result, together with the remarks preceding it, shows that

$$\begin{pmatrix} y_0 \\ u_0 \end{pmatrix}, \begin{pmatrix} y_1 \\ u_1 \end{pmatrix}, \dots, \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix}, \begin{pmatrix} y_d \\ u_d \end{pmatrix}$$

is a finite-weight sequence for (A, B, C, D) if and only if

$$\begin{pmatrix} y_0 \\ u_0 \end{pmatrix} + \begin{pmatrix} y_1 \\ u_1 \end{pmatrix} s + \cdots + \begin{pmatrix} y_{d-1} \\ u_{d-1} \end{pmatrix} s^{d-1} + \begin{pmatrix} y_d \\ u_d \end{pmatrix} s^d \in \overline{\mathcal{C}}.$$

$\overline{\mathcal{C}}$, then, will have the property that $d_M^c(\overline{\mathcal{C}}) = (n-k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1$. For the rest of the paper, we will refer to the code $\overline{\mathcal{C}}$ as the code represented by the matrices (A, B, C, D) .

3 Trivial Rank Deficiency and the sMDS Property

In this section, we give conditions on the entries of the matrices in a realization $(A, B, C, D) \in S_{k,n}^\delta$ guaranteeing that the convolutional code these matrices represent has both the MDP

and sMDS properties. For $(A, B, C, D) \in S_{k,n}^\delta$ and $j \in \mathbb{N}_0$, we form the matrices

$$\mathcal{T}_j := \begin{bmatrix} D & 0 & \cdots & \cdots & 0 \\ CB & D & \ddots & & \vdots \\ CAB & CB & \ddots & \ddots & \vdots \\ \vdots & \vdots & \ddots & \ddots & 0 \\ CA^{j-1}B & CA^{j-2}B & \cdots & CB & D \end{bmatrix}. \quad (3.2)$$

Notation 3.1 Let $l_1, l_2 \in \mathbb{N}$ satisfy $1 \leq l_1 \leq (j+1)(n-k)$ and $1 \leq l_2 \leq (j+1)k$. Let $1 \leq i_1 < \cdots < i_{l_1} \leq (j+1)(n-k)$ and $1 \leq j_1 < \cdots < j_{l_2} \leq (j+1)k$ be two sequences of integers. We denote by $(\mathcal{T}_j)_{j_1, \dots, j_{l_2}}^{i_1, \dots, i_{l_1}}$ the $l_1 \times l_2$ submatrix obtained from \mathcal{T}_j by intersecting rows i_1, \dots, i_{l_1} and columns j_1, \dots, j_{l_2} .

Notice that, if $(\mathcal{T}_j)_{j_1}^{i_1} \neq 0$, then $j_1 \leq \lceil \frac{i_1}{n-k} \rceil k$.

In what follows, the notion of trivial rank deficiency plays an important role. To define trivial rank deficiency, we think of replacing the entries of the block matrices in \mathcal{T}_j with the indeterminates of the polynomial ring $R := \mathbb{K}[x_1, x_2, \dots, x_{(j+1)(n-k)k}]$. Specifically, we replace the entry (s, t) of the matrix D with the indeterminate $x_{(s-1)k+t}$ and the entry (s, t) of the matrix CA^iB with the indeterminate $x_{(i+1)(n-k)k+(s-1)k+t}$. The zero entries above the block diagonal remain zero.

Definition 3.2 Let c be an integer with $0 \leq c \leq n-k-1$, and let l be an integer satisfying $1 \leq l \leq \min\{(j+1)(n-k)-c, (j+1)k\}$. A square submatrix of \mathcal{T}_j is said to be *trivially rank deficient* if the determinant of this submatrix is zero when it is viewed as a matrix over R in the manner described above. A submatrix $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ of \mathcal{T}_j is called *trivially rank deficient* if all $\binom{l+c}{l}$ $l \times l$ submatrices of $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ are trivially rank deficient.

To say that $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ is trivially rank deficient is to say that $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ has less than full rank regardless of how elements of \mathbb{K} are substituted for the indeterminates of R . The next lemma shows how to determine if a given submatrix is trivially rank deficient.

Lemma 3.3 Let l be an integer with $1 \leq l \leq \min\{(j+1)(n-k)-c, (j+1)k\}$, and let $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ be an $(l+c) \times l$ submatrix of \mathcal{T}_j . Then, the following are equivalent:

1. $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+c}}$ is trivially rank deficient.
2. $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_{1+c}, i_{2+c}, \dots, i_{l+c}}$ is trivially rank deficient.
3. The inequality

$$j_t > \left\lceil \frac{i_{t+c}}{n-k} \right\rceil k$$

holds for some $t \in \{1, \dots, l\}$.

PROOF: For notational convenience, we set $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}} := (\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1+c, i_2+c, \dots, i_l+c}$ and $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}} := (\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_l+c}$.

1 \implies **2**: Suppose $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient. Then, by definition, all $\binom{l+c}{l}$ $l \times l$ submatrices of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ are trivially rank deficient. In particular, $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient.

2 \implies **3**: Suppose that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient. We first use induction on l to prove that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is lower block triangular and has a 0 on its diagonal. If $l = 1$ and $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient, then the claim is trivially true. Suppose l satisfies $2 \leq l \leq \min\{(j+1)(n-k) - c, (j+1)k\}$, that the induction hypothesis is satisfied for $1, 2, \dots, l-1$, and that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient. If $(\mathcal{T}_j)_{j_1}^{i_1+c} = 0$, then every entry in $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is 0, and thus all diagonal entries are 0. If $(\mathcal{T}_j)_{j_1}^{i_1+c} \neq 0$, then let x_l be the indeterminate corresponding with $(\mathcal{T}_j)_{j_1}^{i_1+c}$ when \mathcal{T}_j is viewed over R in the manner described before Definition 3.2. Notice that, when $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is viewed in this way, the indeterminate x_l appears exactly once. Since x_l is transcendental over $\mathbb{K}(x_1, \dots, x_{l-1})$, doing a cofactor expansion along the first column of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ (still viewing $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ over R) shows that the $(l-1) \times (l-1)$ submatrix $(\mathcal{T}_j)_{j_2, j_3, \dots, j_l}^{i_1+c, i_2+c, \dots, i_{l-1}+c}$ is trivially rank deficient. By the induction hypothesis, $(\mathcal{T}_j)_{j_2, j_3, \dots, j_l}^{i_1+c, i_2+c, \dots, i_{l-1}+c}$ is lower block triangular and has a 0 on its diagonal. It follows that there is an integer h satisfying $1 \leq h \leq l-1$ such that $(\mathcal{T}_j)_{j_{h+1}}^{i_{h+1}+c} = 0$. This, in turn, means that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is lower block triangular. Because we assumed that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient, it follows that at least one of $(\mathcal{T}_j)_{j_1, j_2, \dots, j_h}^{i_1+c, i_2+c, \dots, i_h+c}$ and $(\mathcal{T}_j)_{j_{h+1}, j_{h+2}, \dots, j_l}^{i_{h+1}+c, i_{h+2}+c, \dots, i_l+c}$ is trivially rank deficient. By the induction hypothesis, at least one of these submatrices is lower block triangular and has a 0 on its diagonal. As the diagonals of these submatrices lie on the diagonal of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$, the claim follows.

Next, we note that the diagonal entries of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ are the entries $(\mathcal{T}_j)_{j_1}^{i_1+c}, (\mathcal{T}_j)_{j_2}^{i_2+c}, \dots, (\mathcal{T}_j)_{j_l}^{i_l+c}$. From the structure of \mathcal{T}_j , it is clear that, when $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is viewed over R , a diagonal entry $(\mathcal{T}_j)_{j_t}^{i_t+c}$ is 0 if and only if

$$j_t > \left\lceil \frac{i_{t+c}}{n-k} \right\rceil k.$$

It follows that

$$j_t > \left\lceil \frac{i_{t+c}}{n-k} \right\rceil k$$

for some $t \in \{1, \dots, l\}$.

3 \implies **1**: If

$$j_t > \left\lceil \frac{i_{t+c}}{n-k} \right\rceil k$$

for some $t \in \{1, \dots, l\}$, then $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ has a 0 on its diagonal and is lower block triangular. $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is therefore trivially rank deficient. Let $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{w_1, w_2, \dots, w_l}$ be a submatrix of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$. Since $w_t \leq i_{t+c}$,

$$j_t > \left\lceil \frac{w_t}{n-k} \right\rceil k$$

holds as well. As before, it follows that $(\mathcal{T}_j)_{j_1, j_2, \dots, j_l}^{w_1, w_2, \dots, w_l}$ is trivially rank deficient. Consequently, all $\binom{l+c}{l}$ $l \times l$ submatrices of $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ are trivially rank deficient, so that $(\mathcal{T}_j)_{\bar{j}}^{\bar{i}}$ is trivially rank deficient. \square

We next characterize the MDP and sMDS properties in terms of trivial rank deficiency. We denote by r the difference of the generalized Singleton bound and the upper bound for the L th column distance:

$$r := (n - k) \left(\left\lfloor \frac{\delta}{k} \right\rfloor + 1 \right) + \delta + 1 - \left(\left\lfloor \frac{\delta}{k} \right\rfloor + \left\lfloor \frac{\delta}{n - k} \right\rfloor + 1 \right) (n - k) - 1 = \delta - \left\lfloor \frac{\delta}{n - k} \right\rfloor (n - k).$$

Note that r is the remainder of δ on division by $n - k$. If $r = 0$, then $L = M$, and a code is MDP if and only if it is sMDS. This case was considered in [8] and [11], so we will assume that $r \in \{1, \dots, n - k - 1\}$. In this situation, $M = L + 1$.

Theorem 3.4 *Let $(A, B, C, D) \in S_{k,n}^\delta$ and \mathcal{C} be the (n, k, δ) -code represented by (A, B, C, D) . Then, \mathcal{C} is an MDP code if and only if every square submatrix of \mathcal{T}_L that is not trivially rank deficient has full rank. \mathcal{C} is an sMDS code if and only if, for every integer l satisfying $1 \leq l \leq \min\{(M + 1)(n - k) - (n - k - r), (M + 1)k\}$, every submatrix $(\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+n-k-r}}$ that is not trivially rank deficient has full rank.*

PROOF: The first statement is [11, Corollary 2.5]. We consider next the second statement. \Leftarrow : Suppose that

$$v := [y_0^T \ y_1^T \ \dots \ y_M^T \mid u_0^T \ u_1^T \ \dots \ u_M^T]^T$$

is formed from the first $M + 1$ vectors of a finite-weight sequence for (A, B, C, D) with $u_0 \neq 0$, so that the matrix equation

$$\left[\begin{array}{c|cccccc} & D & 0 & \dots & \dots & 0 \\ & CB & D & \ddots & & \vdots \\ -I_{(M+1)(n-k)} & CAB & CB & \ddots & \ddots & \vdots \\ & \vdots & \vdots & \ddots & \ddots & 0 \\ & CA^{M-1}B & CA^{M-2}B & \dots & CB & D \end{array} \right] v = 0_{(M+1)n}$$

is satisfied, and denote the weight of

$$u := [u_0^T \ u_1^T \ \dots \ u_M^T]^T$$

by w . For $t \in \{1, \dots, w\}$, let j_t denote the position of the t th nonzero entry in u , and let \bar{u} denote the vector obtained from u by deleting all of the zero entries. Suppose that $(\mathcal{T}_M)_{j_1, j_2, \dots, j_w}^{\bar{i}_1, \bar{i}_2, \dots, \bar{i}_{w+n-k-r}}$ is a submatrix of \mathcal{T}_M such that

$$(\mathcal{T}_M)_{j_1, j_2, \dots, j_w}^{\bar{i}_1, \bar{i}_2, \dots, \bar{i}_{w+n-k-r}} \bar{u} = 0. \quad (3.3)$$

Since $u_0 \neq 0$, we have that

$$j_1 \leq k \leq \left\lceil \frac{i_1}{n - k} \right\rceil k \leq \left\lceil \frac{i_1 + n - k - r}{n - k} \right\rceil k.$$

By Lemma 3.3, $(\mathcal{T}_M)_{j_1}^{i_1, i_2, \dots, i_{1+n-k-r}}$ is not trivially rank deficient, so that it has full rank. This means that at least one of its entries is nonzero, and, since (3.3) holds, it follows that

$$j_2 \leq \left\lceil \frac{i_{1+n-k-r}}{n-k} \right\rceil k \leq \left\lceil \frac{i_{2+n-k-r}}{n-k} \right\rceil k.$$

By Lemma 3.3, $(\mathcal{T}_M)_{j_1, j_2}^{i_1, i_2, \dots, i_{2+n-k-r}}$ is not trivially rank deficient, so that it has full rank. Consequently, at least one 2×2 minor of $(\mathcal{T}_M)_{j_1, j_2}^{i_1, i_2, \dots, i_{2+n-k-r}}$ is nonzero. Again, since (3.3) holds, it follows that

$$j_3 \leq \left\lceil \frac{i_{2+n-k-r}}{n-k} \right\rceil k \leq \left\lceil \frac{i_{3+n-k-r}}{n-k} \right\rceil k.$$

Continuing, we see that, for $t \in \{1, \dots, w\}$,

$$j_t \leq \left\lceil \frac{i_{t+n-k-r}}{n-k} \right\rceil k.$$

A final application of Lemma 3.3 gives that $(\mathcal{T}_M)_{\tilde{j}}^{\tilde{i}}$ is not trivially rank deficient. By hypothesis, it must have full rank, which contradicts the hypothesis that $(\mathcal{T}_M)_{\tilde{j}}^{\tilde{i}} \bar{u} = 0$. Consequently, at most $w + n - k - r - 1$ rows of $(\mathcal{T}_M)_{\tilde{j}}^{\tilde{i}}$ are in the left kernel of \bar{u} . It follows that v has weight at least $w + ((M+1)(n-k) - (w + n - k - r - 1)) = M(n-k) + 1 + r = (L+1)(n-k) + 1 + r$, which means that $d_M^c(\mathcal{C}) \geq (L+1)(n-k) + 1 + r$. Recalling Proposition 2.6 and the definition of r , we conclude that $d_M^c(\mathcal{C}) = (L+1)(n-k) + 1 + r$, so that \mathcal{C} is sMDS.

\implies : We prove the contrapositive. Suppose that the matrix (3.2) has a $(w + n - k - r) \times w$ submatrix $(\mathcal{T}_M)_{\tilde{j}}^{\tilde{i}} := (\mathcal{T}_M)_{j_1, j_2, \dots, j_w}^{i_1, i_2, \dots, i_{w+n-k-r}}$ that is not trivially rank deficient and that has less than full rank. There then exists a vector $(\mathcal{T}_M)_{\tilde{j}}^{\tilde{i}} \bar{u} \neq 0$ of weight $w' \leq w$ such that $\bar{u} = 0$. Let

$$u := [u_0^T \quad u_1^T \quad \cdots \quad u_M^T]^T \in \mathbb{F}^{Mk}$$

be the vector in which the j_t th entry is the t th entry of \bar{u} and all other entries are zero; because of the block Toeplitz structure of \mathcal{T}_M , we may assume that $u_0 \neq 0$. Using (2.1), we form the vector

$$v := [y_0^T \quad y_1^T \quad \cdots \quad y_M^T \mid u_0^T \quad u_1^T \quad \cdots \quad u_M^T]^T.$$

Because $[-I_{(M+1)(n-k)} \mid \mathcal{T}_M]v = 0$, the weight of v is at most $w' + (M+1)(n-k) - (w - n - k - r) \leq (M+1)(n-k) - (n-k-r) = (L+1)(n-k) + r < (L+1)(n-k) + r + 1$. We may choose additional information vectors u_{M+1}, \dots, u_d so that $x_d = 0$ (see, for example, [2]); in other words, it is possible to extend v into a finite-weight sequence for (A, B, C, D) with weight less than the generalized Singleton bound. Thus, $d_M^c(\mathcal{C}) < (L+1)(n-k) + r + 1$, so that \mathcal{C} is not an sMDS code. \square

Theorem 3.4 gives polynomial conditions on the entries of a realization $(A, B, C, D) \in S_{k,n}^\delta$ that may be used to determine whether or not the convolutional code these matrices represent has the MDP and sMDS properties. In the next section, we use this information to show that we can find a realization $(A, B, C, D) \in S_{k,n}^\delta$ representing an (n, k, δ) -code that has the MDP and sMDS properties.

4 Proof of the Existence of sMDS Convolutional Codes

Recall that we defined the block matrices making up \mathcal{T}_M in terms of matrices (A, B, C, D) . In this section, we will work in the opposite direction. Let $\{F_0, F_1, \dots, F_j\}$ be a sequence of matrices in $\mathbb{K}^{(n-k) \times k}$. Slightly abusing notation, we set

$$\mathcal{T}_j := \begin{bmatrix} F_0 & 0 & \cdots & 0 \\ F_1 & F_0 & \ddots & \vdots \\ \vdots & \vdots & \ddots & 0 \\ F_j & F_{j-1} & \cdots & F_0 \end{bmatrix}. \quad (4.4)$$

The plan is to show the existence of a sequence $\{F_0, F_1, \dots, F_M\}$ of matrices in $\mathbb{K}^{(n-k) \times k}$ such that

1. \mathcal{T}_M has the property that, for all integers l with $1 \leq l \leq \min\{(M+1)(n-k) - (n-k-r), (M+1)k\}$, every submatrix $(\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_l + n - k - r}$ that is not trivially rank deficient has full rank;
2. there is a minimal partial realization $(A, B, C, D) \in S_{k,n}^\delta$ of this matrix sequence (this means that $D = F_0$ and $CA^{i-1}B = F_i$ for $1 \leq i \leq M$).

The matrices (A, B, C, D) will represent the desired code. We begin with the following lemma.

Lemma 4.1 *There exists a sequence $\{F_0, F_1, \dots, F_L\}$ of matrices in $\mathbb{K}^{(n-k) \times k}$ such that every square submatrix of \mathcal{T}_L that is not trivially rank deficient has full rank.*

PROOF: Note that we may think of such a matrix sequence $\{F_0, F_1, \dots, F_L\}$ as a point in $\mathbb{K}^{(L+1)(n-k)k}$. To begin, think of the matrix (4.4) with $j = L$ as being defined over the polynomial ring $\mathbb{K}[x_1, x_2, \dots, x_{(L+1)(n-k)k}]$, the entries corresponding with the indeterminates of this ring in a manner analogous to that in the previous section. When viewed in this way, the determinant of a square submatrix of \mathcal{T}_L that is not trivially rank deficient is a nonzero polynomial in $\mathbb{K}[x_1, x_2, \dots, x_{(L+1)(n-k)k}]$, and there is a finite number of such polynomials. The solution sets of these polynomials make up a proper algebraic subset of $\mathbb{K}^{(L+1)(n-k)k}$, the complement of which is a nonempty Zariski open set. Choose $\{F_0, \dots, F_L\}$ to be a point in this open set. \square

To determine the degree of a minimal partial realization of a matrix sequence $\{F_0, F_1, \dots, F_M\}$, we consider the matrices

$$\mathcal{F}_{x,y} := \begin{bmatrix} F_1 & F_2 & \cdots & F_y \\ F_2 & F_3 & \cdots & F_{y+1} \\ \vdots & \vdots & & \vdots \\ F_x & F_{x+1} & \cdots & F_{x+y-1} \end{bmatrix}.$$

In [22, Lemma 3], it is shown that the degree of a minimal partial realization of $\{F_0, F_1, \dots, F_M\}$ is given by the expression

$$\sum_{x=1}^M \text{rank } \mathcal{F}_{x, M+1-x} - \sum_{x=1}^{M-1} \text{rank } \mathcal{F}_{x, M-x}. \quad (4.5)$$

The next results show that, starting with a matrix sequence $\{F_0, F_1, \dots, F_L\}$ as described in Lemma 4.1, we can find a matrix F_M so that the expression (4.5) evaluates to δ .

Lemma 4.2 *Let $\{F_0, \dots, F_M\}$ be a sequence of matrices in $\mathbb{K}^{(n-k) \times k}$ such that every square submatrix of \mathcal{T}_L that is not trivially rank deficient has full rank. Then,*

1. For $x \in \{1, \dots, M-1\}$, $\text{rank } \mathcal{F}_{x, M-x} = \min\{x(n-k), (M-x)k\}$.
2. If $\text{rank } \mathcal{F}_{x, M+1-x} < \min\{x(n-k), (M+1-x)k\}$, then $x = \lceil M \frac{k}{n} \rceil$. If $x \in \{1, \dots, M\} \setminus \{\lceil M \frac{k}{n} \rceil\}$, then $\text{rank } \mathcal{F}_{x, M+1-x} = \min\{x(n-k), (M+1-x)k\}$.
3. Set $\bar{x} := \lceil M \frac{k}{n} \rceil$. The expression (4.5) reduces to $\text{rank } \mathcal{F}_{\bar{x}, M+1-\bar{x}}$.

PROOF: To verify the first claim, observe that $\mathcal{F}_{x, M-x}$ differs by a column permutation from a submatrix of \mathcal{T}_L that has full rank.

For the second claim, suppose first that $x(n-k) \leq (M+1-x)k$. The hypothesis is then that $\text{rank } \mathcal{F}_{x, M+1-x} < x(n-k)$. If $x < M$, it follows from 1 that $\text{rank } \mathcal{F}_{x, M-x} = \min\{x(n-k), (M-x)k\}$, which means that $x(n-k) > (M-x)k$. Together, this gives

$$(M-x)k < x(n-k) \leq (M+1-x)k$$

(note that the first inequality also holds if $x = M$). This can be rewritten as

$$M \frac{k}{n} < x \leq (M+1) \frac{k}{n}.$$

If we suppose instead that $(M+1-x)k \leq x(n-k)$, similar reasoning leads to

$$(M+1) \frac{k}{n} \leq x < M \frac{k}{n} + 1.$$

In all, we have

$$M \frac{k}{n} < x < M \frac{k}{n} + 1.$$

Since x is an integer, $x = \lceil M \frac{k}{n} \rceil$. The second statement follows immediately.

The third claim follows directly from the first two, since $x < \bar{x} \implies x(n-k) < (M-x)k$ and $x > \bar{x} \implies x(n-k) > (M+1-x)k$. \square

Theorem 4.3 *Let $\{F_0, \dots, F_L\}$ be a sequence of matrices in $\mathbb{K}^{(n-k) \times k}$ such that every square submatrix of \mathcal{T}_L that is not trivially rank deficient has full rank. Then, one can find a matrix $F_M \in \mathbb{K}^{(n-k) \times k}$ such that*

1. the matrix

$$\mathcal{F}_{\bar{x}, M+1-\bar{x}} = \begin{bmatrix} F_1 & F_2 & \cdots & F_{M+1-\bar{x}} \\ F_2 & F_3 & \cdots & F_{M+2-\bar{x}} \\ \vdots & \vdots & & \vdots \\ F_{\bar{x}} & F_{\bar{x}+1} & \cdots & F_M \end{bmatrix}$$

has rank δ .

2. the matrix \mathcal{T}_M has the property that, for every integer l with $1 \leq l \leq \min\{(M+1)(n-k) - (n-k-r), (M+1)k\}$, every submatrix $(\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+n-k-r}}$ that is not trivially rank deficient has full rank.

PROOF: We may write

$$\delta = \left\lfloor \frac{\delta}{n-k} \right\rfloor (n-k) + r = \left\lfloor \frac{\delta}{k} \right\rfloor k + r',$$

where $1 \leq r < n-k$ and $0 \leq r' < k$. Since

$$M = L + 1 = \left\lfloor \frac{\delta}{n-k} \right\rfloor + \left\lfloor \frac{\delta}{k} \right\rfloor + 1,$$

we see that

$$\begin{aligned} \frac{Mk}{n} &= \left\lfloor \frac{\delta}{n-k} \right\rfloor \frac{k}{n} + \left\lfloor \frac{\delta}{k} \right\rfloor \frac{k}{n} + \frac{k}{n} = \left\lfloor \frac{\delta}{n-k} \right\rfloor - \left\lfloor \frac{\delta}{n-k} \right\rfloor \frac{n-k}{n} + \left\lfloor \frac{\delta}{k} \right\rfloor \frac{k}{n} + \frac{k}{n} \\ &= \left\lfloor \frac{\delta}{n-k} \right\rfloor - \frac{\delta-r}{n} + \frac{\delta-r'}{n} + \frac{k}{n} = \left\lfloor \frac{\delta}{n-k} \right\rfloor + \frac{k-r'+r}{n}. \end{aligned}$$

Since $1 < k-r'+r < n$, we have $\left\lfloor \frac{\delta}{n-k} \right\rfloor = \bar{x} - 1$, so that $\delta = (\bar{x} - 1)(n-k) + r$ and

$$\frac{Mk}{n} = \bar{x} - 1 + \frac{k-r'+r}{n}.$$

Multiplying both sides by n and subtracting $\bar{x}k$ from both sides, we get

$$(M - \bar{x})k = (\bar{x} - 1)(n-k) + r - r' = \delta - r',$$

from which it follows that $(M - \bar{x})k \leq \delta$. Since $r' < k$, it also follows that $\delta < (M+1 - \bar{x})k$.

We next want to see that we may find a matrix F_M as described in the statement of the theorem. We first consider the top r rows of F_M . Using the same reasoning as in the proof of Lemma 4.1, we may find elements of \mathbb{K} to form these top r rows so that all square submatrices of the top $M(n-k) + r$ rows of \mathcal{T}_M that are not trivially rank deficient have full rank. In particular, all square submatrices of the top δ rows of $\mathcal{F}_{\bar{x}, M+1-\bar{x}}$ have full rank. Denote the $r \times k$ matrix consisting of these r rows by F'_M . Since $\delta < (M+1 - \bar{x})k$, $\text{rank } \mathcal{F}_{\bar{x}, M+1-\bar{x}} \geq \delta$ will hold regardless of how the entries of the bottom $n-k-r$ rows of F_M are chosen. To find entries for these rows so that $\text{rank } \mathcal{F}_{\bar{x}, M+1-\bar{x}} = \delta$, consider the top δ rows of $\mathcal{F}_{\bar{x}, M-\bar{x}}$. Since $\delta \geq (M - \bar{x})k$, we may choose $M - \bar{x}$ of these δ rows to form an

$(M - \bar{x})k \times (M - \bar{x})k$ submatrix that necessarily has full rank. This means that the last $n - k - r$ rows of $\mathcal{F}_{\bar{x}, M - \bar{x}}$ may each be expressed as a linear combination of the rows of our chosen submatrix. Consequently, we may take the last $n - k - r$ rows of F_M to be the corresponding linear combinations of the rows of

$$\begin{bmatrix} F_{M+1-\bar{x}} \\ F_{M+2-\bar{x}} \\ \vdots \\ F'_M \end{bmatrix}$$

extending the rows of our chosen submatrix. With this, we have found an F_M so that $\text{rank } \mathcal{F}_{\bar{x}, M+1-\bar{x}} = \delta$.

Suppose finally that $(\mathcal{T}_M)_{j_j}^{\bar{i}} := (\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_{l+n-k-r}}$ is a submatrix of \mathcal{T}_M that is not trivially rank deficient and does not have full rank. Then, in particular, $(\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_l}$ does not have full rank. Since $(\mathcal{T}_M)_{j_1, j_2, \dots, j_l}^{i_1, i_2, \dots, i_l}$ is contained in the top $M(n - k) + r$ rows of \mathcal{T}_M , it must be trivially rank deficient. By Lemma 3.3, there exists a smallest integer $t \in \{1, \dots, l\}$ such that

$$j_t > \left\lceil \frac{i_t}{n - k} \right\rceil k.$$

Since $(\mathcal{T}_M)_{j_j}^{\bar{i}}$ is not trivially rank deficient, it also follows from Lemma 3.3 that

$$j_\tau \leq \left\lceil \frac{i_\tau + n - k - r}{n - k} \right\rceil k \quad \forall \tau \in \{1, \dots, l\},$$

so that $(\mathcal{T}_M)_{j_j}^{\bar{i}} := (\mathcal{T}_M)_{j_t, j_{t+1}, \dots, j_l}^{i_t + n - k - r, i_{t+1} + n - k - r, \dots, i_{l+n-k-r}}$ is not trivially rank deficient. Since $j_t > k$, $(\mathcal{T}_M)_{j_j}^{\bar{i}}$ must be a submatrix of \mathcal{T}_L . Thus, $(\mathcal{T}_M)_{j_j}^{\bar{i}}$ has full rank. Recalling how t was chosen, we conclude that $(\mathcal{T}_M)_{j_j}^{\bar{i}}$ has full rank. This is a contradiction. We conclude that, if a submatrix $(\mathcal{T}_M)_{j_j}^{\bar{i}}$ is not trivially rank deficient, then it has full rank. \square

Corollary 4.4 *Let $\{F_0, \dots, F_M\}$ be as in Theorem 4.3. Then, the expression (4.5) evaluates to δ .*

We are now ready to finish our existence proof.

Theorem 4.5 *An MDP and sMDS (n, k, δ) -code exists over a sufficiently large finite field.*

PROOF: By Lemma 4.1 and Theorem 4.3, we can find a sequence $\{F_0, \dots, F_M\}$ of matrices in $\mathbb{K}^{(n-k) \times k}$ such that

1. every square submatrix of \mathcal{T}_L that is not trivially rank deficient has full rank
2. every $(l + n - k - r) \times l$ submatrix of \mathcal{T}_M that is not trivially rank deficient has full rank
3. the minimum possible degree of a partial realization of $\{F_0, \dots, F_M\}$ is δ .

Since there are a finite number of entries in the matrices $\{F_0, \dots, F_M\}$, the entries all belong to some finite subfield \mathbb{F} of \mathbb{K} . From [22, Theorem 1], there is a minimal realization $(A, B, C, D) \in S_{k,n}^\delta$ of the sequence $\{F_0, \dots, F_M\}$ with entries in \mathbb{F} . By Theorem 3.4, the (n, k, δ) -code represented by (A, B, C, D) is both MDP and sMDS. \square

With this, we have shown that the conjecture in [8] that codes having both the MDP and sMDS properties exist for all parameters (n, k, δ) is correct. It is still an open problem as to how one may construct matrices of the form (3.4) leading to codes with these properties, and this must be left for future research.

Acknowledgements: The author wishes to thank Joachim Rosenthal, Heide Gluesing-Luerssen, and José Ignacio Iglesias Curto for helpful comments during the preparation of this paper. He also wishes to thank the anonymous referees for their careful readings and detailed comments.

References

- [1] A.C. Antoulas. On recursiveness and related topics in linear systems. *IEEE Trans. Automat. Contr.*, AC-31(12):1121–1135, 1986.
- [2] P.J. Antsaklis. *Linear Systems*. Birkhauser, Boston, 2006.
- [3] D.F. Delchamps. *State Space and Input-Output Linear Systems*. Springer-Verlag, New York, 1988.
- [4] P.L. Falb. *Methods of Algebraic Geometry in Control Theory: Part I*. Birkhäuser, Boston, 1990.
- [5] P.L. Falb. *Methods of Algebraic Geometry in Control Theory: Part II*. Birkhäuser, Boston, 1999.
- [6] M. Fliess. On the structure of linear recurrent error-control codes. *ESAIM Control Optim. Calc. Var.*, 8:703–713 (electronic), 2002. A tribute to J. L. Lions.
- [7] G.D. Forney, Jr. Minimal bases of rational vector spaces, with applications to multi-variable linear systems. *SIAM J. Control*, 13(3):493-520, 1975.
- [8] H. Gluesing-Luerssen, J. Rosenthal, and R. Smarandache. Strongly MDS convolutional codes. *IEEE Trans. Inform. Theory*, 52(2):584-598, 2006.
- [9] H. Gluesing-Luerssen and W. Schmale. On cyclic convolutional codes. *Acta Appl. Math.*, 82:183-237, 2004.
- [10] C. N. Hadjicostis. Non-concurrent error detection and correction in fault-tolerant linear finite-state machines. *IEEE Trans. Automat. Contr.*, AC-48(12):2133-2140, 2003.

- [11] R. Hutchinson, J. Rosenthal, R. Smarandache. Maximum Distance Profile Convolutional Codes. *em Systems and Control Letters*, 54(1):53-63, 2004.
- [12] R. Johannesson and K. Zigangirov. Distances and distance bounds for convolutional codes – an overview. In *Topics in Coding Theory. In honour of L. H. Zetterberg.*, Lecture Notes in Control and Information Sciences # 128, pages 109–136. Springer Verlag, 1989.
- [13] R. Johannesson and K. Sh. Zigangirov. *Fundamentals of Convolutional Coding*. IEEE Press, New York, 1999.
- [14] B. Langfeld, “Minimal Cyclic Convolutional Codes,” Diploma thesis, University of Oldenburg, 2003.
- [15] V. Lomadze. Finite-dimensional time-invariant linear dynamical systems: Algebraic theory. *Acta Appl. Math.*, 19:149–201, 1990.
- [16] R.J. McEliece. The algebraic theory of convolutional codes. In *Handbook of Coding Theory*, volume 1, pages 1065-1138. Elsevier, Amsterdam, 1998.
- [17] J. Rosenthal, J. M. Schumacher, and E. V. York. On behaviors and convolutional codes. *IEEE Trans. Inform. Theory*, 42(6, part 1):1881–1891, 1996.
- [18] J. Rosenthal and R. Smarandache. Maximum distance separable convolutional codes. *Appl. Algebra Engrg. Comm. Comput.*, 10(1):15–32, 1999.
- [19] J. Rosenthal and E. V. York. BCH convolutional codes. *IEEE Trans. Inform. Theory*, 45(6):1833–1844, 1999.
- [20] J. Rosenthal. Connections between linear systems and convolutional codes. In B. Marcus and J. Rosenthal, editors, *Codes, Systems and Graphical Models*, IMA Vol 123, pages 39–66, Springer Verlag, 2001.
- [21] R. Smarandache, H. Gluesing-Luerssen, and J. Rosenthal. Constructions for MDS-convolutional codes. *IEEE Trans. Inform. Theory*, 47(5):2045–2049, 2001.
- [22] A. J. Tether. Construction of minimal linear state-variable models from finite input-output data. *IEEE Transactions on Automatic Control*, 15:427–436, 1970.