Error Performance of Multidimensional Lattice Constellations - Part II: Evaluation over Fading Channels

Koralia N. Pappi, *Student Member, IEEE*, Nestor D. Chatzidiamantis, *Student Member, IEEE*, Theodore N. Chronis, *Student Member, IEEE*, and George K. Karagiannidis, *Senior Member, IEEE*

Abstract

This is the second part of a two-part series of papers, where the error performance of multidimensional lattice constellations with signal space diversity (SSD) is investigated. In Part I, following a novel combinatorial geometrical approach which is based on parallelotope geometry, we have presented an exact analytical expression and two closed-form bounds for the symbol error probability (SEP) in Additive White Gaussian Noise (AWGN). In the present Part II, we extend the analysis and present a novel analytical expression for the Frame Error Probability (FEP) of multidimensional lattice constellations over Nakagami-*m* fading channels. As the FEP of infinite lattices is lower bounded by the Sphere Lower Bound (SLB), we propose the Sphere Upper Bound (SUB) for block fading channels. Furthermore, two novel bounds for the FEP of multidimensional lattice constellations over block fading channels, named Multiple Sphere Lower Bound (MSLB) and Multiple Sphere Upper Bound (MSUB), are presented. The expressions for the SLB and SUB are given in closed form, while the corresponding ones for MSLB and MSUB are given in closed form for unitary block length. Numerical and simulation results illustrate the tightness of the proposed bounds and demonstrate that they can be efficiently used to set the performance limits on the FEP of lattice constellations of arbitrary structure, dimension and rank.

Index Terms

Multidimensional lattice constellations, infinite lattices, signal space diversity (SSD), Nakagami-*m* block fading, sphere bounds, symbol error probability (SEP), frame error probability (FEP).

The authors are with the Electrical and Computer Engineering Department, Aristotle University of Thessaloniki, GR-54124 Thessaloniki, Greece (e-mails: {kpappi, nestoras, tchronis, geokarag}@auth.gr).

I. INTRODUCTION

The performance evaluation of multidimensional signal sets has attracted significant attention due to the signal space diversity (SSD) that these constellations present [2] and the fact that they can be efficiently used to combat the signal degradation caused by fading. The design of such constellations has been extensively studied in [3]–[6], but since the analytical computation of the voronoi cells of multidimensional constellations is difficult [7], their error performance has been evaluated only through approximations and bounds [8]–[10], while for special cases, some exact but complicated analytical expressions were derived [11].

In Part I [1] of this two-part series of papers, based on parallelotope geometry we introduced a novel combinatorial geometrical approach for the evaluation of the error performance of multidimensional lattice constellations in Additive White Gaussian Noise (AWGN). Especially, we proposed an exact analytical expression for the Symbol Error Probability (SEP) of these signal sets and two novel closed-form bounds, namely the Multiple Sphere Lower Bound (MSLB) and the Multiple Sphere Upper Bound (MSUB). With the introduction of the MSLB in part I, the concept of the Sphere Lower Bound (SLB) was extended to the case of finite signal sets. The SLB dates back to Shannon's work [12] and although it has been thoroughly investigated in the literature [7], [13]–[15], it is not generally a reliable lower bound for the important practical cases of finite lattice constellations. Moreover, a similar upper bound, the Sphere Upper Bound (SUB) has been investigated in [7] for AWGN channels.

A. Contribution

In the present Part II, we study the error performance of multidimensional infinite lattices and lattice constellations in Nakagami-m block fading channels. Specifically, for infinite lattices:

- We propose a novel expression for the SUB which is suitable for the analysis in fading channels while it upper bounds the Frame Error Probability (FEP).
- We present novel closed-form expressions for the well known SLB and the proposed SUB in Nakagami-*m* block fading channels.

For multidimensional lattice constellations, based on the proposed expressions for the exact SEP, the MSLB and MSUB in AWGN given in Part I [1]:

- We present a novel analytical expression for the Frame Error Probability (FEP) of finite lattice constellations in the presence of Nakagami-*m* block fading.
- Starting from this expression we propose alternative formulae for the MSLB and the MSUB which are suitable for the performance analysis in fading channels and bound the FEP.

• We present closed-form expressions for the MSLB and MSUB in Nakagami-*m* block fading channels for the case of unitary block length.

B. Structure

The remainder of the paper is organized as follows. In Section II, the channel model and the characteristics of faded lattices are presented. Section III investigates the exact FEP of infinite lattices and lattice constellations, while the SLB, MSLB, SUB and MSUB for block fading are presented and their closed-form expressions are proposed. Section IV illustrates the accuracy and tightness of the proposed bounds via extensive numerical and simulation results, whereas conclusions are discussed in Section V.

C. Notations

Here, we revisit some symbols and terms defined in Part I [1] and also used in Part II:

- Λ denotes an infinite lattice and Λ' a finite lattice constellation, carved from a lattice Λ .
- *N* denotes the dimension of a lattice or lattice constellation, while *K* is the rank of a multidimensional lattice constellation, that is the number of symbols along the direction of each base vector.
- M denotes a generator matrix of a lattice Λ or Λ' , where $\mathbf{M} = [\mathbf{v}_1 \ \mathbf{v}_2...\mathbf{v}_N]$, $\mathbf{M} \in \mathbb{R}^{N \times N}$ and $|\det(\mathbf{M})| = 1$. Vectors \mathbf{v}_i , i = 1, 2, ..., N, are the base vectors of the lattice.
- S_N denotes the set of the base vectors of the N-dimensional lattice and S_{k,p} is a subset of k out of N base vectors, with p an index enumerating the different possible subsets for each k. For specific k, the index is p = 1,..., {N k}.
- $\mathcal{V}_{\mathcal{S}_{k,p}}$ denotes the voronoi cell of the sublattice, defined by the vector subset $\mathcal{S}_{k,p}$.
- $\operatorname{vol}(\cdot)$ is the volume of a k-dimensional geometrical region. Note that $\operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}) = |\det(\mathbf{M})| = 1$.
- d_{min} is the minimum distance between two points in an infinite lattice or a in finite lattice constellation.

II. SYSTEM MODEL

A. Channel Model

Let us consider a flat fading channel whose discrete time received vector is given by

$$\mathbf{y}_l = \mathbf{H}\mathbf{x}_l + \mathbf{z}_l, \quad l = 1, \dots, L, \tag{1}$$

where $\mathbf{y}_l \in \mathbb{R}^N$ is the *N*-dimensional real received signal vector, $\mathbf{x}_l \in \mathbb{R}^N$ is the *N*-dimensional real transmitted signal vector, $\mathbf{H} = \text{diag}(\mathbf{h}) \in \mathbb{R}^{N \times N}$ is the flat fading diagonal matrix with $\mathbf{h} = (h_1, ..., h_N) \in$

 \mathbb{R}^N , and $\mathbf{z}_l \in \mathbb{R}^N$ is the Additive White Gaussian Noise (AWGN) vector whose samples are zero-mean Gaussian independent random variables with variance σ^2 . Furthermore, *L* denotes the number of *N*-dimensional modulation symbols that consist a frame.

The fading matrix \mathbf{H} is assumed to be constant during one frame and changes independently from frame to frame, i.e., block fading channel with N blocks is considered. Thus, for a given channel realization, the channel transition probabilities are given by

$$p(\mathbf{y}|\mathbf{x},\mathbf{H}) = \left(2\pi\sigma^2\right)^{-\frac{N}{2}} \exp\left(-\frac{1}{2\sigma^2} \|\mathbf{y} - \mathbf{H}\mathbf{x}\|^2\right).$$
(2)

Moreover, it is assumed that the real fading coefficients, h_i for i = 1, ..., N, follow Nakagami-*m* distribution [16], with probability density function (pdf) given by

$$p_{h_i}(x) = \frac{2m^m x^{2m-1}}{\Gamma(m)} \exp(-mx^2),$$
(3)

while the coefficients, $\gamma_i = h_i^2$, that correspond to the fading power gains and will be used in the following analysis, are Gamma distributed with pdf

$$p_{\gamma_i}(x) = \frac{m^m x^{m-1}}{\Gamma(m)} \exp\left(-mx\right) \tag{4}$$

and cumulative density function (cdf)

$$P_{\gamma_i}(x) = 1 - \frac{\Gamma(m, mx)}{\Gamma(m)}.$$
(5)

In the above equations, $m \ge 0.5$ and $\Gamma(\cdot)$, $\Gamma(\cdot, \cdot)$ denote the Gamma [17, Eq. (8.310)] and the upper incomplete Gamma [17, Eq. (8.310)] functions, respectively. Finally, the signal-to-noise ratio (SNR) is defined as $\rho = \frac{1}{\sigma^2}$.

B. Faded Lattices

As described in Part I, the transmitted signal vectors \mathbf{x} belong to an *N*-dimensional infinite lattice or to an *N*-dimensional finite lattice constellation, defined respectively as [1, Eq. (1)] [1, Eq. (5)]

$$\Lambda = \mathbf{M}\mathbf{z}, \quad \mathbf{z} \in \mathbb{Z}^N, \tag{6}$$

and

$$\Lambda' = \mathbf{M}\mathbf{u}, \quad \mathbf{u} = [u_1 \ u_2 \ \dots \ u_N]^T, \quad u_i \in \{0, 1, \dots, K-1\}.$$
(7)

Similarly, the faded infinite lattice or the lattice constellation is defined as the lattice seen by the receiver which is given by

$$\Lambda_f = \mathbf{H}\mathbf{M}\mathbf{z}, \quad \mathbf{z} \in \mathbb{Z}^N, \tag{8}$$

and

$$\Lambda'_{f} = \mathbf{HMu}, \quad \mathbf{u} = [u_{1} \ u_{2} \ \dots \ u_{N}]^{T}, \quad u_{i} \in \{0, 1, \dots, K-1\}.$$
(9)

Accordingly, for the lattices in (8) and (9) we define the faded generator matrix

$$\mathbf{M}_{\mathbf{f}} = \mathbf{H}\mathbf{M}.\tag{10}$$

All voronoi cells on both infinite and finite lattices are distorted by fading, resulting in stochastic geometry regions. Furthermore, we denote a faded voronoi cell as $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$, while for infinite lattices all voronoi cells are equal to $\mathcal{V}_{\mathcal{S}_N}(\mathbf{H})$.

III. PERFORMANCE EVALUATION OVER FADING CHANNELS

A. Frame Error Probability of Infinite and Finite Lattices

For the reader's convenience, we first present the exact expressions for the Symbol Error Probability (SEP) of infinite lattices and finite lattice constellations in AWGN channels, as provided in Part I [1]. For an infinite lattice Λ , the SEP is given by [1, Eq. (12)]

$$P_{\infty}(\rho) = 1 - \int_{\mathcal{V}_{\mathcal{S}_N}} p(\mathbf{z}) \mathrm{d}\mathbf{z} = 1 - J_N, \tag{11}$$

whereas for a K-PAM lattice constellation it is given by [1, Eq. (17)]

$$P_{K-PAM}(\rho) = 1 - \frac{\sum_{k=0}^{N} (K-1)^k \sum_{p=1}^{\binom{N}{k}} J_{k,p}}{K^N},$$
(12)

with [1, Eq. (16)]

$$J_{k,m} = \int_{\mathcal{V}_{\mathcal{S}_{k,p}}} p(\mathbf{z}) \mathrm{d}\mathbf{z}, \quad 0 < k < n,$$
(13)

and $J_0 = 1$. For k = 0 or k = N, it is p = 1 and p is omitted. Furthermore, the frame error probability (FEP) can be written in terms of the SEP, $P(\rho)$, as

$$P_f(\rho) = 1 - (P_c(\rho))^L = 1 - (1 - P(\rho))^L,$$
(14)

where $P_{c}(\rho)$ is the probability of correct reception.

The expressions in (11) and (12) are also valid for a specific channel realization, i.e. a channel matrix **H**, where the integration is conducted on the faded voronoi cells $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$. Thus, by averaging these expressions over all fading realizations, the average SEP is obtained as

$$P_{\infty}(\rho) = 1 - \mathbb{E}\left[J_N(\mathbf{H})\right],\tag{15}$$

and

$$P_{K-PAM}(\rho) = 1 - \mathbb{E}\left[\frac{\sum_{k=0}^{N} (K-1)^{k} \sum_{p=1}^{\binom{N}{k}} J_{k,p}(\mathbf{H})}{K^{N}}\right],$$
(16)

where

$$J_{k,p}(\mathbf{H}) = \int_{\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})} p(\mathbf{z}) \mathrm{d}\mathbf{z}, \quad 0 < k < n,$$
(17)

with $J_0(\mathbf{H}) = 1$, and $\mathbb{E}[\cdot]$ denotes expectation with respect to the fading distribution. Moreover, based on (15) and (16), the FEP can be calculated by

$$P_{f,\infty}(\rho) = 1 - \mathbb{E}\left[\left(J_N(\mathbf{H}) \right)^L \right], \tag{18}$$

and

$$P_{f,K-PAM}(\rho) = 1 - \mathbb{E}\left[\left(\frac{\sum\limits_{k=0}^{N} (K-1)^k \sum\limits_{p=1}^{\binom{N}{k}} J_{k,p}(\mathbf{H})}{K^N}\right)^L\right],$$
(19)

for an infinite lattice and a finite lattice constellation respectively. To the best of the authors' knowledge, an expression for the FEP of multidimensional lattice constellations as (19) has not been previously given. The above expressions are difficult to evaluate, due to the unknown shape of the faded voronoi cells. Therefore, in the following we provide upper and lower bounds for these expressions.

B. Bounds

Based on the exact expressions (18) and (19), we can now present lower and upper bounds for the performance of an infinite lattice and a finite lattice constellation.

1) Lower Bounds: For the readers' convenience, a well known lower bound for infinite lattices which was investigated in [15], is revisited here. In this bound, the integral on the faded voronoi cell $\mathcal{V}_{S_N}(\mathbf{H})$ is substituted by an N-dimensional sphere of the same volume, $\mathcal{B}_N(\mathbf{H})$, for which holds

$$\operatorname{vol}(\mathcal{B}_N(\mathbf{H})) = \operatorname{vol}(\mathcal{V}_{\mathcal{S}_N}(\mathbf{H})) = |\det(\mathbf{H}\mathbf{M})| = \prod_{i=1}^N h_i.$$
 (20)

However, the volume of each $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$ in (19)cannot be directly substituted in the same manner.

Definition 1: We define the integrals [15]

$$I_{k}(\mathbf{H}) = \int_{\mathcal{B}_{k}(\mathbf{H})} p(\mathbf{z}) d\mathbf{z} = \begin{cases} 1, & k = 0, \\ 1 - \frac{\Gamma\left(\frac{k}{2}, \frac{R_{k}^{2}(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}, & k = 1, 2, \dots, N, \end{cases}$$
(21)

where $\mathcal{B}_k(\mathbf{H})$ is a k-dimensional sphere of radius $R_k(\mathbf{H})$. When k = 0, we define $I_0(\mathbf{H}) = J_0(\mathbf{H}) = 1$. Definition 2: The sphere radius $R_k(\mathbf{H})$ is given by

$$R_{k}^{2}(\mathbf{H}) = \begin{cases} \frac{1}{\pi} \Gamma(\frac{k}{2}+1)^{\frac{2}{k}} W^{2} \max_{i=1,\dots,N} \gamma_{i}, & k = 1, 2, \dots, (N-1) \\ \frac{1}{\pi} \Gamma(\frac{k}{2}+1)^{\frac{2}{k}} \left(\prod_{i=1}^{N} \gamma_{i}\right)^{\frac{1}{N}}, & k = N \end{cases}$$
(22)

where $\max_{i=1,\ldots,N} \gamma_i$ is the maximum between all $\gamma_i = h_i^2$ and

$$W = \frac{\|\mathbf{v_1}\| + \|\mathbf{v_2}\| + \ldots + \|\mathbf{v_N}\|}{N},$$
(23)

with $\|\mathbf{v}_i\|$ being the norm of vector \mathbf{v}_i . Note that for \mathbb{Z}^N lattices, W = 1. For k = N, the sphere \mathcal{B}_N with radius $R_N(\mathbf{H})$ is of the same volume as the voronoi cell $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$, as in [15].

The FEP of an infinite lattice, given in (18), is lower-bounded by the following Sphere Lower Bound (SLB) [15]

$$P_{slb}\left(\rho\right) = 1 - \mathbb{E}\left[\left(I_{N}(\mathbf{H})\right)^{L}\right] = 1 - \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{N}{2}, \frac{R_{N}^{2}(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{N}{2}\right)}\right)^{L}\right].$$
(24)

Theorem 1: The FEP of a multidimensional finite lattice constellation, given in (19), is lower bounded by

$$P_{mslb}(\rho) = 1 - \mathbb{E}\left[\left(\frac{\sum_{k=0}^{N} (K-1)^{k} {N \choose k} I_{k}(\mathbf{H})}{K^{N}}\right)^{L}\right],$$
(25)

where $P_{mslb}(\rho)$ is called Multiple Sphere Lower Bound (MSLB).

Proof: The proof is given in Appendix A.

2) Upper Bounds: The error performance of infinite lattices in AWGN channels is upper bounded by the well-known upper Sphere Upper Bound (SUB), presented in [1]. Similarly, a Multiple Sphere Upper Bound (MSUB) is also proposed in [1] for finite lattice constellations. These bounds are based on the minimum distance between any two points of the lattice.

Definition 3: The integral of a faded voronoi cell $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$ can be substituted by an integral on a k-dimensional sphere $\mathcal{G}_k(\mathbf{H})$, the radius of which is given by

$$\mathcal{R}^{2}(\mathbf{H}) = \left(\frac{d_{min}}{2} \min_{i=1,\dots,N} h_{i}\right)^{2} = \frac{d_{min}^{2}}{4} \min_{i=1,\dots,N} \gamma_{i}.$$
(26)

Definition 4: We define the integrals

$$\mathcal{I}_{k}(\mathbf{H}) = \int_{\mathcal{G}_{k}(\mathbf{H})} p(\mathbf{z}) d\mathbf{z} = \begin{cases} 1, & k = 0, \\ 1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\mathcal{R}^{2}(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}, & k = 1, 2, \dots, N, \end{cases}$$
(27)

where $\mathcal{G}_k(\mathbf{H})$ is a k-dimensional sphere, with radius defined in (26). When k = 0, we define $\mathcal{I}_0(\mathbf{H}) = J_0(\mathbf{H}) = 1$.

Theorem 2: The FEP of an multidimensional infinite lattice is upper bounded by

$$P_{sub}(\rho) = 1 - \mathbb{E}\left[\left(\mathcal{I}_N(\mathbf{H})\right)^L\right] = 1 - \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{N}{2}, \frac{\mathcal{R}^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{N}{2}\right)}\right)^L\right],\tag{28}$$

where $P_{sub}(\rho)$ is called Sphere Upper Bound (SUB).

Proof: The proof is given in Appendix B.

Theorem 3: The FEP of a multidimensional finite lattice constellation is upper bounded by

$$P_{msub}(\rho) = 1 - \mathbb{E}\left[\left(\frac{\sum_{k=0}^{N} (K-1)^{k} {N \choose k} \mathcal{I}_{k}(\mathbf{H})}{K^{N}}\right)^{L}\right],$$
(29)

where $P_{msub}(\rho)$ is called Multiple Sphere Upper Bound (MSUB).

Proof: The proof is given in Appendix C.

C. Closed-Form Analysis

Next, we define three functions which will be used in deriving closed-form expressions for the bounds presented above.

Definition 5: We define the function

$$A(\rho, N; k, L) = \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\pi^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}\right)^L\right], \quad 0 < k \le N,$$
(30)

where \mathcal{R} is given in (26). The above function, when N is even, is given in closed-form by

$$A(\rho, N; k, L) = 1 + \sum_{q=1}^{L} \sum_{\substack{n_0, \dots, n_{\frac{k}{2}-1} = 0\\ n_0 + \dots + n_{\frac{k}{2}-1} = q}}^{q} \frac{L!}{(L-q)!} \frac{(-1)^q}{\prod_{i=0}^{\frac{k}{2}-1} ((i!)^{n_i} \Gamma(n_i+1))} \\ m \frac{\left[\sum_{j=0}^{m-1} jt_j\right] \frac{\left(\frac{d^2_{\min}\rho}{8}\right)^{\left[\sum_{i=0}^{\frac{k}{2}-1} in_i\right]} \Gamma\left(\sum_{j=0}^{m-1} jt_j + m + \sum_{i=0}^{\frac{k}{2}-1} in_i\right)}{\left(\frac{mN + \frac{q\rho d^2_{\min}}{8}\right)^{\left[\sum_{j=0}^{m-1} jt_j + m + \sum_{i=0}^{\frac{k}{2}-1} in_i\right]}} \frac{(31)}{\prod_{j=0}^{m-1} ((j!)^{t_j} \Gamma(t_j+1))}$$

Proof: The proof is given in Appendix D.

Definition 6: We define the function

$$B(\rho, N; k) = \mathbb{E}\left[1 - \frac{\Gamma\left(\frac{k}{2}, \frac{R_k^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}\right], \quad 0 < k < N,$$
(32)

where R_k is given in (22) for $k \neq N$. The above function, when N is even, is given in closed-form by

$$B(\rho, N; k) = 1 - \frac{1}{\Gamma(\frac{k}{2})} \sum_{q=1}^{N} {N \choose q} \Gamma(q+1) \\ \times \left\{ \sum_{\substack{n_0, n_1, \dots, n_{m-1}=0\\n_0+n_1+\dots+n_{m-1}=q}}^{q} (-1) qm \left(\prod_{i=0}^{m-1} \frac{\left(\frac{m^i}{i!}\right)^{n_i}}{\Gamma(n_i+1)} \right) g \left(\sum_{i=0}^{m-1} in_i + 1, \frac{\rho\Gamma(\frac{k}{2}+1)^{\frac{2}{k}}W^2}{2\pi}, qm, \frac{k}{2} \right) \right. \\ \left. + \left. \sum_{\substack{n_0, n_1, \dots, n_{m-1}=0\\n_0+n_1+\dots+n_{m-1}=q}}^{q} \left(\prod_{i=0}^{m-1} \frac{\left(\frac{m^i}{i!}\right)^{n_i}}{\Gamma(n_i+1)} \right) \left(\sum_{i=0}^{m-1} in_i \right) g \left(\sum_{i=0}^{m-1} in_i, \frac{\rho\Gamma(\frac{k}{2}+1)^{\frac{2}{k}}W^2}{2\pi}, qm, \frac{k}{2} \right) \right\}$$

$$(33)$$

with

$$g(\alpha,\beta,p,\nu) = -\frac{\beta^{\nu}\Gamma(\alpha+\nu)}{\nu p^{\alpha+\nu}} {}_{2}F_{1}\left(\nu,\alpha+\nu;\nu+1;-\frac{\beta}{p}\right) + \frac{\Gamma(\nu)\Gamma(\alpha)}{p^{\alpha}}.$$
(34)

In (34), $_2F_1(\alpha,\beta;\gamma;z)$ is the Gauss Hypergeometric function defined by [17, Eq. (9.100),(9.14)].

Proof: The proof is given in Appendix E.

Definition 7: We define the function

$$C(\rho, N; L) = \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{N}{2}, \frac{R_N^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{N}{2}\right)}\right)^L\right],\tag{35}$$

where R_N is given in (22) for k = N. The above function, when N is even, is written in closed-form as

$$C(\rho, N; L) = 1 + \sum_{q=1}^{L} \sum_{\substack{n_0, \dots, n_{\frac{N}{2}-1} = 0\\ n_0 + \dots + n_{\frac{N}{2}-1} = q}}^{q} \frac{L!}{(L-q)!} \frac{\frac{(-1)^q}{(\Gamma(m))^N} \sqrt{N} \left(\frac{N}{q}\right)^{\left[\sum_{i=0}^{\frac{N}{2}-1} in_i\right]}}{(2\pi)^{\frac{N-1}{2}} \prod_{i=0}^{\frac{N}{2}-1} ((i!)^{n_i} \Gamma(n_i+1))} \times G_{N,N}^{N,N} \left[\left(\frac{\frac{2\pi mN}{q\rho}}{\left(\Gamma\left(\frac{N}{2}+1\right)\right)^{\frac{2}{N}}}\right)^N \left| \frac{1-\sum_{i=0}^{\frac{N}{2}-1} in_i}{N}, \dots, \frac{N-\sum_{i=0}^{\frac{N}{2}-1} in_i}{N} \right],$$
(36)

where $G_{p,q}^{m,n}[\cdot]$ is the Meijer's G-function [17, Eq. (9.301)].

Proof: The proof is given in Appendix F.

March 7, 2019

Note that for the important case of N = 2, $C(\rho, N; L)$ can be written in terms of the more familiar Gauss Hypergeometric function as [18]

$$C(\rho,2;L) = 1 + \sum_{q=1}^{L} \frac{(-1)^q L! \left(\Gamma\left(\frac{1}{2}+m\right)\right)^2 \left(\frac{4\pi m}{q\rho}\right)^{2m}}{\sqrt{\pi} \left(L-q\right)! \Gamma\left(q+1\right) \Gamma\left(\frac{1}{2}+2m\right)} \, _2F_1\left(\frac{1}{2}+m,m;\frac{1}{2}+2m;1-\left(\frac{4\pi m}{q\rho}\right)^2\right).$$
(37)

1) Closed-Form for the SLB: The SLB for the FEP of infinite lattices of even dimension N is given in closed-form by

$$P_{slb}(\rho) = 1 - \mathbb{E}\left[\left(I_N(\mathbf{H}) \right)^L \right] = 1 - C(\rho, N; L).$$
(38)

2) Closed-Form for the SUB: The SUB for the FEP of infinite lattices of even dimension N is given in closed-form by

$$P_{sub}(\rho) = 1 - \mathbb{E}\left[\left(\mathcal{I}_N(\mathbf{H})\right)^L\right] = 1 - A(\rho, N; N, L).$$
(39)

3) Closed-Form for the MSLB: The MSLB for the SEP of infinite lattices of even dimension N in fading channels (L = 1) is given in closed-form by

$$P_{mslb}(\rho) = 1 - \mathbb{E}\left[\frac{\sum_{k=0}^{N} (K-1)^{k} {N \choose k} I_{k}(\mathbf{H})}{K^{N}}\right]$$

$$= 1 - \frac{1 + \sum_{k=1}^{N-1} \left[(K-1)^{k} {N \choose k} B(\rho, N; k) \right] + (K-1)^{N} C(\rho, N; 1)}{K^{N}}.$$
(40)

4) Closed-Form for the MSUB: The MSUB for the SEP of infinite lattices of even dimension N in fading channels (L = 1) is given in closed-form by

$$P_{msub}(\rho) = 1 - \mathbb{E}\left[\frac{\sum_{k=0}^{N} (K-1)^{k} {N \choose k} \mathcal{I}_{k}(\mathbf{H})}{K^{N}}\right] = 1 - \frac{1 + \sum_{k=1}^{N} (K-1)^{k} {N \choose k} A(\rho, N; k, 1)}{K^{N}}.$$
 (41)

IV. NUMERICAL & SIMULATION RESULTS

In this section, we investigate the accuracy and tightness of the proposed bounds, which are plotted along with the performance of \mathbb{Z}^N infinite lattices and various finite lattice constellations. The \mathbb{Z}^N lattices are the mostly used in practical applications, since the bit labeling of constellations carved from them is straightforward and Gray coding can be implemented in most cases. In the following, we consider two different types of \mathbb{Z}^N lattices, those which are optimally rotated in terms of full diversity and largest minimum product distance and non rotated lattices which achieve the worst performance due to low diversity gain [5], [6]. Note that the performance of any other rotation of these lattices falls between the performance of these two extreme cases examined. For both types of lattices, the normalization of the generator matrix results in $d_{min} = 1$ and W = 1.

Fig. 1 depicts the accuracy and tightness of the SLB and the SUB along with the frame error probability of \mathbb{Z}^2 infinite lattices, for various values of frame lengths. Specifically, the analytical results obtained from (38) and (39) are plotted in conjunction with simulation results for the frame error probability of the cyclotomic rotation of the \mathbb{Z}^2 infinite lattice and the non rotated lattice, when m = 1 and L = 1, 100. As it is clearly illustrated, the numerical results obtained from the analytical expressions act as lower and upper bounds in all cases examined. In particular, as the known SLB is observed to be very close to the performance of optimally rotated lattices, the SUB seems to be less tight but still very close to the non-rotated case. Moreover, as the frame length L increases, it is evident that the proposed SUB becomes even tighter. Furthermore, one can observe that the diversity order, i.e. the asymptotic slope of the frame error probability, is independent of the frame length, for both the lattices under investigation and their SLB and SUB.

Fig. 2 demonstrates the results for SLB and the SUB along with the simulated performance of the \mathbb{Z}^2 lattices for various values or the *m* parameter. It is evident that both the SLB and the SUB act as tight bounds, irrespective of *m*. Moreover, the effect of the *m*-parameter on the diversity order of both lattices under investigation and their bounds, are clearly depicted.

Fig. 3 illustrates the effect of the dimension order on the frame error probability of the \mathbb{Z}^N infinite lattices and the corresponding SLB and SUB. In particular, we consider m = 1, L = 1 and N = 2, 8. It is obvious that the SLB and SUB act as bounds irrespective of the dimension N, while the SUB is more tight as the dimension decreases. Furthermore, it is also clear that the SUB has similar diversity order with the non rotated lattices and the SLB has almost the same diversity order with the optimally rotated lattices which achieve full diversity.

Whereas the SLB always acts as a bound for an infinite lattice, this is not the case for a finite lattice constellation. This is clearly illustrated in Fig. 4, where the simulated performance of an optimally rotated and a non rotated \mathbb{Z}^2 4-PAM constellation for m = 1 and L = 1 is plotted in conjunction with the MSLB and MSUB, and the corresponding SLB and SUB for the \mathbb{Z}^2 infinite lattice. It is evident that the SLB is not a lower bound for this finite constellation, whereas the MSLB always is, bounding its performance accurately and tightly for all SNR values. Moreover, it is also clear that the MSUB is tighter than the corresponding SUB, approaching the performance of the non rotated constellation more tightly.

Figs. 5, 6 and 7 illustrate the simulated performance of finite \mathbb{Z}^N 4-PAM lattice constellations for

various values of block length L, parameter m and dimension N respectively. These figures correspond to the cases of Figs. 1, 2 and 3 for infinite lattices. One can observe that the behavior of the MSLB and MSUB is extremely similar to that of the SLB and SUB, when compared with the corresponding simulations. The only difference, which is discernible in Fig. 7 when compared to 3, is that the SLB is tighter than the MSLB for low values of SNR when the dimension is high (N = 8) and the rank of the constellation is low (K = 4). This is expected since the approximation of the decision regions of outer points is less accurate, and the outer-to-inner points ratio in this case is high.

The MSLB and MSUB also take into account the rank K of the constellations. In Fig. 8 constellations of higher rank are depicted, that is the optimally rotated and the non-rotated \mathbb{Z}^2 32-PAM. It is again evident that the MSLB is an extremely tight lower bound, regardless of the rank of the constellation. Moreover, the MSUB is also accurate and tight, illustrating that the tightness of the bounds is not noticeably affected by the rank of the constellations.

Finally, in Fig. 9, the performance of a constellation carved from a lattice with different structure is depicted, together with the numerical results for the corresponding MSLB and MSUB. Specifically, the \mathbb{A}^2 4-PAM constellation is illustrated, which is the best known sphere packing lattice in two dimensions [21], with generator matrix

$$M = \begin{bmatrix} \sqrt{\frac{2}{\sqrt{3}}} & \sqrt{\frac{1}{2\sqrt{3}}} \\ 0 & \sqrt{\frac{3}{2\sqrt{3}}} \end{bmatrix}.$$
(42)

The MSLB and MSUB again bound the performance of this lattice constellation carved from the sphere packing lattice. Moreover, the figure suggests that this rotation is not optimal with respect to the diversity again and the maximization of the minimum product distance. This is an important result, not only for this constellation but also for others with random rotation, because the bounds act as indication of the optimality of a designed constellation.

V. CONCLUSIONS

We have studied the error performance of multidimensional lattice constellations in block fading channels. We first presented analytical expressions for the exact FEP of both infinite lattices and finite signal sets carved from lattices, in the presence of Nakagami-*m* block fading. These expressions were then bounded by the well known SLB and the novel SUB proposed for the infinite lattices, as well as by the proposed MSLB and MSUB for lattice constellations of arbitrary structure, rank and dimension. Then, analytical closed form expressions were derived for the SUB and SLB in lattices with even dimensions, whereas the MSLB and MSUB were given in closed form for constellations of even dimensions and for

transmission in fading channels with single-symbol block length. The proposed analytical framework sets the performance limits of such signal sets and it can be an efficient tool for their analysis and design.

APPENDIX A

PROOF OF THEOREM 1

The volume of $\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})$ in (17) is the same as the volume of the corresponding fundamental parallelotope of a faded sublattice, for which holds [1, Eq. (41)]

$$\operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})) \leq \prod_{i:\mathbf{v}_i \in \mathcal{S}_{k,p}} \|\mathbf{H}\mathbf{v}_i\| \leq \prod_{i:\mathbf{v}_i \in \mathcal{S}_{k,p}} \|\mathbf{v}_i\| \max_{j=1,\dots,N} h_j,$$
(43)

where the first equality is true only when the vectors of $S_{k,p}$ distorted by fading are orthogonal. The second equality holds only if all fading coefficients h_j are equal to $\max_{j=1,\dots,N} h_j$. Moreover, the inequalities in (43) imply that the volume of a faded voronoi cell of a sublattice $S_{k,p}$ will always be at most equal to the volume of a rectangular parallelotope, with edges of norms equal to those of the vectors in $S_{k,p}$, multiplied by the largest fading coefficient. Using (43) yields to

$$\sum_{p=1}^{\binom{N}{k}} \operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})) \le \sum_{p=1}^{\binom{N}{k}} \prod_{i:\mathbf{v}_i \in \mathcal{S}_{k,p}} \|\mathbf{v}_i\| \max_{j=1,\dots,N} h_j,$$
(44)

which can be written as

$$\sum_{p=1}^{\binom{N}{k}} \operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})) \le \left(\max_{j=1,\dots,N} h_j\right)^k \sum_{\substack{b_1+b_2+\dots+b_N=k\\b_1,b_2,\dots,b_N\in\{0,1\}}} \|\mathbf{v}_1\|^{b_1} \|\mathbf{v}_2\|^{b_2} \cdots \|\mathbf{v}_N\|^{b_N}.$$
(45)

Using Maclaurin's Inequality [20, p.52], for $a_1, a_2, \ldots, a_N \in \mathbb{R}$ and 0 < k < N,

$$\varrho_N^{\frac{1}{N}} \le \varrho_k^{\frac{1}{k}} \le \varrho_1, \tag{46}$$

where

$$\varrho_k = \frac{\sum\limits_{\substack{b_1+b_2+\ldots+b_N=k\\b_1,b_2,\ldots,b_N \in \{0,1\}}} a_1^{b_1} a_2^{b_2} \cdots a_N^{b_N}}{\binom{N}{k}}.$$
(47)

If we set $a_i = ||\mathbf{v}_i||, i = 1, 2, ..., N$, then $\rho_1 = W$ and from (46) and (47)

$$\sum_{\substack{b_1+b_2+\ldots+b_N=k\\b_1,b_2,\ldots,b_N\in\{0,1\}}} \|\mathbf{v}_1\|^{b_1} \|\mathbf{v}_2\|^{b_2} \cdots \|\mathbf{v}_N\|^{b_N} \le \binom{N}{k} W^k.$$
(48)

From (45) and (48), for 0 < k < N, we have

$$\sum_{p=1}^{\binom{N}{k}} \operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H})) \le \left(\max_{j=1,\dots,N} h_j\right)^k \binom{N}{k} W^k.$$
(49)

For the spheres $\mathcal{B}_{\mathcal{S}_{k,p}}(\mathbf{H})$ with $\operatorname{vol}(\mathcal{B}_{\mathcal{S}_{k,p}}(\mathbf{H})) = \operatorname{vol}(\mathcal{V}_{\mathcal{S}_{k,p}}(\mathbf{H}))$, holds that

$$\sum_{p=1}^{\binom{N}{k}} J_{k,p}(\mathbf{H}) \le \sum_{p=1}^{\binom{N}{k}} \int_{\mathcal{B}_{\mathcal{S}_{k,p}}(\mathbf{H})} p(\mathbf{z}) d\mathbf{z} = \sum_{p=1}^{\binom{N}{k}} \left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{R^2_{\mathcal{S}_{k,p}}(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)} \right),$$
(50)

where $R_{\mathcal{S}_{k,p}}(\mathbf{H})$ is the radius of $\mathcal{B}_{\mathcal{S}_{k,p}}(\mathbf{H})$. From (49), and using that $\operatorname{vol}\left(\mathcal{B}_{\mathcal{S}_{k,p}}(\mathbf{H})\right) = \frac{\pi^{\frac{k}{2}}R_{\mathcal{S}_{k,p}}^{k}(\mathbf{H})}{\Gamma\left(\frac{k}{2}+1\right)}$

$$\sum_{p=1}^{\binom{N}{k}} \frac{\pi^{\frac{k}{2}} R_{\mathcal{S}_{k,p}}^k(\mathbf{H})}{\Gamma\left(\frac{k}{2}+1\right)} \le \left(\max_{j=1,\dots,N} h_j\right)^k \binom{N}{k} W^k.$$
(51)

Furthermore, by taking into account (22) for the case when 0 < k < N,

$$\sum_{m=1}^{\binom{N}{k}} R_{\mathcal{S}_{k,m}}^{k}(\mathbf{H}) \le \binom{N}{k} R_{k}^{k}(\mathbf{H}).$$
(52)

As proved in [1], the function $f(x; a, b) = \Gamma(a, bx^{1/a})$ is convex in $(0, \infty)$, thus from Jensen's Inequality for convex functions [20] holds that

$$\sum_{i=1}^{M} \Gamma\left(a, bx_i^{1/a}\right) \ge M\Gamma\left(a, b\left(\sum_{i=1}^{L} x_i/L\right)^{1/a}\right).$$
(53)

For $a = \frac{k}{2}$, $b = \frac{\rho}{2}$, $M = \binom{N}{k}$ and $x_i = R^k_{\mathcal{S}_{k,p}}$ we get

$$\sum_{p=1}^{\binom{N}{k}} \Gamma\left(\frac{k}{2}, \frac{\rho}{2} R_{\mathcal{S}_{k,p}}^{2}(\mathbf{H})\right) \geq \binom{N}{k} \Gamma\left(\frac{k}{2}, \frac{\rho}{2} \left(\frac{\sum_{m=1}^{\binom{N}{k}} R_{\mathcal{S}_{k,p}}^{k}(\mathbf{H})}{\binom{N}{k}}\right)^{\frac{2}{k}}\right).$$
(54)

From (52) and since $f(x; a, b) = \Gamma(a, bx^{1/a})$ is a monotonically decreasing function with respect to x,

$$\Gamma\left(\frac{k}{2}, \frac{\rho}{2}\left(\frac{\sum\limits_{p=1}^{N} R_{\mathcal{S}_{k,p}}^{k}(\mathbf{H})}{\binom{N}{k}}\right)^{\frac{2}{k}}\right) \ge \Gamma\left(\frac{k}{2}, \frac{\rho}{2}R_{k}^{2}(\mathbf{H})\right).$$
(55)

March 7, 2019

Using (54) and (55), for 0 < k < N

$$\sum_{p=1}^{\binom{N}{k}} \Gamma\left(\frac{k}{2}, \frac{\rho}{2} R_{\mathcal{S}_{k,p}}^{2}(\mathbf{H})\right) \ge \binom{N}{k} \Gamma\left(\frac{k}{2}, \frac{\rho}{2} R_{k}^{2}(\mathbf{H})\right),$$
(56)

or equivalently

$$\sum_{p=1}^{\binom{N}{k}} \left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\rho}{2}R_{\mathcal{S}_{k,p}}^{2}(\mathbf{H})\right)}{\Gamma\left(\frac{k}{2}\right)} \right) \leq \binom{N}{k} \left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\rho}{2}R_{k}^{2}(\mathbf{H})\right)}{\Gamma\left(\frac{k}{2}\right)} \right).$$
(57)

Taking into account (50) and (57) for some k, 0 < k < N, it yields

$$\sum_{p=1}^{\binom{N}{k}} J_{k,p} \le \binom{N}{k} \left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\rho}{2} R_k^2(\mathbf{H})\right)}{\Gamma\left(\frac{k}{2}\right)} \right) = \binom{N}{k} I_k(\mathbf{H}).$$
(58)

For the case when k = 0, p = 1 and it holds that $J_0(\mathbf{H}) = I_0(\mathbf{H}) = 1$. For k = N, it is also p = 1 and from (22), since $\operatorname{vol}(\mathcal{V}_{\mathcal{S}_N}(\mathbf{H})) = \frac{\pi^{\frac{N}{2}} R_N^k(\mathbf{H})}{\Gamma(\frac{N}{2}+1)}$

$$J_N(\mathbf{H}) \le \left(1 - \frac{\Gamma\left(\frac{N}{2}, \frac{\rho}{2} R_N^2(\mathbf{H})\right)}{\Gamma\left(\frac{N}{2}\right)}\right) = I_N(\mathbf{H}).$$
(59)

Combining (58) and (59), multiplying by $(K-1)^k$ and summing for all k, it results to

$$\sum_{k=0}^{N} (K-1)^{k} \sum_{p=1}^{\binom{N}{k}} J_{k,p}(\mathbf{H}) \le \sum_{k=0}^{N} (K-1)^{k} \binom{N}{k} I_{k}(\mathbf{H}).$$
(60)

Finally, using (19), (25) and (60)

$$P_{mslb}(\rho) \le P_{f,K-PAM}(\rho) \tag{61}$$

and this concludes the proof.

APPENDIX B

PROOF OF THEOREM 2

The proof starts by approximating the decision region of the faded lattice, \mathcal{V}_{S_N} (**H**), with a sphere, whose radius is equal with the packing radius of the lattice [7], [21], i.e., the minimum Euclidean distance between the origin of the lattice and the facets of \mathcal{V}_{S_N} (**H**). If q is the number of neighboring symbols around a point of the unfaded lattice, and \mathbf{d}_i with i = 1, ..., q, is the vector from the point investigated to the i-th neighboring one, the sphere packing radius for a given channel realization **H** becomes equal to the minimum Euclidean distance on the faded lattice, namely

$$d_{\min,\mathcal{S}_N}(\mathbf{H}) = \min_{i=1,\dots,q} \frac{\|\mathbf{H}\mathbf{d}_i\|}{2} = \min_{i=1,\dots,q} \frac{\sqrt{\sum_{j=1}^N h_j^2 d_{ij}^2}}{2}$$
(62)

However for any d_i holds that

$$\sqrt{\sum_{j=1}^{N} h_j^2 d_{ij}^2} \ge \|\mathbf{d}_{\mathbf{i}}\| \min_{j=1,\dots,N} h_j.$$
(63)

Thus, we can conclude that

$$\min_{i=1,\dots,q} \left(\frac{\sqrt{\sum\limits_{j=1}^{N} h_j^2 d_{ij}^2}}{2} \right) \ge \min_{i=1,\dots,q} \frac{\|\mathbf{d}_{\mathbf{i}}\| \min_{j=1,\dots,N} (h_j)}{2}, \tag{64}$$

or equivalently

$$d_{\min,\mathcal{S}_N}(\mathbf{H}) = \min_{i=1,\dots,q} \frac{\sqrt{\sum_{j=1}^N h_j^2 d_{ij}^2}}{2} \ge \frac{d_{\min}}{2} \min_{j=1\dots,N} h_j,$$
(65)

where $d_{min} = \min_{i=1,...,q} ||\mathbf{d}_i||$ is the minimum Euclidean distance between adjacent points on the unfaded infinite lattice. Therefore, the packing radius of the faded lattice can be lower bounded by (26), which yields an upper bound on the frame error probability, $P_{sub}(\rho)$, given in (28). This concludes the proof.

- N.T.

APPENDIX C

PROOF OF THEOREM 3

For a faded sublattice defined by $S_{k,p}$, similarly to Appendix B, the minimum Euclidean distance $d_{min,S_{k,p}}(\mathbf{H})$ between adjacent points can be lower bounded by

$$d_{\min,\mathcal{S}_{k,p}}(\mathbf{H}) \ge \frac{d_{\min,\mathcal{S}_{k,p}}}{2} \min_{j=1\dots,N} h_j,\tag{66}$$

where $d_{min,S_{k,p}}$ is the minimum Euclidean distance between adjacent points on the unfaded sublattice defined by $S_{k,p}$. Since $S_{k,p} \subseteq S_N$, it holds that

$$d_{\min,\mathcal{S}_{k,p}} \ge d_{\min} \tag{67}$$

and consequently

$$d_{\min,\mathcal{S}_{k,p}}(\mathbf{H}) \ge \frac{d_{\min}}{2} \min_{j=1\dots,N} h_j.$$
(68)

Thus, the packing radius of every faded sublattice defined by $S_{k,p}$ can be lower bounded by (26) and the integrals in (27) are lower bounds to the integrals on the faded voronoi cells $\mathcal{V}_{S_{k,p}}(\mathbf{H})$, making the expression in (29) an upper bound of the FEP of finite lattice constellations. This concludes the proof.

APPENDIX D

Closed Form for the Function $A(\rho, N; k, L)$

The following function

$$A(\rho, N; k, L) = \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{k}{2}, \frac{\mathcal{R}^{2}(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}\right)^{L}\right],\tag{69}$$

can be written as [17, Eq. (1.111)]

$$A(\rho, N; k, L) = \sum_{q=0}^{L} {\binom{L}{q}} \frac{(-1)^{q}}{\left(\Gamma\left(\frac{k}{2}\right)\right)^{q}} \mathbb{E}\left[\left(\Gamma\left(\frac{k}{2}, \frac{\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\rho\right)\right)^{q}\right].$$
(70)

Using an alternative representation for the upper incomplete Gamma function [17, Eq. (8.352/2)] and applying the multinomial theorem, we obtain

$$\left[\Gamma\left(\frac{k}{2}, \frac{\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\rho\right)\right]^{q} = \exp\left(-\frac{q\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\rho\right)\left(\Gamma\left(\frac{k}{2}\right)\right)^{q}\Gamma\left(q+1\right)$$

$$\times \sum_{\substack{n_{0}, \dots, n_{\frac{k}{2}-1}=0\\n_{0}+\dots+n_{\frac{k}{2}-1}=q}}^{q} \frac{\left(\frac{\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\rho\right)^{\frac{k}{2}-1}in_{i}}{\prod_{i=0}^{\frac{k}{2}-1}\left((i!)^{n_{i}}\Gamma\left(n_{i}+1\right)\right)}.$$
(71)

Hence, (70) can be rewritten as

$$A(\rho, N; k, L) = \sum_{q=0}^{L} \sum_{\substack{n_0, \dots, n_{\frac{k}{2}-1} = 0\\ n_0 + \dots + n_{\frac{k}{2}-1} = q}}^{q} \frac{L!}{(L-q)!} \frac{(-1)^q \rho^{\frac{k}{2}-1}_{i=0}}{\prod_{i=0}^{L-1} ((i!)^{n_i} \Gamma(n_i+1))} \mathcal{E}_1,$$
(72)

where

$$\mathcal{E}_{1} = \mathbb{E}\left[\left(\frac{\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\right)^{\sum_{i=0}^{\frac{L}{2}-1}in_{i}}\exp\left(-\frac{q\mathcal{R}^{2}\left(\mathbf{H}\right)}{2}\rho\right)\right].$$
(73)

Taking into consideration that the cdf of $\gamma_{\min} = \min_{i=1,\dots,N} \gamma_i$ is given by

$$P_{\gamma_{\min}}(x) = 1 - \left(\frac{\Gamma(m, mx)}{\Gamma(m)}\right)^{N},$$
(74)

and after employing [17, Eq. (8.356.4)], the pdf of $\mathcal{R}^2(\mathbf{H})$ can be straightforwardly derived, according to (26), as

$$p_{\mathcal{R}^{2}}(x) = \frac{\left[\Gamma\left(m, \frac{4m}{d_{\min}^{2}}x\right)\right]^{N-1} x^{m-1} \exp\left(-\frac{4m}{d_{\min}^{2}}x\right)}{\left(\frac{d_{\min}^{2}}{4}\right)^{m} m^{-m} \left[\Gamma\left(m\right)\right]^{N} N^{-1}},$$
(75)

Equivalently, using (71), (75) can be written as

$$p_{\mathcal{R}^{2}}(x) = \frac{N \exp\left(-\frac{4mN}{d_{\min}^{2}}x\right)}{\left(\frac{d_{\min}^{2}}{4m}\right)^{-1} \frac{\Gamma(m)}{\Gamma(N)}} \sum_{\substack{t_{0},\dots,t_{m-1}=0\\t_{0}+\dots+t_{m-1}=N-1}}^{N-1} \frac{\left(\frac{4m}{d_{\min}^{2}}x\right)^{\sum_{j=0}^{m-1} jt_{j}+m-1}}{\prod_{j=0}^{m-1} \left((j!)^{t_{j}} \Gamma(t_{j}+1)\right)}.$$
(76)

Hence, for the expectation in (73), denoted as \mathcal{E}_1 , when q = 0, it holds that $\sum_{i=0}^{\frac{k}{2}-1} in_i = 0$ and thus $\mathcal{E}_1 = 1$, while for q > 0, \mathcal{E} can be can be analytically evaluated as [17, Eq. (3.326.2)]

$$\mathcal{E}_{1} = \frac{Nm^{m}}{\Gamma(m)} \sum_{\substack{t_{0},...,t_{m-1}=0\\t_{0}+...+t_{m-1}=N-1}}^{N-1} \frac{\frac{m^{\left[\sum\limits_{j=0}^{m-1}jt_{j}\right]}\Gamma\left(\sum\limits_{j=0}^{m-1}jt_{j}+m+\sum\limits_{i=0}^{k-1}in_{i}\right)}{\left(mN+\frac{q_{P}d_{\min}^{2}}{8}\right)^{\left[\sum\limits_{j=0}^{m-1}jt_{j}+m+\sum\limits_{i=0}^{k-1}in_{i}\right]}}.$$
(77)

Finally, by combining (72) with (77) and taking into account the case for q = 0, it yields (31) and this concludes the proof.

APPENDIX E

CLOSED FORM FOR THE FUNCTION $B(\rho, N; k)$

The function

$$B(\rho, N; k) = \mathbb{E}\left[1 - \frac{\Gamma\left(\frac{k}{2}, \frac{R_k^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{k}{2}\right)}\right], \quad 0 < k < N,$$
(78)

can be written, using (22), as

$$B(\rho, N; k) = 1 - \frac{1}{\Gamma\left(\frac{k}{2}\right)} \mathbb{E}\left[\Gamma\left(\frac{k}{2}, \frac{\rho\Gamma\left(\frac{k}{2}+1\right)^{\frac{2}{k}}W^2}{2\pi}\max_{i=1,\dots,N}\left(\gamma_i\right)\right)\right],\tag{79}$$

or if we set $b = \max_{i=1,\dots,N} \gamma_i$, then

$$B(\rho, N; k) = 1 - \frac{1}{\Gamma\left(\frac{k}{2}\right)} \int_0^\infty \Gamma\left(\frac{k}{2}, \frac{\rho\Gamma\left(\frac{k}{2}+1\right)^{\frac{2}{k}} W^2}{2\pi} x\right) f_b(x) \, dx. \tag{80}$$

The cdf of b is

$$F_b(x) = \left(1 - \frac{\Gamma(m, mx)}{\Gamma(m)}\right)^N = \sum_{q=0}^N \binom{N}{q} \frac{\Gamma(m, mx)^q}{\Gamma(m)^q}.$$
(81)

Now, as in (71), (81) can be rewritten as

$$F_b(x) = \sum_{q=0}^N \binom{N}{q} \exp\left(-qmx\right) \Gamma\left(q+1\right) \sum_{\substack{n_0, n_1, \dots, n_{m-1}=0\\n_0+n_1+\dots+n_{m-1}=q}}^q x^{\left[\sum_{i=0}^{m-1} in_i\right]} \prod_{i=0}^{m-1} \frac{\left(\frac{m^i}{i!}\right)^{n_i}}{\Gamma\left(n_i+1\right)}.$$
 (82)

The pdf of b is obtained by taking the derivative of (82) as

$$f_{b}(x) = \sum_{q=0}^{N} \binom{N}{q} \exp\left(-qmx\right) \Gamma\left(q+1\right) \\ \times \sum_{\substack{n_{0}, n_{1}, \dots, n_{m-1}=0\\n_{0}+n_{1}+\dots+n_{m-1}=q}}^{q} x^{\left[\sum_{i=0}^{m-1} in_{i}-1\right]} \left(-qmx + \sum_{i=0}^{m-1} in_{i}\right) \left(\prod_{i=0}^{m-1} \frac{\left(\frac{m^{i}}{i!}\right)^{n_{i}}}{\Gamma\left(n_{i}+1\right)}\right)$$
(83)

Hence, (80) becomes equivalent with

$$B(\rho, N; k) = 1 - \frac{1}{\Gamma(\frac{k}{2})} \sum_{q=0}^{N} {N \choose q} \Gamma(q+1) \\ \times \left\{ \sum_{\substack{n_0, n_1, \dots, n_{m-1}=1\\n_0+n_1+\dots+n_{m-1}=q}}^{q} (-qm) \left(\prod_{i=0}^{m-1} \frac{\left(\frac{m^i}{i!}\right)^{n_i}}{\Gamma(n_i+1)} \right) f\left(\sum_{i=0}^{m-1} in_i + 1, \frac{\rho\Gamma(\frac{k}{2}+1)^{\frac{2}{k}}W^2}{2\pi}, qm, \frac{k}{2} \right) \right. \\ \left. + \left. \sum_{\substack{n_0, n_1, \dots, n_{m-1}=1\\n_0+n_1+\dots+n_{m-1}=q}}^{q} \left(\sum_{i=0}^{m-1} in_i \right) \left(\prod_{i=0}^{m-1} \frac{\left(\frac{m^i}{i!}\right)^{n_i}}{\Gamma(n_i+1)} \right) f\left(\sum_{i=0}^{m-1} in_i, \frac{\rho\Gamma(\frac{k}{2}+1)^{\frac{2}{k}}W^2}{2\pi}, qm, \frac{k}{2} \right) \right\} \\ \left. \right\}$$

$$\left. \left. \right\}$$

$$\left. \left. \left. \right\}$$

$$\left. \right\}$$

$$\left. \left. \right\}$$

$$\left. \right\}$$

$$\left. \left. \right\}$$

$$\left. \right\}$$

where

$$f(\alpha,\beta,p,\nu) = \int_0^\infty x^{\alpha-1} \Gamma(\nu,\beta x) \exp(-px) \, dx.$$
(85)

Using [22, Eq. (2.10.3.2)], (84) can be reduced to (33) with $g(\alpha, \beta, p, \nu)$ as defined in (34), and this concludes the proof.

APPENDIX F

Closed Form for the Function $C(\rho, N; L)$

The function

$$C(\rho, N; L) = \mathbb{E}\left[\left(1 - \frac{\Gamma\left(\frac{N}{2}, \frac{R_N^2(\mathbf{H})}{2}\rho\right)}{\Gamma\left(\frac{N}{2}\right)}\right)^L\right],\tag{86}$$

can be written, following a similar analysis as in Appendix D, as

$$C(\rho, N; L) = \sum_{q=0}^{L} \sum_{\substack{n_0, \dots, n_{\frac{N}{2}-1}=0\\n_0+\dots+n_{\frac{N}{2}-1}=q}}^{q} \frac{\frac{L!}{(L-q)!} (-1)^q \left(\frac{1}{2}\rho\right)^{\sum_{i=0}^{\frac{N}{2}-1} in_i}}{\prod_{i=0}^{\frac{N}{2}-1} ((i!)^{n_i} \Gamma(n_i+1))} \mathcal{E}_2,$$
(87)

where

$$\mathcal{E}_{2} = \mathbb{E}\left[\left(R_{N}^{2}\left(\mathbf{H}\right)\right)^{\sum_{i=0}^{\frac{N}{2}-1}in_{i}}\exp\left(-\frac{qR_{N}^{2}\left(\mathbf{H}\right)}{2}\rho\right)\right].$$
(88)

Using [23, Eq. (5)] and after a variable transformation, the pdf of $R_N^2(\mathbf{H})$ can be straightforwardly obtained for Nakagami fading model as

$$p_{R_{N}^{2}}(x) = \frac{Nx^{-1}}{(\Gamma(m))^{N}} G_{0,N}^{N,0} \left[\left(\frac{\pi xm}{\left(\Gamma\left(\frac{N}{2}+1\right)\right)^{\frac{2}{N}}} \right)^{N} \middle| \begin{array}{c} -\\ m,...,m \end{array} \right].$$
(89)

Hence, for the expectation in (88), denoted as \mathcal{E}_2 , when q = 0 it is $\mathcal{E}_2 = 1$, whereas for $q \neq 0$, it can be analytically evaluated, by expressing its integrand exp (·) in terms of Meijer's G-functions according to [24, Eq. (8.4.3.1)] and using [24, Eq. (2.24.1.1)], as

$$\mathcal{E}_{2} = \frac{\sqrt{N} \left(\frac{2N}{q\rho}\right)^{\sum_{i=0}^{\frac{N}{2}-1} in_{i}}}{\left(\Gamma(m)\right)^{N} \left(2\pi\right)^{\frac{N-1}{2}}} G_{N,N}^{N,N} \left[\frac{\left(\frac{2\pi mN}{q\rho}\right)^{N}}{\left(\Gamma\left(\frac{N}{2}+1\right)\right)^{2}} \left| \begin{array}{c} \frac{1-\sum_{i=0}^{\frac{N}{2}-1} in_{i}}{N}, \dots, \frac{N-\sum_{i=0}^{\frac{N}{2}-1} in_{i}}{N} \\ m, \dots, m \end{array} \right].$$
(90)

By combining (90) with (87), and taking into account the special case for q = 0, (87) can be written as in (36) and this concludes the proof.

REFERENCES

- K. N. Pappi, N. D. Chatzidiamantis, T. N. Chronis and G. K. Karagiannidis, "Error Performance of Multidimensional Lattice Constellations - Part I: A Parallelotope Geometry Based Approach for the AWGN Channel", submitted to *IEEE Trans. Commun.*
- [2] J. Boutros and E. Viterbo, "Signal Space Diversity: A power- and bandwidth-efficient diversity technique for the Rayleigh fading channel", *IEEE Trans. Inf. Theory*, vol. 44, no. 4, p. 1453–1467, Jul. 1998.
- [3] J. Boutros, E. Viterbo, C. Rastello, and J. C. Belfiore, "Good lattice constellations for both Rayleigh fading and Gaussian channels", *IEEE Trans. Inf. Theory*, vol. 42, no. 2 pp. 502–518, Mar. 1996.
- [4] X. Giraud, E. Boutillon, and J. C. Belfiore, "Algebraic tools to build modulation schemes for fading channels", *IEEE Trans. Inf. Theory*, vol. 43, no. 3, pp. 938-952, May 1997.
- [5] E. Bayer-Fluckiger, F. Oggier, and E. Viterbo, "New algebraic constructions of rotated Zn-lattice constellations for the Rayleigh fading channel," *IEEE Trans. Inf. Theory*, vol. 50, no. 4, pp. 702–714, Apr. 2004.
- [6] F. Oggier and E. Viterbo, Algebraic Number Theory And Code Design For Rayleigh Fading Channels, Foundations and Trends in Communications and Information Theory. Now Publishers Inc, 2004.

- [7] E. Viterbo and E. Biglieri, "Computing the voronoi cell of a lattice: the diamond-cutting algorithm," *IEEE Trans. Inf. Theory*, vol. 42, no. 1, p. 161–171, Jan. 1996.
- [8] J.-C. Belfiore and E. Viterbo, "Approximating the error probability for the independent Rayleigh fading channel", in *Proc.* 2005 International Symposium on Information Theory, Adelaide, Australia, Sept. 2005.
- [9] G. Taricco and E. Viterbo, "Performance of high-diversity multidimensional constellations", *IEEE Trans. Inf. Theory*, vol. 44, no. 4, pp. 1539-1543, Jul 1998.
- [10] E. Bayer-Fluckiger, F. Oggier, E. Viterbo, "Algebraic lattice constellations: bounds on performance," *IEEE Trans. Inf. Theory*, vol.52, no.1, pp. 319- 327, Jan. 2006.
- [11] J. Kim, W. Lee, J.-K. Kim, and I. Lee, "On the symbol error rates for signal space diversity schemes over a Rician fading channel", *IEEE Trans. Commun.*, vol. 57, no. 8, pp. 2204-2209, Aug. 2009.
- [12] C. E. Shannon, "Probability of error for optimal codes in a Gaussian channel", *The Bell Syst. Techn. J.*, vol. 38, no. 3, pp. 279–324, May 1959
- [13] V. Tarokh, A. Vardy, and K. Zeger, "Universal bound on the performance of lattice codes," *IEEE Trans. Inf. Theory*, vol. 45, no. 2, pp. 670–681, Mar. 1999.
- [14] S. Vialle and J. Boutros, "Performance of optimal codes on Gaussian and Rayleigh fading channels: a geometrical approach", in *Proc. 37th Allerton Conf. on Commun., Control and Comput.*, Monticello, IL, Sept. 1999.
- [15] A. G. Fàbregas and E. Viterbo, "Sphere lower bound for rotated lattice constellations in fading channels", *IEEE Trans. Wireless Commun.*, vol. 7, no. 3, p. 825-830, Mar. 2008.
- [16] M. K. Simon and M.-S. Alouini, Digital Communication over Fading Channels. 2nd ed., New York: Wiley, 2005.
- [17] I. S. Gradshteyn and I. M. Ryzhik, Table of Integrals, Series, and Products, New York, Academic Press, 7th edition, 2007.
- [18] Wolfram Research, "Meijer G-Function: Specific Values", http://functions.wolfram.com/07.34.03.0871.01
- [19] E. Viterbo and F. Oggier, "Tables of algebraic rotations", http://www.tlc.polito.it/~viterbo.
- [20] G.H. Hardy, J.E. Littlewood, and G. Polya, Inequalities, 2nd ed. Cambridge, UK, Cambridge Univ. Press, 1952.
- [21] J. H. Conway and N. J. A. Sloane, Sphere Packings, Lattices and Groups, 3rd ed. Springer, 1999.
- [22] A. P. Prudnikov, Y. A. Brychkov and O. I. Marichev, "Integral and Series. Vol. 2: Special functions.", Amsterdam, Gordon and Breach Science Publishers, 1986.
- [23] G. K. Karagiannidis, T. A. Tsiftsis, and R. K. Mallik, "Bounds for multihop relayed communications in Nakagami-m fading," *IEEE Trans. Commun.*, vol. 54, no. 1, pp. 18-22, Jan. 2006.
- [24] A. P. Prudnikov, Y. A. Brychkov, and O. I. Marichev, *Integrals and Series, Volume 3: More Special Functions*. New York: Gordon and Breach, 1990.



Fig. 1: Frame Error Probability, SLB and SUB for the \mathbb{Z}^2 infinite lattice, for m = 1 and L = 1,100.



Fig. 2: Frame Error Probability, SLB and SUB for the \mathbb{Z}^2 infinite lattice, for m = 1, 4 and L = 1.

10⁰





Fig. 3: Frame Error Probability, SLB and SUB for the \mathbb{Z}^N infinite lattice, for m = 1 L = 1 and N = 2, 8.

Fig. 4: Frame Error Probability, SLB, SUB, MSLB and MSUB for the \mathbb{Z}^2 4-PAM constellation, for m = 1 and L = 1.

Fig. 5: Frame Error Probability, MSLB and MSUB for the \mathbb{Z}^2 4-PAM constellation, for m = 1 and L = 1,100.

Fig. 6: Frame Error Probability, MSLB and MSUB for the \mathbb{Z}^2 4-PAM constellation, for m = 1, 4 and L = 1.

Fig. 7: Frame Error Probability, MSLB and MSUB for the \mathbb{Z}^N 4-PAM constellation, for m = 1, L = 1 and N = 2, 8.

Fig. 8: Frame Error Probability, MSLB and MSUB for the \mathbb{Z}^2 32-PAM constellation, for m = 1 and L = 1.

Fig. 9: Frame Error Probability, MSLB and MSUB for the \mathbb{A}^2 4-PAM constellation, for m = 1 and L = 1.