Trace codes over \mathbb{Z}_4 and Boolean function

Minjia Shi, Yan Liu, Randriam Hugues, Lin Sok, Patrick Sol \acute{e}^{\dagger}

Abstract

We construct trace codes over \mathbb{Z}_4 by using Boolean functions and skew sets, respectively. Their Lee weight distribution is studied by using a Galois ring version of the Walsh-Hadamard transform and exponential sums. We obtain a new family of optimal two-weight codes over \mathbb{Z}_4 .

Keywords: Galois rings, Boolean functions, Character sums, Two-weight codes

1 Introduction

Most trace codes have their coordinate sets indexed by the elements of a finite field, or in the case of \mathbb{Z}_4 -codes by the Teichmüller set of a Galois ring [7]. This is the case, for instance, of the quaternary Kerdock codes [5]. Recently, Ding investigated a different way of constructing trace codes by indexing their coordinate places by the elements of a difference set [2], and in some cases, the support of a Boolean function [2, §VI].

In this paper we generalize Ding's approach to \mathbb{Z}_4 -codes. The support S_f of a Boolean function f is mapped to a subset of a Teichmüller set by inverse reduction modulo 2. The Lee weight distribution of the code is studied by means of a variant of the Walsh-Hadamard transform, which is in fact the Walsh-Hadamard transform for a family of generalized Boolean function with domain \mathbb{F}_2^n and range \mathbb{Z}_4 . In fact some of our codes (§4.1) will have the codes of [2] as residue codes and as torsion codes. Another approach, with a different defining set yields three-weight codes. Using a natural generalization of skew sets of [2], we obtain two-weight codes the Gray images of which meet the recent Griesmer bound for nonlinear binary codes of [1].

The material is organized as follows. The next section sets up the basic notations and definitions. Section 3 gives a character sum approach to the weight distribution of our trace codes. Section 4 discusses the two families of codes we mentioned and give, for the second family, its weight distributions when the Boolean function is

^{*}Key Laboratory of Intelligent Computing & Signal Processing Ministry of Education, Anhui University No. 3 Feixi Road, Hefei Anhui Province 230039, P. R. China, National Mobile Communications Research Laboratory, Southeast University and School of Mathematical Sciences of Anhui University, Anhui, 230601, P. R. China.

[†]CNRS/LAGA Université Paris 8, 2 rue de la Liberté, 93 526 Saint-Denis, France.

bent or semi-bent. Section 5 recapitulates the obtained results and makes some conjectures for future research.

2 Preliminaries

2.1 Rings

In this subsection, we recall several basic facts on the algebraic structure of the Galois ring GR(4, m) and fix several basic notations. For more knowledge on Galois rings we refer to Wan's book [11].

For convenience later, let $\mathcal{R} = GR(4, m)$. Denoted by \mathcal{R}^* the group of units. In \mathcal{R} with maximal ideal $I = \langle 2 \rangle$, there exists a nonzero element ξ of order $2^m - 1$, which is a root of a basic primitive polynomial h(x) of degree m over \mathbb{Z}_4 and $\mathcal{R} = \mathbb{Z}_4[\xi]$. Let $\mathcal{T} = \{0, 1, \xi, \xi^2, \ldots, \xi^{2^m - 2}\}$. It can be showed that any element $c \in \mathcal{R}$ can be written uniquely as c = a + 2b with $a, b \in \mathcal{T}$. It can be also showed that $\mathcal{T} \equiv \mathbb{F}_{2^m}$ (mod 2).

Recall that the *trace* map tr from \mathbb{F}_{2^m} to \mathbb{F}_2 is defined by $tr(a) = \sum_{i=0}^{m-1} a^{2^i}$ for all $a \in \mathbb{F}_{2^m}$. Define the *generalized trace* map Tr from \mathcal{R} to \mathbb{Z}_4 by Tr(c) = tr(a) + 2tr(b) for all $c = a + 2b \in \mathcal{R}$.

2.2 Codes and Gray map

A linear code C over \mathbb{Z}_4 of length n is a \mathbb{Z}_4 -submodule of \mathbb{Z}_4^n . For any two vertors $\mathbf{x} = (x_1, x_2, \ldots, x_n), \mathbf{y} = (y_1, y_2, \ldots, y_n) \in \mathbb{Z}_4^n$, the Euclidean inner product of \mathbf{x} and \mathbf{y} is defined by $\langle \mathbf{x}, \mathbf{y} \rangle = \sum_{i=1}^n x_i y_i$, where the operation is performed in \mathbb{Z}_4 . The dual code of C is denoted by C^{\perp} and defined as $C^{\perp} = \{\mathbf{y} \in \mathbb{Z}_4^n : \langle \mathbf{x}, \mathbf{y} \rangle = 0, \forall \mathbf{x} \in C\}$. By definition, C^{\perp} is also a linear code over \mathbb{Z}_4 . The *residue code* Res(C) of C is the binary code defined as $Res(C) = \{\mathbf{x} \in \mathbb{F}_2^n : \exists \mathbf{y} \in C, \mathbf{y} \equiv \mathbf{x} \pmod{2}\}$. The torsion code Tor(C) is the binary code defined as $Tor(C) = \{\mathbf{x} \in \mathbb{F}_2^n : \exists \mathbf{y} \in C, \mathbf{y} = 2\mathbf{x}\}$. The Lee weight $w_L(\mathbf{x})$ of $\mathbf{x} = (x_1, x_2, \ldots, x_n)$ is defined as $w_L(\mathbf{x}) = n_1(\mathbf{x}) + 2n_2(\mathbf{x}) + n_3(\mathbf{x})$, where $n_i(\mathbf{x})$ denote the number of occurences of a i symbol in \mathbf{x} .

For any $\mathbf{x} = (x_1, x_2, \ldots, x_n) \in \mathbb{Z}_4^n$ with $x_i = r_i + uq_i$, the Gray map ϕ from \mathbb{Z}_4^n to \mathbb{F}_2^2 is given by $\phi(\mathbf{x}) = (q(\mathbf{x}), r(\mathbf{x}) + q(\mathbf{x}))$, where $r(\mathbf{x}) = (r_1, r_2, \ldots, r_n), q(\mathbf{x}) = (q_1, q_2, \ldots, q_n)$ are binary vectors. Then ϕ is a weight-preserving map from $(\mathbb{Z}_4^n, \text{Lee}$ weight) to $(\mathbb{F}_2^{2n}, \text{Hamming weight})$, that is, $w_L(\mathbf{x}) = w_H(\phi(\mathbf{x}))$, where $w_H(\phi(\mathbf{x}))$ denotes the number of nonzero positions in the binary vector $\phi(\mathbf{x})$.

3 Trace codes

3.1 Description of Trace Codes

Let $D = \{d_1, d_2, \ldots, d_n\} \subseteq \mathcal{R} \setminus \{0\}$. We define a linear code of length n over \mathbb{Z}_4 by $C_D = \{c_a = (Tr(ad_1), Tr(ad_2), \ldots, Tr(ad_n)) : a \in \mathcal{R}\}$, and call D the defining set of this code C_D . This construction is generic in the sense that many classes of known codes could be produced by selecting the defining set [2]. The objective of this paper is to construct linear codes C_D by using three classes of D's defined later. If the set D is well chosen, the code C_D may have good or optimal parameters. Otherwise, the code C_D could have bad parameters.

3.2 The Weights of C_D

It is convenient to define for each $b \in \mathcal{R}$, $c_b = (Tr(bd_1), \ldots, Tr(bd_n))$. Let $N_b(j) = |\{1 \le i \le n : Tr(bd_i) = j\}|$ for $0 \le j \le 3$. Then the Lee weight $w_L(c_b)$ of c_b is $n - N_b(0) + N_b(2)$ for each $b \in \mathcal{R}$.

It is easily seen that for any $D = \{d_1, d_2, \ldots, d_n\} \subseteq \mathcal{R} \setminus \{0\}$, we have

$$N_{b}(j) = \frac{1}{4} \sum_{i=1}^{n} \sum_{y=0}^{3} i^{y[Tr(bd_{i})-j]}$$

= $\frac{1}{4} \Big[n + \sum_{i=1}^{n} \sum_{y=1}^{3} i^{y[Tr(bd_{i})-j]} \Big]$
= $\frac{1}{4} \Big[n + \sum_{i=1}^{n} \sum_{y=1}^{3} i^{y[Tr(bd_{i})]} \cdot i^{-jy} \Big]$
= $\frac{1}{4} \Big[n + \sum_{y=1}^{3} \chi(ybD)i^{-jy} \Big],$

where χ is the canonical additive character of \mathcal{R} , ybD denotes the set $\{ybd : d \in D\}$, and $\chi(ybD) = \sum_{x \in D} \chi(ybx)$ for any subset S of \mathcal{R} . When j = 0, then $N_b(0) = \frac{1}{4} \left[n + \sum_{y=1}^3 \chi(ybD) \right]$. When j = 2, then $N_b(2) = \frac{1}{4} \left[n + \sum_{y=1}^3 \chi(ybD)(-1)^y \right]$. Hence, $w_L(c_b) = n - N_b(0) + N_b(2)$ $= n - \frac{1}{4} \left[n + \sum_{y=1}^3 \chi(ybD) \right] + \frac{1}{4} \left[n + \sum_{y=1}^3 \chi(ybD)(-1)^y \right]$ $= n - \frac{1}{4} \left[\sum_{y=1}^3 \chi(ybD) - \sum_{y=1}^3 \chi(ybD)(-1)^y \right]$ $= n - \frac{1}{2} [\chi(bD) + \chi(-bD)],$

that is,

$$w_L(c_b) = n - \Re(\chi(bD)). \tag{1}$$

4 Construction of \mathbb{Z}_4 -codes by Boolean functions

Let f be a Boolean function from \mathbb{F}_{2^m} to \mathbb{F}_2 . The support of f is defined to be

$$S_f = \{x \in \mathbb{F}_{2^m} : f(x) = 1\} \subseteq \mathbb{F}_{2^m}$$

Take a set $\bar{S}_f \subseteq \mathcal{T}$ such that $\bar{S}_f \equiv S_f \pmod{2}$. Let the size of set S_f be n_f , that is, $n_f = |S_f| = |\bar{S}_f|$. The Walsh-Hadamard transform of f is defined by

$$W_f(w) = \sum_{x \in \mathbb{F}_{2^m}} (-1)^{f(x) + tr(wx)},$$
(2)

where $w \in \mathbb{F}_{2^m}$. By [2], the Walsh spectrum of f is the following multiset

$$\{\{W_f(w): w \in \mathbb{F}_{2^m}\}\}.$$

4.1 Case of $D = \{d : d \in \bar{S}_f\}$

Defined $\Gamma(w) = \sum_{x \in \mathcal{T}} i^{Tr(wx)}$ with $w \in \mathcal{R}$. In this case $D = \bar{S}_f$, the weight distribution of $C_{\bar{S}_f}$ can be worked out in this subsetion. To this end, we need the following lemma [12].

Lemma 4.1. Let ϵ be the primitive 8th root of unity, given by $\epsilon = \frac{(1+i)}{\sqrt{2}}$. For any $w = r + 2s \in \mathcal{R}$ with $r(\neq 0), s \in \mathcal{T}$, we have

$$\Gamma(w) = i^{-Tr(\frac{s}{r})} \Gamma(1)$$

with $\Gamma(1) = \begin{cases} \sqrt{2^m} \epsilon^m, & \text{if } m \text{ is odd,} \\ -\sqrt{2^m} \epsilon^m, & \text{if } m \text{ is even.} \end{cases}$ Now, define $Q(x) = \sum_{\substack{i,j=0\\j>i}}^{m-1} x^{2^i+2^j}$ and $\hat{f}(w) = 2^{-m} \sum_{x \in \mathcal{R}} i^{2f(\bar{x})+Tr(wx)}$, where $w \in C$

 \mathcal{R} and $f(\bar{x}) = 1$ if $x \in \bar{S}_f$, otherwise 0. The function $\hat{f}(w)$ is **not** the Walsh-Hadamard transform but it plays a similar role in estimating the weight distribution as the classical Walsh-Hadamard transform in [2]. Moreover, the main result of this subsection is described in the following theorem.

Theorem 4.2. Let symbols and notations be as above. Let $w = r + 2s \in \mathcal{R}$ with $r, s \in \mathcal{T}$. Then $C_{\bar{S}_f}$ is a linear code over \mathbb{Z}_4 with length n_f and its Lee weight distribution is given by the following multiset:

$$\left\{ \left\{ \frac{4n_f - 2\Re(\Gamma(w)) + \Re(W_{f_r}(\bar{s}) + W_{f_r}(\bar{r} + \bar{s}))}{4} \right\} \right\} \cup \left\{ \left\{ \frac{2n_f + \Re(W_f(\bar{s}))}{2} \right\} \right\} (3) \cup \{\{0\}\},$$

with $f_r(x) = f(x) + Q(rx)$.

Proof. It is trivial that $w_L(c_0) = 0$. As defined previously, we have $2^m \hat{f}(w) = \sum_{x \in \mathcal{R}} i^{2f(\bar{x})+Tr(wx)}$, where $f(\bar{x}) = 1$ if $x \in \bar{S}_f$, and $f(\bar{x}) = 0$ if $x \notin \bar{S}_f$. Let $w = 2s \in I$ with $s \in \mathcal{T} \setminus \{0\}$. From the previous discussion in the Sections 2.1 and 3, we have

$$2^{m}\hat{f}(w) = \sum_{\substack{x=y+2z\in\mathcal{R}\\x\in\mathcal{T}+2\mathcal{T}}} i^{2f(\bar{x})+Tr(wx)} = 2^{m} \sum_{y\in\mathcal{T}} (-1)^{f(\bar{y})+tr(\bar{s}\bar{y})} = 2^{m} W_{f}(\bar{s}).$$

On the other hand,

$$2^{m}\hat{f}(w) = \sum_{\substack{x=y+2z \in \mathcal{R} \\ x \in \mathcal{T}+2\mathcal{T}}} i^{2f(\bar{x})+Tr(wx)}$$

$$= \sum_{\substack{x=y+2z \\ x \in \bar{S}_{f}+2\mathcal{T}}} i^{2f(\bar{x})+Tr(wx)} + \sum_{\substack{x=y+2z \\ x \in (\mathcal{T} \setminus \bar{S}_{f})+2T}} i^{2f(\bar{x})+Tr(wx)}$$

$$= \sum_{z \in \mathcal{T}} \sum_{y \in \bar{S}_{f}} i^{2f(\bar{y})+Tr(wy)} + \sum_{z \in \mathcal{T}} \sum_{y \in T \setminus \bar{S}_{f}} i^{2f(\bar{y})+Tr(wy)}$$

$$= 2^{m} \Big(-\sum_{y \in \bar{S}_{f}} i^{Tr(wy)} + \sum_{y \in \mathcal{T} \setminus \bar{S}_{f}} i^{Tr(wy)} \Big)$$

$$= -2^{m+1} \chi(w\bar{S}_{f}),$$

where the last equality follows by $\sum_{y \in \mathcal{T}} i^{Tr(wy)} = \sum_{y \in \mathbb{F}_{2^m}} (-1)^{tr(\bar{s}\bar{y})} = 0$ with $s \neq 0$. It then follows from (1) that the Lee weight of the codeword c_w with $w \in I \setminus \{0\}$ is equal to $\frac{2n_f + \Re(W_f(\bar{s}))}{2}$.

Equal to $\frac{1}{2}$. It remains to consider w = r + 2s with $r \neq 0$. Now consider $E(w) = \sum_{d \in \bar{S}_f} i^{Tr(wd)} = \sum_{d \in \bar{S}_f} i^{Tr(wd)}$ which implies $w_L(c_r) = n_L - \Re(E(w))$. So it is necessary to

 $\sum_{x \in \mathcal{T}} \frac{1 - (-1)^{f(\bar{x})}}{2} i^{Tr(wx)}$, which implies $w_L(c_w) = n_f - \Re(E(w))$. So it is necessary to analyze the exponential sum E(w). By a simple calculation, we have

$$2E(w) = \sum_{x \in \mathcal{T}} i^{Tr(wx)} - \sum_{x \in \mathcal{T}} (-1)^{f(\bar{x})} i^{Tr(wx)}$$

= $\Gamma(w) - \sum_{x \in \mathcal{T}} (-1)^{f(\bar{x}) + tr(\bar{s}\bar{x})} i^{Tr(rx)}$
= $\Gamma(w) - \sum_{x \in \mathcal{T}} (-1)^{f(\bar{x}) + tr(\bar{s}\bar{x}) + Q(\bar{r}\bar{x})} i^{tr(\bar{r}\bar{x})}$

where the last equality follows by $Tr(rx) = tr(\bar{r}\bar{x}) + 2Q(\bar{r}\bar{x})$ in [7]. Furthermore, let $f_r(\bar{x}) = f(\bar{x}) + Q(\bar{r}\bar{x})$, we get $\Re(E(w)) = \frac{1}{2}\Re(\Gamma(w)) - \frac{1}{4}\Re(W_{f_r}(\bar{s}) + W_{f_r}(\bar{r} + \bar{s}))$. Hence, the Lee weight distribution of $C_{\bar{S}_f}$ is given by the multiset in (3). This completes the proof.

Note that $Q(x) = \sum_{\substack{i,j=0\\j>i}}^{m-1} x^{2^i+2^j}$ is a quadratic function. The rank of the quadratic

form g is defined to be the codimension of the binary vector space

$$V_g = \{ x \in \mathbb{F}_{2^m} : g(x+z) - g(x) - g(z) = 0 \text{ for all } z \in \mathbb{F}_{2^m} \}.$$

Let g be a quadratic form of rank h, then $|V_g| = 2^{m-h}$. When $m \leq 8$, it not difficult to determine numerically the rank of Q(x). Indeed it can be proved that the bilinear form B attached to Q is

$$B(x,y) = \sum_{\substack{i,j=0\\j>i}}^{m-1} x^{2^{i}} y^{2^{j}} + y^{2^{i}} x^{2^{j}},$$

a bivariate polynomial that can be factored in Magma. Based on this data, we give the following proposition.

Proposition 4.3. Let $h = \lfloor \frac{m}{2} \rfloor$. Then the rank of Q(x) is equal to 2h.

Let f be a affine function. Without loss of generality, let f(x) = tr(ax) + b with $a \in \mathbb{F}_{2^m}^*$ and $b \in \mathbb{F}_2$. Using Equation (2), for any $s \in \mathbb{F}_{2^m}^*$, we have

$$W_f(s) = \sum_{x \in \mathbb{F}_{2^m}} (-1)^{tr(ax) + b + tr(sx)} = (-1)^b 2^m \delta_{a,s},$$
(4)

where $\delta_{a,s}$ is equal to 1 if a = s, and 0 if not. We are now ready for a connection with affine functions. To this end, we need the following classical lemma [8, vol. 2, p. 1802].

Lemma 4.4. Let f be a Boolean degree 2 and let 2h be the rank of the associated quadratic Boolean function. Let

$$W_f(\lambda) = \sum_{x \in \mathbb{F}_{2^m}} (-1)^{f(x) + tr(\lambda x)}, \quad \lambda \in \mathbb{F}_{2^m},$$

then $\{W_f(\lambda) : \lambda \in \mathbb{F}_{2^m}\}$ has the distribution $\{0, \pm 2^{m-h}\}.$

The following corollary introduces a connection between affine functions and a class of linear code $C_{\bar{S}_f}$ over \mathbb{Z}_4 . And the Lee weight distribution of the linear code $C_{\bar{S}_f}$ is established.

Corollary 4.5. Let $m \ge 2$ be a positive integer. Let the rank of Q(x) is equal to 2h. If f(x) = tr(ax) + b is a affine function in m variables with $a \in \mathbb{F}_{2m}^*, b \in \mathbb{F}_2$, then $C_{\bar{S}_f}$ is a linear code with parameters $(n_f, 4^m)$ with $n_f = 2^{m-1}$, and its Lee weight distribution is $\{0\} \cup \{2^{m-1}, 2^{m-1} + (-1)^b 2^{m-1}\} \cup \{2^{m-1} - \frac{1}{2}\Re(\Gamma(w)), 2^{m-1} - \frac{1}{2}\Re(\Gamma(w)) \pm 2^{m-h-2}, 2^{m-1} - \frac{1}{2}\Re(\Gamma(w)) \pm 2^{m-h-1}\}.$

Proof. It is not hard to get $n_f = 2^{m-1}$ when f is a affine function. The result follows by Theorem 4.1, Lemma 4.2 and Equation (4).

Example 4.6. For m = 4 and b = 1, we have $\Re(\Gamma(w)) = \pm 4$, and we obtain the Lee distance $d_L = 4$. After Gray map we obtain a $(16, 2^8, 4)_2$ code, one unit away from the optimal linear $[16, 8, 5]_2$.

Example 4.7. For m = 5 and b = 1, we have $\Re(\Gamma(w)) = \pm 4$, and we obtain the Lee distance $d_L = 10$. After Gray map we obtain a $(32, 2^{10}, 10)_2$ code, two units away from the optimal linear $[32, 10, 12]_2$.

In the sequence, we will employ bent Boolean functions and semi-bent Bollean function to construct linear binary codes with only a few weights. From Theorem 4.2, we can obtain the following results immediately.

Corollary 4.8. Let m > 2 be an even integer and f be a bent Boolean function in m variables, then the torsion code $Tor(C_{\bar{S}_f})$ of the linear code $C_{\bar{S}_f}$ is a linear code with parameters $[n_f, m, \frac{1}{2}(n_f - 2^{\frac{m-2}{2}})]_2$, where $n_f = 2^{m-1} \pm 2^{\frac{m-2}{2}}$. And its weights are $\frac{1}{2}(n_f \pm 2^{\frac{m-2}{2}})$.

Example 4.9. For m = 4 we have $n_f = 6$, and we obtain the Hamming distance d = 2 of $Tor(C_{\bar{S}_f})$. The best know binary $[6, 4]_2$ linear code has distance 2 only.

Example 4.10. For m = 4 we have $n_f = 8$, and we obtain the Hamming distance d = 3 of $Tor(C_{\bar{S}_f})$. The best know binary $[8, 4, 3]_2$ linear code is extended Hamming code.

Corollary 4.11. Let m > 3 be an odd integer and f be a semi-bent Boolean function in m variables, then the torsion code $Tor(C_{\bar{S}_f})$ of the linear code $C_{\bar{S}_f}$ is a linear code with parameters $[n_f, m, \frac{1}{2}(n_f - 2^{\frac{m-1}{2}})]_2$, where $n_f = 2^{m-1} \pm 2^{\frac{m-1}{2}}$. And its weights are $\frac{1}{2}(n_f \pm 2^{\frac{m-1}{2}})$, and $\frac{1}{2}n_f$.

Example 4.12. For m = 5 we have $n_f = 12$, and we obtain the Hamming distance d = 4 of $Tor(C_{\bar{S}_f})$. The best know binary $[12, 5]_2$ linear code has distance 4.

4.2 Case of $D = \{d = x + 2y : x \in \overline{S}_f, y \in \mathcal{T}\}$

In the light of Theorem 4.2, the linear code $C_{\bar{S}_f}$ has more Lee-weights. In order to get few Lee-weights, we change the definition set of C_D . In this subsection, the definition set of C_D is $D = \{d = x + 2y : x \in \bar{S}_f, y \in \mathcal{T}\}$. The main result of this subsection is described in the following theorem.

Theorem 4.13. Let symbols and notations be as above. Let $w = r + 2s \in \mathcal{R}$ with $r, s \in \mathcal{T}$. Then C_D is a linear code over \mathbb{Z}_4 with length $2^m n_f$ and its weight distribution is given by the following multiset:

$$\{\{2^{m}n_{f}\}\} \cup \{\{2^{m}n_{f}+2^{m-1}\Re(W_{f}(\bar{s}))\}\} \cup \{\{0\}\}.$$
(5)

Proof. It is trivial for $w_L(c_0) = 0$. Let $w = r + 2s \in \mathcal{R}$ with $r, s \in \mathcal{T}$ and $(r, s) \neq (0, 0)$. By a simple calculation, we have

$$\chi(wD) = \sum_{d=x+2y\in D} i^{Tr(wd)}$$
$$= \sum_{x\in\bar{S}_f} \sum_{y\in\mathcal{T}} (-1)^{tr(\bar{r}\bar{y})} i^{Tr(wx)}$$
$$= 2^m \delta_{r,0} \sum_{x\in\bar{S}_f} i^{Tr(wx)},$$

where $\delta_{r,0} = \begin{cases} 1, & \text{if } r = 0, \\ 0, & \text{if } r \neq 0. \end{cases}$ As defined previously, if $w \in \mathcal{R}^*$, we get $w_L(c_w) = |D| = 2^m n_f$. Now, suppose that w = 2s with $s \in \mathcal{T} \setminus \{0\}$, then

$$\begin{split} \chi(wD) &= 2^m \sum_{x \in \bar{S}_f} (-1)^{tr(\bar{s}\bar{x})} \\ &= 2^m \sum_{x \in \mathcal{T}} \frac{1 - (-1)^{f(\bar{x})}}{2} (-1)^{tr(\bar{s}\bar{x})} \\ &= -2^{m-1} W_f(\bar{s}). \end{split}$$

Applying Equation (1), for any $w = 2s \in I \setminus \{0\}$, the Lee weight of the codeword c_w is equal to $2^m n_f + 2^{m-1} \Re(W_f(\bar{s}))$. Hence, the weight distribution of C_D is given by the multiset in (5). This completes the proof.

Theorem 4.13 established a connection between Boolean functions and a class of linear code over \mathbb{Z}_4 . In order to determine the weight distribution of the linear code C_D , it is equivalent to analyze the Walsh spectrum. We are now ready for a connection with bent functions.

Corollary 4.14. Let m > 2 be an even integer. If f is a bent Boolean function in m variables, then C_D is a linear code with parameters $(2^m n_f, 4^m)$, with $n_f = 2^{m-1} \pm 2^{\frac{m-2}{2}}$, and non-zero Lee weights $2^m n_f \pm 2^{\frac{3m-2}{2}}$ and $2^m n_f$.

Proof. The length is estimated as in the binary case [2, (17)]. Since, by the definition of a bent function, the Walsh transform takes values in $\{\pm 2^{\frac{m}{2}}\}$, the result follows by Theorem 4.13.

Similarly, if f is a semi-bent function, we have, by [2, Cor. 11]) the analogous result.

Corollary 4.15. Let m > 3 be an odd integer. If f is a semi-bent Boolean function in m variables, then C_D is a linear code with parameters $(2^m n_f, 4^m, d_L)$, with $n_f = 2^{m-1} \pm 2^{\frac{m-1}{2}}$. And its non-zero Lee weights are $2^m n_f \pm 2^{\frac{3m-1}{2}}$ and $2^m n_f$, respectively.

5 Construction of \mathbb{Z}_4 -codes by skew sets

A subset D of \mathbb{F}_q^* is called a skew set of \mathbb{F}_q if D, -D and $\{0\}$ form a partition of \mathbb{F}_q . Recall that the maximal ideal of Galois ring \mathcal{R} generated by 2. For simplify, denoted by I the maximal ideal. Now, we extend the notion of skew sets from fields to rings as follows.

Definition 5.1. A subset D of \mathcal{R}^* is called a skew set of \mathcal{R} if D, -D and I form a partition of \mathcal{R} .

In the light of Definition 5.1, we see that $|D| = |-D| = (2^m - 1)2^{m-1}$, which implies the length of C_D is $(2^m - 1)2^{m-1}$. We are now ready to prove the following theorem.

Theorem 5.2. Let D be any skew set of \mathcal{R} . Then the code C_D is a two-Lee weight code of length $(2^m - 1)2^{m-1}$ and its Lee weight distribution is given in Table I.

able 1. Dee weight distribution of C	
Weight	Frequency
0	1
2^{2m-1}	$2^{4m} - 1$
$(2^m - 1)2^{m-1}$	$2^m - 1$

Table I. Lee weight distribution of C_D

Proof. In the case b = 0, the codeword c_b is zero-codeword, thus $w_L(c_b) = 0$. It remains to investigate the Lee weight of c_b with $b \neq 0$. By the orthogonality relation of character, for any $b \neq 0$, we have

$$\sum_{x \in \mathcal{R}} \chi(bx) = \chi(bD) + \chi(-bD) + \chi(bI) = 0.$$

Note that

$$\chi(bI) = \sum_{x \in I} i^{Tr(bx)} = \sum_{x \in \mathbb{F}_{2^m}} (-1)^{tr(\bar{b}x)} = \begin{cases} 0, & \text{if } b \neq 0, \\ 2^m, & \text{if } \bar{b} = 0, \end{cases}$$

with $b \equiv \overline{b} \pmod{2}$. Applying Equation (1), we get $w_L(c_b) = 2^{2m-1}$ or $(2^m - 1)2^{m-1}$ depending on the value of \overline{b} .

In the light of Theorem 5.2, $\phi(C_D)$ is a $(2^{2m} - 2^m, 2^{2m}, 2^{2m-1} - 2^{m-1})$ binary code. Generally speaking, by using Gray map, the binary image of a linear code over \mathbb{Z}_4 is nonlinear. Below we mention a open problems.

Open Problem 5.3. Determine the linearity of $\phi(C_D)$.

A central problem of coding theory is to determine the minimum value of n, for which an $(n, M, d)_q$ -code or an $[n, k, d]_q$ -linear code exists. We denote by $N_q(M, d)$ the minimum length of a nonlinear code over \mathbb{F}_q , with M codewords and distance d, while we use $L_q(k, d)$ in the case of a linear code of dimension k with distance d. Observe that

$$N_q(q^k, d) \le L_q(k, d) \tag{6}$$

Recall the Griesmer bound ([4]) on the parameters of an $[n, k, d]_q$ code.

Lemma 5.4. All $[n, k, d]_q$ linear codes satisfy the following bound

$$n \ge L_q(k,d) \ge \sum_{i=0}^{k-1} \left\lceil \frac{d}{q^i} \right\rceil.$$

If there exist a $[2^{2m}-2^m, 2m, 2^{2m-1}-2^{m-1}]_2$ linear code, we know that $L_2(2m, 2^{2m-1}-2^{m-1}) = 2^{2m}-2^m$ by using Griesmer bound. Consider the case m = 2, then we have a $[12, 4, 6]_2$ linear code.

In fact, there is a version of the Griesmer bound for binary non linear codes [1, Theorem 6] that applies in case of distance of the form $2^a - 2^b$. Thus, combing Lemma 5.4 and Equation (6), $\phi(C_D)$ is a optimal code.

Besides the binary image $\phi(C_D)$, there exits a binary code which is canonically associated with C_D . In the sequel, we will investigate the binary code which call torsion code $Tor(C_D)$. **Corollary 5.5.** Keep the conditions in Theorem 5.2. Then $Tor(C_D)$ is a $[2^{2m} - 2^m, m, 2^{2m-2}]_2$ linear code which meets Griesmer bound.

Proof. It is not difficult to obtain the parameters of $Tor(C_D)$. Applying Lemma 5.4, we obtain the results immediately.

Remark 5.6. Recall that the non-zero codewords of the $[2^m - 1, m, 2^{m-1}]_2$ simplex code all have weights 2^{m-1} . In fact, $Tor(C_D)$ is equivalent to the 2^{m-1} copies of $[2^m - 1, m, 2^{m-1}]_2$ simplex code.

6 Conclusion

In the present work we have studied a family of linear codes over the ring \mathbb{Z}_4 . Given a classical Boolean function, or, equivalently its support we have discussed two different constructions of Trace codes. Building on the results in [2], we give upper and lower bounds on the minimum Lee distance. It is worth noticing that both the residue and torsion codes of the first type of codes we have constructed here are the trace codes of [2]. This gives a pair of crude bounds on the Lee minimum distance. However, the weight distribution is difficult to analyze in general, and we could give only partial results when the Boolean function is affine. In particular, computing the rank of a certain quadratic form is a challenging open problem. A better understanding of this quadratic form could lead to a better choice of the Boolean function. The second construction is easier to analyze, and yields threeweight codes. Eventually, a natural generalization of skew sets yields a family of optimal two-weight codes. Using difference sets or relative difference sets might give more powerful results. Another path of inquiry would be to use a similar approach for \mathbb{Z}_4 valued Boolean function like in [9].

Acknowledgement: This manuscript is supported by NSFC of China (61202068), Technology Foundation for Selected Overseas Chinese Scholar, Ministry of Personnel of China (05015133) and the Open Research Fund of National Mobile Communications Research LaboratorySoutheast University (2015D11). The authors thank Claude Carlet for helpful discussions on Boolean functions.

References

- [1] Bellini, E., Guerrini, E., Meneghetti, A., Sala, M., On the Griesmer bounds for nonlinear codes, /arxiv.org/pdf/1502.07379.pdf.
- [2] Ding, C. S., Linear codes from some 2-designs, IEEE Transactions on information theory, vol. 61, no. 6, pp. 3265–3275, 2015.
- [3] Grassl, M., Bounds on the minimum distance of linear codes and quantum codes. Online available at http://www.codetables.de.
- [4] Griesmer, J.H., A bound for error-correcting codes, IBM Journal of Res. and Dev., vol. 4, no. 5, (1960), 532–542.

- [5] A.R. Hammons P.V. Kumar A.R. Calderbank N.J.A. Sloane P Solé, The Z₄-linearity of Kerdock, Preparata, Goethals, and related codes, IEEE Transactions on Information Theory, **IT-40**, (1994) 301–319.
- [6] Huffman, W.C., Pless, V., Fundamentals of Error Correcting Codes, Cambridge University Press, (2003).
- [7] Kumar, P. V., Helleseth, T., An Expansion for the Coordinates of the Trace Function over Galois Rings, AAECC, vol. 8, no. 5, pp. 353–361, 1997.
- [8] Pless, V.S., Huffman, W.C., Handbook of coding theory, North holland, 1998.
- [9] Solé, P., Tokareva, N., Connections Between Quaternary and Binary Bent Functions, Iacr Cryptology Eprint Archive, 2009.
- [10] Stănică, P., Martinsen, T., Gangopadhyay, S., Singh, B. K., Bent and generelized bent Boolean functions, Des. Codes Cryptogr, vol. 69, no. 1, pp. 77–94, 2013.
- [11] Wan, Z. X., *Quaternary codes*, World Scientific, 1997.
- [12] Yang K., Helleseth. T., Kumar, P.V., Shanbhag, A.G., On the weight hierarchy of kerdock codes over Z₄, IEEE Transactions on information theory, vol. 42, no. 5, pp. 1587–1593, 1996.