

Some new bounds on LCD codes over finite fields*

Binbin Pang, Shixin Zhu, Xiaoshan Kai

School of Mathematics, Hefei University of Technology, Hefei 230009, Anhui, P.R.China

Abstract: In this paper, we show that LCD codes are not equivalent to linear codes over small finite fields. The enumeration of binary optimal LCD codes is obtained. We also get the exact value of $LD(n, 2)$ over \mathbb{F}_3 and \mathbb{F}_4 . We study the bound of LCD codes over \mathbb{F}_q .

Keywords: Bounds, LCD codes, Generator Matrix.

1 Introduction

In this paper, let \mathbb{F}_q be a finite field with q elements. The set of non-zero elements of \mathbb{F}_q is denoted by \mathbb{F}_q^* . For any $x \in \mathbb{F}_{q^2}$, the conjugate of x is defined as $\bar{x} = x^q$. A k -dimensional subspace C of \mathbb{F}_q^n is called an $[n, k, d]$ linear code with minimum (Hamming) distance d . Given a linear code C of length n over \mathbb{F}_q (resp. \mathbb{F}_{q^2}), its Euclidean dual code (resp. Hermitian dual code) is denoted by C^\perp (resp. $C^{\perp H}$). The codes C^\perp and $C^{\perp H}$ are defined as follows

$$C^\perp = \{\mathbf{u} \in \mathbb{F}_q^n \mid \mathbf{u} \cdot \mathbf{c} = \mathbf{0}, \forall \mathbf{c} \in C\},$$

$$C^{\perp H} = \{\mathbf{u} \in \mathbb{F}_q^n \mid \mathbf{u} \cdot \bar{\mathbf{c}} = \mathbf{0}, \forall \mathbf{c} \in C\}.$$

A linear code has complementary dual (or LCD code for short) over \mathbb{F}_q if $C \oplus C^\perp = \mathbb{F}_q^n$. The Euclidean (resp. Hermitian) hull of a linear code C is defined to be $\text{Hull}_E(C) = C \cap C^\perp$ (resp. $\text{Hull}_H(C) = C \cap C^{\perp H}$). A linear code over \mathbb{F}_q is called a Euclidean (resp. Hermitian) LCD code if $\text{Hull}_E(C) = \{\mathbf{0}\}$ ($\text{Hull}_H(C) = \{\mathbf{0}\}$). In the later of this paper, Euclidean LCD code is abbreviated to LCD code if no special stated.

In 1992, Massey first initiated LCD codes [1], and he also proved the existence of asymptotically good LCD codes. Sendrier showed that LCD codes meet the asymptotic Gilbert-Varshamov bound over the finite fields [2]. Yang and Massey gave a necessary and sufficient condition for a cyclic code to be LCD over finite fields [3]. After that, there are many literatures on the construction of LCD codes over finite fields [4–9]. What's more there are many LCD MDS code have been constructed by some scholars in [10–13]. Carlet et al. solved the problem of the existence of q -ary $[n, k]$ LCD MDS codes for Euclidean case [12], they also introduced a general construction of LCD codes from any linear codes. Further more, they showed that any linear code over \mathbb{F}_q ($q > 3$) is equivalent to an Euclidean LCD code and any linear code over \mathbb{F}_{q^2} ($q > 2$) is equivalent to a Hermitian LCD code [13]. Sok et al. proved the existence of optimal LCD codes over large finite fields [14]. Liu et al. discussed the structure of LCD codes over finite chain rings [15].

Recently, many researchers have an interest in LCD codes over small finite fields [16–19]. Galvez et al. gave bounds on the minimum distances of binary LCD codes with fixed lengths and dimensions on the dimensions of LCD codes with fixed lengths and minimum distances. [17]. Carlet et al. presented a new characterization of binary LCD codes in terms of their symplectic basis and solve a conjecture proposed by Galvez et al. [18]. Harada et al. studied binary LCD codes with the largest minimum weight among all binary LCD codes [19]. Inspired by these latter works, we consider the bounds on LCD codes over small finite fields.

* E-mail addresses: pbbmath@126.com(B.Pang), zhushixin@hfut.edu.cn(S.Zhu), kxs6@sina.com(X.Kai). This research was supported by the National Natural Science Foundation of China under Grant Nos 61772168, 61572168 and 11501156, the Anhui Provincial Natural Science Foundation under Grant No 1508085SQA198.

In this paper, we give some background and recall some basic results in Section 2. In Section 3, we show that LCD codes are not equivalent to linear codes over small finite fields. In Sections 4, the enumeration of binary optimal LCD codes is obtained. In Sections 5 and 6, we get the exact value of $LD(n, 2)$ over \mathbb{F}_3 and \mathbb{F}_4 . In Section 7, we study the bound of LCD codes over \mathbb{F}_q .

2 Preliminaries

For any vector $\mathbf{a} = (a_1, \dots, a_n) \in \mathbb{F}_q^n$ and permutation σ of $\{1, 2, \dots, n\}$, we define $C_{\mathbf{a}}$ and $\sigma(C)$ as the following linear codes

$$C_{\mathbf{a}} = \{(a_1c_1, a_2c_2, \dots, a_nc_n) \mid (c_1, c_2, \dots, c_n) \in C\},$$

and

$$\sigma(C) = \{(c_{\sigma(1)}, c_{\sigma(2)}, \dots, c_{\sigma(n)}) \mid (c_1, c_2, \dots, c_n) \in C\}.$$

Two codes C and C' in \mathbb{F}_q^n are called equivalent if $C = \sigma(C_{\mathbf{a}})$ for some permutation σ of $\{1, 2, \dots, n\}$ and $\mathbf{a} \in (\mathbb{F}_q^*)^n$. For a matrix A over finite field, A^T denotes the transposed matrix of A and \overline{A} denotes the conjugate of A . We assume that $\det(A)$ denotes the determinant of A , where A is a square matrix. Hamming weight vector \mathbf{a} is the number of nonzero a_i , and denoted by $\text{wt}(\mathbf{a})$.

Lemma 2.1 (see [20]). *If G is a generator matrix for the $[n, k]$ linear code C , then C is an Euclidean (resp. a Hermitian) LCD code if and only if, the $k \times k$ matrix GG^T (resp. $G\overline{G}^T$) is nonsingular.*

Lemma 2.2. *Let A be a $k \times n$ matrix. Let a^1, a^2, \dots, a^n be the columns vectors of A and $\tilde{A} = [a^{\sigma(1)}, a^{\sigma(2)}, \dots, a^{\sigma(n)}]$, where σ is a permutation of $\{1, 2, \dots, n\}$. Then $\det(AA^T) = \det(\tilde{A}\tilde{A}^T)$.*

Proof. By the definition of \tilde{A} , there are primary matrixes Q_1, \dots, Q_s such that $\tilde{A} = AQ_1 \cdots Q_s$. We have

$$\det(\tilde{A}\tilde{A}^T) = \det(AQ_1 \cdots Q_s Q_s^T \cdots Q_1^T A^T) = \det(AA^T).$$

Then the proof is completed. \square

The combinatorial functions $LD(n, k)$ and $LD(n, d)$ has been introduced and studied by Dougherty et al. [22] and Galvez et al. [17]. The definitions of $LD(n, k)$ and $LD(n, d)$ as follows, we will use them frequently in the rest of this paper.

Definition 2.3. $LD(n, k) := \max\{d \mid \text{there exists an } [n, k, d] \text{ LCD code over } \mathbb{F}_q\}$.

Definition 2.4. $LD(n, d) := \max\{k \mid \text{there exists an } [n, k, d] \text{ LCD code over } \mathbb{F}_q\}$.

Let C be an $[n, k, d]$ linear code over \mathbb{F}_q and the matrix G be the generator matrix of C . Then the size of G is $k \times n$ and $\text{rank}(G) = k$. Let

$$G = \begin{bmatrix} a_{11} & a_{12} & \cdots & a_{1n} \\ a_{21} & a_{22} & \cdots & a_{2n} \\ \vdots & \vdots & \vdots & \vdots \\ a_{k1} & a_{k2} & \cdots & a_{kn} \end{bmatrix},$$

where $a_{ij} \in \mathbb{F}_q$, for $1 \leq i \leq k$ and $1 \leq j \leq n$.

Any code over \mathbb{F}_q , we have the following inequality.

Lemma 2.5. $LD(n, k) \leq \lfloor \frac{(q-1)q^{k-1}n}{(q^k-1)} \rfloor$, for $1 \leq k \leq n$.

Proof. From the Griesmer Bound [21], for any q -ary linear $[n, k, d]$ code, we have

$$n \geq \sum_{i=0}^{k-1} \lceil \frac{d}{q^i} \rceil.$$

we have $n \geq \frac{dq(q^k-1)}{(q-1)q^k}$. Hence

$$d \leq \lfloor \frac{(q-1)q^k n}{q(q^k-1)} \rfloor.$$

Therefore any $[n, k, d]$ LCD code must satisfy this inequality. \square

Lemma 2.6. Let n and k are positive integers, $k > 0$, then $LD(n+1, k) \geq LD(n, k)$

Proof. Let G be a generator matrix of an $[n, k, d]$ LCD code C over \mathbb{F}_q . Then C' with the generator matrix $G' = [G \ \mathbf{0}]$ is an LCD code since $\det(G'G'^T) = \det(GG^T) \neq 0$. Note that C' is an $[n+1, k, d]$ code. This completes the proof. \square

3 LCD codes are not equivalent to linear codes over small finite fields

In this section, we investigate the relationship between linear codes and LCD codes over small finite fields. In [20], Carlet et al. showed that an $[n, k, d]$ linear Euclidean LCD code over \mathbb{F}_q with $q > 3$ exists if and only if there is an $[n, k, d]$ linear code over \mathbb{F}_q and an $[n, k, d]$ linear Hermitian LCD code over \mathbb{F}_{q^2} with $q > 2$ exists if and only if there is an $[n, k, d]$ linear code over \mathbb{F}_{q^2} . Now we proved that this result is not true in the small finite fields, such as $\mathbb{F}_2, \mathbb{F}_3$ and \mathbb{F}_4 .

Theorem 3.1. Let C be a linear code over \mathbb{F}_2 with generator matrix G and assume C is not an Euclidean LCD code. Then C is not equivalent to any Euclidean LCD codes over \mathbb{F}_2 .

Proof. Assume C is equivalent to a linear code $\tilde{C} = \sigma(C_{\mathbf{a}})$, where σ is a permutation of $\{1, 2, \dots, n\}$ and $\mathbf{a} \in (\mathbb{F}_2^*)^n$. It is obvious that $\mathbf{a} = (1, 1, \dots, 1)$. Let G and \tilde{G} are the generator matrixes of C and C' , respectively. It is easy to know $\det(GG^T) \neq 0$, then $\det(\tilde{G}\tilde{G}^T) = 0$ from Lemma 2.2. We show that linear code \tilde{C} is not to be Euclidean LCD. \square

Theorem 3.2. Let C be a linear code over \mathbb{F}_3 with generator matrix G and assume C is not an Euclidean LCD code. Then C is not equivalent to any Euclidean LCD codes over \mathbb{F}_3 .

Proof. Assume C is equivalent to a linear code $\tilde{C} = \sigma(C_{\mathbf{a}})$, where σ is a permutation of $\{1, 2, \dots, n\}$ and $\mathbf{a} = (a_1, \dots, a_n) \in (\mathbb{F}_3^*)^n$. Let $G, G_{\mathbf{a}}$ and \tilde{G} are the generator matrixes of $C, C_{\mathbf{a}}$ and C' , respectively. The $G_{\mathbf{a}}$ is obtained from G by multiplying its j -th column by a_j for $j \in \{1, 2, \dots, n\}$, then we have $G_{\mathbf{a}}G_{\mathbf{a}}^T = GG^T$ by simple matrix operations. It is easy to know $\det(GG^T) \neq 0$, then $\det(\tilde{G}\tilde{G}^T) = \det(G_{\mathbf{a}}G_{\mathbf{a}}^T) = \det(GG^T) = 0$ from Lemma 2.2. We show that linear code \tilde{C} is not to be Euclidean LCD. \square

Theorem 3.3. Let C be a linear code over \mathbb{F}_4 with generator matrix G and assume C is not a Hermitian LCD code. Then C is not equivalent to any Hermitian LCD codes over \mathbb{F}_4 .

Proof. Assume C is equivalent to a linear code $\tilde{C} = \sigma(C_{\mathbf{a}})$, where σ is a permutation of $\{1, 2, \dots, n\}$ and $\mathbf{a} = (a_1, \dots, a_n) \in (\mathbb{F}_4^*)^n$. Let $G, G_{\mathbf{a}}$ and \tilde{G} are the generator matrixes of $C, C_{\mathbf{a}}$ and C' , respectively. The $G_{\mathbf{a}}$ is obtained from G by multiplying its j -th column by a_j for $j \in \{1, 2, \dots, n\}$ and $2^2 - 1 = 2 + 1$, then we have $G_{\mathbf{a}}\overline{G_{\mathbf{a}}}^T = G\overline{G}^T$ by simple matrix operations. It is easy to know $\det(G\overline{G}^T) = 0$, then $\det(\tilde{G}\overline{\tilde{G}}^T) = \det(G_{\mathbf{a}}\overline{G_{\mathbf{a}}}^T) = \det(G\overline{G}^T) = 0$ from Lemma 2.2. We show that linear code \tilde{C} is not to be Hermitian LCD. \square

Thus in the later section, we only consider LCD codes over $\mathbb{F}_2, \mathbb{F}_3$ and \mathbb{F}_4 .

4 The enumeration of $[n, 2, d]$ binary optimal LCD codes

In this section we consider binary codes. Recently, Galvez et al. [22] obtain the exact values of $\text{LD}(n, k)$ for $k = 2$ and arbitrary n . By Theorem 1 in [22], we know that there exist LCD codes with $\text{LD}(n, 2) = \lfloor \frac{2n}{3} \rfloor$ only for $n \equiv 1, \pm 2, 3 \pmod{6}$. An $[n, k, d]$ linear code is optimal if the minimum distance achieve the Griesmer Bound. In this section, we will give the enumeration of $[n, 2, d]$ binary optimal LCD codes for $n \equiv 1, \pm 2, 3 \pmod{6}$, where $d = \lfloor \frac{2n}{3} \rfloor$.

An $[n, k]$ linear code C over \mathbb{F}_2 with generator matrix G , Let

$$G = \begin{bmatrix} a_{11} & a_{12} & \cdots & a_{1n} \\ a_{21} & a_{22} & \cdots & a_{2n} \end{bmatrix}.$$

Let $\alpha_1 = [a_{11}, a_{12}, \dots, a_{1n}]$, $\alpha_2 = [a_{21}, a_{22}, \dots, a_{2n}]$, then

$$G = \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix}.$$

Let $\beta_l = [a_{1l}, a_{2l}]^T$ for $1 \leq l \leq n$, then $G = [\beta_1, \beta_2, \dots, \beta_n]$.

The following definition will be frequently in this section.

Definition 4.1. $S_{ij} := |\{i \mid [i, j]^T = \beta_l \mid \text{for } 1 \leq l \leq n\}|$, for $i, j \in \mathbb{F}_2$.

From this definition and notation given above, we have $C = \{0, \alpha_1, \alpha_2, \alpha_1 + \alpha_2\}$. It is easy to know

$$wt(\alpha_1) = S_{10} + S_{11}, wt(\alpha_2) = S_{01} + S_{11}, wt(\alpha_1 + \alpha_2) = S_{10} + S_{01}.$$

We also have

$$GG^T = \begin{bmatrix} S_{10} + S_{11} & S_{11} \\ S_{11} & S_{01} + S_{11} \end{bmatrix}.$$

Based on the notation given above, we can obtain the following theorems.

Theorem 4.2. *Up to equivalence, the number of $[n, 2, d]$ binary optimal LCD codes is 2, for $n \equiv 1, \pm 2 \pmod{6}$.*

Proof. (i) Let $n \equiv 1 \pmod{6}$, i.e., $n = 6t + 1$, for some positive integer t . Let the code with generator matrix G , let $\min\{wt(\alpha_1), wt(\alpha_2), wt(\alpha_1 + \alpha_2)\} \geq \lfloor \frac{2(6t+1)}{3} \rfloor = 4t$, then $(S_{01}, S_{10}, S_{11}) \in T$, where $T = \{(2t - 1, 2t + 1, 2t + 1), (2t, 2t, 2t + 1), (2t, 2t + 1, 2t), (2t + 1, 2t - 1, 2t + 1), (2t + 1, 2t, 2t), (2t + 1, 2t + 1, 2t - 1)\}$. If $(S_{01}, S_{10}, S_{11}) \in T_1$, where $T_1 = \{(2t - 1, 2t + 1, 2t + 1), (2t + 1, 2t - 1, 2t + 1), (2t + 1, 2t + 1, 2t - 1)\}$. Note that the matrix G of those codes always satisfy $\det(GG^T) \neq 0$. Therefore those codes are LCD code. But the code generator by $(S_{01}, S_{10}, S_{11}) = (2t - 1, 2t + 1, 2t + 1)$ is equivalent to the code generator by

$(S_{01}, S_{10}, S_{11}) = (2t + 1, 2t - 1, 2t + 1,)$. If $(S_{01}, S_{10}, S_{11}) \in T_2$, where $T_2 = T \setminus T_1$. Note that the matrix G of those codes always satisfy $\det(GG^T) = 0$. Therefor those codes are not LCD code. Hence, there are only two binary optimal LCD codes.

(ii) Let $n \equiv -2 \pmod{6}$, i.e., $n = 6t - 2$, for some positive integer t . The proof is similar to (i), we omit detail here. We obtain $(S_{01}, S_{10}, S_{11}) \in T$, where $T = \{(2t - 2, 2t, 2t,), (2t - 1, 2t - 1, 2t,), (2t - 1, 2t, 2t - 1,), (2t, 2t - 2, 2t,), (2t, 2t - 1, 2t - 1,), (2t, 2t, 2t - 2,)\}$. If $(S_{01}, S_{10}, S_{11}) \in T_1$, where $T_1 = \{(2t - 1, 2t - 1, 2t,), (2t - 1, 2t, 2t - 1,), (2t, 2t - 1, 2t - 1,)\}$. Note that the matrix G of those codes always satisfy $\det(GG^T) \neq 0$. Therefor those codes are LCD code. But the code generator by $(S_{01}, S_{10}, S_{11}) = (2t - 1, 2t, 2t - 1,)$ is equivalent to the code generator by $(S_{01}, S_{10}, S_{11}) = (2t, 2t - 1, 2t - 1,)$. If $(S_{01}, S_{10}, S_{11}) \in T_2$, where $T_2 = T \setminus T_1$. Note that the matrix G of those codes always satisfy $\det(GG^T) = 0$. Therefor those codes are not LCD code. Hence, there are only two binary optimal LCD codes.

(iii) Let $n \equiv 2 \pmod{6}$, i.e., $n = 6t + 2$, for some positive integer t . The proof is similar to (i), we omit detail here. We obtain $T = \{(2t, 2t + 1, 2t + 1,), (2t + 1, 2t, 2t + 1,), (2t + 1, 2t + 1, 2t,)\}$. If $(S_{01}, S_{10}, S_{11}) \in T$, note that the matrix G of those codes always satisfy $\det(GG^T) \neq 0$. Therefor those codes are LCD code. But the code generator by $(S_{01}, S_{10}, S_{11}) = (2t, 2t + 1, 2t + 1,)$ is equivalent to the code generator by $(S_{01}, S_{10}, S_{11}) = (2t + 1, 2t, 2t + 1,)$. Hence, there are only two binary optimal LCD codes. \square

Theorem 4.3. *Up to equivalence, the number of $[n, 2, d]$ binary optimal LCD codes is 1, for $n \equiv 3 \pmod{6}$.*

Proof. Let $n \equiv 3 \pmod{6}$, i.e., $n = 6t + 3$, for some positive integer t . Let the code with generator matrix G , let $\min\{wt(\alpha_1), wt(\alpha_2), wt(\alpha_1 + \alpha_2)\} \geq \lfloor \frac{2(6t+3)}{3} \rfloor = 4t + 2$, then $(S_{01}, S_{10}, S_{11}) \in T$, where $T = \{(2t - 1, 2t + 2, 2t + 2,), (2t, 2t + 1, 2t + 2,), (2t, 2t + 2, 2t + 1,), (2t + 1, 2t, 2t + 2,), (2t + 1, 2t + 1, 2t + 1,), (2t + 1, 2t + 2, 2t,), (2t + 2, 2t - 1, 2t + 2,), (2t + 2, 2t, 2t + 1,), (2t + 2, 2t + 1, 2t,), (2t + 2, 2t + 2, 2t - 1,)\}$. If $(S_{01}, S_{10}, S_{11}) \in T_1$, where $T_1 = \{(2t + 1, 2t + 1, 2t + 1,)\}$.

Note that the generator matrix G of this code satisfy $GG^T = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}$ i.e., $\det(GG^T) = 1 \neq 0$.

Therefor this code is an LCD code. If $(S_{01}, S_{10}, S_{11}) \in T_2$, where $T_2 = T \setminus T_1$. Note that the matrix G of those codes always satisfy $\det(GG^T) = 0$. Therefor those codes are not LCD code. Hence, there are only one binary optimal LCD code. \square

Theorem 4.4. *The let n be a positive integer, then*

- (1) *Suppose that n is even and $i \geq 0$. If $n > 6i + 3$, then $LK(n, n - 2i - 1) = 1$.*
- (2) *Suppose that n is odd and $i \geq 0$. If $n \geq 6i$, then $LK(n, n - 2i) = 1$.*

Proof. (1) Let C be an $[n, k, n - 2i - 1]$ LCD code over \mathbb{F}_2 with generator matrix G . If $k \geq 2$, there are an $[n, 2, n - 2i - 1]$ LCD code by Theorem 3.4 in [18]. From the Griesmer bound, we have $n \leq 6i + 3$. This is imply that there is no $[n, 2, n - 2i - 1]$ code when $n > 6i + 3$. That is, there is no such an LCD code.

If $k = 1$, because the minimum distance $n - 2i - 1$ is odd, thus we get $GG^T = 1$. There is $[n, 1, n - 2i - 1]$ LCD code by Lemma 2.1.

(2) Let C be an $[n, k, n - 2i]$ LCD code over \mathbb{F}_2 with generator matrix G . If $k \geq 2$, there are an $[n, 2, n - 2i]$ LCD code by Theorem 3.4 in [18]. From the Griesmer bound, we have $n \leq 6i$. Since $LD[6i, 2] = 4i - 1$ from Theorem 2 in [17]. Thus there is no $[6i, 2, 4i]$. This is imply that there is no $[n, 2, n - 2i - 1]$ code when $n \geq 6i$. That is, there is no such an LCD code.

If $k = 1$, because the minimum distance $n - 2i$ is odd, thus we get $GG^T = 1$. There is $[n, 1, n - 2i - 1]$ LCD code by Lemma 2.1. \square

5 The exact value of $LD(n, 2)$ over \mathbb{F}_3

In this section, we consider ternary codes and give the exact value of $LD(n, 2)$ over \mathbb{F}_3 for $k = 2$ and arbitrary n .

An $[n, k]$ linear code C over \mathbb{F}_3 with generator matrix G , Let

$$G = \begin{bmatrix} a_{11} & a_{12} & \cdots & a_{1n} \\ a_{21} & a_{22} & \cdots & a_{2n} \end{bmatrix}.$$

Let $\alpha_1 = [a_{11}, a_{12}, \dots, a_{1n}]$, $\alpha_2 = [a_{21}, a_{22}, \dots, a_{2n}]$, then

$$G = \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix}.$$

Let $\beta_l = [a_{1l}, a_{2l}]^T$ for $1 \leq l \leq n$, then $G = [\beta_1, \beta_2, \dots, \beta_n]$.

The following definition will be frequently in this section.

Definition 5.1. $S_{ij} := |\{i \mid [i, j]^T = \beta_l \text{ for } 1 \leq l \leq n\}|$, for $i, j \in \mathbb{F}_3$.

From this definition and notation given above, we have $C = \{0, \alpha_1, \alpha_2, 2\alpha_1, 2\alpha_2, \alpha_1 + \alpha_2, \alpha_1 + 2\alpha_2, 2\alpha_1 + \alpha_2, 2\alpha_1 + 2\alpha_2\}$. It is easy to know

$$\begin{aligned} wt(\alpha_1) &= wt(2\alpha_1) = \sum_{i=1}^2 \sum_{j=0}^2 S_{ij}, \quad wt(\alpha_2) = wt(2\alpha_2) = \sum_{i=0}^2 \sum_{j=1}^2 S_{ij}, \\ wt(\alpha_1 + \alpha_2) &= wt(2\alpha_1 + 2\alpha_2) = S_{01} + S_{02} + S_{10} + S_{11} + S_{20} + S_{22}, \\ wt(\alpha_1 + 2\alpha_2) &= wt(2\alpha_1 + \alpha_2) = S_{01} + S_{02} + S_{10} + S_{12} + S_{20} + S_{21}. \end{aligned}$$

We also have

$$GG^T = \begin{bmatrix} \sum_{i=1}^2 \sum_{j=0}^2 i^2 S_{ij} & \sum_{i=1}^2 \sum_{j=1}^2 ij S_{ij} \\ \sum_{i=1}^2 \sum_{j=1}^2 ij S_{ij} & \sum_{i=0}^2 \sum_{j=1}^2 j^2 S_{ij} \end{bmatrix}.$$

Based on the notation given above, we can obtain the following theorems.

Theorem 5.2. $LD(n, 2) \leq \lfloor \frac{3n}{4} \rfloor$ for $n \geq 2$

Proof. From the Lemma 2.5, let $q = 3$, and $k = 2$, we get this inequality. \square

Theorem 5.3. Let $n \geq 2$. Then $LD(n, 2) = \lfloor \frac{3n}{4} \rfloor$ for $n \equiv 1, 2 \pmod{4}$.

Proof. Let linear code C generate by G give above, we only need to show the existence of LCD code with minimum distance $d = \lfloor \frac{3n}{4} \rfloor$.

(i) Let $n \equiv 1 \pmod{4}$, i.e., $n = 4t + 1$, for some positive integer t . If t is an odd integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{10} = S_{12} = S_{21} = \frac{t+1}{2}$ and $S_{11} = S_{20} = S_{22} = \frac{t-1}{2}$. Note that this code has minimum distance $3t = \lfloor \frac{3(4t+1)}{4} \rfloor$ and $GG^T = \begin{bmatrix} 0 & 1 \\ 1 & 1 \end{bmatrix}$ i.e., $\det(GG^T) = 2 \neq 0$. Therefor this code is an LCD code. If t is an even integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{10} = S_{11} = S_{12} = \frac{t}{2}$, $S_{21} = \frac{t}{2} - 1$ and $S_{20} = S_{22} = \frac{t}{2} + 1$, Note that this code has minimum distance $3t = \lfloor \frac{3(4t+1)}{4} \rfloor$ and $GG^T = \begin{bmatrix} 1 & 2 \\ 2 & 0 \end{bmatrix}$ i.e., $\det(GG^T) = 2 \neq 0$. Therefor this code is an LCD code.

(ii) Let $n \equiv 2 \pmod{4}$, i.e., $n = 4t + 2$, for some positive integer t . If t is an odd integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{11} = S_{12} = S_{20} = S_{22} = \frac{t+1}{2}$ and $S_{10} = S_{21} = \frac{t-1}{2}$, Note that this code has minimum distance $3t + 1 = \lfloor \frac{3(4t+2)}{4} \rfloor$ and $GG^T = \begin{bmatrix} 1 & 1 \\ 1 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 1 \neq 0$. Therefor this code is an LCD code. If t is an even integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{12} = S_{20} = S_{21} = S_{22} = \frac{t}{2}$ and $S_{10} = S_{11} = \frac{t}{2} + 1$. Note that this code has minimum distance $3t + 1 = \lfloor \frac{3(4t+2)}{4} \rfloor$ and $GG^T = \begin{bmatrix} 2 & 1 \\ 1 & 1 \end{bmatrix}$ i.e., $\det(GG^T) = 1 \neq 0$. Therefor this code is an LCD code. \square

Theorem 5.4. Let $n \geq 2$. Then $LD(n, 2) = \lfloor \frac{3n}{4} \rfloor - 1$ for $n \equiv 0, 3 \pmod{4}$.

Proof. Let linear code C generate by G give above, we will show there is no LCD code with minimum distance $d = \lfloor \frac{3n}{4} \rfloor$.

(i) Let $n \equiv 0 \pmod{4}$, i.e., $n = 4t$, for some positive integer t . Let the code with generator matrix G , let $\min\{wt(\alpha_1), wt(\alpha_2), wt(\alpha_1 + \alpha_2), wt(\alpha_1 + 2\alpha_2)\} \geq \lfloor \frac{3(4t)}{4} \rfloor = 3t$, then, $wt(\alpha_1) = wt(\alpha_2) = wt(\alpha_1 + \alpha_2) = wt(\alpha_1 + 2\alpha_2) = 3t$ and $S_{01} + S_{02} = S_{10} + S_{20} = S_{11} + S_{22} = S_{12} + S_{21} = t$. Note that $GG^T = \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix}$ i.e., $\det(GG^T) = 0$. Therefor those codes are not LCD codes. Furthermore, if t is an odd integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{11} = S_{12} = \frac{t-1}{2}$ and $S_{10} = S_{20} = S_{21} = S_{22} = \frac{t+1}{2}$. Note that this code has minimum distance $3t - 1 = \lfloor \frac{3(4t)}{4} \rfloor - 1$ and $GG^T = \begin{bmatrix} 1 & 0 \\ 0 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 2 \neq 0$. Therefor this code is an LCD code. If t is an even integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{10} = S_{11} = S_{12} = S_{20} = \frac{t}{2}$, $S_{21} = \frac{t}{2} - 1$ and $S_{22} = \frac{t}{2} + 1$. Note that this code has minimum distance $3t - 1 = \lfloor \frac{3(4t)}{4} \rfloor - 1$ and $GG^T = \begin{bmatrix} 0 & 2 \\ 2 & 0 \end{bmatrix}$ i.e., $\det(GG^T) = 2 \neq 0$. Therefor this code is an LCD code.

(ii) Let $n \equiv 3 \pmod{4}$, i.e., $n = 4t+3$, for some positive integer t . Let the code with generator matrix G , let $\min\{wt(\alpha_1), wt(\alpha_2), wt(\alpha_1 + \alpha_2), wt(\alpha_1 + 2\alpha_2)\} \geq \lfloor \frac{3(4t+3)}{4} \rfloor = 3t + 2$, then, $wt(\alpha_1), wt(\alpha_2), wt(\alpha_1 + \alpha_2), wt(\alpha_1 + 2\alpha_2) \in \{3t + 2, 3t + 3\}$. (1). Let $wt(\alpha_1) = wt(\alpha_2) = 3t + 3$, then $S_{01} + S_{02} = S_{10} + S_{20} = t$, if $wt(\alpha_1 + \alpha_2) = 3t + 3$, we have $S_{12} + S_{21} = t$, then $S_{11} + S_{22} = t + 3$, we obtain $wt(\alpha_1 + 2\alpha_2) = 3t$, which is impossible. If $wt(\alpha_1 + \alpha_2) = 3t + 2$, we have $S_{12} + S_{21} = t + 1$, then $S_{11} + S_{22} = t + 2$, we obtain $wt(\alpha_1 + 2\alpha_2) = 3t + 1$, which is also impossible. (2). Let $wt(\alpha_1) = 3t + 2$, $wt(\alpha_2) = 3t + 3$, then $S_{01} + S_{02} = t + 1$, $S_{10} + S_{20} = t$, if $wt(\alpha_1 + \alpha_2) = 3t + 3$, we have $S_{12} + S_{21} = t$, then $S_{11} + S_{22} = t + 2$, we obtain $wt(\alpha_1 + 2\alpha_2) = 3t + 1$, which is impossible. If $wt(\alpha_1 + \alpha_2) = 3t + 2$, we have $S_{12} + S_{21} = t + 1$, then $S_{11} + S_{22} = t + 1$. Note that $GG^T = \begin{bmatrix} 2 & 0 \\ 0 & 0 \end{bmatrix}$ i.e., $\det(GG^T) = 0$. Therefor this code is not an LCD code. (3). Let $wt(\alpha_1) = 3t + 3$, $wt(\alpha_2) = 3t + 2$. It is similar to (2). We get $GG^T = \begin{bmatrix} 0 & 0 \\ 0 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 0$. Therefor this code is not an LCD code. (4). Let $wt(\alpha_1) = wt(\alpha_2) = 3t + 2$, then $S_{01} + S_{02} = S_{10} + S_{20} = t + 1$, if $wt(\alpha_1 + \alpha_2) = 3t + 3$, we have $S_{12} + S_{21} = t$, then $S_{11} + S_{22} = t + 1$. Note that $GG^T = \begin{bmatrix} 2 & 1 \\ 1 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 0$. Therefor this code is not an LCD code. If $wt(\alpha_1 + \alpha_2) = 3t + 2$, we have $S_{11} + S_{22} = t + 1$, then $S_{12} + S_{21} = t$. Note that $GG^T = \begin{bmatrix} 2 & 2 \\ 2 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 0$. Therefor this code is not

an LCD code. Furthermore, if t is an odd integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{10} = S_{11} = S_{12} = S_{20} = \frac{t+1}{2}$, $S_{21} = \frac{t+3}{2}$ and $S_{22} = \frac{t-3}{2}$. Note that this code has minimum distance $3t + 1 = \lfloor \frac{3(4t+3)}{4} \rfloor - 1$ and $GG^T = \begin{bmatrix} 2 & 0 \\ 0 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 1 \neq 0$. Therefore this code is an LCD code. If t is an even integer, let the code with generator matrix G , let $S_{01} = S_{02} = S_{10} = S_{11} = S_{22} = \frac{t}{2}$ and $S_{12} = S_{20} = S_{21} = \frac{t}{2} + 1$. Note that this code has minimum distance $3t + 1 = \lfloor \frac{3(4t+3)}{4} \rfloor - 1$ and $GG^T = \begin{bmatrix} 0 & 1 \\ 1 & 2 \end{bmatrix}$ i.e., $\det(GG^T) = 2 \neq 0$. Therefore this code is an LCD code. This completes the proof. \square

6 The exact value of $\text{LD}(n, 2)$ over \mathbb{F}_4

In this section, we consider quaternary codes and give the exact value of $\text{LD}(n, 2)$ over \mathbb{F}_4 for $k = 2$ and arbitrary n . Let ξ be a primitive element of \mathbb{F}_4 , i.e., $\mathbb{F}_4 = \langle \xi \rangle \cup \{0\}$.

An $[n, k]$ linear code C over \mathbb{F}_4 with generator matrix G . Let

$$G = \begin{bmatrix} a_{11} & a_{12} & \cdots & a_{1n} \\ a_{21} & a_{22} & \cdots & a_{2n} \end{bmatrix}.$$

Let $\alpha_1 = [a_{11}, a_{12}, \dots, a_{1n}]$, $\alpha_2 = [a_{21}, a_{22}, \dots, a_{2n}]$, then

$$G = \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix}.$$

Let $\beta_l = [a_{1l}, a_{2l}]^T$ for $1 \leq l \leq n$, then $G = [\beta_1, \beta_2, \dots, \beta_n]$.

The following definition will be frequently in this section.

Definition 6.1. $S_{ij} := |\{i \mid [i, j]^T = \beta_l \text{ for } 1 \leq l \leq n\}|$, for $i, j \in \mathbb{F}_4$.

From this definition and notation given above, we have $C = \{0, \alpha_1, \alpha_2, \xi\alpha_1, \xi\alpha_2, \xi^2\alpha_1, \xi^2\alpha_2, \alpha_1 + \alpha_2, \xi\alpha_1 + \xi\alpha_2, \xi^2\alpha_1 + \xi^2\alpha_2, \alpha_1 + \xi\alpha_2, \xi\alpha_1 + \xi^2\alpha_2, \xi^2\alpha_1 + \alpha_2, \alpha_1 + \xi^2\alpha_2, \xi\alpha_1 + \alpha_2, \xi^2\alpha_1 + \xi\alpha_2\}$. It is easy to know

$$wt(\alpha_1) = wt(\xi\alpha_1) = wt(\xi^2\alpha_1) = \sum_{i \in \mathbb{F}_4^*} \sum_{j \in \mathbb{F}_4} S_{ij}, wt(\alpha_2) = wt(\xi\alpha_2) = wt(\xi^2\alpha_2) = \sum_{i \in \mathbb{F}_4} \sum_{j \in \mathbb{F}_4^*} S_{ij},$$

$$wt(\alpha_1 + \alpha_2) = wt(\xi\alpha_1 + \xi\alpha_2) = wt(\xi^2\alpha_1 + \xi^2\alpha_2) = \sum_{i \in \mathbb{F}_4} \sum_{\substack{j \in \mathbb{F}_4 \\ i \neq j}} S_{ij},$$

$$wt(\alpha_1 + \xi\alpha_2) = wt(\xi\alpha_1 + \xi^2\alpha_2) = wt(\xi^2\alpha_1 + \alpha_2) = \sum_{i \in \mathbb{F}_4} \sum_{\substack{j \in \mathbb{F}_4 \\ i \neq \xi^2 j}} S_{ij},$$

$$wt(\alpha_1 + \xi^2\alpha_2) = wt(\xi\alpha_1 + \alpha_2) = wt(\xi^2\alpha_1 + \xi\alpha_2) = \sum_{i \in \mathbb{F}_4} \sum_{\substack{j \in \mathbb{F}_4 \\ i \neq \xi j}} S_{ij}.$$

Let $y_0 = S_{11} + S_{\xi\xi} + S_{\xi^2\xi^2}$, $y_1 = S_{1\xi^2} + S_{\xi 1} + S_{\xi^2\xi}$, $y_2 = S_{1\xi^2} + S_{\xi 1} + S_{\xi^2\xi}$, $y_{11} = \sum_{i \in \mathbb{F}_4^*} \sum_{j \in \mathbb{F}_4} S_{ij}$, $y_{22} = \sum_{i \in \mathbb{F}_4} \sum_{j \in \mathbb{F}_4^*} S_{ij}$. We also have

$$\overline{GG}^T = \begin{bmatrix} y_{11} & y_0 + y_1\xi + y_2\xi^2 \\ y_0 + y_2\xi + y_1\xi^2 & y_{22} \end{bmatrix}.$$

Based on the notation given above, we can obtain the following theorems.

Theorem 6.2. $LD(n, 2) \leq \lfloor \frac{4n}{5} \rfloor$ for $n \geq 2$

Proof. From the Lemma 2.5, let $q = 4$, and $k = 2$, we get this inequality. \square

Theorem 6.3. Let $n \geq 2$. Then $LD(n, 2) = \lfloor \frac{4n}{5} \rfloor$ for $n \equiv 1, 2, 3 \pmod{5}$.

Proof. It is similar to the Theorem 5.3, so we omit it. \square

Theorem 6.4. Let $n \geq 2$. Then $LD(n, 2) = \lfloor \frac{4n}{5} \rfloor - 1$ for $n \equiv 0, 4 \pmod{5}$.

Proof. It is similar to the Theorem 5.4, so we omit it. \square

7 Bound of $[n, k]$ LCD codes over \mathbb{F}_q

In this section, we consider LCD codes over \mathbb{F}_q , where $q \geq 3$. We get a relation between $LD(n, k)$ and $LD(n, k - 1)$. Let C be an $[n, k, d]$ linear code over \mathbb{F}_q and the matrix G be the generator matrix of C . Then the size of G is $k \times n$ and $\text{rank}(G) = k$. Let

$$G = \begin{bmatrix} \alpha_1 \\ \alpha_2 \\ \vdots \\ \alpha_k \end{bmatrix},$$

where $\alpha_i \in \mathbb{F}_q^n$, for $1 \leq i \leq k$.

Lemma 7.1. Let C be an $[n, k]$ LCD code over \mathbb{F}_q , where $k < n$. Then there exist a nonzero codeword $\beta \in C^\perp$ such that $\beta \cdot \beta = b \neq 0$.

Proof. If $\beta \neq 0$ and $\beta \cdot \beta = 0$. For any $\gamma \in C^\perp$, $(\beta + \gamma) \cdot (\beta + \gamma) = 0$, then $\beta \in C$. This is impossible. \square

Theorem 7.2. If $1 \leq k \leq n$, then $LD(n, k) \leq LD(n, k - 1)$.

Proof. Let C be an $[n, k - 1]$ LCD code over \mathbb{F}_q with generator matrix $G = \begin{bmatrix} \alpha_1 \\ \alpha_2 \\ \vdots \\ \alpha_{k-1} \end{bmatrix}$, where

$\alpha_i \in \mathbb{F}_q^n$, for $1 \leq i \leq k - 1$. Let $A = GG^T$, we have $\det(A) \neq 0$ by Lemma 2.1. We let C' be

a code over \mathbb{F}_q with generator matrix $G' = \begin{bmatrix} G \\ \beta \end{bmatrix} = \begin{bmatrix} \alpha_1 \\ \alpha_2 \\ \vdots \\ \alpha_{k-1} \\ \beta \end{bmatrix}$, where $\beta \in C^\perp$, $\beta \cdot \beta = b \neq 0$

by Lemma 7.1. Let $A' = G'G'^T = \begin{bmatrix} A & \mathbf{0} \\ \mathbf{0} & b \end{bmatrix}$, we have $\det(A') = b \cdot \det(A) \neq 0$. Then C' is an $[n, k]$ LCD code over \mathbb{F}_q by Lemma 2.1. It is easy to know $C \subseteq C'$, so we have $d(C) \geq d(C')$. Then $LD(n, k) \leq LD(n, k - 1)$. \square

8 Conclusion

In this paper, we show that LCD codes are not equivalent to linear codes over small finite fields. The enumeration of binary optimal LCD codes is obtained. We also get the exact value of $LD(n, 2)$ over \mathbb{F}_3 and \mathbb{F}_4 . The techniques presented in this paper can be used for bound of minimum distance with larger dimensions. We study the bound of LCD codes over \mathbb{F}_q .

References

- [1] Massey J L, Linear codes with complementary duals, *Discrete Math*, 1992, 106/107: 337-342.
- [2] Sendrier N, Linear codes with complementary duals meet the Gilbert-Varshamov bound. *Discret. Math.* 285 (2004), 345-347.
- [3] Yang X, and Massey J L, The condition for a cyclic code to have a complementary dual. *Discret. Math.* 126 (1994), 391-393.
- [4] Liu X S and Liu H, Matrix-Product Complementary Dual Codes. arXiv:1604.03774 (2016).
- [5] Ding C S, Li C J, and Li S X, LCD cyclic codes over finite fields, *IEEE Trans. Inf. Theory*, 63(2016), 4344-4356.
- [6] Gneri C, Özkaya B and Solé P, Quasi-cyclic complementary dual codes. *Finite Fields Their Appl.* 42(2016), 67-80.
- [7] Li S X, Li C J, Ding C S and Liu H, Two families of LCD BCH codes, *IEEE Trans. Inf. Theory*, 63(2017), 5699-5717.
- [8] Lina E R J and Nocon E G, On the construction of some LCD codes over finite fields, *Manila Journal of Science*, 9(2016), 67-82.
- [9] Pang, B B, Zhu S X and Sun Z H, On LCD negacyclic codes over finite fields *Journal of Systems Science and Complexity*, (2017). doi.org/10.1007/s11424-017-6301-7.
- [10] Jin, L F, Construction of MDS codes with complementary duals. *IEEE Trans. Inf. Theory*, 63(2017), 2843-2847.
- [11] Sari M and Köröglu, M E, On MDS Negacyclic LCD Codes. arXiv:1611.06371 (2016.)
- [12] Carlet C, Mesnager S, Tang C M and Qi Y F, Euclidean and Hermitian LCD MDS Codes, arXiv:1702.08033 (2017).
- [13] Carlet C, Mesnager S, Tang C M and Qi Y F, Linear Codes Over \mathbb{F}_q which are Equivalent to LCD Codes. arXiv:1703.04346 (2017).
- [14] Sok L, Shi M J, and Sole P, Construction of Optimal LCD Codes Over Larger Finite Fields, arXiv:1704.04083 (2017).
- [15] Liu X S and Liu H, LCD codes over finite chain rings. *Finite Fields Their Appl.* 34(2015) 1-19.

- [16] Rao Y, Li R H, Lv L D, Chen G and Zuo F, On binary LCD cyclic codes, *Procedia Computer Science*, 107(2017), 778-783.
- [17] Galvez L, Kim J L, Lee N, Roe Y G and Won B S, Some bounds on binary LCD codes, *Cryptogr. Commun.* (2018) 10: 719. <https://doi.org/10.1007/s12095-017-0258-1>.
- [18] Carlet C, Mesnager S, Tang C M and Qi Y F, New characterization and parametrization of LCD codes, arXiv:1709.03217, (2017).
- [19] Harada M and Saito K, Binary linear complementary dual codes, arXiv:1802.06985v1, (2018).
- [20] Carlet C, Mesnager S, Tang C and Qi Y, Linear codes over \mathbb{F}_q which are equivalent to LCD codes, arXiv:1703.04346v2 [cs.IT], (2017).
- [21] Huffman W C, and Pless V, *Fundamentals of Error-correcting Codes*, Cambridge University Press, Cambridge (2010).
- [22] Dougherty S T, Kim J-L, Ozkaya B, Sok L, and Solé P, The combinatorics of LCD codes: linear programming bound and orthogonal matrices, *Int. J. Inf. Coding Theory* 4 (2017), 116-128.