# On Extremal Index of Max-Stable Random Fields

## Enkelejd Hashorva

Department of Actuarial Science, University of Lausanne Chamberonne 1015 Lausanne, Switzerland e-mail: enkelejd.hashorva@unil.ch

**Abstract:** For a given stationary max-stable random field X(t),  $t \in \mathbb{Z}^d$  the corresponding generalised Pickands constant coincides with the classical extremal index  $\theta_X \in [0,1]$ . In this contribution we discuss necessary and sufficient conditions for  $\theta_X$  to be 0, positive or equal to 1 and also show that  $\theta_X$  is equal to the so-called block extremal index. Further, we consider some general functional indices of X and prove that for a large class of functionals they coincide with  $\theta_X$ .

MSC2020 subject classifications: Primary 60G15; secondary 60G70. Keywords and phrases: Max-stable random fields, Brown-Resnick random fields, Pickands constants, classical extremal index, block extremal index, functional index

## 1. Introduction

The connection between Pickands constant and extremal index of stationary max-stable Brown-Resnick random fields (rf's) has been initially pointed out in [16]. Calculation of Pickands constants for a general stationary max-stable rf  $X(t), t \in \mathbb{Z}^d$  has been later dealt with in [25]. Previous investigations concerned with the calculation of extremal index in the context of max-stable processes are [47, 21, 8, 9]. Recent research in [2, 51, 45, 26] has shown, contrary to the prevailing intuitions, that there are certain subtilities (if d > 1) when dealing with stationary multivariate regularly varying rf's (see e.g., [48] for the definition) and the calculation of their extremal indices. Influenced by the findings of [7], several formulas for extremal indices of stationary regularly varying time series have appeared in the literature, see e.g., [35] and the references therein. Various (less well-known) formulas have been discovered also for Pickands constants in contributions unrelated to time series modelling. For instance in sequential analysis and statistical applications [42, 43] and extremes of random fields [52, 29] just to mention a few. For large classes of Gaussian rf's extremal indices have been discussed in [24, 11, 44], see also [49, 4] for non-Gaussian cases and related results.

Without loss of generality, we shall focus on the class of max-stable rf's with Fréchet marginals. Since these are limiting rf's, see e.g., [18], our formulas

 $^{\prime}$ 

for their extremal indices are valid (with obvious modifications) also for the candidate extremal index of more general stationary regularly varying rf's (see [35] for recent findings). Studying max-stable rf's, instead of these more general rf's is also justified by Lemma 2.3 stated in Section 2 and Remark 2.4 iii). In view of the well-known de Haan characterisation given in [13], the rf X with non-degenerated marginal distributions corresponds to some non-negative spectral rf  $Z(t), t \in \mathbb{Z}^d$  having the following representation (in distribution)

$$X(t) = \max_{i>1} \Gamma_i^{-1/\alpha} Z_i(t), \quad t \in \mathbb{Z}^d, \tag{1.1}$$

where  $\Gamma_i = \sum_{k=1}^i Q_k$  with  $Q_k, k \geq 1$  unit exponential random variables (rv's) independent of  $Z_i$ 's which are independent copies of Z.

Clearly, Z is not unique since also  $\tilde{Z}(t) = RZ(t), t \in \mathbb{Z}^d$  is a spectral rf for X, provided that R is a non-negative rv independent of Z such that  $\mathbb{E}\{R^{\alpha}\} = 1$ . Note that if for some  $h \in \mathbb{Z}^d$  we have Z(h) = 1 almost surely, then in view of Balkema's lemma (stated in [14][Lem 4.1]) any spectral rf  $\tilde{Z}$  of X has the same law as Z.

We shall assume without loss of generality that for some  $\alpha \in (0, \infty)$ 

$$\mathbb{P}\left\{\max_{t\in\mathbb{Z}^d} Z(t) > 0\right\} = 1, \quad \mathbb{E}\left\{Z^{\alpha}(t)\right\} = 1, \quad t\in\mathbb{Z}^d. \tag{1.2}$$

Lemma 7.1 in Appendix shows how to construct a spectral rf Z such that the first assumption in (1.2) holds. Note that  $\mathbb{E}\{Z^{\alpha}(t)\}=1$  implies that X(t) has  $\alpha$ -Fréchet distribution function  $e^{-x^{-\alpha}}, x>0$ . This is no restriction since we are interested in stationary max-stable rf's. As in [25] define the Pickands constant (when the limit exists) with respect to the spectral rf Z by

$$\mathcal{H} = \lim_{n \to \infty} \frac{1}{n^d} \mathbb{E} \left\{ \max_{t \in [0,n]^d \cap \mathbb{Z}^d} Z^{\alpha}(t) \right\} \le \lim_{n \to \infty} \frac{1}{n^d} \sum_{t \in [0,n]^d \cap \mathbb{Z}^d} \mathbb{E} \{ Z^{\alpha}(t) \} \le 1. \quad (1.3)$$

Since the finite dimensional distributions (fidi's) of X can be calculated explicitly (see (6.1) below), if  $\mathcal{H}$  exists, then

$$\mathbb{P}\bigg\{\max_{t\in[0,n]^d\cap\mathbb{Z}^d}X(t)\leq n^dx\bigg\}=e^{-\frac{1}{n^d}\mathbb{E}\big\{\max_{t\in[0,n]^d\cap\mathbb{Z}^d}Z^\alpha(t)/x^\alpha\big\}}\to e^{-\mathcal{H}/x^\alpha}(1.4)$$

as  $n \to \infty$  is valid for all x > 0.

As argued in [16] and [25, 10] the sub-additivity of maximum functional implies that  $\mathcal{H}$  is well-defined and finite, provided that X is stationary. Consequently, in view of (1.4) the extremal index (or using the terminology of [51], the classical extremal index) of the stationary max-stable rf X (denoted below by  $\theta_X$ ) always exists, does not depend on the particular spectral rf Z but on the law of the rf X and is given by

$$\theta_X = \mathcal{H} \in [0, 1]. \tag{1.5}$$

In the special case

$$X(t) = V_t, \quad t \in \mathbb{Z}^d, \tag{1.6}$$

where  $V_t$ 's are independent  $\alpha$ -Fréchet rv's we have  $\theta_X = 1$ . We shall show that this is the only max-stable rf with unit Fréchet marginals satisfying  $\theta_X = 1$ . Using this fact and Lemma 2.3 we can construct a spectral rf Z for X, see Remark 3.7 iii).

Hereafter we shall assume for simplicity that the max-stable  $\operatorname{rf} X$  has unit Fréchet marginal distributions, i.e., below we shall consider the case

$$\alpha = 1$$
.

If the spectral rf Z is not easy to determine or  $X(t), t \in \mathbb{Z}^d$  is stationary but not max-stable, commonly the block extremal index (denoted below by  $\widetilde{\theta_X}$ ) is utilised in various applications related to extreme value analysis. Assuming for simplicity that X has unit Fréchet marginals, it is defined by (see [23, 51])

$$\widetilde{\theta_X} := \lim_{n \to \infty} \frac{\mathbb{P}\{\max_{0 \le i \le r_n, i \in \mathbb{Z}^d} X(i) > n\tau\}}{\prod_{j=1}^d r_{nj} \mathbb{P}\{X(0) > n\tau\}}$$
(1.7)

for any  $\tau > 0$  and any sequence  $r_n \in \mathbb{Z}^d, n \geq 1$  with non-decreasing integer-valued components  $r_{nj}, j \leq d$  such that  $\lim_{n \to \infty} r_{nj} = \lim_{n \to \infty} n/r_{nj}^d = \infty$  for any  $j \leq d$ . In our setting we do not need to put the last restriction. In (1.7)  $i \leq r_n$  is interpreted component-wise, i.e.,  $i_j \leq r_{nj}$  for all  $j \leq d$  components of i and  $r_n$ , respectively.

Next, we define functional indices  $\theta_{X,F}$  of X by

$$\theta_{X,F} = \mathbb{E}\{Z(0)F(Z)\} \in [0,1],$$

where  $F: E \mapsto [0,1]$  is a measurable functional with respect to the product  $\sigma$ -field  $\mathcal{E}$  on  $E := [0,\infty)^{\mathbb{Z}^d}$ .

As mentioned above different choices of Z for X are possible. In order to make the definition of  $\theta_{X,F}$  independent of the choice of Z and thus only dependent on the law of X, we shall also require that F is 0-homogeneous, i.e., F(cf) = F(f) for any c > 0,  $f \in E$ . Indeed, under this assumption we have that

$$\theta_{X,F} = \mathbb{E}\{Z(0)F(Z/Z(0))\} = \mathbb{E}\{F(\Theta_0)\},\$$

where the rf  $\Theta_h$  is defined by (hereafter  $\mathbb{I}(\cdot)$  denotes the indicator function)

$$\mathbb{P}\{\Theta_h \in A\} = \mathbb{E}\{Z(h)\mathbb{I}(Z/Z(h) \in A)\}, \quad \forall A \in \mathcal{E}. \tag{1.8}$$

It is known that for any  $h \in \mathbb{Z}^d$  the law of  $\Theta_h$  does not depend on the particular choice of the spectral rf Z and can be directly determined by X. In the case that for a spectral rf Z of X we have that Z(h) > 0 almost surely, this fact follows from Balkema's lemma. The proof for the general case follows from [25][Lem A.1], or from [50][Thm 1.1] and [31][Thm 2]. Consequently, the functional index

 $\theta_{X,F}$  depends only on the law of X. Note that for the definition of  $\theta_{X,F}$  no stationarity of X is assumed.

It is well-known that a max-stable rf X with Fréchet marginals is a multivariate regularly varying rf. For general multivariate regularly varying rf's which are not max-stable, there is no spectral process Z as in our case of max-stable X and therefore the rf's  $\Theta_h$ ,  $h \in \mathbb{Z}^d$  are defined via a conditional limit, see e.g., [18, 40] and (2.1) below. The key advantage in the framework of max-stable rf's is that  $\Theta_h$  is directly obtained by tilting a given spectral rf Z.

At this point two natural questions for a given stationary max-stable rf X arise:

**Question 1:** What is the relation between  $\theta_X$  and  $\widetilde{\theta_X}$ ?

**Question 2:** For what F is the functional index  $\theta_{X,F}$  equal to  $\theta_X$ ?

In this contribution we show that we simply have  $\theta_X = \widetilde{\theta_X}$  and then describe a large class of functionals F such that  $\theta_X = \theta_{F,X}$ . Further, we consider in some detail the cases  $\theta_X = 0$  and  $\theta_X = 1$ .

Brief organisation of the rest of the paper: In the next section we discuss some basic properties of the rf's  $\Theta_h, h \in \mathbb{Z}^d$  and then show how to construct a stationary max-stable rf X from a given rf  $\Theta^*$  which in turn is necessary equal in law with  $\Theta_0$ . In Section 3 we claim that  $\theta_X = \widetilde{\theta_X}$  for any stationary max-stable rf's X. Additionally, we give equivalent conditions that guarantee  $\theta_X > 0$  or  $\theta_X = 0$  and then present several formulas for  $\theta_X$ . Section 4 is concerned with the anti-clustering condition whereas Section 5 displays some examples. All the proofs are relegated to Section 6 which is followed by an Appendix.

## 2. Preliminaries

Unless otherwise specified we shall consider below a max-stable rf  $X(t), t \in \mathbb{Z}^d$  as in the Introduction with spectral rf Z such that  $\mathbb{E}\{Z(t)\} = 1, t \in \mathbb{Z}^d$ . Hence X(t) has unit Fréchet distribution  $e^{-1/x}, x > 0$ . We shall discuss first the case that X is non-stationary.

## 2.1. General max-stable X

The importance of the rf's  $\Theta_h, h \in \mathbb{Z}^d$  defined in (1.8) relates to the following conditional convergence results. Namely, in view of [25][Lem 2.1, A.1 & Rem 6.4] or by [18][Lem 3.5] we have that the convergence in distribution

$$X(t)/X(h)|(X(h) > u) \stackrel{d}{\to} \Theta_h(t), \quad t \in \mathbb{Z}^d,$$
 (2.1)

$$u^{-1}X(t)\Big|(X(h)>u)\stackrel{d}{\to}Y_h(t), \quad t\in\mathbb{Z}^d$$
 (2.2)

hold as  $u \to \infty$  in the product topology of  $E = [0, \infty)^{\mathbb{Z}^d}$ , where  $\Theta_h$  is defined in (1.8) and

$$Y_h(t) = R\Theta_h(t), \quad t \in \mathbb{Z}^d,$$

with R an  $\alpha$ -Pareto rv with survival function  $x^{-\alpha}, x \geq 1$  independent of any other random element (recall that we consider  $\alpha = 1$  for simplicity).

If for a given max-stable rf X if a spectral rf Z is known, it is often simpler to determine the law of  $\Theta_h$  directly via (1.8) than deriving it from (2.1). In particular, if  $\mathbb{P}\{Z(h)=1\}=1$ , then the following equality in law

$$\Theta_h \stackrel{d}{=} Z \tag{2.3}$$

is valid. Below we determine the fidi's of  $Y_h$  in terms of Z and  $\Theta_h$ .

**Lemma 2.1.** For any  $h, t_i \in \mathbb{Z}^d, x_i \in (0, \infty), i \leq n$  we have

$$\mathbb{P}\{Y_h(t_1) \le x_1, \dots, Y_h(t_n) \le x_n\} = \mathbb{E}\left\{\max\left(1, \max_{1 \le i \le n} \frac{\Theta_h(t_i)}{x_i}\right) - \max_{1 \le i \le n} \frac{\Theta_h(t_i)}{x_i}\right\} (2.4)$$

$$= \mathbb{E}\left\{\max\left(Z(h), \max_{1 \le i \le n} \frac{Z(t_i)}{x_i}\right) - \max_{1 \le i \le n} \frac{Z(t_i)}{x_i}\right\}.$$

**Remark 2.2.** For the case of the stationary Brown-Resnick model (2.4) is stated in [51][Prop 6.1] for h = 0.

## 2.2. Stationary max-stable X

In view of [25] [Thm 6.9] the max-stable rf X(t),  $t \in \mathbb{Z}^d$  with unit Fréchet marginals is stationary, if and only if

$$\mathbb{E}\{Z(h)F(Z)\} = \mathbb{E}\{Z(0)F(B^hZ)\}, \quad \forall h \in \mathbb{Z}^d$$
 (2.5)

is valid for any measurable function  $F: E \mapsto [0, \infty]$  which is 0-homogeneous. Here B is the shift-operator so that  $B^h Z(\cdot) = Z(\cdot - h), h \in \mathbb{Z}^d$ . Note that for the stationary Brown-Resnick model the claim in (2.5) is first formulated in [16][Lem 5.2].

For notational simplicity we shall omit the subscript 0 and write simply  $\Theta$  and Y instead of  $\Theta_0$  and  $Y_0$ , respectively; in our notation the origin of  $\mathbb{R}^k, k \in \mathbb{N}$  is denoted by 0.

In view of [25] [Thm 4.3] condition (2.5) is equivalent with the following equality in law

$$\Theta_h \stackrel{d}{=} B^h \Theta$$

valid for any  $h \in \mathbb{Z}^d$ .

Yet another equivalent formulation of condition (2.5) stated for the rf  $\Theta$  is

$$\mathbb{E}\{\Theta(h)F(\Theta)\} = \mathbb{E}\{F(B^h\Theta)\mathbb{I}(B^h\Theta(0) \neq 0)\}, \quad \forall h \in \mathbb{Z}^d$$
 (2.6)

valid again for all measurable functionals F as above, see e.g., [2, 18].

We note in passing that with the same arguments as in [18] it can be shown that (2.6) is equivalent to the so-called time-change formula derived in [2] for multivariate regularly varying rf's.

Next, since for stationary X we have that (2.2) holds, then in view of [2, 18] X is a multivariate regularly varying rf and Y is the so-called tail rf of X, whereas  $\Theta$  is the so-called spectral tail rf. Therefore for a stationary max-stable rf X the rf  $\Theta$  defined in (1.8) is simply the spectral tail rf of X.

Adopting the terminology of [28] for stationary max-stable rf's X, we shall refer to their spectral rf's Z as Brown-Resnick stationary (abbreviated as BRs) rf's.

From Z we can easily define the spectral tail rf  $\Theta$ . Moreover, as mentioned in (2.3) we simply have  $\Theta \stackrel{d}{=} Z$  if Z(0) = 1 almost surely. The key properties of BRs rf's Z and spectral tail rf's  $\Theta$  are the TSF (2.5) and the identity (2.6), respectively. This is revealed by our next result, which shows how to construct a BRs rf Z from a given rf  $\Theta^*$  that satisfies (2.6) and  $\Theta^*(0) = 1$  almost surely, extending thus [27][Thm 4.2] to rf's.

Let in the following

$$\mathcal{I}_{fm}(p \cdot Y) = \min(i \in \mathbb{Z}^d : \max_{j \in \mathbb{Z}^d} |p_j Y(j)| = |p_i Y(i)|),$$

where  $p_j's$  are non-negative numbers such that  $\sum_{j\in\mathbb{Z}^d} p_j^{\alpha} = 1$  (recall  $\alpha = 1$  in our case).

Hereafter N is a rv independent of any other random element such that  $\mathbb{P}\{N=j\}=p_j>0, j\in\mathbb{Z}^d$ . Further, both min and max are defined with respect to a translation-invariant order on  $\mathbb{Z}^d$ , see [2] for the definition.

**Lemma 2.3.** If  $Y(t) = R\Theta^*(t), t \in \mathbb{Z}^d$  with R a unit Pareto rv independent of  $\Theta^*$  which satisfies (2.6) and  $\Theta^*(0) = 1$  almost surely, then  $Z_N$  given by

$$Z_N(t) = \frac{B^N Y(t)}{\max_{i \in \mathbb{Z}^d} p_i B^N Y(i)} \mathbb{I}(\mathcal{I}_{fm}(p \cdot B^N Y) = N), \quad t \in \mathbb{Z}^d$$
 (2.7)

is a spectral rf of some stationary max-stable  $rfX(t), t \in \mathbb{Z}^d$  with unit Fréchet marginals. Moreover, the spectral tail  $rf \Theta$  of X has the same law as  $\Theta^*$ .

Remark 2.4. i) In case  $\alpha \neq 1$  the above construction is still valid by substituting the denominator with  $(\max_{i \in \mathbb{Z}^d} p_i^{\alpha} B^N Y(i))^{1/\alpha}$ . In fact, (2.7) is a minor modification of the construction given in [18][Prop 2.12]. The other known constructions in [27, 35, 18] can be easily extended for the case d > 1, we omit the details.

ii) A  $\mathbb{R}^q$ -valued  $rf \Theta(t), t \in \mathbb{Z}^d$  is called a spectral tail rf if it satisfies (2.6) where  $\Theta(h), \Theta(-h)$  are substituted by  $\|\Theta(h)\|, \|\Theta(-h)\|$  with  $\|\cdot\|$  a norm on  $\mathbb{R}^q$  and F is redefined accordingly and further  $\mathbb{P}\{\|\Theta(0)\| = 1\} = 1$ , see e.g., [3, 35, 2]. For such a rf, a BRs rf  $Z_N$  can be determined as in (2.7) by changing  $\sum_{t \in \mathbb{Z}^d} p_t B^N Y(t)$  to  $\sum_{t \in \mathbb{Z}^d} p_t B^N \|Y(t)\|$  and instead of  $\max_{t \in \mathbb{Z}^d} p_t B^N Y(t)$  and  $p \cdot B^N Y$  putting  $\max_{t \in \mathbb{Z}^d} p_t B^N \|Y(t)\|, p \cdot B^N \|Y(t)\|$ , respectively (with  $Y(t) = R\Theta(t)$  and R a unit Pareto rv independent of  $\Theta$ ).

## 3. Classical, block & functional indices

As mentioned in the Introduction the classical extremal index  $\theta_X$  of a stationary max-stable rf X always exists. We show first that it is equal to the block extremal index  $\widetilde{\theta_X}$  defined in (1.7) and then answer the question when  $\theta_X = 0$ . This is already known for d = 1, see [10]. Our main findings in Theorem 3.6 gives several formulas for  $\theta_X$ . The next result is a minor generalisation of the case d = 1 stated in [20].

**Lemma 3.1.** If  $X(t), t \in \mathbb{Z}^d$  is a stationary max-stable rf, then  $\theta_X = \widetilde{\theta_X}$ .

Below we slightly modify the definition of anchoring maps introduced in [2]. Write next  $\bar{\mathbb{Z}}^d$  for  $\mathbb{Z}^d \cup \{\infty\}$  and recall that  $E = [0, \infty)^{\mathbb{Z}^d}$  is equipped with the product  $\sigma$ -field  $\mathcal{E}$ .

**Definition 3.2.** We call a measurable map  $\mathcal{I}: E \mapsto \overline{\mathbb{Z}}^d$  anchoring if for  $O = \{f \in E : \mathcal{I}(f) \in \mathbb{Z}^d\}$  the following conditions are satisfied for all  $f \in O, i \in \mathbb{Z}^d$ :  $i) \mathcal{I}(f) = i$  implies  $f(i) \geq \min(f(0), 1)$ ;  $ii) \mathcal{I}(f) = \mathcal{I}(B^i f) - i$ .

As in [2] we define two important anchoring maps which are specified with respect to a translation-invariant order on  $\mathbb{Z}^d$ . In particular the minimum and maximum below are with respect to such an order. An instance of a translation-invariant order is the lexicographical one. Hereafter  $\mathcal{S}(f) = \sum_{t \in \mathbb{Z}^d} f^{\alpha}(t)$  for any  $f \in E$ . Note that apart from Section 5.2 we have considered for simplicity only the case  $\alpha = 1$ .

**Example 1.** Let the non-empty set  $O \in \mathcal{E}$  be given by

$$O = \left\{ f \in E : \mathcal{S}(f) < \infty, \quad \max_{i \in \mathbb{Z}^d} f(i) > 0 \right\}$$

and define the first maximum functional

$$\mathcal{I}_{fm}(f) = \min \Big( j \in \mathbb{Z}^d : f(j) = \max_{i \in \mathbb{Z}^d} f(i) \Big), \quad f \in O,$$

where  $\mathcal{I}_{fm}(f) = \infty$  if  $f \notin O$ . Clearly,  $\mathcal{I}_{fm}(f)$  is finite for  $f \in O$  and condition i) holds by the definition, whereas condition ii) follows by the invariance (in the sense of [51]) of the translation-invariant order.

The first and last maximum functionals are important since they are both anchoring and 0-homogeneous. Moreover, for a stationary max-stable rf  $X(t), t \in \mathbb{Z}^d$  with spectral rf  $\Theta$  and Fréchet marginals  $\Phi(x) = e^{-1/x^{\alpha}}, x > 0$  we have that the law of X is specified by  $\mathcal{I}_{fm}$  and  $\Theta$  as follows

$$-\ln \mathbb{P}\{X(i) \le x_i, i \in \mathbb{Z}^d\} = \sum_{i \in \mathbb{Z}^d} \frac{1}{x_i^{\alpha}} \mathbb{P}\{\mathcal{I}_{fm}(\Theta/(B^{-i}x)) = 0\}$$
 (3.1)

for any  $x = (x_i)_{i \in \mathbb{Z}^d}$  with finitely many positive components and the rest equal to  $\infty$ ; here  $\Theta/(B^{-i}x) = (\Theta(j)/x_{j+i})_{j \in \mathbb{Z}^d}$ . The proof of (3.1) is displayed in Appendix, see also [25][Eq. (6.10)]. Note in passing that (3.1) shows that the law

of X is uniquely determined by  $\Theta$ .

**Example 2.** Define the first exceedance functional by

$$\mathcal{I}_{fe}(f) = \min(j \in \mathbb{Z}^d : f(j) > 1), \quad f \in O$$

and set  $\mathcal{I}_{fe}(f) = \infty$  if  $f \notin O$ , where

$$O = \left\{ f \in E : \mathcal{S}(f) < \infty, \quad \max_{t \in \mathbb{Z}^d} f(t) > 1 \right\} \in \mathcal{E}.$$

Clearly,  $\mathcal{I}_{fe}(f)$  for  $f \in O$  is finite and i) holds. Moreover since  $\mathcal{I}_{fe}(f)$ ,  $f \in O$  is determined by a finite number of points in a neighbourhood of 0, then  $\mathcal{I}_{fe}$  is measurable. Again condition ii) is implied by the translation-invariance of the chosen order on  $\mathbb{Z}^d$ .

We call a measurable map  $F: E \mapsto [0, \infty]$  shift-invariant if  $F(B^h f) = F(f), h \in \mathbb{Z}^d, f \in E$ .

**Lemma 3.3.** Let  $\Theta(t), t \in \mathbb{R}^d$  be a real-valued rf satisfying (2.6) with  $\Theta(0) = 1$  almost surely. If R is a unit Pareto rv independent of  $\Theta$ , then for any two anchoring maps  $\mathcal{I}, \mathcal{I}'$  and any shift-invariant map F we have (set  $Y(t) = R\Theta(t), t \in \mathbb{Z}^d$ )

$$\mathbb{P}\{\mathcal{I}(Y) = 0, \mathcal{I}'(Y) \in \mathbb{Z}^d, F(Y) < \infty\} = \mathbb{P}\{\mathcal{I}'(Y) = 0, \mathcal{I}(Y) \in \mathbb{Z}^d, F(Y) < \infty\}. \tag{3.2}$$

Moreover,  $\mathbb{P}{\mathcal{I}(Y) = 0, F(Y) < \infty} = 0$  is equivalent with  $\mathbb{P}{\mathcal{I}(Y) \in \mathbb{Z}^d, F(Y) < \infty} = 0$ .

**Remark 3.4.** If  $\mathcal{I}(Y), \mathcal{I}'(Y)$  are almost surely in  $\mathbb{Z}^d$ , then (3.2) boils down to  $\mathbb{P}\{\mathcal{I}'(Y) = 0\} = \mathbb{P}\{\mathcal{I}(Y) = 0\}$ , which is already shown in [2][Lem 3.5]. In general,  $\mathcal{I}(Y)$  might not be finite almost surely.

Hereafter we consider anchoring maps  $\mathcal{I}: E \mapsto \bar{\mathbb{Z}}^d$  such that

$$\mathbb{P}\{\mathcal{I}(Y) \in \mathbb{Z}^d, \mathcal{S}(Y) < \infty\} = \mathbb{P}\{\mathcal{S}(Y) < \infty\},\tag{3.3}$$

which is in particular valid for both first (last) maximum and first (last) exceedance functionals.

**Lemma 3.5.** If  $X(t), t \in \mathbb{Z}^d$  is a stationary max-stable rf with some spectral rf Z and spectral tail rf  $\Theta$ , then  $\theta_X = 0$  if and only if  $\mathbb{P}\{S(\Theta) = \infty\} = \mathbb{P}\{S(Z) = \infty\} = 1$ . If further the anchoring map Z satisfies (3.3), then  $\theta_X = 0$  is equivalent with

$$\mathbb{P}\{\mathcal{I}(Y) = 0, \mathcal{S}(Y) < \infty\} = 0. \tag{3.4}$$

Since the first and last maximum functionals are 0-homogeneous and finite on the set  $O = \{f \in E : \mathcal{S}(f) < \infty, \max_{i \in \mathbb{Z}^d} f(i) > 0\}$  we have that  $\mathbb{P}\{\mathcal{S}(Z) = \infty\} = 1$  is equivalent with

$$\mathbb{P}\{\mathcal{I}_{fm}(Z) \not\in \mathbb{Z}^d\} = 1$$

and the same also holds for the last maximum functional.

In view of Lemma 3.5, Lemma 7.2 and [19]  $\theta_X = 0$  is equivalent with  $\mathbb{P}\{S(Z) = \infty\} = 1$ . Further we have the following equivalent statements (below  $\|\cdot\|$  is a norm on  $\mathbb{R}^d$ ):

**A1**:  $Z(t) \to 0$  almost surely as  $||t|| \to \infty$ ;

**A2**:  $\Theta(t) \to 0$  almost surely as  $||t|| \to \infty$ ;

**A3**:  $S(Z) < \infty$  almost surely;

**A4**:  $S(\Theta) < \infty$  almost surely.

The equivalence of  $\mathbf{A1}$  and  $\mathbf{A3}$  is shown in [19], whereas the equivalence of  $\mathbf{A1}$  and  $\mathbf{A2}$  is a direct consequence of Lemma 7.2 and similarly for the equivalence of  $\mathbf{A3}$  and  $\mathbf{A4}$ . The equivalence  $\mathbf{A2}$  and  $\mathbf{A4}$  follows from [27] and [51]. Note further that  $Y(t) = R\Theta(t) \to 0$  almost surely as  $||t|| \to \infty$  is equivalent with  $\mathbf{A2}$  and  $\mathcal{S}(Y) = R\mathcal{S}(\Theta) < \infty$  almost surely is equivalent with  $\mathbf{A4}$ .

We state next the main result of this section; define in the following  $\mathcal{B}(Y) = \sum_{t \in \mathbb{Z}^d} \mathbb{I}(Y(t) > 1)$  and interpret 0: 0 and  $\infty: \infty$  as 0.

**Theorem 3.6.** Let  $\mathcal{I}, X$  be as in Lemma 3.5. If  $\mathcal{I}$  satisfies (3.3) and  $\mathbb{P}\{\mathcal{S}(\Theta) < \infty\} > 0$ , then

$$\theta_X = \mathbb{P}\{\mathcal{I}(Y) = 0, \mathcal{S}(Y) < \infty\}$$
 (3.5)

$$= \mathbb{P}\{\mathcal{I}_{fe}(Y) = 0\} \tag{3.6}$$

$$= \mathbb{P}\{\mathcal{I}_{fm}(\Theta) = 0\} \tag{3.7}$$

$$= \mathbb{P}\{\mathcal{I}(\Theta) = 0, \mathcal{S}(\Theta) < \infty\}$$
 (3.8)

$$= \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^d} \Theta(t)}{\sum_{t \in \mathbb{Z}^d} \Theta(t)}\right\}$$
(3.9)

$$= \mathbb{E}\left\{Z(0)\frac{\max_{t \in \mathbb{Z}^d} Z(t)}{\sum_{t \in \mathbb{Z}^d} Z(t)}\right\}$$
(3.10)

$$= \mathbb{E}\left\{\frac{1}{\mathcal{B}(Y)}\right\},\tag{3.11}$$

where (3.8) holds if further  $\mathcal{I}$  is 0-homogeneous. Moreover  $\{\mathcal{B}(Y) < \infty\} = \{\mathcal{S}(Y) < \infty\}$  almost surely and in particular  $\theta_X = 1$  if and only if  $\Theta(i) = 0$  almost surely for all  $i \in \mathbb{Z}^d$ ,  $i \neq 0$ .

Remark 3.7. i)  $\Theta(t) = \Theta_1(t_1)\Theta_2(t_2), t_1 \in \mathbb{Z}^k, t_2 \in \mathbb{Z}^m, t = (t_1, t_2) \in \mathbb{Z}^d$  with  $\Theta_1, \Theta_2$  independent rf's satisfying (2.6) and  $\mathbb{P}\{\Theta_i(0) = 1\} = 1, i = 1, 2$ , then (3.9) implies that  $\theta_X = \theta_{X_1}\theta_{X_2}$  where  $X, X_i, i = 1, 2$  are stationary max-stable rf's with spectral rf  $\Theta$  and  $\Theta_i, i = 1, 2$ , respectively.

ii) For d=1 and  $\theta_X=1$  the claim that  $\Theta(i)=0, i\neq 0$  in Theorem 3.6 follows also from [30]/Prop 2.2 (ii)].

iii) Since  $\Theta$  uniquely defines X, then Theorem 3.6 implies that the only stationary max-stable rf X such that  $\theta_X = 1$  is that given by (1.6). In view of (2.1)  $\Theta(i) = 0, i \neq 0$  and hence by (2.7)

$$Z_N(t) = \frac{1}{n_t} \mathbb{I}(N=t), \quad t \in \mathbb{Z}^d$$

is a spectral rf for X specified in (1.6), where N is a discrete rv with positive probability mass function  $p_t > 0, t \in \mathbb{Z}^d$ .

- iv) Taking  $F(f) = \mathbb{I}(\mathcal{I}(f) = 0, \mathcal{S}(f) < \infty)$ , then (3.8) implies  $\theta_X = \theta_{X,F}$  under the further assumption that  $\mathcal{I}$  is a 0-homogeneous functional satisfying (3.3).
- v) It follows from the proof of Theorem 3.6 that (3.11) holds without the assumption that  $\mathbb{P}\{S(\Theta) < \infty\} > 0$ . Hence  $\theta_X = 0$  if and only if  $\mathcal{B}(Y) = \infty$  almost surely. Further, from Theorem 3.6 we have that **A1**, **A2**, **A3** and **A4** are equivalent with **A5**:  $\mathcal{B}(Y) < \infty$  almost surely.
- iv) Formula (3.9) appears initially as extremal index in [38, 39] and in [17] as Pickands constant.

### 4. The anti-clustering condition

Since stationary max-stable rf's with Fréchet marginals are multivariate regularly varying (see for more details [2]) the classical extremal index of those rf's can be calculated using the findings of [2] and [51]. In the framework of stationary multivariate regularly varying rf's the anti-clustering condition of [7] plays a crucial role for the calculation of extremal index. Considering the stationary max-stable rf  $X(t), t \in \mathbb{Z}^d$  with unit Fréchet marginals, in view of [2] the aforementioned condition reads as follows:

**Condition C**: Suppose that there exists a positive sequence of non-decreasing integers  $r_n \to \infty$  as  $n \to \infty$  and  $\lim_{n \to \infty} r_n^d/n = 0$  such that for any s > 0

$$\lim_{m \to \infty} \limsup_{n \to \infty} \mathbb{P} \left\{ \max_{m < \|t\| < r_n, t \in \mathbb{Z}^d} X(t) > ns | X(0) > ns \right\} = 0.$$

The equivalence of Condition C and  $\mathbb{P}\{S(\Theta) < \infty\} = 1$  for the case d = 1 is known, see [18]. The case  $d \geq 1$  of Brown-Resnick model is dealt with in [51][Prop 6.2]. Next we show that this equivalence holds for a general stationary max-stable rf X with spectral tail rf  $\Theta$  and spectral rf Z.

**Lemma 4.1.** The anti-clustering Condition C for X is equivalent with Ai, i = 1, ..., 5.

If  $\mathbb{P}\{S(\Theta) < \infty\} = 1$  or equivalently Condition C holds, then by [2] Lemma 3.1, Lemma 4.1 and [2][Prop 5.2] for any anchoring map  $\mathcal{I}$ 

$$\theta_X = \mathbb{P}\{\mathcal{I}(Y) = 0\} = \mathbb{P}\{\mathcal{I}_{fm}(Y) = 0\} = \mathbb{P}\{\mathcal{I}_{fm}(\Theta) = 0\} \in (0, 1],$$
 (4.1)

provided that  $\mathbb{P}\{\mathcal{I}(Y) \in \mathbb{Z}^d\} = 1$ . In the special case  $\mathcal{I} = \mathcal{I}_{fe}$  (as shown already in [2])

$$\theta_X = \mathbb{P}\{\max_{0 < t} Y(t) \le 1\}. \tag{4.2}$$

Here  $\prec$  denotes a translation-invariant order on  $\mathbb{Z}^d$ .

<sup>'</sup> 11

Remark 4.2. The expression in (4.2) is a well-known formula in the Gaussian setup and has appeared in numerous papers inspired by [1]. This special formula for the Gaussian setup is also referred to as Albin's constant, see [17]. In the context of stationary regularly varying time series the same formula has appeared in [3].

Next, consider the case that Condition C does not hold, i.e.,  $p = \mathbb{P}\{S(\Theta) < \infty\} \in (0,1)$  and define the rf's  $\Theta_1 = \Theta|(S(\Theta) < \infty)$  and  $\Theta_2 = \Theta|(S(\Theta) = \infty)$ . In view of [19][Thm 9, Prop 10], for two independent stationary max-stable rf's  $\eta_i(t), t \in \mathbb{Z}^d, i = 1, 2$  with unit Fréchet marginals and corresponding spectral tail rf's equal in law to  $\Theta_i, i = 1, 2$  we have that X has the same law as

$$\max(p\eta_1(t), (1-p)\eta_2(t)), \quad t \in \mathbb{Z}^d.$$
 (4.3)

Since  $\eta_1$  satisfies Condition C, then by [51][Prop 5.2], Lemma 3.1, (4.1) and Theorem 3.6

$$\theta_X = p\mathbb{P}\{\mathcal{I}_{fm}(\Theta_1) = 0\} = p\theta_{n_1} \in (0, 1].$$
 (4.4)

Alternatively, since by the stationarity of X we have that  $\theta_X$  exists and moreover  $\theta_{\eta_2} = 0$ , then Lemma 7.5 implies that  $\theta_X = p\theta_{\eta_1}$ . Consequently, we conclude that Condition C, Lemma 7.5, representation (4.3) together with the findings of [2] establish the validity of the first four expressions in Theorem 3.6. We remark that from the above arguments, by (4.2) and Lemma 2.1 we obtain

$$\theta_X = \mathbb{E} \left\{ \max_{0 \le t} \Theta(t) - \max_{0 < t} \Theta(t); S(\Theta) < \infty \right\}$$
$$= \mathbb{E} \left\{ \max_{0 \le t} Z(t) - \max_{0 < t} Z(t); S(Z) < \infty \right\}.$$

The first formula above is already obtained for the Brown-Resnick model (see Section 5) in [51][Corr 6.3] and for the case d=1 in [20][Thm 2.1].

# 5. Examples

We present below some examples starting first with the Brown-Resnick model. The second example and Lemma 2.3 show in particular how to construct stationary max-stable rf's starting from any  $\alpha$ -summable deterministic sequence. We then discuss how to construct from some given rf a stationary max-stable rf X such that  $\theta_X$  equals a given constant.

## 5.1. Brown-Resnick model

Consider  $Z(t) = e^{W(t) - \sigma^2(t)/2}$ ,  $t \in \mathbb{Z}^d$  with  $W(t), t \in \mathbb{Z}^d$  a centered Gaussian rf with variance function  $\sigma^2$  which is not identical to 0 and  $\sigma(0) = 0$ . Let  $X(t), t \in \mathbb{Z}^d$  denote a max-stable rf with spectral rf Z. The case W is a standard

Brownian motion and d = 1 is investigated in [6] and therefore this construction is referred to as the Brown-Resnick model.

For any fixed  $h \in \mathbb{Z}^d$  the Gaussian rf (set  $\gamma(s,t) = Var(W(t) - W(s)), s, t \in \mathbb{Z}^d$ )

$$S_h(t) = W(t) - W(h) - \gamma(h, t)/2, \quad \forall t \in \mathbb{Z}^d$$

is such that  $S_h(h)=0$  almost surely and has variance function  $\sigma_h^2(t)=\gamma(h,t)$ . With the same arguments as in [25], it follows that  $Z_h(t)=e^{S_h(t)}, t\in\mathbb{Z}^d$  is also a spectral rf for X for any  $h\in\mathbb{Z}^d$ . Since  $S_h(t), t\in\mathbb{Z}^d$  is a Gaussian rf with variance  $Var(W(t)-W(h))=\gamma(t,h)$ , then the law of X depends only on  $\gamma(h,t)$  and not on  $\sigma^2$ . If we assume that W has stationary increments, then (2.5) implies that X is a stationary max-stable rf. The fact that  $Z_h(h)=1$  for any  $h\in\mathbb{Z}^d$  almost surely implies that  $\Theta:=\Theta_0$  defined in (1.8) is simply given by  $\Theta(t)=Z(t), t\in\mathbb{Z}^d$  and hence (recall  $Y=R\Theta$ )

$$Y(t) = e^{\widetilde{W}(t) + Q}, \quad \widetilde{W}(t) = W(t) - \sigma^2(t)/2, \quad t \in \mathbb{Z}^d,$$

where  $Q = \ln R$  is a unit exponential rv independent of W.

For an N(0,1) rv V with distribution  $\Phi$  being independent of Q and all  $c > 0, x \in \mathbb{R}$  (set  $\bar{\Phi} = 1 - \Phi, V_c = cV - c^2/2$ )

$$\mathbb{P}\{V_c + Q > x\} = \mathbb{P}\{V_c + Q > x, V_c > x\} + \mathbb{P}\{V_c + Q > x, V_c \le x\} 
= \mathbb{P}\{V_c > x\} + e^{-x} \mathbb{E}\{e^{V_c} \mathbb{I}(V_c \le x)\} 
= \mathbb{P}\{V_c > x\} + e^{-x} \mathbb{P}\{cV \le x - c^2/2\},$$
(5.1)

where we used that the exponentially tilted rv U defined by  $\mathbb{P}\{U \leq x\} = \mathbb{E}\{e^{V_c}\mathbb{I}(V_c \leq x)\}, x \in \mathbb{R} \text{ has } N(c^2/2, c^2) \text{ distribution, see e.g., [25][Lem 7.1]. Consequently, for all <math>t \in \mathbb{Z}^d$  such that  $c := \sigma(t) > 0$  and all y > 0

$$\mathbb{P}\{Y(t) \le y\} = \Phi(c^{-1} \ln y + c/2) - e^{-1/y} \Phi(c^{-1} \ln y - c/2), \quad (5.2)$$

which agrees with the claim of [51][Prop 6.1] where the stationary case is considered.

Next, under the assumption that W has stationary increments, in view of (3.9) and (3.11)

$$\theta_X = \mathbb{E}\left\{\frac{1}{\sum_{t \in \mathbb{Z}^d} \mathbb{I}(\widetilde{W}(t) + Q > 0)}\right\} = \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^d} e^{\widetilde{W}(t)}}{\sum_{t \in \mathbb{Z}^d} e^{\widetilde{W}(t)}}\right\}, \quad (5.3)$$

which yields the following lower bound

$$\theta_{X} = \mathbb{E}\left\{\frac{1}{\sum_{t \in \mathbb{Z}^{d}} \mathbb{I}(\widetilde{W}(t) + Q > 0)}\right\} \geq \frac{1}{\mathbb{E}\left\{\sum_{t \in \mathbb{Z}^{d}} \mathbb{I}(\widetilde{W}(t) + Q > 0)\right\}}$$

$$= \frac{1}{\sum_{t \in \mathbb{Z}^{d}} \mathbb{P}\left\{\widetilde{W}(t) + Q > 0\right\}}$$

$$= \frac{1}{\sum_{t \in \mathbb{Z}^{d}} \bar{\Phi}(\sigma^{2}(t)/2)},$$
(5.4)

where we used Fubini theorem for the first equality and (5.1) implies (5.4). The lower bound above is strictly positive under some growth conditions on  $\sigma$ , see [12] for similar calculations in the continuous case. Derivation of a tight positive lower bound is of general interest since in most of the cases direct evaluation of  $\theta_X$  is not feasible.

It is of some interest to compare two different extremal indices of stationary max-stable Brown-Resnick rf's for different variance functions. With similar arguments as in [10][Thm 3.1] we can prove the following result:

**Lemma 5.1.** Let  $X_1(t), t \in \mathbb{Z}^d$  and  $X_2(t), t \in \mathbb{Z}^d$  be two stationary max-stable Brown-Resnick rf's corresponding to two centered Gaussian processes  $W_1, W_2$  with stationary increments, continuous trajectories and variance functions  $\sigma_1^2$  and  $\sigma_2^2$  which vanish at the origin. If  $\sigma_1(t) \geq \sigma_2(t)$  holds for all  $t \in \mathbb{Z}^d$ , then  $\theta_{X_1} \geq \theta_{X_2}$ .

Remark 5.2. i) Under the conditions of Lemma 5.1

$$\mathbb{E}\left\{\frac{1}{\sum_{t\in\mathbb{Z}^d}\mathbb{I}(\widetilde{W}_1(t)+Q>0)}\right\} \geq \mathbb{E}\left\{\frac{1}{\sum_{t\in\mathbb{Z}^d}\mathbb{I}(\widetilde{W}_2(t)+Q>0)}\right\}.$$

ii) The calculation of  $\theta_X$  and different expressions for it have appeared in the literature in various contexts: the most prominent one concerns extremes of Gaussian rf's where in fact  $\widetilde{\theta_X}$  has been originally calculated, see e.g., [34, 15, 29]. The first expression in (5.3) for the continuous setup, d=1 and the fractional Brownian motion case is obtained in [5][Thm 10.5.1]. Applications to sequential analysis and statistics have given rise to various forms of formula (5.3), see e.g., [41, 32]. As already shown in [17] (5.3) is useful for simulations of  $\theta_X$ .

## 5.2. $\Theta$ generated by summable sequences

Let  $c_i, i \in \mathbb{Z}^d$  be non-negative constants satisfying  $\sum_{i \in \mathbb{Z}^d} c_i^{\alpha} = C \in (0, \infty)$  for some  $\alpha > 0$  and define

$$\Theta(i) = \frac{c_{i+S}}{c_S}, \quad i \in \mathbb{Z}^d$$

for a given rv S with values in  $\mathbb{Z}^d$  satisfying

$$\mathbb{P}\{S=i\} = c_i^{\alpha}/C, \quad i \in \mathbb{Z}^d.$$

Clearly,  $\Theta(0) = 1$  almost surely and moreover  $\Theta$  satisfies (2.6) stated for the case  $\alpha > 0$  as below, namely for any  $h \in \mathbb{Z}^d$ 

$$\mathbb{E}\{\Theta^{\alpha}(h)F(\Theta)\} = \mathbb{E}\{c_{h+S}^{\alpha}/c_{S}^{\alpha}\mathbb{I}(c_{S} \neq 0)F(c_{\cdot+S})\}$$
$$= \frac{1}{C}\sum_{i\in\mathbb{Z}^{d}}c_{h+i}^{\alpha}\mathbb{I}(c_{i} \neq 0)F(c_{\cdot+i})$$

$$= \mathbb{E}\big\{F(B^h\Theta)\mathbb{I}(\Theta(-h)\neq 0)\big\}$$

is valid for any 0-homogeneous measurable functional  $F: E \mapsto [0, \infty]$ . Clearly,  $S(\Theta) = \sum_{t \in \mathbb{Z}^d} \Theta^{\alpha}(t)$  is finite almost surely, hence

$$\theta_X = \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^d} c_{t+S}^{\alpha}}{\sum_{t \in \mathbb{Z}^d} c_{t+S}^{\alpha}}\right\} = \frac{1}{C} \max_{t \in \mathbb{Z}^d} c_t^{\alpha} \in (0, 1].$$
 (5.5)

We note that  $\theta_X$  given in (5.5) is the extremal index of a large class of stationary rf's, see e.g., [4, 45].

## 5.3. Constructions of X with given extremal index

From the previous example we conclude that for any  $a \in (0,1]$  we can construct a stationary max-stable rf X such that  $\theta_X = a$ . We present below examples of rf X satisfying  $\theta_X = 0$  and then we construct stationary max-stable rf's  $X^{(p)}$  indexed by  $p \in (0,1)$  and calculate their extremal indices.

Consider next independent, non-negative rf's  $\Theta_k(t), t \in \mathbb{Z}, k \leq d$  that satisfy (2.6) such that  $\mathbb{P}\{\Theta_k(0)=1\}=1, k \leq d$ . It follows that the rf  $\Theta(t)=\prod_{1\leq k\leq d}\Theta_k(t_k), t=(t_1,\ldots,t_k)\in\mathbb{Z}^d$  also satisfies (2.6). In view of Lemma 2.3 we can construct stationary max-stable rf's  $X,X_k,k\leq d$  corresponding to  $\Theta,\Theta_k,k\leq d$ . As already mentioned in Remark 3.7 ii) we have  $\theta_X=\prod_{k\leq d}\theta_{X_k}$  and therefore  $\theta_X=0$  if some  $\theta_{X_k}$  equals zero. If we define  $\Theta_k(j)=1$  for all even integers j and  $\Theta_k(j)=0$  for all odd integers j, then  $\Theta_k$  satisfies (2.6). Since  $S(\Theta_k)=\infty$  almost surely, then  $\theta_{X_k}=0$  follows and hence also  $\theta_X=0$ .

In view of our examples, we can construct two independent stationary maxstable rf's  $\eta_1(t), \eta_2(t), t \in \mathbb{Z}^d$  with unit Fréchet marginals and spectral tail rf's  $Z_1$  and  $Z_2$ , respectively satisfying  $\mathbb{P}\{\mathcal{S}(Z_1) < \infty\} = \mathbb{P}\{\mathcal{S}(Z_2) = \infty\} = 1$ . The rf  $X^{(p)}(t) = \max(p\eta_1(t), (1-p)\eta_2(t)), t \in \mathbb{Z}^d$  for any given  $p \in (0,1)$  is stationary and further max-stable with unit Fréchet marginals. As already shown in the previous section, we have  $\theta_{X^{(p)}} = p\theta_{\eta_1}$ .

# 6. Proofs

PROOF OF LEMMA 2.1: For a given non-negative spectral rf Z of a max-stable rf X with unit Fréchet marginals by the de Haan representation of X for any  $t_i \in \mathbb{Z}^d, x_i \in (0, \infty), i \leq n$ 

$$-\ln \mathbb{P}\{X(t_1) \le x_1, \dots, X(t_n) \le x_n\} = \mathbb{E}\left\{\max_{1 \le i \le n} \frac{Z(t_i)}{x_i}\right\}.$$
 (6.1)

Consequently, with  $t_0 = h \in \mathbb{Z}^d$  and  $x_0 = 1$  we obtain as  $u \to \infty$ 

$$\mathbb{P}\{u^{-1}X(t_i) \le x_i, i = 1, \dots, n | X(t_0) > u\} 
\sim u \mathbb{P}\{u^{-1}X(t_i) \le x_i, i = 1, \dots, n, u^{-1}X(t_0) > x_0\} 
= u[\mathbb{P}\{u^{-1}X(t_i) \le x_i, i = 1, \dots, n\} - \mathbb{P}\{u^{-1}X(t_i) \le x_i, i = 0, \dots, n\}]$$

$$\begin{split} &\rightarrow \quad \mathbb{E}\bigg\{\max_{i=0,\ldots,n}\frac{Z(t_i)}{x_i} - \max_{i=1,\ldots,n}\frac{Z(t_i)}{x_i}\bigg\}, \quad u \rightarrow \infty \\ &= \quad \mathbb{E}\bigg\{\mathbb{I}(Z(t_0) > 0)\Big[\max_{i=0,\ldots,n}\frac{Z(t_i)}{x_i} - \max_{i=1,\ldots,n}\frac{Z(t_i)}{x_i}\Big]\bigg\} \\ &= \quad \mathbb{E}\bigg\{Z(t_0)\mathbb{I}(Z(t_0) > 0)\Big[\max_{i=0,\ldots,n}\frac{Z(t_i)}{Z(t_0)x_i} - \max_{i=1,\ldots,n}\frac{Z(t_i)}{Z(t_0)x_i}\Big]\bigg\} \\ &= \quad \mathbb{E}\bigg\{\max_{i=0,\ldots,n}\frac{\Theta_h(t_i)}{x_i} - \max_{i=1,\ldots,n}\frac{\Theta_h(t_i)}{x_i}\bigg\}, \end{split}$$

where the last line follows by the definition of  $\Theta_h$  in (1.8). Hence in view of (2.2) and the fact that  $\Theta_h(h) = 1$  almost surely, the proof is complete.

PROOF OF LEMMA 2.3: Since by the assumptions  $\sum_{j\in\mathbb{Z}^d} p_j = 1$  and  $\Theta^*$  is non-negative we have for any  $j\in\mathbb{Z}^d$ 

$$\mathbb{E}\left\{\sum_{i\in\mathbb{Z}^d} p_i \Theta^*(i-j)\right\} = \sum_{i\in\mathbb{Z}^d} p_i \mathbb{E}\left\{\Theta^*(i-j)\right\} = \sum_{i\in\mathbb{Z}^d} p_i \mathbb{P}\left\{\Theta^*(j-i) > 0\right\} \le 1,$$

which together with the non-negativity of  $\Theta^*$  implies for some norm  $\|\cdot\|$  on  $\mathbb{R}^d$ 

$$\lim_{\|t\| \to \infty, t \in \mathbb{Z}^d} p_t \Theta^*(t - j) = \lim_{\|t\| \to \infty, t \in \mathbb{Z}^d} p_t Y(t - j) = 0$$

$$(6.2)$$

almost surely. Consequently, since further

$$\mathbb{P}\{p_N > 0\} = \mathbb{P}\{Y(0) > 1\} = 1,$$

then  $\max_{t\in\mathbb{Z}^d} p_t B^N Y(t) \in (0,\infty)$  almost surely and thus  $Z_N$  in (2.7) is well-defined. Next, for any  $a,h\in\mathbb{Z}^d$  and any 0-homogeneous measurable functional  $F:E\mapsto [0,\infty]$ , by the independence of N and Y applying Fubini theorem we obtain

$$\mathbb{E}\{Z_{N}(h)F(B^{a}Z_{N})\}$$

$$= \mathbb{E}\left\{\frac{B^{N}Y(h)}{\max_{s\in\mathbb{Z}^{d}}p_{s}B^{N}Y(s)}\mathbb{I}(\mathcal{I}_{fm}(p\cdot B^{N}Y) = N)F(B^{a+N}Y)\right\}$$

$$= \sum_{j\in\mathbb{Z}^{d}}\mathbb{E}\left\{p_{j}\frac{B^{j}\Theta^{*}(h)}{\max_{s\in\mathbb{Z}^{d}}p_{s}\Theta^{*}(s-j)}\mathbb{I}(\mathcal{I}_{fm}(p\cdot B^{j}\Theta^{*}) = j)F(B^{a+j}\Theta^{*})\right\}$$

$$= \sum_{j\in\mathbb{Z}^{d}}\mathbb{E}\left\{B^{j}\Theta^{*}(h)\mathbb{I}(\mathcal{I}_{fm}(p\cdot B^{j}\Theta^{*}) = j)F(B^{a+j}\Theta^{*})\right\}$$

$$= \sum_{j\in\mathbb{Z}^{d}}\mathbb{E}\left\{\mathbb{I}(\mathcal{I}_{fm}(p\cdot B^{h}\Theta^{*}) = j,\Theta^{*}(j-h) > 0)F(B^{a+h}\Theta^{*})\right\}$$

$$= \mathbb{E}\left\{F(B^{a+h}\Theta^{*})\sum_{j\in\mathbb{Z}^{d}}\mathbb{I}(\mathcal{I}_{fm}(p\cdot B^{h}\Theta^{*}) = j,\Theta^{*}(j-h) > 0)\right\}$$

$$= \mathbb{E}\{F(B^{a+h}\Theta^*)\}$$
  
=  $\mathbb{E}\{Z_N(a)F(B^hZ_N)\},$ 

where the third equality follows since  $\mathcal{I}_{fm}(p \cdot B^j \Theta^*) = j$  implies

$$\max_{s \in \mathbb{Z}^d} p_s \Theta^*(s - j) = p_j B^j \Theta^*(j) = p_j \Theta^*(0) = p_j > 0$$

almost surely, the fourth equality follows from (2.6) and the assumption that  $\mathbb{P}\{\Theta^*(0)=1\}=1$ , the sixth one is consequence of the following (which follows from (6.2))

$$\sum_{j \in \mathbb{Z}^d} \mathbb{I}(\mathcal{I}_{fm}(p \cdot B^h \Theta^*) = j) = \mathbb{I}(\mathcal{I}_{fm}(p \cdot B^h \Theta^*) \in \mathbb{Z}^d) = 1$$

almost surely and the fact that  $\mathcal{I}_{fm}(p \cdot B^h \Theta^*) = j$  implies for any  $h \in \mathbb{Z}^d$ 

$$p_j \Theta^*(j-h) \ge p_h \Theta^*(0) \ge p_h > 0$$

almost surely and consequently  $\Theta^*(j-h) > 0$  almost surely. Finally, the last claimed equality is established by repeating the calculations for  $\mathbb{E}\{Z_N(a)F(B^hZ_N)\}$ . Hence the proof follows by (2.5) and the definition of the spectral tail rf  $\Theta$  via the spectral rf Z.

PROOF OF LEMMA 3.1: Let  $r_n \in \mathbb{Z}^d$ ,  $n \geq 1$  be non-negative integers with components  $r_{nj}, j \leq d$  such that  $\lim_{n \to \infty} n/r_{nj} = \lim_{n \to \infty} r_{nj} = \infty$ . The stationarity of X yields further

$$C(A) = \mathbb{E}\left\{\max_{i \in A} Z(i)\right\} = C(A')$$

for any finite set of indices  $A \subset \mathbb{Z}^d$  and any  $A' \subset \mathbb{Z}^d$  which is a shift/translation of A. Moreover, by the sub-additivity of the maximum

$$C(A \cup B) < C(A) + C(B)$$
.

Hence the growth of C(A) is as that of the counting measure of A, see [16] for this argument and [33]. Consequently,

$$\lim_{n\to\infty}\frac{\mathbb{E}\big\{\max_{0\leq i\leq r_n,i\in\mathbb{Z}^d}Z(i)\big\}}{\prod_{i=1}^d r_{nj}}\quad=\quad \lim_{n\to\infty}n^{-d}\mathbb{E}\Big\{\max_{i\in[0,n]^d,i\in\mathbb{Z}^d}Z(i)\Big\}=\mathcal{H}.$$

The assumption on  $r_n$  and (6.1) imply that

$$\widetilde{\theta_X} \sim \frac{\mathbb{P}\{\max_{0 \le i \le r_n, i \in \mathbb{Z}^d} X(i) > n\}}{\prod_{i=1}^d r_{ni} \mathbb{P}\{X(0) > n\}} \sim \frac{\mathbb{E}\{\max_{0 \le i \le r_n, i \in \mathbb{Z}^d} Z(i)\}}{\prod_{i=1}^d r_{ni}}, \quad n \to \infty.$$

Hence  $\mathcal{H} = \theta_X$  establishes the proof.

PROOF OF LEMMA 3.3: We give first a key characterisation of tail rf's proved initially in [35] and also stated for rf's in [2]. Namely, for any measurable map  $F: E \mapsto [0, \infty]$ 

$$\mathbb{E}\{F(Y)\mathbb{I}(Y(i)>1/t)\} = t\mathbb{E}\left\{F(B^iY)\mathbb{I}(Y(-i)>t)\right\} \tag{6.3}$$

holds for all  $i \in \mathbb{Z}^d$ , t > 0. If  $\mathcal{I}, \mathcal{I}'$  are two anchoring maps, since Y(0) = R > 1 almost surely and  $\mathcal{I}(Y) = i$  implies Y(i) > 1 almost surely, by (6.3)

$$\begin{split} &\mathbb{P}\{\mathcal{I}(Y) \in \mathbb{Z}^d, \mathcal{I}'(Y) = 0, F(Y) < \infty\} \\ &= \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(Y) = i, \mathcal{I}'(Y) = 0, F(Y) < \infty\} \\ &= \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(Y) = i, Y(i) > 1, \mathcal{I}'(Y) = 0, F(Y) < \infty\} \\ &= \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(B^iY) = i, Y(-i) > 1, \mathcal{I}'(B^iY) = 0, F(Y) < \infty\} \\ &= \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(Y) = 0, F(Y) < \infty, Y(-i) > 1, \mathcal{I}'(Y) = -i\} \\ &= \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(Y) = 0, F(Y) < \infty, \mathcal{I}'(Y) = -i\} \\ &= \mathbb{P}\{\mathcal{I}'(Y) \in \mathbb{Z}^d, \mathcal{I}(Y) = 0, F(Y) < \infty\}. \end{split}$$

With similar arguments we obtain

$$\mathbb{P}\{\mathcal{I}(Y) \in \mathbb{Z}^d, F(Y) < \infty\} = \sum_{i \in \mathbb{Z}^d} \mathbb{P}\{\mathcal{I}(Y) = 0, F(Y) < \infty, Y(-i) > 1\}.$$

Consequently,  $\mathbb{P}\{\mathcal{I}(Y)=0,F(Y)<\infty\}=0$  is equivalent with

$$\mathbb{P}\{\mathcal{I}(Y) \in \mathbb{Z}^d, F(Y) < \infty\} = 0$$

establishing the proof.

PROOF OF LEMMA 3.5: As shown in [19] condition  $\mathbb{P}\{\mathcal{S}(Z) = \infty\} = 1$  is equivalent with X being generated by a non-singular conservative flow. The latter is equivalent with  $\theta_X = 0$ , see [21] (which follows by [38] if d = 1 and by [37] for d > 1). In view of Lemma 3.3 and (3.3)  $\mathbb{P}\{\mathcal{I}(Y) = 0, \mathcal{S}(Y) < \infty\} = 0$  is equivalent with  $\mathbb{P}\{\mathcal{S}(Y) < \infty\} = 0$ . Applying Lemma 7.2 in Appendix the latter is equivalent with  $\mathbb{P}\{\mathcal{S}(Z) < \infty\} = 0$ . This establishes the proof since the latter is equivalent with  $\theta_X = 0$ .

PROOF OF THEOREM 3.6: We have that  $\mathbb{P}\{S(Z) < \infty\} = 0$  is equivalent with X is generated by a non-singular conservative flow, which in view of [38, 37, 36] is equivalent with  $\theta_X = 0$ . Applying Lemma 7.3 in Appendix to BRs spectral rf

Z we have that ZF(Z) is also a BRs spectral rf for any measurable functional  $F: E \mapsto [0,\infty]$ , which is 0-homogeneous and shift-invariant. Since both  $\mathbb{I}(\mathcal{S}(f) = \infty), \mathbb{I}(\mathcal{S}(f) < \infty), f \in E$  are measurable 0-homogeneous and shift-invariant functionals and by the above

$$\lim_{n \to \infty} \frac{1}{n^d} \mathbb{E} \left\{ \max_{t \in [0,n]^d \cap \mathbb{Z}^d} Z(t) \mathbb{I}(\mathcal{S}(Z) = \infty) \right\} = 0$$

we have using further (1.5)

$$\theta_{X} = \mathcal{H} = \lim_{n \to \infty} \frac{1}{n^{d}} \mathbb{E} \left\{ \max_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} Z(t) \right\}$$

$$= \lim_{n \to \infty} \frac{1}{n^{d}} \mathbb{E} \left\{ \max_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} Z(t) \mathbb{I}(\mathcal{S}(Z) < \infty) \right\}. \tag{6.4}$$

Next, assuming that  $\mathbb{P}\{S(Z) < \infty\} > 0$  by Lemma 7.2  $\mathbb{P}\{S(\Theta) < \infty\} > 0$  and the converse also holds. Setting  $Z_*(t) = Z(t)\mathbb{I}(S(Z) < \infty)$  by Lemma 7.3 it is BRs and further  $S(Z_*) < \infty$  almost surely. In view of Lemma 7.1 we can assume that  $S(Z_*) > 0$  almost surely. Applying (2.5) and using the equivalence of **A1** and **A3** we obtain further

$$\theta_{X} = \lim_{n \to \infty} \frac{1}{n^{d}} \sum_{h \in [0,n]^{d} \cap \mathbb{Z}^{d}} \mathbb{E} \left\{ Z_{*}(h) \frac{\max_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} Z_{*}(t)}{\sum_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} Z_{*}(t)} \right\}$$

$$= \lim_{n \to \infty} \frac{1}{n^{d}} \sum_{h \in [0,n]^{d} \cap \mathbb{Z}^{d}} \mathbb{E} \left\{ Z_{*}(0) \frac{\max_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} B^{h} Z_{*}(t)}{\sum_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} B^{h} Z_{*}(t)} \right\}$$

$$= \lim_{\epsilon \downarrow 0} \lim_{n \to \infty} \frac{1}{n^{d}} \sum_{h \in [\epsilon n, (1-\epsilon)n]^{d} \cap \mathbb{Z}^{d}} \mathbb{E} \left\{ Z_{*}(0) \frac{\max_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} B^{h} Z_{*}(t)}{\sum_{t \in [0,n]^{d} \cap \mathbb{Z}^{d}} B^{h} Z_{*}(t)} \right\}$$

$$= \mathbb{E} \left\{ Z_{*}(0) \frac{\max_{t \in \mathbb{Z}^{d}} Z_{*}(t)}{\sum_{t \in \mathbb{Z}^{d}} Z_{*}(t)} \right\}$$

$$= \mathbb{E} \left\{ \frac{\max_{t \in \mathbb{Z}^{d}} \Theta(t)}{S(\Theta)} \mathbb{I}(S(\Theta) < \infty) \right\}.$$

Since by definition the events  $\{\mathcal{I}_{fm}(\Theta) \in \mathbb{Z}^d\}$  and  $\{\mathcal{S}(\Theta) < \infty\}$  are almost surely the same, the 0-homogeneity of  $\mathcal{I}_{fm}(\cdot)$  implies (recall  $\Theta(0) = 1$  almost surely)

$$\theta_{X} = \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^{d}} \Theta(t)}{\mathcal{S}(\Theta)} \mathbb{I}(\mathcal{I}_{fm}(\Theta) \in \mathbb{Z}^{d})\right\}$$

$$= \sum_{j \in \mathbb{Z}^{d}} \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^{d}} \Theta(t)}{\mathcal{S}(\Theta)} \mathbb{I}(\mathcal{I}_{fm}(\Theta) = j)\right\}$$

$$= \sum_{j \in \mathbb{Z}^{d}} \mathbb{E}\left\{\Theta(j) \frac{\Theta(0)}{\mathcal{S}(\Theta)} \mathbb{I}(\mathcal{I}_{fm}(\Theta) = j)\right\}$$

$$= \sum_{j \in \mathbb{Z}^d} \mathbb{E} \left\{ \frac{\Theta(-j)}{\mathcal{S}(\Theta)} \mathbb{I}(\mathcal{I}_{fm}(B^j \Theta) = j) \right\}$$

$$= \mathbb{E} \left\{ \sum_{j \in \mathbb{Z}^d} \frac{\Theta(-j)}{\mathcal{S}(\Theta)} \mathbb{I}(\mathcal{I}_{fm}(\Theta) = 0) \right\}$$

$$= \mathbb{P} \{ \mathcal{I}_{fm}(\Theta) = 0 \}$$

$$= \mathbb{P} \{ \mathcal{I}_{fm}(\Theta) = 0, \mathcal{S}(\Theta) < \infty \},$$

where we applied (2.6) in the last third line combined with condition ii) in the definition of anchoring maps and also used that S(f),  $f \in E$  is a shift-invariant functional. Clearly, the last two formulas hold also for the last maximum functional. Since (3.3) implies

$$\mathbb{P}\{\mathcal{I}(Y) \notin \mathbb{Z}^d, \mathcal{S}(Y) < \infty\} = 0, \tag{6.5}$$

then using Lemma 3.3 to obtain the second equality below we have

$$\mathbb{P}\{\mathcal{I}_{fm}(\Theta) = 0, \mathcal{S}(\Theta) < \infty\} = \mathbb{P}\{\mathcal{I}_{fm}(Y) = 0, \mathcal{S}(Y) < \infty, \mathcal{I}(Y) \in \mathbb{Z}^d\} 
+ \mathbb{P}\{\mathcal{I}_{fm}(Y) = 0, \mathcal{S}(Y) < \infty, \mathcal{I}(Y) \notin \mathbb{Z}^d\} 
= \mathbb{P}\{\mathcal{I}_{fm}(Y) \in \mathbb{Z}^d, \mathcal{S}(Y) < \infty, \mathcal{I}(Y) = 0\} 
= \mathbb{P}\{\mathcal{I}(Y) = 0, \mathcal{S}(Y) < \infty\}$$

and hence  $\theta_X = \mathbb{P}\{\mathcal{I}_{fe}(Y) = 0\}$  follows and the same is true also for the last excedance functional. In view of the equivalence **A2** and **A4** we have

$$\{\mathcal{S}(Y) < \infty\} \subset \{\mathcal{B}(Y) < \infty\},\tag{6.6}$$

with  $\mathcal{B}(Y) := \sum_{t \in \mathbb{Z}^d} \mathbb{I}(Y(t) > 1)$ . Hence since  $Y(0) = R\Theta(0) = R > 1$  almost surely implies  $\mathcal{B}(Y) \ge 1$  almost surely

$$\begin{split} &\mathbb{E}\Big\{\frac{\mathcal{B}(Y)}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{I}(Y)=0,\mathcal{S}(Y)<\infty)\Big\}\\ &=&\sum_{t\in\mathbb{Z}^d}\mathbb{E}\Big\{\frac{1}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{I}(Y)=0,Y(t)>1,\mathcal{S}(Y)<\infty)\Big\}\\ &=&\mathbb{E}\Big\{\frac{1}{\mathcal{B}(Y)}\sum_{t\in\mathbb{Z}^d}\mathbb{I}(\mathcal{I}(Y)=-t,Y(-t)>1,\mathcal{S}(Y)<\infty)\Big\}\\ &=&\mathbb{E}\Big\{\frac{1}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{I}(Y)\in\mathbb{Z}^d,\mathcal{S}(Y)<\infty)\Big\}\\ &=&\mathbb{E}\Big\{\frac{1}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{S}(Y)<\infty)\Big\}\\ &=&\mathbb{E}\Big\{\frac{1}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{S}(Y)<\infty)\Big\}, \end{split}$$

where we used (6.3) to derive the last fourth line and the last second equality follows from (6.5). With the same arguments as in the proof of [46][Lem 2.5] considering the discrete setup as in [18] for any n > 0

$$\mathbb{E}\bigg\{\max_{t\in[0,n]^d\cap\mathbb{Z}^d}Z(t)\bigg\} = \sum_{t\in[0,n]^d\cap\mathbb{Z}^d}\mathbb{E}\bigg\{\frac{1}{\sum_{s\in[0,n]^d\cap\mathbb{Z}^d}\mathbb{I}(Y(s-t)>1)}\bigg\}.$$

Since Y(0) > 1 almost surely and thus the denominator in the expectation above is greater equal 1 and converges as  $n \to \infty$  almost surely to  $\mathcal{B}(Y)$ , it follows by the dominated convergence theorem that

$$\theta_X = \lim_{n \to \infty} n^{-d} \mathbb{E} \left\{ \max_{t \in [0, n]^d \cap \mathbb{Z}^d} Z(t) \right\} = \mathbb{E} \left\{ \frac{1}{\mathcal{B}(Y)} \right\} \le 1,$$

hence (3.11) holds. From the last two expressions of  $\theta_X$  we conclude that  $\mathbb{E}\left\{\frac{1}{\mathcal{B}(Y)}\mathbb{I}(\mathcal{S}(Y)=\infty)\right\}=0$ . Consequently, almost surely  $\{\mathcal{B}(Y)<\infty\}\subset\{\mathcal{S}(Y)<\infty\}$ , which together with (6.6) implies that almost surely

$$\{\mathcal{B}(Y) < \infty\} = \{\mathcal{S}(Y) < \infty\}.$$

Next, if  $\mathbb{P}\{\Theta(i)=0\}=1$  for all  $i\neq 0, i\in\mathbb{Z}^d$ , then

$$\theta_X = \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^d} \Theta(t)}{\sum_{t \in \mathbb{Z}^d} \Theta(t)} \mathbb{I}(\mathcal{S}(\Theta) < \infty)\right\} = 1.$$

Conversely, if  $\theta_X = 1$ , then necessarily  $\mathbb{P}\{\mathcal{S}(\Theta) < \infty\} = 1$  and thus

$$\theta_X = 1 = \mathbb{E}\left\{\frac{\max_{t \in \mathbb{Z}^d} \Theta(t)}{\sum_{t \in \mathbb{Z}^d} \Theta(t)}\right\}$$

implying that  $\max_{t \in \mathbb{Z}^d} \Theta(t) = \sum_{t \in \mathbb{Z}^d} \Theta(t)$  almost surely. Taking  $\mathcal{I}(f) = \mathcal{I}_{fm}(f)$  we have that  $\theta_X = \mathbb{P}\{\mathcal{I}(\Theta) = 0\} = 1$  implies that  $\max_{t \in \mathbb{Z}^d} \Theta(t) = \Theta(0) = 1$  almost surely and therefore

$$\sum_{t \in \mathbb{Z}^d} \Theta(t) = 1 + \sum_{t \in \mathbb{Z}^d, t \neq 0} \Theta(t) = 1$$

almost surely. Consequently, (recall  $\Theta(i)$ 's are non-negative)  $\mathbb{P}\{\Theta(i)=0\}=1$  for all  $i\neq 0, i\in \mathbb{Z}^d$  establishing the proof.

PROOF OF LEMMA 4.1: For any s>0 and any non-decreasing sequence of integers  $r_n, n\in\mathbb{N}$  tending to infinity such that  $\lim_{n\to\infty}r_n^d/n=0$  we have for any positive integer m (recall  $\mathbb{E}\{Z(t)\}=1$  for any  $t\in\mathbb{Z}^d$ )

$$n^{-1} \mathbb{E} \left\{ \max_{m < \|t\| < r_n, t \in \mathbb{Z}^d} Z(t) \right\} \le n^{-1} \sum_{m < \|t\| < r_n, t \in \mathbb{Z}^d} \mathbb{E} \{ Z(t) \} \to 0, \quad n \to \infty,$$

hence by (6.1) and the dominated convergence theorem

$$1 - \lim_{n \to \infty} \mathbb{P}\left\{ \max_{m < ||t|| < r_n, t \in \mathbb{Z}^d} X(t) > ns | X(0) > ns \right\}$$

$$\begin{split} &= s \lim_{n \to \infty} n \mathbb{P} \{ \max_{m < \|t\| < r_n, t \in \mathbb{Z}^d} X(t) \le ns, X(0) > ns \} \\ &= \mathbb{E} \left\{ \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d, t = 0} Z(t) - \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d} Z(t) \right\} \\ &= \mathbb{E} \left\{ \mathbb{I}(Z(0) > 0) \left[ \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d, t = 0} Z(t) - \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d} Z(t) \right] \right\} \\ &= \mathbb{E} \left\{ Z(0) \mathbb{I}(Z(0) > 0) \left[ \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d, t = 0} \frac{Z(t)}{Z(0)} - \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d} \frac{Z(t)}{Z(0)} \right] \right\} \\ &= \mathbb{E} \left\{ \left( 1 - \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d} \Theta(t) \right)_+ \right\} \end{split}$$

for any positive integer m (recall  $\Theta(0) = 1$  almost surely). If **A1** holds, then by the dominated convergence theorem

$$\lim_{m\to\infty}\mathbb{E}\bigg\{\max_{m<\|t\|<\infty,t\in\mathbb{Z}^d,t=0}Z(t)-\max_{m<\|t\|<\infty,t\in\mathbb{Z}^d}Z(t)\bigg\}=\mathbb{E}\{Z(0)\}=1,$$

hence Condition C is satisfied.

Conversely, if Condition C is satisfied for some sequence  $r_n, n \geq 1$  of non-negative increasing integers, then by the above calculations

$$1 - \lim_{m \to \infty} \lim_{n \to \infty} \mathbb{P}\left\{ \max_{m < \|t\| < r_n, t \in \mathbb{Z}^d} X(t) > ns | X(0) > ns \right\}$$
$$= \lim_{m \to \infty} \mathbb{E}\left\{ \left(1 - \max_{m < \|t\| < \infty, t \in \mathbb{Z}^d} \Theta(t)\right)_+ \right\} = 1$$

and thus almost surely as  $m \to \infty$ 

$$\max_{m<||t||<\infty,t\in\mathbb{Z}^d}\Theta(t)\to 0.$$

Consequently, by Lemma 7.4 in Appendix condition A2 holds, hence the proof follows from Remark 3.7.  $\hfill\Box$ 

#### 7. Appendix

For notational simplicity we consider the case  $\alpha=1$  in the following. The results for  $\alpha>0$  can be formulated with obvious modifications.

**Lemma 7.1.** If  $X(t), t \in \mathbb{Z}^d$  is a max-stable rf with de Haan representation (1.1) and some spectral rf Z satisfying  $\mathbb{E}\{Z(t)\} \in (0,\infty)$  for all  $t \in \mathbb{Z}^d$ , then we can find a spectral rf  $Z_*$  for X such that  $\max_{t \in \mathbb{Z}^d} Z_*(t) > 0$  almost surely.

PROOF OF LEMMA 7.1: Let  $w_i, i \in \mathbb{Z}^d$  be positive constants such that

$$\mathbb{E}\left\{\sum_{i\in\mathbb{Z}^d}w_iZ(i)\right\}\in(0,\infty).$$

 $w_i$ 's exist since  $\mathbb{E}\{Z(i)\}\in(0,\infty)$  for any  $i\in\mathbb{Z}^d$ . By the choice of  $w_i$ 's we have that

$$M = \max_{i \in \mathbb{Z}^d} w_i Z(i)$$

is a non-negative rv and  $a = \mathbb{E}\{M\} \in (0, \infty)$ . Let  $Z_*(t), t \in \mathbb{Z}^d$  be a rf defined by

$$\mathbb{P}\{Z_* \in A\} = \mathbb{E}\{M\mathbb{I}(aZ/M \in A)/a\}$$

for any measurable set  $A \subset E$ . Since by the above definition

$$\mathbb{P}\{\max_{i\in\mathbb{Z}^d} w_i Z_*(i) = 0\} = \mathbb{E}\{M\mathbb{I}(\max_{i\in\mathbb{Z}^d} w_i Z(i)/M = 0)/a\} = 0$$

it follows that  $\mathbb{P}\{\max_{i\in\mathbb{Z}^d} Z_*(i) = 0\} = 0$ . Moreover, for any  $x_i \in (0,\infty), t_i \in \mathbb{Z}^d, i \leq n$ 

$$\begin{split} &-\ln \mathbb{P}\{X(t_1) \leq x_1, \dots, X(t_n) \leq x_n\} \\ &= \mathbb{E}\{\max_{1 \leq i \leq n} Z(t_i)/x_i\} \\ &= \mathbb{E}\{\mathbb{I}(\max_{1 \leq i \leq n} Z(t_i) > 0) \max_{1 \leq i \leq n} Z(t_i)/x_i\} \\ &= \mathbb{E}\{M/a\mathbb{I}(M > 0)\mathbb{I}(\max_{1 \leq i \leq n} Z(t_i) > 0) \max_{1 \leq i \leq n} aZ(t_i)/(Mx_i)\} \\ &= \mathbb{E}\{\mathbb{I}(\max_{1 \leq i \leq n} Z_*(t_i) > 0) \max_{1 \leq i \leq n} Z_*(t_i)/x_i\} \\ &= \mathbb{E}\{\max_{1 \leq i \leq n} Z_*(t_i)/x_i\}, \end{split}$$

where the third equality is a simple consequence of  $\max_{1 \leq i \leq n} Z(t_i) > 0$  implies M > 0. Hence  $Z_*$  is a spectral rf for X. The calculations above show that we can define alternatively  $Z_*(t) = \mathbb{P}\{\max_{s \in \mathbb{Z}^d} Z(s) > 0\} Z(t)$  conditioned on  $\max_{s \in \mathbb{Z}^d} Z(s) > 0$ , which was suggested by the reviewer.

Proof of (3.1): As in the proof of Lemma 7.1, we can assume without loss of generality that Z is such that  $\max_{t\in\mathbb{Z}^d}(Z(t)/x_t)>0$  almost surely for any  $x=(x_j)_{j\in\mathbb{Z}^d}$  a positive sequence. Suppose for simplicity that  $\alpha=1$  and let next x be a sequence with finite number of positive elements and the rest equal to  $\infty$  (we interpret  $a/\infty$  as 0). Since further Z/x consists of zeros and finitely many positive numbers, then  $\mathcal{I}_{fm}(Z/x)\in\mathbb{Z}^d$  almost surely. Consequently, by (6.1), Fubini theorem and the fact that  $\mathcal{I}_{fm}(Z/x)=j$  implies  $\max_{i\in\mathbb{Z}^d}(Z(t_i)/x_i)=Z(j)/x_j$  almost surely

$$\begin{aligned} -\ln \mathbb{P}\{X(i) \leq x_i, i \in \mathbb{Z}^d\} &= \mathbb{E}\{\max_{i \in \mathbb{Z}^d} Z(t_i) / x_i \mathbb{I}(\mathcal{I}_{fm}(Z/x) \in \mathbb{Z}^d)\} \\ &= \sum_{j \in \mathbb{Z}^d} \mathbb{E}\{\max_{i \in \mathbb{Z}^d} Z(t_i) / x_i \mathbb{I}(\mathcal{I}_{fm}(Z/x) = j)\} \\ &= \sum_{j \in \mathbb{Z}^d} \frac{1}{x_j} \mathbb{E}\{Z(j) \mathcal{I}_{fm}(Z/x) = j\} \end{aligned}$$

$$= \sum_{j \in \mathbb{Z}^d} \frac{1}{x_j} \mathbb{E} \{ Z(0) \mathcal{I}_{fm}(B^j Z/x) = j \}$$

$$= \sum_{j \in \mathbb{Z}^d} \frac{1}{x_j} \mathbb{E} \{ Z(0) \mathbb{I}(\mathcal{I}_{fm}((B^j Z/x)/Z(0)) = j) \}$$

$$= \sum_{j \in \mathbb{Z}^d} \frac{1}{x_j} \mathbb{P} \{ \mathcal{I}_{fm}(B^j(\Theta/(B^{-j}x))) = j \}$$

$$= \sum_{j \in \mathbb{Z}^d} \frac{1}{x_j} \mathbb{P} \{ \mathcal{I}_{fm}(\Theta/(B^{-j}x)) = 0 \},$$

where the fourth first equality follows from (2.5) and the last equality follows since  $\mathcal{I}_{fm}$  is an anchoring map.

**Lemma 7.2.** Let  $Z(t), t \in \mathbb{Z}^d$  be a BRs rf satisfying (1.2). If  $F: E \mapsto [0, \infty]$  is a shift-invariant and 0-homogeneous measurable map, then  $\mathbb{E}\{F(Z)\} = 0$  is equivalent with  $\mathbb{E}\{F(\Theta)\} = 0$ . If further F is bounded by 1, then  $\mathbb{E}\{F(Z)\} = 1$  is equivalent with  $\mathbb{E}\{F(\Theta)\} = 1$ .

PROOF OF LEMMA 7.2: By the shift-invariance of F and (2.5) we have

$$\begin{array}{lcl} 0 & = & \mathbb{E}\{F(\Theta)\} = \mathbb{E}\{Z(0)F(Z/Z(0))\} = \sum_{i \in \mathbb{Z}^d} \mathbb{E}\big\{Z(0)F(B^{-i}Z)\big\} \\ \\ & = & \sum_{i \in \mathbb{Z}^d} \mathbb{E}\{Z(i)F(Z)\} \geq \mathbb{E}\bigg\{\Big(\max_{i \in \mathbb{Z}^d} Z(i)\Big)F(Z)\bigg\}, \end{array}$$

hence since Z is chosen such that  $\max_{i \in \mathbb{Z}^d} Z(i) > 0$  almost surely, then  $\mathbb{E}\{F(Z)\} = 0$  follows. If  $\mathbb{E}\{F(Z)\} = 0$ , then F(Z) = 0 almost surely and thus

$$0 = \mathbb{E}\{Z(0)F(Z)\} = \mathbb{E}\{F(\Theta)\} = 0$$

follows. Next,  $\mathbb{E}\{F(\Theta)\}=1$  is the same as  $\mathbb{E}\{1-F(\Theta)\}=0$ , which is equivalent with  $\mathbb{E}\{1-F(Z)\}=0$  as shown above, establishing the proof.

**Lemma 7.3.** If  $F: E \mapsto [0, \infty]$  is a 0-homogeneous measurable functional and  $Z(t), t \in \mathbb{Z}^d$  is a BRs rf, then  $Z_* = ZF(Z)$  is also a BRs rf, provided that  $\mathbb{E}\{Z_*(t_0)\} \in (0, \infty)$  for some  $t_0 \in \mathbb{Z}^d$ .

PROOF OF LEMMA 7.3: Using (2.5) we have that  $\mathbb{E}\{Z_*(t)\} = \mathbb{E}\{Z_*(t_0)\} \in (0, \infty)$  for any  $t \in \mathbb{Z}^d$  and in particular  $\mathbb{P}\{F(Z) = 0\} < 1$  and  $\mathbb{P}\{F(Z) = \infty\} = 0$ . Since F is 0-homogeneous, we have that  $Z_*$  satisfies (2.5), which is an equivalent condition for a spectral rf to be a BRs rf, see [25].

**Lemma 7.4.** If  $V(t), t \in \mathbb{Z}^d$  is a non-negative rf, then  $\mathbb{P}\{\lim_{\|t\| \to \infty} V(t) = 0\} = 1$  is equivalent with there exists a non-decreasing sequence of integers  $r_n, n \geq 1$  that converge to infinite as  $n \to \infty$  such that

$$\lim_{m \to \infty} \limsup_{n \to \infty} \mathbb{P}\{ \max_{m \le ||t|| \le r_n} V(t) > \delta \} = 0 \tag{7.1}$$

is valid for any  $\delta > 0$ .

PROOF OF LEMMA 7.4: It is well-known that (see e.g., [22][A1.3])

$$\mathbb{P}\{\lim_{\|t\|\to\infty}V(t)=0\}=1$$

if and only if for all large m and any  $\delta, \varepsilon$  positive

$$\mathbb{P}\{\max_{\|t\| \ge m} V(t) > \delta\} < \varepsilon,$$

which clearly implies (7.1). Assuming that the latter condition holds, then for given  $\delta, \varepsilon$  positive there exists N such that for all m, n larger than N we have  $\mathbb{P}\{\max_{m \leq ||t|| \leq r_n} V(t) > \delta\} < \varepsilon$ . Since  $\lim_{n \to \infty} r_n = \infty$ , then  $\mathbb{P}\{\max_{m \leq ||t||} V(t) > \delta\} \le \varepsilon$ , hence the claim follows.

**Lemma 7.5.** Let  $\eta_i(t), i = 1, 2, t \in \mathbb{Z}^d$  be two independent stationary rf's with unit Fréchet marginal distributions. If the extremal indices of both  $\eta_1$  and  $\eta_2$  exist, then the rf  $X(t) = \max(p\eta_1(t), (1-p)\eta_2(t)), t \in \mathbb{Z}^d$  has for any  $p \in (0,1)$  extremal index  $\theta_X = p\theta_{\eta_1} + (1-p) \theta_{\eta_2} \in [0,1]$ .

PROOF OF LEMMA 7.5: By the independence of  $\eta_1$  and  $\eta_2$  we have that X is stationary with unit Fréchet marginal distributions. In order to show the claim it suffices to prove that  $\max_{t\in[0,n]^d}X(t)/n^d$  converges in distribution as  $n\to\infty$  to  $(p\theta_{\eta_1}+(1-p)\theta_{\eta_2})\xi$ , where  $\xi$  is a unit Fréchet rv. As  $n\to\infty$ , by the assumptions  $\max_{t\in[0,n]^d}\eta_i(t)/n^d$  converge for i=1,2 in distribution to  $p_i\theta_{\eta_i}\xi_i$  with  $\xi_1,\xi_2$  two independent unit Fréchet rv's and  $p_1=1-p_2=p$ . Since  $\max(p_1\theta_{\eta_1}\xi_1,p_2\theta_{\eta_2}\xi_2)$  has the same df as  $(p_1\theta_{\eta_1}+p_2\theta_{\eta_2})\xi$ , the claim follows by the independence of  $\eta_i$ 's and Slutsky's lemma.

## Acknowledgments

Partial support by SNSF Grants 200021-175752/1 and 200021-196888 is kindly acknowledged. I am in debt to the reviewer and the Editor for several suggestions, comments and corrections which improved the manuscript significantly.

#### References

- [1] J. M. P. Albin. On extremal theory for stationary processes. *Ann. Probab.*, 18(1):92–128, 1990.
- [2] B. Basrak and H. Planinić. Compound Poisson approximation for random fields with application to sequence alignment. arXiv preprint arXiv:1809.00723, 2018.
- [3] B. Basrak and J. Segers. Regularly varying multivariate time series. *Stochastic Process. Appl.*, 119(4):1055–1080, 2009.
- [4] B. Basrak and A. Tafro. Extremes of moving averages and moving maxima on a regular lattice. *Probab. Math. Statist.*, 34(1):61–79, 2014.
- [5] S. M. Berman. Sojourns and Extremes of Stochastic Processes. The Wadsworth & Brooks/Cole Statistics/Probability Series. Wadsworth & Brooks/Cole Advanced Books & Software, Pacific Grove, CA, 1992.

- [6] B. M. Brown and S. I. Resnick. Extreme values of independent stochastic processes. J. Appl. Probab., 14:732–739, 1977.
- [7] R. A. Davis and T. Hsing. Point process and partial sum convergence for weakly dependent random variables with infinite variance. Ann. Probab., 23(2):879–917, 1995.
- [8] R. A. Davis, T. Mikosch, and Y. Zhao. Measures of serial extremal dependence and their estimation. Stochastic Process. Appl., 123(7):2575–2602, 2013.
- [9] K. Dębicki and E. Hashorva. On extremal index of max-stable processes. *Probability and Mathematical Statistics*, 27(2):299–317, 2017.
- [10] K. Dębicki and E. Hashorva. Approximation of Supremum of Max-Stable Stationary Processes & Pickands Constants. J. Theoret. Probab., 33(1):444– 464, 2020.
- [11] K. Dębicki, E. Hashorva, and N. Soja-Kukieła. Extremes of homogeneous Gaussian random fields. *J. Appl. Probab.*, 52(1):55–67, 2015.
- [12] K. Dębicki, Z. Michna, and X. Peng. Approximation of sojourn times of Gaussian processes. *Methodol. Comput. Appl. Probab.*, 21(4):1183–1213, 2019.
- [13] L. de Haan. A spectral representation for max-stable processes. *Ann. Probab.*, 12(4):1194–1204, 1984.
- [14] L. de Haan and J. Pickands, III. Stationary min-stable stochastic processes. *Probab. Theory Relat. Fields*, 72(4):477–492, 1986.
- [15] K. Dębicki. Ruin probability for Gaussian integrated processes. *Stochastic Processes and their Applications*, 98(1):151–174, 2002.
- [16] A. B. Dieker and T. Mikosch. Exact simulation of Brown-Resnick random fields at a finite number of locations. *Extremes*, 18:301–314, 2015.
- [17] A. B. Dieker and B. Yakir. On asymptotic constants in the theory of extremes for Gaussian processes. *Bernoulli*, 20(3):1600–1619, 2014.
- [18] C. Dombry, E. Hashorva, and P. Soulier. Tail measure and spectral tail process of regularly varying time series. *Ann. Appl. Probab.*, 28(6):3884–3921, 2018.
- [19] C. Dombry and Z. Kabluchko. Ergodic decompositions of stationary maxstable processes in terms of their spectral functions. *Stochastic Processes* and their Applications, 127(6):1763–1784, 2017.
- [20] K. Dębicki and E. Hashorva. On extremal index of max-stable stationary processes. *Probab. Math. Statist.*, 37(2):299–317, 2017.
- [21] A. Ehlert and M. Schlather. Capturing the multivariate extremal index: bounds and interconnections. *Extremes*, 11(4):353–377, 2008.
- [22] P. Embrechts, C. Klüppelberg, and T. Mikosch. *Modelling extremal events*, volume 33 of *Applications of Mathematics (New York)*. Springer-Verlag, Berlin, 1997. For insurance and finance.
- [23] H. Ferreira and L. Pereira. How to compute the extremal index of stationary random fields. *Statist. Probab. Lett.*, 78(11):1301–1304, 2008.
- [24] J. P. French and R. A. Davis. The asymptotic distribution of the maxima of a Gaussian random field on a lattice. *Extremes*, 16(1):1–26, 2013.
- [25] E. Hashorva. Representations of max-stable processes via exponential tilt-

- ing. Stochastic Process. Appl., 128(9):2952-2978, 2018.
- [26] A. Jakubowski and N. Soja-Kukieła. Managing local dependencies in asymptotic theory for maxima of stationary random fields. *Extremes*, 22(2):293—315, 2019.
- [27] A. Janßen. Spectral tail processes and max-stable approximations of multivariate regularly varying time series. Stochastic Process. Appl., 129(6):1993–2009, 2019.
- [28] Z. Kabluchko, M. Schlather, and L. de Haan. Stationary max-stable fields associated to negative definite functions. *Ann. Probab.*, 37:2042–2065, 2009.
- [29] S. G. Kobelkov and V. I. Piterbarg. On maximum of Gaussian random field having unique maximum point of its variance. *Extremes*, 22(3):413– 432, 2019.
- [30] D. Krizmanić. Functional weak convergence of partial maxima processes. *Extremes*, 19(1):7–23, 2016.
- [31] I. Molchanov, M. Schmutz, and K. Stucki. Invariance properties of random vectors and stochastic processes based on the zonoid concept. *Bernoulli*, 20(3):1210–1233, 2014.
- [32] Y. Nardi, D. O. Siegmund, and B. Yakir. The distribution of maxima of approximately Gaussian random fields. *Ann. Statist.*, 36(3):1375–1403, 2008
- [33] X.-X. Nguyen. Ergodic theorems for subadditive spatial processes. Z. Wahrsch. Verw. Gebiete, 48(2):159–176, 1979.
- [34] J. Pickands, III. Asymptotic properties of the maximum in a stationary Gaussian process. *Trans. Amer. Math. Soc.*, 145:75–86, 1969.
- [35] H. Planinić and P. Soulier. The tail process revisited. *Extremes*, 21(4):551–579, 2018.
- [36] P. Roy. Nonsingular group actions and stationary  $S\alpha S$  random fields. *Proc. Amer. Math. Soc.*, 138(6):2195–2202, 2010.
- [37] P. Roy and G. Samorodnitsky. Stationary symmetric  $\alpha$ -stable discrete parameter random fields. J. Theoret. Probab., 21(1):212–233, 2008.
- [38] G. Samorodnitsky. Extreme value theory, ergodic theory and the boundary between short memory and long memory for stationary stable processes. *Ann. Probab.*, 32(2):1438–1468, 2004.
- [39] G. Samorodnitsky. Maxima of continuous-time stationary stable processes. *Adv. in Appl. Probab.*, 36(3):805–823, 2004.
- [40] J. Segers, Y. Zhao, and T. Meinguet. Polar decomposition of regularly varying time series in star-shaped metric spaces. *Extremes*, 20(3):539–566, 2017.
- [41] D. Siegmund and B. Yakir. Tail probabilities for the null distribution of scanning statistics. *Bernoulli*, 6(2):191–213, 2000.
- [42] D. Siegmund, B. Yakir, and N. R. Zhang. Tail approximations for maxima of random fields by likelihood ratio transformations. *Sequential Anal.*, 29(3):245–262, 2010.
- [43] D. Siegmund, B. Yakir, and N. R. Zhang. Detecting simultaneous variant intervals in aligned sequences. *Ann. Appl. Stat.*, 5(2A):645–668, 2011.
- [44] N. Soja-Kukieła. Extremes of multidimensional stationary Gaussian ran-

- [45] N. Soja-Kukieła. On maxima of stationary fields. Adv. Appl. Probability, in press, 2019.
- [46] P. Soulier. The tail process and tail measure of continuous time regularly varying stochastic processes. arXiv:2004.00325, 2020.
- [47] S. A. Stoev. Max-stable processes: Representations, ergodic properties and statistical applications. *Dependence in Probability and Statistics, Lecture Notes in Statistics 200, Doukhan, P., Lang, G., Surgailis, D., Teyssiere, G. (Eds.)*, 200:21–42, 2010.
- [48] C. Tillier and O. Wintenberger. Regular variation of a random length sequence of random variables and application to risk assessment. *Extremes*, 21(1):27–56, 2018.
- [49] K. F. Turkman. A note on the extremal index for space-time processes. J. Appl. Probab., 43(1):114–126, 2006.
- [50] Y. Wang and S. A. Stoev. On the association of sum- and max-stable processes. *Statist. Probab. Lett.*, 80(5-6):480–488, 2010.
- [51] L. Wu and G. Samorodnitsky. Regularly varying random fields. *Stochastic Process. Appl.*, 130(7):4470–4492, 2020.
- [52] B. Yakir. Extremes in random fields. Wiley Series in Probability and Statistics. John Wiley & Sons, Ltd., Chichester; Higher Education Press, Beijing, 2013. A theory and its applications.