

Construction of Complete Complementary Codes over Small Alphabet

Palash Sarkar, Chunlei Li, Sudhan Majhi, and Zilong Liu

Abstract

Complete complementary codes (CCCs) play a vital role not only in wireless communication, particularly in multicarrier systems where achieving an interference-free environment is of paramount importance, but also in the construction of other codes that necessitate appropriate functions to meet the diverse demands within today's landscape of wireless communication evaluation. This research is focused on the area of constructing q -ary functions for both of traditional and spectrally null constraint (SNC) CCCs* of flexible length, set size and alphabet. We construct traditional CCCs with lengths, defined as $L = \prod_{i=1}^k p_i^{m_i}$, set sizes, defined as $K = \prod_{i=1}^k p_i^{n_i+1}$, and an alphabet size of $q = \prod_{i=1}^k p_i$, such that $p_1 < p_2 < \dots < p_k$. The parameters m_1, m_2, \dots, m_k (each greater than or equal to 2) are positive integers, while n_1, n_2, \dots, n_k are non-negative integers satisfying $n_i \leq m_i - 1$, and the variable k represents a positive integer. To achieve these specific parameters, we define q -ary functions over a domain $\mathbf{Z}_{p_1}^{m_1} \times \dots \times \mathbf{Z}_{p_k}^{m_k}$ that is considered a proper subset of \mathbb{Z}_q^m and encompasses $\prod_{i=1}^k p_i^{m_i}$ vectors, where $\mathbf{Z}_{p_i}^{m_i} = \{0, 1, \dots, p_i - 1\}^{m_i}$, and the value of m is derived from the sum of m_1, m_2, \dots, m_k . This organization of the domain allows us to encompass all conceivable integer-valued length sequences over the alphabet \mathbb{Z}_q . It has been demonstrated that by constraining a q -ary function that generates traditional CCCs, we can derive SNC-CCCs with identical length and alphabet, yet a smaller or equal set size compared to the traditional CCCs. Our achieved alphabet and set size are minimized when $k \geq 2$, and m_i is co-prime to m_j for some $1 \leq i \neq j \leq k$, in contrast to existing CCCs with the same length L but possessing a set size greater than or equal to K .

Index Terms

Aperiodic correlation, function, multicarrier code-division multiple-access (MC-CDMA), complete complementary code set (CCCS).

I. INTRODUCTION

A. Background of Traditional CCCs

The study of complementary sequences has been attracting increasing research attention in recent years due to their interesting correlation properties as well as their wide applications in engineering. Formally, a collection of sequences with identical length and zero aperiodic auto-correlation sum (AACS) for all non-zero time shifts are called a complementary set (CS) and each constituent sequence is called a complementary sequence [1]–[3]. In particular, a CS of

*When no codes in CCCs having zero components, we call it as traditional CCCs, else, we call it as SNC-CCCs in this paper.

size two is called a Golay complementary pair (GCP), a widely known concept proposed by Marcel J. E Golay in the late 1940s [4]. In this case, the two constituent sequences are called Golay sequences. Furthermore, by rearranging every CS to be an ordered set, a collection of CSs with zero aperiodic cross-correlation sum (ACCS) for all time shifts is called mutually orthogonal Golay complementary sets (MOGCSs) [5]. It is noted that the set size (denoted by K) of MOGCSs is upper bounded by the number of constituent sequences (denoted by M), i.e., $K \leq M$. When $K = M$, the resultant MOGCSs are called a set of complete complementary codes (CCCs) [6].

So far, complementary sequences and CCCs have been widely applied in numerous applications in coding, signal processing, and wireless communications. For example, they have been employed for peak-to-average power ratio (PAPR) reduction in code-keying orthogonal frequency division multiplexing (OFDM) [7], signature sequences for interference-free multi-carrier code-division multiple-access (MC-CDMA) over asynchronous wireless channels [8], [9], training/sensing sequences in multiple-input multiple-output (MIMO) communication/radar systems [10]–[12], information hiding in image/audio/video signals [13], kernel/seed sequences to construct Z-complementary code set (ZCCS) [14], [15] and quasi-complementary sequence set [16]–[18] for MC-CDMA, and zero-correlation zone (ZCZ) sequences [19]–[23] in quasi-synchronous direct-sequence CDMA communications.

There have been significant research attempts on efficient constructions of complementary sequences (including GCPs, MOGCSs and CCCs) with flexible lengths. With interleaving and concatenation, Golay first constructed binary GCPs of lengths $2MN$ from two shorter GCPs with lengths M and N , respectively [24]. Budišin developed recursive algorithms for more polyphase and multi-level complementary sequences through a series of sequence operations (e.g., phase rotations, shifting) associated with permutation vectors [25], [26]. In 1999, Davis and Jedwab proposed a systematic construction of 2^h -ary ($h \in \mathbb{Z}^+$) GCPs with power-of-two lengths using second-order generalized Boolean functions (GBFs) [7]. Such Golay sequences are called Golay-Davis-Jedwab (GDJ) complementary sequences in this paper. Paterson extended the idea of 2^h -ary GCPs to q -ary (even q) CSs with power-of-two constituent sequences and power-of-two lengths [2]. His work was further generalized in 2007 by Schmidt by moving to the higher-order GBFs [27]. Recently, Sarkar *et al.* proposed a construction in [28] using higher-order GBFs for complementary sequences with lower PMEPR upper bound. For complementary sequences with non-power-of-two lengths, Chen contributed with the aid of certain truncated Reed-Muller codes [29].

The constructions of MOGCSs especially CCCs are more stringent owing to the additional requirement of zero ACCS [5], [9], [30]. In 2020, Wu *et al.* introduced a construction of MOGCSs with non-power-of-two lengths based on GBFs in [31] where the set size is exactly half of the number of constituent sequences in a CS, i.e., $K = M/2$. Later several attempt have been made to construct non-power-of-two lengths MOGCSs with parametric restriction $K = M/2$, such as in [32], [33]. However, in a recent work [34], the authors successfully constructed binary CCCs

of lengths in the form of $5 \cdot 2^m$ and $13 \cdot 2^m$, and the set size in the form of power-of-two. Still to the date, there is a large gap in the function/polynomial based construction of CCCs having flexible parameters, specially lengths and alphabet size. Another powerful tool is paraunitary (PU) generator with which a set of CCCs can be efficiently obtained by sending a pipeline of shifted impulses to multistage filterbanks whose coefficients are extracted from a group of PU matrices [35]–[39]. Very recently, the inherent connections between the GBF generator and the PU generator in CCC construction have been uncovered by Wang *et al.* [40].

B. Background of SNC-CCCs

The conventional approach to sequence design assumes the presence of continuous spectral bands, allowing the sequences energy to be distributed across all carriers within that band. However, given the limited and valuable radio spectrum available for wireless communication and radar sensing, researchers are actively seeking more efficient utilization methods [41]. This emerging concept is known as cognitive radio (CR) [42] or cognitive radar [43]. It involves a set of intelligent radio devices with the capability to sense and analyze the radio frequency (RF) environment. They identify unused spectral bands and temporarily utilize them for data transmission. In particular, an overlay cognitive radio network continuously scans for unused frequency bands, often referred to as “white space,” within licensed spectrum ranges. This is done to accommodate new users, referred to as secondary users, while minimizing any potential impact on the primary licensed users.

Recent literature reveals, SNC complementary sequences find a lot of research attention due to its null constraint properties and applications in wireless communications. More recently, the demand for OFDM or multi-carrier CDMA sequences with SNCs (also referred to as non-contiguous) is driven by their possible use cases, such as in the Third-Generation Partnership Project (3GPP), Long-Term Evolution (LTE) enhanced licensed-assisted access (eLAA), and New Radio in Unlicensed (NR-U) have adopted SNC sequences [44], [45]. This demand is primarily motivated by the potential application scenarios of such sequences within the domain of CR communications. In the context of OFDM-based CR transmissions, secondary users are restricted to transmitting only on sub-carriers that are unoccupied by the primary user. This necessitates the presence of spectral nulls at particular positions within the code word transmitted by secondary users, aligning with the sub-carriers that the primary user utilizes. In [45], [46], authors generalized traditional GCP to proposed SNC-GCP. In [47], Zhou *et al.* provide an iterative construction of SNC-MOGCS based on traditional CCCs. In [48], authors used two sequences from a GCP as the seed sequence and then inserted zeros (the number of zeros is a multiple of the length of GCP) into two sequences to get new ones with zero aperiodic correlation zone. Authors in [49], proposed the construction of SNC zero correlation zone (ZCZ) sequences and SNC Z-periodic complementary sets (ZPCS). In [50], Shen *et al.*, proposed construction of SNC-CCCs based on extended Boolean functions (EBFs). While the construction [50] can produce CCCs of arbitrary length, its alphabet size may become as large as sequence lengths,

especially when the sequence lengths take the form $\prod_{i=1}^k p_i^{m_i}$, where m_i and m_j are coprime to each other for some $1 \leq i \neq j \leq k$, and $k > 1$. In the literature, the above mentioned constructions are the only constructions for SNC-CS or SNC-CCC.

C. Contributions and Approach

We observe that conventional direct constructions of sequences mostly rely on the tool of functions where the sequence length and alphabet size mostly depend on its domain and co-domain, respectively. As example, in most of the GBFs based constructions, the sequence length is limited to the length power-of-two, unless any additional operations been performed on the power-of-two lengths sequences. However, one way to cross the barrier is modifying the domain in a form such that it's size can cover most of the positive integers. In [50], the authors used EBFs with a domain of \mathbb{Z}_q^m and co-domain of \mathbb{Z}_q , where $q \geq 2$ is an integer. With this setting of domain and co-domain, and by choosing proper functions on them, they constructed CCCs of size q^{n+1} , length in the form q^m , and the alphabet size in the form of q , where $m \geq 2$, $0 \leq n \leq m - 1$. However, this choice leads to a higher alphabet and set size when they require to generate CCCs of lengths in the form of $\prod_{i=1}^k p_i^{m_i}$ with some of m_1, m_2, \dots, m_k are co-prime to each other. In this case, the alphabet size becomes as large as $\prod_{i=1}^k p_i^{m_i}$ and also the set size. To achieve lower alphabet sizes, we introduced those functions where the domain is in the form $\mathbb{Z}_{p_1}^{m_1} \times \mathbb{Z}_{p_2}^{m_2} \times \dots \times \mathbb{Z}_{p_k}^{m_k}$ and co-domain in the form $\mathbb{Z}_{p_1 p_2 \dots p_k}$, by doing so, we are capable of generating sequences of lengths in the form of $\prod_{i=1}^k p_i^{m_i}$ and alphabet size of $\prod_{i=1}^k p_i$. We can observe that this choices of domain and co-domain allow us to achieve all possible length sequences while maintaining a small alphabet size.

To generate CCCs with aforementioned parameters, our core idea is to construct q -ary functions having specific graphical properties as defined in Section III of this paper, where $q = \prod_{i=1}^k p_i$. Specifically, we construct q -ary functions which results in a function of algebraic degree 2 after restricting some variables in the main function. The graph of the restricted function is a collection of Hamiltonian paths. It has been firstly shown that the restricted functions generates SNC-CCCs of lengths in the form $L = \prod_{i=1}^k p_i^{m_i}$, set size in the form $\prod_{i=1}^k p_i$. The alphabet size of the proposed SNC-CCCs is given by $1 + \prod_{i=1}^k p_i$. Later it has been shown that the main function generates traditional CCCs of same lengths L and the set size in the form $\prod_{i=1}^k p_i^{n_i+1}$. The alphabet size for our proposed traditional CCCs is given by $\prod_{i=1}^k p_i$. As every integers greater than 1 can be factored uniquely as the product of powers of prime numbers (by unique factorization theorem), it can be observed that the proposed q -ary functions is capable of producing traditional CCCs of arbitrary length and set size. We also have derived a relationship between the proposed traditional CCCs and the SNC-CCCs. For $k = 1$ and $p_1 = 2$, the GDJ sequences are obtained as a special case of our construction. For $k = 1$, and $p_1 = 2$, our proposed construction is also able to produce CSs and CCCs with the same parameters as that reported in the works by Paterson [2], Schmidt [27], and Sarkar *et al.* [28]. As a byproduct of this research,

we introduce a novel class of linear code which may be regarded as a generalization of RM code and its connection with the proposed complementary sequences.

II. PRELIMINARIES

In this paper, the following notations are used otherwise stated.

- \mathbb{Z} denotes the set of all integers.
- $\mathbf{Z}_n = \{0, 1, \dots, n-1\} \subset \mathbb{Z}$
- $\mathbf{a} \cdot \mathbf{b} = a_0 b_0 + a_1 b_1 + \dots + a_{L-1} b_{L-1}$.
- For a finite set S , $|S|$ denotes the cardinality of S .
- For two finite sets S and S' , $S \times S'$ denotes the cartesian product between S and S' .
- $S^n = \underbrace{S \times S \times \dots \times S}_{n \text{ times}}$
- $q = \prod_{i=1}^k p_i$, where p_1, p_1, \dots, p_k are k distinct primes such that $p_1 < p_2 < \dots < p_k$.
- $\zeta_q = \exp(2\pi\sqrt{-1}/q)$ is a primitive q -th root of unity.
- $m_i (\geq 2)$ is a positive integer, where $i = 1, 2, \dots, k$.
- $n_i (\leq m_i - 1)$ is a non-negative integer, where $i = 1, 2, \dots, k$.
- $L_i = p_i^{m_i}$, $L = \prod_{i=1}^k L_i$ and $K = \prod_{i=1}^k p_i^{n_i+1}$.
- $m = \sum_{i=1}^k m_i$.
- $\mathcal{V}_L = \mathbf{Z}_{p_1}^{m_1} \times \mathbf{Z}_{p_2}^{m_2} \times \dots \times \mathbf{Z}_{p_k}^{m_k}$.

A. Aperiodic Auto- and Cross-Correlation

For any two complex-valued sequences $\mathbf{a} = (a_0, a_1, \dots, a_{L-1})$ and $\mathbf{b} = (b_0, b_1, \dots, b_{L-1})$ of length L , we define the aperiodic cross-correlation function (ACCF) at a shift τ , with $0 \leq |\tau| < L$ as

$$\Theta(\mathbf{a}, \mathbf{b})(\tau) = \begin{cases} \sum_{\alpha=0}^{L-\tau-1} a_\alpha b_{\alpha+\tau}^*, & 0 \leq \tau < L, \\ \sum_{\alpha=0}^{L+\tau-1} a_{\alpha-\tau} b_\alpha^*, & -L < \tau < 0. \end{cases} \quad (1)$$

For $\mathbf{a} = \mathbf{b}$, the ACCF defined in (1) reduces to the aperiodic auto-correlation function (AACF) of \mathbf{a} , which will be denoted as $\Theta(\mathbf{a})(\tau)$ for short. The set $\{x \in \mathbf{Z}_L : a_x \neq 0\}$ is called the support of \mathbf{a} . If the set $\mathbf{Z}_L \setminus \{x \in \mathbf{Z}_L : a_x \neq 0\}$ is a non-empty set, \mathbf{a} is called a *spectrally null constrained (SNC) sequence* [50]; otherwise, it is called a traditional sequence. Let $\mathcal{C} = \{\mathbf{C}_1, \mathbf{C}_2, \dots, \mathbf{C}_{K-1}\}$ be a collection of K codes, each containing M sequences of length L . By arranging each code as a two-dimensional matrix, we write \mathbf{C}_k as

$$\mathbf{C}_t = \begin{bmatrix} \mathbf{c}_t^1 \\ \mathbf{c}_t^2 \\ \vdots \\ \mathbf{c}_t^M \end{bmatrix}_{M \times L},$$

where $t = 0, 1, \dots, K - 1$. The ACCF (sum) between \mathbf{C}_{t_1} and \mathbf{C}_{t_2} for $0 \leq t_1, t_2 \leq K - 1$ is defined as

$$\Theta(\mathbf{C}_{t_1}, \mathbf{C}_{t_2})(\tau) = \sum_{j=1}^M \Theta(\mathbf{c}_{t_1}^j, \mathbf{c}_{t_2}^j)(\tau), \quad (2)$$

For $t_1 = t_2 = t$, the ACCF in (2) reduces to the AACF of \mathbf{C}_t and we denote it by $\Theta(\mathbf{C}_t)(\tau)$. The set \mathcal{C} is said to be a set of traditional complete complementary code (CCC) if the aperiodic correlation sum of its codes satisfies the following properties:

$$\Theta(\mathbf{C}_{t_1}, \mathbf{C}_{t_2})(\tau) = \begin{cases} LM, & \tau = 0, t_1 = t_2, \\ 0, & 0 < |\tau| < L, t_1 = t_2, \\ 0, & |\tau| < L, t_1 \neq t_2. \end{cases} \quad (3)$$

In this case any of the codes in \mathcal{C} is known as a traditional CS or complementary code (CC) [51]. If there is at least one SNC constituent sequence in any codes of \mathcal{C} and satisfying (3), the set of codes \mathcal{C} is called SNC-CCC [50]. It is to be noted that both of the terms ‘traditional CCCs’ and ‘CCCs’ bear the same meaning in this paper.

B. Functions and Traditional Sequences

In this section, we define necessary algebraic operations on the set \mathcal{V}_L in order to introduce q -ary functions while maintaining \mathcal{V}_L as the domain. We start with a given positive integer $L = L_1 L_2$, define a mapping $\rho: \mathbf{Z}_L \rightarrow \mathbf{Z}_{L_1} \times \mathbf{Z}_{L_2}$ as $\rho(x) := (x_1, x_2)$ where

$$x_2 = x \bmod L_2 \text{ and } x_1 = (x - x_2)/L_2.$$

It is clear that ρ is bijective and its inverse ρ^{-1} is given by $x = \rho^{-1}(x_1, x_2) = x_1 * L_2 + x_2$. More generally, for an integer $L = \prod_{i=1}^k L_i$, we can define a one-to-one mapping $\rho: \mathbf{Z}_L \rightarrow \mathbf{Z}_{L_1} \times \mathbf{Z}_{L_2} \times \dots \times \mathbf{Z}_{L_k}$ as $\phi(x) = (x_1, x_2, \dots, x_k)$, where x_i 's is recursively derived as follows:

$$\begin{aligned} y_k &= x \\ x_t &= y_t \bmod L_t \text{ and } y_{t-1} = \frac{y_t - x_t}{L_t} \quad \text{for } t = k, \dots, 2, 1. \end{aligned} \quad (4)$$

From the above recursive relations, it is easy to verify that the pre-image of (x_1, x_2, \dots, x_k) is given by

$$\begin{aligned} x &= \rho^{-1}((x_1, x_2, \dots, x_k)) = (y_{k-1} L_k + x_k) \\ &= ((y_{k-2} L_{k-1} + x_{k-1}) L_k + x_k) = \dots = \\ &= ((x_1 L_2 + x_2) L_3 + x_3) L_4 \dots L_k + x_k \\ &= x_1 L_2 \dots L_k + x_2 L_3 \dots L_k + \dots + x_{k-1} L_k + x_k \\ &= x_1 \Delta_1 + x_2 \Delta_2 + \dots + x_k \Delta_k \end{aligned} \quad (5)$$

where $\Delta_i = \frac{L}{L_1 \dots L_i}$. Note that the above relation does not pose any restriction on the relation among L_1, L_2, \dots, L_k . In particular, when $L_1 = L_2 = \dots = L_k = p$, the image $\rho(x) =$

(x_1, x_2, \dots, x_k) corresponds to the conventional p -ary expansion of $x = \sum_{i=1}^k x_i \Delta_i$, where $\Delta_i = \frac{p^k}{\prod_{1 \leq j \leq i} p} = p^{k-i}$. From this discussion, we can define an one-to-one mapping $\rho : \mathbf{Z}_L \rightarrow \mathcal{V}_L$ as

$$\mathbf{x} := \rho(x) = (\mathbf{x}_1, \dots, \mathbf{x}_k) = (x_{1,1}, \dots, x_{1,m_1}, \dots, x_{k,1}, \dots, x_{k,m_k})$$

where $\mathbf{x}_i = (x_{i,1}, \dots, x_{i,m_i}) \in \mathbf{Z}_{p_i}^{m_i}$ is the p_i -ary expansion of the corresponding integer x_i in $\mathbf{Z}_{p_i}^{m_i}$, namely, $x_i = \sum_{j=1}^{m_i} x_{i,j} p_i^{m_i-j}$. In the sequel we will say \mathbf{x} is the vectorial representation of an integer $x \in \mathbf{Z}_L$ and x is the integer representation of a vector $\mathbf{x} \in \mathcal{V}_L$, which are connected via the equality $\mathbf{x} = \rho(x)$.

Now we consider functions from \mathcal{V}_L to \mathbb{Z}_q in m variables $x_{1,1}, \dots, x_{1,m_1}, \dots, x_{k,1}, \dots, x_{k,m_k}$, where the arithmetic operations among these variables and coefficients are taken modulo q . **For an element $\mathbf{e} = (\mathbf{e}_1, \dots, \mathbf{e}_k) \in \mathcal{V}_L$, we define a monomial $\mathbf{x}^{\mathbf{e}}$ over the m variables as**

$$\mathbf{x}^{\mathbf{e}} = \mathbf{x}_1^{\mathbf{e}_1} \cdots \mathbf{x}_k^{\mathbf{e}_k} = \prod_{j=1}^{m_1} x_{1,j}^{e_{1,j}} \cdots \prod_{j=1}^{m_k} x_{k,j}^{e_{k,j}},$$

where by convention we assume $0^0 = 0$ and $x^0 = 1$ for $x \neq 0$. The algebraic degree of $\mathbf{x}^{\mathbf{e}}$ is given by

$$\deg(\mathbf{x}^{\mathbf{e}}) = \sum_{j=1}^{m_1} e_{1,j} + \cdots + \sum_{j=1}^{m_k} e_{k,j} = \|\mathbf{e}\|_1,$$

where $\|\mathbf{e}\|_1$ denotes the L^1 -norm of \mathbf{e} . There are $|\mathcal{V}_L|$ number of monomials and a linear combination of those monomials with \mathbb{Z}_q -valued coefficients represents a q -ary function $f : \mathcal{V}_L \rightarrow \mathbb{Z}_q$ which can be expressed as

$$f(\mathbf{x}) = \sum_{\mathbf{e} \in \mathcal{V}_L} c_{\mathbf{e}} \mathbf{x}^{\mathbf{e}} = \sum_{\mathbf{e} \in \mathcal{V}_L} c_{\mathbf{e}} \mathbf{x}_1^{\mathbf{e}_1} \cdots \mathbf{x}_k^{\mathbf{e}_k}.$$

For $k = 1$ and $p_1 = 2$, the function f reduces to a Boolean function [7], and for $p_1 > 2$, it reduces to an extended Boolean function [50]. The algebraic degree of f is defined by $\deg(f) = \max\{\|\mathbf{e}\|_1 : c_{\mathbf{e}} \neq 0\}$. Alternatively, we may define another notion of degree, *Hamming degree*, of the above function f as

$$\deg_H(f) = \max\{\text{wt}(\mathbf{e}) : c_{\mathbf{e}} \neq 0\},$$

where $\text{wt}(\mathbf{e})$ is the Hamming weight of $\mathbf{e} = (e_{1,1}, \dots, e_{1,m_1}, \dots, e_{k,1}, \dots, e_{k,m_k})$. From the definition, it is clear that any q -ary function f has $\deg_H(f) \leq \deg(f)$. A q -ary functions from \mathcal{V}_L to \mathbb{Z}_q of Hamming degree at most r can be uniquely expressed as

$$f(\mathbf{x}) = \sum_{\mathbf{e} \in \mathcal{V}_L, \text{wt}(\mathbf{e}) \leq r} c_{\mathbf{e}} \mathbf{x}^{\mathbf{e}}.$$

Denote by $\mathcal{U}_{L,r}$ the set of all the above q -ary functions with Hamming degree at most r . Then $\mathcal{U}_{L,r}$ can be expressed as

$$\mathcal{U}_{L,r} = \left\{ \sum_{\mathbf{e} \in \mathcal{V}_L, \text{wt}(\mathbf{e}) \leq r} c_{\mathbf{e}} \mathbf{x}^{\mathbf{e}} : c_{\mathbf{e}} \in \mathbb{Z}_q \right\}. \quad (6)$$

Let us also denote the set of all q -ary functions of algebraic-degree at most r by $\Omega_{L,r}$ given by

$$\Omega_{L,r} = \left\{ \sum_{\mathbf{e} \in \mathcal{V}_L, \|\mathbf{e}\|_1 \leq r} c_{\mathbf{e}} \mathbf{x}^{\mathbf{e}} : c_{\mathbf{e}} \in \mathbb{Z}_q \right\}. \quad (7)$$

which says $\Omega_{L,r} \subset \mathcal{U}_{L,r}$.

Example 1. Let us assume $k = 2$, $p_1 = 2$, $p_2 = 3$, $m_1 = 3$, $m_2 = 2$, $q = p_1 p_2 = 6$, and so $L = p_1^{m_1} p_2^{m_2} = 72$. Table I containing the q -ary vector representation $\mathbf{x} = (x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) \in \mathcal{V}_{72}$ of x , where $x \in \mathbf{Z}_{72}$, and Table II contains all the monomials of Hamming weight at most 2 over the 5 variables $x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}$. There are 27 monomials and therefore $\mathcal{U}_{72,2}$ contains 6^{27} functions which can be obtained by taking linear combination of the monomials in Table II with coefficients from \mathbb{Z}_6 .


Table I: The Set \mathcal{V}_{72} for $p_1 = 2$, $p_2 = 3$, $m_1 = 3$, and $m_2 = 2$.

x	\mathbf{x}	x	\mathbf{x}	x	\mathbf{x}	x	\mathbf{x}	x	\mathbf{x}	x	\mathbf{x}
0	00000	12	00110	24	01020	36	10000	48	10110	60	11020
1	00001	13	00111	25	01021	37	10001	49	10111	61	11021
2	00002	14	00112	26	01022	38	10002	50	10112	62	11022
3	00010	15	00120	27	01100	39	10010	51	10120	63	11100
4	00011	16	00121	28	01101	40	10011	52	10121	64	11101
5	00012	17	00122	29	01102	41	10012	53	10122	65	11102
6	00020	18	01000	30	01110	42	10020	54	11000	66	11110
7	00021	19	01001	31	01111	43	10021	55	11001	67	11111
8	00022	20	01002	32	01112	44	10022	56	11002	68	11112
9	00100	21	01010	33	01120	45	10100	57	11010	69	11120
10	00101	22	01011	34	01121	46	10101	58	11011	70	11121
11	00102	23	01012	35	01122	47	10102	59	11012	71	11122

Table II: Set of Monomials of Hamming weight at most 2.

$\mathbf{e} \in \mathcal{V}_{72}$	$\mathbf{x}^{\mathbf{e}}$	$\mathbf{e} \in \mathcal{V}_{72}$	$\mathbf{x}^{\mathbf{e}}$	$\mathbf{e} \in \mathcal{V}_{72}$	$\mathbf{x}^{\mathbf{e}}$
00000	1	00100	$x_{1,3}$	01020	$x_{1,2}x_{2,1}^2$
00001	$x_{2,2}$	00101	$x_{1,3}x_{2,2}$	01100	$x_{1,2}x_{1,3}$
00002	$x_{2,2}^2$	00102	$x_{1,3}x_{2,2}^2$	10000	$x_{1,1}$
00010	$x_{2,1}$	00110	$x_{1,3}x_{2,1}$	10001	$x_{1,1}x_{2,2}$
00011	$x_{2,1}x_{2,2}$	00120	$x_{1,3}x_{2,1}^2$	10002	$x_{1,1}x_{2,2}^2$
00012	$x_{2,1}x_{2,2}^2$	01000	$x_{1,2}$	10010	$x_{1,1}x_{2,1}$
00020	$x_{2,1}^2$	01001	$x_{1,2}x_{2,2}$	10020	$x_{1,1}x_{2,1}^2$
00021	$x_{2,1}^2x_{2,2}$	01002	$x_{1,2}x_{2,2}^2$	10100	$x_{1,1}x_{1,3}$
00022	$x_{2,1}^2x_{2,2}^2$	01010	$x_{1,2}x_{2,1}$	11000	$x_{1,1}x_{1,2}$

For any function $f \in \mathcal{U}_{L,2}$, we can represent it by an undirected graph $G(f)$ as follows: $G(f)$ contains m vertices representing the m variable $x_{i,j}$; if f contains a nonzero term $cx_{i,j}^e$ with $e \geq 1$, then there are $e - 1$ edges from vertex $x_{i,j}$ to itself with a common label c as shown in Figure 1; if f contains a nonzero term in two variables, say $cx_{i_1,j_1}^{e_1}x_{i_2,j_2}^{e_2}$, then there is an edge between the two variables labeled with weight c , and there are corresponding number of edges from each vertex to itself as presented in Figure 2.

Figure 1: Graph of $cx_{i,j}^e$ Figure 2: Graph of $cx_{i_1,j_1}^{e_1}x_{i_2,j_2}^{e_2}$

For a q -ary function $f : \mathcal{V}_L \rightarrow \mathbb{Z}_q$, we define the \mathbb{Z}_q -valued sequence of length L as follows:

$$\eta(f) = (f_0, f_1, \dots, f_{L-1}), \quad (8)$$

where $f_x = f(\mathbf{x})$ and $x \in \mathbf{Z}_L$. We define the complex-valued sequence over the alphabet \mathbb{Z}_q as

$$\psi(f) = (\zeta_q^{f_0}, \zeta_q^{f_1}, \dots, \zeta_q^{f_{L-1}}). \quad (9)$$

As all the components of $\psi(f)$ is non-zero, $\psi(f)$ is a tradition sequence over the alphabet \mathbb{Z}_q , and (9) establish a relationship between f with a length- L traditonal complex-valued sequence $\psi(f)$.

Example 2. In Example 1, let us consider the following 6-ary function $f \in \mathcal{U}_{72,2}$:

$$f(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) = 2x_{1,1}x_{1,2} + 4x_{1,2}x_{1,3} + x_{1,2}x_{2,1} + x_{1,2}x_{2,2} + 3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + x_{1,2} + 2. \quad (10)$$

In Figure (3), we present the graph corresponding to f . From (8), the \mathbb{Z}_6 -valued sequence corresponding to f is of length, $L = 2^3 3^2 = 72$, and appears as

$$\eta(f) = (222234240222234240222234240333345351345402525450513030450513030012135252),$$

and the complex-valued sequence corresponding to f is

$$\psi(f) = (\omega_6^2 \omega_6^2 \omega_6^2 \omega_6^2 \omega_6^3 \omega_6^4 \omega_6^2 \omega_6^4 \omega_6^0 \omega_6^2 \omega_6^2 \omega_6^2 \omega_6^2 \omega_6^3 \omega_6^4 \omega_6^2 \omega_6^4 \omega_6^0 \omega_6^3 \omega_6^3 \omega_6^3 \omega_6^3 \omega_6^4 \omega_6^5 \omega_6^3 \omega_6^5 \omega_6^1 \omega_6^3 \omega_6^4 \omega_6^5 \omega_6^4 \omega_6^0 \omega_6^2 \omega_6^5 \omega_6^2 \omega_6^5 \omega_6^4 \omega_6^5 \omega_6^0 \omega_6^5 \omega_6^1 \omega_6^3 \omega_6^0 \omega_6^3 \omega_6^0 \omega_6^4 \omega_6^5 \omega_6^0 \omega_6^5 \omega_6^1 \omega_6^3 \omega_6^0 \omega_6^3 \omega_6^0 \omega_6^0 \omega_6^1 \omega_6^2 \omega_6^1 \omega_6^3 \omega_6^5 \omega_6^2 \omega_6^5 \omega_6^2).$$




Figure 3: Graph corresponding to f in (10)

In the below section, we shall also draw a connection between q -ary functions f and SNC sequences along with SNC position sets.

C. Functions and SNC Sequences

Similarly as \mathcal{V}_L , we define another set $\mathcal{V}_{L'}$ containing the vector representations of $0, 1, \dots, \prod_{i=1}^k p_i^{n_i} - 1$ of length $L' = \prod_{i=1}^k p_i^{n_i}$. Then $\mathcal{V}_{L'}$ can be expressed as

$$\mathcal{V}_{L'} = \{ \mathbf{c} = (\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k) : \mathbf{c}_i \in \mathbf{Z}_{p_i}^{n_i}, i = 1, 2, \dots, k \} = \mathbf{Z}_{p_1}^{n_1} \times \mathbf{Z}_{p_2}^{n_2} \times \dots \times \mathbf{Z}_{p_k}^{n_k}$$

Let $J = \{J_1, J_2, \dots, J_k\}$, where $J_i = \{j_{i,1}, j_{i,2}, \dots, j_{i,n_i}\} \subset \{1, 2, \dots, m_i\}$, and $\mathbf{x}_J = (\mathbf{x}_{1J_1}, \mathbf{x}_{2J_2}, \dots, \mathbf{x}_{kJ_k})$, where $\mathbf{x}_{iJ_i} = (x_{i,j_{i,1}}, x_{i,j_{i,2}}, \dots, x_{i,j_{i,n_i}})$, $i = 1, 2, \dots, k$. When $\mathbf{x}_J = \mathbf{c}$ for some $\mathbf{c} \in \mathcal{V}_{L'}$ in f , we call it a restriction of f and we denote it by $f|_{\mathbf{x}_J=\mathbf{c}}$. To define sequences corresponding to a q -ary function having restriction on some variables, let us first define the following sets

$$\mathcal{V}_L^{\mathbf{c}} = \{ \mathbf{x} \in \mathcal{V}_L : \mathbf{x}_{1J_1} = \mathbf{c}_1, \mathbf{x}_{2J_2} = \mathbf{c}_2, \dots, \mathbf{x}_{kJ_k} = \mathbf{c}_k \} \subset \mathcal{V}_L,$$

and

$$\mathcal{N}_{\mathbf{c}} = \{x \in \mathbf{Z}_L : x = \varphi(\mathbf{x}), \mathbf{x} \in \mathcal{V}_L^{\mathbf{c}}\} \subset \mathbf{Z}_L.$$

Then

$$\mathcal{V}_L = \cup_{\mathbf{c} \in \mathcal{V}_{L'}} \mathcal{V}_L^{\mathbf{c}}, \text{ and } \mathbf{Z}_L = \cup_{\mathbf{c} \in \mathcal{V}_{L'}} \mathcal{N}_{\mathbf{c}} \quad (11)$$

Also for any $\mathbf{c} \neq \mathbf{c}'$ in $\mathcal{V}_{L'}$,

$$\mathcal{V}_L^{\mathbf{c}} \cap \mathcal{V}_L^{\mathbf{c}'} = \emptyset, \text{ and } \mathcal{N}_{\mathbf{c}} \cap \mathcal{N}_{\mathbf{c}'} = \emptyset. \quad (12)$$

We define a length- L SNC complex-valued sequence corresponding to $f|_{\mathbf{x}_J=\mathbf{c}}$ as follows:

$$\psi(f|_{\mathbf{x}_J=\mathbf{c}}) = \begin{cases} \zeta_q^{f_x}, & x \in \mathcal{N}_{\mathbf{c}}, \\ 0, & \text{otherwise,} \end{cases} \quad (13)$$

where $f_x = f(\mathbf{x})$, and $\mathbf{x} \in \mathcal{V}_L^{\mathbf{c}}$. In (13), the elements in $\mathcal{N}_{\mathbf{c}}$ represent the positions of non-zero components of $\psi(f|_{\mathbf{x}_J=\mathbf{c}})$. Therefore, $\mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}$ represent the positions of null components. As $|\mathcal{N}_{\mathbf{c}}| = |\mathcal{V}_L^{\mathbf{c}}| = \prod_{i=1}^k p_i^{m_i - n_i}$,

$$|\mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}| = L - \prod_{i=1}^k p_i^{m_i - n_i}.$$

Therefore, it is clear that the set $\mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}$ is non-empty only when $n_i \neq 0$ for some values of i , $1 \leq i \leq k$, and in this case, $\psi(f|_{\mathbf{x}_J=\mathbf{c}})$ forms a SNC sequence with support $\mathcal{N}_{\mathbf{c}}$. It is to be noted that the alphabet size for $\psi(f|_{\mathbf{x}_J=\mathbf{c}})$ is of $q + 1$ as it contains some null components along with $|\mathcal{N}_{\mathbf{c}}|$ non-zero components from the L components of $\psi(f)$. From (11), (12), and (13), we have

$$\psi(f) = \sum_{\mathbf{c} \in \mathcal{D}'} \psi(f|_{\mathbf{x}_J=\mathbf{c}}), \quad (14)$$

which says a q -ary function f can be expressed as the sum of $\prod_{i=1}^k p_i^{n_i}$ L -length complex-valued SNC sequences each having $L - \prod_{i=1}^k p_i^{m_i - n_i}$ null or zero components. In the later presentation, whenever we use the notation τ , we consider it as non-negative integer.

D. SNC Sequences and Their Correlation Distribution

For two \mathbb{Z}_q -valued functions f and g , from (13), the ACCF between $\psi(f|_{\mathbf{x}_J=\mathbf{c}})$ and $\psi(g|_{\mathbf{x}_J=\mathbf{c}})$ at τ can be expressed as

$$\Theta(\psi(f|_{\mathbf{x}_J=\mathbf{c}}), \psi(g|_{\mathbf{x}_J=\mathbf{c}}))(\tau) = \begin{cases} \sum_{x=0}^{L-1-\tau} \zeta_q^{f_x - g_{x+\tau}}, & (x, x + \tau) \in \mathcal{N}_{\mathbf{c}} \times \mathcal{N}_{\mathbf{c}}, \quad 0 \leq \tau < L, \\ 0, & \text{otherwise.} \end{cases} \quad (15)$$

To simplify (15) and for later presentation, let us define the following set to determine correlation functions and their distributions for SNC sequences:

$$\mathcal{A}_{\tau}(\mathbf{c}) = \{(x, y) \in \mathcal{N}_{\mathbf{c}} \times \mathcal{N}_{\mathbf{c}} : 0 \leq x \leq L - \tau - 1, y = x + \tau\}. \quad (16)$$

Let us also define the set of all τ for which $\mathcal{A}_\tau \neq \emptyset$ as

$$\mathcal{T}_c = \{\tau \in \mathbf{Z}_L : |\mathcal{A}_\tau(\mathbf{c})| \neq \emptyset\}. \quad (17)$$

As $|\mathcal{N}_c| = |\mathcal{V}_L^c| = \prod_{i=1}^k p_i^{m_i - n_i}$,

$$|\mathcal{T}_c| \geq \prod_{i=1}^k p_i^{m_i - n_i},$$

which says there exist at least $\prod_{i=1}^k p_i^{m_i - n_i}$ number of $\tau \in \mathbf{Z}_L$ for which $\mathcal{A}_\tau(\mathbf{c})$ is non-empty, however, it doesn't guarantee the ACCF in (15) to be zero. Then $|\mathbf{Z}_L \setminus \mathcal{T}_c| \leq L - \prod_{i=1}^k p_i^{m_i - n_i}$, and so there exist at most $L - \prod_{i=1}^k p_i^{m_i - n_i}$ many τ 's for which $\mathcal{A}_\tau(\mathbf{c}) = \emptyset$. Then (15) can be represented as

$$\Theta(\psi(f|_{\mathbf{x}_J=\mathbf{c}}), \psi(g|_{\mathbf{x}_J=\mathbf{c}}))(\tau) = \begin{cases} \sum_{(x,y) \in \mathcal{A}_\tau(\mathbf{c})} \zeta_q^{f x - g x + \tau}, & \tau \in \mathcal{T}_c, \tau \geq 0, \\ 0, & \text{otherwise.} \end{cases} \quad (18)$$

Below, we present another example to explain the above-described matters which we have mainly defined after Example 2.

Example 3. Let us consider the same function f , as defined in (10), which is presented below:

$$f(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) = 2x_{1,1}x_{1,2} + 4x_{1,2}x_{1,3} + x_{1,2}x_{2,1} + x_{1,2}x_{2,2} + 3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + x_{1,2} + 2.$$

Let us consider that $n_1 = 1$, $n_2 = 0$, and $J = \{J_1, J_2\} = \{J_{1,2}\} = \{2\}$, where $J_2 = \emptyset$. Hence $\mathbf{x}_J = (\mathbf{x}_{1,J_1}, \mathbf{x}_{2,J_2}) = (x_{1,2})$. Then

$$\mathcal{V}_{72}^0 = \{(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) \in \mathcal{V}_{72} : x_{1,2} = 0\}, \quad (19)$$

and

$$\begin{aligned} \mathcal{N}_0 &= \{x \in \mathbf{Z}_{72} : x = 9((x_{1,1}, 0, x_{1,3}) \cdot (4, 2, 1)) + (x_{2,1}, x_{2,2}) \cdot (3, 1), x_{1,1}, x_{1,3} \in \mathbf{Z}_2, x_{2,1}, x_{2,2} \in \mathbf{Z}_3\} \\ &= [0, 17] \cup [36, 53]. \end{aligned} \quad (20)$$

Similarly, we can obtain \mathcal{V}_{72}^1 and \mathcal{N}_1 given below:

$$\mathcal{V}_{72}^1 = \{(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) \in \mathcal{V}_{72} : x_{1,2} = 1\}, \quad (21)$$

and

$$\begin{aligned} \mathcal{N}_1 &= \{x \in \mathbf{Z}_{72} : x = 9((x_{1,1}, 1, x_{1,3}) \cdot (4, 2, 1)) + (x_{2,1}, x_{2,2}) \cdot (3, 1), x_{1,1}, x_{1,3} \in \mathbf{Z}_2, x_{2,1}, x_{2,2} \in \mathbf{Z}_3\} \\ &= [18, 35] \cup [54, 71]. \end{aligned} \quad (22)$$

From (13), we have

$$\psi(f|_{x_{1,2}=0}) = (\zeta_6^2 \zeta_6^2 \zeta_6^2 \zeta_6^2 \zeta_6^4 \zeta_6^0 \zeta_6^2 \zeta_6^0 \zeta_6^4 \zeta_6^2 \zeta_6^2 \zeta_6^2 \zeta_6^4 \zeta_6^0 \zeta_6^2 \zeta_6^0 \zeta_6^4 \mathbf{0}_{18} \zeta_6^2 \zeta_6^2 \zeta_6^2 \zeta_6^2 \zeta_6^4 \zeta_6^0 \zeta_6^2 \zeta_6^0 \zeta_6^4 \zeta_6^5 \zeta_6^5 \zeta_6^5 \zeta_6^1 \zeta_6^3 \zeta_6^5 \zeta_6^3 \zeta_6^1 \mathbf{0}_{18}).$$




Figure 5: Graph of proposed q -ary Functions of Hamming Degree 2




Figure 4: Correlation Plotting of $\psi(f|_{x_{1,2}=0})$

Now following (17), let us find \mathcal{T}_0 , i.e., we have to find those τ for which $\mathcal{A}_\tau(0) \neq \emptyset$. From (16), for some τ , the set $\mathcal{A}_\tau(0)$ is non-empty if there exist at least one pair $(x, x + \tau)$ in $\mathcal{N}_0 \times \mathcal{N}_0$ for some values of x in \mathcal{N}_0 , which says $\tau \in [0, 17] \cup [19, 53]$. Similarly as above, one can obtain $\psi(f|_{x_{1,2}=1})$ and \mathcal{T}_1 .

III. PROPOSED q -ARY FUNCTIONS AND CCCS

Let $f : \mathcal{V}_L \rightarrow \mathbb{Z}_q$ be a q -ary function of Hamming degree r such that $G(f|_{\mathbf{x}=\mathbf{c}})$ is a collection of k Hamiltonian paths P_1, P_2, \dots, P_k , for $\mathbf{c} \in \mathcal{V}_L$, where $P_i = G(f_i)$ and

$$f_i = \frac{q}{p_i} \left(\sum_{\alpha=1}^{m_i-n_i-1} x_{i,\pi_i^c(\alpha)} x_{i,\pi_i^c(\alpha+1)} \right) + g_i(x_{i,\pi_i^c(1)}, x_{i,\pi_i^c(2)}, \dots, x_{i,\pi_i^c(m_i-n_i)}), \quad (23)$$

where $c \in \mathbf{Z}_L$ is the decimal representation of \mathbf{c} , π_i^c is a one-to-one mapping from $\{1, 2, \dots, m_i - n_i\}$ to the set $\{1, 2, \dots, m_i\} \setminus J_i$, and g_i is a linear function over the variables $x_{i,\pi_i^c(1)}, x_{i,\pi_i^c(2)}, \dots$, and $x_{i,\pi_i^c(m_i-n_i)}$, where $i = 1, 2, \dots, k$. Another way we can say $f|_{\mathbf{x}_j=\mathbf{c}} = f_1 + f_2 + \dots + f_k$. As an example, Figure 5 represents the class of q -ary functions of Hamming degree two that

satisfies the afore-mentioned graphical properties that after deletion of the variables x_{i,α_1} , where $\alpha_1 = j_{i,\alpha_2}$, $\alpha_2 = 1, 2, \dots, n_i$, and $i = 1, 2, \dots, k$, which says after restricting \mathbf{x}_J at $\mathbf{c} \in \mathcal{V}_{L'}$, the graph results to a collection of k Hamiltonian paths represented by the quadratic parts in the expression of f_i for $i = 1, 2, \dots, k$ in (23). For a fixed choice of \mathbf{x}_J , the class of Hamming degree two q -ary functions that can be represented by the graph appears in Figure 5 can be expressed as follows:

$$\mathfrak{C}_{J,2} = \left\{ \sum_{i=1}^k \frac{q}{p_i} \left(\sum_{\alpha=1}^{m_i-n_i-1} x_{i,\pi_i(\alpha)} x_{i,\pi_i(\alpha+1)} \right) + \sum_{\mathbf{e} \in \chi} c_{\mathbf{e}} x^{\mathbf{e}} : c_{\mathbf{e}} \in \mathbb{Z}_q, \pi_i \in \mathfrak{P}_{m_i, n_i}, i = 1, 2, \dots, k \right\}, \quad (24)$$

where \mathfrak{P}_{m_i, n_i} is the set of all those one-to-one mappings, from $\{1, 2, \dots, m_i - n_i\}$ to the set $\{1, 2, \dots, m_i\} \setminus J_i$, for which the quadratic term in the expression of f_i given in (23) represent distinct functions and it says, $|\mathfrak{P}_{m_i, n_i}| = \frac{(m_i - n_i)!}{2}$. The set χ in (24) can be expressed as follows:

$$\chi = \chi_1 \cup \chi_2 \cup \chi_3,$$

where

$$\chi_1 = \{\mathbf{e} \in \mathcal{V}_L : 0 \leq \text{wt}(\mathbf{e}) = \text{wt}(\mathbf{e}_J) \leq 2\},$$

$$\chi_2 = \{\mathbf{e} \in \mathcal{V}_L : \text{wt}(\mathbf{e}) = 2, \text{wt}(\mathbf{e}_J) = 1, e_{i,j} \in \{0, 1\} \forall j \in \{1, 2, \dots, m_i\} \setminus J_i, i = 1, 2, \dots, k\},$$

$$\chi_3 = \{\mathbf{e} \in \mathcal{V}_L : \text{wt}(\mathbf{e}) = 1, \text{wt}(\mathbf{e}_J) = 0, e_{i,j} \in \{0, 1\} \forall j \in \{1, 2, \dots, m_i\} \setminus J_i, i = 1, 2, \dots, k\}.$$

The cardinality of χ is $|\chi_1| + |\chi_2| + |\chi_3|$, where

$$|\chi_1| = 1 + \sum_{i=1}^k \left(n_i(p_i - 1) + \binom{n_i}{2} (p_i - 1)^2 \right) + \sum_{i < j} n_i n_j (p_i - 1)(p_j - 1),$$

$$|\chi_2| = (m - n) \sum_{i=1}^k n_i (p_i - 1),$$

and

$$|\chi_3| = m - n.$$

Then we obtain the cardinality of $\mathfrak{C}_{J,2}$ as

$$|\mathfrak{C}_{J,2}| = \left(\prod_{i=1}^k \mathfrak{P}_{m_i, n_i} \right) q^{|\chi|} = \left(\prod_{i=1}^k \frac{(m_i - n_i)!}{2} \right) q^{|\chi|}.$$

As Figure 5 represents a class of functions of Hamming degree 2, in (24), $\pi_i^c = \pi_i$ for all c . Besides $\mathfrak{C}_{J,2} \subset \mathcal{U}_{L,2}$, and the graph of any function in (24) satisfies the graphical properties as introduced in Figure 5. Let us go through the following example to illustrate the Figure 5 and the aforementioned matters as discussed in this section.

Table III: List of Elements in χ_1 and χ_3

χ_1							
$x_{1,1}$	$x_{1,2}$	$x_{1,3}$	$x_{1,4}$	$x_{2,1}$	$x_{2,2}$	$x_{2,3}$	\mathbf{x}^e
							1
				1			$x_{2,1}$
				2			$x_{2,1}^2$
1							$x_{1,1}$
1				1			$x_{1,1}x_{2,1}$
1				2			$x_{1,1}x_{2,1}^2$
χ_3							
	1						$x_{1,2}$
		1					$x_{1,3}$
			1				$x_{1,4}$
						1	$x_{2,3}$
					1		$x_{2,2}$

Example 4. Let us consider $k = 2$, $m_1 = 4$, $m_2 = 3$, $p_1 = 2$, $p_2 = 3$, $q = 6$, and $n_1 = n_2 = 1$. Then $\mathbf{x}_J = (\mathbf{x}_{1J_1}, \mathbf{x}_{2J_2})$, where we assume $\mathbf{x}_{1J_1} = (x_{1,1})$ and $\mathbf{x}_{2J_2} = (x_{2,1})$. Following (23), we obtain

$$\begin{aligned} \mathfrak{C}_{J,2} = & \left\{ 3 \left(x_{1,\pi_1(1)}x_{1,\pi_1(2)} + x_{1,\pi_1(2)}x_{1,\pi_1(3)} \right) \right. \\ & \left. + 2x_{2,\pi_2(1)}x_{2,\pi_2(2)} + \sum_{\mathbf{e} \in \chi} c_{\mathbf{e}}x^{\mathbf{e}} : c_{\mathbf{e}} \in \mathbb{Z}_6, \pi_i \in \mathfrak{P}_{m_i, n_i}, i = 1, 2 \right\}. \end{aligned} \quad (25)$$

Here

$$\begin{aligned} \mathfrak{P}_{4,1} &= \{(\pi_1(1), \pi_1(2), \pi_1(3)) : \pi_1 : \{1, 2, 3\} \rightarrow \{2, 3, 4\} \text{ is an one-to-one mapping}\} \\ &= \{(2, 3, 4), (2, 4, 3), (3, 2, 4)\}, \\ \mathfrak{P}_{3,1} &= \{(\pi_2(1), \pi_2(2)) : \pi_2 : \{1, 2\} \rightarrow \{2, 3\} \text{ is an one-to-one mapping}\} \\ &= \{(2, 3)\}. \end{aligned} \quad (26)$$

The set of elements $\mathbf{e} \in \chi$ and their corresponding monomials \mathbf{x}^e are listed in Table III and Table IV, and $|\chi| = 26$. From (25), (26), Table III and Table IV, we have


$$|\mathfrak{C}_{J,2}| = |\mathfrak{P}_{4,1}| \cdot |\mathfrak{P}_{3,1}| \cdot 6^{26} = 3 \cdot 6^{26}. \quad (27)$$

We can also verify that all the $3 \cdot 6^{26}$ functions $f : \mathcal{V}_{432} \rightarrow \mathbb{Z}_6$ in (25) satisfy the graph as presented in Figure 6, where \mathcal{V}_{432} is presented in Table XI of Appendix B.

Let $f : \mathcal{V}_L \rightarrow \mathbb{Z}_q$ be a q -ary functions of Hamming degree at most r , and satisfies all the graphical and functional properties as introduced in the beginning of Section III and in (23),

Table IV: List of Elements in χ_2

χ_2							
$x_{1,1}$	$x_{1,2}$	$x_{1,3}$	$x_{1,4}$	$x_{2,1}$	$x_{2,2}$	$x_{2,3}$	\mathbf{x}^e
1	1						$x_{1,1}x_{1,2}$
1		1					$x_{1,1}x_{1,3}$
1			1				$x_{1,1}x_{1,4}$
1						1	$x_{1,1}x_{2,3}$
1					1		$x_{1,1}x_{2,2}$
	1			1			$x_{1,2}x_{2,1}$
		1		1			$x_{1,3}x_{2,1}$
			1	1			$x_{1,4}x_{2,1}$
				1		1	$x_{2,1}x_{2,3}$
				1	1		$x_{2,1}x_{2,2}$
	1			2			$x_{1,2}x_{2,1}^2$
		1		2			$x_{1,3}x_{2,1}^2$
			1	2			$x_{1,4}x_{2,1}^2$
				2		1	$x_{2,1}^2x_{2,3}$
				2	1		$x_{2,1}^2x_{2,2}$

Figure 6: Graph of Proposed 6-ary Functions of Hamming Degree 2 with $x_{1,1}$ and $x_{2,1}$ as the Restricted Variables

respectively. In the case $r = 2$, $f \in \mathfrak{C}_{J,2}$. Now using f , let us define the following set of q -ary functions:

$$C_t = \left\{ f + \sum_{i=1}^k \frac{q}{p_i} ((\mathbf{d}_i \cdot \mathbf{x}_{J_i} + d_i x_{i,\pi_i^c(m_i-n_i)}) + (\mathbf{t}_i \cdot \mathbf{x}_{J_i} + t_i x_{i,\pi_i^c(1)})) : \mathbf{d}_i \in \mathbf{Z}_{p_i}^{n_i}, d_i \in \mathbf{Z}_{p_i}, \right. \\ \left. i = 1, 2, \dots, k \right\}, \quad (28)$$

where $\mathbf{t}_i \in \mathbf{Z}_{p_i}^{n_i}$, $t_i \in \mathbf{Z}_{p_i}$, and (\mathbf{t}_i, t_i) is the vectorial form of t , and

$$t = \sum_{i=1}^{k-1} ((\mathbf{t}_i, t_i) \cdot (p_i^{n_i}, p_i^{n_i-1}, \dots, 1)) \prod_{j=1}^{k-i} p_{k-j+1}^{n_{k-j+1}+1} + (\mathbf{t}_k, t_k) \cdot (p_k^{n_k}, p_k^{m_k-2}, \dots, 1). \quad (29)$$

From (28), for each of t in $\{0, 1, \dots, (\prod_{i=1}^k p_i^{n_i+1}) - 1\}$, it is clear that $\psi(C_t)$ forms a complex-valued code over \mathbb{Z}_q , containing K sequences each having length of L . Let us construct the following set of codes

$$\mathcal{C} = \{\psi(C_t) : 0 \leq t < \prod_{i=1}^k p_i^{n_i+1}\}. \quad (30)$$

Now let us construct the following set using the restricted q -ary function $f|_{\mathbf{x}=\mathbf{c}}$ as

$$\mathcal{S}_u^{\mathbf{c}} = \left\{ \sum_{i=1}^k f_i + \frac{q}{p_i} (d_i x_{i, \pi_i^{\mathbf{c}}(m_i - n_i)} + t_i x_{i, \pi_i^{\mathbf{c}}(1)}) : d_i \in \mathbf{Z}_{p_i}, i = 1, 2, \dots, k \right\}, \quad (31)$$

where $u = \sum_{i=1}^{k-1} t_i \prod_{j=1}^{k-i} p_{k-j+1}^{n_{k-j+1}+1} + t_k$ is the decimal representation of (t_1, t_2, \dots, t_k) . Then we define the following sets of SNC complex-valued codes:

$$\mathcal{S}_{\mathbf{c}} = \left\{ \psi(\mathcal{S}_u^{\mathbf{c}}) : 0 \leq u < \prod_{i=1}^k p_i \right\}. \quad (32)$$

In the next section, we shall discuss the correlation properties of the code sets $\mathcal{S}_{\mathbf{c}}$ and \mathcal{C} .

Theorem 1. *For any $\mathbf{c} \in \mathcal{V}_L$, the code set $\mathcal{S}_{\mathbf{c}}$ forms $(\prod_{i=1}^k p_i, L)$ -CCC with $\mathcal{N}_{\mathbf{c}}$ as support.*

Proof: Let us define $h : \mathcal{V}_L^{\mathbf{c}} \rightarrow \mathbb{Z}_q$ be a function given by

$$h = \left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^{\mathbf{c}}(m_i - n_i)} + t_i x_{i, \pi_i^{\mathbf{c}}(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}}.$$

Then

$$\psi(h) = \begin{cases} \zeta_q^{h_x}, & x \in \mathcal{N}_{\mathbf{c}}, \\ 0, & x \in \mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}. \end{cases} \quad (33)$$

As $x \in \mathcal{N}_{\mathbf{c}}$,

$$h_x = h(\mathbf{x}) = \sum_{i=1}^k \left(f_i(\mathbf{x}_i) + \frac{q}{p_i} (d_i x_{i, \pi_i^{\mathbf{c}}(m_i - n_i)} + t_i x_{i, \pi_i^{\mathbf{c}}(1)}) \right).$$

Then

$$\psi(h) = \begin{cases} \prod_{i=1}^k \zeta_q^{(f_i(\mathbf{x}_i) + \frac{q}{p_i} (d_i x_{i, \pi_i^{\mathbf{c}}(m_i - n_i)} + t_i x_{i, \pi_i^{\mathbf{c}}(1)})}), & x \in \mathcal{N}_{\mathbf{c}}, \\ 0, & x \in \mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}. \end{cases} \quad (34)$$

Similarly as h , for $h' : \mathcal{V}_L^{\mathbf{c}} \rightarrow \mathbb{Z}_q$, given by

$$h' = \left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^{\mathbf{c}}(m_i - n_i)} + t'_i x_{i, \pi_i^{\mathbf{c}}(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}},$$

$$\psi(h') = \begin{cases} \zeta_q^{h'_x}, & x \in \mathcal{N}_{\mathbf{c}}, \\ 0, & x \in \mathbf{Z}_L \setminus \mathcal{N}_{\mathbf{c}}. \end{cases} \quad (35)$$

Let us assume $\tau \geq 0$ and $y \in \mathcal{N}_c$. For $\mathbf{y} = (\mathbf{y}_1, \mathbf{y}_2, \dots, \mathbf{y}_k) \in \mathcal{V}_L^c$, as the vector representation of y , and $y = x + \tau$, similarly as (35), $\psi(h')$ can also be expressed as

$$\psi(h') = \begin{cases} \prod_{i=1}^k \zeta_q^{\left(f_i(\mathbf{y}_i) + \frac{q}{p_i} (d_i y_{i, \pi_i^c(m_i - n_i)} + t'_i y_{i, \pi_i^c(1)})\right)}, & y \in \mathcal{N}_c, \\ 0, & y \in \mathbf{Z}_L \setminus \mathcal{N}_c. \end{cases} \quad (36)$$

Let

$$F_{d_i, t_i}(\mathbf{x}_i) = f_i(\mathbf{x}_i) + \frac{q}{p_i} (d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)}), \quad (37)$$

and

$$F_{d_i, t'_i}(\mathbf{y}_i) = f_i(\mathbf{y}_i) + \frac{q}{p_i} (d_i y_{i, \pi_i^c(m_i - n_i)} + t'_i y_{i, \pi_i^c(1)}). \quad (38)$$

Then from (33), and (35), for $u \neq u'$, where $u' = \sum_{i=1}^{k-1} t'_i \prod_{j=1}^{k-i} p_{k-j+1}^{n_{k-j+1}+1} + t'_k$, the ACCF between $\psi(\mathcal{S}_u^c)$ and $\psi(\mathcal{S}_{u'}^c)$ at $\tau \in \mathcal{T}_c$ can be expressed as

$$\begin{aligned} \Theta(\psi(\mathcal{S}_u^c), \psi(\mathcal{S}_{u'}^c))(\tau) &= \sum_{\mathbf{d} \in \mathcal{V}_{L''}} \Theta \left(\psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}} \right), \right. \\ &\quad \left. \psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^c(m_i - n_i)} + t'_i x_{i, \pi_i^c(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}} \right) \right) (\tau) \\ &= \sum_{\mathbf{d} \in \mathcal{V}_{L''}} \sum_{(x, y) \in \mathcal{A}_\tau(\mathbf{c})} \zeta_q^{h_x - h'_y} \\ &= \sum_{(x, y) \in \mathcal{A}_\tau(\mathbf{c})} \prod_{i=1}^k \sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)}, \end{aligned} \quad (39)$$

where $\mathbf{d} = (d_1, d_2, \dots, d_k)$, and $\mathcal{V}_{L''} = \mathbf{Z}_{p_1} \times \mathbf{Z}_{p_2} \times \dots \times \mathbf{Z}_{p_k}$, where $L'' = \prod_{i=1}^k p_i$. As $\mathbf{x} = (\mathbf{x}_1, \mathbf{x}_2, \dots, \mathbf{x}_k)$ and $\mathbf{y} = (\mathbf{y}_1, \mathbf{y}_2, \dots, \mathbf{y}_k)$ are in \mathcal{V}_L^c , from (23), (37), and (39), we have

$$\begin{aligned} &\sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} \\ &= \zeta_q^{f_i(\mathbf{x}_i) - f_i(\mathbf{y}_i)} \zeta_{p_i}^{(t_i x_{i, \pi_i^c(1)} - t'_i y_{i, \pi_i^c(1)})} \sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_{p_i}^{d_i (x_{i, \pi_i^c(m_i - n_i)} - y_{i, \pi_i^c(m_i - n_i)})} \end{aligned} \quad (40)$$

For some $\tau \in \mathcal{T}_c$, there is possibility that there exist $\{i_1, i_2, \dots, i_v\} \subset \{1, 2, \dots, k\}$, where $0 \leq v \leq k$, the following condition holds: $\mathbf{x}_i = \mathbf{y}_i$ for $i \in \{i_1, i_2, \dots, i_v\}$. Then $\mathbf{x}_i \neq \mathbf{y}_i$ for $i \in \{1, 2, \dots, k\} \setminus \{i_1, i_2, \dots, i_v\}$.

Case 1 ($\mathbf{x}_i = \mathbf{y}_i$, $i \in \{i_1, i_2, \dots, i_v\}$). In this case, from (40), we have

$$\begin{aligned} &\sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} \\ &= p_i \zeta_{p_i}^{(t_i - t'_i) x_{i, \pi_i^c(1)}} \end{aligned} \quad (41)$$

As $(x, y) \in \mathcal{A}_\tau(\mathbf{c})$, $\tau = y - x$, we have

$$\tau = \sum_{\substack{i=1 \\ i \notin \{i_1, i_2, \dots, i_v\}}}^k (y_i - x_i) \prod_{j=1}^{k-i} L_{k-j+1}, \quad (42)$$

where $\prod_{j=1}^{k-i} L_{k-j+1} = 1$ if $k \notin \{i_1, i_2, \dots, i_v\}$. In (42), τ is constant for all possible values of $x_i = y_i \in \mathbf{Z}_{L_i}$, which says $\mathcal{A}_\tau(\mathbf{c})$ contains all those $(x, y) \in \mathcal{N}_c \times \mathcal{N}_c$, for which the vector representations \mathbf{x} and \mathbf{y} in \mathcal{V}_L^c of x and y , respectively, follows $\mathbf{x}_i = \mathbf{y}_i$. Then from (41), we have

$$\begin{aligned} & \sum_{\substack{(x, y) \in \mathcal{A}_\tau(\mathbf{c}) \\ x_i = y_i \\ i \in \{i_1, i_2, \dots, i_v\}}} \prod_{i \in \{i_1, i_2, \dots, i_v\}} \sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} \\ &= \begin{cases} \prod_{i \in \{i_1, i_2, \dots, i_v\}} p_i^{m_i - n_i + 1}, & t_i = t'_i, \quad i = 1, 2, \dots, v, \\ 0, & \text{otherwise.} \end{cases} \end{aligned} \quad (43)$$

Case 2 ($x_i \neq y_i$, $i \notin \{i_1, i_2, \dots, i_v\}$). From the expression in (40), this case can be defined into the following sub-cases:

Sub-Case 1 ($x_{i, \pi_i^c(m_i - n_i)} \neq y_{i, \pi_i^c(m_i - n_i)}$). Since $x_{i, \pi_i^c(m_i - n_i)} \neq y_{i, \pi_i^c(m_i - n_i)}$,

$$\sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_{p_i}^{d_i (x_{i, \pi_i^c(m_i - n_i)} - y_{i, \pi_i^c(m_i - n_i)})} = 0.$$

Then again from (40),

$$\sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} = 0.$$

Sub-Case 2 ($x_{i, \pi_i^c(m_i - n_i)} = y_{i, \pi_i^c(m_i - n_i)}$).

$$F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i) = f_i(\mathbf{x}_i) - f_i(\mathbf{y}_i) + (t_i x_{i, \pi_i^c(1)} - t'_i y_{i, \pi_i^c(1)}). \quad (44)$$

Let $(x^\kappa, y^\kappa) \in \mathcal{N}_c \times \mathcal{N}_c$ such that $\mathbf{x}^\kappa = (\mathbf{x}_1^\kappa, \mathbf{x}_2^\kappa, \dots, \mathbf{x}_k^\kappa)$ and $\mathbf{y}^\kappa = (\mathbf{y}_1^\kappa, \mathbf{y}_2^\kappa, \dots, \mathbf{y}_k^\kappa)$ are the vector representation of x^κ and y^κ in \mathcal{V}_L^c , and given by

$$\begin{aligned} \mathbf{x}_i^\kappa &= (x_{i,1}, \dots, x_{i, \pi_i^c(1)}, \dots, ((x_{i, \pi_i^c(l+1)} - \kappa) \bmod p_i), \dots, x_{i, \pi_i^c(m_i - n_i)}, \dots, x_{i, m_i}), \\ \mathbf{y}_i^\kappa &= (y_{i,1}, \dots, y_{i, \pi_i^c(1)}, \dots, ((y_{i, \pi_i^c(l+1)} - \kappa) \bmod p_i), \dots, y_{i, \pi_i^c(m_i - n_i)}, \dots, y_{i, m_i}), \end{aligned} \quad (45)$$

where $\kappa = 1, 2, \dots, p_i - 1$, $1 \leq l < m_i - n_i$, and \mathbf{x}_i^κ and \mathbf{y}_i^κ differs from \mathbf{x}_i and \mathbf{y}_i only at $\pi_i^c(l)$ th position, respectively. We also assume $\pi_i^c(l)$ is the smallest integer such that $x_{i, \pi_i^c(l)} \neq y_{i, \pi_i^c(l)}$,

and $x_{i,\pi_i^c(j)} = y_{i,\pi_i^c(j)}$, where $l < j \leq m_i - n_i$. Then $y^\kappa = x^\kappa + \tau$ and $(x^\kappa, y^\kappa) \in \mathcal{A}_\tau(\mathbf{c})$, for $\kappa = 1, 2, \dots, p_i - 1$. Now

$$\begin{aligned} f_i(\mathbf{x}_i) - f_i(\mathbf{x}_i^\kappa) &= \frac{q}{p_i} \left((x_{i,\pi_i^c(l)}x_{i,\pi_i^c(l+1)} + x_{i,\pi_i^c(l+1)}x_{i,\pi_i^c(l+2)}) - (x_{i,\pi_i^c(l)}(x_{i,\pi_i^c(l+1)} - \kappa + \lambda_i p_i) \right. \\ &\quad \left. - (x_{i,\pi_i^c(l+1)} - \kappa + \lambda_i p_i)x_{i,\pi_i^c(l+2)}) \right) + \lambda'_i(x_{i,\pi_i^c(l+1)} - x_{i,\pi_i^c(l+1)} + \kappa - \lambda_i p_i) \\ &= \frac{q}{p_i}(\kappa - \lambda_i p_i)(x_{i,\pi_i^c(l)} + x_{i,\pi_i^c(l+2)}) + \lambda'_i(\kappa - \lambda_i p_i), \end{aligned} \quad (46)$$

where $\lambda_i = 0$ when $x_{i,\pi_i^c(l+1)} - k \geq 0$, and 1, else, and $\lambda'_i \in \mathbf{Z}_q$, $i = 1, 2, \dots, k$. Similarly,

$$f_i(\mathbf{y}_i) - f_i(\mathbf{y}_i^\kappa) = \frac{q}{p_i}(\kappa - \lambda_i p_i)(y_{i,\pi_i^c(l)} + y_{i,\pi_i^c(l+2)}) + \lambda'_i(\kappa - \lambda_i p_i), \quad (47)$$

From (44), (46), and (47), we have

$$\begin{aligned} F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i) - (F_{d_i, t_i}(\mathbf{x}_i^\kappa) - F_{d_i, t'_i}(\mathbf{y}_i^\kappa)) \\ = f_i(\mathbf{x}_i) - f_i(\mathbf{x}_i^\kappa) - (f_i(\mathbf{y}_i) - f_i(\mathbf{y}_i^\kappa)) \\ = \frac{q}{p_i}(\kappa - \lambda_i p_i)(x_{i,\pi_i^c(l)} - y_{i,\pi_i^c(l)}). \end{aligned} \quad (48)$$

Then

$$\sum_{\kappa=1}^{p_i-1} \zeta_q^{-(F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i))} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i^\kappa) - F_{d_i, t'_i}(\mathbf{y}_i^\kappa)} = \sum_{\kappa=1}^{p_i-1} \zeta_q^{\kappa(x_{i,\pi_i^c(l)} - y_{i,\pi_i^c(l)})} = -1, \quad (49)$$

which says

$$\zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} + \sum_{\kappa=1}^{p_i-1} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i^\kappa) - F_{d_i, t'_i}(\mathbf{y}_i^\kappa)} = 0, \quad (50)$$

Then

$$\sum_{\substack{(x, y) \in \mathcal{A}_\tau(\mathbf{c}) \\ x_i \neq y_i \\ i \notin \{i_1, i_2, \dots, i_v\}}} \prod_{i \notin \{i_1, i_2, \dots, i_v\}} \sum_{d_i \in \mathbf{Z}_{p_i}} \zeta_q^{F_{d_i, t_i}(\mathbf{x}_i) - F_{d_i, t'_i}(\mathbf{y}_i)} = 0. \quad (51)$$

Using all the above cases in (39), we have

$$\Theta(\psi(\mathcal{S}_u^c), \psi(\mathcal{S}_{u'}^c))(\tau) = \begin{cases} \prod_{i=1}^k p_i^{m_i - n_i + 1}, & \tau = 0, u = u', \\ 0, & \text{otherwise.} \end{cases} \quad (52)$$

Therefore the code set \mathcal{S}_c forms $(\prod_{i=1}^k p_i, L)$ -SNC-CCC and from (33), it is clear that the set \mathcal{N}_c is support for \mathcal{S}_c . \blacksquare

As $\mathbf{c} \in \mathcal{V}_{L'}$, for a q -ary function f , there exist $\prod_{i=1}^k p_i^{n_i}$ number of SNC-CCCs \mathcal{S}^c . In the below example, we illustrate Theorem 1 with the help of the 6-ary function f as given in Example 2.

Example 5. Let $f : \mathcal{V}_{72} \rightarrow \mathbb{Z}_6$ be the same 6-ary function as defined in (10). It can be expressed as below:

$$f(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) = 2x_{1,1}x_{1,2} + 4x_{1,2}x_{1,3} + x_{1,2}x_{2,1} + x_{1,2}x_{2,2} + 3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + x_{1,2} + 2.$$

From Figure 7, for $c \in \{0, 1\}$, $G(f|_{x_{1,2}=c})$ is a collection of two Hamiltonian paths identified by the monomials $x_{1,1}x_{1,3}$ and $x_{2,1}x_{2,2}$. Then $n_1 = 1$, $n_2 = 0$, and $J = \{J_1, J_2\} = \{J_{1,2}\} = \{2\}$, where $J_2 = \emptyset$. Hence $\mathbf{x}_J = (\mathbf{x}_{1J_1}, \mathbf{x}_{2J_2}) = (x_{1,2})$. Then

$$\mathcal{V}_{72}^0 = \{(x_{1,1}, x_{1,2}, x_{1,3}, x_{2,1}, x_{2,2}) \in \mathcal{V}_{72} : x_{1,2} = 0\},$$

and

$$\begin{aligned} \mathcal{N}_0 &= \{x \in \mathbf{Z}_{72} : x = (x_{1,1}, 0, x_{1,3}) \cdot (4, 2, 1) + (x_{2,1}, x_{2,2}) \cdot (3, 1), x_{1,1}, x_{1,3} \in \mathbf{Z}_2, x_{2,1}, x_{2,2} \in \mathbf{Z}_3\} \\ &= \{0, 1, \dots, 17\} \cup \{36, 37, \dots, 53\}. \end{aligned} \quad (53)$$

Then $f|_{x_{1,2}=0} = 3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + 2$ and $f|_{x_{1,2}=1} = 3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + 2x_{1,1} + 4x_{1,3} + x_{2,1} + x_{2,2} + 3$, which says, $\pi_1(1) = 1$, $\pi_1(2) = 3$, $\pi_2(1) = 1$, and $\pi_2(2) = 2$. Then following (31), we derive the following set 6-ary functions:

$$\mathcal{S}_u^0 = \{3x_{1,1}x_{1,3} + 2x_{2,1}x_{2,2} + 2 + 3(d_1x_{1,3} + t_1x_{1,1}) + 2(d_2x_{2,2} + t_2x_{2,1}) : d_1 \in \mathbf{Z}_2, d_2 \in \mathbf{Z}_3\}, \quad (54)$$

where $t_1 \in \mathbf{Z}_2$, and $t_2 \in \mathbf{Z}_3$, and $u = 3t_1 + t_2$. We present the set of SNC codes $\mathcal{S}_0 = \{\psi(\mathcal{S}_u^0) : u = 0, 1, \dots, 5\}$ in Table VI. The AACFs and ACCFs of the codes in \mathcal{S}_0 follow the correlation plot as given in Figure 8, which says \mathcal{S}_0 forms (5, 72)-SNC-CCC. Similarly, we can obtain \mathcal{S}_0 and the corresponding SNC code set \mathcal{S}_1 , also and verify that it forms (5, 72)-SNC-CCC. Hence the presented example verifies the proposed result in Theorem 1.




Figure 7: Proposed q -ary Functions




Figure 8: Correlation Plotting for the codes in \mathcal{S}_0

In the following theorem, we shall prove that the set of codes \mathcal{C} forms (K, L) -CCC.

Theorem 2. *The code set \mathcal{C} forms (K, L) -CCC over the alphabet \mathbb{Z}_q .*

Proof: From (28), C_t can be expressed as

$$C_t = \left\{ f + \sum_{i=1}^k \frac{q}{p_i} \left((\mathbf{d}_i + \mathbf{t}_i) \cdot \mathbf{x}_{J_i} + (d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)}) \right) : \mathbf{d}_i \in \mathbf{Z}_{p_i}^{n_i}, d_i \in \mathbf{Z}_{p_i}, i = 1, 2, \dots, k \right\}. \quad (55)$$

Let us assume

$$\mathcal{F} = f + \sum_{i=1}^k \frac{q}{p_i} \left((\mathbf{d}_i + \mathbf{t}_i) \cdot \mathbf{x}_{J_i} + (d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)}) \right),$$

and

$$\mathcal{F}' = f + \sum_{i=1}^k \frac{q}{p_i} \left((\mathbf{d}'_i + \mathbf{t}'_i) \cdot \mathbf{x}_{J_i} + (d'_i x_{i, \pi_i^{c'}(m_i - n_i)} + t'_i x_{i, \pi_i^{c'}(1)}) \right).$$

Let $\mathbf{c} = (\mathbf{c}_1, \mathbf{c}_2, \dots, \mathbf{c}_k)$ and $\mathbf{c}' = (\mathbf{c}'_1, \mathbf{c}'_2, \dots, \mathbf{c}'_k)$, where $\mathbf{c}_i, \mathbf{c}'_i \in \mathbf{Z}_{p_i}^{n_i}$, $i = 1, 2, \dots, k$, which says, $\mathbf{c}, \mathbf{c}' \in \mathcal{V}_L$. Now

$$\psi(\mathcal{F}|_{\mathbf{x}_J=\mathbf{c}}) = \psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} \left(d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)} \right) \right) \Big|_{\mathbf{x}_J=\mathbf{c}} \right) \prod_{i=1}^k \zeta_{p_i}^{(\mathbf{d}_i + \mathbf{t}_i) \cdot \mathbf{c}_i} \quad (56)$$

Similarly,

$$\psi(\mathcal{F}'|_{\mathbf{x}_J=\mathbf{c}'}) = \psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} \left(d'_i x_{i, \pi_i^{c'}(m_i - n_i)} + t'_i x_{i, \pi_i^{c'}(1)} \right) \right) \Big|_{\mathbf{x}_J=\mathbf{c}'} \right) \prod_{i=1}^k \zeta_{p_i}^{(\mathbf{d}'_i + \mathbf{t}'_i) \cdot \mathbf{c}'_i} \quad (57)$$

Now

$$\begin{aligned}
& \Theta(\psi(\mathcal{F}|_{\mathbf{x}_J=\mathbf{c}}), \psi(\mathcal{F}'|_{\mathbf{x}_J=\mathbf{c}'}))(\tau) \\
&= \Theta\left(\psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^c(m_i-n_i)} + t_i x_{i,\pi_i^c(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}}\right), \right. \\
&\quad \left. \psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^{c'}(m_i-n_i)} + t'_i x_{i,\pi_i^{c'}(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}'}\right)\right) (\tau) \prod_{i=1}^k \zeta_{p_i}^{(\mathbf{d}_i \cdot (\mathbf{c}_i - \mathbf{c}'_i)) + ((\mathbf{t}_i \cdot \mathbf{c}_i) - (\mathbf{t}'_i \cdot \mathbf{c}'_i))}
\end{aligned} \tag{58}$$

For a non-negative integer τ ,

$$\begin{aligned}
& \Theta(\psi(C_t), \psi(C_{t'}))(\tau) \\
&= \sum_{\mathbf{D} \in \mathcal{V}_{L'}, \mathbf{d} \in \mathcal{V}_{L''}} \Theta\left(\sum_{\mathbf{c} \in \mathcal{D}'} \psi(\mathcal{F}|_{\mathbf{x}_J=\mathbf{c}}), \sum_{\mathbf{c}' \in \mathcal{D}'} \psi(\mathcal{F}'|_{\mathbf{x}_J=\mathbf{c}'})\right) (\tau) \\
&= \sum_{\mathbf{D} \in \mathcal{V}_{L'}, \mathbf{d} \in \mathcal{V}_{L''}} \sum_{\mathbf{c}, \mathbf{c}' \in \mathcal{V}_{L'}} \Theta\left(\psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^c(m_i-n_i)} + t_i x_{i,\pi_i^c(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}}\right), \right. \\
&\quad \left. \psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^{c'}(m_i-n_i)} + t'_i x_{i,\pi_i^{c'}(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}'})\right) (\tau) \prod_{j=1}^k \zeta_{p_j}^{(\mathbf{d}_j \cdot (\mathbf{c}_j - \mathbf{c}'_j)) + ((\mathbf{t}_j \cdot \mathbf{c}_j) - (\mathbf{t}'_j \cdot \mathbf{c}'_j))},
\end{aligned} \tag{59}$$

where $\mathbf{D} = (\mathbf{d}_1, \mathbf{d}_2, \dots, \mathbf{d}_k)$, $\mathbf{d} = (d_1, d_2, \dots, d_k)$, and $\mathcal{D}'' = \mathbf{Z}_{p_1} \times \mathbf{Z}_{p_2} \times \dots \times \mathbf{Z}_{p_k}$. From (59), we have

$$\begin{aligned}
& \Theta(\psi(C_t), \psi(C_{t'}))(\tau) \\
&= \sum_{\mathbf{d} \in \mathcal{V}_{L''}} \sum_{\mathbf{c}, \mathbf{c}' \in \mathcal{V}_{L'}} \Theta\left(\psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^c(m_i-n_i)} + t_i x_{i,\pi_i^c(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}}\right), \right. \\
&\quad \left. \psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^{c'}(m_i-n_i)} + t'_i x_{i,\pi_i^{c'}(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}'})\right) (\tau) \sum_{\mathbf{D} \in \mathcal{V}_{L'}} \prod_{j=1}^k \zeta_{p_j}^{(\mathbf{d}_j \cdot (\mathbf{c}_j - \mathbf{c}'_j)) + ((\mathbf{t}_j \cdot \mathbf{c}_j) - (\mathbf{t}'_j \cdot \mathbf{c}'_j))} \\
&= |\mathcal{V}_{L'}| \sum_{\mathbf{d} \in \mathcal{V}_{L''}} \sum_{\mathbf{c} \in \mathcal{V}_{L'}} \Theta\left(\psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^c(m_i-n_i)} + t_i x_{i,\pi_i^c(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}}\right), \right. \\
&\quad \left. \psi\left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i,\pi_i^c(m_i-n_i)} + t'_i x_{i,\pi_i^c(1)})\right) \Big|_{\mathbf{x}_J=\mathbf{c}}\right) (\tau) \prod_{j=1}^k \zeta_{p_j}^{(\mathbf{t}_j - \mathbf{t}'_j) \cdot \mathbf{c}_j} \\
&= |\mathcal{V}_{L'}| \sum_{\mathbf{c} \in \mathcal{V}_{L'}} \Theta(\psi(\mathcal{S}_{\mathbf{u}}^{\mathbf{c}}, \mathcal{S}_{\mathbf{u}'}^{\mathbf{c}}))(\tau) \prod_{j=1}^k \zeta_{p_j}^{(\mathbf{t}_j - \mathbf{t}'_j) \cdot \mathbf{c}_j}.
\end{aligned} \tag{60}$$

In Theorem 1, we have

$$\begin{aligned}
\Theta(\psi(\mathcal{S}_u^c), \psi(\mathcal{S}_{u'}^c))(\tau) &= \sum_{\mathbf{d} \in \mathcal{V}_{L'}} \Theta \left(\psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^c(m_i - n_i)} + t_i x_{i, \pi_i^c(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}} \right), \right. \\
&\quad \left. \psi \left(\left(f + \sum_{i=1}^k \frac{q}{p_i} (d_i x_{i, \pi_i^c(m_i - n_i)} + t'_i x_{i, \pi_i^c(1)}) \right) \Big|_{\mathbf{x}_J = \mathbf{c}} \right) \right) (\tau) \\
&= \begin{cases} \prod_{i=1}^k p_i^{m_i - n_i + 1}, & \tau = 0, u = u', \\ 0, & \text{otherwise.} \end{cases}
\end{aligned} \tag{61}$$

From (60) and (61), we have

$$\begin{aligned}
\Theta(\psi(C_t), \psi(C_{t'}))(\tau) &= \begin{cases} |\mathcal{V}_{L'}|^2 \prod_{i=1}^k p_i^{m_i - n_i + 1}, & \mathbf{t}_i = \mathbf{t}'_i, t_i = t'_i, i = 1, 2, \dots, k, \\ 0, & \text{otherwise,} \end{cases} \\
&= \begin{cases} \prod_{i=1}^k p_i^{m_i + n_i + 1}, & t = t', \\ 0, & \text{otherwise,} \end{cases}
\end{aligned} \tag{62}$$

where $u = u' \implies t_i = t'_i, i = 1, 2, \dots, k$. Therefore the code set \mathcal{C} forms (K, L) -CCC. ■

Example 6. Let us consider the same function as defined in Example 5 to illustrate Theorem 2. Then following (28), we derive the following set of 6-ary functions.

$$\begin{aligned}
C_t &= \left\{ f + \sum_{i=1}^2 \frac{q}{p_i} ((\mathbf{d}_i \cdot \mathbf{x}_{J_i} + d_i x_{i, \pi_i^c(m_i - n_i)}) + (\mathbf{t}_i \cdot \mathbf{x}_{J_i} + t_i x_{i, \pi_i^c(1)})) : \mathbf{d}_i \in \mathbf{Z}_{p_i}^{n_i}, d_i \in \mathbf{Z}_{p_i}, \right. \\
&\quad \left. i = 1, 2 \right\} \\
&= \{f + 3((d_{1,1}x_{1,2} + d_1x_{1,3}) + 3(t_{1,1}x_{1,2} + t_1x_{1,1}) + 2(d_2x_{2,2} + t_2x_{2,1})) : d_{1,1}, d_1 \in \mathbf{Z}_2, d_2 \in \mathbf{Z}_3\},
\end{aligned} \tag{63}$$

where $\mathbf{t}_1 = t_{1,1}, t_1 \in \mathbf{Z}_2, \mathbf{d}_1 = d_{1,1}$, and as $n_2 = 0, \mathbf{d}_2, \mathbf{t}_2 \in \emptyset, t_2 \in \mathbf{Z}_3$, and $t = 3(2t_{1,1} + t_1) + t_2$. The \mathbf{Z}_6 -valued codes C_0, C_1, \dots, C_{11} are presented in Table VII, Table VIII, Table IX, and Table X. The AACFs and ACCFs of the codes in $\mathcal{C} = \{\psi(C_t) : 0 \leq t < 12\}$, follow the correlation plot as given in Figure 9. Then \mathcal{C} forms $(12, 72)$ -CCC over \mathbf{Z}_6 and it follows the proposed Theorem 2.




Figure 9: Correlation Plotting for the codes in \mathcal{C}

Corollary 1. *The relationship between the SNC CC $\psi(\mathcal{S}_u^c)$ and the traditional CC $\psi(C_t)$ can be deduced from (31) and (56) in the following form:*

$$\psi(C_t) = \left\{ \sum_{\mathbf{c} \in \mathcal{D}} \psi(\mathcal{S}_u^c) \prod_{i=1}^k \zeta_{p_i}^{(\mathbf{d}_i + \mathbf{t}_i) \cdot \mathbf{c}_i} : \mathbf{d}_i \in \mathbf{Z}_{p_i}^{n_i} \ i = 1, 2, \dots, k \right\}. \quad (64)$$

The above equation establishes a connection between the proposed SNC-CCC introduced in Theorem 1 and the traditional CCC presented in Theorem 2.

In Theorem 2, a variety of outcomes are obtained, some of which encompass existing constructions. The following remark delves into these aspects in depth:

In the following remarks, we compare our proposed results with existing related results.

Remark 1 (Comparison with [2], [5], [7]). *In Theorem 2, the variable K signifies the count of CCs within the set of CCCs, including their constituent sequences, while L represents the sequence length. Additionally, \mathbb{Z}_q denotes the alphabet set. We can revisit the expressions for K , L , and q as follows:*

$$K = \prod_{i=1}^k p_i^{n_i+1}, \quad L = \prod_{i=1}^k p_i^{m_i}, \quad q = \prod_{i=1}^k p_i.$$

For $k = 1$ and $p_1 = 2$, the parameters can be expressed as:

$$K = 2^{n_1+1}, \quad L = 2^{m_1}, \quad q = 2,$$

underscoring that the findings reported in [2], [5], [7] emerge as special cases of Theorem 2, where [2], [5], [7] introduce the construction of GCPs, CCs, and CCCs with the parameters as

mentioned above. It is to be noted here that our proposed construction also works if we choose q to be a positive integer such that $p_i|q$, $i = 1, 2, \dots, k$. As we are interested in small alphabet, throughout the paper we fix q to its minimum value that is $\prod_{i=1}^k p_i$.

Remark 2. In [40], Wang et al proposed a PU matrix based construction of CCCs, followed by a systematic approach to extract p -ary functions, for prime p , as the generators for CCCs of non-power-of-two lengths. The construction method in [40] needs to perform the following steps (unlike our proposed one) to generate CCCs:

- It needs to follow a generic framework for constructing desired PU matrices.
- A series of operations need to be performed to extract multivariable functions from the constructed PU matrices.

In [52, Th. 4], Wang et al proposed a construction of (p, p, p^m) -CCC using multivariable functions which are obtained through the following steps:

- First, construct a Butson-type Hadamard (BH) matrix of order p^n with the help of p -ary sequences with two-level autocorrelation of period $p^n - 1$.
- Then, construct δ -quadratic terms with the help of the constructed BH matrix of order p^n .
- Finally, with the help of δ -quadratic terms and suitable permutation polynomials, multivariable functions are obtained to generate (p, p, p^m) -CCC over the alphabet \mathbb{Z}_p .

Therefore, the afore-mentioned constructions may not be suitable for rapid hardware generations of CCCs. Besides, the proposed construction generates more flexible parameters as compared to [40] and [52].

Remark 3. In the context of the current constructions, the importance of defining the domain and co-domain of a function becomes apparent when considering the alphabet size of the resultant sequences. This study characterizes the domain as $\mathcal{V}_L \subset \mathbb{Z}_q^m$ and the co-domain as \mathbb{Z}_q . This configuration generates sequences of length L over the alphabet \mathbb{Z}_q , which is determined by the prime factors of L . Notably, when co-primes values for $m_i \neq m_j$ occur for some specific indices $i \neq j \in \{1, 2, \dots, k\}$, the proposed construction leads to the creation of CCCs featuring the minimal alphabet $q = \prod_{i=1}^k p_i$. This outcome deviates from existing constructions, particularly in cases where $k \geq 2$. For instance, in a recent work [50], the authors adopt a domain \mathbb{Z}_q^m , where $m \geq 2$, and a co-domain of \mathbb{Z}_q , yielding (q^{n+1}, q^m) -CCCs with an alphabet size of q , where $0 \leq n \leq m - 1$. When dealing with scenarios where $L = \prod_{i=1}^k p_i^{m_i}$ and some of m_1, m_2, \dots, m_k are co-primes to each-other, [50] can also generate a sequence length of L by setting $m = 1$ and $q = L$. However, this yields both the alphabet size and set size as L , which is relatively larger than our outcomes. In practical applications, CCCs characterized by modest set and alphabet sizes tend to outperform those with larger dimensions, owing to considerations like the Peak-to-Mean Envelope Power Ratio (PMEPR) of constituent sequences [2], [7]. This is where our proposed construction showcases its strengths, achieving superior performance when scrutinized through vital parameters such as alphabet and set size.

In Table V, we also compare our proposed construction with the existing constructions of CCCs [5], [9], [30], [50].

Table V: Comparison with [5], [9], [30], [50]

Sequence Class	Type	Set size (K)	Length (L)	Alphabet size	Constraints
[5]	Traditional	2^{k+1}	2^m	q	$m \geq 1, k \geq 0, q$ is even
[9]	Traditional	2^{k+1}	2^m	q	$m \geq 1, k \geq 0, q$ is even
[30]	Traditional	2^{k+1}	2^m	q	$m \geq 1, k \geq 0, q$ is even
[50, Thm. 2]	Traditional	q^{k+1}	q^m	q	$m \geq 1, k \geq 0, q (\geq 2)$ is integer
[50, Thm. 3]	SNC	q^{k+1}	$U(q^m - 1) + V(q - 1) + 1$	$q + 1$	$m \geq 1, k \geq 0, U, V \geq 1, q (\geq 2)$ is integer
<i>Theorem 1</i>	SNC	$\prod_{i=1}^k p_i$	$\prod_{i=1}^k p_i^{m_i}$	$q + 1$	$q = \prod_{i=1}^k p_i, m_i \geq 2$
<i>Theorem 2</i>	Traditional	$\prod_{i=1}^k p_i^{n_i+1}$	$\prod_{i=1}^k p_i^{m_i}$	q	$q = \prod_{i=1}^k p_i, m_i \geq 2, n_i \geq 0, p_i$ is a prime number

IV. CONCLUSION

In this paper, we have firstly proposed q -ary function based construction of SNC-CCCs of length $\prod_{i=1}^k p_i^{m_i}$, set sizes $\prod_{i=1}^k p_i$, and alphabet size is $q + 1$, where $q = \prod_{i=1}^k p_i$. Then the idea of SNC-CCCs has been extended to traditional CCCs of lengths and alphabet size same as of SNC-CCCs, set size $\prod_{i=1}^k p_i^{n_i+1}$, and the alphabet size is q . The proposed construction is able maintain a low alphabet size for a given set of other parameters as compared to the existing works of CCCs, specially, when $k \geq 2$ and some of m_1, m_2, \dots, m_k are co-prime to each other. A detailed connection has also been established between the proposed q -ary functions and the undirected graphs.

Table VII: Codes C_0 , C_1 , and C_2 over \mathbf{Z}_6

C_0	<p>222240204222240204345414543123252321222240204555513531501030105012141210 240204222240204222303432501141210345240204222513531555525054123030105234 204222240204222240321450525105234303204222240531555513543012141054123252 222240204555513531345414543450525054222240204222240204501030105345414543 240204222513531555303432501414543012240204222240204222525054123303432501 204222240531555513321450525432501030204222240204222240543012141321450525 222240204222240204012141210450525054222240204555513531234303432345414543 240204222240204222030105234414543012240204222513531555252321450303432501 204222240204222240054123252432501030204222240531555513210345414321450525 222240204555513531012141210123252321222240204222240204234303432012141210 240204222513531555030105234141210345240204222240204222252321450030105234 204222240531555513054123252105234303204222240204222240210345414054123252</p>
C_1	<p>222402042222402042345030321123414105222402042555135315501252543012303054 240420000240420000303054345141432123240420000513153333525210501030321012 204444024204444024321012303105450141204444024531111351543234525054345030 222402042555135315345030321450141432222402042222402042501252543345030321 240420000513153333303054345414105450240420000240420000525210501303054345 204444024531111351321012303432123414204444024204444024543234525321012303 222402042222402042012303054450141432222402042555135315234525210345030321 240420000240420000030321012414105450240420000513153333252543234303054345 204444024204444024054345030432123414204444024531111351210501252321012303 222402042555135315012303054123414105222402042222402042234525210012303054 240420000513153333030321012141432123240420000240420000252543234030321012 204444024531111351054345030105450141204444024204444024210501252054345030</p>
C_2	<p>222024420222024420345252105123030543222024420555351153501414321012525432 240042444240042444303210123141054501240042444513315111525432345030543450 204000402204000402321234141105012525204000402531333135543450303054501414 222024420555351153345252105450303210222024420222024420501414321345252105 240042444513315111303210123414321234240042444240042444525432345303210123 204000402531333135321234141432345252204000402204000402543450303321234141 222024420222024420012525432450303210222024420555351153234141054345252105 240042444240042444030543450414321234240042444513315111252105012303210123 204000402204000402054501414432345252204000402531333135210123030321234141 222024420555351153012525432123030543222024420222024420234141054012525432 240042444513315111030543450141054501240042444240042444252105012030543450 204000402531333135054501414105012525204000402204000402210123030054501414</p>

Table VIII: Codes C_3 , C_4 , and C_5 over \mathbb{Z}_6

C_3	<p>222240204222240204345414543123252321555513531222240204234303432345414543 240204222240204222303432501141210345513531555240204222252321450303432501 204222240204222240321450525105234303531555513204222240210345414321450525 222240204555513531345414543450525054555513531555513531234303432012141210 240204222513531555303432501414543012513531555513531555252321450030105234 204222240531555513321450525432501030531555513531555513210345414054123252 222240204222240204012141210450525054555513531222240204501030105012141210 240204222240204222030105234414543012513531555240204222525054123030105234 204222240204222240054123252432501030531555513204222240543012141054123252 222240204555513531012141210123252321555513531555513531501030105345414543 240204222513531555030105234141210345513531555513531555525054123303432501 204222240531555513054123252105234303531555513531555513543012141321450525</p>
C_4	<p>222402042222402042345030321123414105555135315222402042234525210345030321 240420000240420000303054345141432123513153333240420000252543234303054345 204444024204444024321012303105450141531111351204444024210501252321012303 222402042555135315345030321450141432555135315555135315234525210012303054 240420000513153333303054345414105450513153333513153333252543234030321012 204444024531111351321012303432123414531111351531111351210501252054345030 222402042222402042012303054450141432555135315222402042501252543012303054 240420000240420000030321012414105450513153333240420000525210501030321012 204444024204444024054345030432123414531111351204444024543234525054345030 222402042555135315012303054123414105555135315555135315501252543345030321 240420000513153333030321012141432123513153333513153333525210501303054345 204444024531111351054345030105450141531111351531111351543234525321012303</p>
C_5	<p>222024420222024420345252105123030543555351153222024420234141054345252105 240042444240042444303210123141054501513315111240042444252105012303210123 204000402204000402321234141105012525531333135204000402210123030321234141 222024420555351153345252105450303210555351153555351153234141054012525432 240042444513315111303210123414321234513315111513315111252105012030543450 204000402531333135321234141432345252531333135531333135210123030054501414 222024420222024420012525432450303210555351153222024420501414321012525432 240042444240042444030543450414321234513315111240042444525432345030543450 204000402204000402054501414432345252531333135204000402543450303054501414 222024420555351153012525432123030543555351153555351153501414321345252105 240042444513315111030543450141054501513315111513315111525432345303210123 204000402531333135054501414105012525531333135531333135543450303321234141</p>

Table IX: Codes C_6 , C_7 , and C_8 over \mathbf{Z}_6

C_6	<p>222240204222240204012141210450525054222240204555513531234303432345414543 240204222240204222030105234414543012240204222513531555252321450303432501 204222240204222240054123252432501030204222240531555513210345414321450525 222240204555513531012141210123252321222240204222240204234303432012141210 240204222513531555030105234141210345240204222240204222252321450030105234 204222240531555513054123252105234303204222240204222240210345414054123252 222240204222240204345414543123252321222240204555513531501030105012141210 240204222240204222303432501141210345240204222513531555525054123030105234 204222240204222240321450525105234303204222240531555513543012141054123252 222240204555513531345414543450525054222240204222240204501030105345414543 240204222513531555303432501414543012240204222240204222525054123303432501 204222240531555513321450525432501030204222240204222240543012141321450525</p>
C_7	<p>222402042222402042012303054450141432222402042555135315234525210345030321 240420000240420000030321012414105450240420000513153333252543234303054345 204444024204444024054345030432123414204444024531111351210501252321012303 222402042555135315012303054123414105222402042222402042234525210012303054 240420000513153333030321012141432123240420000240420000252543234030321012 204444024531111351054345030105450141204444024204444024210501252054345030 222402042222402042345030321123414105222402042555135315501252543012303054 240420000240420000303054345141432123240420000513153333525210501030321012 204444024204444024321012303105450141204444024531111351543234525054345030 222402042555135315345030321450141432222402042222402042501252543345030321 240420000513153333303054345414105450240420000240420000525210501303054345 204444024531111351321012303432123414204444024204444024543234525321012303</p>
C_8	<p>222024420222024420012525432450303210222024420555351153234141054345252105 240042444240042444030543450414321234240042444513315111252105012303210123 204000402204000402054501414432345252204000402531333135210123030321234141 222024420555351153012525432123030543222024420222024420234141054012525432 240042444513315111030543450141054501240042444240042444252105012030543450 204000402531333135054501414105012525204000402204000402210123030054501414 222024420222024420345252105123030543222024420555351153501414321012525432 240042444240042444303210123141054501240042444513315111525432345030543450 204000402204000402321234141105012525204000402531333135543450303054501414 222024420555351153345252105450303210222024420222024420501414321345252105 240042444513315111303210123414321234240042444240042444525432345303210123 204000402531333135321234141432345252204000402204000402543450303321234141</p>

Table X: Codes C_9 , C_{10} , and C_{11} over \mathbf{Z}_6

C_9	<p>222240204222240204012141210450525054555513531222240204501030105012141210 240204222240204222030105234414543012513531555240204222525054123030105234 204222240204222240054123252432501030531555513204222240543012141054123252 222240204555513531012141210123252321555513531555513531501030105345414543 240204222513531555030105234141210345513531555513531555525054123303432501 204222240531555513054123252105234303531555513531555513543012141321450525 222240204222240204345414543123252321555513531222240204234303432345414543 240204222240204222303432501141210345513531555240204222252321450303432501 204222240204222240321450525105234303531555513204222240210345414321450525 222240204555513531345414543450525054555513531555513531234303432012141210 240204222513531555303432501414543012513531555513531555252321450030105234 204222240531555513321450525432501030531555513531555513210345414054123252</p>
C_{10}	<p>222402042222402042012303054450141432555135315222402042501252543012303054 240420000240420000030321012414105450513153333240420000525210501030321012 204444024204444024054345030432123414531111351204444024543234525054345030 222402042555135315012303054123414105555135315555135315501252543345030321 240420000513153333030321012141432123513153333513153333525210501303054345 204444024531111351054345030105450141531111351531111351543234525321012303 222402042222402042345030321123414105555135315222402042234525210345030321 240420000240420000303054345141432123513153333240420000252543234303054345 204444024204444024321012303105450141531111351204444024210501252321012303 222402042555135315345030321450141432555135315555135315234525210012303054 240420000513153333303054345414105450513153333513153333252543234030321012 204444024531111351321012303432123414531111351531111351210501252054345030</p>
C_{11}	<p>222024420222024420012525432450303210555351153222024420501414321012525432 240042444240042444030543450414321234513315111240042444525432345030543450 204000402204000402054501414432345252531333135204000402543450303054501414 222024420555351153012525432123030543555351153555351153501414321345252105 240042444513315111030543450141054501513315111513315111525432345303210123 204000402531333135054501414105012525531333135531333135543450303321234141 222024420222024420345252105123030543555351153222024420234141054345252105 240042444240042444303210123141054501513315111240042444252105012303210123 204000402204000402321234141105012525531333135204000402210123030321234141 222024420555351153345252105450303210555351153555351153234141054012525432 240042444513315111303210123414321234513315111513315111252105012030543450 204000402531333135321234141432345252531333135531333135210123030054501414</p>

APPENDIX B
SET OF ELEMENTS IN \mathcal{V}_{432}

Table XI: The Set \mathcal{V}_{432} for $p_1 = 2$, $p_2 = 3$, $m_1 = 4$, and $m_2 = 3$

000000	0001110	0010220	1000100	1001210	1011020	0100200	0110010	0111120	1101001	1110112
0000001	0001111	0010221	1000101	1001211	1011021	0100201	0110011	0111121	1101002	1110120
0000002	0001112	0010222	1000102	1001212	1011022	0100202	0110012	0111122	1101010	1110121
0000010	0001120	0011000	1000110	1001220	1011100	0100210	0110020	0111200	1101011	1110122
0000011	0001121	0011001	1000111	1001221	1011101	0100211	0110021	0111201	1101012	1110200
0000012	0001122	0011002	1000112	1001222	1011102	0100212	0110022	0111202	1101020	1110201
0000020	0001200	0011010	1000120	1010000	1011110	0100220	0110100	0111210	1101021	1110202
0000021	0001201	0011011	1000121	1010001	1011111	0100221	0110101	0111211	1101022	1110210
0000022	0001202	0011012	1000122	1010002	1011112	0100222	0110102	0111212	1101100	1110211
0000100	0001210	0011020	1000200	1010010	1011120	0101000	0110110	0111220	1101101	1110212
0000101	0001211	0011021	1000201	1010011	1011121	0101001	0110111	0111221	1101102	1110220
0000102	0001212	0011022	1000202	1010012	1011122	0101002	0110112	0111222	1101110	1110221
0000110	0001220	0011100	1000210	1010020	1011200	0101010	0110120	1100000	1101111	1110222
0000111	0001221	0011101	1000211	1010021	1011201	0101011	0110121	1100001	1101112	1111000
0000112	0001222	0011102	1000212	1010022	1011202	0101012	0110122	1100002	1101120	1111001
0000120	0010000	0011110	1000220	1010100	1011210	0101020	0110200	1100010	1101121	1111002
0000121	0010001	0011111	1000221	1010101	1011211	0101021	0110201	1100011	1101122	1111010
0000122	0010002	0011112	1000222	1010102	1011212	0101022	0110202	1100012	1101200	1111011
0000200	0010010	0011120	1001000	1010110	1011220	0101100	0110210	1100020	1101201	1111012
0000201	0010011	0011121	1001001	1010111	1011221	0101101	0110211	1100021	1101202	1111020
0000202	0010012	0011122	1001002	1010112	1011222	0101102	0110212	1100022	1101210	1111021
0000210	0010020	0011200	1001010	1010120	0100000	0101110	0110220	1100100	1101211	1111022
0000211	0010021	0011201	1001011	1010121	0100001	0101111	0110221	1100101	1101212	1111100
0000212	0010022	0011202	1001012	1010122	0100002	0101112	0110222	1100102	1101220	1111101
0000220	0010100	0011210	1001020	1010200	0100010	0101120	0111000	1100110	1101221	1111102
0000221	0010101	0011211	1001021	1010201	0100011	0101121	0111001	1100111	1101222	1111110
0000222	0010102	0011212	1001022	1010202	0100012	0101122	0111002	1100112	1110000	1111111
0001000	0010110	0011220	1001100	1010210	0100020	0101200	0111010	1100120	1110001	1111112
0001001	0010111	0011221	1001101	1010211	0100021	0101201	0111011	1100121	1110002	1111120
0001002	0010112	0011222	1001102	1010212	0100022	0101202	0111012	1100122	1110010	1111121
0001010	0010120	1000000	1001110	1010220	0100100	0101210	0111020	1100200	1110011	1111122
0001011	0010121	1000001	1001111	1010221	0100101	0101211	0111021	1100201	1110012	1111200
0001012	0010122	1000002	1001112	1010222	0100102	0101212	0111022	1100202	1110020	1111201
0001020	0010200	1000010	1001120	1011000	0100110	0101220	0111100	1100210	1110021	1111202
0001021	0010201	1000011	1001121	1011001	0100111	0101221	0111101	1100211	1110022	1111210
0001022	0010202	1000012	1001122	1011002	0100112	0101222	0111102	1100212	1110100	1111211
0001100	0010210	1000020	1001200	1011010	0100120	0110000	0111110	1100220	1110101	1111212
0001101	0010211	1000021	1001201	1011011	0100121	0110001	0111111	1100221	1110102	1111220
0001102	0010212	1000022	1001202	1011012	0100122	0110002	0111112	1100222	1110110	1111221
								1101000	1110111	1111222

REFERENCES

- [1] C.-C. Tseng and C. Liu, "Complementary sets of sequences," *IEEE Trans. Inf. Theory*, vol. 18, no. 5, pp. 644–652, Sept. 1972.
- [2] K. G. Paterson, "Generalized Reed-Muller codes and power control in OFDM modulation," *IEEE Trans. Inf. Theory*, vol. 46, no. 1, pp. 104–120, Jan. 2000.
- [3] Z. Liu, Y. Li, and Y. L. Guan, "New constructions of general QAM Golay complementary sequences," *IEEE Trans. Inf. Theory*, vol. 59, no. 11, pp. 7684–7692, Nov. 2013.
- [4] M. J. E. Golay, "Multislit spectroscopy," *Journal of the Optical Society of America*, vol. 39, no. 6, pp. 437–444, June 1949.
- [5] A. Rathinakumar and A. K. Chaturvedi, "Complete mutually orthogonal Golay complementary sets from Reed-Muller codes," *IEEE Trans. Inf. Theory*, vol. 54, no. 3, pp. 1339–1346, Mar. 2008.
- [6] N. Suehiro and M. Hatori, "N-shift cross-orthogonal sequences," *IEEE Trans. Inf. Theory*, vol. 34, no. 1, pp. 143–146, 1988.
- [7] J. A. Davis and J. Jedwab, "Peak-to-mean power control in OFDM, Golay complementary sequences, and Reed-Muller codes," *IEEE Trans. Inf. Theory*, vol. 45, no. 7, pp. 2397–2417, Nov. 1999.
- [8] H.-H. Chen, *The Next Generation CDMA Technologies*. Wiley, 2007.
- [9] Z. Liu, Y. L. Guan, and U. Paramalli, "New complete complementary codes for peak-to-mean power control in multi-carrier CDMA," *IEEE Trans. Commun.*, vol. 62, no. 3, pp. 1105–1113, Mar. 2014.
- [10] S. Wang and A. Abdi, "MIMO ISI channel estimation using uncorrelated Golay complementary sets of polyphase sequences," *IEEE Trans. Veh. Technol.*, vol. 56, no. 5, pp. 3024–3039, Sept. 2007.
- [11] A. Pezeshki, A. R. Calderbank, W. Moran, and S. D. Howard, "Doppler resilient Golay complementary waveforms," *IEEE Trans. Inf. Theory*, vol. 54, no. 9, pp. 4254–4266, Sept. 2008.
- [12] J. Tang, N. Zhang, Z. Ma, and B. Tang, "Construction of Doppler resilient complete complementary code in MIMO radar," *IEEE Trans. Signal Process.*, vol. 62, no. 18, pp. 4704–4712, Sept. 2014.
- [13] T. Kojima, T. Tachikawa, A. Oizumi, Y. Yamaguchi, and U. Paramalli, "A disaster prevention broadcasting based on data hiding scheme using complete complementary codes," in *Proc. International Symposium on Information Theory and its Applications (ISITA)*, Oct. 2014, pp. 45–49.
- [14] P. Sarkar, S. Majhi, and Z. Liu, "Optimal Z -complementary code set from generalized Reed-Muller codes," *IEEE Trans. Commun.*, vol. 67, no. 3, pp. 1783–1796, Mar. 2019.
- [15] P. Sarkar, S. Majhi, and Z. Liu, "Pseudo-boolean functions for optimal z -complementary code sets with flexible lengths," *IEEE Signal Process. Lett.*, vol. 28, pp. 1350–1354, 2021.
- [16] A. R. Adhikary, Y. Feng, Z. Zhou, and P. Fan, "Asymptotically optimal and near-optimal aperiodic quasi-complementary sequence sets based on florentine rectangles," *IEEE Trans. Commun.*, vol. 70, no. 3, pp. 1475–1485, Mar. 2022.
- [17] Z. Zhou, F. Liu, A. R. Adhikary, and P. Fan, "A generalized construction of multiple complete complementary codes and asymptotically optimal aperiodic quasi-complementary sequence sets," *IEEE Trans. Commun.*, vol. 68, no. 6, pp. 3564–3571, June 2020.
- [18] P. Sarkar, C. Li, S. Majhi, and Z. Liu, "New correlation bound and construction of quasi-complementary sequence sets," *IEEE Trans. Inf. Theory*, 2024.
- [19] X. Deng and P. Fan, "Spreading sequence sets with zero correlation zone," *Electro. Lett.*, vol. 36, no. 11, pp. 993–994, 2000.
- [20] Y. Liu, C. Chen, and Y. T. Su, "New constructions of zero-correlation zone sequences," *IEEE Trans. Inf. Theory*, vol. 59, no. 8, pp. 4994–5007, 2013.
- [21] R. Appuswamy and A. K. Chaturvedi, "A new framework for constructing mutually orthogonal complementary sets and ZCZ sequences," *IEEE Trans. Inf. Theory*, vol. 52, no. 8, pp. 3817–3826, 2006.
- [22] X. Tang, P. Fan, and J. Lindner, "Multiple binary ZCZ sequence sets with good cross-correlation property based on complementary sequence sets," *IEEE Trans. Inf. Theory*, vol. 56, no. 8, pp. 4038–4045, Aug. 2010.
- [23] Z. Liu, Y. L. Guan, and U. Paramalli, "A new construction of zero correlation zone sequences from generalized reed-muller codes," in *Proc. 2014 IEEE Inf. Theory Workshop (ITW'2014)*.
- [24] M. J. E. Golay, "Complementary series," *IRE Trans. Inf. Theory*, vol. 7, no. 2, pp. 82–87, Apr. 1961.
- [25] S. Z. Budišin, "New complementary pairs of sequences," *Electro. Lett.*, vol. 26, no. 13, pp. 881–883, June 1990.
- [26] —, "New multilevel complementary pairs of sequences," *Electro. Lett.*, vol. 26, no. 22, pp. 1861–1863, Oct. 1990.

- [27] K. U. Schmidt, "Complementary sets, generalized Reed-Muller codes, and power control for OFDM," *IEEE Trans. Inf. Theory*, vol. 53, no. 2, pp. 808–814, Feb. 2007.
- [28] P. Sarkar, S. Majhi, and Z. Liu, "A direct and generalized construction of polyphase complementary sets with low pmep and high code-rate for ofdm system," *IEEE Trans. Commun.*, vol. 68, no. 10, pp. 6245–6262, 2020.
- [29] C. Chen, "Complementary sets of non-power-of-two length for peak-to-average power ratio reduction in OFDM," *IEEE Trans. Inf. Theory*, vol. 62, no. 12, pp. 7538–7545, Dec. 2016.
- [30] C. Chen, C. Wang, and C. Chao, "Complete complementary codes and generalized Reed-Muller codes," *IEEE Commun. Lett.*, vol. 12, no. 11, pp. 849–851, Nov. 2008.
- [31] S.-W. Wu, C.-Y. Chen, and Z. Liu, "How to construct mutually orthogonal complementary sets with non-power-of-two lengths?" *IEEE Trans. Inf. Theory*, vol. 67, no. 6, pp. 3464–3472, 2021.
- [32] B. Shen, Y. Yang, Y. Feng, and Z. Zhou, "A generalized construction of mutually orthogonal complementary sequence sets with non-power-of-two lengths," *IEEE Trans. Commun.*, vol. 69, no. 7, pp. 4247–4253, 2021.
- [33] H. Xiao and X. Cao, "New constructions of mutually orthogonal complementary sets and z-complementary code sets based on extended Boolean functions," *Cryptogr. Commun.*, 2023.
- [34] P. Kumar, S. Majhi, and S. Paul, "A direct construction of golay complementary pairs and binary complete complementary codes of length non-power of two," *IEEE Trans. commun.*, vol. 71, no. 3, pp. 1352–1363, 2023.
- [35] S. Budisin and P. Spasojević, "Paraunitary generation/correlation of QAM complementary sequence pairs," *Proc. Cryptogr. Commun.*, vol. 6, no. 1, pp. 59–102, Oct. 2014.
- [36] Z. Wang, G. Wu, and D. Ma, "A new method to construct Golay complementary set by paraunitary matrices and Hadamard matrices," in *Proc. Sequences and Their Applications (SETA)*, Sept. 2016, pp. 252–264.
- [37] S. Das, S. Budišin, S. Majhi, Z. Liu, and Y. L. Guan, "A multiplier-free generator for polyphase complete complementary codes," *IEEE Trans. Signal Process.*, vol. 66, no. 5, pp. 1184–1196, Mar. 2018.
- [38] S. Das, S. Majhi, and Z. Liu, "A novel class of complete complementary codes and their applications for APU matrices," *IEEE Signal Process. Lett.*, vol. 25, no. 9, pp. 1300–1304, Sept. 2018.
- [39] S. Das, S. Majhi, S. Budišin, and Z. Liu, "A new construction framework for polyphase complete complementary codes with various lengths," *IEEE Trans. Signal Process.*, vol. 67, no. 10, pp. 2639–2648, May 2019.
- [40] Z. Wang, D. Ma, G. Gong, and E. Xue, "New construction of complementary sequence (or array) sets and complete complementary codes," *IEEE Trans. Inf. Theory*, vol. 67, no. 7, pp. 4902–4928, 2021.
- [41] Q. Zhao and B. M. Sadler, "A survey of dynamic spectrum access," *IEEE Signal Process. Mag.*, vol. 24, no. 3, pp. 79–89, 2007.
- [42] S. Haykin, "Cognitive radio: brain-empowered wireless communications," *IEEE journal on selected areas in communications*, vol. 23, no. 2, pp. 201–220, 2005.
- [43] —, "Cognitive radar: a way of the future," *IEEE Signal Process. Mag.*, vol. 23, no. 1, pp. 30–40, 2006.
- [44] B. Shen, Y. Yang, P. Fan, and Z. Zhou, "Constructions of non-contiguous complementary sequence sets and their applications," *IEEE Trans. Wireless Commun.*, vol. 21, no. 7, pp. 4871–4882, 2022.
- [45] A. Şahin and R. Yang, "An uplink control channel design with complementary sequences for unlicensed bands," *IEEE Trans. Wireless Commun.*, vol. 19, no. 10, pp. 6858–6870, 2020.
- [46] A. Şahin and R. Yang, "A generic complementary sequence construction and associated encoder/decoder design," *IEEE Trans. Commun.*, vol. 69, no. 11, pp. 7691–7705, 2021.
- [47] Y. Zhou, Y. Yang, Z. Zhou, K. Anand, S. Hu, and Y. L. Guan, "New complementary sets with low papr property under spectral null constraints," *IEEE Trans. Inf. Theory*, vol. 66, no. 11, pp. 7022–7032, 2020.
- [48] R. N. Ipanov, A. I. Baskakov, N. Olyunin, and M.-H. Ka, "Radar signals with zac based on pairs of d-code sequences and their compression algorithm," *IEEE Signal Process. Lett.*, vol. 25, no. 10, pp. 1560–1564, 2018.
- [49] Y. Li, L. Tian, and Y. Zeng, "Spectrally-null-constrained zc sequences for mimo-ofdm channel estimation over non-contiguous carriers," *IEEE commun. Lett.*, vol. 27, no. 2, pp. 442–446, 2022.
- [50] B. Shen, Y. Yang, Z. Zhou, and S. Mesnager, "Constructions of spectrally null constrained complete complementary codes via the graph of extended Boolean functions," *IEEE Trans. Inf. Theory*, vol. 69, no. 9, pp. 6028–6039, 2023.
- [51] P. Sarkar, Z. Liu, and S. Majhi, "Multivariable function for new complete complementary codes with arbitrary lengths," 2021.
- [52] Z. Wang and G. Gong, "Constructions of complementary sequence sets and complete complementary codes by ideal two-level autocorrelation sequences and permutation polynomials," *IEEE Trans. Inf. Theory*, vol. 69, no. 7, pp. 4723–4739, 2023.