

# A Direct Construction of Cross Z-Complementary Sequence Sets with Large Set Size

Praveen Kumar, Sudhan Majhi, *Senior Member, IEEE*, Subhabrata Paul

**Abstract**—This letter presents a direct construction of cross Z-complementary sequence sets (CZCSSs), whose aperiodic correlation sums exhibit zero correlation zones at both the front-end and tail-end shifts. CZCSS can be regarded as an extension of the symmetrical Z-complementary code set (SZCCS). The available construction of SZCCS has a limitation on the set size, with a maximum set size of 8. The proposed generalized Boolean function based construction can generate CZCSS of length in the form of non-power-of-two with variable set size  $2^{n+1}$ , where each code has  $2^{n+1}$  constituent sequences. The proposed construction also yields cross Z-complementary pairs and cross Z-complementary sets with a large number of constituent sequences compared to the existing work.

**Index Terms**—Cross Z-complementary pair (CZCP), cross Z-complementary set (CZCS), cross Z-complementary sequence set (CZCSS), generalized Boolean functions (GBFs), zero-correlation-zone (ZCZ).

## I. INTRODUCTION

THE idea of Z-complementary pairs (ZCPs) was introduced by Fan *et al.* [1]. Within a certain zone, known as the zero-correlation zone (ZCZ), the aperiodic auto-correlation sum (AACs) of the two sequences in a ZCP is zero. When this ZCZ width  $Z$  is equal to the sequence length  $N$ , ZCP becomes a Golay complementary pair (GCP). Unlike GCPs, ZCPs are available in arbitrary lengths with a variety of ZCZ widths [2]–[6].

Liu *et al.* examined the training sequence design for the spatial modulation (SM) system in [7], leading to the development of the cross Z-complementary pair (CZCP). CZCPs have both front-end and tail-end ZCZ for AACs and tail-end ZCZ for aperiodic cross-correlation sum (ACCS). The cross-ZCZ (CZCZ) ratio of a CZCP is defined as the ratio of ZCZ width  $Z$  and maximum possible ZCZ width  $Z_{max}$ . The maximum possible ZCZ width for a CZCP of length  $N$  is  $N/2$ , i.e.,  $Z_{max} = N/2$ . A CZCP is called perfect if its CZCZ ratio takes the value equal to 1. Several constructions of CZCPs with different lengths and CZCZ ratios can be found in [8]–[13]. Recently, the CZCPs are extended to cross Z-complementary set (CZCS) [14].

The idea of ZCPs introduced in [1] was generalized to Z-complementary code set (ZCCS) by Feng *et al.* in [15]. ZCCSs only consider the front-end ZCZ of the AACs and ACCSs [16]–[19]. Recently, the idea of ZCCS is extended to

symmetrical-ZCCS (SZCCS) which exhibits both the front-end and tail-end ZCZ properties [20]. The authors in [20], have presented a generalized Boolean functions (GBFs) based construction of  $(8, 8, 2^m, 2^{m-2} - 1)$ -SZCCS. In practice, a front-end ZCZ and a tail-end ZCZ have particular interest for mitigating interference with small and large delays, respectively. The cross Z-complementary sequence set (CZCSS) is a generalization of SZCCS, which satisfies all the properties of SZCCS and have some extra correlation properties satisfying for tail-end ZCZ. SZCCSs with larger set size are used in designing training sequences for broadband generalized spatial modulation (GSM) systems over frequency-selective channels [20].

In this letter, we proposed a GBFs based construction of CZCSSs of non-power-of-two length whose set size is the same as the number of constituent sequences. To generate the desired CZCSSs, first a new CZCPs are constructed, then by using the proposed CZCPs and CZCPs of [8], CZCSSs with large set size are constructed. To the best of the authors' knowledge, the proposed construction of CZCSSs is not reported in the existing literature. Since CZCS and SZCCS are special cases of the proposed CZCSS, so this letter also facilitates these constructions with large flock size and set size, respectively.

The rest of the letter is arranged in the following manner. Section II covers the fundamental notations and definitions. Section III discusses the proposed CZCSS construction based on GBF. Section IV has final observations.

## II. NOTATIONS AND DEFINITIONS

The basic notations, definitions, and earlier known findings that are necessary for the proposed construction are explained in this section.

**Definition 1:** Let  $\mathbf{c}_1 = (c_{10}, c_{11}, \dots, c_{1L-1})$  and  $\mathbf{c}_2 = (c_{20}, c_{21}, \dots, c_{2L-1})$  be two  $L$  length sequences over  $\mathbb{Z}_q$ . At a shift  $\tau$ , the aperiodic cross-correlation function (ACCF) is defined by

$$C(\mathbf{c}, \mathbf{d})(\tau) = \begin{cases} \sum_{i=0}^{L-1-\tau} \omega^{c_{1i} - c_{2i+\tau}}, & 0 \leq \tau \leq L-1, \\ \sum_{i=0}^{L-1+\tau} \omega^{c_{1i-\tau} - c_{2i}}, & -L+1 \leq \tau \leq -1, \\ 0, & |\tau| \geq L, \end{cases} \quad (1)$$

where  $q (\geq 2)$  is an integer and  $\omega = \exp(2\pi\sqrt{-1}/q)$ . When  $\mathbf{c}_1 = \mathbf{c}_2$ ,  $A(\mathbf{c}_1, \mathbf{c}_2)(\tau)$  is called aperiodic auto-correlation function (AACF) of  $\mathbf{c}_1$  and it is denoted by  $A(\mathbf{c}_1)(\tau)$ .

Praveen Kumar and Subhabrata Paul are with the Department of Mathematics, IIT Patna, Bihta, Patna, 801106, Bihar, India (e-mail: praveen\_2021ma03@iitp.ac.in; subhabrata@iitp.ac.in).

Sudhan Majhi is with the Department of Electrical Communication Engineering (IISC), Indian Institute of Science, Bangalore, CV Raman Rd, 560012, Karnataka, India (email:smajhi@iisc.ac.in)

**Definition 2:** A ZCP with ZCZ  $Z$  is a pair of sequences  $\mathbf{c}$  and  $\mathbf{d}$  of length  $N$  whose AACSS is zero for all non-zero shifts inside a zone, i.e.,

$$A(\mathbf{c})(\tau) + A(\mathbf{d})(\tau) = 0, \text{ for all } 0 < \tau < Z. \quad (2)$$

When  $Z = N$ , the pair  $(\mathbf{c}, \mathbf{d})$  is known as a GCP.

**Definition 3:** For an integer  $Z$  and  $N$ , let  $\mathcal{U}_1 = \{1, 2, \dots, Z\}$  and  $\mathcal{U}_2 = \{N - Z, N - Z + 1, \dots, N - 1\}$ . Then a length  $N$  sequence pair  $(\mathbf{c}, \mathbf{d})$  is called an  $(N, Z)$ -CZCP if it satisfies the following two conditions:

$$\begin{aligned} C1: & A(\mathbf{c})(\tau) + A(\mathbf{d})(\tau) = 0, \text{ for all } |\tau| \in \mathcal{U}_1 \cup \mathcal{U}_2; \\ C2: & C(\mathbf{c}, \mathbf{d})(\tau) + C(\mathbf{d}, \mathbf{c})(\tau) = 0, \text{ for all } |\tau| \in \mathcal{U}_2. \end{aligned} \quad (3)$$

**Definition 4:** Consider a set  $\mathcal{C} = \{C^0, C^1, \dots, C^{K-1}\}$ , where each set  $C^p$  consists of  $M$  sequences, i.e.,  $C^p = \{\mathbf{c}_0^p, \mathbf{c}_1^p, \dots, \mathbf{c}_{M-1}^p\}$ , and length of each sequence  $\mathbf{c}_l^p$  is  $N$ , where  $0 \leq p \leq K - 1$  and  $0 \leq l \leq M - 1$ . The set  $\mathcal{C}$  is called a CZCSS, denoted by  $(K, M, N, Z)$ -CZCSS, if for  $\mathcal{U}_1 = \{1, 2, \dots, Z\}$  and  $\mathcal{U}_2 = \{N - Z, N - Z + 1, \dots, N - 1\}$  with  $Z \leq N$ , it satisfies the following properties

$$\begin{aligned} P1: & \sum_{i=0}^{M-1} A(\mathbf{c}_i^p)(\tau) = 0, \quad \text{for all } |\tau| \in \mathcal{U}_1 \cup \mathcal{U}_2; \\ P2: & \sum_{i=0}^{M-1} C(\mathbf{c}_i^p, \mathbf{c}_{i+1}^p)(\tau) = 0, \quad \text{for all } |\tau| \in \mathcal{U}_2; \\ P3: & \sum_{i=0}^{M-1} C(\mathbf{c}_i^p, \mathbf{c}_i^{p'})(\tau) = 0, \quad \text{for all } |\tau| \in \{0\} \cup \mathcal{U}_1 \cup \mathcal{U}_2; \\ P4: & \sum_{i=0}^{M-1} C(\mathbf{c}_i^p, \mathbf{c}_{i+1}^{p'})(\tau) = 0, \quad \text{for all } |\tau| \in \mathcal{U}_2; \end{aligned} \quad (4)$$

where  $\mathbf{c}_M^p = \mathbf{c}_0^p, \mathbf{c}_M^{p'} = \mathbf{c}_0^{p'}$  and  $p \neq p'$ .

The complex-valued sequence corresponding to a GBF  $f : \{0, 1\}^m \rightarrow \mathbb{Z}_q$  of  $m$  variables  $x_0, x_1, \dots, x_{m-1}$  is expressed as [8]

$$\Psi(f) = (\omega^{f_0}, \omega^{f_1}, \dots, \omega^{f_{2^m-1}}), \quad (5)$$

where  $f_i = f(s_{i,0}, s_{i,1}, \dots, s_{i,m-1})$ ,  $\omega = \exp(2\pi\sqrt{-1}/q)$ , and  $\mathbf{s}_i = (s_{i,0}, s_{i,1}, \dots, s_{i,m-1})$  is the binary vector representation of the integer  $i$ . Corresponding to a GBF  $f$  with  $m$  variables the sequence  $\Psi(f)$  is of length  $2^m$ . This letter focuses on  $q$ -ary CZCSSs of length in the form of non-power-of-two, where  $q$  is a positive even integer throughout the remainder of this letter. The truncated complex-valued sequence  $\Psi_L(f)$  corresponding to the GBF  $f$  is defined here by eliminating the first and final  $L$  components of the sequence  $\Psi(f)$ .

**Lemma 1 ([21]):** For any permutation  $\pi$  of  $\{0, 1, 2, \dots, m-1\}$  and constants  $c, c_i \in \mathbb{Z}_q$ , let  $g : \{0, 1\}^m \rightarrow \mathbb{Z}_q$  be a GBF defined by

$$g = \frac{q}{2} \sum_{i=0}^{m-2} x_{\pi(i)} x_{\pi(i+1)} + \sum_{i=0}^{m-1} c_i x_i + c. \quad (6)$$

Then for any arbitrary constant  $c' \in \mathbb{Z}_q$ , the sequence pair  $(\mathbf{a}, \mathbf{b}) = (\Psi(g), \Psi(g + \frac{q}{2} x_{\pi(0)} + c'))$  is a GCP and the pair  $(\mathbf{c}, \mathbf{d}) = (\Psi(g + \frac{q}{2} x_{\pi(m-1)}), \Psi(g + \frac{q}{2} (x_{\pi(0)} + x_{\pi(m-1)} + c')))$  is a complementary mate of  $(\mathbf{a}, \mathbf{b})$  [21].

### III. PROPOSED CONSTRUCTION

In this section, a direct construction of CZCSS of length in the form of non-power-of-two based on GBF is presented. To construct the CZCSS, first a new CZCP is constructed and using this proposed and existing CZCP [8], CZCSSs are constructed.

For any integer  $m \geq 4$ , let  $\pi$  be a permutation of  $\{0, 1, \dots, m-3\}$ . Let us define a GBF  $G : \{0, 1\}^m \rightarrow \mathbb{Z}_q$  as

$$G = \frac{q}{2} (\bar{x}_{m-1} x_{m-2} g + x_{m-1} \bar{x}_{m-2} (g + x_{\pi(0)} + m - 2)) + c, \quad (7)$$

where  $\bar{x} = 1 - x, c \in \mathbb{Z}_q$  is any constant and  $g : \{0, 1\}^{m-2} \rightarrow \mathbb{Z}_q$  is a GBF defined as

$$g = \sum_{\alpha=0}^{m-4} x_{\pi(\alpha)} x_{\pi(\alpha+1)}, \quad (8)$$

As Lemma 1,  $(g, g + x_{\pi(m-3)})$  is a GCP and  $(g + x_{\pi(0)} + m - 2, g + x_{\pi(0)} + x_{\pi(m-3)} + m - 2)$  is its complementary mate, the following result follows.

**Lemma 2 ([8]):** Let  $G_1 = G + \frac{q}{2} (x_{m-1} x_{m-2})$  and  $G_2 = G + \frac{q}{2} x_{\pi(m-3)} (x_{m-1} + x_{m-2})$ , then the pair of sequences  $(\mathbf{a}, \mathbf{b}) = (\Psi_{2^{m-2}-1}(G_1), \Psi_{2^{m-2}-1}(G_2))$  forms a  $(2^{m-1} + 2, 2^{\pi(m-3)} + 1)$ -CZCP.

**Lemma 3:** For GBF  $g$  defined in (8) and for any shift  $2^{m-2} - 2^{\pi(m-3)} \leq \tau \leq 2^{m-2} - 1$ , the following cross-correlation property holds

$$C(\mathbf{p}, \mathbf{q})(\tau) + C(\mathbf{u}, \mathbf{v})(\tau) = 0, \quad (9)$$

where, for any  $c_1 \in \mathbb{Z}_q$ ,  $\mathbf{p} = \Psi(\frac{q}{2}g)$ ,  $\mathbf{q} = \Psi(\frac{q}{2}(g + x_{\pi(0)} + x_{\pi(m-3)} + c_1))$ ,  $\mathbf{u} = \Psi(\frac{q}{2}(g + x_{\pi(m-3)}))$  and  $\mathbf{v} = \Psi(\frac{q}{2}(g + x_{\pi(0)} + c_1))$ .

**Proof:** For a given integer  $i$ , set  $j = i + \tau$  and let  $(i_0, i_1, \dots, i_{m-1})$  and  $(j_0, j_1, \dots, j_{m-1})$  be the binary representation of  $i$  and  $j$ , respectively. Then the value of ACCS is given by

$$\begin{aligned} & C(\mathbf{p}, \mathbf{q})(\tau) + C(\mathbf{u}, \mathbf{v})(\tau) \\ &= \sum_{i=0}^{N-\tau} ((-1)^{g_i - g_j} ((-1)^{-j_{\pi(0)} - j_{\pi(m-3)}} + (-1)^{i_{\pi(m-3)} - j_{\pi(0)}})), \end{aligned} \quad (10)$$

where  $N = 2^{m-2} - 1$ . Since  $2^{m-2} - 2^{\pi(m-3)} \leq \tau \leq 2^{m-2} - 1$ , so  $i_{\pi(m-3)} \neq j_{\pi(m-3)}$ . Let if possible  $i_{\pi(m-3)} = j_{\pi(m-3)}$ , then the value of  $\tau$  is calculated as

$$\begin{aligned} \tau = j - i &= (j_0 - i_0)2^0 + (j_1 - i_1)2^1 + \dots \\ &+ (j_{\pi(m-3)} - i_{\pi(m-3)})2^{\pi(m-3)} + \dots + (j_{m-3} - i_{m-3})2^{m-3} \\ &\leq 2^0 + 2^1 + \dots + 2^{m-3} - 2^{\pi(m-3)} \leq 2^{m-2} - 2^{\pi(m-3)} - 1, \end{aligned} \quad (11)$$

i.e.,  $\tau < 2^{m-2} - 2^{\pi(m-3)}$ , which is a contradiction. So  $i_{\pi(m-3)} \neq j_{\pi(m-3)}$  and the result follows from (10). ■

**Lemma 4:** The sequence pair  $(\mathbf{c}, \mathbf{d}) = (\Psi_{2^{m-2}-1}(G_1 + \frac{q}{2}x_{m-2}), \Psi_{2^{m-2}-1}(G_2 + \frac{q}{2}x_{m-2}))$  forms a  $(2^{m-1} + 2, 2^{\pi(m-3)} + 1)$ -CZCP. Additionally, the CZCPs  $(\mathbf{a}, \mathbf{b})$  and  $(\mathbf{c}, \mathbf{d})$  satisfy the following two properties:

$$C(\mathbf{a}, \mathbf{c})(\tau) + C(\mathbf{b}, \mathbf{d})(\tau) = 0, \text{ for all } \tau, \quad (12)$$

and

$$C(\mathbf{a}, \mathbf{d})(\tau) + C(\mathbf{b}, \mathbf{c})(\tau) = 0, 2^{m-1} - 2^{\pi(m-3)} < \tau \leq 2^{m-1} + 1. \quad (13)$$

*Proof:* The proof of (c, d) as a CZCP can be done similarly as the proof of Lemma 2 [8]. Next, we provide a brief proof of the property in (12). For  $\tau = 0$ , the result follows immediately from Lemma 1. Now, for different values of  $\tau$ , the proof is splitted into different cases.

*Case I:*  $0 < \tau \leq 2^{m-2}$ . Using Lemma 1 the ACCS is given by

$$\begin{aligned} & C(\mathbf{a}, \mathbf{c})(\tau) + C(\mathbf{b}, \mathbf{d})(\tau) \\ &= -\omega^{\frac{q}{2}g(s_{2^{m-2}+\tau-1})} \left(1 + \omega^{\frac{q}{2} \times s_{2^{m-2}+\tau-1, \pi(m-3)}}\right) \\ &+ \omega^{\frac{q}{2}(g+x_{\pi(0)}+m-2)(s_{3 \times 2^{m-2}-\tau})} \left(1 - \omega^{\frac{q}{2} \times s_{3 \times 2^{m-2}-\tau, \pi(m-3)}}\right), \end{aligned} \quad (14)$$

where  $g$  is defined in (8.)

*Subcase I:*  $s_{2^{m-2}+\tau-1, \pi(m-3)} = 1$  and  $s_{3 \times 2^{m-2}-\tau, \pi(m-3)} = 0$ . In this case, the sum in (14) is 0.

*Subcase II:*  $s_{2^{m-2}+\tau-1, \pi(m-3)} = 0$  and  $s_{3 \times 2^{m-2}-\tau, \pi(m-3)} = 1$ . Since  $2^{m-2} + \tau - 1 + 3 \times 2^{m-2} - \tau = 2^m - 1$ . So, the binary vector representation of  $s_{2^{m-2}+\tau-1, \pi(m-3)} = 0$  is complement of  $s_{3 \times 2^{m-2}-\tau, \pi(m-3)}$ . Hence  $(g+x_{\pi(0)}+m-2)(s_{3 \times 2^{m-2}-\tau}) = g(s_{2^{m-2}+\tau-1})$ , and sum in (14) is 0.

*Case II:*  $2^{m-2} \leq \tau < 2^{m-2} + 2^{\pi(m-3)}$ .

$$\begin{aligned} & C(\mathbf{a}, \mathbf{c})(\tau) + C(\mathbf{b}, \mathbf{d})(\tau) \\ &= \omega^{\frac{q}{2}(g+x_{\pi(0)}+m-2)(s_{2^{m-2}+\tau-1})} \left(1 + \omega^{\frac{q}{2} \times s_{2^{m-2}+\tau-1, \pi(m-3)}}\right) \\ &+ \omega^{\frac{q}{2}g(s_{3 \times 2^{m-2}-\tau})} \left(1 - \omega^{\frac{q}{2} \times s_{3 \times 2^{m-2}-\tau, \pi(m-3)}}\right). \end{aligned} \quad (15)$$

Now, again considering two different subcases, as in Case I the sum in (15) becomes zero.

*Case III:*  $\tau > 2^{m-2} + 2^{\pi(m-3)}$ .

The sum  $C(\mathbf{a}, \mathbf{c})(\tau) + C(\mathbf{b}, \mathbf{d})(\tau)$  take the same values as in (15). From [8, Lemma 4], the only possible value of  $s_{2^{m-2}+\tau-1, \pi(m-3)} = 1$  and  $s_{3 \times 2^{m-2}-\tau, \pi(m-3)} = 0$ , and hence the sum in (15) is zero.

So, from Case I- Case III, the result in (12) follows. Next, the property of (13) will be proved. Now, for  $2^{m-1} - 2^{\pi(m-3)} < \tau < 2^{m-1} + 1$ , the ACCS of sequence pairs (a, d) and (b, c) is given by

$$\begin{aligned} & C(\mathbf{a}, \mathbf{d})(\tau) + C(\mathbf{b}, \mathbf{c})(\tau) = C(\mathbf{p}, \mathbf{q})(u) + C(\mathbf{u}, \mathbf{v})(u) \\ &+ \omega^{-\frac{q}{2}(g+x_{\pi(0)}+m-2)(s_{2^{m-2}+\tau-1})} \left(\omega^{-\frac{q}{2} \times s_{2^{m-2}+\tau-1, \pi(m-3)}} + 1\right) \\ &+ \omega^{\frac{q}{2}g(s_{3 \times 2^{m-2}-\tau})} \left(1 - \omega^{\frac{q}{2} \times s_{3 \times 2^{m-2}-\tau, \pi(m-3)}}\right), \end{aligned} \quad (16)$$

where  $u = \tau - 2^{m-2} - 1$ . Since  $2^{m-1} - 2^{\pi(m-3)} < \tau < 2^{m-1} + 1$ , then  $2^{m-2} - 2^{\pi(m-3)} \leq u \leq 2^{m-2} - 1$ . So, from Lemma 3,  $C(\mathbf{p}, \mathbf{q})(u) + C(\mathbf{u}, \mathbf{v})(u) = 0$ , and from [8, Lemma 4], the only possible values of  $s_{2^{m-2}+\tau-1, \pi(m-3)} = 1$  and  $s_{3 \times 2^{m-2}-\tau, \pi(m-3)} = 0$ , and hence the sum in (16) is zero. Now for  $\tau = 2^{m-1} + 1$ , the cross-correlation sum is given by

$$C(\mathbf{a}, \mathbf{d})(\tau) + C(\mathbf{b}, \mathbf{c})(\tau) = \omega^{q/2} + \omega^0 = 0. \quad (17)$$

Hence, the results follows from (16) and (17). ■

*Example 1:* Let  $m = 5, q = 4$  and  $\pi(0) = 1, \pi(1) = 0, \pi(2) = 2$  and  $G : \{0, 1\}^4 \rightarrow \mathbb{Z}_q$  be a GBF defined as

$$G = 2(\bar{x}_4 x_3 g + x_4 \bar{x}_3 (g + x_1 + 3)), \quad (18)$$

where  $g$  is a GBF defined as  $g = x_1 x_0 + x_0 x_2$ . Also let  $G_1 = G + 2x_4 x_3$  and  $G_2 = G + 2x_2(x_4 + x_3)$ , then from Lemma 2, the pair of sequences  $(\mathbf{a}, \mathbf{b}) = (\Psi_7(G_1), \Psi_7(G_2))$  forms a (18, 5)-CZCP. Also from Lemma 4, the pair  $(\mathbf{c}, \mathbf{d}) = (\Psi_7(G_1 + 2x_3), \Psi_7(G_2 + 2x_3))$  is a (18, 5)-CZCP. The sequence pairs are given below explicitly, where  $i$  represents  $\omega^i$ .

$\mathbf{a} = (000020200220220002)$ ,  $\mathbf{b} = (000022022220202220)$ .  
 $\mathbf{c} = (022202022220220000)$ ,  $\mathbf{d} = (022200200220202222)$ .  
 Additionally the sequence pairs  $(\mathbf{a}, \mathbf{b})$  and  $(\mathbf{c}, \mathbf{d})$  satisfy the following two properties

$$\begin{aligned} & C(\mathbf{a}, \mathbf{c})(\tau) + C(\mathbf{b}, \mathbf{d})(\tau) = 0, \text{ for all } \tau. \\ & \{C(\mathbf{a}, \mathbf{d})(\tau) + C(\mathbf{b}, \mathbf{c})(\tau)\}_{\tau=-17}^{17} \\ &= (000004048012044441244412440120048400000). \end{aligned}$$

*Remark 1:* Although, the CZCPs generated from Lemma 4 and [8, Th. 1] have the same length and ZCZ width, but these pairs are totally different. In fact, the CZCPs obtained from Lemma 4 is a complementary mate of CZCPs obtained from [8, Th. 1].

In next theorem, construction of CZCSS of non-power-of-two length and large set size is provided, which has not been reported before.

*Theorem 1:* For  $d \in \{1, 2\}$ , let  $\mathcal{F}_d^t, \mathcal{G}_d^t : \{0, 1\}^{m+n} \rightarrow \mathbb{Z}_q$  be defined by

$$\mathcal{F}_d^t(\mathbf{x}, \mathbf{y}) = G_d + \frac{q}{2} \mathbf{t} \cdot \mathbf{y}; \quad \mathcal{G}_d^t(\mathbf{x}, \mathbf{y}) = G_d + \frac{q}{2} x_{m-2} + \frac{q}{2} \mathbf{t} \cdot \mathbf{y}, \quad (19)$$

where  $\mathbf{t} = (t_0, t_1, \dots, t_{n-1}) \in \mathbb{Z}_2^n$ ,  $\mathbf{x} = (x_0, x_1, \dots, x_{m-1})$ , and  $\mathbf{y} = (y_0, y_1, \dots, y_{n-1})$ . Also, let  $S_t$  and  $S'_t$  be two sets defined by

$$S_t = \{\Psi_{2^{m-2}-1}(\mathcal{F}_d^t(\mathbf{x}, \mathbf{y})) : d \in \{1, 2\}, \mathbf{y} \in \mathbb{Z}_2^n\}, \quad (20)$$

and

$$S'_t = \{\Psi_{2^{m-2}-1}(\mathcal{G}_d^t(\mathbf{x}, \mathbf{y})) : d \in \{1, 2\}, \mathbf{y} \in \mathbb{Z}_2^n\}, \quad (21)$$

for some fixed  $\mathbf{t}$ . Then  $\{S_t : \mathbf{t} \in \mathbb{Z}_2^n\} \cup \{S'_t : \mathbf{t}' \in \mathbb{Z}_2^n\}$  forms a  $(2^{n+1}, 2^{n+1}, 2^{m-1} + 2, 2^{\pi(m-3)} + 1)$ -CZCSS.

*Proof:* For proving the result, we use the notation that  $i$ -th sequence of the set  $S_t$  is denoted by  $S_{t,i}$  and  $S_{t,2^{n+1}+1} = S_{t,1}$ . Also define the sets  $\mathcal{U}_1 = \{1, 2, \dots, 2^{\pi(m-3)} + 1\}$  and  $\mathcal{U}_2 = \{2^{m-1} - 2^{\pi(m-3)} + 1, 2^{m-1} - 2^{\pi(m-3)} + 2, \dots, 2^{m-1} + 1\}$ . For  $\mathbf{t} \in \mathbb{Z}_2^n$ , the property P1 of Definition 4 is calculated as

$$\begin{aligned} C(S_t, S_t)(\tau) &= \sum_{d \in \{1, 2\}} \sum_{\mathbf{y} \in \mathbb{Z}_2^n} C\left(G_d + \frac{q}{2} \mathbf{t} \cdot \mathbf{y}, G_d + \frac{q}{2} \mathbf{t} \cdot \mathbf{y}\right)(\tau) \\ &= A(G_1)(\tau) + A(G_2)(\tau) \cdot \sum_{\mathbf{y} \in \mathbb{Z}_2^n} \omega^{\frac{q}{2}(\mathbf{t}-\mathbf{t}) \cdot \mathbf{y}} \\ &= 2^n (A(G_1)(\tau) + A(G_2)(\tau)) \\ &= 0 \text{ for } |\tau| \in \mathcal{U}_1 \cup \mathcal{U}_2. \end{aligned} \quad (22)$$

The above equation becomes zero as  $G_1$  and  $G_2$  forms a CZCP. Since  $G_1 + \frac{q}{2} x_{m-2}$  and  $G_2 + \frac{q}{2} x_{m-2}$  is also a CZCP, similarly it can also be shown that  $C(S'_t, S'_t)(\tau) = 0$ , for all

$|\tau| \in \mathcal{U}_1 \cup \mathcal{U}_2$ . For proving the property P2 of *Definition 4*, consider the following cross-correlation

$$\begin{aligned}
& \sum_{i=1}^{2^{n+1}} C(S_{\mathbf{t},i}, S_{\mathbf{t},i+1})(\tau) \\
&= \sum_{\mathbf{y}=0}^{2^n-2} C\left(G_1 + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_1 + \frac{q}{2}\mathbf{t} \cdot (\mathbf{y} + 1)\right)(\tau) \\
&\quad + C\left(G_1 + \frac{q}{2}\mathbf{t} \cdot (2^n - 1), G_2 + \frac{q}{2}\mathbf{t} \cdot \mathbf{0}\right)(\tau) \\
&\quad + \sum_{\mathbf{y}=0}^{2^n-2} C\left(G_2 + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_2 + \frac{q}{2}\mathbf{t} \cdot (\mathbf{y} + 1)\right)(\tau) \quad (23) \\
&\quad + C\left(G_2 + \frac{q}{2}\mathbf{t} \cdot (2^n - 1), G_1 + \frac{q}{2}\mathbf{t} \cdot \mathbf{0}\right)(\tau) \\
&= \sum_{\mathbf{y}=0}^{2^n-2} \left(\omega^{\frac{q}{2}\mathbf{t} \cdot \mathbf{y}} (A(G_1)(\tau) + A(G_2)(\tau))\right) \\
&\quad + \omega^{\frac{q}{2}\mathbf{t} \cdot (2^n - 1)} (C(G_1, G_2)(\tau) + C(G_2, G_1)(\tau)) \\
&= 0, \text{ for all } |\tau| \in \mathcal{U}_2. \text{ (as } G_1, G_2 \text{ is a CZCP)}
\end{aligned}$$

Similarly, it can also be shown that  $\sum_{i=1}^{2^{n+1}} C(S'_{\mathbf{t},i}, S'_{\mathbf{t},i+1})(\tau) = 0$ , for all  $|\tau| \in \mathcal{U}_2$ . So, the property P2 of *Definition 4* is proved. For proving the property P3 of *Definition 4*, the following different cases need to be proved. For  $\mathbf{t} \neq \mathbf{t}' \in \mathbb{Z}_2^n$ , we need to prove  $C(S_{\mathbf{t}}, S_{\mathbf{t}'} ) = 0$ ,  $C(S'_{\mathbf{t}}, S'_{\mathbf{t}'} ) = 0$ , for all  $|\tau| \in \{0\} \cup \mathcal{U}_1 \cup \mathcal{U}_2$ , and for any  $\mathbf{t}, \mathbf{t}' \in \mathbb{Z}_2^n$ , for all  $|\tau| \in \{0\} \cup \mathcal{U}_1 \cup \mathcal{U}_2$ ,  $C(S_{\mathbf{t}}, S'_{\mathbf{t}'} ) = 0$ . Consider the cross-correlation between sets  $S_{\mathbf{t}}$  and  $S_{\mathbf{t}'}$

$$\begin{aligned}
& C(S_{\mathbf{t}}, S_{\mathbf{t}'})(\tau) \\
&= \sum_{d \in \{1,2\}} \sum_{\mathbf{y} \in \mathbb{Z}_2^n} C\left(G_d + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_d + \frac{q}{2}\mathbf{t}' \cdot \mathbf{y}\right)(\tau) \quad (24) \\
&= (A(G_1)(\tau) + A(G_2)(\tau)) \cdot \sum_{\mathbf{y} \in \mathbb{Z}_2^n} \omega^{\frac{q}{2}(\mathbf{t}-\mathbf{t}') \cdot \mathbf{y}}.
\end{aligned}$$

Since, for  $\mathbf{t} \neq \mathbf{t}'$ ,  $\sum_{\mathbf{y} \in \mathbb{Z}_2^n} \omega^{q/2(\mathbf{t}-\mathbf{t}') \cdot \mathbf{y}} = 0$ . So, from (24)  $C(S_{\mathbf{t}}, S_{\mathbf{t}'})(\tau) = 0$ , for all  $\tau$ . Similarly,  $C(S'_{\mathbf{t}}, S'_{\mathbf{t}'})(\tau) = 0$ , for all  $\tau$ . Now for any  $\mathbf{t}, \mathbf{t}' \in \mathbb{Z}_2^n$ , consider the cross-correlation between the sets

$$\begin{aligned}
& C(S_{\mathbf{t}}, S'_{\mathbf{t}'})(\tau) \\
&= \sum_{d \in \{1,2\}} \sum_{\mathbf{y} \in \mathbb{Z}_2^n} C\left(G_d + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_d + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t}' \cdot \mathbf{y}\right)(\tau) \\
&= \left(C\left(G_1, G_1 + \frac{q}{2}x_{m-2}\right)(\tau) + C\left(G_2, G_2 + \frac{q}{2}x_{m-2}\right)(\tau)\right) \\
&\quad \cdot \sum_{\mathbf{y} \in \mathbb{Z}_2^n} \omega^{\frac{q}{2}(\mathbf{t}-\mathbf{t}') \cdot \mathbf{y}} \\
&= 0, \text{ for all } \tau. \text{ (using Lemma 4)} \quad (25)
\end{aligned}$$

Now, the two cases for the property P4 of *Definition 4* namely, for any  $\mathbf{t} \neq \mathbf{t}' \in \mathbb{Z}_2^n$ ,  $\sum_{i=1}^{2^{n+1}} C(S_{\mathbf{t},i}, S_{\mathbf{t}',i+1})(\tau) = 0$  and  $\sum_{i=1}^{2^{n+1}} C(S'_{\mathbf{t},i}, S'_{\mathbf{t}',i+1})(\tau) = 0$  for all  $|\tau| \in \mathcal{U}_2$  can also be proved in a similar way as the property P3 is proved. Here,

we prove the remaining case, i.e., for any  $\mathbf{t}, \mathbf{t}' \in \mathbb{Z}_2^n$ , consider the cross-correlation term

$$\begin{aligned}
& \sum_{i=1}^{2^{n+1}} C(S'_{\mathbf{t},i}, S_{\mathbf{t}',i+1})(\tau) \\
&= \sum_{\mathbf{y}=0}^{2^n-2} C\left(G_1 + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_1 + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t}' \cdot (\mathbf{y} + 1)\right)(\tau) \\
&\quad + C\left(G_1 + \frac{q}{2}\mathbf{t} \cdot (2^n - 1), G_2 + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t}' \cdot \mathbf{0}\right)(\tau) \\
&\quad + \sum_{\mathbf{y}=0}^{2^n-2} C\left(G_2 + \frac{q}{2}\mathbf{t} \cdot \mathbf{y}, G_2 + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t}' \cdot (\mathbf{y} + 1)\right)(\tau) \\
&\quad + C\left(G_2 + \frac{q}{2}\mathbf{t} \cdot (2^n - 1), G_1 + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t}' \cdot \mathbf{0}\right)(\tau) \\
&= \left(C(G_1, G_1 + \frac{q}{2}x_{m-2})(\tau) + C(G_2, G_2 + \frac{q}{2}x_{m-2})(\tau)\right) \\
&\quad \cdot \sum_{\mathbf{y}=0}^{2^n-2} \omega^{\frac{q}{2}(\mathbf{t}\mathbf{y} - \mathbf{t}'(\mathbf{y}+1))} \\
&\quad + \left(C(G_1, G_2 + \frac{q}{2}x_{m-2})(\tau) + C(G_2, G_1 + \frac{q}{2}x_{m-2})(\tau)\right) \\
&\quad \cdot \omega^{\frac{q}{2}\mathbf{t} \cdot (2^n - 1)} \\
&= 0, \text{ for all } |\tau| \in \mathcal{U}_2. \quad (26)
\end{aligned}$$

The sum in (26) is zero from *Lemma 4*. ■

*Example 2:* Let  $n = 2$  and all other parameters and functions are as defined in *Example 1*. Then for  $\mathbf{t} = (t_0, t_1) \in \{0, 1\}^2$ , and  $\mathbf{y} = (y_0, y_1) \in \{0, 1\}^2$ , consider the sets

$$S_{\mathbf{t}} = \left\{ \Psi_7 \left( G_d + \frac{q}{2}\mathbf{t} \cdot \mathbf{y} \right) : d \in \{1, 2\}, \mathbf{y} \in \mathbb{Z}_2^2 \right\}, \quad (27)$$

and

$$S'_{\mathbf{t}} = \left\{ \Psi_7 \left( G_d + \frac{q}{2}x_{m-2} + \frac{q}{2}\mathbf{t} \cdot \mathbf{y} \right) : d \in \{1, 2\}, \mathbf{y} \in \mathbb{Z}_2^2 \right\}. \quad (28)$$

Then from *Theorem 1*  $\{S_{\mathbf{t}} : \mathbf{t} \in \mathbb{Z}_2^2\} \cup \{S'_{\mathbf{t}'} : \mathbf{t}' \in \mathbb{Z}_2^2\}$  forms a  $(8, 8, 18, 5)$ -CZCSS.

*Remark 2:* The ZCZ width of the proposed CZCSS is maximum when  $\pi(m-3) = m-3$ .

*Remark 3:* In [14] several concatenation based constructions of  $(4, N, Z)$ -CZCS is provided. Every CZCSS is a collection of CZCS, hence for the first time *Theorem 1* also facilitate the GBF based construction of  $(2^{n+1}, 2^{m-1} + 2, 2^{\pi(m-3)} + 1)$ -CZCSSs.

*Remark 4:* Since every CZCSS is also a SZCCS, so *Theorem 1* also generates  $(2^{n+1}, 2^{n+1}, 2^{m-1} + 2, 2^{\pi(m-3)} + 1)$ -SZCCS. The available construction of SZCCS in [20], is limited to maximum set size 8, this is for the first time that SZCCS with large set size is constructed.

#### IV. CONCLUSION

In this letter, we have proposed a direct construction of CZCSS of non-power-of-two length and large set size based on GBF, which has not been reported before. The set size of the proposed CZCSS is equal to the number of constituent sequences. The proposed construction also generates non-power-of-two length CZCSs containing a large number of sequences and non-power-of-two length SZCCS with a large set size.



## REFERENCES

- [1] P. Fan, W. Yuan, and Y. Tu, "Z-complementary binary sequences," *IEEE Signal Process. Lett.*, vol. 14, no. 8, pp. 509–512, Aug. 2007.
- [2] C.-Y. Pai, S.-W. Wu, and C.-Y. Chen, "Z-complementary pairs with flexible lengths from generalized Boolean functions," *IEEE Commun. Lett.*, vol. 24, no. 6, pp. 1183–1187, 2020.
- [3] C.-Y. Chen, "A novel construction of Z-complementary pairs based on generalized Boolean functions," *IEEE Signal Process. Lett.*, vol. 24, no. 7, pp. 987–990, 2017.
- [4] A. R. Adhikary, P. Sarkar, and S. Majhi, "A direct construction of  $q$ -ary even length Z-complementary pairs using generalized Boolean functions," *IEEE Signal Process. Lett.*, vol. 27, pp. 146–150, 2020.
- [5] A. R. Adhikary, S. Majhi, Z. Liu, and Y. L. Guan, "New sets of optimal odd-length binary Z-complementary pairs," *IEEE Trans. Inf. Theory*, vol. 66, no. 1, pp. 669–678, 2020.
- [6] P. Kumar, P. Sarkar, S. Majhi, and S. Paul, "A direct construction of even length ZCPs with large ZCZ ratio," *Cryptogr. Commun.*, 2022.
- [7] Z. Liu, P. Yang, Y. L. Guan, and P. Xiao, "Cross Z-complementary pairs for optimal training in spatial modulation over frequency selective channels," *IEEE Trans. Signal Process.*, vol. 68, pp. 1529–1543, 2020.
- [8] A. R. Adhikary, Z. Zhou, Y. Yang, and P. Fan, "Constructions of cross Z-complementary pairs with new lengths," *IEEE Trans. Signal Process.*, vol. 68, pp. 4700–4712, 2020.
- [9] M. Yang, S. Tian, N. Li, and A. R. Adhikary, "New sets of quadriphase cross Z-complementary pairs for preamble design in spatial modulation," *IEEE Signal Process. Lett.*, vol. 28, pp. 1240–1244, 2021.
- [10] Z.-M. Huang, C.-Y. Pai, and C.-Y. Chen, "Binary cross Z-complementary pairs with flexible lengths from Boolean functions," *IEEE Commun. Lett.*, vol. 25, no. 4, pp. 1057–1061, 2021.
- [11] C. Fan, D. Zhang, and A. R. Adhikary, "New sets of binary cross Z-complementary sequence pairs," *IEEE Commun. Lett.*, vol. 24, no. 8, pp. 1616–1620, 2020.
- [12] F. Zeng, X. He, Z. Zhang, and L. Yan, "Quadriphase cross Z-complementary pairs for pilot sequence design in spatial modulation systems," *IEEE Signal Process. Lett.*, vol. 29, pp. 508–512, 2022.
- [13] Z. Liu, P. Yang, Y. L. Guan, and P. Xiao, "Cross Z-complementary pairs (CZCPs) for optimal training in broadband spatial modulation systems," in *2020 IEEE Int. Symp. Inf. Theory (ISIT)*, 2020, pp. 2926–2930.
- [14] Z.-M. Huang, C.-Y. Pai, and C.-Y. Chen, "Cross Z-complementary sets for training design in spatial modulation," *IEEE Trans. Commun.*, pp. 1–1, 2022.
- [15] L. Feng, P. Fan, X. Tang, and K.-k. Loo, "Generalized pairwise Z-complementary codes," *IEEE Signal Process. Lett.*, vol. 15, pp. 377–380, 2008.
- [16] P. Sarkar, S. Majhi, and Z. Liu, "Optimal Z-complementary code set from generalized Reed-Muller codes," *IEEE Trans. Commun.*, vol. 67, no. 3, pp. 1783–1796, 2019.
- [17] —, "Pseudo-Boolean functions for optimal Z-complementary code sets with flexible lengths," *IEEE Signal Process. Lett.*, vol. 28, pp. 1350–1354, 2021.
- [18] P. Sarkar, A. Roy, and S. Majhi, "Construction of Z-complementary code sets with non-power-of-two lengths based on generalized Boolean functions," *IEEE Commun. Lett.*, vol. 24, no. 8, pp. 1607–1611, 2020.
- [19] G. Ghosh, S. Majhi, P. Sarkar, and A. K. Upadhyaya, "Direct construction of optimal Z-complementary code sets with even lengths by using generalized Boolean functions," *IEEE Signal Process. Lett.*, vol. 29, pp. 872–876, 2022.
- [20] Y. Zhou, Z. Zhou, Z. Liu, Y. Yang, P. Yang, and P. Fan, "Symmetrical Z-complementary code sets (SZCCSs) for optimal training in generalized spatial modulation," 2020. [Online]. Available: <https://arxiv.org/abs/2010.11372>
- [21] S.-W. Wu and C.-Y. Chen, "Optimal Z-complementary sequence sets with good peak-to-average power-ratio property," *IEEE Signal Process. Lett.*, vol. 25, no. 10, pp. 1500–1504, 2018.