

Renewable Composite Quantile Method and Algorithm for Nonparametric Models with Streaming Data

Yan Chen¹, Shuixin Fang² and Lu Lin^{1*}

^{1*}Zhongtai Securities Institute for Financial Studies, Shandong University, Shanda Nanlu, Jinan, 250100, Shandong, P.R. China.

²School of Mathematics, Shandong University, Shanda Nanlu, Jinan, 250100, Shandong, P.R. China.

*Corresponding author(s). E-mail(s): linlu@sdu.edu.cn;
Contributing authors: yan_chen@mail.sdu.edu.cn; fangsx@mail.sdu.edu.cn;

Abstract

We are interested in renewable estimation and algorithms for nonparametric models with streaming data. We express the parameter of interest through a functional depending on a weight function and a conditional distribution function (CDF). By renewable kernel estimations combined with function interpolations, we obtain renewable estimator for the CDF and propose the method of renewable weighted composite quantile regression (WCQR). By fully using the model structure, we propose new weight selectors, by which the WCQR can achieve asymptotic unbiasedness when estimating specific functions in the model. We also propose practical bandwidth selectors for streaming data and find the optimal weight function minimizing the asymptotic variance. Our asymptotical results show that our estimator is almost equivalent to the oracle estimator obtained from the entire data together. And our method also enjoys adaptiveness to error distributions, robustness to outliers, and efficiency in both estimation and computation. Simulation studies and real data analyses further confirm our theoretical findings.

Keywords: Renewable algorithm, Streaming Data, Composite quantile regression, Nonparametric regression, Polynomial interpolation

1 Introduction

1.1 Problem Setup and Challenges

In this paper, we are interested in nonparametric regression problems for massive data taking the form of streaming data. Specifically, the considered nonparametric model is that

$$Y = m(X) + \sigma(X)\varepsilon, \quad (1)$$

where Y and X are supposed respectively to be scalar response variable and covariate for simplicity; ε is the random error independent of X , and the distribution of ε is unknown and satisfies $\mathbb{E}[\varepsilon] = 0$ and $\text{Var}[\varepsilon] = 1$; $m : \mathbb{R} \rightarrow \mathbb{R}$ and $\sigma : \mathbb{R} \rightarrow [0, \infty)$ are both unknown functions. The considered streaming data consist of a series of cross-sectional data chunks $\mathcal{D}_t = \{(X_{tj}, Y_{tj}) : 1 \leq j \leq n_t\}$ for $t = 1, 2, \dots$, where all (X_{tj}, Y_{tj}) are independent and identically distributed (i.i.d.) observations of (X, Y) . In our

setting, the data chunks $\mathcal{D}_1, \mathcal{D}_2, \dots$, are not available simultaneously, but arrive sequentially one after another.

As we know, most conventional statistic algorithms are designed under the premise that the full data can be fitted on the computer memory simultaneously. However, such a premise is no longer true for streaming data mentioned above. To deal with streaming data, the online-updating (or renewable) algorithms are widely considered. For example, at the time t , one has obtained a summary statistic T_t of the historical data $\cup_{s \leq t} \mathcal{D}_s$. Then as the new data block \mathcal{D}_{t+1} arrives, T_t is updated to T_{t+1} by incremental computation without accessing the historical raw data, i.e., $T_{t+1} = \mathcal{R}(T_t; \mathcal{D}_{t+1})$ with \mathcal{R} a function independent with $\cup_{s \leq t} \mathcal{D}_s$. When modified into the above renewable form, the statistics may lose desirable statistical properties, which brings new challenges in designing statistical algorithms for online-updating.

The first challenge arises from the data partitioning. As we know, nonparametric methods inevitably suffer from estimation bias. The bias can not be reduced by simply averaging the local estimators from each data block, which essentially prevents the renewable estimator from achieving the standard statistical convergence rate. Hence when designing algorithms for streaming data, it is crucial to sufficiently reduce the estimation bias.

The second challenge lies in the potentially poor quality of steaming data. Outliers and fat-tailed features are more likely to hide in these massive raw data. And even worse, it is quite hard to detect or address them, because the relevant procedures usually involve reusing the historical raw data. Thus it has a significant value for renewable algorithms that the obtained estimator is robust to outliers or adaptive to fat-tailed features.

The third challenge is caused from the exploding data size. The streaming data source usually generates extremely large amounts of raw data in a short period of time. To deal with such a rapid data stream, the updating algorithm should be implemented efficiently.

1.2 Existing Works on Online-Updating and Motivations

There have been many works developed for streaming data. The existing online-updating methods can be classified into the following categories. In some restrictive cases, the estimator has a closed-form expression and the value can be exactly obtained by some recursive updating operations, see, e.g., Schifano et al. (2016); Bucak and Gungel (2009); Nion and Sidiropoulos (2009), etc. However, it is more often the case that the estimator has no closed-form expression, then iterative algorithms of online-updating are often used to approximate the value of the estimator, see, e.g., Robbins and Monro (1951); Toulis et al. (2014); Moroshko et al. (2015); Chen et al. (2019), etc. Additionally, several online cumulative frameworks are proposed for likelihood, estimating equations and so on, see, e.g., Luo and Song (2020); Lin et al. (2020); Wang et al. (2022), etc. And there are also some works based on the deep learning techniques, see, Ashfahani and Pratama (2019); Das et al. (2019); Pratama et al. (2019), to name a few.

In the first scenario, the obtained estimator enjoys exactly the same statistical properties as that of the oracle estimator obtained by using the offline methods together with the full dataset. However, such a result deeply relies on the closed-form expression of the estimator, which is unavailable for most robust estimators including the quantile estimators. Without the closed-form expression, the differentiability condition of the objective functions is required to achieve the oracle property, see, e.g., Luo and Song (2020) and Lin et al. (2020). However, most robust objective functions (e.g., quantile based objective functions) are not differentiable.

In this paper, we will address the above issues by proposing a new method for stream data, where the renewable algorithm does not rely on the estimator's closed-form expression, but the obtained estimator still achieves the standard statistical convergence rate. Meanwhile, we also focus on some aspects of aforementioned three challenges and pursue that the proposed method enjoys robustness to outliers or adaptiveness to various error distributions, and the updating algorithm is simple such that it can be implemented efficiently.

1.3 Contributions and Article Frame

In this paper, a renewable composite quantile method and algorithm are proposed for model (1) with streaming data.

Inspired by L-Estimation (see, e.g., Koenker and Portnoy, 1987; Portnoy and Koenker, 1989; Boente and Fraiman, 1994), we express the parameter of interest through a functional instead of a closed-form expression. Here the functional takes the form of an integral depending on a weight function and a conditional distribution function (CDF) of Y . Then the renewable estimation is attained by two steps:

1. *Numerical Approximation:* The CDF in the functional is approximated by function interpolations. Then the parameter of interest can be approximately expressed by a finite number of function values of the CDF.
2. *Statistical Approximation:* The aforementioned function values of CDF are estimated by kernel estimators, which have closed-form expressions and can be exactly obtained through recursive updating algorithms.

By combining the above numerical and statistical approximations, we finally propose our renewable weighted composite quantile regression (WCQR) method for streaming data.

To estimate the function $m(\cdot)$ or $\sigma(\cdot)$ by renewable WCQR, the weight function should be selected correctly. To this end, we fully use the structure of the model (1) and propose new selection criterions for the weight functions, under which the renewable estimator can estimate $m(x)$ and $\sigma(x)$ asymptotically unbiased. Then we deduce the asymptotic distributions of the proposed estimators. Based on this, a practical bandwidth selector is proposed for the online-updating estimator, and the optimal weight function is also obtained by minimizing the asymptotic variance under the constraint of the above selection criterions. Finally, our theoretical findings are demonstrated by simulation studies and real data analyses.

Compared with the competitors, our method has the following main virtues:

- 1) *Oracle comparability.* Through numerical approximations, our WCQR estimator is assembled from some renewable statistics exactly obtained via online-updating. Thanks to this,

not only the algorithm gets rid of any restriction on the block size or block number of the streaming data, but also the obtained estimator enjoys almost the same asymptotic properties as that of the oracle estimator obtained on the full data set.

- 2) *Robustness.* Benefit from robust feature of the quantile estimation, when the model has a symmetric error distribution, our regression method enjoys robustness compared with the common methods such as ordinary least squares.
- 3) *Model adaptiveness.* With model-based weight functions, our estimation method is adaptive to symmetric or asymmetric models. Different from existing methods, the selection criterions of the weight functions are directly established on the structure of the nonparametric models instead of the information of the errors. Thus in our method, the weight selection does not rely on any pilot estimations for the error distributions and the model adaptiveness can be preserved in case of streaming data.
- 4) *Estimation efficiency.* Under the above weight criterions, we find the optimal weight function, under which our renewable estimator enjoys minimized asymptotic variance in estimating $m(x)$ and $\sigma(x)$.
- 5) *Computational efficiency.* Thanks to the closed-form expression of the kernel estimators, our algorithm is quite simple in updating procedures with no need for solving any optimization problems or nonlinear equations. This feature is particularly desirable for rapid data stream.

The paper is then organized in the following way. In Section 2, we give some preliminaries above the existing composite quantile estimations and the L-Estimation. In Section 3, the main idea of our methodologies is introduced in detail, including the computation of the renewable WCQR estimator, the selection of the weight functions, and some specific estimators and detailed renewable algorithms for estimating $m(x)$ and $\sigma(x)$. In Section 4, the asymptotic properties of the proposed method are established; the selector of online-updating bandwidth is proposed and the optimal selection of the weight function is discussed. Section 5 contains comprehensive simulation studies and real data analyses to further demonstrate the desirable performance of the

proposed estimators and algorithms. Some algorithms, lemmas, and technical proofs are deferred to the supplementary material.

1.4 Notations

For a random variable Z , denote by $f_Z(\cdot)$ and $F_Z(\cdot)$ the the probability density function (PDF) and the distribution function of Z , respectively. Denote by $Q_{Y|x}(\tau)$ the conditional $100\tau\%$ quantile of Y given $X = x \in \mathbb{R}$ and $\tau \in (0, 1)$, i.e. $Q_{Y|x}(\tau) = \inf \{t : \mathbb{P}(Y \leq t|X = x) \geq \tau\}$. Denote by $F_{Y|x}(\cdot)$ the conditional distribution function (CDF) of Y given $X = x$, i.e., $F_{Y|x}(y) = \mathbb{P}(Y < y|X = x)$. Denote by $f_{Y|x}(\cdot)$ the conditional PDF of Y given $X = x$. For $a, b \in \mathbb{R}$, denote $a \wedge b = \min \{a, b\}$. For indexes i and j , denote by δ_{ij} the kronecker symbol, i.e., $\delta_{ij} = 1$ if $i = j$ and $\delta_{ij} = 0$ if $i \neq j$. Denote by $I_d(\cdot)$ the identity function, i.e., $I_d(y) = y$. Denote by $I(\cdot)$ the indicative function, i.e., if the proposition \mathcal{P} is true, $I(\mathcal{P}) = 1$, and otherwise, $I(\mathcal{P}) = 0$. For a function $f : \mathbb{R} \rightarrow \mathbb{R}$, denote by $\text{Supp} \{f(\cdot)\}$ the support set of f ; for $I_0 \subset \mathbb{R}$ and $1 \leq p < \infty$, denote $\|f\|_{p, I_0} = (\int_{I_0} |f(y)|^p dy)^{1/p}$ and $\|f\|_{\infty, I_0} = \sup_{y \in I_0} |f(y)|$. For a finite point set $G \subset \mathbb{R}$, denote $\Delta(G) = \max_{y_i \in G} (\min_{y_j \in G \setminus \{y_i\}} |y_i - y_j|)$, i.e., the maximum spacing between any two adjacent points in G ; denote by $\#G$ the number of elements in G , and denote by $\min G$ (resp. $\max G$) the minimum (resp. maximum) of G . For two sets G_1 and G_2 , denote $G_1 \setminus G_2 = \{y : y \in G_1, y \notin G_2\}$. For a set $E \subset \mathbb{R}$ and a function $f : \mathbb{R} \rightarrow \mathbb{R}$, denote $f(E) = \{f(x) : x \in E\}$; denote $I(E) = [\inf E, \sup E]$ the closed interval generated by E .

2 Preliminary

In this section, we will briefly review some fundamental works, from which we obtain inspirations for our method.

2.1 Composite Quantile Regression and L-Estimation

To estimate the regression function $m(x)$, the well-known composite quantile regression (CQR) estimator (see, e.g., Zou and Yuan, 2008; Kai

et al., 2010) takes the form of

$$\hat{m}_{\text{cqr}}(x) = \frac{1}{q} \sum_{i=1}^q \hat{Q}_{Y|x}(\tau_i), \quad (2)$$

where $\hat{Q}_{Y|x}(\tau_i)$ are some consistent estimators of the quantile $Q_{Y|x}(\tau_i)$, and τ_i are quantile levels chosen as $\tau_i = i/(q+1)$. When the PDF of ε is symmetric around 0, one can expect $m(x) = 1/q \sum_{i=1}^q Q_{Y|x}(\tau_i)$ implying that $\hat{m}_{\text{cqr}}(x)$ is an asymptotic unbiased estimator of $m(x)$. However, when the error is general, the aforementioned equality is not necessarily true and the naive CQR estimator may suffer from non-negligible bias. To address this issue, Sun et al. (2013) extended the CQR estimator to the WCQR estimator in from of

$$\hat{m}_{\text{wcqr}}(x) = \sum_{i=1}^q \omega_i \hat{Q}_{Y|x}(\tau_i), \quad (3)$$

where ω_i are weights selected to satisfy $\sum_{i=1}^q \omega_i = 1$ and $\sum_{i=1}^q \omega_i F_\varepsilon^{-1}(\tau_i) = 0$, such that the equality $m(x) = \sum_{i=1}^q \omega_i Q_{Y|x}(\tau_i)$ is established and meanwhile, the non-negligible bias of $\hat{m}_{\text{wcqr}}(x)$ is eliminated.

The CQR and WCQR estimators can be expressed as L-estimators (see, e.g., Gutenbrunner and Jurečková, 1992; Koenker and Zhao, 1994) taking the form

$$\hat{m}_L(x; \nu) = \int_{[0,1]} \hat{Q}_{Y|x}(\tau) d\nu(\tau), \quad (4)$$

with ν a measure on $[0, 1]$. To cover the CQR (resp. WCQR) estimators, the measure of L-estimators can be particularly chosen as $\nu = 1/q \sum_{i=1}^q \delta_{\tau_i}$ (resp. $\nu = \sum_{i=1}^q \omega_i \delta_{\tau_i}$) with δ_{τ_i} a unit mass on τ_i . Additionally, when the measure ν is well chosen based on the error distribution in (1), the L-estimator can efficiently (or robustly) estimate $m(x)$ and $\sigma(x)$ (see, e.g., Serfling, 1980; Koenker and Portnoy, 1987; Portnoy and Koenker, 1989; Koenker, 2005, etc).

In this paper, we still call $\hat{m}_L(x; \nu)$ the WCQR estimator to highlight the weighted composite of quantile estimators.

2.2 Local Polynomial Interpolation

We will briefly review the main idea of local polynomial interpolation (LPI), which is a fundamental tool for numerical approximations and will be applied in our method. For more details about the interpolation techniques, readers may refer to Gautschi (2012); Sauer (2011); Burden et al. (2015), etc.

Suppose that $(y_1, f_1), \dots, (y_q, f_q)$ are given data point generated from an unknown objective function $f : \mathbb{R} \rightarrow \mathbb{R}$, i.e., $f_i = f(y_i)$ for $i = 1, \dots, q$. Denote the node set $G_x = \{y_i\}_{i=1}^q$ and the elements y_i are called the interpolation nodes.

The so-called LPI aims at finding a piecewise polynomial function passing through all the given data points of $f(\cdot)$. To achieve this, for $1 \leq l \leq q$ and $y \in \mathbb{R}$, we denote by $\mathcal{N}_l(y, G_x)$ the set consisting of the l nearest interpolation nodes around y , or strictly speaking, $\mathcal{N}_l(y, G_x) = G_0$ with G_0 the unique set satisfying:

- a) $\#G_0 = l$, $G_0 \subset G_x$;
- b) for any $y' \in G_0$ and $y'' \in G_x \setminus G_0$, it holds that $|y - y'| \leq |y - y''|$, and whenever the equality holds, $y' < y''$.

Then we define the l th-degree LPI basis functions as

$$L(y, y_i; l, G_x) = \ell_i(y) I(y_i \in \mathcal{N}_{l+1}(y, G_x)) \quad (5)$$

for $y_i \in G_x$ with $\ell_i(\cdot)$ the l th-degree Lagrange interpolating polynomials defined as

$$\ell_i(y) = \frac{\prod_{y_j \in \mathcal{N}_{l+1}(y, G_x) \setminus \{y_i\}} (y - y_j)}{\prod_{y_j \in \mathcal{N}_{l+1}(y, G_x) \setminus \{y_i\}} (y_i - y_j)}.$$

Using the basis functions, the l th-degree LPI function is constructed as

$$\mathcal{I}_l f(y) = \sum_{y_i \in G_x} f(y_i) L(y, y_i; l, G_x). \quad (6)$$

Here and in the following context, we formally use \mathcal{I}_l to denote the l th-degree LPI operator in the sense that $\mathcal{I}_l f(\cdot)$ is a l th-degree LPI function obtained by (6).

It is easy to verify that $L(y_i, y_j; l, G_x) = \delta_{ij}$, implying that $\mathcal{I}_l f(\cdot)$ indeed passes through the points $\{(y_i, f_i)\}_{i=1}^q$. The accuracy of the LPI function approximating the objective function can

be guaranteed by the following standard result (see, e.g., Theorem 3.3 of Burden et al. 2015 or Theorem 3.3 of Sauer 2011):

Lemma 1 (Burden et al. 2015; Sauer 2011) *Suppose that $f(\cdot)$ has continuous derivatives upto order $l+1$, and $\mathcal{I}_l f(\cdot)$ is given in (6). Then it holds that*

$$f(y) = \mathcal{I}_l f(y) + \frac{f^{(l+1)}(c)}{(l+1)!} \prod_{y_i \in \mathcal{N}_{l+1}(y, G_x)} (y - y_i),$$

where c is a number depends on y and lies in $[\min \overline{\mathcal{N}}_{l+1}(y), \max \overline{\mathcal{N}}_{l+1}(y)]$ with $\overline{\mathcal{N}}_{l+1}(y) = \mathcal{N}_{l+1}(y, G_x) \cup \{y\}$.

3 Methodology

In this section, we aim at proposing a renewable WCQR estimation to estimate $m(x)$ and $\sigma(x)$ for $x \in I_*$ with I_* a bounded interval on \mathbb{R} .

3.1 Renewable WCQR Estimation

We start from a special case of (4), where the measure ν exists a density function $J(\cdot)$ on $[0, 1]$, and the WCQR estimator $\hat{m}_L(x; \nu)$ can be expressed as

$$\hat{r}(x; J) = \int_{[0,1]} J(\tau) \widehat{Q}_{Y|x}(\tau) d\tau. \quad (7)$$

By selecting appropriate $J(\cdot)$, the estimator $\hat{r}(x; J)$ is able to estimate a kind of parameters that can expressed as

$$r(x; J) = \int_{[0,1]} J(\tau) Q_{Y|x}(\tau) d\tau. \quad (8)$$

To obtain $\hat{r}(x; J)$, the conventional approach is to minimize an L_1 -norm loss function characterized by the check function $\rho_\tau(u) = u(\tau - I(u \leq 0))$. However, solving such a non-smooth minimization problem is quite difficult when the data are of the form of streaming data sets. To address this issue, we manage to avoid estimating the quantiles in (3). Thus we introduce the substitution: $y = \widehat{Q}_{Y|x}(\tau)$, i.e., $\tau = \widehat{F}_{Y|x}(y)$ and rewrite (7) into

$$\hat{r}(x; J) = \int_{\mathbb{R}} y J\left(\widehat{F}_{Y|x}(y)\right) d\widehat{F}_{Y|x}(y), \quad (9)$$

where $\widehat{F}_{Y|x}(y)$ is an estimator of the CDF $F_{Y|x}(y)$.

Now the the key problem is to obtain a renewable estimation of $F_{Y|x}(\cdot)$. To this end, we approximate $F_{Y|x}(\cdot)$ by its LPI function given by

$$\mathcal{I}_l F_{Y|x}(y) = \sum_{y_i \in G_x} F_{Y|x}(y_i) L(y, y_i; l, G_x), \quad (10)$$

where $G_x = \{y_i\}_{i=1}^q$ is the set of interpolation nodes chosen for $x \in I_*$ and $L(\cdot, y_i; l, G_x)$ are PLI basis functions defined in (5). Then the unknown values $F_{Y|x}(y_i)$ can be estimated by their empirical analogues obtained from the streaming data sets $\mathcal{D}_1, \mathcal{D}_2, \dots$, i.e.,

$$\widehat{F}_{Y|x,t}(y_i) = \frac{\widehat{S}_{Y|x,t}(y_i)}{\widehat{f}_{X,t}(x)} \quad \text{for } y_i \in G_x, \quad (11)$$

where $\widehat{f}_{X,t}(x)$ and $\widehat{S}_{Y|x,t}(y_i)$ are renewable statistics obtained by

$$\begin{aligned} N_t &= N_{t-1} + n_t, \\ \widehat{f}_{X,t}(x) &= \frac{N_{t-1}}{N_t} \widehat{f}_{X,t-1}(x) \\ &\quad + \frac{1}{N_t} \sum_{j=1}^{n_t} K_{h_t}(X_{tj} - x), \quad (12) \\ \widehat{S}_{Y|x,t}(y_i) &= \frac{N_{t-1}}{N_t} \widehat{S}_{Y|x,t-1}(y_i) \\ &\quad + \frac{1}{N_t} \sum_{j=1}^{n_t} I(Y_{tj} < y_i) K_{h_t}(X_{tj} - x) \quad (13) \end{aligned}$$

with initial values $N_0 = \widehat{f}_{X,0}(x) = \widehat{S}_{Y|x,0}(y_i) = 0$ and the bandwidths $h_t > 0$. Based on (10), we plug in the estimators $\widehat{F}_{Y|x,t}(y_i)$ of $F_{Y|x}(y_i)$ and obtain the interpolated empirical CDF as follows

$$\mathcal{I}_l \widehat{F}_{Y|x,t}(y) = \sum_{y_i \in G_x} \widehat{F}_{Y|x,t}(y_i) L(y, y_i; l, G_x). \quad (14)$$

By (9) with $\mathcal{I}_l \widehat{F}_{Y|x,t}(y)$ in place of $\widehat{F}_{Y|x}(y)$, we can obtain the renewable WCQR estimator as

$$\widetilde{r}_t(x; J) = \int_{\mathbb{R}} y J\left(\mathcal{I}_l \widehat{F}_{Y|x,t}(y)\right) d\mathcal{I}_l \widehat{F}_{Y|x,t}(y). \quad (15)$$

Since the expression of $\mathcal{I}_l \widehat{F}_{Y|x,t}(\cdot)$ is known, the integral in (15) can be accurately approximated by numerical integrations, e.g., the well-known

trapezoidal rule, Simpson rule and Romberg integration, etc (see, e.g., Section 3 of Gautschi 2012).

By applying LPI on the x -axis, we can extend the pointwise estimator $\widetilde{r}_t(x; J)$ to estimate the function $r(\cdot; J)$ on the entire interval $x \in I_*$. Specifically, we can approximate $r(\cdot; J)$ by its LPI function, i.e.,

$$\mathcal{I}_l r(x; J) = \sum_{x_i \in G_*} r(x_i; J) L(x, x_i; l, G_*), \quad (16)$$

where $G_* = \{x_i\}_{i=1}^{\bar{q}}$ is a set of grid points introduced on the interval I_* , and typically x_i can be chosen as equal-spaced grid points on I_* . With $r(x_i; J)$ estimated by $\widetilde{r}_t(x_i; J)$, we can obtain the renewable interpolated WCQR estimator as

$$\mathcal{I}_l \widetilde{r}_t(x; J) = \sum_{x_i \in G} \widetilde{r}_t(x_i; J) L(x, x_i; l, G_*) \quad (17)$$

for $x \in I_*$. In Section 3.3, we will see that $\mathcal{I}_l \widetilde{r}_t(\cdot; J)$ plays a role in selecting the weight function $J(\cdot)$ for streaming data.

For the restriction on the weight function in (15), we have the following remark.

Remark 1 By Lemma 1, we can conclude that

$$\begin{aligned} &\|\mathcal{I}_l F_{Y|x} - F_{Y|x}\|_{\infty, I(G_x)} \\ &\leq \|F_{Y|x}^{(l+1)}\|_{\infty, I(G_x)} |\Delta(G_x)|^{l+1} \end{aligned}$$

with $I(G_x) = [\min G_x, \max G_x]$. Thus if $F_{Y|x}(\cdot)$ is sufficiently smooth and the nodes are dense enough, the error caused from LPI can be negligible on $I(G_x)$. However, when y moves away from the interval $I(G_x)$, the LPI approximation cannot guarantee its accuracy. Fortunately, we can select appropriate $J(\cdot)$ to suppress the error of LPI when y lies outside $I(G_x)$. Specifically, for the renewable WCQR estimator $\widetilde{r}_t(x; J)$, we can select $J(\cdot)$ satisfying

$$\text{Supp}\{J(\cdot)\} \subset \mathcal{I}_l \widehat{F}_{Y|x,t}^{-1}(I(G_x)). \quad (18)$$

And for the interpolated WCQR estimator $\mathcal{I}_l \widetilde{r}_t(\cdot; J)$, we can select $J(\cdot)$ satisfying (18) for all $x \in G_*$ with G_* satisfying $I(G_*) \supset I_*$. Given $I(G_x)$ wide enough, the above restrictions are mild in robust estimations, because $\text{Supp}\{J(\cdot)\} \subset (0, 1)$ is a natural condition to guarantee the robustness of $\widehat{r}(x; J)$ (see, e.g., Section 8.1.3 of Serfling, 1980).

In the remainder of this section, we mainly discuss the selection of the weight function $J(\cdot)$,

which plays a key role in reducing the estimation bias and variance of our renewable WCQR estimator.

3.2 Model-Based Weight Selections

To estimate $m(x)$ (resp. $\sigma(x)$) by renewable WCQR estimation, we should select appropriate weight functions $J(\cdot)$ to establish the equality $r(x; J) = m(x)$ (resp. $\sigma(x)$). To this end, recalling (8) and using the relation $Q_{Y|x}(\tau) = m(x) + \sigma(x)F_\varepsilon^{-1}(\tau)$ obtained from the model (1), we can deduce

$$\begin{aligned} r(x; J) &= m(x) \int_{[0,1]} J(\tau) d\tau \\ &+ \sigma(x) \int_{[0,1]} J(\tau) F_\varepsilon^{-1}(\tau) d\tau, \end{aligned} \quad (19)$$

which yields the conditions for estimating $m(x)$:

$$\begin{aligned} C_{m1} &: \int_{[0,1]} J(\tau) d\tau = 1, \\ C_{m2} &: \int_{[0,1]} J(\tau) F_\varepsilon^{-1}(\tau) d\tau = 0, \end{aligned} \quad (20)$$

and the conditions for estimating $\sigma(x)$:

$$\begin{aligned} C_{\sigma1} &: \int_{[0,1]} J(\tau) d\tau = 0, \\ C_{\sigma2} &: \int_{[0,1]} J(\tau) F_\varepsilon^{-1}(\tau) d\tau = 1. \end{aligned} \quad (21)$$

Among the above conditions, C_{m1} and $C_{\sigma1}$ can be easily satisfied. However, C_{m2} and $C_{\sigma2}$ are related to the unknown quantile function $F_\varepsilon^{-1}(\cdot)$. Unless the error distribution is known to be symmetric, it is quite difficult to choose $J(\cdot)$ in an online-updating manner; see the following remark.

Remark 2 In the existing works, e.g., Sun et al. (2013); Lin et al. (2019); Jiang et al. (2016), the condition C_{m2} is fulfilled empirically by replacing the unknown function $F_\varepsilon^{-1}(\cdot)$ with its estimator $\widehat{F}_\varepsilon^{-1}(\cdot)$. Here $\widehat{F}_\varepsilon^{-1}(\cdot)$ is the sample quantile function of the ‘‘pseudo’’ samples $\widehat{\varepsilon}_{ti} = (Y_{ti} - \widehat{m}(X_{ti})) / \widehat{\sigma}(X_{ti})$, where $\widehat{m}(\cdot)$ and $\widehat{\sigma}(\cdot)$ are some pilot estimators of $m(\cdot)$ and $\sigma(\cdot)$. The generation of pseudo samples involves reusing the historical raw data and requires sophisticated computations, which are hardly to be implemented for streaming data.

To avoid the problem mentioned above, we fully use the structure of the Model (1) and obtain the following important lemma, which gives an alternative way to fulfill the conditions C_{m2} and $C_{\sigma2}$.

Lemma 2 *Let $W : \mathbb{R} \rightarrow \mathbb{R}$ be a function satisfying $\mathbb{E}[W(X)\sigma(X)] > 0$, then the following results hold:*

i) *if C_{m1} holds, then*

$$\begin{aligned} \mathbb{E}[W(X)\sigma(X)] &= \int_{[0,1]} J(\tau) F_\varepsilon^{-1}(\tau) d\tau \\ &= \mathbb{E}[W(X)(r(X; J) - Y)]; \end{aligned}$$

ii) *if $C_{\sigma1}$ holds, then*

$$\begin{aligned} \mathbb{E}[W(X)r^2(X; J)] &= \left(\int_{[0,1]} J(\tau) F_\varepsilon^{-1}(\tau) d\tau \right)^2 \\ &= \mathbb{E}[W(X)(Y^2 - m^2(X))]. \end{aligned}$$

Lemma 2 suggests the following alternative conditions on the weight function:

$$C'_{m2} : \mathbb{E}[W(X)r(X; J)] = \mathbb{E}[W(X)Y], \quad (22)$$

$$\begin{aligned} C'_{\sigma2} &: \mathbb{E}[W(X)r^2(X; J)] \\ &= \mathbb{E}[W(X)(Y^2 - m^2(X))]. \end{aligned} \quad (23)$$

Lemma 2 also shows that $(C_{m1}, C_{m2}) \Leftrightarrow (C_{m1}, C'_{m2})$ and $(C_{\sigma1}, C_{\sigma2}) \Leftrightarrow (C_{\sigma1}, C'_{\sigma2})$, i.e., the condition C_{m2} (resp. $C_{\sigma2}$) can be equivalently replaced with C'_{m2} (resp. $C'_{\sigma2}$). The following remark shows the advantage of C'_{m2} over C_{m2} .

Remark 3 As stated in Remark 2, to fulfill C_{m2} , the existing methods in Sun et al. (2013); Lin et al. (2019); Jiang et al. (2016) rely on the estimation of the inverse of the CDF of ε , which is unavailable directly from the sample set of (X, Y) . Instead of directly related to the distribution of the error, the condition C'_{m2} only relies on the two expectations in (22), which can be directly estimated by the sample of (X, Y) , and the estimation has the convergence rate of parametric estimation. Moreover, in the next subsection, we will see that C'_{m2} can be easily expressed in a renewable form.

Although the condition $C'_{\sigma2}$ in (23) relies on the unknown regression function $m(\cdot)$, it will be shown in the next subsection that the unknown $m(\cdot)$ does not bring any essential difficulties to our renewable estimation.

3.3 Specific Renewable WCQR Estimators and Algorithms

To construct specific $J(\cdot)$ satisfying the conditions in the last subsection, we can obtain specific WCQR estimators for $m(x)$ and $\sigma(x)$.

Throughout this subsection, we assume that the function $W(\cdot)$ in (22) and (23) satisfies $\text{Supp}\{W(\cdot)\} \subset I_*$, under which we can avoid estimating $r(x; J)$ with x outside of I_* . The simplest example of $W(\cdot)$ is that $W(x) = I(x \in I_*)$.

3.3.1 Estimators for the Conditional Mean

We first consider a simple case, where the model (1) is symmetric in the sense that the PDF of ε is symmetric around 0. For symmetric models, (C_{m1}, C_{m2}) can be easily fulfilled whenever $J(\cdot)$ is normalized and symmetric around 1/2. A representative example is the α -trimmed weight function:

$$J_{m,0.5}(\tau) = 0.5L_\alpha(\tau) + 0.5U_\alpha(\tau), \quad (24)$$

where $L_\alpha(\tau) = (0.5 - \alpha)^{-1} I(\alpha \leq \tau \leq 0.5)$ and $U_\alpha(\tau) = (0.5 - \alpha)^{-1} I(0.5 < \tau \leq 1 - \alpha)$ with $\alpha \in (0, 0.5)$ selected according to Remark 1. With the weight function $J_{m,0.5}(\cdot)$, the WCQR estimator $\tilde{r}_t(x; J_{m,0.5})$ given by (15) is a renewable version of the native local α -trimmed mean (NTM) (see, e.g., Bednar and Watt, 1984; Boente and Fraiman, 1994), and in the following, we will call $\tilde{r}_t(x; J_{m,0.5})$ the renewable NTM.

The following remark shows that the NTM is robust to outliers but not adaptive to symmetric or asymmetric error distributions.

Remark 4 The prototype of $\tilde{r}_t(x; J_{m,0.5})$ is the α -trimmed mean, which has been singled out by several prominent authors as the quintessential robust estimator of location (see, e.g., Bickel and Lehmann, 1975; Stigler, 1977; Koenker, 2005). And we can expect that $\tilde{r}_t(x; J_{m,0.5})$ enjoys robustness comparable to the α -trimmed mean. However, since $\tilde{r}_t(x; J_{m,0.5})$ actually estimate the location $r(x; J_{m,0.5})$ rather than the conditional mean $m(x)$, the estimation consistency deeply relies on the symmetry of the error to guarantee the conditions (C_{m1}, C_{m2}) and the equality $r(x; J_{m,0.5}) = m(x)$. When the error distribution is asymmetric, the estimator $\tilde{r}_t(x; J_{m,0.5})$ will suffer

from a non-negligible bias caused from $r(x; J_{m,0.5}) \neq m(x)$.

To address the issue mentioned in Remark 4, we should modify the α -trimmed weight function $J_{m,0.5}(\cdot)$, such that the conditions (C_{m1}, C_{m2}) can be fulfilled for general error distributions. Thus we generalize $J_{m,0.5}(\cdot)$ into

$$J_{m,w}(\tau) = \omega L_\alpha(\tau) + (1 - \omega) U_\alpha(\tau), \quad (25)$$

where $w \in \mathbb{R}$ is a parameter selected to satisfy the alternative condition C'_{m2} , i.e.,

$$w = \frac{E_{WY} - E_{WU}}{E_{WL} - E_{WU}} \quad (26)$$

with

$$\begin{aligned} E_{WY} &= \mathbb{E}[W(X)Y], \\ E_{WL} &= \int_{I_*} W(x) r(x; L_\alpha) f_X(x) dx, \\ E_{WU} &= \int_{I_*} W(x) r(x; U_\alpha) f_X(x) dx. \end{aligned}$$

Since $J_{m,w}(\cdot)$ satisfies (C_{m1}, C'_{m2}) implying that $r(x; J_{m,w}) = m(x)$, i.e., the non-negligible bias is corrected. In the following text, we will call $\tilde{r}_t(x; J_{m,w})$ the renewable bias-corrected local α -trimmed mean (BCTM).

Remark 5 The BCTM $\hat{r}(x; J_{m,w})$ is an extension of the NTM $\hat{r}(x; J_{m,0.5})$. Actually, when the model (1) is symmetric, by straightforward calculation, we have $w = 1/2$, in which case $\hat{r}(x; J_{m,w})$ is identical to $\hat{r}(x; J_{m,0.5})$.

To obtain the BCTM for streaming data, we should construct a renewable estimator for the unknown w . Based on the expressions in (26) and the plug-in estimators, w can be estimated by

$$\hat{w}_t = \frac{\hat{E}_{WY,t} - \hat{E}_{WU,t}}{\hat{E}_{WL,t} - \hat{E}_{WU,t}} \quad (27)$$

where

$$\begin{aligned}\widehat{E}_{WY,t} &= \frac{N_{t-1}}{N_t} \widehat{E}_{WY,t-1} + \frac{1}{N_t} \sum_{j=1}^{n_t} W(X_{tj}) Y_{tj} \\ \widehat{E}_{WL,t} &= \int_{I_*} W(x) \mathcal{I}_l \tilde{r}_t(x; L_\alpha) \mathcal{I}_l \widehat{f}_{X,t}(x) dx, \\ \widehat{E}_{WU,t} &= \int_{I_*} W(x) \mathcal{I}_l \tilde{r}_t(x; U_\alpha) \mathcal{I}_l \widehat{f}_{X,t}(x) dx\end{aligned}$$

with the initial value $\widehat{E}_{WY,0} = 0$. Here $\mathcal{I}_l \tilde{r}_t(\cdot; L_\alpha)$ and $\mathcal{I}_l \tilde{r}_t(\cdot; U_\alpha)$ are the interpolated WCQR estimator given in (17), and $\mathcal{I}_l f_X(\cdot)$ is the interpolated empirical PDF given by

$$\mathcal{I}_l f_X(\cdot) = \sum_{x_i \in G_*} \widehat{f}_{X,t}(x_i) L(\cdot, x_i; l, G_*) \quad (28)$$

with $\widehat{f}_{X,t}(x_i)$ the renewable statistics obtained by (12) and G_* the node set introduced in (16).

If we omit the error caused by LPI approximation, \widehat{w}_t is a consistent estimator of w , and we known from the Slutsky's Lemma that the estimator $\tilde{r}_t(x; J_{m,\widehat{w}_t})$ has the same asymptotic distribution as that of $\tilde{r}_t(x; J_{m,w})$.

In the following remark, we show the pros and cons of the BCTM compared with the NTM.

Remark 6 Compared with the NTM, the first advantage of the BCTM is that the estimation consistency is based on the structure of the model instead of the symmetry of the error. Thus the BCTM is adaptive to symmetric or asymmetric error distributions. However this adaptiveness comes with a little costs in robustness, when estimating the parameter ω . Actually, it is easy to check that the estimators $\widehat{E}_{W1,t}$ and $\widehat{E}_{W2,t}$ have bounded influence functions, and thus both of them are robust to outliers. However, the estimator $\widehat{E}_{WY,t}$ is somewhat non-robust. Fortunately, the unknown $E_{WY,t}$ is a scalar parameter rather than a general function, thus the estimator $\widehat{E}_{WY,t}$ can achieve $\sqrt{N_t}$ -consistency, which is faster than the optimal convergence rate of nonparametric regression estimation. Hence the final nonparametric estimator $\tilde{r}_t(x; J_{m,\widehat{w}_t})$ is less susceptible to the weak robustness of $\widehat{E}_{WY,t}$. This point will be further demonstrated in our numerical studies in Section 5.

In Algorithm 1, we present the detail procedures to obtain the renewable BCTM for the

estimation of $m(x)$ with x belonging to some grid points in I_1 .

3.3.2 Estimators for the Conditional Variance

To estimate $\sigma(x)$, the first condition $C_{\sigma 1}$ can be fulfilled by taking $J(\cdot)$ antisymmetry around 1/2. Then parallel to the NTM, we introduce the antisymmetry α -trimmed weight function:

$$J_{\sigma,1}(\tau) = (-L_\alpha(\tau) + U_\alpha(\tau)). \quad (29)$$

From (19) and (29), we can see that

$$r(x; J_{\sigma,1}) = c_0 \sigma(x) \text{ for } x \in I_*$$

with $c_0 = \int_{[0,1]} J_{\sigma,1}(\tau) F_\varepsilon^{-1}(\tau) d\tau$ a constant independent with x . Thus the renewable WCQR estimator $\tilde{r}_t(x; J_{\sigma,1})$ is qualified to estimate $\sigma(x)$ consistently up to scale; that is,

$$\tilde{r}_t(x; J_{\sigma,1}) = c_0 \sigma(x) + O\left(|\Delta(G_x)|^{l+1}\right) + o_p(1).$$

If we aim higher and want to estimate $\sigma(x)$ consistently, we should rescale the weight function such that $c_0 = 1$, or equivalently, $C_{\sigma 2}$ holds. To this end, we extend $J_{\sigma,1}(\cdot)$ into

$$J_{\sigma,\theta}(\tau) = \theta J_{\sigma,1}(\tau) \quad (30)$$

where θ is a scale parameter selected to satisfying the alternative $C'_{\sigma 2}$, i.e.,

$$\theta^2 = \frac{\mathbb{E}[W(X)(Y^2 - m^2(X))]}{\mathbb{E}[W(X)r^2(X; J_{\sigma,1})]}. \quad (31)$$

The main issue is to obtain a renewable estimation of the unknown θ . Similar to the idea introduced in Section 3.3.1, we can estimate θ by

$$\widehat{\theta}_t = \sqrt{\frac{\widehat{E}_{WY^2,t} - \widehat{E}_{Wm^2,t}}{\widehat{E}_{Wr^2,t}}} \quad (32)$$

Algorithm 1 Renewable BCTM for estimating $\{m(x_i)\}_{i=1}^{\bar{q}}$ with x_i grid points on \mathbb{R}

Input Set of grid points $G_* = \{x_i\}_{i=1}^{\bar{q}}$, kernel function $K(\cdot)$, node sets G_{x_i} for $x_i \in G_*$, PLI degree l

- 1: Set initial values $N_0 = \widehat{E}_{WY,0} = \widehat{f}_{X,0}(x_i) = \widehat{S}_{Y|x_i,0}(y_{ij}) = 0$ for $y_{ij} \in G_{x_i}$ and $x_i \in G_*$
- 2: **for** $t = 1, 2, \dots$ **do**
- 3: Obtain the t -th data batch $\mathcal{D}_t = \{X_{tj}, Y_{tj}\}_{j=1}^{n_t}$
- 4: Select the t -th bandwidth h_t
- 5: $N_t = N_{t-1} + n_t$
- 6: $\widehat{E}_{WY,t} = N_{t-1}/N_t \widehat{E}_{WY,t-1} + 1/N_t \sum_{j=1}^{n_t} W(X_{tj})Y_{tj}$
- 7: **for** $x_i \in G_*$ **do**
- 8: $\widehat{f}_{X,t}(x_i) = N_{t-1}/N_t \widehat{f}_{X,t-1}(x_i) + 1/N_t \sum_{j=1}^{n_t} K_{h_t}(X_{tj} - x_i)$, where $K_h(\cdot) = 1/hK(\cdot/h)$
- 9: $\widehat{S}_{Y|x_i,t}(y_{ij}) = N_{t-1}/N_t \widehat{S}_{Y|x_i,t-1}(y_{ij}) + 1/N_t \sum_{j=1}^{n_t} I(Y_{tj} < y_{ij}) K_{h_t}(X_{tj} - x_i)$ for $y_{ij} \in G_{x_i}$
- 10: **end for**
- 11: **if** the estimators for $\{m(x_i)\}_{x_i \in G_*}$ are needed **then**
- 12: Define the function $\mathcal{I}_l \widehat{f}_{X,t}(\cdot) = \sum_{x_i \in G_*} \widehat{f}_{X,t}(x_i) L(\cdot, x_i; l, G_*)$
- 13: Define the function $\mathcal{I}_l \widehat{F}_{Y|x_i,t}(\cdot) = \sum_{y_{ij} \in G_{x_i}} \widehat{S}_{Y|x_i,t}(y_{ij}) / \widehat{f}_{X,t}(x_i) L(\cdot, y_{ij}; l, G_{x_i})$ for $x_i \in G_*$
- 14: **for** $J \in \{L_\alpha, U_\alpha\}$ **do**
- 15: $\tilde{r}_t(x_i; J) = \int_{\mathbb{R}} y J(\mathcal{I}_l \widehat{F}_{Y|x_i,t}(y)) d\mathcal{I}_l \widehat{F}_{Y|x_i,t}(y)$ for $x_i \in G_*$
- 16: Define the function $\mathcal{I}_l \tilde{r}_t(\cdot; J) = \sum_{x_i \in G_*} \tilde{r}_t(x_i; J) L(\cdot, x_i; l, G_*)$
- 17: **end for**
- 18: $\widehat{E}_{WL,t} = \int_{I_*} W(x) \mathcal{I}_l \tilde{r}_t(x; L_\alpha) \mathcal{I}_l \widehat{f}_{X,t}(x) dx$
- 19: $\widehat{E}_{WU,t} = \int_{I_*} W(x) \mathcal{I}_l \tilde{r}_t(x; U_\alpha) \mathcal{I}_l \widehat{f}_{X,t}(x) dx$
- 20: $\widehat{w}_t = (\widehat{E}_{WY,t} - \widehat{E}_{WU,t}) / (\widehat{E}_{WL,t} - \widehat{E}_{WU,t})$
- 21: $\tilde{r}_t(x_i; J_{m, \widehat{w}_t}) = \widehat{w}_t \tilde{r}_t(x_i; L_\alpha) + (1 - \widehat{w}_t) \tilde{r}_t(x_i; U_\alpha)$ for $x_i \in G_*$
- 22: Output $\{\tilde{r}_t(x_i; J_{m, \widehat{w}_t})\}_{x_i \in G_*}$ as the estimators for $\{m(x_i)\}_{x_i \in G_*}$
- 23: **end if**
- 24: **end for**

where

$$\widehat{E}_{WY^2,t} = \frac{N_{t-1}}{N_t} \widehat{E}_{WY^2,t-1} + \frac{1}{N_t} \sum_{j=1}^{n_t} W(X_{tj}) Y_{tj}^2,$$

$$\widehat{E}_{Wm^2,t} = \int_{I_*} W(x) \tilde{m}_t^2(x) \mathcal{I}_l \widehat{f}_{X,t}(x) dx,$$

$$\widehat{E}_{Wr^2,t} = \int_{I_*} W(x) (\mathcal{I}_l \tilde{r}_t)^2(x; J_{\sigma,1}) \mathcal{I}_l \widehat{f}_{X,t}(x) dx$$

with the initial value $\widehat{E}_{WY^2,0} = 0$. Here $\mathcal{I}_l \tilde{r}_t(\cdot; J_{\sigma,1})$ and $\mathcal{I}_l \widehat{f}_{X,t}(\cdot)$ are renewable estimators obtained by (17) and (28), respectively, and $\tilde{m}_t(\cdot)$ is an renewable estimator of $m(\cdot)$, e.g.,

$$\tilde{m}_t(\cdot) = \mathcal{I}_l \tilde{r}_t(\cdot; J_{m,w}).$$

with $w = 0.5$ for symmetric models and $w = \widehat{w}_t$ given in (27) for asymmetric models.

Based on (15) with $J_{\sigma, \widehat{\theta}_t}(\cdot)$ in place of $J(\cdot)$, we can obtain the renewable estimator $\tilde{r}_t(x; J_{\sigma, \widehat{\theta}_t})$ for the conditional standard deviation $\sigma(x)$. In the following remark, we make a comparison between the two estimators $\tilde{r}_t(x; J_{\sigma,1})$ and $\tilde{r}_t(x; J_{\sigma, \widehat{\theta}_t})$.

Remark 7 The estimator $\tilde{r}_t(x; J_{\sigma, \widehat{\theta}_t})$ contains more information about $\sigma(x)$, since it can identify the constant c_0 , which is unrevealed by $\tilde{r}_t(x; J_{\sigma,1})$. In another aspect, $\tilde{r}_t(x; J_{\sigma,1})$ enjoys stronger robustness, which is comparable to the classic α -trimmed mean. However $\tilde{r}_t(x; J_{\sigma, \widehat{\theta}_t})$ depends on the plug-in estimator $\widehat{E}_{WY^2,t}$, and similar to the discussions in Remark 6, $\widehat{E}_{WY^2,t}$ is somewhat non-robust but enjoys the convergence rate of parametric estimation.

In the supplementary material, we present a complete algorithm to obtain renewable WCQR

estimators for $m(x)$ and $\sigma(x)$ from asymmetric models.

In the following remark, we show the desirable computation efficiency of our algorithms in dealing with rapid data streams.

Remark 8 Algorithm 1 mainly consists of two parts: the updating part (Lines 5 - 10) where the cumulative statistics are updated, and the estimation part (Lines 12 - 21) where the WCQR estimator is computed by calculating integrals. Notice that the updating part is relatively simple without solving any nonlinear equations. And at each updating step, the computations among each $x_* \in G_*$ can be implemented parallelly. Benefit from this, the updating part can be implemented fast enough to catch up with the rapid data stream. The estimation part seems to be computationally intensive. Fortunately, this part is implemented only when one needs the current value of the WCQR estimator. Thus it would not cause trouble in computation speed even when the data stream is rapid. The above desirable feature is also enjoyed by Algorithm A.1 in the supplementary material.

4 Theoretical Analyses

In this section, we will deduce the asymptotic distribution of the renewable WCQR estimator, based on which we will propose renewable bandwidth selectors and obtain the optimal weight functions by minimizing the asymptotic variance.

4.1 Asymptotic Distributions

For theoretical analyses of the estimator $\tilde{r}_t(x; J)$, we introduce the following standard assumptions.

Assumption 1 *The functions $f_X(\cdot)$, $m(\cdot)$ and $\sigma(\cdot)$ have continuous derivatives up to order 4 on I_* . On a open set containing $\text{Supp}\{J(\cdot)\}$, the function $F_\varepsilon(\cdot)$ has continuous derivatives up to order $\max\{l+1, 4\}$, where l is the degree of PLI given in (10). The function $f_X(\cdot)$ admits a positive lower bounded on I_* .*

Assumption 2 *The kernel function $K(u)$ is symmetric and compactly supported, and satisfies that $\int_{\mathbb{R}} K(u)du = 1$, $k_{4,1} = \int_{\mathbb{R}} u^4 K(u)du < \infty$ and $k_{0,2} = \int_{\mathbb{R}} K^2(u)du < \infty$.*

Assumption 3 *The bandwidth h_t and smoothing parameter b_t satisfies that as $t \rightarrow \infty$,*

$$h_t = o(1) \quad \text{and} \quad \sum_{s=1}^t \frac{n_s}{h_s} \left(\sum_{s=1}^t n_s h_s^4 \right)^{-2} = o(1), \quad (33)$$

$$\frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} = o(1). \quad (34)$$

Assumption 4 *The L-score function $J(\cdot)$ is piecewise continuously differentiable. There exist constants $0 < \underline{\tau} < \bar{\tau} < 1$ such that $\text{Supp}\{J(\cdot)\} \subset [\underline{\tau}, \bar{\tau}]$. The node set G_x satisfies $[\underline{\tau}, \bar{\tau}] \subset (\min F_{Y|x}(G_x), \max F_{Y|x}(G_x))$.*

In Assumptions 1 and 2, all the conditions on $f_X(\cdot)$, $m(\cdot)$, $\sigma(\cdot)$ and $K(\cdot)$ are standard for nonparametric regressions, and the condition on $F_\varepsilon(\cdot)$ is required by the LPI approximation to guarantee its accuracy. Among the conditions in Assumption 3, the first one in (33) is required for a vanishing estimation bias; the second one in (33) is used to simplify the bias terms in the asymptotic results; the last condition (34) is necessary for a bounded estimation variance, and it is fulfilled whenever $N_t \min_{1 \leq s \leq t} h_s \rightarrow \infty$. Assumption 4 is used to bound the remainder term in the asymptotic expansion of $\tilde{r}_t(x; J)$; the restrictions on $\text{Supp}\{J(\cdot)\}$ and G_x are also required by the LPI approximation and in practical applications, it can be fulfilled empirically; see Remark 1.

The following theorem gives the asymptotic properties of the interpolated empirical CDF $\mathcal{I}_l \hat{F}_{Y|x,t}(\cdot)$.

Theorem 3 *Under Assumptions 1 - 3, it holds for $y \in \mathbb{R}$ that*

$$\left\{ \frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \right\}^{-1/2} \left\{ \mathcal{I}_l \hat{F}_{Y|x,t}(y) - F_{Y|x}(y) - R_{\mathcal{I}_l, F, x}(y) - \mathcal{I}_l B_{F, x}(y) \sum_{s=1}^t \frac{n_s h_s^2}{N_t} \right\} \xrightarrow{d} N\left(0, \mathcal{I}_l^2 C_{F, x}(y, y)\right),$$

where

$$R_{\mathcal{I}_l, F, x}(y) = -\frac{F_{Y|x}^{(l+1)}(y)(c)}{(l+1)!} \prod_{y_i \in \mathcal{N}_{l+1}(y, G_x)} (y - y_i),$$

$$\mathcal{I}_l B_{F, x}(y) = \sum_{y_i \in G_x} B_{F, x}(y_i) L(y, y_i; l, G_x),$$

$$\mathcal{I}_l^2 C_{F,x}(z_1, z_2) = \sum_{y_i, y_j \in G_x} L(z_1, y_i; l, G_x) \times L(z_2, y_j; l, G_x) C_{F,x}(y_i, y_j)$$

with

$$B_{F,x}(y_i) = \frac{k_{2,1}}{2} \left\{ \partial_x^2 F_{Y|x}(y_i) + 2\partial_x F_{Y|x}(y_i) \frac{f'_X(x)}{f_X(x)} \right\}, \quad (35)$$

$$C_{F,x}(y_i, y_j) = \frac{k_{0,2}}{f_X(x)} \left\{ F_{Y|x}(y_i \wedge y_j) - F_{Y|x}(y_i) F_{Y|x}(y_j) \right\} \quad (36)$$

and $c \in [\min \bar{N}_{l+1}(y), \max \bar{N}_{l+1}(y)]$ with $\bar{N}_{l+1}(y)$ given in Lemma 1.

Based on Theorem 3, we can conclude that

$$\begin{aligned} \left\| \mathcal{I}_l \widehat{F}_{Y|x,t} - F_{Y|x} \right\|_{2,I(G_x)} &= O(|\Delta(G_x)|^{l+1}) \\ + O\left(\sum_{s=1}^t \frac{n_s h_s^2}{N_t} \right) &+ O_p \left(\sqrt{\frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s}} \right). \end{aligned} \quad (37)$$

From (37) we can see that the error of our interpolated empirical CDF consists of two parts: the first part depending on $\Delta(G_x)$ is a numerical error caused from the LPI approximation, and the second part depending on the bandwidths consists of statistical errors corresponding to the bias and variance of kernel estimations. Because the statistical errors have a convergence rate the same with that of the oracle empirical CDF obtained on the imaginary full data set $\cup_{s \leq t} \mathcal{D}_t$, and the numerical error is usually negligible compared with the statistical ones (see the following Remark 9), it can be expected that our estimator enjoys a performance almost as well as the oracle estimator.

Remark 9 In practical applications, the numerical error in (37) is usually much smaller than the remaining statistical errors. Actually, when the nodes in G_x are uniformly spaced, the numerical error is of order $O((\#G_x)^{-(l+1)})$, which can be reduced significantly by increasing the number $\#G_x$ of nodes and the degrees l of LPI, whenever the computation resources permit. Unlike the numerical one, the statistical errors deeply rely on the number N_t of samples, and the convergence rate is relatively slow (no more than $O(N_t^{-2/5})$).

Based on Theorem 3, we have the following main result on the asymptotic property of the estimator $\tilde{r}_t(x; J)$.

Theorem 4 *Under Assumptions 1 - 4, it holds that*

$$\begin{aligned} &\left\{ \frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \right\}^{-1/2} \left\{ \tilde{r}_t(x; J) - r(x; J) \right. \\ &\left. - B_{\mathcal{I}_l, m, x} \sum_{s=1}^t \frac{n_s h_s^2}{N_t} - R_{\mathcal{I}_l, m, x} \right\} \xrightarrow{d} N(0, \Sigma_{\mathcal{I}_l, m, x}). \end{aligned} \quad (38)$$

where

$$B_{\mathcal{I}_l, m, x} = - \int_{\mathbb{R}} J(F_{Y|x}(y)) \mathcal{I}_l B_{F,x}(y) dy,$$

$$R_{\mathcal{I}_l, m, x} = - \int_{\mathbb{R}} J(F_{Y|x}(y)) R_{\mathcal{I}_l, F, x}(y) dy + O(|\Delta(G_x)|^{2l+2}),$$

$$\Sigma_{\mathcal{I}_l, m, x} = \int_{\mathbb{R}} \int_{\mathbb{R}} C_{\mathcal{I}_l, J, x}(z_1, z_2) dz_1 dz_2$$

with

$$C_{\mathcal{I}_l, J, x}(z_1, z_2) = J(F_{Y|x}(z_1)) J(F_{Y|x}(z_2)) \times \mathcal{I}_l^2 C_{F,x}(z_1, z_2)$$

and $\mathcal{I}_l B_{F,x}(y)$, $R_{\mathcal{I}_l, F, x}(y)$ and $\mathcal{I}_l^2 C_{F,x}(z_1, z_2)$ given in Theorem 3.

Theorem 4 shows that the LPI operator \mathcal{I}_l has influence on the asymptotic bias and variance of $\tilde{r}_t(x; J)$, while its influence is no more than the order of numerical errors. The following corollary states the details.

Corollary 5 *Under the conditions of Theorem 4, it holds that*

$$B_{\mathcal{I}_l, m, x} = B_{m, x} + O(|\Delta(G_x)|^{l+1}),$$

$$R_{\mathcal{I}_l, m, x} = O(|\Delta(G_x)|^{l+1})$$

$$\Sigma_{\mathcal{I}_l, m, x} = \Sigma_{m, x} + O(|\Delta(G_x)|^{l+1}),$$

where the dominant terms are

$$B_{m, x} = - \int_{\mathbb{R}} J(F_{Y|x}(y)) B_{F,x}(y) dy$$

$$\Sigma_{m, x} = \frac{k_{0,2} \sigma^2(x)}{f_X(x)} \int_{[\underline{\tau}, \bar{\tau}]} \int_{[\underline{\tau}, \bar{\tau}]} S_J(\tau_1, \tau_2) d\tau_1 d\tau_2$$

with

$$S_J(\tau_1, \tau_2) = \frac{(\tau_1 \wedge \tau_2 - \tau_1 \tau_2) J(\tau_1) J(\tau_2)}{f_\varepsilon(F_\varepsilon^{-1}(\tau_1)) f_\varepsilon(F_\varepsilon^{-1}(\tau_2))}. \quad (39)$$

Combining Theorem 4 and Corollary 5, we can find that the error between $\tilde{r}_t(x; J)$ and $r(x; J)$ has a convergence rate the same with the error given in (37), i.e.,

$$\begin{aligned} \tilde{r}_t(x; J) - r(x; J) &= O(|\Delta(G_x)|^{l+1}) \\ &+ O\left(\sum_{s=1}^t \frac{n_s h_s^2}{N_t}\right) + O_p\left(\sqrt{\frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s}}\right), \end{aligned} \quad (40)$$

where the first term is the numerical error caused from LPI, and the remaining two terms are statistical errors caused from kernel estimations. By the discussion in Remark 9, the numerical error is usually negligible compared with the statistical ones. Moreover, the convergence rates of the statistical errors are the same with that of the oracle estimator $\hat{r}(x; J)$ obtained on the imaginary full data set $\cup_{s \leq t} \mathcal{D}_t$. Theoretically, our renewable WCQR estimator behaves almost as well as the oracle estimator.

Based on the relation (19) and the results in Lemma 2 and Theorem 4, we can immediately obtain the following corollary, which gives asymptotic properties of the estimators introduced in Section 3.3.

Corollary 6 *Given $J(\cdot)$ satisfying (C_{m1}, C_{m2}) or (C_{m1}, C'_{m2}) (resp. $(C_{\sigma 1}, C_{\sigma 2})$ or $(C_{\sigma 1}, C'_{\sigma 2})$), the result (38) in Theorem 4 holds with $r(x; J)$ replaced with $m(x)$ (resp. $\sigma(x)$).*

4.2 The Selection of Bandwidths

For implementing bandwidth selection, we need to calculate the asymptotic mean square error (AMSE) and the asymptotic mean integrated squared error (AMISE) between $\tilde{r}_t(x; J)$ and $r(x; J)$. It follows from Theorem 4 and Corollary 5 that the asymptotic bias and variance of $\tilde{r}_t(x; J)$ can be given by

$$\begin{aligned} \text{Bias}\{\tilde{r}_t(x; J)\} &= B_{m,x} \sum_{s=1}^t \frac{n_s}{N_t} h_s^2 \\ &+ o\left(\sum_{s=1}^t \frac{n_s}{N_t} h_s^2\right) + O(|\Delta(G_x)|^{l+1}), \\ \text{Var}\{\tilde{r}_t(x; J)\} &= \frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \Sigma_{m,x} \end{aligned}$$

$$+ \frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \left(o(1) + O(|\Delta(G_x)|^{l+1}) \right).$$

By Remark 9, it is reasonable to assume the numerical error is negligible compared with the statistical ones, thus we can omit the terms $O(|\Delta(G_x)|^{l+1})$ and other high order terms in the asymptotic bias and variance. Then the AMSE and AMISE can be respectively defined as

$$\begin{aligned} \text{AMSE}\{\tilde{r}_t(x; J)\} &= \mathcal{E}_t(x; H_t), \\ \text{AMISE}\{\tilde{r}_t(x; J)\} &= \int_{I_*} \mathcal{E}_t(x; H_t) \widetilde{W}(x) dx, \end{aligned}$$

where $\widetilde{W}(\cdot)$ is a weight function defined on I_* ; $H_t = (h_1, \dots, h_t)^\top$ is a vector consisting of the used bandwidth components h_s up to the t -th data batch and $\mathcal{E}_t(x; \cdot)$ is an error function defined by

$$\begin{aligned} \mathcal{E}_t(x; H_t) &= \left(B_{m,x} \sum_{s=1}^t \frac{n_s h_s^2}{N_t} \right)^2 \\ &+ \frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \Sigma_{m,x} \end{aligned} \quad (41)$$

with the asymptotic bias $B_{m,x}$ and the asymptotic variance $\Sigma_{m,x}$ given in Corollary 5.

4.2.1 Theoretically optimal bandwidths

We first consider an ideal situation where the streaming data is finite with the terminal time T and the cumulative number N_T known throughout the updating procedures $t = 1, \dots, T$. In this case, the theoretical optimal variable bandwidths $\tilde{H}_T^*(x) = (\tilde{h}_1^*(x), \dots, \tilde{h}_T^*(x))^\top$ and the optimal constant bandwidth $\tilde{H}_T^* = (\tilde{h}_1^*, \dots, \tilde{h}_T^*)^\top$ can be obtained conventionally by minimizing the terminal AMSE and AMISE, respectively, i.e.,

$$\begin{aligned} \tilde{H}_T^*(x) &= \arg \min_{H_T \in [0, \infty)^T} \mathcal{E}_T(x; H_T), \\ \tilde{H}_T^* &= \arg \min_{H_T \in [0, \infty)^T} \int_{I_*} \mathcal{E}_T(x; H_T) \widetilde{W}(x) dx. \end{aligned}$$

A straightforward calculation leads to

$$\tilde{h}_t^*(x) = (C_h(x))^{1/5} N_T^{-1/5}, \quad \tilde{h}_t^* = (C_h)^{1/5} N_T^{-1/5} \quad (42)$$

for $t = 1, \dots, T$, where

$$C_h(x) = \frac{\Sigma_{m,x}}{4(B_{m,x})^2},$$

$$C_h = \frac{\int_{I_*} \Sigma_{m,x} \widetilde{W}(x) dx}{4 \int_{I_*} (B_{m,x})^2 \widetilde{W}(x) dx}.$$

The following remark shows the standard statistical convergence rate of $\tilde{r}_T(x; J)$ under the optimal bandwidths.

Remark 10 Recalling the error expressions in (37) and (40), we conclude that when the bandwidths are the optimal ones given in (42), the statistical errors of $\mathcal{I}_l \widehat{F}_{Y|x,T}(\cdot)$ and $\tilde{r}_T(x; J)$ both enjoy the optimal convergence rate of $O_p(N_T^{-2/5})$. We should remark that such a standard convergence rate is obtained on the streaming data sets without any restrictions on the batch size or batch number.

4.2.2 Practical sub-optimal bandwidths

It is usually closer to the real condition that the streaming data are endless or the terminal cumulative number N_T is unpredictable. In such a case, the theoretical optimal bandwidths in (42) are impractical, and we have to find sub-optimal bandwidths that do not rely on the information of future streaming data sets. To this end, we introduce the following lemma, which reveals the structure of the error function given in (41).

Lemma 7 *The function \mathcal{E}_t defined in (41) has the decomposition:*

$$\mathcal{E}_t(x; H_t) = \left(\frac{N_{t-1}}{N_t} \right)^2 \mathcal{E}_{t-1}(x; H_{t-1})$$

$$+ \left(\frac{n_t}{N_t} \right)^2 E_t(x, h_t; H_{t-1})$$

with $E_t(x, h_t; H_{t-1})$ defined by

$$E_t(x, h_t; H_{t-1}) = h_t^4 (B_{m,x})^2 + \frac{1}{n_t h_t} \Sigma_{m,x}$$

$$+ 2h_t^2 \sum_{s=1}^{t-1} \frac{n_s h_s^2}{n_t} (B_{m,x})^2.$$

From Lemma 7, we can see that at t -th updating procedure, the AMSE \mathcal{E}_t can be expressed as a weighted sum of two parts: the first one \mathcal{E}_{t-1}

is the error of the last updating step, which has a fixed value at the current updating procedure; the second part $E_t(x, h_t; H_{t-1})$ relies on h_t and H_{t-1} , where H_{t-1} has been given in the previous updating procedure and only h_t is need to be determined. Thus the optimal value of h_t should minimize $E_t(x, h_t; H_{t-1})$ after the value of H_{t-1} is given. We thus define the sub-optimal variable and constant bandwidths respectively by

$$h_t^*(x) = \arg \min_{h_t \in [0, \infty)} E_t(x, h_t; H_{t-1}^*(x)),$$

$$h_t^* = \arg \min_{h_t \in [0, \infty)} \int_{I_*} E_t(x, h_t; H_{t-1}^*) \widetilde{W}(x) dx,$$

where $H_{t-1}^*(x) = (h_1^*(x), \dots, h_{t-1}^*(x))^\top$ and $H_{t-1}^* = (h_1^*, \dots, h_{t-1}^*)^\top$ are the sub-optimal bandwidths selected for the first $t-1$ data batches. By straightforward calculation, the sub-optimal bandwidths can be obtained by solving the following equations:

$$h_t^*(x) = \{C_h(x)\}^{1/3} \left(\sum_{s=1}^{t-1} n_s (h_s^*(x))^2 \right. \\ \left. + n_t (h_t^*(x))^2 \right)^{-1/3}, \quad (43)$$

$$h_t^* = C_h^{1/3} \left(\sum_{s=1}^{t-1} n_s (h_s^*)^2 + n_t (h_t^*)^2 \right)^{-1/3}. \quad (44)$$

The sub-optimal bandwidths in (43) and (44) are given by non-linear equations, which are not convenient for practical applications, especially in the scenario of the fast online-updating. To address this issue, we use $h_{s-1}^*(x)$ and h_{s-1}^* to approximate the unknown $h_s^*(x)$ and h_s^* on the right side of (43) and (44), respectively, which lead to the online-updating bandwidths that

$$\widehat{h}_t(x) = \{C_h(x)\}^{1/3} \{S_{h,t}(x)\}^{-1/3}, \quad (45)$$

$$\widehat{h}_t = C_h^{1/3} S_{h,t}^{-1/3}$$

for $t = 2, \dots, T$, where

$$S_{h,t}(x) = S_{h,t-1}(x) + n_t \left(\widehat{h}_{t-1}^*(x) \right)^2,$$

$$S_{h,t-1} = S_{h,t-1} + n_t \left(\widehat{h}_{t-1}^* \right)^2$$

with the initial values given by $S_{h,1}(x) = S_{h,1} = 0$, $\tilde{h}_1^*(x) = (C_h(x))^{1/5} n_1^{-1/5}$ and $\tilde{h}_t^* = (C_h)^{1/5} n_1^{-1/5}$.

The optimal and sub-optimal bandwidths in (42) and (45) all depend on unknown parameters. In practical applications, the unknown parameters can be estimated by cross validations on a validation data set. More details will be discussed in Section 5.

4.3 The Optimal Weight Functions

Although the renewable WCQR estimators introduced in Section 3.3 can estimate $m(x)$ and $\sigma(x)$ at a convergence rate comparable to the oracle estimators, their weight functions are generally not optimal in terms of estimation variance. Based on the asymptotic distribution in Theorem 4, we can go a step further to find the optimal weight function in the sense the associated renewable estimator estimate $m(x)$ or $\sigma(x)$ with a minimized asymptotic variance.

To this end, we introduce the set $\mathbb{J}_m(\underline{\tau}, \bar{\tau})$ (resp. $\mathbb{J}_\sigma(\underline{\tau}, \bar{\tau})$) consisting of all the weight functions $J(\cdot) : [0, 1] \rightarrow \mathbb{R}$ satisfying the constrains (C_{m1}, C_{m2}) (resp. $(C_{\sigma1}, C_{\sigma2})$) and being square integrable with a support in $[\underline{\tau}, \bar{\tau}] \subset (0, 1)$. Here $\underline{\tau}$ and $\bar{\tau}$ are pre-given parameters introduced in Assumption 4. By Theorem 4 and Corollary 5, the variance of $\hat{r}(x; J)$ can be expressed as

$$\begin{aligned} & \left(\frac{1}{N_t} \sum_{s=1}^t \frac{n_s}{N_t h_s} \right)^{-1} \text{Var} \{ \tilde{m}(x; J) \} \\ &= \frac{k_{0,2} \sigma^2(x)}{f_X(x)} V(J) + O(|\Delta(G_x)|^{l+1}) + o(1) \end{aligned}$$

with $V(\cdot)$ a quadratic functional given by

$$V(J) = \int_{[\underline{\tau}, \bar{\tau}]} \int_{[\underline{\tau}, \bar{\tau}]} S_J(\tau_1, \tau_2) d\tau_1 d\tau_2. \quad (46)$$

For $z(\cdot) = m(\cdot)$ or $\sigma(\cdot)$, the optimal weight function $J_z^*(\cdot)$ for estimating $z(x)$ is given by the following functional minimization problem:

$$J_z^*(\cdot) = \arg \min_{J \in \mathbb{J}_z(\underline{\tau}, \bar{\tau})} V(J) \quad \text{for } z = m, \sigma. \quad (47)$$

By tools of variational analysis, we can obtain the closed-form expression of $J_z^*(\cdot)$ as in the following theorem and corollary.

Theorem 8 *Given $f_\varepsilon(\cdot)$ twice differentiable, the optimal weight function in (47) can be expressed by*

$$J_z^*(\tau) = I(\underline{\tau} \leq \tau \leq \bar{\tau}) (C_1 \Psi_1(\tau) + C_2 \Psi_2(\tau)), \quad (48)$$

where $\Psi_i(\cdot)$, $i = 1, 2$, are two basis function given by

$$\Psi_i(\tau) = -\{(\delta_{1i} + \delta_{2i} I_d) \log f_\varepsilon\}'' \left(F_\varepsilon^{-1}(\tau) \right) \quad (49)$$

with I_d the identity function, i.e., $I_d(y) = y$ for $y \in \mathbb{R}$; the coefficients C_1 and C_2 are coefficients selected to satisfy the corresponding conditions in (20) or (21) i.e.,

$$\begin{aligned} \text{if } z = m, \quad C_i &= \frac{\delta_{1i} A_{12} - \delta_{2i} A_{11}}{A_{01} A_{12} - A_{02} A_{11}}, \quad i = 1, 2, \\ \text{if } z = \sigma, \quad C_i &= \frac{\delta_{2i} A_{01} - \delta_{1i} A_{02}}{A_{01} A_{12} - A_{02} A_{11}}, \quad i = 1, 2, \end{aligned}$$

with

$$A_{kj} = \int_{[\underline{\tau}, \bar{\tau}]} \left(F_\varepsilon^{-1}(\tau) \right)^k \Psi_j(\tau) d\tau,$$

for $k = 0, 1$, and $j = 1, 2$.

The following remark shows that Theorem 8 is an extension of existing results about the optimal weight functions in L-Estimation.

Remark 11 Theorem 8 allows us to find the optimal weight function under the constraint $\text{Supp}\{J(\cdot)\} \subset [\underline{\tau}, \bar{\tau}]$. This constraint is artificially introduced to control the error caused from LPI (see Remark 1). If we consider a special case of Theorem 8, where $[\underline{\tau}, \bar{\tau}] = [0, 1]$, i.e., the constraint on $\text{Supp}\{J(\cdot)\}$ is removed, then the optimal weight function $J_m^*(\cdot)$ (resp. $J_\sigma^*(\cdot)$) degenerates into $\Psi_1(\cdot)$ (resp. $\Psi_2(\cdot)$), which is just the optimal score functions for $m(x)$ (reps. $\sigma(x)$) given in Portnoy and Koenker (1989); Koenker (2005).

The optimal weight function in (48) is deeply related to the distribution function and the PDF of the error, which can be difficult to estimate especially in the case of streaming data. In the following corollary, we manage to express $J_z^*(\cdot)$ using the CDF $F_{Y|x}(\cdot)$.

Corollary 9 *Under Assumption 1, the optimal weight function in (48) can be expressed as*

$$J_z^*(\tau) = I(\underline{\tau} \leq \tau \leq \bar{\tau}) (\tilde{C}_1 \tilde{\Psi}_1(\tau) + \tilde{C}_2 \tilde{\Psi}_2(\tau)), \quad (50)$$

where $\tilde{\Psi}_i(\cdot)$, $i = 1, 2$, are basis functions given by

$$\tilde{\Psi}_i(\tau) = - \int_{I_*} \{(\delta_{1i} + \delta_{2i} \mathbf{I}_d) \log F_{Y|x}'\}'' \left(F_{Y|x}^{-1}(\tau) \right) dx$$

and the coefficients \tilde{C}_1 and \tilde{C}_2 are selected to fulfill the corresponding conditions (C_{z1}, C'_{z2}) , i.e.,

$$\text{if } z = m, \quad \begin{cases} \tilde{C}_1 = \frac{d_0 \tilde{A}_{12} - d_1 \tilde{A}_{02}}{\tilde{A}_{01} \tilde{A}_{12} - \tilde{A}_{02} \tilde{A}_{11}}, \\ \tilde{C}_2 = \frac{-d_0 \tilde{A}_{11} + d_1 \tilde{A}_{01}}{\tilde{A}_{01} \tilde{A}_{12} - \tilde{A}_{02} \tilde{A}_{11}}, \end{cases}$$

$$\text{if } z = \sigma, \quad \begin{cases} \tilde{C}_1 \tilde{A}_{01} + \tilde{C}_2 \tilde{A}_{02} = 0, \\ \tilde{C}_1^2 \tilde{D}_{1,1} + 2\tilde{C}_1 \tilde{C}_2 \tilde{D}_{1,2} + \tilde{C}_2^2 \tilde{D}_{2,2} = d_3^2, \end{cases}$$

with $d_0 = 1$, $d_1 = \mathbb{E}[W(X)Y]$ and

$$d_3^2 = \mathbb{E} \left[W(X)(Y^2 - m^2(X)) \right],$$

$$\tilde{A}_{kj} = \int_{I_*} \int_{\mathbb{R}} \{yW(x)f_X(x)\}^k \times \tilde{\Psi}_j(F_{Y|x}(y)) dF_{Y|x}(y) dx,$$

for $k = 0, 1$ and $j = 1, 2$.

Corollary 9 suggests a renewable estimation method for the optimal weight function based on the interpolated empirical CDF given in (14). Specifically speaking, the estimator of $J_z^*(\cdot)$ can be given by (50) with the unknown $F_{Y|x}(\cdot)$ and its derivatives replaced by $\mathcal{I}_l \hat{F}_{Y|x,t}(\cdot)$ and its corresponding derivatives, and the involved constants \tilde{C}_i can be estimated by renewable procedures similar to the ones introduced in (27) and (32).

5 Numerical Experiments

In this section, we conduct simulation studies and real data analyses to verify performance of various estimators involved in this paper.

In the numerical experiments, all the involved kernel functions are taken as the Epanechnikov kernel, i.e., $K(z) = \max\{0, 3/4(1 - z^2)\}$. To implement the renewable WCQR estimation, 3rd-degree LPI is used to obtain the interpolated empirical CDF. To obtain the LPI nodes, the set G_* is formed by 100 grid points evenly distributed over the intervals I_* . And for each x_i in G_* , the set G_{x_i} consists of the points y_{ij} given by

$$y_{ij} = \arg \min_{y \in \mathbb{R}} \sum_{q: X_q \in \mathcal{N}_k(x_i, \mathcal{D}_{\text{val}})} \rho_{\tau_j}(Y_q - y)$$

for $\tau_j = j/100$ and $j = 1, \dots, 99$, where \mathcal{N}_k is defined in Section 2.2 and \mathcal{D}_{val} is a validation data set containing the first 1000 samples collected from the data stream.

For implementations, we need to artificially determine a terminal time T for the streaming data sets. Depending on whether or not the cumulative number N_T is supposed to be known, we consider two bandwidth selectors: the ‘‘oracle’’ optimal constant bandwidth \hat{h}_t^* from (42) and the online-updating constant bandwidth \hat{h}_t from (45). The unknown constant C_h in (42) and (45) is replaced by its estimator \hat{C}_h obtained by 5-fold Cross-Validation on the validation data set \mathcal{D}_{val} .

We mainly discuss the performance of the following two proposed online-updating estimators:

- \tilde{r}_{ntm} : the NTM $\tilde{r}_T(x; J_{m,1/2})$ defined in (15) with the weight function $J_{m,1/2}$ given in (25) with $\alpha = 0.1$; the bandwidth is selected as the online-updating \hat{h}_t given in (45) with C_h replaced by \hat{C}_h .
- \tilde{r}_{bctm} : the BCTM $\tilde{r}_T(x; J_{m,\hat{w}_T})$ defined in (15) with the weight function J_{m,\hat{w}_T} given in (25) with $\alpha = 0.1$ and \hat{w}_T obtained by (27); the bandwidth selector is the same with that of \tilde{r}_{ntm} .

For comparison, we introduce the following benchmark estimators:

- $\tilde{r}_{\text{bctm}}^*$: the oracle BCTM computed on the full data \mathcal{D} , i.e.,

$$\tilde{r}_{\text{bctm}}^*(x) = \int_{\mathbb{R}} J_{m,\hat{w}_T}(\tau) \hat{Q}_{Y|x}^*(\tau) d\tau,$$

where

$$\hat{Q}_{Y|x}^*(\tau) = \arg \min_{y \in \mathbb{R}} \sum_{t=1}^T \mathcal{L}(y; x, \tau, \mathcal{D}_t),$$

$$\mathcal{L}(y; x, \tau, \mathcal{D}_t) = \sum_{j=1}^{n_t} \rho_{\tau}(Y_{tj} - y) K_{h_t}(X_{tj} - x);$$

here all h_t are selected as the estimated oracle optimal constant bandwidths, i.e., $h_t = \hat{C}_h n_T^{-1/5}$.

- $\tilde{r}_{\text{bctm}}^a$: the simple average of the BCTMs computed on the data batches $\mathcal{D}_1, \dots, \mathcal{D}_T$; more

specifically,

$$\begin{aligned}\tilde{r}_{\text{bctm}}^{\text{a}}(x) &= \frac{1}{T} \sum_{t=1}^T \tilde{r}_{\text{bctm}}^{[t]}(x), \\ \tilde{r}_{\text{bctm}}^{[t]}(x) &= \int_{\mathbb{R}} J_{m, \hat{w}_T}(\tau) \hat{Q}_{Y|x}^{[t]}(\tau) d\tau\end{aligned}$$

with $\hat{Q}_{Y|x}^{[t]}(\tau) = \arg \min_{y \in \mathbb{R}} \mathcal{L}(y; x, \tau, \mathcal{D}_t)$; here all h_t are selected as the estimated local optimal constant bandwidths as $h_t = \hat{C}_h n_t^{-1/5}$.

- \tilde{r}_{nw} : the Nadaraya-Watson (NW) estimator given by $\tilde{r}_{\text{nw}}(x) = Z_{Y,T}(x)/Z_T(x)$, where $Z_{Y,T}(x)$ and $Z_T(x)$ are renewable estimators obtained by

$$\begin{aligned}Z_{Y,t}(x) &= Z_{Y,t-1}(x) + \sum_{j=1}^{n_t} Y_{tj} K_{h_t}(X_{tj} - x), \\ Z_t(x) &= Z_{t-1}(x) + \sum_{j=1}^{n_t} K_{h_t}(X_{tj} - x),\end{aligned}$$

and the bandwidth selector is similar to that of \tilde{r}_{ntm} and \tilde{r}_{bctm} , i.e., h_t is given by (45) with the constant C_h estimated by 5-fold Cross-Validation on \mathcal{D}_{val} .

5.1 Simulation Studies

In the simulation studies, we will consider various experiment conditions, such as homoscedastic or heteroscedastic models, and symmetric or asymmetric errors. To this end, we introduce the following two models:

$$\begin{aligned}\text{Model1 :} & Y = \sin(2X) + 2 \exp(-16X^2) + 0.5\varepsilon \\ & \text{with } X \sim N(0, 1), \quad I_* = [-1.5, 1.5], \\ \text{Model2 :} & Y = X \sin(2\pi X) + (2 + \cos(2\pi X))\varepsilon \\ & \text{with } X \sim U(0, 1), \quad I_* = [0, 1].\end{aligned}$$

The above Model 1 and model 2 are respectively homoscedastic and heteroscedastic, and were discussed by Fan and Gijbels (1992). We consider various kinds of distributions of ε . Moreover, we use the mixtures of two error distributions to model so-called contaminated data. More specifically, a mixture distribution is chosen as $0.95F_\varepsilon + 0.05F_{\lambda\varepsilon}$ with a multiplying factor λ , where F_ε is the distribution function of ε . If without special statement, all the distributions of ε involved in the

simulations are centralized. Based on the combinations of different models and error distributions, we consider the following four examples:

- Example 1a: the Model 1 with various symmetric error distributions;
- Example 1b: the Model 1 with various asymmetric error distributions;
- Example 2a: the Model 2 with various symmetric error distributions;
- Example 2b: the Model 2 with various asymmetric error distributions.

To model the streaming data, we generate the full data of size N_T from the considered models and equally divide the full data into T data batches. To show the influence of the number of data batches, we fix $N_T = 10^4$ and successively take $T = 1, 5, 10, 100, 1000$, resulting the size of each data batch $n_t = 10^4, 2 \times 10^3, 10^3, 10^2, 10$, respectively.

For each estimation, the number of replications in the simulation is designed as 400. The performance of any estimator $\hat{g}(\cdot)$ of a function $g(\cdot)$ is evaluated by the average squared errors (ASEs) defined by $\text{ASE}(\hat{g}) = (\#G_*)^{-1} \sum_{x_i \in G_*} |\hat{g}(x_i) - g(x_i)|^2$. We use the ratio of average squared errors (RASEs): $\text{RASE}(\hat{g}_1, \hat{g}_2) = \text{ASE}(\hat{g}_1)/\text{ASE}(\hat{g}_2)$ to compare the performance of two estimators \hat{g}_1 and \hat{g}_2 . We test the involved estimators in the four test examples, and report the RMSEs in Tables 1 and 2. For the presented numerical results, we have the following discussions:

We first focus on the performance of the proposed estimator \tilde{r}_{bctm} with \tilde{r}_{nw} used as a benchmark. From the $\text{RASE}(\tilde{r}_{\text{nw}}, \tilde{r}_{\text{bctm}})$ in Table 1, we can see that when $\lambda = 1$, i.e., there is no contaminations in the streaming data, the relative performance between \tilde{r}_{bctm} and \tilde{r}_{nw} depends on the choices of the error distributions. Generally, \tilde{r}_{bctm} show a relatively better performance than \tilde{r}_{nw} when the error distribution is non-normal and heavy tailed. This phenomenon is in line with the feature of quantile estimations. However, when $\lambda > 1$, i.e., the streaming data are contaminated, the values of $\text{RASE}(\tilde{r}_{\text{nw}}, \tilde{r}_{\text{bctm}})$ are greater than 1 in most cases, indicating that \tilde{r}_{bctm} outperforms \tilde{r}_{nw} uniformly for all choices of the considered error distributions and the size n_t of data batches. Generally, the values

Table 1 The performance comparison between \tilde{r}_{bctm} , \tilde{r}_{ntm} and \tilde{r}_{nw} under models with various error distributions

Example	Distribution	λ	RASE($\tilde{r}_{\text{nw}}, \tilde{r}_{\text{bctm}}$)				RASE($\tilde{r}_{\text{bctm}}, \tilde{r}_{\text{ntm}}$)			
			$T = 10$		$T = 100$		$T = 10$		$T = 100$	
			mean	std.	mean	std.	mean	std.	mean	std.
1a	$N(0, 1)$	1	1.022	0.217	0.824	0.132	0.989	0.251	1.048	0.168
		3	1.007	0.214	1.204	0.248	1.047	0.229	0.909	0.189
		5	1.357	0.495	1.419	0.454	1.041	0.403	1.032	0.333
		10	2.855	1.014	2.590	0.888	1.193	0.452	0.979	0.382
	Standard Laplace	1	1.573	0.378	1.470	0.427	1.126	0.310	0.962	0.243
		3	1.725	0.470	1.694	0.479	1.013	0.276	1.035	0.282
		5	2.306	0.750	1.803	0.565	1.029	0.310	1.274	0.442
		10	3.352	1.414	4.752	1.877	1.337	0.464	1.062	0.346
	t(3)	1	1.568	0.482	1.857	0.675	0.949	0.395	0.970	0.308
		3	1.765	0.528	1.953	0.701	1.064	0.377	0.815	0.282
		5	2.703	1.297	2.781	1.192	1.182	0.583	1.121	0.528
		10	5.494	3.647	5.512	2.176	1.120	0.608	1.070	0.372
2a	$N(0, 1)$	1	0.449	0.112	0.769	0.118	1.098	0.268	1.179	0.201
		3	0.668	0.164	0.748	0.141	1.068	0.256	1.404	0.378
		5	0.612	0.198	0.661	0.183	1.050	0.347	1.153	0.327
		10	1.445	0.414	1.446	0.473	1.779	0.757	1.109	0.377
	Standard Laplace	1	0.813	0.238	1.111	0.206	1.094	0.331	1.108	0.224
		3	1.803	0.480	0.948	0.198	1.110	0.306	1.077	0.233
		5	1.206	0.446	1.258	0.321	1.430	0.589	0.984	0.253
		10	2.159	0.759	4.373	1.602	1.263	0.428	0.987	0.394
	t(3)	1	1.376	0.270	1.659	0.574	0.989	0.198	1.065	0.370
		3	2.186	0.873	1.167	0.371	1.048	0.348	1.088	0.357
		5	2.643	0.968	1.351	0.504	1.041	0.352	1.141	0.463
		10	3.018	1.115	1.674	0.625	1.152	0.381	1.207	0.482
1b	F(10, 6)	1	1.009	0.321	1.083	0.342	0.070	0.026	0.064	0.019
		3	1.149	0.731	1.136	0.439	0.080	0.056	0.072	0.027
		5	1.613	1.268	1.191	0.577	0.094	0.065	0.119	0.049
		10	3.173	1.729	2.650	1.274	0.072	0.037	0.097	0.044
	Gamma(5, 1)	1	0.907	0.197	0.865	0.181	0.197	0.064	0.228	0.074
		3	1.145	0.322	1.054	0.208	0.197	0.067	0.270	0.071
		5	1.175	0.395	1.487	0.427	0.234	0.070	0.198	0.068
		10	2.547	0.767	3.989	1.907	0.277	0.090	0.234	0.069
	Lognorm(0, 1)	1	0.830	0.359	0.787	0.223	0.064	0.028	0.062	0.020
		3	1.030	0.341	0.832	0.304	0.071	0.019	0.093	0.027
		5	2.060	1.564	1.586	0.657	0.052	0.032	0.073	0.030
		10	1.931	1.178	3.297	1.466	0.097	0.045	0.070	0.030
2b	F(10, 4)	1	0.948	0.646	1.607	0.927	0.179	0.255	0.052	0.030
		3	2.102	0.974	1.174	0.555	0.058	0.023	0.071	0.027
		5	2.328	1.063	1.670	0.853	0.091	0.034	0.106	0.068
		10	2.289	1.475	1.739	1.412	0.142	0.173	0.146	0.229
	F(2, 5)	1	1.229	1.261	0.877	0.300	0.234	1.007	0.123	0.034
		3	0.826	0.280	1.040	0.342	0.134	0.041	0.129	0.031
		5	1.225	0.482	1.441	0.743	0.112	0.041	0.311	1.412
		10	1.270	0.662	1.613	0.713	0.206	0.118	0.139	0.056
	Lognorm(0.5, 1)	1	0.930	0.372	0.920	0.363	0.048	0.023	0.049	0.027
		3	1.530	0.485	1.048	0.448	0.045	0.015	0.039	0.018
		5	2.101	1.159	1.585	0.540	0.041	0.016	0.068	0.019
		10	1.774	0.626	3.877	1.741	0.087	0.031	0.053	0.029

of RASE($\tilde{r}_{\text{nw}}, \tilde{r}_{\text{bctm}}$) increase when λ increasing. This means that compare with the NW estimator, the BCTM is more robust to contaminated data.

In the following, we show the adaptiveness of our estimators under various symmetric and asymmetric error distributions. To this end, we

compare the performance of the bias-corrected estimator \tilde{r}_{bctm} and its prototype \tilde{r}_{ntm} without bias-correction. From the RASE($\tilde{r}_{\text{bctm}}, \tilde{r}_{\text{ntm}}$) in Table 1, we can see that \tilde{r}_{ntm} slightly outperforms \tilde{r}_{bctm} in Example 1a and 2a, where the error distributions are symmetric. However, for

Table 2 The performance comparison between \tilde{r}_{bctm} and $\tilde{r}_{\text{bctm}}^*$ under streaming data with various batch sizes

Example	Distribution	λ	RASE($\tilde{r}_{\text{bctm}}^*$, \tilde{r}_{bctm})							
			$T = 5$		$T = 10$		$T = 100$		$T = 1000$	
			mean	std.	mean	std.	mean	std.	mean	std.
1a	$N(0, 1)$	1	1.024	0.120	1.036	0.137	0.943	0.127	0.937	0.147
		3	1.106	0.116	0.879	0.107	0.993	0.147	1.003	0.172
		5	0.969	0.127	1.095	0.163	1.098	0.182	1.025	0.149
		10	1.069	0.116	1.053	0.133	0.992	0.150	1.063	0.151
	Standard Laplace	1	0.992	0.140	1.045	0.165	1.056	0.191	0.958	0.147
		3	0.968	0.117	1.114	0.153	1.106	0.182	1.173	0.183
		5	1.018	0.145	1.015	0.125	0.879	0.125	0.992	0.149
		10	1.051	0.124	0.802	0.098	0.939	0.120	0.756	0.113
	t(3)	1	1.015	0.131	1.058	0.141	1.067	0.154	0.968	0.128
		3	1.012	0.140	0.846	0.108	0.956	0.129	0.932	0.130
		5	1.037	0.123	0.925	0.119	1.096	0.166	1.159	0.180
		10	0.894	0.113	0.988	0.125	0.831	0.104	0.833	0.111
1b	F(10, 6)	1	0.908	0.102	0.956	0.147	0.901	0.111	0.922	0.151
		3	1.088	0.133	0.846	0.090	0.822	0.104	1.075	0.173
		5	0.885	0.091	0.843	0.074	0.726	0.083	0.875	0.118
		10	0.860	0.065	0.999	0.116	0.836	0.096	0.993	0.165
	Gamma(5, 1)	1	1.042	0.109	1.014	0.135	1.056	0.140	1.027	0.151
		3	1.121	0.144	1.003	0.131	0.826	0.109	0.867	0.137
		5	0.990	0.116	0.905	0.128	0.959	0.147	1.091	0.149
		10	1.120	0.133	0.776	0.075	1.147	0.159	1.089	0.147
	Lognorm(0, 1)	1	1.011	0.102	1.060	0.141	0.819	0.103	0.959	0.144
		3	1.046	0.129	0.875	0.099	0.799	0.094	0.875	0.115
		5	0.851	0.075	0.996	0.137	0.820	0.098	0.940	0.142
		10	0.912	0.094	0.776	0.067	0.870	0.105	1.018	0.121
2a	$N(0, 1)$	1	0.945	0.066	0.891	0.056	0.813	0.054	0.841	0.056
		3	0.924	0.057	0.897	0.061	0.792	0.061	0.843	0.059
		5	0.895	0.059	0.919	0.064	0.813	0.054	0.840	0.073
		10	0.912	0.048	0.818	0.049	0.841	0.071	0.883	0.082
	Standard Laplace	1	0.887	0.063	0.895	0.067	0.777	0.075	0.751	0.050
		3	0.853	0.040	0.879	0.100	0.755	0.061	0.844	0.081
		5	0.864	0.059	0.838	0.074	0.778	0.063	0.839	0.075
		10	0.829	0.056	0.853	0.064	0.856	0.077	0.747	0.072
	t(3)	1	0.897	0.061	0.880	0.054	0.865	0.080	0.854	0.065
		3	0.956	0.079	0.923	0.086	0.898	0.091	0.828	0.075
		5	0.949	0.077	0.855	0.108	0.870	0.069	0.797	0.078
		10	0.885	0.068	0.852	0.049	0.792	0.049	0.794	0.059
2b	F(10, 4)	1	1.014	0.120	0.906	0.079	1.001	0.151	0.786	0.089
		3	0.896	0.086	0.867	0.109	1.022	0.147	1.049	0.152
		5	0.929	0.113	0.913	0.117	0.934	0.129	0.930	0.143
		10	0.846	0.066	0.946	0.138	0.748	0.111	0.811	0.119
	F(2, 5)	1	0.970	0.093	0.887	0.100	1.097	0.130	0.951	0.129
		3	0.869	0.066	0.791	0.065	0.929	0.091	0.787	0.088
		5	1.018	0.109	0.823	0.088	0.820	0.119	0.762	0.084
		10	1.020	0.125	0.780	0.053	0.739	0.069	0.991	0.154
	Lognorm(0.5, 1)	1	0.927	0.119	0.965	0.108	0.788	0.148	0.768	0.108
		3	0.815	0.067	0.905	0.129	0.822	0.128	0.891	0.148
		5	0.980	0.086	1.079	0.165	0.828	0.110	0.672	0.080
		10	0.859	0.088	0.783	0.090	0.848	0.119	0.790	0.098

the asymmetric error distributions in Example 1b and 2b, all the values of RASE(\tilde{r}_{bctm} , \tilde{r}_{ntm}) are closed to zero, indicating that the NTM can be inconsistent and far inferior to the BCTM. The above results show that under the weight selection criterions in Section 3.2, our renewable

WCQR estimator is adaptive to symmetric and asymmetric error distributions.

To show the pros and cons of the BCTM compared with the NTM, we recall that the two estimators both use the weight function defined in (25) but with different values of the parameter

w . For models with symmetric error distributions, eliminating the dominant bias requires $w = 1/2$. The NTM exactly uses this value, while the BCTM uses the estimated value in (27), which is obtained from the data and thus results a little loss in efficiency. However, the results in Table 1 also show that the advantage of NTM over BCTM is only established on the prerequisite that the error distribution is known to be symmetric. This is usually impractical in the application scenarios of robust statistic with massive data sets. Moreover, we also find that even in Example 1a and 2a with large λ and with heavy-tailed error distributions, there is no obvious gap between the BCTM and the NTM, which justifies our claim in Remark 6 that the robustness of the BCTM is not susceptible to the non-robust estimation of E_{WY} .

Finally, we discuss the influence of data partitioning on the online-updating estimators. In Table 2, we consider various batch sizes n_t and present the relative performance of the online-updating estimator \tilde{r}_{bctm} compared with its oracle counterpart $\tilde{r}_{\text{bctm}}^*$ obtained on the full data. We can see that, for homoscedastic models, all the RASE ($\tilde{r}_{\text{bctm}}^*, \tilde{r}_{\text{bctm}}$) are insensitive to n_t with most values closed to 1. And for heteroscedastic models, most values of RASE ($\tilde{r}_{\text{bctm}}^*, \tilde{r}_{\text{bctm}}$) are slightly less than 1. Even if the size n_t of each data batch is only 10, our online-updating BCTM still performs well with most RASEs no less than 0.75. This is because the partitioning of full data only effects the selection of the bandwidths of \tilde{r}_{bctm} in case of unpredictable N_T . In general, the above numerical results show that in our estimation method, the effects of data partitioning are quite small, and our online-updating estimator enjoys desirable properties comparable to the oracle estimator.

5.2 Real Data Examples

For case study, we apply our method to the Beijing Multi-Site Air-Quality Data set from the UCI machine learning repository (<https://archive-beta.ics.uci.edu/ml/datasets/beijing+multi+site+air+quality+data>). This data set consists of hourly data about 6 main air pollutants and 6 relevant meteorological variables collected from 12 nationally-controlled air-quality monitoring sites in Beijing, China. The observational data cover the time period from March

Table 3 The relations studied in Real Data Examples

Example	X	Y	$\#\mathcal{D}_{\text{train}}$	$\#\mathcal{D}_{\text{test}}$
3a	DEWP	O3	305572	101808
3b	WSPM	PM10	311146	103146

1st, 2013 to February 28th, 2017, and the 420768 observed values of each variable. Our goal is to fit the relationship between the main air pollutants and the relevant meteorological variables in the dataset.

From the data set, we select two pairs of air pollutants and meteorological variables as the response variable Y and the covariate X in model (1), and then we obtain two examples listed in Table 3. In Table 3, the terms DEWP, O3, WSPM and PM10 are abbreviations to dew point temperature (degree Celsius), O3 concentration ($\mu\text{g}/\text{m}^3$), wind speed (m/s) and PM10 concentration ($\mu\text{g}/\text{m}^3$), respectively.

To test the performance of the involved estimators, we drop the data that suffer from data missing and then divide the remainder data set into training set $\mathcal{D}_{\text{train}}$ and testing set $\mathcal{D}_{\text{test}}$. The set $\mathcal{D}_{\text{train}}$ consists of the data collected before March 1st, 2017, which are used to obtain the involved estimators. And the set $\mathcal{D}_{\text{test}}$ consists of the data collected after March 1st, 2017, which are used to test the involved estimators. The number of samples in $\mathcal{D}_{\text{train}}$ and $\mathcal{D}_{\text{test}}$ are listed in Table 4. To model the data stream, the data in $\mathcal{D}_{\text{train}}$ are revealed to the algorithm chronologically by chunks. According to the reality, we consider three different sizes of data chunks, where the data chunks are respectively formed by monthly, daily and hourly data in $\mathcal{D}_{\text{train}}$. To simulate the data corrections, we randomly select 5% samples (X_{ti}, Y_{ti}) from $\mathcal{D}_{\text{train}}$ and replace by $(X_{ti}, Y_{ti} + \eta_{ti})$, where η_{ti} are random numbers sampled from $N(0, \gamma^2 \hat{\sigma}^2)$ with $\hat{\sigma}$ the sample standard deviation of all Y_{ti} in $\mathcal{D}_{\text{train}}$.

For an estimator $\hat{g}(\cdot)$, its prediction accuracy is described by the root mean square error (RMSE) and the mean absolute error (MAE) on $\mathcal{D}_{\text{test}}$,

Table 4 The performance of estimators in fitting the data in the test set.

Example	γ	Data chunk levels	RMSE					MAE					
			\hat{m}_{bctm}	\hat{m}_{bctm}^*	\hat{m}_{bctm}^a	\hat{m}_{ntm}	\hat{m}_{nw}	\hat{m}_{bctm}	\hat{m}_{bctm}^*	\hat{m}_{bctm}^a	\hat{m}_{ntm}	\hat{m}_{nw}	
3a	0	Monthly	52.76677	52.77872	58.6693	53.61709	52.73482	40.28165	40.28661	42.29119	39.37884	40.54636	
		Daily	52.7082		65.28168	53.58219	52.64124	40.21613		45.07949	39.33414	40.46221	
		Hourly	52.69518		66.34659	53.54145	52.62801	40.20903		45.71091	39.30018	40.44384	
	200	Monthly	52.69007	52.73489	59.25697	53.6353	53.72931	40.8557	40.85224	42.36754	39.48367	42.26342	
		Daily	53.69169		65.39519	53.68864	53.67594	39.49466		45.26383	39.50784	40.54927	
		Hourly	52.8724		66.04215	53.6895	52.99187	40.10549		45.66194	39.49896	41.14098	
	300	Monthly	52.95225	52.9567	60.29439	53.69834	59.87844	40.96671	40.96929	43.39408	39.54018	42.42427	
		Daily	52.68371		66.64786	53.43147	55.48577	40.48201		45.92729	39.30806	43.07228	
		Hourly	55.25677		65.7168	53.6054	55.82718	44.41829		45.38226	39.48709	45.48346	
	500	Monthly	52.91115	52.91262	62.37687	53.59242	62.33681	41.00842	41.01051	44.33797	39.44115	43.40568	
		Daily	52.89287		96.74874	53.50994	55.48631	39.70204		63.44539	39.37509	42.44378	
		Hourly	54.10149		67.13018	53.55919	69.35807	39.2646		46.3392	39.39992	47.44568	
	3b	0	Monthly	91.38395	91.37405	95.18209	92.59383	91.42939	65.07803	65.04084	73.76033	62.50045	65.68535
			Daily	91.36178		106.1427	92.60719	91.41144	65.07932		88.91665	62.47347	65.65522
			Hourly	91.36137		126.5157	92.5812	91.42891	65.01998		111.9207	62.48859	65.68522
200		Monthly	91.35244	91.38479	95.50069	92.50853	91.71021	65.03844	65.31028	74.40362	62.54186	66.04368	
		Daily	93.11323		106.1581	92.56961	95.25753	62.51619		88.80122	62.558	64.91864	
		Hourly	92.17945		125.7656	92.53873	138.3714	68.06108		111.1167	62.58303	101.5362	
300		Monthly	93.14993	92.76423	94.17937	92.55509	138.3714	69.57595	68.48768	71.93381	62.57268	101.5362	
		Daily	92.27852		158.0106	92.57684	93.18936	62.75523		86.9397	62.59626	64.99413	
		Hourly	91.95882		172.4052	92.50875	98.86813	67.9056		107.3754	62.55404	75.97422	
500		Monthly	93.71550	93.57659	96.90465	92.50837	100.2169	62.12962	62.17538	76.69216	62.55527	70.08925	
		Daily	91.95389		153.4074	92.55708	96.75755	67.84169		81.48874	62.57731	64.51765	
		Hourly	92.39591		160.0886	92.53574	93.19995	62.61390		99.66012	62.52227	64.90633	

namely

$$\text{RMSE}(\hat{g}) = \sqrt{\frac{1}{n_{\text{test}}} \sum_{(X_i, Y_i) \in \mathcal{D}_{\text{test}}} (Y_i - \hat{g}(X_i))^2},$$

$$\text{MAE}(\hat{g}) = \frac{1}{n_{\text{test}}} \sum_{(X_i, Y_i) \in \mathcal{D}_{\text{test}}} |Y_i - \hat{g}(X_i)|,$$

where n_{test} is the number of observations in $\mathcal{D}_{\text{test}}$.

The RMSEs and MAEs of the involved estimators are reported in Table 4. From Table 4, we have the following findings:

- (i) In most cases, \tilde{r}_{bctm} is superior than \tilde{r}_{nw} in RMSE and MAE. Moreover, the advantage of \tilde{r}_{bctm} over \tilde{r}_{nw} is enlarged when γ is relatively large. This suggests that our BCTM is more robust than the NW estimator.
- (ii) In all cases, the performance of \tilde{r}_{bctm} is insensitive to the data chunk levels and is very close to that of the oracle estimator $\tilde{r}_{\text{bctm}}^*$. On the contrary, the performance of $\tilde{r}_{\text{bctm}}^a$ deteriorates significantly when the data chunks becomes

smaller. This shows that the data partitioning has little influence on our online-updating strategy, and our online-updating estimator enjoys the asymptotic properties as well as that of the oracle estimator obtained on the full data set.

- (iii) In most cases, \tilde{r}_{bctm} shows a smaller RMSEs than that of \tilde{r}_{ntm} , which indicates the necessity of our bias-correction technique based on weight selection. We should also remark that the MAE of \tilde{r}_{ntm} appears to be the smallest one among that of all the involved estimators. This is not surprising, since both of the BCTM and the NW estimator estimate the conditional mean $m(x)$, while \tilde{r}_{ntm} estimate the conditional α -trimmed mean $r(x; J_{m,0.5})$. Although $m(x)$ minimizes the RMSE, it generally does not minimize the MAE, unless the error distribution is asymmetric.

In summary, by comprehensively investigating the numerical results in various experiment conditions, we can conclude the desirable performance of our estimation method and algorithms.

Supplementary information. The supplementary material contains the relevant lemmas and proofs for the theoretical results.

Declarations

Funding. The research was supported by National Key R&D Program of China (2018YFA0703900) and NNSF project (11971265) of China.

Competing Interests. The authors have no competing interests to declare that are relevant to the content of this article.

References

- Ashfahani, A. and M. Pratama 2019. *Autonomous Deep Learning: Continual Learning Approach for Dynamic Environments*, pp. 666–674.
- Bednar, J. and T. Watt. 1984. Alpha-trimmed means and their relationship to median filters. *IEEE Transactions on Acoustics, Speech, and Signal Processing* 32(1): 145–153. <https://doi.org/10.1109/TASSP.1984.1164279> .
- Bickel, P.J. and E.L. Lehmann. 1975. Descriptive statistics for nonparametric models. II. Location. *Ann. Statist.* 3(5): 1045–1069 .
- Boente, G. and R. Fraiman. 1994. Local L -estimators for nonparametric regression under dependence. *J. Nonparametr. Statist.* 4(1): 91–101. <https://doi.org/10.1080/10485259408832603> .
- Bucak, S.S. and B. Günsel. 2009. Incremental subspace learning via non-negative matrix factorization. *Pattern Recognition* 42(5): 788–797. <https://doi.org/https://doi.org/10.1016/j.patcog.2008.09.002> .
- Burden, R.L., J.D. Faires, and A.M. Burden. 2015. *Numerical analysis*. Cengage learning.
- Chen, X., W. Liu, and Y. Zhang. 2019. Quantile regression under memory constraint. *Ann. Statist.* 47(6): 3244–3273. <https://doi.org/10.1214/18-AOS1777> .
- Das, M., M. Pratama, S. Savitri, and J. Zhang 2019. Muse-rnn: A multilayer self-evolving recurrent neural network for data stream classification. In *2019 IEEE International Conference on Data Mining (ICDM)*, pp. 110–119.
- Fan, J. and I. Gijbels. 1992. Variable bandwidth and local linear regression smoothers. *Ann. Statist.* 20(4): 2008–2036. <https://doi.org/10.1214/aos/1176348900> .
- Gautschi, W. 2012. *Numerical analysis*. Springer Science & Business Media, LLC, New York.
- Gutenbrunner, C. and J. Jurečková. 1992. Regression rank scores and regression quantiles. *Ann. Statist.* 20(1): 305–330. <https://doi.org/10.1214/aos/1176348524> .
- Jiang, R., W.M. Qian, and Z.G. Zhou. 2016. Single-index composite quantile regression with heteroscedasticity and general error distributions. *Statist. Papers* 57(1): 185–203. <https://doi.org/10.1007/s00362-014-0646-y> .
- Kai, B., R. Li, and H. Zou. 2010. Local composite quantile regression smoothing: an efficient and safe alternative to local polynomial regression. *J. R. Stat. Soc. Ser. B Stat. Methodol.* 72(1): 49–69. <https://doi.org/10.1111/j.1467-9868.2009.00725.x> .
- Koenker, R. 2005. *Quantile regression*, Volume 38 of *Econometric Society Monographs*. Cambridge University Press, Cambridge.
- Koenker, R. and S. Portnoy. 1987. L -estimation for linear models. *J. Amer. Statist. Assoc.* 82(399): 851–857 .
- Koenker, R. and Q.S. Zhao. 1994. L -estimation for linear heteroscedastic models. *J. Nonparametr. Statist.* 3(3-4): 223–235. <https://doi.org/10.1080/10485259408832584> .
- Lin, L., F. Li, K. Wang, and L. Zhu. 2019. Composite estimation: an asymptotically weighted least squares approach. *Statist. Sinica* 29(3): 1367–1393 .
- Lin, L., W. Li, and J. Lu. 2020. Unified rules of renewable weighted sums for various

- online updating estimations. arXiv:2008.08824 [stat.ME].
- Luo, L. and P.X.K. Song. 2020. Renewable estimation and incremental inference in generalized linear models with streaming data sets. *J. R. Stat. Soc. Ser. B. Stat. Methodol.* 82(1): 69–97 .
- Moroshko, E., N. Vaitis, and K. Crammer. 2015. Second-order non-stationary online learning for regression. *J. Mach. Learn. Res.* 16: 1481–1517 .
- Nion, D. and N.D. Sidiropoulos. 2009. Adaptive algorithms to track the parafac decomposition of a third-order tensor. *IEEE Transactions on Signal Processing* 57(6): 2299 – 2310. <https://doi.org/10.1109/TSP.2009.2016885> .
- Portnoy, S. and R. Koenker. 1989. Adaptive L -estimation for linear models. *Ann. Statist.* 17(1): 362–381. <https://doi.org/10.1214/aos/1176347022> .
- Pratama, M., C. Za'in, A. Ashfahani, Y.S. Ong, and W. Ding 2019. Automatic construction of multi-layer perceptron network from streaming examples. In *Proceedings of the 28th ACM International Conference on Information and Knowledge Management, CIKM '19*, New York, NY, USA, pp. 1171–1180. Association for Computing Machinery.
- Robbins, H. and S. Monro. 1951. A Stochastic Approximation Method. *The Annals of Mathematical Statistics* 22(3): 400 – 407. <https://doi.org/10.1214/aoms/1177729586> .
- Sauer, T. 2011. *Numerical analysis*. Addison-Wesley Publishing Company.
- Schifano, E.D., J. Wu, C. Wang, J. Yan, and M.H. Chen. 2016. Online updating of statistical inference in the big data setting. *Technometrics* 58(3): 393–403. <https://doi.org/10.1080/00401706.2016.1142900> .
- Serfling, R.J. 1980. *Approximation theorems of mathematical statistics*. Wiley Series in Probability and Mathematical Statistics. John Wiley & Sons, Inc., New York.
- Stigler, S.M. 1977. Do robust estimators work with real data? *Ann. Statist.* 5(6): 1055–1098 .
- Sun, J., Y. Gai, and L. Lin. 2013. Weighted local linear composite quantile estimation for the case of general error distributions. *J. Statist. Plann. Inference* 143(6): 1049–1063. <https://doi.org/10.1016/j.jspi.2013.01.002> .
- Toulis, P., J. Rennie, and E. Airoldi. 2014. Statistical analysis of stochastic gradient methods for generalized linear models. *International Conference on Machine Learning* 32(1): 667 – 675 .
- Wang, K., H. Wang, and S. Li. 2022. Renewable quantile regression for streaming datasets. *Knowledge-Based Systems* 235: 107675. <https://doi.org/https://doi.org/10.1016/j.knosys.2021.107675> .
- Zou, H. and M. Yuan. 2008. Composite quantile regression and the oracle model selection theory. *Ann. Statist.* 36(3): 1108–1126. <https://doi.org/10.1214/07-AOS507> .