

On the critical regularity of nonlinearities for semilinear classical wave equations

Wenhui Chen^{*1} and Michael Reissig^{†2}

¹School of Mathematics and Information Science, Guangzhou University, 510006 Guangzhou, China

²Institute of Applied Analysis, Faculty of Mathematics and Computer Science, Technical University Bergakademie Freiberg, 09596 Freiberg, Germany

Abstract

In this paper, we consider the Cauchy problem for semilinear classical wave equations

$$u_{tt} - \Delta u = |u|^{p_S(n)} \mu(|u|)$$

with the Strauss exponent $p_S(n)$ and a modulus of continuity $\mu = \mu(\tau)$, which provides an additional regularity of nonlinearities in $u = 0$ comparing with the power nonlinearity $|u|^{p_S(n)}$. We obtain a sharp condition on μ as a threshold between global (in time) existence of small data radial solutions by deriving polynomial-logarithmic type weighted $L_t^\infty L_r^\infty$ estimates, and blow-up of solutions in finite time even for small data by applying iteration methods with slicing procedure. These results imply the critical regularity of source nonlinearities for semilinear classical wave equations.

Keywords: semilinear wave equation, critical regularity of nonlinearities, the Strauss exponent, modulus of continuity, global existence of solution, blow-up of solution.

AMS Classification (2020) 35L71, 35L05, 35B33, 35A01, 35B44

1 Introduction

In the last forty years, the Cauchy problem for semilinear classical wave equations with power nonlinearity, namely,

$$\begin{cases} u_{tt} - \Delta u = |u|^p, & x \in \mathbb{R}^n, t > 0, \\ u(0, x) = u_0(x), \quad u_t(0, x) = u_1(x), & x \in \mathbb{R}^n, \end{cases} \quad (1.1)$$

with $p > 1$, has been deeply studied by the mathematical community. For example, the questions on global (in time) existence of solutions, blow-up of solutions in finite time and sharp lifespan estimates of solutions were of interest. In particular, the critical exponent for the semilinear Cauchy problem (1.1) is given by the so-called Strauss exponent $p_S(n)$, which was proposed by Walter A. Strauss in

^{*}Wenhui Chen (wenhui.chen.math@gmail.com)

[†]Michael Reissig (reissig@math.tu-freiberg.de)

[23]. Nowadays, the correctness of the Strauss exponent is well-known. The Strauss exponent $p_S(n)$ is the positive root of the quadratic equation

$$(n-1)p^2 - (n+1)p - 2 = 0 \tag{1.2}$$

for $n \geq 2$, that is,

$$p_S(n) := \frac{n+1 + \sqrt{n^2 + 10n - 7}}{2(n-1)} \quad \text{when } n \geq 2,$$

and we put $p_S(1) := +\infty$. On one hand, for blow-up results when $1 < p \leq p_S(n)$, we refer interested readers to the classical papers [12, 13, 8, 22, 21, 11, 26, 27] and the new proofs proposed in [25, 10]. On the other hand, concerning global (in time) existence results when $p > p_S(n)$, we refer to [12, 9, 19, 7, 24] and references therein. Summarizing these known results, in the scale of power nonlinearities $\{|u|^p\}_{p>1}$, the critical exponent $p = p_S(n)$ for semilinear classical wave equations (1.1) has been found, to be the threshold condition between global (in time) existence of solutions and blow-up of local (in time) solutions with small initial data.

Nevertheless, to determine the critical nonlinearity or the critical regularity of nonlinearities, it seems too rough to restrict the consideration of semilinear wave equations (1.1) to the scale of power nonlinearities $\{|u|^p\}_{p>1}$. The question of the critical regularity of nonlinearities for semilinear classical wave equations is completely open as far as the authors know. For this reason, our contribution of this paper is to give an answer to this question for a class of modulus of continuity. Furthermore, we will suggest a candidate for the general critical nonlinearity via our derived results.

In this manuscript, we consider the following Cauchy problem for semilinear classical wave equations with modulus of continuity in the nonlinearity:

$$\begin{cases} u_{tt} - \Delta u = |u|^{p_S(n)} \mu(|u|), & x \in \mathbb{R}^n, t > 0, \\ u(0, x) = u_0(x), \quad u_t(0, x) = u_1(x), & x \in \mathbb{R}^n, \end{cases} \tag{1.3}$$

for $n \geq 2$ (due to $p_S(1) = +\infty$), where $p_S(n)$ stands for the Strauss exponent, and $\mu = \mu(\tau)$ is a modulus of continuity. To be specific, a function $\mu : [0, +\infty) \rightarrow [0, +\infty)$ is called a modulus of continuity, if μ is a continuous, concave and increasing function satisfying $\mu(0) = 0$. The additional term of modulus of continuity provides an additional regularity of the nonlinear term in $u = 0$ in the Cauchy problem (1.3) comparing with the power nonlinearity $|u|^{p_S(n)}$. Note that the critical nonlinearity has been studied recently in semilinear classical damped wave equations [6] and the corresponding weakly coupled systems [5]. Nevertheless, due to the lack of crucial damping mechanisms, the study of the semilinear Cauchy problem (1.3) is not a generalization of those of [6, 5], e.g. the usual test function methods and the Matsumura type $L^p - L^q$ estimates do not work for our model (1.3).

The main purpose of this paper is to derive the critical regularity of nonlinearities for the semilinear Cauchy problem (1.3), namely, the threshold condition for modulus of continuity μ . First of all, by applying iteration methods with slicing procedure (motivated by [1, 25]) for a new weighted functional, which contains a local (in time) solution and a modulus of continuity, under some conditions

of initial data, we will prove a blow-up result in Section 3 when

$$\lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(n)}} \in [c_l, +\infty]$$

with a suitably large constant $c_l \gg 1$. Next, we will study the three dimensional Cauchy problem (1.3) with modulus of continuity satisfying

$$\lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(3)}} = 0$$

in the radial case. By developing polynomial-logarithmic type weighted $L_t^\infty L_r^\infty$ estimates via refined analysis in the (t, r) -plane, we will demonstrate global (in time) existence of small data radial solution in Section 4. The typical example is that for a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ which satisfies

$$\mu(\tau) = c_l \left(\log \frac{1}{\tau} \right)^{-\gamma} \quad \text{with } c_l \gg 1, \quad \text{when } \tau \in (0, \tau_0]. \quad (1.4)$$

Our results of this paper ensure that the critical regularity of nonlinearities $|u|^{p_S(3)} \mu(|u|)$ in semi-linear classical wave equations with the modulus of continuity satisfying (1.4) is described by the threshold $\gamma = \frac{1}{p_S(3)}$. Namely, global (in time) existence of solutions holds when $\gamma > \frac{1}{p_S(3)}$ and blow-up of solutions holds when $0 < \gamma \leq \frac{1}{p_S(3)}$. Other examples will be shown in Section 2. To end this paper, we will give a conjecture for general conditions of the critical nonlinearity for the semilinear Cauchy problem (1.3) as final remarks in Section 5.

Notation: Firstly, c and C denote some positive constants, which may be changed from line to line. We write $f \lesssim g$ if there exists a positive constant C such that $f \leq Cg$. The relation $f \simeq g$ holds if and only if $g \lesssim f \lesssim g$. Moreover, $B_R(0)$ denotes the ball around the origin with radius R . We denote $\langle y \rangle := 3 + |y|$ for any $y \in \mathbb{R}$ throughout this manuscript.

2 Main results

Before stating our blow-up result, we firstly introduce the notion of energy solutions to the Cauchy problem (1.3) that we are going to use later.

Definition 2.1. Let $u_0 \in H^1$ and $u_1 \in L^2$. We say that $u = u(t, x)$ is an energy solution to the semilinear Cauchy problem (1.3) on $[0, T)$ if

$$u \in \mathcal{C}([0, T), H^1) \cap \mathcal{C}^1([0, T), L^2) \quad \text{such that } |u|^{p_S(n)} \mu(|u|) \in L^1_{\text{loc}}([0, T) \times \mathbb{R}^n)$$

fulfills the next integral relation:

$$\begin{aligned} & \int_{\mathbb{R}^n} u_t(t, x) \phi(t, x) dx + \int_0^t \int_{\mathbb{R}^n} (\nabla u(s, x) \cdot \nabla \phi(s, x) - u_s(s, x) \phi_s(s, x)) dx ds \\ & = \int_{\mathbb{R}^n} u_1(x) \phi(0, x) dx + \int_0^t \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) \phi(s, x) dx ds \end{aligned} \quad (2.1)$$

for any $\phi \in \mathcal{C}_0^\infty([0, T) \times \mathbb{R}^n)$ and any $t \in [0, T)$.

Theorem 2.1. *Let us consider a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ satisfying*

$$\lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(n)}} =: C_{\text{Str}} \in [c_l, +\infty] \quad (2.2)$$

with a suitably large constant $c_l \gg 1$. We assume that the function $g : \tau \in \mathbb{R} \rightarrow g(\tau) := \tau[\mu(|\tau|)]^{\frac{1}{p_S(n)}}$ is convex on \mathbb{R} . Let $u_0 \in H^1$ and $u_1 \in L^2$ be non-negative, non-trivial and compactly supported functions with supports contained in $B_R(0)$ for some $R > 0$. Let

$$u \in \mathcal{C}([0, T], H^1) \cap \mathcal{C}^1([0, T], L^2) \quad \text{such that} \quad |u|^{p_S(n)} \mu(|u|) \in L^1_{\text{loc}}([0, T] \times \mathbb{R}^n)$$

be an energy solution to the semilinear Cauchy problem (1.3) on $[0, T]$ for $n \geq 2$ according to Definition 2.1. Then, the energy solution u blows up in finite time.

Example 2.1. *The hypothesis (2.2) and the supposed property for the function $g = g(\tau)$ of Theorem 2.1 hold for the following functions $\mu = \mu(\tau)$ on a small interval $[0, \tau_0]$ with $0 < \tau_0 \ll 1$:*

- $\mu(0) = 0$ and $\mu(\tau) = (\log \frac{1}{\tau})^{-\gamma}$ with $0 < \gamma < \frac{1}{p_S(n)}$;
- $\mu(0) = 0$ and $\mu(\tau) = c_l (\log \frac{1}{\tau})^{-\frac{1}{p_S(n)}}$ with $c_l \gg 1$;
- $\mu(0) = 0$ and $\mu(\tau) = (\log \frac{1}{\tau})^{-\frac{1}{p_S(n)}} (\log^k \frac{1}{\tau})^\gamma$ with $\gamma > 0$ and $k \geq 2$, here \log^k denotes the iterated logarithm (k times application).

Note that the modulus of continuity in the last cases can be continued to $\tau \in [0, +\infty)$ in such a way that $\mu = \mu(\tau)$ is a continuous, concave and increasing function, for example, a smooth and concave continuation function with $\mu(0) = 0$ such that

$$\mu(\tau) = \begin{cases} c_l (\log \frac{1}{\tau})^{-\gamma} & \text{when } \tau \in (0, \frac{1}{3}], \\ \text{strictly increasing} & \text{when } \tau \in [\frac{1}{3}, 3], \\ c_l (\log \tau)^\gamma & \text{when } \tau \in [3, +\infty), \end{cases}$$

with a suitably large constant $c_l \gg 1$ and $0 < \gamma \leq \frac{1}{p_S(n)}$. A counterexample for the condition (2.2) in Theorem 2.1 is $\mu(\tau) = \tau^\nu$ with $\nu > 0$. This is not surprising due to the global (in time) existence results [12, 9, 19, 7, 24] for the semilinear classical wave equations (1.1) with power nonlinearity $|u|^{p_S(n)+\nu}$.

Remark 2.1. *Concerning the semilinear wave equation (1.1) with the critical exponent $p = p_S(n)$, by taking the additional term of modulus of continuity $\mu(|u|)$ fulfilling (2.2) in the nonlinearity, Theorem 2.1 shows that the energy solutions still blow up in finite time.*

To indicate the sharpness of the condition (2.2), we next study the three dimensional semilinear Cauchy problem (1.3) with a modulus of continuity satisfying (2.4). Before showing our result, taking $r = |x|$, let us introduce a definition of radial solutions to our aim model in three dimensions, namely,

$$\begin{cases} u_{tt} - u_{rr} - \frac{2}{r}u_r = |u|^{p_S(3)}\mu(|u|), & r > 0, t > 0, \\ u(0, r) = u_0(r), \quad u_t(0, r) = u_1(r), & r > 0. \end{cases} \quad (2.3)$$

Definition 2.2. *The function $u = u(t, r)$ is called a global (in time) mild solution to the semilinear Cauchy problem (2.3) if $u \in \mathcal{C}([0, +\infty) \times \mathbb{R}_+)$ carrying its initial data, and satisfying the following integral equality:*

$$u(t, r) = \mathfrak{E}_0(t, r) *_{(r)} u_0(r) + \mathfrak{E}_1(t, r) *_{(r)} u_1(r) + \int_0^t \mathfrak{E}_1(t-s, r) *_{(r)} \left[|u(s, r)|^{p_S(3)} \mu(|u(s, r)|) \right] ds.$$

In the above, $\mathfrak{E}_0 = \mathfrak{E}_0(t, r)$ and $\mathfrak{E}_1 = \mathfrak{E}_1(t, r)$ are the fundamental solutions to the corresponding linear Cauchy problem to (2.3) with vanishing right-hand side.

We turn to the global (in time) existence of radial solutions in the subsequent theorem.

Theorem 2.2. *Let us consider a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ satisfying*

$$\lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(3)}} = 0, \quad (2.4)$$

furthermore,

$$\mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(3)}} \lesssim \left(\log \log \frac{1}{\tau} \right)^{-1} \quad \text{when } \tau \in (0, \tau_0]. \quad (2.5)$$

Let $\bar{u}_0 \in \mathcal{C}_0^2$ and $\bar{u}_1 \in \mathcal{C}_0^1$ be radial. Then, there exists $0 < \varepsilon_0 \ll 1$ such that for any $\varepsilon \in (0, \varepsilon_0)$, if $u_0 = \varepsilon \bar{u}_0$ and $u_1 = \varepsilon \bar{u}_1$, then the semilinear Cauchy problem (1.3) for $n = 3$ admits a uniquely determined global (in time) small data radial solution in the sense of Definition 2.2 such that $u \in \mathcal{C}([0, +\infty) \times \mathbb{R}^3)$.

Remark 2.2. *Since the assumption (2.5) implies (2.4) as $\tau \rightarrow 0^+$, one may drop the condition (2.4) directly. Nevertheless, to emphasize the importance of the essential condition (2.4) for the global (in time) existence result, we retain this condition. We conjecture that the logarithmic type decay condition (2.5) is a technical restriction.*

Example 2.2. *The hypotheses (2.4) and (2.5) hold for the following functions $\mu = \mu(\tau)$ on a small interval $[0, \tau_0]$ with $0 < \tau_0 \ll 1$:*

- $\mu(\tau) = \tau^\gamma$ with $\gamma \in (0, 1]$;
- $\mu(\tau) = [\log(1 + \tau)]^\gamma$ with $\gamma \in (0, 1]$;
- $\mu(0) = 0$ and $\mu(\tau) = (\log \frac{1}{\tau})^{-\gamma}$ with $\gamma > \frac{1}{p_S(3)}$;
- $\mu(0) = 0$ and $\mu(\tau) = (\log \frac{1}{\tau})^{-\frac{1}{p_S(3)}} (\log \log \frac{1}{\tau})^\gamma$ with $\gamma \leq -1$;
- $\mu(0) = 0$ and $\mu(\tau) = (\log \frac{1}{\tau})^{-\frac{1}{p_S(3)}} (\log \log \frac{1}{\tau})^{-1} (\log^k \frac{1}{\tau})^\gamma$ with $\gamma < 0$ and $k \geq 3$.

Remark 2.3. *By assuming additionally decay properties for initial data with respect to the radial behavior, we also can derive some pointwise decay estimates for the global (in time) radial solutions. More details will be given in Corollary 4.1 and in our proof in Section 4.*

Remark 2.4. *The key tool to prove Theorem 2.2 is to derive polynomial-logarithmic type weighted $L_t^\infty L_r^\infty$ estimates. Concerning higher dimensional cases, one may recall more general representations of radial solutions to the linear wave equation associated with polynomial type weighted $L_t^\infty L_r^\infty$ estimates (see [14, 16] for odd dimensions and [17] for even dimensions). Furthermore, by setting suitable logarithmic factors to be the additional part of weighted functions, one may derive some weighted $L_t^\infty L_r^\infty$ estimates to get a global (in time) existence result for higher dimensions n , nevertheless, this purpose is beyond the scope of this manuscript.*

Remark 2.5. *Let us summarize the given results in Theorems 2.1 and 2.2. We recall the typical modulus of continuity proposed in Examples 2.1 and 2.2. In the consideration of semilinear wave equations (1.3) for $n = 3$ with the modulus of continuity satisfying (1.4), we may conclude that the critical regularity of nonlinearities is described by the threshold $\gamma = \frac{1}{p_S(3)}$. This is one of the main contributions of this paper and it answers the open question proposed in the introduction.*

Remark 2.6. *Motivated by the global (in time) existence condition (2.4) as well as the blow-up condition (2.2), one may introduce the following possible quantity:*

$$0 \leq C_{\text{Str}} := \lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(n)}}, \quad (2.6)$$

to describe the critical regularity of nonlinearities for semilinear wave equations (1.3). The blow-up phenomenon occurs when $C_{\text{Str}} \in [c_l, +\infty]$ in Theorem 2.1 and the global (in time) existence result holds when $C_{\text{Str}} = 0$ in Theorem 2.2. Explanations more in detail will be provided in Section 5.

3 Blow-up of energy solutions

This section is organized as follows. In Subsection 3.1, we will introduce a test function, and derive sharp estimates for it in $L^1(B_{R+t}(0))$. Then, thanks to some estimates for auxiliary functions, the iteration frame and lower bound estimates for a time-dependent functional will be established in Subsections 3.2 and 3.3, respectively. Finally, in Subsection 3.4, we will demonstrate the lower bound of this functional blows up in finite time by using iteration methods with slicing procedure.

3.1 Preliminaries and auxiliary functions

Let us set a non-negative parameter

$$q := \frac{n-1}{2} - \frac{1}{p_S(n)} \quad \text{for } n \geq 2. \quad (3.1)$$

Next, we recall the following pair of auxiliary functions from [25]:

$$\xi_q(t, x) := \int_0^{\lambda_0} e^{-\lambda(R+t)} \cosh(\lambda t) \Phi(\lambda x) \lambda^q d\lambda, \quad (3.2)$$

$$\eta_q(t, s, x) := \int_0^{\lambda_0} e^{-\lambda(R+t)} \frac{\sinh(\lambda(t-s))}{\lambda(t-s)} \Phi(\lambda x) \lambda^q d\lambda, \quad (3.3)$$

where λ_0 is a fixed positive parameter and the test function $\Phi = \Phi(x)$ defined by

$$\Phi : x \in \mathbb{R}^n \rightarrow \Phi(x) := \int_{\mathbb{S}^{n-1}} e^{x \cdot \omega} d\sigma_\omega \quad \text{for } n \geq 2,$$

was introduced by [26]. The test function Φ is positive, smooth, and satisfies $\Delta\Phi = \Phi$ with

$$\Phi(x) \simeq |x|^{-\frac{n-1}{2}} e^{|x|} \quad \text{as } |x| \rightarrow +\infty. \quad (3.4)$$

By introducing the function with separate variables

$$\Psi(t, x) := e^{-t} \Phi(x),$$

it is the solution to the free wave equation $\Psi_{tt} - \Delta\Psi = 0$ and has the next property.

Lemma 3.1. *The test function fulfills the sharp estimates*

$$\int_{B_{R+t}(0)} \Psi(t, x) dx \simeq (R+t)^{\frac{n-1}{2}}$$

for any $t \geq 0$ and $n \geq 2$.

Proof. By using integration by parts, we arrive at

$$e^{-t} \int_0^{R+t} \zeta^{\frac{n-1}{2}} e^\zeta d\zeta = (R+t)^{\frac{n-1}{2}} e^R - \frac{n-1}{2} e^{-t} \int_0^{R+t} \zeta^{\frac{n-3}{2}} e^\zeta d\zeta \lesssim (R+t)^{\frac{n-1}{2}}.$$

Shrinking the domain of integration to $[t, R+t]$, one notices

$$e^{-t} \int_0^{R+t} \zeta^{\frac{n-1}{2}} e^\zeta d\zeta \geq \int_t^{R+t} \zeta^{\frac{n-1}{2}} d\zeta = \frac{2}{n+1} \left((R+t)^{\frac{n+1}{2}} - t^{\frac{n+1}{2}} \right) \gtrsim (R+t)^{\frac{n-1}{2}}.$$

Therefore, the previous sharp estimates imply

$$\int_{B_{R+t}(0)} \Psi(t, x) dx \simeq \int_{B_{R+t}(0)} |x|^{-\frac{n-1}{2}} e^{|x|-t} dx \simeq e^{-t} \int_0^{R+t} \zeta^{\frac{n-1}{2}} e^\zeta d\zeta \simeq (R+t)^{\frac{n-1}{2}}$$

because of (3.4). The proof is completed. \square

Additionally, some useful estimates of ξ_q and η_q are stated in the following lemma, whose proof can be found in [25, Lemma 3.1]. Note that our setting of q fulfills all assumptions in Lemma 3.2. Moreover, we recall the notation $\langle y \rangle = 3 + |y|$.

Lemma 3.2. *There exists $\lambda_0 > 0$ such that the following properties hold for $n \geq 2$:*

(i) *if $q > -1$, $|x| \leq R$ and $t \geq 0$, then*

$$\begin{aligned} \xi_q(t, x) &\geq A_0, \\ \eta_q(t, 0, x) &\geq B_0 \langle t \rangle^{-1}; \end{aligned}$$

(ii) *if $q > -1$, $|x| \leq R + s$ and $t > s \geq 0$, then*

$$\eta_q(t, s, x) \geq B_1 \langle t \rangle^{-1} \langle s \rangle^{-q};$$

(iii) if $q > \frac{n-3}{2}$, $|x| \leq R + t$ and $t > 0$, then

$$\eta_q(t, t, x) \leq B_2 \langle t \rangle^{-\frac{n-1}{2}} \langle t - |x| \rangle^{\frac{n-3}{2} - q}.$$

Here, A_0 and B_k , with $k = 0, 1, 2$, are positive constants depending only on λ_0 , q and R .

To end this subsection, we include the following generalized version of Jensen's inequality [20], whose proof also has been shown in [6, Lemma 8].

Lemma 3.3. *Let $g = g(\tau)$ be a convex function on \mathbb{R} . Let $\alpha = \alpha(x)$ be defined and non-negative almost everywhere on Ω , such that α is positive in a set of positive measure. Then, it holds*

$$g\left(\frac{\int_{\Omega} v(x)\alpha(x)dx}{\int_{\Omega} \alpha(x)dx}\right) \leq \frac{\int_{\Omega} g(v(x))\alpha(x)dx}{\int_{\Omega} \alpha(x)dx}$$

for all non-negative functions $v = v(x)$ provided that all the integral terms are meaningful.

3.2 Construction of an iteration frame

In order to prove Theorem 2.1, we are going to use an iteration argument to derive lower bound estimates for the weighted space average of a local (in time) solution containing modulus of continuity. For this reason, we first derive a nonlinear integral inequality to get an iteration frame.

Proposition 3.1. *Let $u_0 \in H^1$ and $u_1 \in L^2$ be non-negative, non-trivial and compactly supported functions with supports contained in $B_R(0)$ for some $R > 0$. Let u be an energy solution to the semilinear Cauchy problem (1.3) on $[0, T)$ according to Definition 2.1. Then, the following integral identity holds:*

$$\begin{aligned} \int_{\mathbb{R}^n} u(t, x)\eta_q(t, t, x)dx &= \int_{\mathbb{R}^n} u_0(x)\xi_q(t, x)dx + t \int_{\mathbb{R}^n} u_1(x)\eta_q(t, 0, x)dx \\ &\quad + \int_0^t (t-s) \int_{\mathbb{R}^n} |u(s, x)|^{p_s(n)} \mu(|u(s, x)|) \eta_q(t, s, x) dx ds \end{aligned} \quad (3.5)$$

for any $t \in (0, T)$, where ξ_q and η_q are defined in (3.2) and (3.3), respectively.

Proof. From finite propagation speed for solutions of wave equations, $u(t, \cdot)$ has compact support contained in $B_{R+t}(0)$ for any $t \geq 0$. Therefore, we may employ (2.1) for a non-compactly supported test function. We now define the test function

$$\psi = \psi(s, x) := y(t, s; \lambda)\Phi(\lambda x) \quad \text{with} \quad y(t, s; \lambda) := \frac{\sinh(\lambda(t-s))}{\lambda}.$$

As Φ is an eigenfunction of the Laplacian and $y(t, s; \lambda)$ solves $(\partial_s^2 - \lambda^2)y(t, s; \lambda) = 0$ with the end-points $y(t, t; \lambda) = 0$ and $y_s(t, t; \lambda) = -1$, the function ψ solves the free wave equation $\psi_{ss} - \Delta\psi = 0$ and satisfies

$$\begin{aligned} \psi(t, x) &= 0, & \psi(0, x) &= \lambda^{-1} \sinh(\lambda t)\Phi(\lambda x), \\ \psi_s(t, x) &= -\Phi(\lambda x), & \psi_s(0, x) &= -\cosh(\lambda t)\Phi(\lambda x). \end{aligned}$$

Applying the test function ψ in (2.1) with an integration by parts once more, we may derive

$$\begin{aligned} \int_{\mathbb{R}^n} u(t, x) \Phi(\lambda x) dx &= \cosh(\lambda t) \int_{\mathbb{R}^n} u_0(x) \Phi(\lambda x) dx + t \frac{\sinh(\lambda t)}{\lambda t} \int_{\mathbb{R}^n} u_1(x) \Phi(\lambda x) dx \\ &\quad + \int_0^t (t-s) \frac{\sinh(\lambda(t-s))}{\lambda(t-s)} \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) \Phi(\lambda x) dx ds. \end{aligned}$$

Multiplying both sides of the last equality by $e^{-\lambda(R+t)} \lambda^q$, integrating the resultant with respect to λ over $[0, \lambda_0]$ and applying Tonelli's theorem, we complete the derivation of (3.5). \square

Hereafter until the end of this section, we shall assume that u_0, u_1 satisfy the assumptions from Theorem 2.1. Let u be an energy solution to the semilinear Cauchy problem (1.3) on $[0, T)$. Inspired by the modulus of continuity in its nonlinearity, let us introduce the time-dependent functional

$$\mathcal{U}(t) := \int_{\mathbb{R}^n} u(t, x) \left[\mu(|u(t, x)|) \right]^{\frac{1}{p_S(n)}} \eta_q(t, t, x) dx$$

with the parameter q defined in (3.1). Moreover, it follows immediately the non-negativity of the functional for any $t \geq 0$ by

$$\mathcal{U}(t) \geq \int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \inf_{x \in \mathbb{R}^n} \left[\mu(|u(t, x)|) \right]^{\frac{1}{p_S(n)}} \geq 0, \quad (3.6)$$

where we employed as a direct consequence $\int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \geq 0$ from (3.5), with the help of non-negative data and non-negative nonlinearity.

A further step is to derive some estimates involving $\mathcal{U}(t)$ both in the left- and right-hand sides, which will establish an iteration frame. According to (3.5) and non-negativity of initial data, we may claim

$$\int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \geq \int_0^t (t-s) \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) \eta_q(t, s, x) dx ds. \quad (3.7)$$

Using Hölder's inequality, we arrive at

$$\mathcal{U}(s) \leq \left(\int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) \eta_q(t, s, x) dx \right)^{\frac{1}{p_S(n)}} \left(\int_{B_{R+s}} \frac{[\eta_q(s, s, x)]^{p'_S(n)}}{[\eta_q(t, s, x)]^{\frac{p'_S(n)}{p_S(n)}}} dx \right)^{\frac{1}{p'_S(n)}}.$$

Remark that $p'_S(n)$ denotes Hölder's conjugate of $p_S(n)$. With the aid of the properties (ii) and (iii) in Lemma 3.2 (both $q > \frac{n-3}{2}$ and $q > -1$ are always fulfilled), we obtain

$$\begin{aligned} \int_{B_{R+s}} \frac{[\eta_q(s, s, x)]^{p'_S(n)}}{[\eta_q(t, s, x)]^{\frac{p'_S(n)}{p_S(n)}}} dx &\lesssim \langle t \rangle^{\frac{p'_S(n)}{p_S(n)}} \langle s \rangle^{\frac{p'_S(n)}{p_S(n)} q - \frac{n-1}{2} p'_S(n)} \int_{B_{R+s}} \langle s - |x| \rangle^{(\frac{n-3}{2} - q) p'_S(n)} dx \\ &\lesssim \langle t \rangle^{\frac{p'_S(n)}{p_S(n)}} \langle s \rangle^{\frac{q}{p_S(n)-1} - \frac{n-1}{2} p'_S(n)} \int_{B_{R+s}} \langle s - |x| \rangle^{-1} dx \\ &\lesssim \langle t \rangle^{\frac{p'_S(n)}{p_S(n)}} \langle s \rangle^{\frac{p'_S(n)}{p_S(n)}} \log \langle s \rangle, \end{aligned}$$

due to our choice of q in (3.1) and

$$\begin{aligned} \frac{q}{p_S(n) - 1} - \frac{n-1}{2} p'_S(n) + n - 1 &= \frac{p'_S(n)}{p_S(n)} \left(\frac{n-1}{2} - \frac{1}{p_S(n)} - \frac{n-1}{2} p_S(n) + (n-1)(p_S(n) - 1) \right) \\ &= \frac{p'_S(n)}{p_S(n)} \left[\frac{1}{p_S(n)} \left(\frac{n-1}{2} p_S^2(n) - \frac{n+1}{2} p_S(n) - 1 \right) + 1 \right] = \frac{p'_S(n)}{p_S(n)}. \end{aligned}$$

Note that $\log\langle s \rangle \geq \log 3 > 0$. Plugging the previous estimates in (3.7), it leads to

$$\begin{aligned} \int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx &\gtrsim \int_0^t (t-s) [\mathcal{U}(s)]^{p_S(n)} \left(\int_{B_{R+s}} \frac{[\eta_q(s, s, x)]^{p'_S(n)}}{[\eta_q(t, s, x)]^{\frac{p'_S(n)}{p_S(n)}}} dx \right)^{-\frac{p_S(n)}{p'_S(n)}} ds \\ &\gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log\langle s \rangle)^{p_S(n)-1}} ds. \end{aligned} \quad (3.8)$$

Moreover, thanks to the support condition of $u(t, \cdot)$, let us apply Lemma 3.3 with $\Omega = B_{R+t}(0)$, $\alpha = \eta_q(t, t, x)$, $v = u(t, x)$ and the convex function $g = g(\tau) = \tau[\mu(|\tau|)]^{\frac{1}{p_S(n)}}$ from our assumption in Theorem 2.1 to deduce

$$g \left(\frac{\int_{B_{R+t}(0)} u(t, x) \eta_q(t, t, x) dx}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \right) \leq \frac{\mathcal{U}(t)}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx},$$

in other words,

$$\int_{B_{R+t}(0)} u(t, x) \eta_q(t, t, x) dx \leq \int_{B_{R+t}(0)} \eta_q(t, t, x) dx g^{-1} \left(\frac{\mathcal{U}(t)}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \right). \quad (3.9)$$

Note that the function $g = g(\tau)$ is strictly monotonic from the monotonically increasing property of $\mu = \mu(|\tau|)$. After combining (3.8) and (3.9) it follows

$$\frac{1}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log\langle s \rangle)^{p_S(n)-1}} ds \lesssim g^{-1} \left(\frac{\mathcal{U}(t)}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \right).$$

The action of the mapping g on both sides of the last estimate yields

$$\begin{aligned} \mathcal{U}(t) &\gtrsim \int_{B_{R+t}(0)} \eta_q(t, t, x) dx g \left[\frac{1}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log\langle s \rangle)^{p_S(n)-1}} ds \right] \\ &\gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log\langle s \rangle)^{p_S(n)-1}} ds \\ &\quad \times \left[\mu \left(\left| \frac{1}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log\langle s \rangle)^{p_S(n)-1}} ds \right| \right) \right]^{\frac{1}{p_S(n)}}. \end{aligned}$$

Employing the non-negativity of $\mathcal{U}(t)$ stated in (3.6) as well as

$$\begin{aligned} \int_{B_{R+t}(0)} \eta_q(t, t, x) dx &\lesssim \langle t \rangle^{-\frac{n-1}{2}} \int_0^{R+t} \zeta^{n-1} \langle t-\zeta \rangle^{\frac{n-3}{2}-q} d\zeta \\ &\lesssim \langle t \rangle^{\frac{n-1}{2}} \int_0^{R+t} \langle t-\zeta \rangle^{-1+\frac{1}{p_S(n)}} d\zeta \leq C_1^{-1} \langle t \rangle^{\frac{n-1}{2}+\frac{1}{p_S(n)}} \end{aligned} \quad (3.10)$$

from Lemma 3.2, in conclusion, we obtain the iteration frame

$$\begin{aligned} \mathcal{U}(t) &\geq C_0 \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1}} ds \\ &\quad \times \left[\mu \left(C_1 \langle t \rangle^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1}} ds \right) \right]^{\frac{1}{p_S(n)}} \end{aligned} \quad (3.11)$$

for any $t \geq 0$, with positive constants C_0 and C_1 .

3.3 Derivation of a first lower bound estimate

By applying (3.7) and the property (ii) in Lemma 3.2, we may arrive at

$$\int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-q} \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) dx ds.$$

An application of Hölder's inequality gives

$$\begin{aligned} &\left| \int_{\mathbb{R}^n} u(s, x) \left[\mu(|u(s, x)|) \right]^{\frac{1}{p_S(n)}} \Psi(s, x) dx \right|^{p_S(n)} \\ &\leq \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) dx \left(\int_{B_{R+s}(0)} |\Psi(s, x)|^{p'_S(n)} dx \right)^{\frac{p_S(n)}{p'_S(n)}} \\ &\lesssim (R+s)^{(n-1)(\frac{p_S(n)}{2}-1)} \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) dx, \end{aligned}$$

where we employed the next inequality (e.g. the proof was shown in [26, 18] by using an integration by parts):

$$\int_{B_{R+s}(0)} |\Psi(s, x)|^{p'_S(n)} dx \lesssim (R+s)^{(n-1)(1-\frac{1}{2}p'_S(n))}.$$

That is to say

$$\begin{aligned} &\int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \\ &\gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \left| \int_{\mathbb{R}^n} u(s, x) \left[\mu(|u(s, x)|) \right]^{\frac{1}{p_S(n)}} \Psi(s, x) dx \right|^{p_S(n)} ds, \end{aligned} \quad (3.12)$$

due to the fact that

$$-q - (n-1) \left(\frac{p_S(n)}{2} - 1 \right) = -\frac{1}{p_S(n)} \left(\frac{n-1}{2} p_S^2(n) - \frac{n-1}{2} p_S(n) - 1 \right) = -1.$$

Let us apply Lemma 3.3 again with $g(\tau) = \tau [\mu(|\tau|)]^{\frac{1}{p_S(n)}}$ and $\alpha = \Psi(s, x)$ to arrive at

$$\int_{\mathbb{R}^n} u(s, x) \left[\mu(|u(s, x)|) \right]^{\frac{1}{p_S(n)}} \Psi(s, x) dx \geq \int_{B_{R+s}(0)} \Psi(s, x) dx g \left(\frac{\int_{B_{R+s}(0)} u(s, x) \Psi(s, x) dx}{\int_{B_{R+s}(0)} \Psi(s, x) dx} \right). \quad (3.13)$$

A further step of integration by parts to (2.1) shows

$$\begin{aligned} & \int_{\mathbb{R}^n} u_t(t, x) \phi(t, x) dx - \int_{\mathbb{R}^n} u(t, x) \phi_t(t, x) dx \\ &= - \int_{\mathbb{R}^n} u_0(x) \phi_t(0, x) dx + \int_{\mathbb{R}^n} u_1(x) \phi(0, x) dx - \int_0^t \int_{\mathbb{R}^n} u(s, x) (\phi_{ss}(s, x) - \Delta \phi(s, x)) dx ds \\ & \quad + \int_0^t \int_{\mathbb{R}^n} |u(s, x)|^{p_S(n)} \mu(|u(s, x)|) \phi(s, x) dx ds. \end{aligned}$$

Again, since u is supported in a forward cone, we may apply the definition of energy solutions even though the test function is not compactly supported. Taking as test function $\phi = \phi(t, x)$ the function $\Psi = \Psi(t, x)$, it holds

$$\frac{d}{dt} \int_{\mathbb{R}^n} u(t, x) \Psi(t, x) dx + 2 \int_{\mathbb{R}^n} u(t, x) \Psi(t, x) dx \geq \int_{\mathbb{R}^n} (u_0(x) + u_1(x)) \Phi(x) dx$$

due to the non-negativity of nonlinearity and $\Psi_{tt} = \Delta \Psi$. By multiplying e^{2t} on both sides of the last inequality, we can find

$$\int_{\mathbb{R}^n} u(t, x) \Psi(t, x) dx \geq \frac{1}{2} (1 + e^{-2t}) \int_{\mathbb{R}^n} u_0(x) \Phi(x) dx + \frac{1}{2} (1 - e^{-2t}) \int_{\mathbb{R}^n} u_1(x) \Phi(x) dx.$$

From our assumption on initial data, one gets

$$\int_{B_{R+s}(0)} u(s, x) \Psi(s, x) dx \gtrsim 1, \quad (3.14)$$

where the unexpressed multiplicative constant may depend on u_0 as well as u_1 . With the aid of Lemma 3.1 and (3.14), we are able to estimate from (3.13) and (3.12) that

$$\begin{aligned} & \int_{\mathbb{R}^n} u(t, x) \eta_q(t, t, x) dx \\ & \gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \left| \int_{B_{R+s}(0)} \Psi(s, x) dx \right|^{p_S(n)} \left| g \left(\frac{\int_{B_{R+s}(0)} u(s, x) \Psi(s, x) dx}{\int_{B_{R+s}(0)} \Psi(s, x) dx} \right) \right|^{p_S(n)} ds \\ & \gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} (R+s)^{\frac{(n-1)p_S(n)}{2}} \left| g \left(C_2 (R+s)^{-\frac{n-1}{2}} \right) \right|^{p_S(n)} ds \\ & \gtrsim \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \mu \left(C_2 (R+s)^{-\frac{n-1}{2}} \right) ds \end{aligned}$$

with a positive constant C_2 . According to (3.9), we derive

$$\langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \mu \left(C_2 (R+s)^{-\frac{n-1}{2}} \right) ds \lesssim \int_{B_{R+t}(0)} \eta_q(t, t, x) dx g^{-1} \left(\frac{\mathcal{U}(t)}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \right).$$

Furthermore, recalling the increasing property of μ and shrinking the interval of integration $[0, t]$ to $[1, t]$ for $t \geq 1$, one obtains

$$\begin{aligned} \mathcal{U}(t) &\gtrsim \int_{B_{R+t}(0)} \eta_q(t, t, x) dx g \left(\frac{1}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \mu \left(C_2(R+s)^{-\frac{n-1}{2}} \right) ds \right) \\ &\gtrsim \langle t \rangle^{-1} \mu \left(C_2(R+t)^{-\frac{n-1}{2}} \right) \int_1^t (t-s) \langle s \rangle^{-1} ds \\ &\quad \times \left[\mu \left(\frac{1}{\int_{B_{R+t}(0)} \eta_q(t, t, x) dx} \langle t \rangle^{-1} \mu \left(C_2(R+t)^{-\frac{n-1}{2}} \right) \int_1^t (t-s) \langle s \rangle^{-1} ds \right) \right]^{\frac{1}{p_S(n)}}. \end{aligned}$$

Taking account of

$$\begin{aligned} \langle t \rangle^{-1} \int_1^t (t-s) \langle s \rangle^{-1} ds &\gtrsim \langle t \rangle^{-1} \int_1^t \frac{t-s}{s} ds = \langle t \rangle^{-1} \int_1^t \log s ds \\ &\gtrsim \frac{1}{3t} \int_{2t/3}^t \log s ds \gtrsim \log \left(\frac{2t}{3} \right) \end{aligned}$$

for any $t \geq \frac{3}{2}$, and recalling (3.10), we may derive the lower bound estimate

$$\mathcal{U}(t) \gtrsim \log \left(\frac{2t}{3} \right) \mu \left(C_2(R+t)^{-\frac{n-1}{2}} \right) \left[\mu \left(2C_3 \langle t \rangle^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \log \left(\frac{2t}{3} \right) \mu \left(C_2(R+t)^{-\frac{n-1}{2}} \right) \right) \right]^{\frac{1}{p_S(n)}}$$

with a positive constant C_3 .

Our assumption (2.2) shows that there is a suitably large constant $c_l \gg 1$ such that the next estimate holds:

$$\mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(n)}} > \frac{c_l}{2} \quad \text{for } 0 < \tau \leq \tau_0 \ll 1. \quad (3.15)$$

Let us choose a large constant $t_0 \geq 1$ such that for any $t \geq \frac{3}{2}t_0$, the following inequalities hold (later, we will take t_0 to be suitably large):

$$\begin{aligned} C_2 &\leq \tau_0 (R+t)^{\frac{n-1}{2}}, \quad (3.16) \\ c_l C_2^{-1} C_3 \left(\frac{n-1}{2} \right)^{-\frac{1}{p_S(n)}} \log \left(\frac{2t}{3} \right) &\geq \langle t \rangle^{\frac{n-1}{2} + \frac{1}{p_S(n)}} (R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \left[\log \left(C_2^{-\frac{2}{n-1}} (R+t) \right) \right]^{\frac{1}{p_S(n)}}. \end{aligned}$$

Note that the second inequality in the above (it will be used for reducing the argument) can be guaranteed since

$$\langle t \rangle^{\frac{n-1}{2} + \frac{1}{p_S(n)}} (R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \left[\log \left(C_2^{-\frac{2}{n-1}} (R+t) \right) \right]^{\frac{1}{p_S(n)}} \simeq [\log(R+t)]^{\frac{1}{p_S(n)}} \lesssim \log \left(\frac{2t}{3} \right)$$

for large time t since $p_S(n) > 1$. According to our assumption (2.2) for $t \geq \frac{3}{2}t_0$, it follows

$$\begin{aligned} &\mu \left(2C_3 \langle t \rangle^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \log \left(\frac{2t}{3} \right) \mu \left(C_2(R+t)^{-\frac{n-1}{2}} \right) \right) \\ &\geq \mu \left(c_l C_3 \langle t \rangle^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \left[\log \left(C_2^{-1} (R+t)^{\frac{n-1}{2}} \right) \right]^{-\frac{1}{p_S(n)}} \log \left(\frac{2t}{3} \right) \right) \\ &\geq \mu \left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)}} \right). \end{aligned}$$

Summarizing, we deduce the following first lower bound estimate:

$$\mathcal{U}(t) \geq M_0 \log \left(\frac{2t}{3t_0} \right) \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \right) \right]^{1 + \frac{1}{p_S(n)}} \quad (3.17)$$

for any $t \geq \frac{3}{2}t_0$ with a large parameter $t_0 \geq 1$, with a positive constant M_0 independent of c_l . Here, $\epsilon_0 > 0$ is a sufficiently small constant. We have to underline that such a small ϵ_0 does not bring any influence on the blow-up condition.

3.4 Iteration procedure and blow-up phenomenon: Proof of Theorem 2.1

Up to now, we have determined among other things the iteration frame (3.11) for the functional $\mathcal{U}(t)$ and the first lower bound estimate (3.17) containing a logarithmic factor and a factor depending on the given modulus of continuity. In this part, we are going to prove a sequence of lower bound estimates for $\mathcal{U}(t)$ by applying the so-called slicing procedure, which has been introduced in [1].

Let us choose the sequence $\{\ell_j\}_{j \in \mathbb{N}_0}$ with $\ell_j := 2 - 2^{-(j+1)}$. Our goal is to derive the sequence of lower bound estimates for the functional $\mathcal{U}(t)$ as follows:

$$\mathcal{U}(t) \geq M_j (\log \langle t \rangle)^{-b_j} \left[\log \left(\frac{t}{\ell_{2j} t_0} \right) \right]^{a_j} \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \right) \right]^{\sigma_j} \quad (3.18)$$

for $t \geq \ell_{2j} t_0$ with a suitably large constant $t_0 \gg 1$, where $\{M_j\}_{j \in \mathbb{N}_0}$, $\{a_j\}_{j \in \mathbb{N}_0}$, $\{b_j\}_{j \in \mathbb{N}_0}$ and $\{\sigma_j\}_{j \in \mathbb{N}_0}$ are sequences of non-negative real numbers that we shall determine recursively throughout the iteration procedure. From the first lower bound estimate (3.17), we may choose with $j = 0$ the parameters

$$a_0 := 1, \quad b_0 := 0, \quad \sigma_0 := 1 + \frac{1}{p_S(n)}. \quad (3.19)$$

We are going to prove the validity of (3.18) for any $j \in \mathbb{N}_0$ by using an inductive argument. As we have already shown the validity of the basic case (3.17), it remains to prove the inductive step. Let us assume that (3.18) holds for $j \geq 1$, our purpose is to demonstrate it for $j + 1$.

First of all, via the lower bound estimate (3.18), we know

$$\begin{aligned} & \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1}} ds \\ & \geq M_j^{p_S(n)} \langle t \rangle^{-1} \int_0^t \frac{t-s}{\langle s \rangle} \frac{\left[\log \left(\frac{s}{\ell_{2j} t_0} \right) \right]^{a_j p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1 + b_j p_S(n)}} \left[\mu \left(C_2(R+s)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \right) \right]^{\sigma_j p_S(n)} ds \\ & \geq \frac{1}{3} M_j^{p_S(n)} \langle t \rangle^{-1} (\log \langle t \rangle)^{-(p_S(n)-1) - b_j p_S(n)} \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \right) \right]^{\sigma_j p_S(n)} \\ & \quad \times \int_{\ell_{2j} t_0}^t \frac{t-s}{s} \left[\log \left(\frac{s}{\ell_{2j} t_0} \right) \right]^{a_j p_S(n)} ds \end{aligned}$$

for $t \geq \ell_{2j+2}t_0$, where we shrank the interval of integration $[0, t]$ to $[\ell_{2j}t_0, t]$ so that $\langle s \rangle = 3 + |s| \leq 3s$ for any $s \geq \ell_{2j}t_0$. By employing integration by parts, we may derive

$$\begin{aligned} \int_{\ell_{2j}t_0}^t \frac{t-s}{s} \left[\log \left(\frac{s}{\ell_{2j}t_0} \right) \right]^{a_j p_S(n)} ds &\geq \frac{1}{a_j p_S(n) + 1} \int_{\frac{\ell_{2j}}{\ell_{2j+2}}t}^t \left[\log \left(\frac{s}{\ell_{2j}t_0} \right) \right]^{a_j p_S(n)+1} ds \\ &\geq \frac{1}{3(a_j p_S(n) + 1)} \left(1 - \frac{\ell_{2j}}{\ell_{2j+2}} \right) \langle t \rangle \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \end{aligned}$$

for $t \geq \ell_{2j+2}t_0$ so that $\ell_{2j}t_0 \leq \frac{\ell_{2j}}{\ell_{2j+2}}t$. For this reason, the last relation for $t \geq \ell_{2j+2}t_0$ implies immediately

$$\begin{aligned} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1}} ds &\geq \frac{M_j^{p_S(n)} 2^{-(2j+3)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} (\log \langle t \rangle)^{-(p_S(n)-1)-b_j p_S(n)} \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \\ &\times \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2}-\frac{1}{p_S(n)}-\epsilon_0} \right) \right]^{\sigma_j p_S(n)}. \end{aligned} \quad (3.20)$$

Plugging (3.18) into the iteration frame (3.11), we arrive after taking into consideration (3.20) at

$$\begin{aligned} \mathcal{U}(t) &\geq \frac{C_0 2^{-(2j+3)} M_j^{p_S(n)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} (\log \langle t \rangle)^{-(p_S(n)-1)-b_j p_S(n)} \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \\ &\times \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2}-\frac{1}{p_S(n)}-\epsilon_0} \right) \right]^{\sigma_j p_S(n)} [\mathcal{F}_\mu(t)]^{\frac{1}{p_S(n)}}, \end{aligned} \quad (3.21)$$

where we introduce

$$\mathcal{F}_\mu(t) := \mu \left(C_1 \langle t \rangle^{-\frac{n-1}{2}-\frac{1}{p_S(n)}} \langle t \rangle^{-1} \int_0^t (t-s) \langle s \rangle^{-1} \frac{[\mathcal{U}(s)]^{p_S(n)}}{(\log \langle s \rangle)^{p_S(n)-1}} ds \right)$$

and estimate

$$\begin{aligned} \mathcal{F}_\mu(t) &\geq \mu \left(\frac{C_1 2^{-(2j+3)} M_j^{p_S(n)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} \langle t \rangle^{-\frac{n-1}{2}-\frac{1}{p_S(n)}} (\log \langle t \rangle)^{-(p_S(n)-1)-b_j p_S(n)} \right. \\ &\quad \left. \times \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2}-\frac{1}{p_S(n)}-\epsilon_0} \right) \right]^{\sigma_j p_S(n)} \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \right). \end{aligned}$$

Taking a suitably large t_0 such that for $t \geq \ell_{2j+2}t_0$, recalling the conclusion (3.15) from our assumption (2.2) and the condition (3.16), then the following inequality holds:

$$\begin{aligned} &\frac{(\frac{C_1}{2})^{\sigma_j p_S(n)} C_1 C_2^{-1} 2^{-(2j+3)} M_j^{p_S(n)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \\ &\geq \langle t \rangle^{\frac{n-1}{2} + \frac{1}{p_S(n)}} (R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} (\log \langle t \rangle)^{p_S(n)-1+b_j p_S(n)} \left[\log \left(C_2^{-1}(R+t)^{\frac{n-1}{2} + \frac{1}{p_S(n)} + \epsilon_0} \right) \right]^{\sigma_j} \end{aligned} \quad (3.22)$$

for a fixed j , because the polynomial decay factor $(R+t)^{-\epsilon_0}$ plays from the point of decay a dominant role in comparison with all logarithmic factors on the right-hand side of the last inequality. Later, we will verify the last inequality (3.22) uniformly for all $j \gg 1$ by choosing suitable parameters a_j, b_j, σ_j and estimating M_j . According to the last lower bounds estimates, it provides

$$\mathcal{F}_\mu(t) \geq \mu \left(C_2(R+t)^{-\frac{n-1}{2}-\frac{1}{p_S(n)}-\epsilon_0} \right) \quad (3.23)$$

for $t \geq \ell_{2j+2}t_0$ with a suitably large $t_0 \gg 1$. Summarizing the above estimates (3.21) as well as (3.23), we claim the lower bound estimate

$$\begin{aligned} \mathcal{U}(t) &\geq \frac{C_0 2^{-(2j+3)} M_j^{p_S(n)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} (\log \langle t \rangle)^{-(p_S(n)-1)-b_j p_S(n)} \left[\log \left(\frac{t}{\ell_{2j+2}t_0} \right) \right]^{a_j p_S(n)+1} \\ &\quad \times \left[\mu \left(C_2(R+t)^{-\frac{n-1}{2}-\frac{1}{p_S(n)}-\epsilon_0} \right) \right]^{\sigma_j p_S(n) + \frac{1}{p_S(n)}} \end{aligned}$$

for $t \geq \ell_{2j+2}t_0$. In other words, we have proved (3.18) for $j+1$ provided that

$$\begin{aligned} M_{j+1} &:= \frac{C_0 2^{-(2j+3)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} M_j^{p_S(n)}, \\ a_{j+1} &:= 1 + a_j p_S(n), \quad b_{j+1} := p_S(n) - 1 + b_j p_S(n), \quad \sigma_{j+1} := \frac{1}{p_S(n)} + \sigma_j p_S(n). \end{aligned}$$

By using recursively the relations and the initial exponents (3.19), we deduce

$$\begin{aligned} a_j &= \frac{p_S(n)}{p_S(n) - 1} p_S^j(n) - \frac{1}{p_S(n) - 1}, \quad b_j = p_S^j(n) - 1, \\ \sigma_j &= \frac{p_S(n)}{p_S(n) - 1} p_S^j(n) - \frac{1}{(p_S(n) - 1)p_S(n)}. \end{aligned} \quad (3.24)$$

Due to the facts that $\ell_{2j} \leq 2$ and $a_j \leq \frac{p_S(n)}{p_S(n)-1} p_S^j(n)$, the lower bound of M_j can be estimated by

$$M_j = \frac{C_0 2^{-(2j+1)}}{3\ell_{2j}(1 + a_{j-1} p_S(n))} M_{j-1}^{p_S(n)} \geq C_4 [4p_S(n)]^{-j} M_{j-1}^{p_S(n)}$$

with the constant $C_4 := \frac{C_0(p_S(n)-1)}{12p_S(n)} > 0$, which depends on n but is independent of j . Applying the logarithmic function to both sides of the last inequality and using iteratively the resulting inequality, we may obtain

$$\begin{aligned} \log M_j &\geq p_S(n) \log M_{j-1} - j \log[4p_S(n)] + \log C_4 \\ &\geq \cdots \geq p_S^j(n) \log M_0 - \left(\sum_{k=0}^{j-1} (j-k) p_S^k(n) \right) \log[4p_S(n)] + \left(\sum_{k=0}^{j-1} p_S^k(n) \right) \log C_4 \\ &\geq p_S^j(n) \left(\log M_0 - \frac{p_S(n) \log[4p_S(n)]}{[p_S(n) - 1]^2} + \frac{\log C_4}{p_S(n) - 1} \right) \\ &\quad + \frac{j[p_S(n) - 1] + p_S(n)}{[p_S(n) - 1]^2} \log[4p_S(n)] - \frac{\log C_4}{p_S(n) - 1}, \end{aligned}$$

where we used the identities

$$\sum_{k=0}^{j-1} (j-k)p^k = \frac{1}{p-1} \left(\frac{p^{j+1} - p}{p-1} - j \right) \quad \text{and} \quad \sum_{k=0}^{j-1} p^k = \frac{p^j - 1}{p-1}.$$

Let us define $j_1 = j_1(p_S(n))$ as the smallest non-negative integer such that

$$j_1 \geq \frac{\log C_4}{\log[4p_S(n)]} - \frac{p_S(n)}{p_S(n) - 1}.$$

We may estimate

$$\log M_j \geq p_S^j(n) \left(\log M_0 - \frac{p_S(n) \log[4p_S(n)]}{[p_S(n) - 1]^2} + \frac{\log C_4}{p_S(n) - 1} \right) = p_S^j(n) \log C_5 \quad (3.25)$$

carrying the positive constant

$$C_5 := M_0[4p_S(n)]^{-\frac{p_S(n)}{[p_S(n)-1]^2}} C_4^{\frac{1}{p_S(n)-1}},$$

which depends on n but is independent of j .

Let us now prove the inequality (3.22) uniformly for all $j \gg 1$. Due to the choices of parameters a_j, b_j, σ_j , we may estimate

$$\begin{aligned} & \langle t \rangle^{\frac{n-1}{2} + \frac{1}{p_S(n)}} (R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} (\log \langle t \rangle)^{p_S(n)-1+b_j p_S(n)} \\ & \times \left[\log \left(C_2^{-1} (R+t)^{\frac{n-1}{2} + \frac{1}{p_S(n)} + \epsilon_0} \right) \right]^{\sigma_j} \left[\log \left(\frac{t}{\ell_{2j+2} t_0} \right) \right]^{-a_j p_S(n)-1} \\ & \leq C (R+t)^{-\epsilon_0} (\log \langle t \rangle)^{p_S(n)-2+b_j p_S(n)+\sigma_j - a_j p_S(n)} \\ & \leq C (R+t)^{-\epsilon_0} (\log \langle t \rangle)^{-1 + \frac{1}{p_S(n)}}. \end{aligned}$$

Moreover, from the lower bound of M_j in (3.25), we know

$$\frac{\left(\frac{c_l}{2}\right)^{\sigma_j p_S(n)} C_1 C_2^{-1} 2^{-(2j+3)} M_j^{p_S(n)}}{3\ell_{2j+2}(a_j p_S(n) + 1)} \geq \frac{\tilde{C}}{(p_S^{j+1}(n) - 1)4^j} \left[\left(\frac{c_l}{2}\right)^{\frac{p_S(n)}{p_S(n)-1}} C_5 \right]^{p_S^{j+1}(n)},$$

where \tilde{C} is a positive constant independent of j . Note that C_5 only depends on $M_0, C_0, p_S(n)$ but it is independent of c_l . Taking a suitably large constant c_l , in the last two inequalities, we notice

$$\frac{\tilde{C}}{(p_S^{j+1}(n) - 1)4^j} \left[\left(\frac{c_l}{2}\right)^{\frac{p_S(n)}{p_S(n)-1}} C_5 \right]^{p_S^{j+1}(n)} \geq C (R+t)^{-\epsilon_0} (\log \langle t \rangle)^{-1 + \frac{1}{p_S(n)}}$$

for any $j \gg 1$. Thus, we verified (3.22) uniformly for all $j \gg 1$.

Consequently, recalling the sequence of estimates (3.18) associated with (3.24), (3.25) and $\ell_{2j} \leq 2$,

the lower bound estimate of $\mathcal{U}(t)$ can be presented as follows:

$$\begin{aligned}
\mathcal{U}(t) &\geq \exp\left(p_S^j(n) \log C_5\right) (\log\langle t \rangle)^{-p_S^j(n)+1} \left[\log\left(\frac{t}{2t_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1} p_S^j(n) - \frac{1}{p_S(n)-1}} \\
&\quad \times \left[\mu\left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1} p_S^j(n) - \frac{1}{(p_S(n)-1)p_S(n)}} \\
&\geq \exp\left\{p_S^j(n) \log\left[C_5(\log\langle t \rangle)^{-1} \left[\log\left(\frac{t}{2t_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1}} \left[\mu\left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1}}\right]\right\} \\
&\quad \times \log\langle t \rangle \left[\log\left(\frac{t}{2t_0}\right)\right]^{-\frac{1}{p_S(n)-1}} \left[\mu\left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{-\frac{1}{(p_S(n)-1)p_S(n)}}
\end{aligned}$$

for $t \geq 2t_0$ and any $j \geq j_1$. There exists a constant $C_6 > 0$ such that for $t \geq t_1$ with a suitably large constant t_1 , it holds

$$C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \geq (C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}.$$

Moreover, concerning suitably large $t \geq t_2$, the following estimates hold:

$$\log\langle t \rangle = \log(3+t) \leq 2\log(C_6 t), \quad \log\left(\frac{t}{2t_0}\right) \geq \frac{1}{2t_0} \log(C_6 t), \quad (C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \leq \tau_0.$$

For $t \geq \max\{2t_0, t_1, t_2\}$, the lower bound of the functional can be controlled by

$$\begin{aligned}
\mathcal{U}(t) &\geq \exp\left\{p_S^j(n) \log\left[C_5 2^{-1} (2t_0)^{-\frac{p_S(n)}{p_S(n)-1}} [\log(C_6 t)]^{\frac{1}{p_S(n)-1}} \left[\mu\left((C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1}}\right]\right\} \\
&\quad \times \log\langle t \rangle \left[\log\left(\frac{t}{2t_0}\right)\right]^{-\frac{1}{p_S(n)-1}} \left[\mu\left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{-\frac{1}{(p_S(n)-1)p_S(n)}}. \tag{3.26}
\end{aligned}$$

Recalling our assumption (2.2) it follows that there exists a positive, continuous function $\kappa = \kappa(\tau)$ such that

$$\lim_{\tau \rightarrow 0^+} \kappa(\tau) \in [c_l, +\infty] \quad \text{and} \quad \mu(\tau) = \left(\log \frac{1}{\tau}\right)^{-\frac{1}{p_S(n)}} \kappa(\tau). \tag{3.27}$$

When $t \geq \max\{2t_0, t_1, t_2\}$, the crucial part in (3.26) is expressed by

$$\log(C_6 t) \left[\mu\left((C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{p_S(n)} = \left(\frac{n-1}{2} + \frac{1}{p_S(n)} + \epsilon_0\right)^{-1} \left[\kappa\left((C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{p_S(n)}$$

and the lower bound estimate turns into

$$\begin{aligned}
\mathcal{U}(t) &\geq \exp\left\{p_S^j(n) \log\left[C_7 \left[\kappa\left((C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{\frac{p_S(n)}{p_S(n)-1}}\right]\right\} \log\langle t \rangle \left[\log\left(\frac{t}{2t_0}\right)\right]^{-\frac{1}{p_S(n)-1}} \\
&\quad \times \left[\mu\left(C_2(R+t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0}\right)\right]^{-\frac{1}{(p_S(n)-1)p_S(n)}}
\end{aligned}$$

with a suitable constant $C_7 > 0$ independent of j . Let us take account of the property (3.27) of $\kappa = \kappa(\tau)$, namely,

$$\kappa(\tau) > \frac{c_l}{2} \quad \text{when } 0 < \tau \ll 1$$

with a suitably large constant $c_l > 2(100/C_7)^{[p_S(n)-1]/p_S(n)}$, where C_7 only depends on $M_0, C_0, p_S(n)$, n and is independent of j . Then for large time $t \geq \max\{2t_0, t_1, t_2\}$, we find that in the last estimate

$$\log \left[C_7 [\kappa(\tau)]^{\frac{p_S(n)}{p_S(n)-1}} \right] > \log \left[C_7 (c_l/2)^{\frac{p_S(n)}{p_S(n)-1}} \right] > 1$$

for $0 < \tau = (C_6 t)^{-\frac{n-1}{2} - \frac{1}{p_S(n)} - \epsilon_0} \ll 1$. Finally, taking the limit as $j \rightarrow +\infty$ in the above estimate the lower bound for $\mathcal{U}(t)$ blows up in finite time. This completes the proof of Theorem 2.1. \square

4 Global (in time) existence of radial solutions in three dimensions

Firstly, by introducing a polynomial-logarithmic type weighted Banach space, we will prepare uniform bounded L^∞ estimates of the radial solution to the three dimensional free wave equation in Subsection 4.1. Then, the philosophy of the proof for Theorem 2.2 and its key tool will be stated in Subsection 4.2. We will demonstrate the global (in time) existence result in Subsection 4.3 by applying a refined analysis in the (t, r) -plane to estimate the nonlinear terms.

4.1 Preliminary and weighted $L_t^\infty L_r^\infty$ estimates for the linearized model

As preparations for studying nonlinear models, we will state some polynomial-logarithmic type weighted $L_t^\infty L_r^\infty$ estimates for the linear wave equation in the radial case. Let us first extend initial data $u_0(r)$ and $u_1(r)$ by even reflections, namely,

$$u_0(-r) = u_0(r) \quad \text{and} \quad u_1(-r) = u_1(r) \quad \text{for } r < 0.$$

Note that our assumptions $u_0 \in \mathcal{C}^2$ and u_0 radially symmetric ensure $u_0'(0) = 0$. Due to our interest of radial solutions and the application of even reflections, we may rewrite the semilinear Cauchy problem (1.3) in three dimensions as

$$\begin{cases} u_{tt} - u_{rr} - \frac{2}{r}u_r = |u|^{p_S(3)}\mu(|u|), & r \in \mathbb{R}, t > 0, \\ u(0, r) = u_0(r), \quad u_t(0, r) = u_1(r), & r \in \mathbb{R}. \end{cases} \quad (4.1)$$

Now we turn our focus to the linear model with vanishing right-hand side and the same initial data as those of (4.1), namely,

$$\begin{cases} v_{tt} - v_{rr} - \frac{2}{r}v_r = 0, & r \in \mathbb{R}, t > 0, \\ v(0, r) = u_0(r), \quad v_t(0, r) = u_1(r), & r \in \mathbb{R}. \end{cases} \quad (4.2)$$

Let us recall $u_0 \in \mathcal{C}_0^2$ as well as $u_1 \in \mathcal{C}_0^1$. According to the well-known d'Alembert's formula, the solution to the linear Cauchy problem (4.2) can be represented as follows:

$$\begin{aligned} v(t, r) &= \frac{\partial}{\partial t} \left(\int_{-1}^1 H_{u_0}(t + r\sigma) d\sigma \right) + \int_{-1}^1 H_{u_1}(t + r\sigma) d\sigma \\ &= \frac{1}{2r} \left((t+r)u_0(t+r) - (t-r)u_0(t-r) \right) + \frac{1}{r} \int_{t-r}^{t+r} H_{u_1}(\rho) d\rho, \end{aligned} \quad (4.3)$$

where we denoted

$$H_{u_j}(\rho) := \frac{\rho}{2} u_j(\rho) \quad \text{with } j = 0, 1.$$

Its proof is standard by taking the new variable $rv(t, r)$ and the representation of solution for the one dimensional free wave equation.

Motivated by the papers [2, 15, 4], we are able to derive some decay estimates in some weighted $L_t^\infty L_r^\infty$ spaces for radial solutions of the linear Cauchy problem (4.2). In order to overcome some difficulties from the influence of modulus of continuity when we consider the nonlinear model (4.1), we will include an additional logarithmic type weighted function in the solution space. To be specific, we introduce the Banach space

$$X_\kappa := \left\{ v \in \mathcal{C}([0, +\infty) \times \mathbb{R}) : v \text{ is even in } r \text{ and } \|v\|_{X_\kappa} < +\infty \right\}$$

with a polynomial-logarithmic type weighted norm

$$\|v\|_{X_\kappa} := \sup_{t \geq 0, r \in \mathbb{R}} \left(\omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\kappa-1} |v(t, r)| \right) \quad \text{with } \kappa := 1 + \frac{1}{p_S(3)}.$$

Here, the new weighted factor is defined by

$$\omega(\tau) := (\log \tau)^{\frac{1}{p_S(3)}} \quad \text{for any } \tau \geq 3. \quad (4.4)$$

Then, we have the next result for bounded estimates in the Banach space X_κ .

Proposition 4.1. *Let $u_0 \in \mathcal{A}_\kappa \cap \mathcal{C}^2$ and $u_1 \in \mathcal{B}_{\kappa+1} \cap \mathcal{C}^1$ with $\kappa > 1$. Then, the following estimate holds:*

$$\|v\|_{X_\kappa} \lesssim \|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}},$$

where the Banach spaces for initial data are defined as follows:

$$\begin{aligned} \mathcal{A}_\kappa &:= \left\{ h \in \mathcal{C}^1 : h \text{ is an even function and } \|h\|_{\mathcal{A}_\kappa} < +\infty \right\}, \\ \mathcal{B}_\kappa &:= \left\{ h \in \mathcal{C} : h \text{ is an even function and } \|h\|_{\mathcal{B}_\kappa} < +\infty \right\}, \end{aligned}$$

carrying the corresponding norms

$$\begin{aligned} \|h\|_{\mathcal{A}_\kappa} &:= \sup_{r \geq 0} \left(\omega(\langle r \rangle) \langle r \rangle^\kappa |h(r)| \right) + \sup_{r \geq 0} \left(\omega(\langle r \rangle) \langle r \rangle^{\kappa+1} |h'(r)| \right), \\ \|h\|_{\mathcal{B}_\kappa} &:= \sup_{r \geq 0} \left(\omega(\langle r \rangle) \langle r \rangle^\kappa |h(r)| \right). \end{aligned}$$

In the above, we used the property to be even for the functions $\langle r \rangle$ and $|h(r)|, |h'(r)|$ so that we just need to consider $r \geq 0$ in these norms.

Proof. By using the definitions of $\|u_0\|_{\mathfrak{A}_\kappa}$ and $\|u_1\|_{\mathfrak{B}_{\kappa+1}}$, respectively, we may estimate

$$\begin{aligned} |H_{u_0}(\rho)| &\lesssim [\omega(\langle\rho\rangle)]^{-1}\langle\rho\rangle^{1-\kappa}\|u_0\|_{\mathfrak{A}_\kappa}, \\ |H'_{u_0}(\rho)| &\lesssim |u_0(\rho)| + \langle\rho\rangle|u'_0(\rho)| \lesssim [\omega(\langle\rho\rangle)]^{-1}\langle\rho\rangle^{-\kappa}\|u_0\|_{\mathfrak{A}_\kappa}, \\ |H_{u_1}(\rho)| &\lesssim [\omega(\langle\rho\rangle)]^{-1}\langle\rho\rangle^{-\kappa}\|u_1\|_{\mathfrak{B}_{\kappa+1}}. \end{aligned}$$

Let us employ the triangle inequality to observe

$$\langle t - |r| \rangle = 3 + |t - |r|| \leq 3 + |t \pm r| = \langle t \pm r \rangle. \quad (4.5)$$

According to the solution formula (4.3), one may derive

$$\begin{aligned} |v(t, r)| &\leq \frac{1}{|r|} \left(|H_{u_0}(t+r)| + |H_{u_0}(t-r)| \right) + \frac{1}{|r|} \int_{t-|r|}^{t+|r|} |H_{u_1}(\rho)| d\rho \\ &\lesssim \frac{1}{|r|} \left([\omega(\langle t+r \rangle)]^{-1}\langle t+r \rangle^{1-\kappa} + [\omega(\langle t-r \rangle)]^{-1}\langle t-r \rangle^{1-\kappa} \right) \left(\|u_0\|_{\mathfrak{A}_\kappa} + \|u_1\|_{\mathfrak{B}_{\kappa+1}} \right) \\ &\quad + \frac{1}{|r|} \int_{t-|r|}^{t+|r|} [\omega(\langle\rho\rangle)]^{-1}\langle\rho\rangle^{-\kappa} d\rho \left(\|u_0\|_{\mathfrak{A}_\kappa} + \|u_1\|_{\mathfrak{B}_{\kappa+1}} \right) \\ &\lesssim \left(\frac{1}{|r|} [\omega(\langle t-|r| \rangle)]^{-1}\langle t-|r| \rangle^{1-\kappa} + \frac{1}{|r|} \int_{t-|r|}^{t+|r|} [\omega(\langle\rho\rangle)]^{-1}\langle\rho\rangle^{-\kappa} d\rho \right) \left(\|u_0\|_{\mathfrak{A}_\kappa} + \|u_1\|_{\mathfrak{B}_{\kappa+1}} \right), \end{aligned}$$

because of $\kappa > 1$, where we used the relation (4.5). Let us separate our next consideration into two situations with respect to the interplay between t and $|r|$.

- When $t \geq 2|r|$, since the integrand takes its maximum for $\rho = t - |r|$ and $\langle t + |r| \rangle \approx \langle t - |r| \rangle$, thanks to the representation (4.3), we may estimate

$$\begin{aligned} &\omega(\langle t - |r| \rangle)\langle t + |r| \rangle\langle t - |r| \rangle^{\kappa-1}|v(t, r)| \\ &\lesssim \frac{\omega(\langle t - |r| \rangle)\langle t + |r| \rangle\langle t - |r| \rangle^{\kappa-1}}{|r|} |H_{u_0}(t+r) - H_{u_0}(t-r)| + \frac{\langle t + |r| \rangle}{\langle t - |r| \rangle} \|u_1\|_{\mathfrak{B}_{\kappa+1}} \\ &\lesssim \omega(\langle t - |r| \rangle)\langle t + |r| \rangle\langle t - |r| \rangle^{\kappa-1} |H'_{u_0}(\zeta)| + \|u_1\|_{\mathfrak{B}_{\kappa+1}} \\ &\lesssim \|u_0\|_{\mathfrak{A}_\kappa} + \|u_1\|_{\mathfrak{B}_{\kappa+1}}, \end{aligned}$$

where we employed the mean value theorem with $\zeta \in (t-r, t+r)$, (4.5) and

$$|H'_{u_0}(\zeta)| \lesssim [\omega(\langle\zeta\rangle)]^{-1}\langle\zeta\rangle^{-\kappa}\|u_0\|_{\mathfrak{A}_\kappa} \lesssim [\omega(\langle t - |r| \rangle)]^{-1}\langle t - |r| \rangle^{-\kappa}\|u_0\|_{\mathfrak{A}_\kappa}.$$

- When $t \leq 2|r|$, we have some further discussions.

– If $|r| \leq 1$, since $\langle t - |r| \rangle \approx \langle t + |r| \rangle \approx 3$ and the compact (t, r) -zone, then we get

$$\omega(\langle t - |r| \rangle)\langle t + |r| \rangle\langle t - |r| \rangle^{\kappa-1}|v(t, r)| \lesssim \|u_0\|_{\mathfrak{A}_\kappa} + \|u_1\|_{\mathfrak{B}_{\kappa+1}},$$

whose approach is the same as the one for $t \geq 2|r|$.

– If $|r| \geq 1$, since $\langle t + |r| \rangle \leq 3\langle r \rangle$ and $|r| \approx \langle r \rangle$, then we get

$$\begin{aligned} & \omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\kappa-1} |v(t, r)| \\ & \lesssim \left(\frac{\langle t + |r| \rangle}{|r|} + \frac{\langle t + |r| \rangle}{|r|} \langle t - |r| \rangle^{\kappa-1} \int_{t-|r|}^{t+|r|} \langle \rho \rangle^{-\kappa} d\rho \right) (\|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}}) \\ & \lesssim \left(1 + \frac{\langle t - |r| \rangle^{\kappa-1}}{\kappa - 1} (\langle t - |r| \rangle^{1-\kappa} - \langle t + |r| \rangle^{1-\kappa}) \right) (\|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}}) \\ & \lesssim \|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}}, \end{aligned}$$

because of $\kappa > 1$.

In other words, we arrive at

$$\left\| \omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\kappa-1} v(t, r) \right\|_{L^\infty([0, +\infty) \times \mathbb{R})} \lesssim \|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}},$$

which completes our proof. \square

4.2 Philosophy of our approach

By Duhamel's principle, the solution to the inhomogeneous linear Cauchy problem with $F = F(t, r)$ as a source term and vanishing data is given by

$$v^{\text{inh}}(t, r) = \int_0^t \int_{-1}^1 H_F[s](t - s + r\sigma) d\sigma ds = \frac{1}{r} \int_0^t \int_{t-s-r}^{t-s+r} H_F[s](\rho) d\rho ds$$

with $H_F[s](\rho) := \frac{\rho}{2} F(s, \rho)$. Concerning the semilinear Cauchy problem (4.1), inspired by the last representation, we introduce

$$Lu(t, r) := \int_0^t \int_{-1}^1 H_u[s](t - s + r\sigma) d\sigma ds = \frac{1}{r} \int_0^t \int_{t-s-r}^{t-s+r} H_u[s](\rho) d\rho ds$$

with the nonlinear term

$$H_u[s](\rho) := \frac{\rho}{2} |u(s, \rho)|^{p_S(3)} \mu(|u(s, \rho)|).$$

In view of Duhamel's principle as well as the above setting, we expect that if we find $u \in X_\kappa$ with $\kappa > 1$ such that

$$\begin{aligned} u(t, r) &= v(t, r) + Lu(t, r) \\ &= \frac{\partial}{\partial t} \left(\int_{-1}^1 H_{u_0}(t + r\sigma) d\sigma \right) + \int_{-1}^1 H_{u_1}(t + r\sigma) d\sigma + \frac{1}{r} \int_0^t \int_{t-s-r}^{t-s+r} H_u[s](\rho) d\rho ds, \end{aligned}$$

then $u = u(t, r)$ is a solution of the Cauchy problem (4.1). Note that $v \in X_\kappa$ when $\kappa > 1$ for the linear Cauchy problem (4.2) via Proposition 4.1 and initial data u_0, u_1 with compact support. In

order to prove Theorem 2.2, in the subsequent part, we will demonstrate the following two crucial inequalities:

$$\|Lu\|_{X_\kappa} \lesssim \|u\|_{X_\kappa}^{p_S(3)}, \quad (4.6)$$

$$\|Lu - L\tilde{u}\|_{X_\kappa} \lesssim \|u - \tilde{u}\|_{X_\kappa} \left(\|u\|_{X_\kappa}^{p_S(3)-1} + \|\tilde{u}\|_{X_\kappa}^{p_S(3)-1} \right), \quad (4.7)$$

for any $u, \tilde{u} \in X_\kappa$, under some conditions for the modulus of continuity. Let us recall $u_0 = \varepsilon \bar{u}_0$ and $u_1 = \varepsilon \bar{u}_1$. Combining (4.6) with Proposition 4.1, we immediately claim

$$\|v + Lu\|_{X_\kappa} \lesssim \varepsilon \left(\|\bar{u}_0\|_{\mathcal{A}_\kappa} + \|\bar{u}_1\|_{\mathcal{B}_{\kappa+1}} \right) + \|u\|_{X_\kappa}^{p_S(3)}. \quad (4.8)$$

Providing that we take a small parameter $0 < \varepsilon < \varepsilon_0 \ll 1$ and compactly supported initial data, we combine (4.8) and (4.7) to claim that there exists a global (in time) small data radial solution $u \in X_\kappa$ by using Banach's fixed point theorem.

From the condition (2.4), there exists a positive and continuous function $\bar{\kappa} = \bar{\kappa}(\tau)$ such that

$$\mu(\tau) = \left(\log \frac{1}{\tau} \right)^{-\frac{1}{p_S(3)}} \bar{\kappa}(\tau) \quad \text{and} \quad \lim_{\tau \rightarrow 0^+} \bar{\kappa}(\tau) = 0. \quad (4.9)$$

Furthermore, the condition (2.5) means that the above function $\bar{\kappa}$ satisfies the next additional condition:

$$\bar{\kappa}(\tau) \log \log \frac{1}{\tau} \lesssim 1 \quad \text{when} \quad \tau \in (0, \tau_0]. \quad (4.10)$$

Before starting our proof, let us introduce a crucial lemma.

Lemma 4.1. *Let us consider a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ satisfying the conditions (2.4) and (2.5). Let us recall the weighted factor via (4.4). Then, the integral*

$$I(\xi) := \int_{-|\xi|}^{|\xi|} [\omega(\langle \eta \rangle)]^{-p_S(3)} \langle \xi + \eta \rangle \langle \eta \rangle^{-1} \mu \left(\varepsilon_0 [\omega(\langle \eta \rangle)]^{-1} \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} \right) d\eta$$

fulfills the following estimate:

$$I(\xi) \lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} (\log \log \langle \xi \rangle) \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right).$$

Proof. To begin with, let us split $I(\xi)$ into two parts

$$I_1(\xi) := \int_{-\frac{|\xi|}{2}}^{\frac{|\xi|}{2}} [\omega(\langle \eta \rangle)]^{-p_S(3)} \langle \xi + \eta \rangle \langle \eta \rangle^{-1} \mu \left(\varepsilon_0 [\omega(\langle \eta \rangle)]^{-1} \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} \right) d\eta,$$

$$I_2(\xi) := \left(\int_{\frac{|\xi|}{2}}^{|\xi|} + \int_{-|\xi|}^{-\frac{|\xi|}{2}} \right) [\omega(\langle \eta \rangle)]^{-p_S(3)} \langle \xi + \eta \rangle \langle \eta \rangle^{-1} \mu \left(\varepsilon_0 [\omega(\langle \eta \rangle)]^{-1} \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} \right) d\eta.$$

For the first integral, we use the asymptotic behaviors $\langle \xi \rangle \approx \langle \eta + \xi \rangle \approx \langle \eta - \xi \rangle$ when $\eta \in [-\frac{|\xi|}{2}, \frac{|\xi|}{2}]$

to deduce

$$\begin{aligned}
I_1(\xi) &\lesssim \langle \xi \rangle \int_{-\frac{|\xi|}{2}}^{\frac{|\xi|}{2}} \langle \eta \rangle^{-1} [\log(\langle \eta \rangle)]^{-1} \mu \left(\varepsilon_0 \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} [\log(\langle \eta \rangle)]^{-\frac{1}{p_S(3)}} \right) d\eta \\
&\lesssim \langle \xi \rangle \mu \left(\varepsilon_0 \langle \xi \rangle^{-1} \right) \int_0^{\frac{|\xi|}{2}} \langle \eta \rangle^{-1} [\log(\langle \eta \rangle)]^{-1} d\eta \\
&\lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} (\log \log \langle \xi \rangle) \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right), \tag{4.11}
\end{aligned}$$

where we used the condition (4.9) and the increasing property with $[\langle \eta \rangle \log(\langle \eta \rangle)]^{-\frac{1}{p_S(3)}} < 1$.

Let us turn to the first part of $I_2(\xi)$, which is denoted by $I_{2,1}(\xi)$. When $\xi \geq 0$, due to $\eta \in [\frac{\xi}{2}, \xi]$, the equivalences $\langle \eta + \xi \rangle \approx \langle \eta \rangle \approx \langle \xi \rangle$ hold. It leads to

$$\begin{aligned}
I_{2,1}(\xi) &\lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-1} \mu \left(\varepsilon_0 \langle \xi \rangle^{-1-\frac{1}{p_S(3)}} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} \right) \\
&\lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-1-\frac{1}{p_S(3)}} \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right),
\end{aligned}$$

because $[\langle \xi \rangle \log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} < 1$. When $\xi \leq 0$, the equivalences $\langle \eta - \xi \rangle \approx \langle \xi \rangle \approx \langle \eta \rangle$ are valid for $\eta \in [-\xi, -\frac{\xi}{2}]$. Then, one deduces

$$\begin{aligned}
I_{2,1}(\xi) &\lesssim [\log(\langle \xi \rangle)]^{-1} \langle \xi \rangle^{-1} \mu \left(\varepsilon_0 \langle \xi \rangle^{-1-\frac{1}{p_S(3)}} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} \right) \int_{-\xi}^{-\frac{\xi}{2}} \langle -\xi - \eta \rangle d\eta \\
&\lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-1-\frac{1}{p_S(3)}} \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right).
\end{aligned}$$

The above two estimates are stronger than the estimate (4.11). Repeating the same procedure as those for $I_{2,1}(\xi)$, by symmetry we are able to get

$$I_{2,2}(\xi) \lesssim \langle \xi \rangle [\log(\langle \xi \rangle)]^{-1-\frac{1}{p_S(3)}} \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right).$$

Summarizing the above derived estimates, we complete the proof of this lemma. \square

4.3 Some estimates for solutions to nonlinear models: Proof of Theorem 2.2

Let us consider $u \in X_\kappa$. From the definition of the Banach space X_κ with $\kappa > 1$, we obtain

$$\begin{aligned}
|u(s, \rho)|^{p_S(3)} \mu(|u(s, \rho)|) &\lesssim [\omega(\langle s - |\rho| \rangle)]^{-p_S(3)} \langle s + |\rho| \rangle^{-p_S(3)} \langle s - |\rho| \rangle^{-(\kappa-1)p_S(3)} \|u\|_{X_\kappa}^{p_S(3)} \\
&\quad \times \mu \left([\omega(\langle s - |\rho| \rangle)]^{-1} \langle s + |\rho| \rangle^{-1} \langle s - |\rho| \rangle^{-(\kappa-1)} \|u\|_{X_\kappa} \right) \\
&\lesssim [\omega(\langle s - |\rho| \rangle)]^{-p_S(3)} \langle s + |\rho| \rangle^{-p_S(3)} \langle s - |\rho| \rangle^{-(\kappa-1)p_S(3)} \|u\|_{X_\kappa}^{p_S(3)} \\
&\quad \times \mu \left(\varepsilon_0 [\omega(\langle s - |\rho| \rangle)]^{-1} \langle s + |\rho| \rangle^{-1} \langle s - |\rho| \rangle^{-(\kappa-1)} \right),
\end{aligned}$$

where we assumed $\|u\|_{X_\kappa} \leq \varepsilon_0$ for some $\varepsilon_0 > 0$ sufficiently small.

With the aim of proving (4.6), we just need to show

$$\omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\kappa-1} |Lu(t, r)| \lesssim \|u\|_{X_\kappa}^{p_S(3)}.$$

Because Lu is even in r , we may restrict ourselves to non-negative values of r . Concerning $r \geq 0$, applying the definition of Lu , we get

$$\begin{aligned} |Lu(t, r)| &\leq \frac{1}{r} \int_0^t \int_{t-s-r}^{t-s+r} |H_u[s](\rho)| d\rho ds \\ &\lesssim \frac{1}{r} \int_0^t \int_{t-s-r}^{t-s+r} \langle \rho \rangle [\omega(\langle s - |\rho| \rangle)]^{-p_S(3)} \langle s + |\rho| \rangle^{-p_S(3)} \langle s - |\rho| \rangle^{-(\kappa-1)p_S(3)} \\ &\quad \times \underbrace{\mu \left(\varepsilon_0 [\omega(\langle s - |\rho| \rangle)]^{-1} \langle s + |\rho| \rangle^{-1} \langle s - |\rho| \rangle^{-(\kappa-1)} \right)}_{=: I_0(t, r)} d\rho ds \|u\|_{X_\kappa}^{p_S(3)} \end{aligned}$$

for the case $t \geq r$. In the case $t \leq r$, we can slightly modify the representation formulate for Lu . Precisely, being $H_u[s](\rho)$ an odd function with respect to ρ , one notices

$$\int_{(t-s)-r}^{r-(t-s)} H_u[s](\rho) d\rho = 0.$$

The additivity of the integral regions shows

$$Lu(t, r) = \frac{1}{r} \int_0^t \int_{r-(t-s)}^{(t-s)+r} H_u[s](\rho) d\rho ds.$$

As a consequence, when $t \leq r$, we may replace $I_0(t, r)$ by

$$\begin{aligned} \tilde{I}_0(t, r) &:= \int_0^t \int_{r-(t-s)}^{r+(t-s)} \langle \rho \rangle [\omega(\langle s - |\rho| \rangle)]^{-p_S(3)} \langle s + |\rho| \rangle^{-p_S(3)} \langle s - |\rho| \rangle^{-(\kappa-1)p_S(3)} \\ &\quad \times \mu \left(\varepsilon_0 [\omega(\langle s - |\rho| \rangle)]^{-1} \langle s + |\rho| \rangle^{-1} \langle s - |\rho| \rangle^{-(\kappa-1)} \right) d\rho ds. \end{aligned}$$

All in all, we already derived

$$|Lu(t, r)| \lesssim \begin{cases} r^{-1} I_0(t, r) \|u\|_{X_\kappa}^{p_S(3)} & \text{when } t \geq r, \\ r^{-1} \tilde{I}_0(t, r) \|u\|_{X_\kappa}^{p_S(3)} & \text{when } t \leq r, \end{cases}$$

for any $r \geq 0$.

Estimates for $I_0(t, r)$ with $t \geq r$. Since $|t - s - r| \leq t - s + r$ (we are working with $r \geq 0$) and the even function with respect to ρ of the integrand in $I_0(t, r)$ so that

$$\begin{aligned} I_0(t, r) &\leq 2 \int_0^t \int_{\max\{0, t-s-r\}}^{t-s+r} \langle s + \rho \rangle^{-p_S(3)} \langle s - \rho \rangle^{-(\kappa-1)p_S(3)} \langle \rho \rangle [\omega(\langle s - \rho \rangle)]^{-p_S(3)} \\ &\quad \times \mu \left(\varepsilon_0 [\omega(\langle s - \rho \rangle)]^{-1} \langle s + \rho \rangle^{-1} \langle s - \rho \rangle^{-(\kappa-1)} \right) d\rho ds. \end{aligned}$$

We now perform the change of two variables

$$\xi = s + \rho, \quad \eta = \rho - s, \quad \text{namely, } \rho = \frac{\xi + \eta}{2}, \quad s = \frac{\xi - \eta}{2}. \quad (4.12)$$

Since $\rho, s \geq 0$, we get $|\eta| \leq \xi$. Furthermore, $\rho \in [\max\{0, t - s - r\}, t - s + r]$ leads to

$$t - r \leq s + \max\{0, t - s - r\} \leq s + \rho = \xi \leq t + r.$$

Hence, recalling $\kappa := 1 + \frac{1}{p_S(3)}$ in the definition of the Banach space X_κ , we may employ Lemma 4.1 to derive

$$\begin{aligned} I_0(t, r) &\lesssim \int_{t-r}^{t+r} \langle \xi \rangle^{-p_S(3)} \int_{-\xi}^{\xi} [\omega(\langle \eta \rangle)]^{-p_S(3)} \langle \xi + \eta \rangle \langle \eta \rangle^{-1} \mu \left(\varepsilon_0 [\omega(\langle \eta \rangle)]^{-1} \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} \right) d\eta d\xi \\ &\lesssim \int_{t-r}^{t+r} \langle \xi \rangle^{-p_S(3)} I(\xi) d\xi \\ &\lesssim \int_{t-r}^{t+r} \langle \xi \rangle^{1-p_S(3)} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} (\log \log \langle \xi \rangle) \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right) d\xi. \end{aligned}$$

Thus, from the even behavior of Lu with respect to r , taking account of $t \geq r \geq 0$, we may arrive at

$$\begin{aligned} \omega(\langle t-r \rangle) \langle t+r \rangle \langle t-r \rangle^{\frac{1}{p_S(3)}} |Lu(t, r)| &\lesssim \omega(\langle t-r \rangle) \langle t+r \rangle \langle t-r \rangle^{\frac{1}{p_S(3)}} r^{-1} |I_0(t, r)| \|u\|_{X_\kappa}^{p_S(3)} \\ &\lesssim J_0(t, r) \|u\|_{X_\kappa}^{p_S(3)}, \end{aligned}$$

where

$$\begin{aligned} J_0(t, r) &:= [\log(\langle t-r \rangle)]^{\frac{1}{p_S(3)}} \frac{\langle t+r \rangle \langle t-r \rangle^{\frac{1}{p_S(3)}}}{r} \\ &\quad \times \int_{t-r}^{t+r} \langle \xi \rangle^{1-p_S(3)} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} (\log \log \langle \xi \rangle) \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right) d\xi. \end{aligned}$$

Noticing that $\varepsilon_0 \langle \xi \rangle^{-1} \leq \varepsilon_0 3^{-1} \leq \tau_0$ with $0 < \varepsilon_0 \ll 1$, we directly apply (4.10) to derive

$$\bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right) \left[\log \log \left(\varepsilon_0^{-1} \langle \xi \rangle \right) \right] \lesssim 1. \quad (4.13)$$

Due to $\varepsilon_0^{-1} \gg 1$, we simplify our aim as

$$J_0(t, r) \lesssim [\log(\langle t-r \rangle)]^{\frac{1}{p_S(3)}} \frac{\langle t+r \rangle \langle t-r \rangle^{\frac{1}{p_S(3)}}}{r} \int_{t-r}^{t+r} \langle \xi \rangle^{1-p_S(3)} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} d\xi.$$

Next, we will estimate $J_0(t, r)$ precisely in different zones of the (t, r) -plane.

Zone I: $t \geq 2r \geq 0$. For $\xi \in [t-r, t+r]$, we know the equivalence $\langle \xi \rangle \approx \langle t+r \rangle$. It follows

$$\begin{aligned} J_0(t, r) &\lesssim \langle t+r \rangle^{2-p_S(3)} \langle t-r \rangle^{\frac{1}{p_S(3)}} [\log(\langle t+r \rangle)]^{-\frac{1}{p_S(3)}} [\log(\langle t-r \rangle)]^{\frac{1}{p_S(3)}} \\ &\lesssim \langle t+r \rangle^{2-p_S(3)+\frac{1}{p_S(3)}} \lesssim 1, \end{aligned}$$

since $-p_S^2(3) + 2p_S(3) + 1 = 0$ for three dimensions (see (1.2) with $n = 3$).

Zone II: $0 \leq r \leq 1$ and $t \leq 2r$. We own the equivalence $\langle t+r \rangle \approx 3$ so that

$$J_0(t, r) \lesssim \langle t+r \rangle^{1+\frac{1}{p_S(3)}} \langle t-r \rangle^{1-p_S(3)} \lesssim 1$$

by using the bounds $2 \leq \langle t-r \rangle \leq \langle t+r \rangle$.

Zone III: $r \geq 1$ and $r \leq t \leq 2r$. Via the equivalences $r \approx \langle r \rangle \approx \langle t + r \rangle$, we are able to conclude

$$J_0(t, r) \lesssim \frac{\langle t + r \rangle}{r} \langle t - r \rangle^{\frac{1}{p_S(3)}} \int_{t-r}^{t+r} \langle \xi \rangle^{1-p_S(3)} d\xi \lesssim \langle t - r \rangle^{2-p_S(3)+\frac{1}{p_S(3)}} \lesssim 1,$$

where we applied $p_S(3) = 1 + \sqrt{2} > 2$.

Summarizing, we have derived the key estimate

$$\omega(\langle t - r \rangle) \langle t + r \rangle \langle t - r \rangle^{\frac{1}{p_S(3)}} |Lu(t, r)| \lesssim J_0(t, r) \|u\|_{X_\kappa}^{p_S(3)} \lesssim \|u\|_{X_\kappa}^{p_S(3)}$$

for any $t \geq r$.

Estimates for $\tilde{I}_0(t, r)$ with $t \leq r$. This part just discusses the case for $r \geq 1$ since the situation in a compact set $t \leq r \leq 1$ is trivial. As before, we take the change of variables (4.12). According to $s \geq 0$ and $\rho \geq r - (t - s)$, we deduce $r - t \leq \eta \leq \xi$, while from $s \geq 0$ and $|\rho - r| \leq t - s$ it follows $r - t \leq \xi \leq r + t$. For this reason, we find

$$\tilde{I}_0(t, r) \lesssim \int_{r-t}^{r+t} \langle \xi \rangle^{-p_S(3)} \int_{r-t}^{\xi} [\omega(\langle \eta \rangle)]^{-p_S(3)} \langle \xi + \eta \rangle \langle \eta \rangle^{-1} \mu \left(\varepsilon_0 [\omega(\langle \eta \rangle)]^{-1} \langle \xi \rangle^{-1} \langle \eta \rangle^{-\frac{1}{p_S(3)}} \right) d\eta d\xi.$$

The relation $[r - t, \xi] \subset [-\xi, \xi]$ and the application of Lemma 4.1 associated with (4.13) yield

$$\begin{aligned} \tilde{I}_0(t, r) &\lesssim \int_{r-t}^{r+t} \langle \xi \rangle^{1-p_S(3)} [\log(\langle \xi \rangle)]^{-\frac{1}{p_S(3)}} (\log \log \langle \xi \rangle) \bar{\kappa} \left(\varepsilon_0 \langle \xi \rangle^{-1} \right) d\xi \\ &\lesssim [\log(\langle r - t \rangle)]^{-\frac{1}{p_S(3)}} \int_{r-t}^{r+t} \langle \xi \rangle^{1-p_S(3)} d\xi \\ &\lesssim \langle t - r \rangle^{2-p_S(3)} [\log(\langle t - r \rangle)]^{-\frac{1}{p_S(3)}}, \end{aligned}$$

due to $2 - p_S(3) = 1 - \sqrt{2} < 0$. Hence,

$$\begin{aligned} \omega(\langle t - r \rangle) \langle t + r \rangle \langle t - r \rangle^{\frac{1}{p_S(3)}} |Lu(t, r)| &\lesssim \omega(\langle t - r \rangle) \langle t + r \rangle \langle t - r \rangle^{\frac{1}{p_S(3)}} r^{-1} |\tilde{I}_0(t, r)| \|u\|_{X_\kappa}^{p_S(3)} \\ &\lesssim \frac{\langle t + r \rangle}{r} \langle t - r \rangle^{2-p_S(3)+\frac{1}{p_S(3)}} \|u\|_{X_\kappa}^{p_S(3)} \\ &\lesssim \|u\|_{X_\kappa}^{p_S(3)} \end{aligned}$$

by the same reason as the one in *Zone III* of estimates for $I_0(t, r)$.

Thus, we may claim

$$\left\| \omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\frac{1}{p_S(3)}} Lu(t, r) \right\|_{L^\infty([0, +\infty) \times \mathbb{R})} \lesssim \|u\|_{X_\kappa}^{p_S(3)} \quad (4.14)$$

with the weighted factor defined in (4.4) and the conditions (2.4) as well as (2.5). As a by-product, due to

$$|Lu(t, r) - L\tilde{u}(t, r)| \lesssim \frac{1}{r} \|u - \tilde{u}\|_{X_\kappa} \left(\|u\|_{X_\kappa}^{p_S(3)-1} + \|\tilde{u}\|_{X_\kappa}^{p_S(3)-1} \right) \times \begin{cases} r^{-1} I_0(t, r) & \text{when } t \geq r, \\ r^{-1} \tilde{I}_0(t, r) & \text{when } t \leq r, \end{cases}$$

one can prove

$$\begin{aligned} & \left\| \omega(\langle t - |r| \rangle) \langle t + |r| \rangle \langle t - |r| \rangle^{\frac{1}{p_S(3)}} \left(Lu(t, r) - L\tilde{u}(t, r) \right) \right\|_{L^\infty([0, +\infty) \times \mathbb{R})} \\ & \lesssim \|u - \tilde{u}\|_{X_\kappa} \left(\|u\|_{X_\kappa}^{p_S(3)-1} + \|\tilde{u}\|_{X_\kappa}^{p_S(3)-1} \right), \end{aligned}$$

by the same way as those for (4.14).

Summarizing the last statements, we have completed the proof of the desired inequalities (4.6) as well as (4.7), namely, the proof of Theorem 2.2 is completed. Furthermore, by employing Banach's fixed point theorem, with the weighted data, we can get the next global (in time) existence result with some pointwise decay estimates.

Corollary 4.1. *Let us consider a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ fulfilling (2.4) and (2.5). Let $u_0 \in (\mathcal{A}_\kappa \cap \mathcal{C}^2)$ and $u_1 \in (\mathcal{B}_{\kappa+1} \cap \mathcal{C}^1)$ be radial with $\kappa = 1 + \frac{1}{p_S(3)}$. Then, there exists $0 < \varepsilon_0 \ll 1$ such that for any $\varepsilon \in (0, \varepsilon_0)$ fulfilling $\|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}} < \varepsilon_0$, the semilinear Cauchy problem (1.3) for $n = 3$ admits a uniquely determined global (in time) small data radial solution $u \in \mathcal{C}([0, +\infty) \times \mathbb{R}^3)$. Furthermore, the solution fulfills the following pointwise decay estimates:*

$$|u(t, r)| \lesssim [\log(\langle t - |r| \rangle)]^{-\frac{1}{p_S(3)}} \langle t + |r| \rangle^{-1} \langle t - |r| \rangle^{-\frac{1}{p_S(3)}} \left(\|u_0\|_{\mathcal{A}_\kappa} + \|u_1\|_{\mathcal{B}_{\kappa+1}} \right).$$

Here, the data spaces \mathcal{A}_κ and \mathcal{B}_κ were defined in Proposition 4.1.

Remark 4.1. *One of our new tools is the introduction of new weighted data spaces with logarithmic factors so that we finally can derive polynomial-logarithmic type decay estimates for the global (in time) radial solutions to the Cauchy problem (4.1) with modulus of continuity from the previous Corollary 4.1.*

5 Final remarks

In this paper, we derived a blow-up result and a global (in time) existence result for semilinear classical wave equations with a modulus of continuity in the nonlinearity $|u|^{p_S(n)} \mu(|u|)$. Specially, considering a modulus of continuity $\mu = \mu(\tau)$ with $\mu(0) = 0$ carrying the form (1.4) with $0 < \tau_0 \ll 1$, we described the critical regularity of nonlinearities $|u|^{p_S(3)} \mu(|u|)$ by the threshold $\gamma = \frac{1}{p_S(3)}$.

According to the general blow-up condition (2.2) and the global (in time) existence result in Theorem 2.2, we expect that the general threshold is described by the quantity (2.6), i.e.

$$C_{\text{Str}} = \lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right)^{\frac{1}{p_S(n)}}. \quad (5.1)$$

Let us explain it via three situations concerning the value of $C_{\text{Str}} \geq 0$.

- **Blow-up of solutions when $C_{\text{Str}} = +\infty$:** Due to the proposed condition (2.2) in Theorem 2.1, the validity of the last conjecture from the blow-up viewpoint is already known when $C_{\text{Str}} = +\infty$.

- **Blow-up of solutions when $C_{\text{Str}} \in (0, +\infty)$:** Due to the proposed condition (2.2) in Theorem 2.1, we already know the blow-up phenomenon occurs when $C_{\text{Str}} \in [c_l, +\infty)$ with a suitably large constant $c_l \gg 1$. Recently, the blow-up result for semilinear classical wave equations with modulus of continuity in derivative type nonlinearity has been studied by [3]. Considering the model $u_{tt} - \Delta u = |u_t|^{p_G(n)} \mu(|u_t|)$ with the Glassey exponent $p_G(n) := \frac{n+1}{n-1}$ for $n \geq 2$, the author of [3] proposes a new blow-up condition even for the completed intermediate case as follows:

$$\lim_{\tau \rightarrow 0^+} \mu(\tau) \left(\log \frac{1}{\tau} \right) = C_{\text{Gla}} \in (0, +\infty].$$

Motivated by the above explanation, we believe the blow-up result still holds in the intermediate case $C_{\text{Str}} \in (0, c_l)$. However, due to some technical difficulties, the rigorous justification is still challenging.

- **Global (in time) existence of solutions when $C_{\text{Str}} = 0$:** Due to the proposed condition (2.4), i.e. $C_{\text{Str}} = 0$, and the decay assumption (2.5) in Theorem 2.2, our conjecture is partially verified from the global (in time) existence perspective.

Lastly, we underline that the validity of our conjecture (5.1) has been verified in the present manuscript for the semilinear three dimensional Cauchy problem (1.3) with a modulus of continuity fulfilling $\mu(0) = 0$ and $\mu(\tau) = c_l (\log \frac{1}{\tau})^{-\gamma}$ with $c_l \gg 1$ when $\tau \in (0, \tau_0]$, because the global (in time) existence result for $\gamma > \frac{1}{p_S(3)}$ and the blow-up result for $0 < \gamma \leq \frac{1}{p_S(3)}$ have been rigorously demonstrated in Theorems 2.2 and 2.1, respectively.

Acknowledgments

The first author was partially supported by the National Natural Science Foundation of China (grant No. 12171317) and Guangdong Basic and Applied Basic Research Foundation (grant No. 2023A1515012044).

References

- [1] R. Agemi, Y. Kurokawa, H. Takamura, Critical curve for p - q systems of nonlinear wave equations in three space dimensions. *J. Differential Equations* **167** (2000), no. 1, 87–133.
- [2] F. Asakura, Existence of a global solution to a semilinear wave equation with slowly decreasing initial data in three space dimensions. *Comm. Partial Differential Equations* **11** (1986), no. 13, 1459–1487.
- [3] W. Chen, A blow-up result for semilinear wave equations with modulus of continuity in derivative type nonlinearity. *Preprint* (2023).
- [4] M. D’Abicco, S. Lucente, M. Reissig, A shift in the Strauss exponent for semilinear wave equations with a not effective damping. *J. Differential Equations* **259** (2015), no. 10, 5040–5073.
- [5] T.A. Dao, M. Reissig, The interplay of critical regularity of nonlinearities in a weakly coupled system of semi-linear damped wave equations. *J. Differential Equations* **299** (2021), 1–32.

- [6] M.R. Ebert, G. Girardi, M. Reissig, Critical regularity of nonlinearities in semilinear classical damped wave equations. *Math. Ann.* **378** (2020), no. 3-4, 1311–1326.
- [7] V. Georgiev, H. Lindblad, C.D. Sogge, Weighted Strichartz estimates and global existence for semilinear wave equations. *Amer. J. Math.* **119** (1997), no. 6, 1291–1319.
- [8] R.T. Glassey, Finite-time blow-up for solutions of nonlinear wave equations. *Math. Z.* **177** (1981), no. 3, 323–340.
- [9] R.T. Glassey, Existence in the large for $\square u = F(u)$ in two space dimensions. *Math. Z.* **178** (1981), no. 2, 233–261.
- [10] M. Ikeda, M. Sobajima, K. Wakasa, Blow-up phenomena of semilinear wave equations and their weakly coupled systems. *J. Differential Equations* **267** (2019), no. 9, 5165–5201.
- [11] H. Jiao, Z. Zhou, An elementary proof of the blow-up for semilinear wave equation in high space dimensions. *J. Differential Equations* **189** (2003), no. 2, 355–365.
- [12] F. John, Blow-up of solutions of nonlinear wave equations in three space dimensions. *Manuscripta Math.* **28** (1979), no. 1-3, 235–268.
- [13] T. Kato, Blow-up of solutions of some nonlinear hyperbolic equations. *Comm. Pure Appl. Math.* **33** (1980), no. 4, 501–505.
- [14] H. Kubo, Asymptotic behaviour of solutions to semilinear wave equations with initial data of slow decay. *Math. Methods Appl. Sci.* **17** (1994), no. 12, 953–970.
- [15] H. Kubo, Slowly decaying solutions for semilinear wave equations in odd space dimensions. *Nonlinear Anal.* **28** (1997), no. 2, 327–357.
- [16] H. Kubo, K. Kubota, Asymptotic behaviors of radially symmetric solutions of $\square u = |u|^p$ for super critical values p in odd space dimensions. *Hokkaido Math. J.* **24** (1995), no. 2, 287–336.
- [17] H. Kubo, K. Kubota, Asymptotic behaviors of radially symmetric solutions of $\square u = |u|^p$ for super critical values p in even space dimensions. *Japan. J. Math. (N.S.)* **24** (1998), no. 2, 191–256.
- [18] N.-A. Lai, H. Takamura, Nonexistence of global solutions of nonlinear wave equations with weak time-dependent damping related to Glassey’s conjecture. *Differential Integral Equations* **32** (2019), no. 1-2, 37–48.
- [19] H. Lindblad, C.D. Sogge, On existence and scattering with minimal regularity for semilinear wave equations. *J. Funct. Anal.* **130** (1995), no. 2, 357–426
- [20] L. Pick, A. Kufner, O. John, S. Fučík, *Function spaces*. De Gruyter Series in Nonlinear Analysis and Applications, 14. Walter de Gruyter & Co., Berlin, 2013.
- [21] J. Schaeffer, The equation $u_{tt} - \Delta u = |u|^p$ for the critical value of p . *Proc. Roy. Soc. Edinburgh Sect. A* **101** (1985), no. 1-2, 31–44.
- [22] T.C. Sideris, Nonexistence of global solutions to semilinear wave equations in high dimensions. *J. Differential Equations* **52** (1984), no. 3, 378–406.
- [23] W.A. Strauss, Nonlinear scattering theory at low energy. *J. Funct. Anal.* **41** (1981), no. 1, 110–133.
- [24] D. Tataru, Strichartz estimates in the hyperbolic space and global existence for the semilinear wave equation. *Trans. Amer. Math. Soc.* **353** (2001), no. 2, 795–807.
- [25] K. Wakasa, B. Yordanov, Blow-up of solutions to critical semilinear wave equations with variable coefficients. *J. Differential Equations* **266** (2019), no. 9, 5360–5376.

- [26] B.T. Yordanov, Q.S. Zhang, Finite time blow up for critical wave equations in high dimensions. *J. Funct. Anal.* **231** (2006), no. 2, 361–374.
- [27] Y. Zhou, Blow up of solutions to semilinear wave equations with critical exponent in high dimensions. *Chinese Ann. Math. Ser. B* **28** (2007), no. 2, 205–212.