1

Suppose we observe data  $\mathcal{D} = \{(x_i, y_i)\}_{i=1}^n$  generated by the process

Keywords: Gaussian process, Markov process, Brownian motion, noisy data

the Brownian motion and bridge as special cases.

$$y_i = f(x_i) + \varepsilon_i,\tag{1}$$

where  $x_i \ge 0$  is non-decreasing in *i*, where  $f : [0, \infty) \to \mathbb{R}$  is unknown, and where the errors  $\varepsilon_i$  are jointly normally distributed (hereafter "Gaussian") with  $E[\varepsilon_i | x_1, x_2, ..., x_n] = 0$  independently of  $\{f(x)\}_{x\ge 0}$ . We use  $\mathcal{D}$  to construct pointwise estimates

Estimating sample paths of Gauss-Markov

processes from noisy data

Benjamin Davies<sup>\*</sup>

Draft version: April 2, 2024

Abstract

I derive the pointwise conditional means and variances of an arbitrary Gauss-Markov process, given noisy observations of points on a sample path. These moments depend on the process's mean and covariance functions, and on the conditional moments of the sampled points. I study

$$\hat{f}_{\mathcal{D}}(x) \equiv \mathrm{E}[f(x) \mid \mathcal{D}]$$

with mean squared error (MSE)

Introduction

$$\mathbf{E}\left[\left(f(x) - \hat{f}_{\mathcal{D}}(x)\right)^2 \mid \mathcal{D}\right] = \operatorname{Var}(f(x) \mid \mathcal{D}).$$
(2)

In this note, I derive expressions for E[f(x) | D] and Var(f(x) | D) when  $\{f(x)\}_{x \ge 0}$  is a sample path of a Gauss-Markov process. Such processes have two defining properties:

<sup>\*</sup>Department of Economics, Stanford University; bldavies@stanford.edu.

- (G) For every finite subset  $X \subset [0, \infty)$ , the vector  $(f(x))_{x \in X} \in \mathbb{R}^{|X|}$  is multivariate Gaussian;
- (M) If x < x' < x'', then f(x) and f(x'') are conditionally independent given f(x').

Property (G) implies that f(x) | D is Gaussian, and so its distribution is fully determined by its mean E[f(x) | D] and variance Var(f(x) | D). Theorem 1 expresses these moments in terms of the means and (co)variances of the  $f(x_i) | D$ . This allows me to construct the estimate  $\hat{f}_D(x)$  and its MSE at all points  $x \ge 0$ . This estimate optimally extrapolates from, or interpolates between, the observations  $(x_i, y_i)$  in D.<sup>1</sup>

I let these observations be noisy, with Gaussian errors  $\varepsilon_i = y_i - f(x_i)$ . This allows me to extend analyses that assume observations have no noise (e.g., Bardhi, 2024; Callander, 2011; Carnehl and Schneider, 2023).<sup>2</sup> I also let the sampled points  $x_i$  be less or greater than the target point x. This contrasts with Davies (2024), who studies sequential learning from noisy observations of a sample path. Such learning always involves extrapolation, whereas I allow for interpolation.

## 2 Preliminaries

The data  $\mathcal{D} = \{(x_i, y_i)\}_{i=1}^n$  contain noisy observations  $y_i = f(x_i) + \varepsilon_i$  of the values  $f(x_i)$ . These observations equal the sum of two Gaussian random variables and so are Gaussian too. Moreover, by property (G), the vector  $(f(x_1), f(x_2), \dots, f(x_n), f(x))$  is multivariate Gaussian for all  $x \ge 0$ . It follows that

$$(y_1, y_2, \dots, y_n, f(x)) = (f(x_1), f(x_2), \dots, f(x_n), f(x)) + (\varepsilon_1, \varepsilon_2, \dots, \varepsilon_n, f(x))$$

is also multivariate Gaussian. Consequently, we can construct the conditional distribution of f(x) given  $y_1, y_2, \ldots, y_n$  using a well-known result about multivariate Gaussian variables:

**Lemma 1.** Let  $n_1 \ge 1$  and  $n_2 \ge 1$  be integers, and let  $z \sim \mathcal{N}(\mu, \Sigma)$  be multivariate Gaussian with mean  $\mu \in \mathbb{R}^{n_1+n_2}$  and variance  $\Sigma \in \mathbb{R}^{(n_1+n_2)\times(n_1+n_2)}$ . Partition  $z = (z_1, z_2)$  into vectors  $z_1 \in \mathbb{R}^{n_1}$  and  $z_2 \in \mathbb{R}^{n_2}$ , and let  $\mu = (\mu_1, \mu_2)$  and

$$\Sigma = egin{pmatrix} \Sigma_{11} & \Sigma_{12} \ \Sigma_{21} & \Sigma_{22} \end{pmatrix}$$

be the corresponding partitions of  $\mu$  and  $\Sigma$ . If  $\Sigma_{22}$  is invertible, then

$$\underbrace{z_1 \mid z_2 \sim \mathcal{N}\Big(\mu_1 + \Sigma_{12}\Sigma_{22}^{-1}(z_2 - \mu_2), \ \Sigma_{11} - \Sigma_{12}\Sigma_{22}^{-1}\Sigma_{21}\Big)}_{(3)}$$

<sup>&</sup>lt;sup>1</sup>The estimate is "optimal" in that it minimizes the MSE (2) for all  $x \ge 0$ .

<sup>&</sup>lt;sup>2</sup>Rasmussen and Williams (2006, p. 16) derive expressions for E[f(x) | D] and Var(f(x) | D) when  $\{f(x)\}_{x\geq 0}$  follows a Gaussian (but not necessarily Markov) process and the errors  $\varepsilon_i$  are iid. I impose the Markov property (M) to obtain (relatively) closed-form expressions for E[f(x) | D] and Var(f(x) | D). I also allow for arbitrary (co)variances in the  $\varepsilon_i$ .

See Bishop (2006, p. 87) or DeGroot (2004, p. 55) for proofs of this lemma, and Appendix A for proofs of my other results.

Substituting  $z_1 = f(x)$  and  $z_2 = (y_1, y_2, ..., y_n)$  into (3) provides expressions for the moments of  $f(x) \mid D = z_1 \mid z_2$ . I refine these expressions by imposing properties (G) and (M).

Property (G) comes from  ${f(x)}_{x\geq 0}$  being a sample path of a Gaussian process.<sup>3</sup> This process can be characterized by

1. A mean function  $m : [0, \infty) \to \mathbb{R}$  with  $m(x) \equiv \mathbb{E}[f(x)]$  for all  $x \ge 0$ , and

2. A covariance function  $C : [0, \infty)^2 \to \mathbb{R}$  with  $C(x, x') \equiv \text{Cov}(f(x), f(x'))$  for all  $x, x' \ge 0$ .

For convenience, I define a variance function  $V : [0, \infty) \to \mathbb{R}$  by  $V(x) \equiv C(x, x)$  for all  $x \ge 0$ . The values of m(x), V(x), and C(x, x') are known for all  $x, x' \ge 0$ , but the values of f(x) are not.

Property (M) comes from  $\{f(x)\}_{x\geq 0}$  being a sample path of a Markov process. It allows me to focus on the conditional distribution of f(x) given at most two values  $f(x_i)$ : those with  $x_i$  closest to x. Lemma 2 characterizes this conditional distribution.

**Lemma 2.** Let  $\{f(x)\}_{x\geq 0}$  be a sample path of a Gauss-Markov process, let  $x, x', x'' \geq 0$  be arbitrary, and *define* 

$$w(x, x', x'') \equiv \frac{1}{V(x')V(x'') - C(x', x'')^2} \begin{bmatrix} C(x, x')V(x'') - C(x, x'')C(x', x'') \\ C(x, x'')V(x') - C(x, x')C(x', x'') \end{bmatrix}.$$
(4)

Then  $f(x) \mid f(x')$  is Gaussian with mean

$$E[f(x) \mid f(x')] = m(x) + \frac{C(x, x')}{V(x')}(f(x') - m(x'))$$
(5)

and variance

$$Var(f(x) \mid f(x')) = V(x) - \frac{C(x, x')^2}{V(x')},$$
(6)

and  $f(x) \mid f(x'), f(x'')$  is Gaussian with mean

$$\mathbf{E}[f(x) \mid f(x'), f(x')] = m(x) + w(x, x', x'')^T \begin{bmatrix} f(x') - m(x') \\ f(x'') - m(x'') \end{bmatrix}$$

and variance

$$\operatorname{Var}(f(x) \mid f(x'), f(x'')) = V(x) - w(x, x', x'')^T \begin{bmatrix} C(x, x') \\ C(x, x'') \end{bmatrix}$$

For example, suppose  $x_k \le x \le x_{k+1}$  for some k < n. Lemma 2 characterizes the distributions of  $f(x) | f(x_{k+1})$  and  $f(x) | f(x_k)$ ,  $f(x_{k+1})$  when the values of  $f(x_k)$  and  $f(x_{k+1})$  are known. However, variation in the errors  $\varepsilon_i$  makes the values of  $f(x_k)$  and  $f(x_{k+1})$  unknown. So the conditional

<sup>&</sup>lt;sup>3</sup>Gaussian processes are stochastic processes satisfying by property (G). For more information on these processes and their applications, see Section 6.4 of Bishop (2006) or Chapter 2 of Rasmussen and Williams (2006).

means of  $f(x) | f(x_{k+1})$  and  $f(x) | f(x_k), f(x_{k+1})$  given  $\mathcal{D}$  are random. But their conditional variances given  $\mathcal{D}$  are *not* random; by Lemma 2, these variances depend on only the known values of the variance function  $V : [0, \infty) \to \mathbb{R}$  and covariance function  $C : [0, \infty) \to \mathbb{R}$ .

## **3** Conditional moments of a Gauss-Markov process

Theorem 1 refines Lemma 1 by imposing properties (G) and (M). Specifically, it characterizes the mean and variance of  $f(x) \mid D$  when  $\{f(x)\}_{x \ge 0}$  is a sample path of an arbitrary Gauss-Markov process. These moments depend on the location of x relative to the points  $x_i$  at which D contains noisy observations  $y_i$  of  $f(x_i)$ .

**Theorem 1.** Let  $\{f(x)\}_{x\geq 0}$  be a sample path of a Gauss-Markov process. Suppose  $\mathcal{D} = \{(x_i, y_i)\}_{i=1}^n$  is generated by the process (1), where  $x_i \geq 0$  is non-decreasing in i and the errors  $\varepsilon_i = y_i - f(x_i)$  are jointly Gaussian with  $E[\varepsilon_i \mid x_1, x_2, ..., x_n] = 0$  independently of  $\{f(x)\}_{x\geq 0}$ . Then  $f(x) \mid \mathcal{D}$  is Gaussian for all  $x \geq 0$ . Moreover:

(*i*) If  $x \leq x_1$ , then

$$\mathbf{E}[f(x) \mid \mathcal{D}] = m(x) + \frac{C(x_1, x)}{V(x_1)} (\mathbf{E}[f(x_1) \mid \mathcal{D}] - m(x_1))$$

and

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \left(\frac{C(x_1, x)}{V(x_1)}\right)^2 \operatorname{Var}(f(x_1) \mid \mathcal{D}) + \operatorname{Var}(f(x) \mid f(x_1)).$$

(ii) If  $x_k \leq x \leq x_{k+1}$  for some k < n, then

$$\mathbf{E}[f(x) \mid \mathcal{D}] = m(x) + w(x, x_k, x_{k+1})^T \begin{bmatrix} \mathbf{E}[f(x_k) \mid \mathcal{D}] - m(x_k) \\ \mathbf{E}[f(x_{k+1}) \mid \mathcal{D}] - m(x_{k+1}) \end{bmatrix}$$

and

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = w(x, x_k, x_{k+1})^T \operatorname{Var}\left( \begin{bmatrix} f(x_k) \\ f(x_{k+1}) \end{bmatrix} \mid \mathcal{D} \right) w(x, x_k, x_{k+1}) + \operatorname{Var}(f(x) \mid f(x_k), f(x_{k+1}))$$

with  $w(x, x_k, x_{k+1})$  defined as in Lemma 2.

(iii) If  $x \ge x_n$ , then

$$\mathbf{E}[f(x) \mid \mathcal{D}] = m(x) + \frac{C(x_n, x)}{V(x_n)} (\mathbf{E}[f(x_n) \mid \mathcal{D}] - m(x_n))$$

and

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \left(\frac{C(x_n, x)}{V(x_n)}\right)^2 \operatorname{Var}(f(x_n) \mid \mathcal{D}) + \operatorname{Var}(f(x) \mid f(x_n)).$$

If  $x \le x_1$ , then the estimate  $\hat{f}_{\mathcal{D}}(x) \equiv \mathbb{E}[f(x) | \mathcal{D}]$  of f(x) is linear in the estimate  $\hat{f}_{\mathcal{D}}(x_1)$  of  $f(x_1)$ . Conversely, if  $x \ge x_n$ , then  $\hat{f}_{\mathcal{D}}(x)$  is linear in the estimate  $\hat{f}_{\mathcal{D}}(x_n)$  of  $f(x_n)$ . In both cases, we can construct  $\hat{f}_{\mathcal{D}}(x)$  in two steps:

- 1. Use  $\mathcal{D}$  to estimate the "boundary" values  $f(x_1)$  and  $f(x_n)$ ;
- 2. Extrapolate  $\hat{f}_{\mathcal{D}}(x)$  from the closest boundary estimate.

For example, suppose  $\mathcal{D} = \{(x_1, y_1)\}$  contains one observation  $y_1 = f(x_1) + \varepsilon_1$  with error  $\varepsilon_1 \sim \mathcal{N}(0, \sigma_{\varepsilon}^2)$ . Then

$$f(x_1) \mid \mathcal{D}_1 \sim \mathcal{N}\left(m(x_1) + \frac{V(x_1)}{V(x_1) + \sigma_{\varepsilon}^2}(y_1 - m(x_1)), \left(\frac{1}{V(x_1)} + \frac{1}{\sigma_{\varepsilon}^2}\right)^{-1}\right)$$

by Lemma 1, and so

$$\hat{f}_{\mathcal{D}}(x) = m(x) + \frac{C(x_1, x)}{V(x_1)} (E[f(x_1) \mid \mathcal{D}] - m(x_1))$$
  
=  $m(x) + \frac{C(x_1, x)}{V(x_1) + \sigma_{\varepsilon}^2} (y_1 - m(x_1))$ 

is linear in the deviation  $(y_1 - m(x_1))$  of  $y_1$  from its mean  $m(x_1)$ . Intuitively, this deviation provides information about the difference  $(f(x_1) - m(x_1))$ , which the factor  $C(x_1, x)/(V(x) + \sigma_{\varepsilon}^2)$  translates into information about the difference (f(x) - m(x)). This factor is larger when the covariance  $C(x_1, x)$  of  $y_1$  and f(x) is larger, and when the variance  $V(x) + \sigma_{\varepsilon}^2$  of  $y_1$  is smaller.

If n > 1 and  $x_1 \le x \le x_n$ , then we can construct  $\hat{f}_{\mathcal{D}}(x)$  in three steps:

- 1. Find an index k < n for which  $x_k \le x \le x_{k+1}$ ;
- 2. Use  $\mathcal{D}$  to estimate the values of  $f(x_k)$  and  $f(x_{k+1})$ ;
- 3. Interpolate  $\hat{f}_{\mathcal{D}}(x)$  from the estimates  $\hat{f}_{\mathcal{D}}(x_k)$  and  $\hat{f}_{\mathcal{D}}(x_{k+1})$ .

The interpolant  $\hat{f}_{\mathcal{D}}(x)$  is a weighted sum of the mean m(x), the deviation  $(\hat{f}_{\mathcal{D}}(x_k) - m(x_k))$ , and the deviation  $(\hat{f}_{\mathcal{D}}(x_{k+1}) - m(x_{k+1}))$ . The weights on the two deviations depend on the (co)variances of f(x),  $f(x_k)$ , and  $f(x_{k+1})$ , as well as the (co)variances of  $\varepsilon_k$  and  $\varepsilon_{k+1}$ .

Theorem 1 expresses the moments of  $f(x) \mid D$  in terms of the moments of the  $f(x_i) \mid D$ . The latter moments can be computed analytically if *n* is small (e.g., as in the case with n = 1 above), or numerically if *n* is large. The expressions in Theorem 1 reveal how changing the moments of the  $f(x_i) \mid D$  changes the moments of  $f(x) \mid D$ .

# 4 Conditional moments of a Brownian motion

I now consider a specific Gauss-Markov process: a Brownian motion with known drift  $\mu \in \mathbb{R}$  and scale  $\sigma \ge 0$ , and unknown initial value  $f(0) \sim \mathcal{N}(\mu_0, \sigma_0^2)$ .<sup>4</sup> This process has mean and covariance functions defined by

$$m(x) = \mu_0 + \mu x$$

and

$$C(x, x') = \sigma_0^2 + \sigma^2 \min\{x, x'\}$$

for all  $x, x' \ge 0.5$  Substituting these expressions into Theorem 1 yields the following result.

**Corollary 1.** Let  $\{f(x)\}_{x\geq 0}$  be a sample path of a Brownian motion with drift  $\mu \in \mathbb{R}$ , scale  $\sigma \geq 0$ , and initial value  $f(0) \sim \mathcal{N}(\mu_0, \sigma_0^2)$ . Define  $\mathcal{D} = \{(x_i, y_i)\}_{i=1}^n$  as in Theorem 1. Then  $f(x) \mid \mathcal{D}$  is Gaussian for all  $x \geq 0$ . Moreover:

(*i*) If  $x \leq x_1$ , then

$$E[f(x) \mid \mathcal{D}] = \mu_0 + \mu x + \frac{\sigma_0^2 + \sigma^2 x}{\sigma_0^2 + \sigma^2 x_1} (E[f(x_1) \mid \mathcal{D}] - \mu_0 - \mu x_1)$$

and

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \left(\frac{\sigma_0^2 + \sigma^2 x}{\sigma_0^2 + \sigma^2 x_1}\right)^2 \operatorname{Var}(f(x_1) \mid \mathcal{D}) + \left(\frac{\sigma_0^2 + \sigma^2 x}{\sigma_0^2 + \sigma^2 x_1}\right) \sigma^2 (x_1 - x).$$

(ii) If  $x_k \leq x \leq x_{k+1}$  for some k < n, then

$$E[f(x) \mid \mathcal{D}] = \frac{x_{k+1} - x_k}{x_{k+1} - x_k} E[f(x_k) \mid \mathcal{D}] + \frac{x - x_k}{x_{k+1} - x_k} E[f(x_{k+1}) \mid \mathcal{D}]$$

and

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \frac{1}{(x_{k+1} - x_k)^2} \begin{bmatrix} x_{k+1} - x \\ x - x_k \end{bmatrix}^T \operatorname{Var}\left( \begin{bmatrix} f(x_k) \\ f(x_{k+1}) \end{bmatrix} \mid \mathcal{D} \right) \begin{bmatrix} x_{k+1} - x \\ x - x_k \end{bmatrix} + \frac{\sigma^2 (x_{k+1} - x)(x - x_k)}{x_{k+1} - x_k}.$$

<sup>4</sup>So the sample path  $\{f(x)\}_{x\geq 0}$  solves the stochastic differential equation

$$\mathrm{d}f(x) = \mu\,\mathrm{d}x + \sigma\,\mathrm{d}W(x),$$

where  $\{W(x)\}_{x\geq 0}$  is an unknown sample path of a (standard) Wiener process. This process has initial value W(0) = 0 and iid Gaussian increments  $dW(x) \equiv W(x + dx) - W(x) \sim \mathcal{N}(0, dx)$ .

<sup>5</sup>Thus  $V(x) = \sigma_0^2 + \sigma^2 x$  for all  $x \ge 0$ .



Figure 1: Learning about a Brownian motion from noisy and noise-free observations

*Notes*: Red lines show sample path  $\{f(x)\}_{x\geq 0}$  of Brownian motion with drift  $\mu = 0$ , scale  $\sigma = 1$ , and initial value f(0) = 0. Black dots represent observations  $(x_i, y_i)$  with  $x_i = 2^{i-1}$  and  $y_i = f(x_i) + \varepsilon_i$ . Black lines represent estimates  $\hat{f}_{\mathcal{D}}(x)$  of f(x) when  $\mathcal{D} = \{(x_i, y_i)\}_{i=1}^4$ . Gray regions represent 90% confidence intervals, constructed analytically from the conditional variances defined in Corollary 1. Left panel has  $\varepsilon_i \sim \mathcal{N}(0, 1)$  iid; right panel has  $\varepsilon_i = 0$  for each *i*.

(iii) If  $x \ge x_n$ , then

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \operatorname{Var}(f(x_n) \mid \mathcal{D}) + \sigma^2(x - x_n).$$

 $\mathbf{E}[f(x) \mid \mathcal{D}] = \mathbf{E}[f(x_n) \mid \mathcal{D}] + \mu(x - x_n)$ 

If  $\{f(x)\}_{x\geq 0}$  is a sample path of a Brownian motion, then the estimate  $\hat{f}_{\mathcal{D}}(x) \equiv \mathbb{E}[f(x) | \mathcal{D}]$ of f(x) is piecewise linear in  $x \geq 0$ . For example, consider the canonical case in which the initial value  $f(0) = \mu_0$  is known. As *x* increases from zero, the estimate

$$\hat{f}_{\mathcal{D}}(x) = \begin{cases} \mu_0 + \frac{x}{x_1} \left( \hat{f}_{\mathcal{D}}(x_1) - \mu_0 \right) & \text{if } x < x_1 \\ \hat{f}_{\mathcal{D}}(x_k) + \frac{x - x_k}{x_{k+1} - x_k} \left( \hat{f}_{\mathcal{D}}(x_{k+1}) - \hat{f}_{\mathcal{D}}(x_k) \right) & \text{if } x_k \le x < x_{k+1} \text{ for some } k < n \\ \hat{f}_{\mathcal{D}}(x_n) + \mu(x - x_n) & \text{otherwise} \end{cases}$$

interpolates linearly between  $(0, \mu_0)$  and  $(x_1, \hat{f}_D(x_1))$ , then between  $(x_1, \hat{f}_D(x_1))$  and  $(x_2, \hat{f}_D(x_2))$ , then between  $(x_2, \hat{f}_D(x_2))$  and  $(x_3, \hat{f}_D(x_3))$ , and so on until  $(x_n, \hat{f}_D(x_n))$ . Beyond this point, the data  $\mathcal{D}$  provide no information about f(x). Consequently, the estimate  $\hat{f}_D(x)$  treats  $\{f(x)\}_{x \ge x_n}$  as a Brownian motion with drift  $\mu$ , scale  $\sigma$ , and (possibly random) initial value  $\hat{f}_D(x_n)$ .

I illustrate this behavior in Figure 1. It shows how  $\hat{f}_{\mathcal{D}}(x)$  varies with  $x \ge 0$  when  $(\mu_0, \mu, \sigma_0, \sigma) = (0, 0, 0, 1)$  and the data contain n = 4 observations with iid errors. Figure 1 also shows the 90%

confidence interval around  $\hat{f}_{\mathcal{D}}(x)$ , constructed analytically from the conditional variances defined in Corollary 1. This interval expands as *x* moves away from the sampled points  $x_i$ .<sup>6</sup>

Suppose the data are *not* noisy (i.e.,  $\varepsilon_i = 0$  for each *i*) and  $x_k \le x \le x_{k+1}$  for some k < n. Then the distribution of  $f(x) \mid \mathcal{D}$  coincides with the distribution obtained by assuming  $\{f(x)\}_{x_k \le x \le x_{k+1}}$ is a sample path of a Brownian bridge with scale  $\sigma$ , known initial value  $f(x_k)$ , and known terminal value  $f(x_{k+1})$ .<sup>7</sup> Corollary 1(ii) generalizes to Brownian bridges with *unknown* initial and terminal values. For example, suppose  $x_1 \le x \le x_2$  and that

$$\begin{bmatrix} f(x_1) \\ f(x_2) \end{bmatrix} \mid \mathcal{D} \sim \mathcal{N}\left( \begin{bmatrix} \mu_1 \\ \mu_2 \end{bmatrix}, \begin{bmatrix} \sigma_1^2 & \rho\sigma_1\sigma_2 \\ \rho\sigma_1\sigma_2 & \sigma_2^2 \end{bmatrix} \right)$$

for some means  $\mu_1, \mu_2 \in \mathbb{R}$ , variances  $\sigma_1^2, \sigma_2^2 \ge 0$ , and correlation  $\rho \in [-1, 1]$ . Then  $f(x) \mid \mathcal{D}$  has mean

$$\mathsf{E}[f(x) \mid \mathcal{D}] = \mu_1 + \frac{x - x_1}{x_2 - x_1}(\mu_2 - \mu_1)$$

and variance

$$\operatorname{Var}(f(x) \mid \mathcal{D}) = \frac{(1-x)^2 \sigma_1^2 + 2x(1-x)\rho \sigma_1 \sigma_2 + x^2 \sigma_2^2}{(x_2 - x_1)^2} + \frac{\sigma^2 (x_2 - x)(x - x_1)}{x_2 - x_1}$$

Choosing  $\sigma_1 = 0$  and  $\sigma_2 = 0$  yields the mean and variance for the Brownian bridge on  $[x_1, x_2]$  with  $f(x_1) = \mu_1$  and  $f(x_2) = \mu_2$ .

# References

Bardhi, A. (2024). Attributes: Selective Learning and Influence. Econometrica, 92(2):311-353.

Bishop, C. M. (2006). Pattern recognition and machine learning. Springer, New York.

Callander, S. (2011). Searching and Learning by Trial and Error. *American Economic Review*, 101(6):2277–2308.

Carnehl, C. and Schneider, J. (2023). A Quest for Knowledge.

Davies, B. (2024). Learning about a changing state.

DeGroot, M. H. (2004). Optimal Statistical Decisions. Wiley, first edition.

Karatzas, I. and Shreve, S. E. (1988). *Brownian Motion and Stochastic Calculus*, volume 113 of *Graduate Texts in Mathematics*. Springer New York, New York, NY.

Rasmussen, C. E. and Williams, C. K. I. (2006). *Gaussian processes for machine learning*. MIT Press, Cambridge, MA.

<sup>6</sup>If f(0) is known (i.e.,  $\sigma_0^2 = 0$ ) and the observations  $y_i$  have no noise (i.e.,  $\varepsilon_i = 0$  for each *i*), then the MSE

$$\mathbf{E}\left[\left(f(x) - \hat{f}_{\mathcal{D}}(x)\right)^2 \mid \mathcal{D}\right] = \sigma^2 \begin{cases} \frac{x(x_1 - x)}{x_1} & \text{if } x < x_1\\ \frac{(x_{k+1} - x)(x - x_k)}{x_{k+1} - x_k} & \text{if } x_k \le x < x_{k+1} \text{ for some } k < n\\ x - x_n & \text{otherwise} \end{cases}$$

attains its piecewise maxima at the midpoint of each piece.

<sup>7</sup>See, e.g., Section 5.6.B of Karatzas and Shreve (1988) for more information about Brownian bridges.

# **A Proofs**

*Proof of Lemma* 2. Now f(x), f(x'), and f(x'') are jointly Gaussian by property (G). Therefore, by Lemma 1, both f(x) | f(x') and f(x) | f(x'), f(x'') are (univariate) Gaussian. Choosing  $z_1 = f(x)$  and  $z_2 = f(x')$  in the statement of Lemma 1 yields (5) and (6), while choosing  $z_2 = (f(x'), f(x''))$  yields

$$E[f(x) | f(x'), f(x')] = m(x) + \begin{bmatrix} C(x, x') \\ C(x, x'') \end{bmatrix}^T \begin{bmatrix} V(x') & C(x', x'') \\ C(x', x'') & V(x'') \end{bmatrix}^{-1} \begin{bmatrix} f(x') - m(x') \\ f(x'') - m(x'') \end{bmatrix}$$
$$= m(x) + w(x, x', x'')^T \begin{bmatrix} f(x') - m(x') \\ f(x'') - m(x'') \end{bmatrix}$$

and

$$\begin{aligned} \operatorname{Var}(f(x) \mid f(x'), f(x')) &= V(x) - \begin{bmatrix} C(x, x') \\ C(x, x'') \end{bmatrix}^T \begin{bmatrix} V(x') & C(x', x'') \\ C(x', x'') & V(x'') \end{bmatrix}^{-1} \begin{bmatrix} C(x, x') \\ C(x, x'') \end{bmatrix} \\ &= V(x) - w(x, x', x'')^T \begin{bmatrix} C(x, x') \\ C(x, x'') \end{bmatrix}. \end{aligned}$$

*Proof of Theorem 1.* The  $y_i = f(x_i) + \varepsilon_i$  are sums of (jointly) Gaussian random variables, so they are also jointly Gaussian. Thus  $(y_1, y_2, ..., y_n, f(x))$  is multivariate Gaussian. It follows from Lemma 1 that  $f(x) \mid \mathcal{D} = f(x) \mid (y_1, y_2, ..., y_n)$  is (univariate) Gaussian.

By property (M) and the errors' independence of  $\{f(x)\}_{x\geq 0}$ , we know f(x) is conditionally independent of  $\mathcal{D}$  given the values  $f(x_i)$  with  $x_i$  closest to x. I use this fact to prove cases (i)–(iii):

(i) Suppose  $x \le x_1$ . Then f(x) is conditionally independent of  $\mathcal{D}$  given  $f(x_1)$ . Thus

$$E[f(x) \mid \mathcal{D}] \stackrel{\star}{=} E[E[f(x) \mid \mathcal{D}_n, f(x_1)] \mid \mathcal{D}]$$
  
=  $E[E[f(x) \mid f(x_1)] \mid \mathcal{D}]$   
$$\stackrel{\star \star}{=} E\left[m(x) + \frac{C(x_1, x)}{V(x_1)}(f(x_1) - m(x_1)) \mid \mathcal{D}\right]$$
  
=  $m(x) + \frac{C(x_1, x)}{V(x_1)}(E[f(x_1) \mid \mathcal{D}] - m(x_1)),$ 

where \* holds by the law of total expectation and \*\* holds by Lemma 2. Likewise

$$\begin{aligned} \operatorname{Var}(f(x) \mid \mathcal{D}) &\stackrel{\star}{=} \operatorname{Var}(\operatorname{E}[f(x) \mid \mathcal{D}, f(x_1)] \mid \mathcal{D}) + \operatorname{E}[\operatorname{Var}(f(x) \mid \mathcal{D}, f(x_1)) \mid \mathcal{D}] \\ &= \operatorname{Var}(\operatorname{E}[f(x) \mid f(x_1)] \mid \mathcal{D}) + \operatorname{E}[\operatorname{Var}(f(x) \mid f(x_1)) \mid \mathcal{D}] \\ &\stackrel{\star \star}{=} \operatorname{Var}\left(m(x) + \frac{C(x_1, x)}{V(x_1)}(f(x_1) - m(x_1)) \mid \mathcal{D}\right) + \operatorname{Var}(f(x) \mid f(x_1)) \\ &= \left(\frac{C(x_1, x)}{V(x_1)}\right)^2 \operatorname{Var}(f(x_1) \mid \mathcal{D}) + \operatorname{Var}(f(x) \mid f(x_1)), \end{aligned}$$

where  $\star$  holds by the law of total variance and  $\star\star$  holds by Lemma 2.

(ii) Now suppose  $x_k \le x \le x_{k+1}$  for some k < n. Then f(x) is conditionally independent of  $\mathcal{D}$  given  $f(x_k)$  and  $f(x_{k+1})$ . Thus

$$\begin{split} \mathbf{E}[f(x) \mid \mathcal{D}] &\stackrel{\star}{=} \mathbf{E}[\mathbf{E}[f(x) \mid \mathcal{D}_{n}, f(x_{k}), f(x_{k+1})] \mid \mathcal{D}] \\ &= \mathbf{E}[\mathbf{E}[f(x) \mid f(x_{k}), f(x_{k+1})] \mid \mathcal{D}] \\ &\stackrel{\star\star}{=} \mathbf{E}\left[m(x) + w(x, x_{k}, x_{k+1})^{T} \begin{bmatrix} f(x_{k}) - m(x_{k}) \\ f(x_{k+1}) - m(x_{k+1}) \end{bmatrix} \mid \mathcal{D} \end{bmatrix} \\ &= m(x) + w(x, x_{k}, x_{k+1})^{T} \begin{bmatrix} \mathbf{E}[f(x_{k}) \mid \mathcal{D}] - m(x_{k}) \\ \mathbf{E}[f(x_{k+1}) \mid \mathcal{D}] - m(x_{k+1}) \end{bmatrix}, \end{split}$$

where  $\star$  holds by the law of total expectation and  $\star\star$  holds by Lemma 2. Likewise

$$\begin{aligned} \operatorname{Var}(f(x) \mid \mathcal{D}) &\stackrel{\star}{=} \operatorname{Var}(\operatorname{E}[f(x) \mid \mathcal{D}, f(x_k), f(x_{k+1})] \mid \mathcal{D}) + \operatorname{E}[\operatorname{Var}(f(x) \mid \mathcal{D}, f(x_k), f(x_{k+1})) \mid \mathcal{D}] \\ &= \operatorname{Var}(\operatorname{E}[f(x) \mid f(x_k), f(x_{k+1})] \mid \mathcal{D}) + \operatorname{Var}(f(x) \mid f(x_k), f(x_{k+1})) \\ &\stackrel{\star}{=} \operatorname{Var}\left(m(x) + w(x, x', x'')^T \begin{bmatrix} f(x') - m(x') \\ f(x'') - m(x'') \end{bmatrix} \mid \mathcal{D} \right) \\ &+ \operatorname{Var}(f(x) \mid f(x_k), f(x_{k+1})) \\ &= w(x, x_k, x_{k+1})^T \operatorname{Var}\left( \begin{bmatrix} f(x_k) \\ f(x_{k+1}) \end{bmatrix} \mid \mathcal{D} \right) w(x, x_k, x_{k+1}) \\ &+ \operatorname{Var}(f(x) \mid f(x_k), f(x_{k+1})), \end{aligned}$$

where  $\star$  holds by the law of total variance and  $\star\star$  holds by Lemma 2.

(iii) Finally, suppose  $x \ge x_n$ . Then f(x) is conditionally independent of  $\mathcal{D}$  given  $f(x_n)$ . The result follows from similar arguments used to prove case (i).

*Proof of Corollary* 1. The Brownian motion is a Gauss-Markov process, so  $f(x) \mid D$  is Gaussian by Theorem 1. We can also use that theorem to prove cases (i)–(iii).

Consider cases (i) and (iii). By Lemma 2 and the definitions of *m* and *C*, we have

$$\begin{aligned} \operatorname{Var}(f(x) \mid f(x')) &= \sigma_0^2 + \sigma^2 x - \frac{(\sigma_0^2 + \sigma^2 \min\{x, x'\})^2}{\sigma_0^2 + \sigma^2 x'} \\ &= \frac{\sigma_0^2 \sigma^2 (x + x' - 2\min\{x, x'\}) + \sigma^4 (xx' - \min\{x, x'\}^2)}{\sigma_0^2 + \sigma^2 x'} \\ &= \frac{\sigma_0^2 \sigma^2 |x - x'| + \sigma^4 \min\{x, x'\} |x - x'|}{\sigma_0^2 + \sigma^2 x'} \\ &= \left(\frac{\sigma_0^2 + \sigma^2 \min\{x, x'\}}{\sigma_0^2 + \sigma^2 x'}\right) \sigma^2 |x - x'| \\ &= \sigma^2 |x - x'| \begin{cases} \frac{\sigma_0^2 + \sigma^2 x}{\sigma_0^2 + \sigma^2 x'} & \text{if } x \le x' \\ 1 & \text{otherwise} \end{cases} \end{aligned}$$
(7)

for all  $x' \ge 0$ . Cases (i) and (iii) follow from substituting (7), along the definitions of *m* and *C*, into the statement of Theorem 1.

Now consider case (ii). Define  $w(x, x_k, x_{k+1})$  as in Lemma 2. If  $x_k \le x \le x_{k+1}$ , then

$$w(x, x_k, x_{k+1}) \equiv \frac{1}{V(x_k)V(x_{k+1}) - C(x_k, x_{k+1})^2} \begin{bmatrix} C(x, x_k)V(x_{k+1}) - C(x, x_{k+1})C(x_k, x_{k+1}) \\ C(x, x_{k+1})V(x_k) - C(x, x_k)C(x_k, x_{k+1}) \end{bmatrix}$$
$$= \frac{1}{V(x_k)V(x_{k+1}) - V(x_k)^2} \begin{bmatrix} V(x_k)V(x_{k+1}) - V(x)V(x_k) \\ V(x)V(x_k) - V(x_k)V(x_k) \end{bmatrix}$$
$$= \frac{1}{x_{k+1} - x_k} \begin{bmatrix} x_{k+1} - x \\ x - x_k \end{bmatrix}$$

because  $C(x', x'') = V(\min\{x', x''\})$  for all  $x', x'' \ge 0$  by the definitions of *C* and *V*. So

$$w^{T} \begin{bmatrix} \mathbf{E}[f(x_{k}) \mid \mathcal{D}] - m(x_{k}) \\ \mathbf{E}[f(x_{k+1}) \mid \mathcal{D}] - m(x_{k+1}) \end{bmatrix}$$
  
=  $\frac{1}{x_{k+1} - x_{k}} \begin{bmatrix} x_{k+1} - x \\ x - x_{k} \end{bmatrix}^{T} \begin{bmatrix} \mathbf{E}[f(x_{k}) \mid \mathcal{D}] \\ \mathbf{E}[f(x_{k+1}) \mid \mathcal{D}] \end{bmatrix} - \frac{1}{x_{k+1} - x_{k}} \begin{bmatrix} x_{k+1} - x \\ x - x_{k} \end{bmatrix}^{T} \begin{bmatrix} \mu_{0} + \mu x_{k} \\ \mu_{0} + \mu x_{k+1} \end{bmatrix}$   
=  $\frac{(x_{k+1} - x) \mathbf{E}[f(x_{k}) \mid \mathcal{D}] + (x - x_{k}) \mathbf{E}[f(x_{k+1}) \mid \mathcal{D}]}{x_{k+1} - x_{k}} - \mu_{0} - \mu x$ 

by the definition of *m*, and

$$\begin{aligned} \operatorname{Var}(f(x) \mid f(x_k), f(x_{k+1})) &= V(x) - w(x, x_k, x_{k+1})^T \begin{bmatrix} C(x, x_k) \\ C(x, x_{k+1}) \end{bmatrix} \\ &= \sigma_0^2 + \sigma^2 x - \frac{1}{x_{k+1} - x_k} \begin{bmatrix} x_{k+1} - x \\ x - x_k \end{bmatrix}^T \begin{bmatrix} \sigma_0^2 + \sigma^2 x_k \\ \sigma_0^2 + \sigma^2 x \end{bmatrix} \\ &= \frac{\sigma^2 (x_{k+1} - x) (x - x_k)}{x_{k+1} - x_k} \end{aligned}$$

by Lemma 2. The result follows from Theorem 1(ii).