

# A LINEAR-QUADRATIC PARTIALLY OBSERVED STACKELBERG STOCHASTIC DIFFERENTIAL GAME WITH MULTIPLE FOLLOWERS AND ITS APPLICATION TO MULTI-AGENT FORMATION CONTROL

YICHUN LI, JINGTAO SHI, AND YUEYANG ZHENG

**ABSTRACT.** In this paper, we study a linear-quadratic partially observed Stackelberg stochastic differential game problem in which a single leader and multiple followers are involved. We consider more practical formulation for partial information that none of them can observe the complete information and the followers know more than the leader. Some completely different methods including orthogonal decomposition are applied to overcome the difficulties caused by partially observability which improves the tools and relaxes the constraint condition imposed on admissible control in the existing literature. More precisely, the followers encounter the standard linear-quadratic partially observed optimal control problems, however, a kind of forward-backward indefinite linear-quadratic partially observed optimal control problem is considered by the leader. Instead of maximum principle of forward-backward control systems, inspired by the existing work related to definite case and classical forward control system, some distinct forward-backward linear-quadratic decoupling techniques including the completing the square technique are applied to solve the leader's problem. More interestingly, we develop the deterministic formation control in multi-agent system with a framework of Stackelberg differential game and extend it to the stochastic case. The optimal strategies are obtained by our theoretical result suitably.

## 1. INTRODUCTION

Inspired by some natural phenomenon appearing in the swarming behavior of living beings, such as flocks of birds, schools of fish, colonies of bacteria and herds of wildebeest, the introduction of formation control of multi-agent systems gives a corresponding theoretical characteristic. The studies of formation control now becomes a hot frontier research topic because of its widespread applications to mobile robots, satellite control, unmanned surface vessels and unmanned aerial vehicles. Therefore, the aim of formation control is to design a controller to drive all the agents to maintain the formation along the desired trajectories. For solving the formation control, there are now several approaches such as behavior-based approach, virtual-structure approach, leader-follower approach, consensus and optimal control and differential game. However, it is worth noting that most of investigations are related to the deterministic formation control in which only deterministic differential game approaches are applied. As far as we know, there is little literature that

---

Y. Li is supported by the China Postdoctoral Science Foundation (2024M750904).

J. Shi is supported by National Key R&D Program of China (2022YFA1006104), National Natural Science Foundations of China (12471419, 12271304), and Shandong Provincial Natural Science Foundations (ZR2024ZD35, ZR2022JQ01).

Y. Zheng is supported by National Natural Science Foundations of China (12401577), the Postdoctoral Fellowship Program (Grade B) of China Postdoctoral Science Foundation (GZB20230168), and the China Postdoctoral Science Foundation (2024M750488).

studies the stochastic case where necessary probability theories closed to forward backward stochastic differential equations (FBSDEs for short) are the key to model the stochastic framework of formation control. Meanwhile, the stochastic characteristic in Stackelberg differential game shows the mutual feedback between leader and follower. Therefore, instead of Nash differential game approach, the Stackelberg game including leader-follower mechanism is adapted to formation control well when consider one of the agent leading the formation direction and tracking the desired trajectory as the leader while other agents keeping the formation by following the leader with a fixed distance as the followers when they can exchange information such as relative positions and velocities in order to maintain a formation.

The Stackelberg game, also known as the leader-follower game, was introduced firstly by Stackelberg [30] where its hierarchical feature was first shown under the economic background that certain companies have advantages of domination over others in some markets environment. In the classical Stackelberg game, two agents played by asymmetric roles are usually considered in which the leader claims his strategy in advance, and the follower, considering the given leader's strategy, makes an instantaneous reaction (that can be regarded as a map from or feedback to the leader's control) by optimizing his cost functional. Then the leader would like to choose an optimal strategy to optimize his cost functional by taking the rational response of the follower into account. Since its meaningful structure and background, the leader-follower's feature mainly plays an important role in many aspects, such as principle-agent problems [4], newsvendor/wholesaler problems [26], optimal reinsurance problems [3] and operations management and marketing channel problems [13]. Now in our paper, the stochastic Stackelberg differential game can be applied in the formation control problems where the uncertainties coming from Brownian motions are considered and the stochastic model is studied in the martingale's environment.

When it comes to the Stackelberg game in the past decades, there have been a great deal of significant works among which we only mention a few closely related. In the stochastic case, Yong [38] studied an indefinite linear quadratic (LQ for short) Stackelberg differential game with random coefficients and control-dependent diffusion, where FBSDEs and Riccati equations are applied to obtain the state feedback representation of open-loop Stackelberg equilibrium. Since then, Stackelberg differential games has been studied extensively in the literature such as in the fields of mean-field [6, 9, 17, 23], delay [37, 20], jump [22] and regime switching [21, 19]. In terms of the agents' different information sets, Bensoussan et al. [2] introduced several solution concepts, and obtained the maximum principle for the leader's problem under the adapted closed-loop memoryless information structure. Li and Yu [11] studied the solvabilities of coupled FBSDEs with a multilevel self-similar domination-monotonicity structure which was applied to solve a LQ generalized multilevel hierarchical Stackelberg differential game and characterize its corresponding equilibrium in a closed form. Then it was extended to the jump-diffusion [12] and time-delay systems [10].

Different from the complete information background in previous literature, some of the agents with asymmetry of roles in reality can only get the partial information usually due to the delay in information transmission, inequality in market competition, private information in different class and limitation policy by the government. In particular, the major difficulty in the formation control problem shows that each agent is only able to exchange information with other agents according to the communication topology, which means the constrained information limits many game strategy design approaches that usually consider individual agents to have global information. In this case, the formation control

problem would be formulated in such a way that individual agents try to minimize their partially observed formation errors and to solve it from a stochastic Stackelberg differential game theory point of view. Based on the above analysis, therefore, the partially observed setting matches the leader-follower feature well, such problems have aroused intense interest [28, 39], and there are also lots of works on this issue. Li et al. [14] investigated the LQ Gaussian Stackelberg game under a class of nested observation information, where the follower only use the observation data to design its strategy but the leader use the global observation data. Very recently, Wang and Wang [32] studied a partially observed LQ stochastic Stackelberg game with two followers where both of followers can not observe the state process but leader can know the full information. Then Si and Shi [29] studied an overlapping information LQ Stackelberg stochastic differential game with two leaders and two followers in which the noisy information available to the leaders and the followers may be asymmetric and have overlapping part. Especially, in the recent work [39], based on the classical state decomposition technique [1] and backward separation principle developed in the partially observed control problem [33, 34], a kind of partially observed LQ Stackelberg game theory was investigated and was applied to a practical dynamic advertising problem. However, the conditions satisfied by control process are relatively strong and not natural enough in [39]. Moreover, the stochastic LQ optimal control of fully coupled FBSDEs would be encountered by the leader in most of the Stackelberg literature in which the maximum principle is the main tool to obtain the maximum condition satisfied by optimal control, then get the optimal state feedback by decoupling the Hamiltonian system. Few work considers solving the fully coupled forward backward stochastic LQ optimal control by the completion of squares methods but the recent work studied by [8], and there is no any result on the counterpart with partially observable information.

The stochastic Stackelberg differential game theory mentioned in the above literature are mostly applied to investigate in the fields of mathematical finance, management science and economy, but relatively few literature consider the multi-agent formation control such as unmanned aerial vehicle, robots and aircraft carrier formation corrupted by stochastic noise such as Brownian motion, in which the dynamic system is described by stochastic differential equations (SDEs for short) or FBSDEs instead of deterministic model. Different from the deterministic formation control, we introduce the notion of partially observed stochastic formation control whose acquirement need more probability and stochastic analysis technique, on one hand, the observation equation should be introduced and the formation control becomes a stochastic process adapted to the information filtration generated by observable process; On the other hand, stochastic filtering theory and solvability of stochastic Hamiltonian systems are necessary, which add more difficulties than the deterministic case.

Therefore, the main contributions of our work in this paper can be summarized as follows.

- (i) A class of partially observed stochastic LQ Stackelberg differential game problem is investigated, where one leader and  $N$  followers constitute a group of  $N + 1$  agents all of whom can only have access to noisy observation process related to the state. Motivated by a class of formation control, a distinguished partially observable setting that the leader knows less than the followers is considered in our paper.
- (ii) In the existing literature, the state decomposition technique and backward separation principle has been widely applied to solve the partially observed LQ optimal

control of SDEs and FBSDEs and plenty of excellent works are obtained. Motivated by the idea in [31], we utilize the orthogonal decomposition technique of the state process to divide the original cost functional into two sub-cost functionals: one is the functional of control processes and filtering processes which can be regarded as the completely observed classical optimal control problem and another is independent of control process. In the new procedure studied in the leader's problem, as far as we know, it is first time that we make an extension to the fully coupled forward backward stochastic systems by applying the technique to the forward and backward state process. Therefore, we relax the limitation imposed on the control process that strong double-adapted conditions for breaking the circular dependence between the controlled filtration and control process have to be satisfied. Distinguished with the state decomposition technique which divides the state equation into a controlled equation and uncontrolled equation, actually the core is to introduce a sub-filtration independent of control to overcome the loop. However, orthogonal decomposition idea used in our paper mainly focus on the separation of cost functional instead of filtration, the core is to first obtain the filtering equation for any fixed control, then determining the optimal control by the completion of squares method in the transformed completed observable case.

- (iii) For the leader's problem, instead of applying maximum principle to get a candidate control, we initially study the indefinite partially observed LQ optimal control of fully coupled FBSDEs with the new methods combining with completion of squares method, idea of four-step scheme and dimension-enlargement motivated by [8] which is further extended by us to the multi-dimensional case with inhomogeneous terms.
- (iv) Besides the difference of methods from that applied in [39], the multi-agent formation control is investigated in the stochastic case for the first time, where the leader and followers play a asymmetrical Stackelberg game and Nash game are played among these finite followers with symmetrical roles. Moreover, there exists some deterministic Stackelberg differential game approach to formation control, but in our work, we add the partially observation element into the background to characterize the asymmetry of leader-follower structure, so the partially observed stochastic formation control is closed to the stochastic filtering theory of FBSDEs. We obtain the optimal state filtering feedback form of Stackelberg equilibrium.

The rest of the article is organized as follows. Section 2 presents some preliminaries and formulates the partially observed LQ stochastic Stackelberg differential game with  $N$  followers. A LQ partially observed optimal control of the follower's problem is studied, the filtering equation of forward state is derived, then the optimal state filtering feedback forms of the followers' optimal control and optimal cost are obtained by introducing two Riccati equations and two backward stochastic differential equations (BSDEs for short) in Section 3. In Section 4, we investigate an indefinite LQ partially observed optimal control of fully coupled FBSDEs with conditional mean field terms, where the forward backward stochastic filtering equation is first obtained, then we complete the leader's problem by introducing a series of ordinary differential equations (ODEs for short), Riccati equations and BSDEs and we get the optimal state filtering feedback form of optimal control and it corresponding optimal cost. In Section 5, for an application, we consider a class of multi-agent formation control problem and extend it into the stochastic case, then it can be solved by the obtained partially observed Stackelberg game approach. Section 6 concludes

the paper. In the Appendix, we investigate an LQ optimal control theory of fully coupled FBSDEs for the multi-dimensional case with inhomogeneous terms.

## 2. PROBLEM FORMULATION

Let  $(\Omega, \mathcal{F}, \mathbb{P})$  be a complete probability space on which two standard  $l_1$ -dimensional and  $l_2$ -dimensional Brownian motions  $W^1 = (W_t^{1,1}, W_t^{1,2}, \dots, W_t^{1,l_1})_{0 \leq t \leq T}^\top$  and  $W^2 = (W_t^{2,1}, W_t^{2,2}, \dots, W_t^{2,l_2})_{0 \leq t \leq T}^\top$  are defined. Assume that  $\mathbb{F} = \{\mathcal{F}_t, 0 \leq t \leq T\}$  is the  $\mathbb{P}$ -augmentation of the natural filtration of  $W^1, W^2$ , where  $\mathcal{F}_0$  contains all  $\mathbb{P}$ -null sets of  $\mathcal{F}$ . Denote by  $\mathbb{R}^n$  the  $n$ -dimensional real Euclidean space, and let  $\mathbb{R}^{n \times m}$  be the set of  $n \times m$  real matrixes. Let  $\langle \cdot, \cdot \rangle$  (respectively,  $|\cdot|$ ) denote the usual scalar product (respectively, usual norm) of  $\mathbb{R}^n$  and  $\mathbb{R}^{n \times m}$ . The scalar product (respectively, norm) of matrices  $M = (m_{ij}), N = (n_{ij}) \in \mathbb{R}^{n \times m}$  is denoted by  $\langle M, N \rangle = \text{Tr}\{MN^\top\}$  (respectively,  $\|M\| = \sqrt{MM^\top}$ ), where the superscript  $\top$  denotes the transpose of vectors or matrices.

We introduce the following spaces. We denote by  $\mathcal{S}^n$  all  $n \times n$  symmetric matrices, by  $\mathcal{S}_+^n$  the subspace of all nonnegative definite matrices of  $\mathcal{S}^n$ , by  $\mathcal{S}_-^n$  the subspace of all negative definite matrices of  $\mathcal{S}^n$ , by  $L^\infty(0, T; \mathbb{R}^{n \times m})$  the space of essential bounded measurable  $\mathbb{R}^{n \times m}$ -valued functions.

We consider the following multi-dimensional state equation of the leader and the followers:

$$\begin{cases} dX_t^{u_1, u_2} = [A(t)X_t^{u_1, u_2} + B_1^\top(t)u_1(t) + B_2(t)u_2(t) + \alpha_t]dt + C_1(t)dW_t^1 + C_2(t)dW_t^2, \\ X_0 = x_0, \end{cases} \quad (2.1)$$

where for  $t \in [0, T]$ ,  $X_t \in \mathbb{R}^n, A(t) \in \mathbb{R}^{n \times n}$ . And we denote  $u_1 = (u_{11}, u_{12}, \dots, u_{1N})^\top \in \mathbb{R}^{Nm}$  with  $u_{1i} \in \mathbb{R}^m$  for  $i = 1, \dots, N$ ,  $B_1 = (B_{11}^\top, B_{12}^\top, \dots, B_{1N}^\top)^\top$  with  $B_{1i} \in \mathbb{R}^{n \times m}$  for  $i = 1, \dots, N$ ,  $B_1^\top(t)u_1(t) = \sum_{i=1}^N B_{1i}(t)u_{1i}(t)$ ,  $B_2(t) \in \mathbb{R}^{n \times m}, \alpha(t) \in \mathbb{R}^n, C_1(t) \in \mathbb{R}^{n \times l_1}, C_2(t) \in \mathbb{R}^{n \times l_2}$ , and  $W_t^1, W_t^2$  are both  $\mathbb{R}^{l_1}$  and  $\mathbb{R}^{l_2}$ -valued mutually independent Brownian motions with independent components.

We suppose that the followers and the leader can not observe the above process  $X$ , instead, the only observed processes by them are described as follows, respectively:

$$\begin{aligned} dY_1^{u_1, u_2}(t) &= [f_1(t)X_t^{u_1, u_2} + g_1(t)]dt + K_1(t)dW_t^1, \\ dY_2^{u_1, u_2}(t) &= [f_2(t)X_t^{u_1, u_2} + g_2(t)]dt + K_2(t)dW_t^2, \end{aligned} \quad (2.2)$$

where we assume the processes observed by all the followers are the same, i.e.,  $Y_{1i}^{u_1, u_2} = Y_1^{u_1, u_2} \in \mathbb{R}^{l_1}, f_{1i} = f_1 \in \mathbb{R}^{l_1 \times n}, g_{1i} = g_1 \in \mathbb{R}^{l_1}, K_{1i} = K_1 \in \mathbb{R}^{l_1 \times l_1}$  for  $i = 1, 2, \dots, N$ ,  $Y_{2i}^{u_1, u_2} \in \mathbb{R}^{l_2}, f_{2i} \in \mathbb{R}^{l_2 \times n}, g_{2i} \in \mathbb{R}^{l_2}, K_{2i} \in \mathbb{R}^{l_2 \times l_2}$ . It should be noted that the drift term can contain the state variable in the leader's observation equation, which is an extension of that in [39] because of the new technique we applied in this paper.

We denote filtrations  $\mathcal{F}_t^{Y_i^{u_1, u_2}}$  by the  $\sigma$ -algebra generated by  $Y_i^{u_1, u_2}$  up to  $t$ , respectively, for  $i = 1, 2$ , for  $t \in [0, T]$  and assume that  $\mathcal{F}_t^{Y_2^{u_1, u_2}} \subset \mathcal{F}_t^{Y_1^{u_1, u_2}}$ .

The cost functionals of the followers and the leader are defined as follows:

$$\begin{aligned}
J_{1i}(x_0; u_1, u_2) &= \mathbb{E} \left[ \int_0^T \left[ \left\langle \begin{pmatrix} Q_{1i} & S_{1i}^\top \\ S_{1i} & R_{1i} \end{pmatrix} \begin{pmatrix} X \\ u_{1i} \end{pmatrix}, \begin{pmatrix} X \\ u_{1i} \end{pmatrix} \right\rangle + 2 \left\langle \begin{pmatrix} q_{1i} \\ r_{1i} \end{pmatrix}, \begin{pmatrix} X \\ u_{1i} \end{pmatrix} \right\rangle \right] dt \\
&\quad + \langle G_{1i} X_T, X_T \rangle + 2 \langle g_{1i}, X_T \rangle \Big], \quad i = 1, 2, \dots, N, \\
J_2(x_0; u_1, u_2) &= \mathbb{E} \left[ \int_0^T \left[ \left\langle \begin{pmatrix} Q_2 & S_2^\top \\ S_2 & R_2 \end{pmatrix} \begin{pmatrix} X \\ u_2 \end{pmatrix}, \begin{pmatrix} X \\ u_2 \end{pmatrix} \right\rangle + 2 \left\langle \begin{pmatrix} q_2 \\ r_2 \end{pmatrix}, \begin{pmatrix} X \\ u_2 \end{pmatrix} \right\rangle \right] dt \\
&\quad + \langle G_2 X_T, X_T \rangle + 2 \langle g_2, X_T \rangle \Big], \tag{2.3}
\end{aligned}$$

which are minimized for the purpose of this paper, by choosing the corresponding optimal controls  $\bar{u}_1, \bar{u}_2$  in the admissible control sets  $\mathcal{U}_{ad}^F, \mathcal{U}_{ad}^L$  defined by

$$\begin{aligned}
\mathcal{U}_{ad}^F &= \left\{ u_1 : [0, T]^N \times \Omega \rightarrow \mathbb{R}^{Nm} \mid u_1(t) = (u_{11}(t), \dots, u_{1N}(t))^\top \in \mathcal{F}_t^{Y_1^{u_1, u_2}} \right. \\
&\quad \left. \text{and } \mathbb{E} \int_0^T |u_1(t)|^2 dt < \infty \right\}, \\
\mathcal{U}_{ad}^L &= \left\{ u_2 : [0, T] \times \Omega \rightarrow \mathbb{R} \mid u_2(t) \in \mathcal{F}_t^{Y_2^{u_1, u_2}} \text{ and } \mathbb{E} \int_0^T |u_2(t)|^2 dt < \infty \right\},
\end{aligned}$$

respectively.

Now we need the following assumptions:

- (A1)  $A(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times n})$ ,  $B_{1i}(\cdot), B_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times m})$ , for  $i = 1, \dots, N$ ,  
 $\alpha(\cdot) \in L^\infty(0, T; \mathbb{R}^n)$ ,  $C_1(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times l_1})$ ,  $C_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times l_2})$ ;
- (A2)  $f_1(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_1 \times n})$ ,  $f_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_2 \times n})$ ,  $g_1(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_1})$ ,  
 $g_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_2})$ ,  $K_1(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_1 \times l_1})$ ,  $K_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{l_2 \times l_2})$ ;
- (A3)  $Q_{1i}(\cdot) \in L^\infty(0, T; \mathcal{S}_+^n)$ ,  $S_{1i}(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times m})$ ,  $R_{1i}(\cdot) \in L^\infty(0, T; \mathcal{S}_+^m)$ ,  
 $q_{1i}(\cdot) \in L^\infty(0, T; \mathbb{R}^n)$ ,  $r_{1i}(\cdot) \in L^\infty(0, T; \mathbb{R}^m)$ , for  $i = 1, \dots, N$ ,  
 $Q_2(\cdot) \in L^\infty(0, T; \mathcal{S}_+^n)$ ,  $S_2(\cdot) \in L^\infty(0, T; \mathbb{R}^{n \times m})$ ,  $R_2(\cdot) \in L^\infty(0, T; \mathcal{S}_+^m)$ ,  
 $q_2(\cdot) \in L^\infty(0, T; \mathbb{R}^n)$ ,  $r_2(\cdot) \in L^\infty(0, T; \mathbb{R}^m)$ .

### 3. THE FOLLOWERS' PROBLEM

In this section, we consider a linear-quadratic partially observed optimal control problem by the technique from [31]. Fix the leader's control  $u_2$ , in order to overcome the difficulty that the control process is adapted to the controlled filtration, for any fixed admissible control  $u_1 \in \mathcal{U}_{ad}^F$ , define the following notations:

$$\hat{X}_t^{u_1, u_2} \triangleq \mathbb{E} \left[ X_t^{u_1, u_2} \mid \mathcal{F}_t^{Y_1^{u_1, u_2}} \right], \quad \tilde{X}_t^{u_1, u_2} \triangleq X_t^{u_1, u_2} - \hat{X}_t^{u_1, u_2} \tag{3.1}$$

and stochastic process

$$V_t^{u_1, u_2} \triangleq Y_1^{u_1, u_2}(t) - \int_0^t [f_1(s) \hat{X}_s^{u_1, u_2} + g_1(s)] ds. \tag{3.2}$$

For any admissible control  $u_2$  and a fixed admissible control  $u_1 \in \mathcal{U}_{ad}^F$ , we can obtain

$$\check{V}_t^{u_1, u_2} \triangleq \int_0^t K_1^{-1}(s) dV_s^{u_1, u_2} \tag{3.3}$$

is a standard  $\mathcal{F}_t^{Y_1^{u_1, u_2}}$ -Brownian motion. Indeed, first, we have  $\check{V}^{u_1, u_2}$  is a continuous  $\mathcal{F}_t^{Y_1^{u_1, u_2}}$ -adapted, integrable process, and

$$d\check{V}_t^{u_1, u_2} = K_1^{-1}(t)dV_t^{u_1, u_2} = K_1^{-1}(t)f_1(t)\check{X}_t^{u_1, u_2}dt + dW_t^1.$$

Thus, for  $0 \leq s < t \leq T$ ,

$$\begin{aligned} & \mathbb{E}\left[\check{V}_t^{u_1, u_2} - \check{V}_s^{u_1, u_2} \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] \\ &= \mathbb{E}\left[W_t^1 - W_s^1 \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] + \mathbb{E}\left[\int_s^t K_1^{-1}(r)f_1(r)\check{X}_r^{u_1, u_2}dr \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] \\ &= \mathbb{E}\left[\mathbb{E}[W_t^1 - W_s^1 | \mathcal{F}_s]\middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] + \int_s^t K_1^{-1}(r)f_1(r)\mathbb{E}\check{X}_r^{u_1, u_2}dr = 0, \end{aligned}$$

which implies that  $\check{V}^{u_1, u_2}$  is a  $\mathcal{F}_t^{Y_1^{u_1, u_2}}$ -martingale. Meanwhile,

$$\begin{aligned} d[\check{V}_t^{u_1, u_2}(\check{V}_t^{u_1, u_2})^\top] &= K_1^{-1}(t)f_1(t)\check{X}_t^{u_1, u_2}(\check{V}_t^{u_1, u_2})^\top dt + (dW_t^1)(\check{V}_t^{u_1, u_2})^\top \\ &\quad + \check{V}_t^{u_1, u_2}K_1^{-1}(t)f_1(t)(\check{X}_t^{u_1, u_2})^\top dt + \check{V}_t^{u_1, u_2}(dW_t^1)^\top + I_1 dt. \end{aligned}$$

Due to

$$\begin{aligned} & \mathbb{E}\left[\int_s^t \check{V}_r^{u_1, u_2}(K_1^{-1}(r)f_1(r)\check{X}_r^{u_1, u_2})^\top dr \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] \\ &= \int_s^t \mathbb{E}\left[\mathbb{E}[\check{V}_r^{u_1, u_2}(\check{X}_r^{u_1, u_2})^\top | \mathcal{F}_r^{Y_1^{u_1, u_2}}] \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] f_1^\top(r)(K_1^{-1}(r))^\top dr \\ &= \int_s^t \mathbb{E}\left[\check{V}_r^{u_1, u_2}\mathbb{E}(\check{X}_r^{u_1, u_2})^\top \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] f_1^\top(r)(K_1^{-1}(r))^\top dr = 0, \end{aligned}$$

and

$$\mathbb{E}\left[\int_s^t \check{V}_r^{u_1, u_2}d(W_r^1)^\top \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] = \mathbb{E}\left[\mathbb{E}\left[\int_s^t \check{V}_r^{u_1, u_2}d(W_r^1)^\top \middle| \mathcal{F}_s\right] \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] = 0,$$

we have

$$\mathbb{E}\left[(\check{V}_t^{u_1, u_2})^2 - (\check{V}_s^{u_1, u_2})^2 \middle| \mathcal{F}_s^{Y_1^{u_1, u_2}}\right] = (t-s)I_1,$$

which implies that  $\check{V}^{u_1, u_2}$  is a standard Brownian motion.

Next, we consider the following process

$$\Lambda_t^{1, u_1, u_2} \triangleq \hat{X}_t^{u_1, u_2} - x_0 - \int_0^t [A(s)\hat{X}_s^{u_1, u_2} + B_1^\top(s)u_1(s) + B_2(s)u_2(s) + \alpha(s)] ds. \quad (3.4)$$

In the following, we will prove that  $\Lambda^{1,u_1,u_2} \equiv \{\Lambda_t^{1,u_1,u_2}; 0 \leq t \leq T\}$  is an RCLL square-integrable  $\mathcal{F}_t^{Y_1^{u_1,u_2}}$ -martingale with  $\Lambda_0 = 0$ , a.s.. Indeed, for fixed  $0 \leq s < t \leq T$ , we have

$$\begin{aligned}
& \mathbb{E} \left[ \Lambda_t^{1,u_1,u_2} - \Lambda_s^{1,u_1,u_2} \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] \\
&= \mathbb{E} \left[ \mathbb{E} [X_t^{u_1,u_2} | \mathcal{F}_t^{Y_1^{u_1,u_2}}] - \mathbb{E} [X_s^{u_1,u_2} | \mathcal{F}_s^{Y_1^{u_1,u_2}}] \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] \\
&\quad - \int_s^t \left\{ A(r) \mathbb{E} \left[ \mathbb{E} [X_r^{u_1,u_2} | \mathcal{F}_r^{Y_1^{u_1,u_2}}] \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] + B_1^\top(r) \mathbb{E} [u_1(r) | \mathcal{F}_s^{Y_1^{u_1,u_2}}] \right. \\
&\quad \left. + B_2(r) \mathbb{E} [u_2(r) | \mathcal{F}_s^{Y_1^{u_1,u_2}}] + \alpha(r) \right\} dr \\
&= \mathbb{E} \left[ X_t^{u_1,u_2} - X_s^{u_1,u_2} - \int_s^t \{A(r)X_r^{u_1,u_2} + B_1^\top(r)u_1(r) + B_2(r)u_2(r) + \alpha(r)\} dr \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] \\
&= \mathbb{E} \left[ \mathbb{E} \left[ \int_s^t C_1(r) dW_r^1 + \int_s^t C_2(r) dW_r^2 \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] \middle| \mathcal{F}_s^{Y_1^{u_1,u_2}} \right] = 0.
\end{aligned}$$

Now by the theorem of Fujisaki, Kallianpar and Kunita [27], there exists a square-integrable  $\mathcal{F}_t^{Y_1^{u_1,u_2}}$ -progressively measurable process  $\lambda^{1,u_1,u_2} = \{\lambda_t^{1,u_1,u_2}; 0 \leq t \leq T\} \in \mathbb{R}^{n \times l_1}$  such that

$$\Lambda_t^{1,u_1,u_2} = \int_0^t \lambda_s^{1,u_1,u_2} (K_1(s)K_1^\top(s))^{-1} dV^{u_1,u_2}(s), \quad 0 \leq t \leq T. \quad (3.5)$$

To determine the process  $\lambda^{1,u_1,u_2}$ , we let  $\zeta^{u_1,u_2} = \{\zeta_t^{u_1,u_2}; 0 \leq t \leq T\} \in \mathbb{R}^{n \times l_1}$  be a fixed but arbitrary square integrable  $\{\mathcal{F}_t^{Y_1^{u_1,u_2}}\}$ -progressively measurable process. Consider the  $\mathcal{F}_t^{Y_1^{u_1,u_2}}$ -martingale

$$\eta_t^{u_1,u_2} \triangleq \int_0^t \zeta_s^{u_1,u_2} (K_1(s)K_1^\top(s))^{-1} dV^{u_1,u_2}(s), \quad 0 \leq t \leq T, \quad (3.6)$$

and then

$$\mathbb{E} [\Lambda_t^{1,u_1,u_2} (\eta_t^{u_1,u_2})^\top] = \mathbb{E} \int_0^t \lambda_s^{1,u_1,u_2} (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds.$$

On the other hand, we also have

$$\begin{aligned}
& \mathbb{E} [\Lambda_t^{1,u_1,u_2} (\eta_t^{u_1,u_2})^\top] \\
&= \mathbb{E} [\hat{X}_t^{u_1,u_2} (\eta_t^{u_1,u_2})^\top] - \mathbb{E} \int_0^t [A(s)\hat{X}_s^{u_1,u_2} + B_1^\top(s)u_1(s) + B_2(s)u_2(s) + \alpha(s)] (\eta_t^{u_1,u_2})^\top ds.
\end{aligned}$$

Since for  $0 \leq s \leq t \leq T$ ,

$$\begin{aligned}
\mathbb{E} [\hat{X}_s^{u_1,u_2} (\eta_t^{u_1,u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} [\hat{X}_s^{u_1,u_2} (\eta_t^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}] \right] = \mathbb{E} [\hat{X}_s^{u_1,u_2} (\eta_s^{u_1,u_2})^\top] \\
&= \mathbb{E} \left[ \mathbb{E} [X_s^{u_1,u_2} | \mathcal{F}_s^{Y_1^{u_1,u_2}}] (\eta_s^{u_1,u_2})^\top \right] = \mathbb{E} [X_s^{u_1,u_2} (\eta_s^{u_1,u_2})^\top],
\end{aligned}$$

and

$$\begin{aligned}
& \mathbb{E} [(B_1^\top(s)u_1(s) + B_2(s)u_2(s) + \alpha(s)) (\eta_t^{u_1,u_2})^\top] \\
&= \mathbb{E} \left[ \sum_{i=1}^N B_{1i}(s) \mathbb{E} [u_{1i}(s) (\eta_t^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}] \right] \\
&\quad + \mathbb{E} [B_2(s) \mathbb{E} [u_2(s) (\eta_t^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}]] + \mathbb{E} [\alpha(s) \mathbb{E} [(\eta_t^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}]] \\
&= \mathbb{E} [B_1^\top(s)u_1(s) (\eta_s^{u_1,u_2})^\top + B_2(s)u_2(s) (\eta_s^{u_1,u_2})^\top + \alpha(s) (\eta_s^{u_1,u_2})^\top],
\end{aligned}$$

then we obtain

$$\begin{aligned}
& \mathbb{E}[\Lambda_t^{1,u_1,u_2}(\eta_t^{u_1,u_2})^\top] \\
&= \mathbb{E}[X_t^{u_1,u_2}(\eta_t^{u_1,u_2})^\top] \\
&\quad - \mathbb{E} \int_0^t [A(s)X_s^{u_1,u_2} + B_1^\top(s)u_1(s) + B_2(s)u_2(s) + \alpha(s)] (\eta_s^{u_1,u_2})^\top ds.
\end{aligned} \tag{3.7}$$

Observing that

$$d\eta_t^{u_1,u_2} = \zeta_t^{u_1,u_2} (K_1(s)K_1^\top(s))^{-1} f_1(t) \tilde{X}_t^{u_1,u_2} dt + \zeta_t^{u_1,u_2} K_1^{-1}(t) dW_t^1,$$

and using Itô's formula, it has

$$\begin{aligned}
& \mathbb{E}[X_t^{u_1,u_2}(\eta_t^{u_1,u_2})^\top] \\
&= \mathbb{E} \int_0^t \left\{ X_s^{u_1,u_2} [\zeta_s^{u_1,u_2} (K_1(s)K_1^\top(s))^{-1} f_1(s) \tilde{X}_s^{u_1,u_2}]^\top + [A(s)X_s^{u_1,u_2} + B_1^\top(s)u_1(s) \right. \\
&\quad \left. + B_2(s)u_2(s) + \alpha(s)] (\eta_s^{u_1,u_2})^\top + C_1(s) (\zeta_s^{u_1,u_2} K_1^{-1}(s))^\top \right\} ds,
\end{aligned}$$

where

$$\begin{aligned}
& \mathbb{E} \int_0^t X_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&= \mathbb{E} \int_0^t \hat{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&\quad + \mathbb{E} \int_0^t \tilde{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&= \mathbb{E} \int_0^t \mathbb{E} [\hat{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}] f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&\quad + \mathbb{E} \int_0^t \mathbb{E} [\tilde{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top | \mathcal{F}_s^{Y_1^{u_1,u_2}}] f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&= \mathbb{E} \int_0^t \mathbb{E} [\tilde{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top] f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds \\
&= \mathbb{E} \int_0^t \Sigma_s f_1^\top(s) (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds,
\end{aligned}$$

where we set  $\Sigma_s \triangleq \mathbb{E} [\tilde{X}_s^{u_1,u_2} (\tilde{X}_s^{u_1,u_2})^\top]$ , which implies that

$$\begin{aligned}
& \mathbb{E}[X_t^{u_1,u_2}(\eta_t^{u_1,u_2})^\top] \\
&= \mathbb{E} \int_0^t [A(s)X_s^{u_1,u_2} + B_1^\top(s)u_1(s) + B_2(s)u_2(s) + \alpha(s)] (\eta_s^{u_1,u_2})^\top ds \\
&\quad + \mathbb{E} \int_0^t [\Sigma_s^{u_1,u_2} f_1^\top(s) + C_1(s)K_1^\top(s)] (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds.
\end{aligned}$$

Then making the comparison with (3.7) we get

$$\mathbb{E}[\Lambda_t^{1,u_1,u_2}(\eta_t^{u_1,u_2})^\top] = \mathbb{E} \int_0^t [\Sigma_s f_1^\top(s) + C_1(s)K_1^\top(s)] (K_1(s)K_1^\top(s))^{-1} (\zeta_s^{u_1,u_2})^\top ds.$$

So we obtain

$$\lambda_s^1 = \Sigma_s f_1^\top(s) + C_1(s)K_1^\top(s), \quad 0 \leq s \leq T. \tag{3.8}$$

The filtering process  $\hat{X}^{u_1, u_2}$  satisfies

$$\begin{aligned}
d\hat{X}_t^{u_1, u_2} &= [A(t)\hat{X}_t^{u_1, u_2} + B_1^\top(t)u_1(t) + B_2(t)u_2(t) + \alpha(t)]dt \\
&\quad + [\Sigma_t f_1^\top(t) + C_1(t)K_1^\top(t)](K_1(t)K_1^\top(t))^{-1}dV^{u_1, u_2}(t) \\
&= [A(t)\hat{X}_t^{u_1, u_2} + B_1^\top(t)u_1(t) + B_2(t)u_2(t) + \alpha(t)]dt \\
&\quad + [\Sigma_t f_1^\top(t) + C_1(t)K_1^\top(t)](K_1(t)K_1^\top(t))^{-1}f_1(t)\tilde{X}_t^{u_1, u_2}dt \\
&\quad + [\Sigma_t f_1^\top(t) + C_1(t)K_1^\top(t)]K_1^{-1}(t)dW_t^1,
\end{aligned} \tag{3.9}$$

and  $\tilde{X}^{u_1, u_2}$  satisfies

$$\begin{aligned}
d\tilde{X}_t^{u_1, u_2} &= [A(t) - [\Sigma_t f_1^\top(t) + C_1(t)K_1^\top(t)](K_1(t)K_1^\top(t))^{-1}f_1(t)\tilde{X}_t^{u_1, u_2}]dt \\
&\quad - \Sigma_t f_1^\top(t)K_1^{-1}(t)dW_t^1 + C_2(t)dW_t^2.
\end{aligned} \tag{3.10}$$

Then apply Itô's formula to  $\tilde{X}^{u_1, u_2}(\tilde{X}^{u_1, u_2})^\top$ , we have

$$\begin{aligned}
\Sigma_t &= \int_0^t \left[ (A(s) - C_1(s)K_1^{-1}(s)f_1(s))\Sigma_s + \Sigma_s(A(s) - C_1(s)K_1^{-1}(s)f_1(s))^\top \right. \\
&\quad \left. - \Sigma_s f_1^\top(s)(K_1(s)K_1^\top(s))^{-1}f_1(s)\Sigma_s + C_2(s)C_2^\top(s) \right] ds.
\end{aligned} \tag{3.11}$$

Next, based on the orthogonal decomposition of the state process [31], we divide the cost functional  $J_{1i}(x_0; u_1, u_2)$  for the  $i$ th follower as follows:

$$\begin{aligned}
J_{1i}(x_0; u_1, u_2) &= \mathbb{E} \left[ \int_0^T \left[ \left\langle \begin{pmatrix} Q_{1i} & S_{1i}^\top \\ S_{1i} & R_{1i} \end{pmatrix} \begin{pmatrix} \hat{X}^{u_1, u_2} + \tilde{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix}, \begin{pmatrix} \hat{X}^{u_1, u_2} + \tilde{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix} \right\rangle \right. \\
&\quad \left. + 2 \left\langle \begin{pmatrix} q_{1i} \\ r_{1i} \end{pmatrix}, \begin{pmatrix} \hat{X}^{u_1, u_2} + \tilde{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix} \right\rangle \right] dt \\
&\quad \left. + \langle G_{1i}(\hat{X}_T^{u_1, u_2} + \tilde{X}_T^{u_1, u_2}), \hat{X}_T^{u_1, u_2} + \tilde{X}_T^{u_1, u_2} \rangle + 2 \langle g_{1i}, \hat{X}_T^{u_1, u_2} + \tilde{X}_T^{u_1, u_2} \rangle \right] \\
&= \mathbb{E} \left[ \int_0^T \left( \langle Q_{1i}(t)\tilde{X}_t^{u_1, u_2}, \tilde{X}_t^{u_1, u_2} \rangle + 2 \langle q_{1i}(t), \tilde{X}_t^{u_1, u_2} \rangle \right) dt \right. \\
&\quad \left. + \langle G_{1i}\tilde{X}_T^{u_1, u_2}, \tilde{X}_T^{u_1, u_2} \rangle + 2 \langle g_{1i}, \tilde{X}_T^{u_1, u_2} \rangle \right] \\
&\quad + \mathbb{E} \left[ \int_0^T \left[ \left\langle \begin{pmatrix} Q_{1i} & S_{1i}^\top \\ S_{1i} & R_{1i} \end{pmatrix} \begin{pmatrix} \hat{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix}, \begin{pmatrix} \hat{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix} \right\rangle \right. \right. \\
&\quad \left. \left. + 2 \left\langle \begin{pmatrix} q_{1i} \\ r_{1i} \end{pmatrix}, \begin{pmatrix} \hat{X}^{u_1, u_2} \\ u_{1i} \end{pmatrix} \right\rangle \right] dt + \langle G_{1i}\hat{X}_T^{u_1, u_2}, \hat{X}_T^{u_1, u_2} \rangle + 2 \langle g_{1i}, \hat{X}_T^{u_1, u_2} \rangle \right] \\
&\triangleq \tilde{J}_{1i}(x_0; u_1, u_2) + \hat{J}_{1i}(x_0; u_1, u_2).
\end{aligned} \tag{3.12}$$

We introduce Riccati equations:

$$\begin{cases} \dot{P}_t^{1i} + A^\top(t)P_t^{1i} + P_t^{1i}A(t) - (P_t^{1i}B_{1i}(t) + S_{1i}^\top(t))R_{1i}^{-1}(t)(B_{1i}^\top(t)P_t^{1i} + S_{1i}(t)) + Q_{1i}(t) = 0, \\ P_T^{1i} = G_{1i}, \end{cases} \tag{3.13}$$

and BSDEs:

$$\left\{ \begin{array}{l} -d\varphi_t^{1i,u_2} = \left\{ [A(t) - B_{1i}(t)R_{1i}^{-1}(t)(B_{1i}(t)^\top P_t^{1i} + S_{1i}(t))]^\top \varphi_t^{1i,u_2} + P_t^{1i}\alpha(t) \right. \\ \quad \left. + q_{1i}(t) - [R_{1i}^{-1}(t)(B_{1i}^\top(t)P_t^{1i} + S_{1i}(t))]^\top r_{1i}(t) + P_t^{1i}B_2(t)u_2(t) \right\} dt \\ \quad - \lambda_t^{1i,u_2} d\check{V}^{u_1,u_2}(t), \\ \varphi_T^{1i,u_2} = g_{1i}, \quad i = 1, \dots, N. \end{array} \right. \quad (3.14)$$

Apply Itô's formula to  $\langle P_t^{1i} \hat{X}_t^{u_1,u_2}, \hat{X}_t^{u_1,u_2} \rangle$  and  $\langle \varphi_t^{1i,u_2}, \hat{X}_t^{u_1,u_2} \rangle$  on  $[0, T]$ , respectively, and insert them into  $\hat{J}_{1i}(x_0; u_1, u_2)$ , then we have (We usually omit the time variable  $t$  in the following for simplicity.)

$$\begin{aligned} & \hat{J}_{1i}(x_0; u_1, u_2) \\ &= \mathbb{E}[\langle P_0^{1i} x_0 + 2\varphi_0^{1i,u_2}, x_0 \rangle] + \mathbb{E} \int_0^T \left[ \langle R_{1i} [u_{1i} + R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i}) \hat{X}^{u_1,u_2} \right. \\ & \quad \left. + R_{1i}^{-1}(B_{1i}^\top \varphi^{1i,u_2} + r_{1i})], [u_{1i} + R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i}) \hat{X}^{u_1,u_2} + R_{1i}^{-1}(B_{1i}^\top \varphi^{1i,u_2} + r_{1i})] \rangle \right. \\ & \quad \left. - \langle R_{1i}^{-1}(B_{1i}^\top \varphi^{1i,u_2} + r_{1i}), (B_{1i}^\top \varphi^{1i,u_2} + r_{1i}) \rangle + \sum_{j=1}^{l_1} \langle P^{1i}(\Delta_j + C_{1j}), \Delta_j + C_{1j} \rangle \right. \\ & \quad \left. + 2\langle B_2 u_2, \varphi^{1i,u_2} \rangle + 2\langle \varphi^{1i,u_2}, \alpha \rangle + 2\langle \Delta(t) + C_1, \lambda^{1i,u_2} \rangle \right] dt, \end{aligned} \quad (3.15)$$

where  $\Delta(t) \equiv (\Delta_1(t), \dots, \Delta_{l_1}(t)) \triangleq \Sigma_t (K_1^{-1}(t) f_1(t))^\top$ . Similarly, we also introduce ODEs:

$$\left\{ \begin{array}{l} \dot{\Pi}_t^{1i} + [A - (\Sigma f_1^\top K_1^{-1} + C_1) K_1^{-1} f_1]^\top \Pi_t^{1i} \\ \quad + \Pi_t^{1i} [A - (\Sigma f_1^\top + C_1 K_1^\top)(K_1 K_1^\top)^{-1} f_1] + Q_{1i} = 0, \\ \Pi_T^{1i} = G_{1i}, \end{array} \right. \quad (3.16)$$

and BSDEs:

$$\left\{ \begin{array}{l} -d\pi_t^{1i} = \left\{ [A - (\Sigma f_1^\top K_1^{-1} + C_1) K_1^{-1} f_1]^\top \pi_t^{1i} + q_{1i} \right\} dt - \beta_t^1 dW_t^1 - \beta_t^2 dW_t^2, \\ \pi_T^{1i} = g_{1i}, \quad i = 1, \dots, N. \end{array} \right. \quad (3.17)$$

Apply Itô's formula to  $\langle \Pi_t^{1i} \check{X}_t^{u_1,u_2}, \check{X}_t^{u_1,u_2} \rangle$  and  $\langle \pi_t^{1i}, \check{X}_t^{u_1,u_2} \rangle$  on  $[0, T]$ , respectively, and insert them into  $\tilde{J}_{1i}(x_0; u_1, u_2)$ , then we have

$$\begin{aligned} \tilde{J}_{1i}(x_0; u_1, u_2) &= \mathbb{E} \int_0^T \left[ \sum_{j=1}^{l_1} \langle \Pi^{1i} \Delta_j, \Delta_j \rangle + \sum_{j=1}^{l_2} \langle \Pi^{1i} C_{2j}, C_{2j} \rangle \right. \\ & \quad \left. - 2\langle \Sigma f_1^\top K_1^{-1}, \beta^1 \rangle + 2\langle C_2, \beta^2 \rangle \right] dt. \end{aligned} \quad (3.18)$$

Now, the optimal filtering feedback form of the  $i$ th follower's optimal control is

$$\bar{u}_{1i}(t) = -R_{1i}^{-1}(t) [B_{1i}^\top(t) P_t^{1i} + S_{1i}(t)] \hat{X}_t^{\bar{u}_1, u_2} - R_{1i}^{-1}(t) [B_{1i}(t)^\top \varphi_t^{1i, u_2} + r_{1i}(t)], \quad (3.19)$$

where  $\hat{X}^{\bar{u}_1, u_2}$  satisfies

$$\begin{aligned} d\hat{X}_t^{\bar{u}_1, u_2} = & \left[ \left( A(t) - \sum_{i=1}^N B_{1i}(t)R_{1i}^{-1}(t)[B_{1i}(t)^\top P_t^{1i} + S_{1i}(t)] \right) \hat{X}_t^{\bar{u}_1, u_2} \right. \\ & \left. - \sum_{i=1}^N B_{1i}(t)R_{1i}^{-1}(t)[B_{1i}(t)^\top \varphi_t^{1i, u_2} + r_{1i}(t)] + B_2(t)u_2(t) + \alpha(t) \right] dt \quad (3.20) \\ & + [\Sigma_t f_1^\top(t) + C_1(t)K_1^\top(t)](K_1(t)K_1^\top(t))^{-1}dV^{\bar{u}_1, u_2}(t). \end{aligned}$$

Now, for any fixed  $u_2$ , the optimal cost of the  $i$ th follower is given by

$$\begin{aligned} J_{1i}(x_0; \bar{u}_1, u_2) = & \mathbb{E}[\langle P_0^{1i}x_0 + 2\varphi_0^{1i, u_2}, x_0 \rangle] + \mathbb{E} \int_0^T \left\{ \sum_{j=1}^{l_1} \langle \Pi^{1i} \Delta_j, \Delta_j \rangle \right. \\ & + \sum_{j=1}^{l_2} \langle \Pi^{1i} C_{2j}, C_{2j} \rangle - 2\langle \Delta, \beta^1 \rangle - \langle R_{1i}^{-1}(B_{1i}^\top \varphi^{1i, u_2} + r_{1i}), B_{1i}^\top \varphi^{1i, u_2} + r_{1i} \rangle \\ & + \sum_{j=1}^{l_1} \langle P^{1i}(\Delta_j + C_{1j}), \Delta_j + C_{1j} \rangle + 2\langle B_2 u_2, \varphi^{1i, u_2} \rangle \\ & \left. + 2\langle \alpha, \varphi^{1i, u_2} \rangle + 2\langle C_2, \beta^2 \rangle + 2\langle (\Delta + C_1), \lambda^{1i, u_2} \rangle \right\} dt. \quad (3.21) \end{aligned}$$

**Remark 3.1.** It is acknowledged that the separation principle introduced in [36] is the key step that separate the optimal control and state estimate in the classical partially observed stochastic control problem of SDEs. Then a backward separation principle is also introduced in [33] for solving the partially observed FBSDEs. However, the necessary state decomposition technique in the above two work plays an important role, therefore, the restriction imposed on the admissible control require additional condition in terms of the filtration generated by observation process. In their procedure, different from that in [33] in which they show the “backward” idea that first addresses the control problem and the filtering equation is then obtained, the classical idea in [36] is to investigate the filtering equation first, which is similar to the steps in our work. Based on the orthogonal decomposition, we focus on the decomposition of cost functional alternatively and then transform the original partially observed control into a class of “completely observed” control problem based on the known information filtration, so we do not need the restriction introduced by state decomposition and relax the definition of admissible control. As far as we know, the technique is also applied to investigate the partially observed LQ stochastic control of mean-field SDEs recently in [24], but there is no any related result for forward backward stochastic system yet, which has been now completed in the following section for leader’s problem.

#### 4. THE LEADER’S PROBLEM

In this section, the leader encounters a kind of partially observed stochastic optimal control of non-standard FBSDEs with conditional mean-field terms. So we extend the result in [31] to the case of forward-backward partially observed stochastic system.

Since the state equation (2.1) of  $X^{u_2} \equiv X^{\bar{u}_1, u_2}$ , now, contains  $\varphi^{1i, u_2}$  and  $\hat{X}^{u_2} \equiv \hat{X}^{\bar{u}_1, u_2}$  by  $\bar{u}_{1i}$  in (3.19), thus the state equation of the leader becomes an FBSDE with conditional mean filed terms. In the following part, for obtaining the explicit form, we consider the

case that  $f_1(\cdot) = g_1(\cdot) = 0$ , i.e.,  $\mathcal{F}_t^{Y_1^{u_2}} \equiv \mathcal{F}_t^{Y_1^{\bar{u}_1, u_2}} = \mathcal{F}_t^{W^1}$ , then  $\check{V}^{u_2}(t) \equiv \check{V}^{\bar{u}_1, u_2}(t) = W_t^1$ . And thus

$$\left\{ \begin{array}{l} dX_t^{u_2} = \left\{ A(t)X_t^{u_2} - \sum_{i=1}^N B_{1i}(t)R_{1i}^{-1}(t) [B_{1i}^\top(t)P_t^{1i} + S_{1i}(t)] \hat{X}_t^{u_2} \right. \\ \quad \left. - \sum_{i=1}^N B_{1i}(t)R_{1i}^{-1}(t) [B_{1i}^\top(t)\varphi_t^{1i, u_2} + r_{1i}(t)] \right. \\ \quad \left. + B_2(t)u_2(t) + \alpha(t) \right\} dt + C_1(t)dW_t^1 + C_2(t)dW_t^2, \\ -d\varphi_t^{1i, u_2} = \left\{ [A(t) - B_{1i}(t)R_{1i}^{-1}(t)(B_{1i}^\top(t)P_t^{1i} + S_{1i}(t))] \varphi_t^{1i, u_2} \right. \\ \quad \left. + P_t^{1i}\alpha(t) + q_{1i}(t) - R_{1i}^{-1}(t) [B_{1i}^\top(t)P_t^{1i} + S_{1i}(t)] r_{1i}(t) \right. \\ \quad \left. + P_t^{1i}B_2(t)u_2(t) \right\} dt - \lambda_t^{1i, u_2} dW_t^1, \\ X_0^{u_2} = x_0, \varphi_T^{1i, u_2} = g_{1i}, \quad i = 1, 2, \dots, N. \end{array} \right. \quad (4.1)$$

Now we assume  $\mathcal{F}_t^{Y_2^{u_2}} \subset \mathcal{F}_t^{Y_1^{u_2}} = \mathcal{F}_t^{W^1}$ , where we have denoted by  $Y_2^{u_2} \equiv Y_2^{\bar{u}_1, u_2}$ . Set, for a fixed admissible control  $u_2 \in \mathcal{F}_{ad}^L$ ,

$$\begin{aligned} \check{X}_t^{u_2} &\triangleq \mathbb{E} \left[ X_t^{u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right], \quad \tilde{X}_t^{u_2} = X_t^{u_2} - \check{X}_t^{u_2} \\ \check{\varphi}_t^{1i, u_2} &\triangleq \mathbb{E} \left[ \varphi_t^{1i, u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right], \quad \check{\lambda}_t^{1i, u_2} \triangleq \mathbb{E} \left[ \lambda_t^{1i, u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right], \quad i = 1, 2, \dots, N, \\ U_t^{u_2} &\triangleq Y_2^{u_2}(t) - \int_0^t [f_2(s)\check{X}_s^{u_2} + g_2(s)] ds, \end{aligned} \quad (4.2)$$

and  $\check{U}_t^{u_2} \triangleq \int_0^t K_2^{-1}(s)dU_s^{u_2}$  is an  $\mathcal{F}_t^{Y_2^{u_2}}$ -Brownian motion. First, we consider the process

$$\begin{aligned} \Lambda_t^{2, u_2} &\triangleq \check{X}_t^{u_2} - x_0 - \int_0^t \left\{ \left[ A - \sum_{i=1}^N B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i}) \right] \check{X}_s^{u_2} - \sum_{i=1}^N B_{1i}R_{1i}^{-1}B_{1i}^\top \check{\varphi}_s^{1i, u_2} \right. \\ &\quad \left. + B_2u_2 - \sum_{i=1}^N B_{1i}R_{1i}^{-1}r_{1i} + \alpha \right\} ds, \end{aligned} \quad (4.3)$$

which is  $\mathcal{F}_t^{Y_2^{u_2}}$ -adapted and RCLL,  $\Lambda_0^{2, u_2} = 0$ . For fixed  $0 \leq s < t \leq T$ , we have

$$\begin{aligned} \mathbb{E} \left[ \Lambda_t^{2, u_2} - \Lambda_s^{2, u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] &= \mathbb{E} \left[ \check{X}_t^{u_2} - \check{X}_s^{u_2} - \int_s^t \left[ \left( A - \sum_{i=1}^N B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i}) \right) \check{X}_r^{u_2} \right. \right. \\ &\quad \left. \left. - \sum_{i=1}^N B_{1i}R_{1i}^{-1}B_{1i}^\top \check{\varphi}_r^{1i, u_2} + B_2u_2 - \sum_{i=1}^N B_{1i}R_{1i}^{-1}r_{1i} + \alpha \right] dr \middle| \mathcal{F}_s^{Y_2^{u_2}} \right], \end{aligned}$$

where

$$\mathbb{E} \left[ \check{X}_t^{u_2} - \check{X}_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] = \mathbb{E} \left[ \mathbb{E} \left[ X_t^{u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] - \mathbb{E} \left[ X_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] = \mathbb{E} \left[ X_t^{u_2} - X_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right],$$

$$\begin{aligned}
& \mathbb{E} \left[ \int_s^t \left( A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right) \check{X}_r^{u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right] \\
&= \int_s^t \left( A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right) \mathbb{E} \left[ \check{X}_r^{u_2} \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \int_s^t A \mathbb{E} \left[ \mathbb{E} \left[ \check{X}_r^{u_2} \middle| \mathcal{F}_r^{Y^{u_2}} \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&\quad - \int_s^t \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E} \left[ \mathbb{E} \left[ \check{X}_r^{u_2} \middle| \mathcal{F}_r^{Y^{u_2}} \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \int_s^t A \mathbb{E} \left[ X_r^{u_2} \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&\quad - \int_s^t \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E} \left[ \mathbb{E} \left[ X_r^{u_2} \middle| \mathcal{F}_r^{W^1} \right] \middle| \mathcal{F}_r^{Y^{u_2}} \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \mathbb{E} \left[ \int_s^t A X_r^{u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right] - \int_s^t \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E} \left[ \mathbb{E} \left[ \hat{X}_r^{u_2} \middle| \mathcal{F}_r^{Y^{u_2}} \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \mathbb{E} \left[ \int_s^t A X_r^{u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right] - \int_s^t \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E} \left[ \hat{X}_r^{u_2} \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \mathbb{E} \left[ \int_s^t A X_r^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \hat{X}_r^{u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right],
\end{aligned}$$

and

$$\begin{aligned}
\mathbb{E} \left[ \int_s^t B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\Phi}_r^{1i, u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right] &= \int_s^t B_{1i} R_{1i}^{-1} B_{1i}^\top \mathbb{E} \left[ \mathbb{E} \left[ \Phi_r^{1i, u_2} \middle| \mathcal{F}_r^{Y^{u_2}} \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] dr \\
&= \mathbb{E} \left[ \int_s^t B_{1i} R_{1i}^{-1} B_{1i}^\top \Phi_r^{1i, u_2} dr \middle| \mathcal{F}_s^{Y^{u_2}} \right],
\end{aligned}$$

which implies that

$$\begin{aligned}
& \mathbb{E} \left[ \Lambda_t^{2, u_2} - \Lambda_s^{2, u_2} \middle| \mathcal{F}_s^{Y^{u_2}} \right] \\
&= \mathbb{E} \left[ X_t^{u_2} - X_s^{u_2} - \int_s^t \left[ A X_r^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \hat{X}_r^{u_2} \right. \right. \\
&\quad \left. \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \Phi_r^{1i, u_2} + B_2 u_2 - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right] dr \middle| \mathcal{F}_s^{Y^{u_2}} \right] \\
&= \mathbb{E} \left[ \int_s^t C_1 dW^1 + \int_s^t C_2 dW^2 \middle| \mathcal{F}_s^{Y^{u_2}} \right] \\
&= \mathbb{E} \left[ \mathbb{E} \left[ \int_s^t C_1 dW^1 + \int_s^t C_2 dW^2 \middle| \mathcal{F}_s \right] \middle| \mathcal{F}_s^{Y^{u_2}} \right] = 0.
\end{aligned}$$

Thus,  $\Lambda_t^{2, u_2}$  is an  $\mathcal{F}_s^{Y^{u_2}}$ -martingale. Then similarly, there exists  $\mathcal{F}_s^{Y^{u_2}}$ -progressively measurable  $\lambda^{2, u_2}$ , such that  $\Lambda_t^{2, u_2} = \int_0^t \lambda_s^{2, u_2} (K_2(s) K_2^\top(s))^{-1} dU_s^{u_2}$ . Let  $\tilde{\zeta}^{u_2} = \{\tilde{\zeta}_t^{u_2}; 0 \leq t \leq T\}$

be a fixed but arbitrary  $\mathbb{R}^{n \times l_2}$ -valued square-integrable  $\mathcal{F}_t^{Y_2^{u_2}}$ -progressively measurable process. Consider the  $\mathcal{F}_t^{Y_2^{u_2}}$ -martingale:

$$\tilde{\varphi}_t^{u_2} \triangleq \int_0^t \tilde{\zeta}_s^{u_2} (K_2(s) K_2^\top(s))^{-1} dU_s^{u_2}. \quad (4.4)$$

Applying Itô's formula, we have

$$\mathbb{E}[\Lambda_t^{2,u_2} (\tilde{\varphi}_t^{u_2})^\top] = \mathbb{E} \int_0^t \lambda_s^{2,u_2} (K_2(s) K_2^\top(s))^{-1} (\tilde{\zeta}_s^{u_2})^\top ds, \quad \forall 0 \leq t \leq T.$$

Meanwhile, we can get

$$\begin{aligned} \Lambda_t^{2,u_2} (\tilde{\varphi}_t^{u_2})^\top &= \check{X}_t^{u_2} (\tilde{\varphi}_t^{u_2})^\top - x_0 (\tilde{\varphi}_0^{u_2})^\top - \int_0^t \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{X}_s^{u_2} \right. \\ &\quad \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\varphi}_s^{1i,u_2} + B_2 u_2 - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right\} (\tilde{\varphi}_s^{u_2})^\top ds. \end{aligned}$$

Taking expectation on both sides, and noting that

$$\begin{aligned} \mathbb{E}[\check{X}_t^{u_2} (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ X_t^{u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] (\tilde{\varphi}_t^{u_2})^\top \right] = \mathbb{E} [X_t^{u_2} (\tilde{\varphi}_t^{u_2})^\top], \\ \mathbb{E}[\check{X}_s^{u_2} (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ \check{X}_s^{u_2} (\tilde{\varphi}_t^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] = \mathbb{E} \left[ \check{X}_s^{u_2} \mathbb{E} \left[ (\tilde{\varphi}_t^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] \\ &= \mathbb{E} [\check{X}_s^{u_2} (\tilde{\varphi}_s^{u_2})^\top] = \mathbb{E} [X_s^{u_2} (\tilde{\varphi}_s^{u_2})^\top], \\ \mathbb{E}[\check{X}_s^{u_2} (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ X_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_t^{u_2})^\top \right] = \mathbb{E} \left[ \mathbb{E} \left[ \mathbb{E} \left[ X_s^{u_2} \middle| \mathcal{F}_s^{W^1} \right] \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_t^{u_2})^\top \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \hat{X}_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_t^{u_2})^\top \right] = \mathbb{E} \left[ \mathbb{E} \left[ \mathbb{E} \left[ \hat{X}_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_t^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \hat{X}_s^{u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_s^{u_2})^\top \right] = \mathbb{E} [\hat{X}_s^{u_2} (\tilde{\varphi}_s^{u_2})^\top], \\ \mathbb{E}[\check{\varphi}_s^{1i,u_2} (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ \check{\varphi}_s^{1i,u_2} (\tilde{\varphi}_t^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] = \mathbb{E} [\check{\varphi}_s^{1i,u_2} (\tilde{\varphi}_s^{u_2})^\top] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \varphi_s^{1i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\tilde{\varphi}_s^{u_2})^\top \right] = \mathbb{E} [\varphi_s^{1i,u_2} (\tilde{\varphi}_s^{u_2})^\top], \\ \mathbb{E}[u_2(s) (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ u_2(s) (\tilde{\varphi}_t^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] = \mathbb{E} [u_2(s) (\tilde{\varphi}_s^{u_2})^\top], \end{aligned}$$

we get

$$\begin{aligned} \mathbb{E}[\Lambda_t^{2,u_2} (\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} [X_t^{u_2} (\tilde{\varphi}_t^{u_2})^\top] - \mathbb{E} \left[ \int_0^t \left\{ A X_s^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \hat{X}_s^{u_2} \right. \right. \\ &\quad \left. \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \varphi_s^{1i,u_2} + B_2 u_2 - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right\} (\tilde{\varphi}_s^{u_2})^\top ds \right]. \end{aligned}$$

Noting

$$\begin{aligned} d\tilde{\varphi}_t^{u_2} &= \tilde{\zeta}_t^{u_2} (K_2(t) K_2^\top(t))^{-1} dU_t^{u_2} = \tilde{\zeta}_t^{u_2} (K_2(t) K_2^\top(t))^{-1} [f_2(t) (X_t^{u_2} - \check{X}_t^{u_2}) dt + K_2(t) dW_t^2] \\ &= \tilde{\zeta}_t^{u_2} (K_2(t) K_2^\top(t))^{-1} f_2(t) \tilde{X}_t^{u_2} dt + \tilde{\zeta}_t^{u_2} (K_2(t) K_2^\top(t))^{-1} K_2(t) dW_t^2, \end{aligned}$$

and applying Itô's formula, it follows that

$$\begin{aligned} \mathbb{E}[X_t^{u_2}(\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \int_0^t \left\{ X_s^{u_2}(\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right. \\ &\quad + \left[ AX_s^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \hat{X}_s^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \varphi_s^{1i, u_2} \right. \\ &\quad \left. \left. + B_2 u_2 - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right] (\tilde{\varphi}_s^{u_2})^\top + C_2 K_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right\} ds, \end{aligned}$$

among which

$$\begin{aligned} &\mathbb{E}[X_s^{u_2}(\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ X_s^{u_2}(\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ (\check{X}_s^{u_2} + \tilde{X}_s^{u_2})(\tilde{X}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \check{X}_s^{u_2}(\tilde{X}_s^{u_2})^\top + \tilde{X}_s^{u_2}(\tilde{X}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \check{X}_s^{u_2}(\tilde{X}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right] + \mathbb{E}[\tilde{\Sigma}_s f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top] \\ &= \mathbb{E}[\tilde{\Sigma}_s f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top], \end{aligned}$$

where  $\tilde{\Sigma}_s \triangleq \mathbb{E}[\tilde{X}_s^{u_2}(\tilde{X}_s^{u_2})^\top]$ . Thus, we have

$$\begin{aligned} \mathbb{E}[X_t^{u_2}(\tilde{\varphi}_t^{u_2})^\top] &= \mathbb{E} \int_0^t \left\{ \left[ AX_s^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \hat{X}_s^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \varphi_s^{1i, u_2} \right. \right. \\ &\quad \left. \left. + B_2 u_2 - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right] (\tilde{\varphi}_s^{u_2})^\top \right. \\ &\quad \left. + (\tilde{\Sigma}_s f_2^\top + C_2 K_2^\top) (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top \right\} ds, \end{aligned}$$

and

$$\mathbb{E}[\Lambda_t^{2, u_2}(\tilde{\varphi}_t^{u_2})^\top] = \mathbb{E} \int_0^t (\tilde{\Sigma}_s f_2^\top + C_2 K_2^\top) (K_2 K_2^\top)^{-1} (\tilde{\zeta}_s^{u_2})^\top ds,$$

Therefore, we obtain  $\lambda_t^2 = \tilde{\Sigma}_t f_2^\top(t) + C_2(t) K_2^\top(t)$ ,  $0 \leq t \leq T$ , and the equation of  $\check{X}^{u_2}$  is

$$\begin{aligned} \check{X}_t^{u_2} &= x_0 + \int_0^t \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{X}_r^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\varphi}_r^{1i, u_2} + B_2 u_2 \right. \\ &\quad \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right\} ds + \int_0^t (\tilde{\Sigma}_s f_2^\top + C_2 K_2^\top) (K_2 K_2^\top)^{-1} dU_s^{u_2}. \end{aligned} \quad (4.5)$$

In the following, we derive, for a fixed admissible control  $u_2 \in \mathcal{U}_{ad}^L$ , the filtering equation for  $\check{\varphi}^{1i, u_2}$ . We introduce

$$\begin{aligned} \Gamma_t^{i, u_2} &\triangleq \check{\varphi}_t^{1i, u_2} - g_{1i} - \int_t^T \left\{ [A(s) - B_{1i}(s) R_{1i}^{-1}(s) (B_{1i}(s)^\top P_s^{1i} + S_{1i}(s))] \check{\varphi}_s^{1i, u_2} \right. \\ &\quad + P_s^{1i} \alpha(s) + q_{1i}(s) - R_{1i}^{-1}(s) (B_{1i}(s)^\top P_s^{1i} + S_{1i}(s)) r_{1i}(s) \\ &\quad \left. + P_s^{1i} B_2(s) u_2(s) \right\} ds, \quad i = 1, 2, \dots, N. \end{aligned} \quad (4.6)$$

For fixed  $0 \leq s < t \leq T$ , we have

$$\begin{aligned} & \mathbb{E} \left[ \Gamma_t^{i,u_2} - \Gamma_s^{i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \\ &= \mathbb{E} \left[ \check{\varphi}_t^{1i,u_2} - \check{\varphi}_s^{1i,u_2} + \int_s^t \left\{ [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \check{\varphi}^{1i,u_2} + P^{1i}\alpha + q_{1i} \right. \right. \\ & \quad \left. \left. - R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})r_{1i} + P^{1i}B_2u_2 \right\} dr \middle| \mathcal{F}_s^{Y_2^{u_2}} \right], \end{aligned}$$

where

$$\begin{aligned} & \mathbb{E} \left[ \check{\varphi}_t^{1i,u_2} - \check{\varphi}_s^{1i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \varphi_t^{1i,u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] - \mathbb{E} \left[ \varphi_s^{1i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] = \mathbb{E} \left[ \varphi_t^{1i,u_2} - \varphi_s^{1i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right], \end{aligned}$$

and

$$\begin{aligned} & \mathbb{E} \left[ \int_s^t [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \check{\varphi}^{1i,u_2} dr \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \\ &= \int_s^t [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \mathbb{E} \left[ \mathbb{E} \left[ \varphi_r^{1i,u_2} \middle| \mathcal{F}_r^{Y_2^{u_2}} \right] \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] dr \\ &= \mathbb{E} \left[ \int_s^t [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \varphi_r^{1i,u_2} dr \middle| \mathcal{F}_s^{Y_2^{u_2}} \right], \end{aligned}$$

which imply that

$$\begin{aligned} & \mathbb{E} \left[ \Gamma_t^{i,u_2} - \Gamma_s^{i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \\ &= \mathbb{E} \left[ \varphi_t^{1i,u_2} - \varphi_s^{1i,u_2} + \int_s^t \left\{ [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \varphi^{1i} + P^{1i}\alpha + q_{1i} \right. \right. \\ & \quad \left. \left. - R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})r_{1i} + P^{1i}B_2u_2 \right\} dr \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \\ &= \mathbb{E} \left[ \int_s^t \lambda_r^{1,u_2} dW^1 \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] = \mathbb{E} \left[ \mathbb{E} \left[ \int_s^t \lambda_r^{1,u_2} dW^1 \middle| \mathcal{F}_s^{W^1} \right] \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] = 0, \end{aligned}$$

so  $\Gamma_t^{i,u_2}$  is an  $\mathcal{F}_t^{Y_2^{u_2}}$ -martingale. Similarly, we have

$$\Gamma_t^{i,u_2} = \int_0^t \tilde{\eta}_s^{i,u_2} (K_2 K_2^\top)^{-1} dU_s^{u_2}, \quad \forall 0 \leq t \leq T,$$

where  $\tilde{\eta}^{i,u_2} = \{\tilde{\eta}_t^{i,u_2}; 0 \leq t \leq T\}$  is to be determined,  $i = 1, 2, \dots, N$ . Let  $\tilde{\beta}^{i,u_2} = \{\tilde{\beta}_t^{i,u_2}; 0 \leq t \leq T\}$  be a fixed but arbitrary  $\mathbb{R}^{n \times l_2}$ -valued square-integrable  $\mathcal{F}_t^{Y_2^{u_2}}$ -progressively process. Consider the  $\{\mathcal{F}_t^{Y_2^{u_2}}\}$ -martingale

$$\varepsilon_t^{i,u_2} \triangleq \int_0^t \tilde{\beta}_s^{i,u_2} (K_2(s)K_2^\top(s))^{-1} dU_s^{u_2},$$

and apply Itô's formula, then we get

$$\mathbb{E} \left[ \Gamma_t^{i,u_2} (\varepsilon_t^{i,u_2})^\top \right] = \mathbb{E} \int_0^t \tilde{\eta}_s^{i,u_2} (K_2(s)K_2^\top(s))^{-1} (\tilde{\beta}_s^{i,u_2})^\top ds.$$

Moreover, we have

$$\begin{aligned} & \mathbb{E}[\Gamma_t^{i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] \\ &= \mathbb{E}[\check{\varphi}_t^{1i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] - \mathbb{E} \int_t^T \left\{ [A(s) - B_{1i}(s)R_{1i}^{-1}(s)(B_{1i}(s)^\top P_s^{1i} + S_{1i}(s))] \check{\varphi}_s^{1i,u_2} \right. \\ & \quad \left. + P_s^{1i} \alpha(s) + q_{1i}(s) - R_{1i}^{-1}(s)(B_{1i}(s)^\top P_s^{1i} + S_{1i}(s))r_{1i}(s) + P_s^{1i} B_2(s)u_2(s) \right\} (\boldsymbol{\varepsilon}_T^{i,u_2})^\top ds, \end{aligned}$$

where

$$\begin{aligned} \mathbb{E}[\Gamma_t^{i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ \Gamma_t^{i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] \right] = \mathbb{E}[\Gamma_t^{i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top], \\ \mathbb{E}[\check{\varphi}_t^{1i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ \check{\varphi}_t^{1i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] \right] = \mathbb{E}[\check{\varphi}_t^{1i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \varphi_t^{1i,u_2} \middle| \mathcal{F}_t^{Y_2^{u_2}} \right] (\boldsymbol{\varepsilon}_t^{i,u_2})^\top \right] = \mathbb{E}[\varphi_t^{1i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top], \\ \mathbb{E}[\check{\varphi}_s^{1i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ \check{\varphi}_s^{1i,u_2}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] = \mathbb{E}[\check{\varphi}_s^{1i,u_2}(\boldsymbol{\varepsilon}_s^{i,u_2})^\top] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \varphi_s^{1i,u_2} \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] (\boldsymbol{\varepsilon}_s^{i,u_2})^\top \right] = \mathbb{E}[\varphi_s^{1i,u_2}(\boldsymbol{\varepsilon}_s^{i,u_2})^\top], \\ \mathbb{E}[u_2(s)(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] &= \mathbb{E} \left[ \mathbb{E} \left[ u_2(s)(\boldsymbol{\varepsilon}_T^{i,u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] = \mathbb{E}[u_2(s)(\boldsymbol{\varepsilon}_s^{i,u_2})^\top], \end{aligned}$$

which implies that

$$\begin{aligned} & \mathbb{E}[\Gamma_t^{i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top] \\ &= \mathbb{E}[\varphi_t^{1i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top] - \mathbb{E} \int_t^T \left\{ [A(s) - B_{1i}(s)R_{1i}^{-1}(s)(B_{1i}(s)^\top P_s^{1i} + S_{1i}(s))] \varphi_s^{1i,u_2} \right. \\ & \quad \left. + P_s^{1i} \alpha(s) + q_{1i}(s) - R_{1i}^{-1}(s)(B_{1i}(s)^\top P_s^{1i} + S_{1i}(s))r_{1i}(s) + P_s^{1i} B_2(s)u_2(s) \right\} (\boldsymbol{\varepsilon}_s^{i,u_2})^\top ds. \end{aligned}$$

Now, we also get

$$d\boldsymbol{\varepsilon}_t^{i,u_2} = \tilde{\beta}_t^{i,u_2} (K_2 K_2^\top)^{-1} dU_t^{u_2} = \tilde{\beta}_t^{i,u_2} (K_2 K_2^\top)^{-1} f_2 \tilde{X}_t^{u_2} dt + \tilde{\beta}_t^{i,u_2} (K_2 K_2^\top)^{-1} K_2 dW^2.$$

By Itô's formula, we have

$$\begin{aligned} & \mathbb{E}[g_{1i}(\boldsymbol{\varepsilon}_T^{i,u_2})^\top] \\ &= \mathbb{E}[\varphi_t^{1i,u_2}(\boldsymbol{\varepsilon}_t^{i,u_2})^\top] + \mathbb{E} \int_t^T \left\{ \varphi_s^{1i,u_2} (\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^{i,u_2})^\top \right. \\ & \quad - [(A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})) \varphi_s^{1i,u_2} + P^{1i} \alpha + q_{1i} \\ & \quad \left. - R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})r_{1i} + P^{1i} B_2 u_2] (\boldsymbol{\varepsilon}_s^{i,u_2})^\top \right\} ds, \end{aligned}$$

among which

$$\begin{aligned} & \mathbb{E}[\varphi_s^{1i,u_2} (\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^i)^\top] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \varphi_s^{1i,u_2} (\tilde{X}_s^{u_2})^\top f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^i)^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] \right] \\ &= \mathbb{E} \left[ \mathbb{E} \left[ \check{\varphi}_s^{1i,u_2} (\tilde{X}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^i)^\top \right] \\ & \quad + \mathbb{E} \left[ \mathbb{E} \left[ (\varphi_s^{1i,u_2} - \check{\varphi}_s^{1i,u_2}) (\tilde{X}_s^{u_2})^\top \middle| \mathcal{F}_s^{Y_2^{u_2}} \right] f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^i)^\top \right] \\ &= \mathbb{E}[\check{\Sigma}_s^i f_2^\top (K_2 K_2^\top)^{-1} (\tilde{\beta}_s^i)^\top], \end{aligned}$$

where  $\check{\Sigma}_s^i \triangleq \mathbb{E}[(\varphi_s^{1i,u_2} - \check{\phi}_s^{1i,u_2})(\check{X}_s^{u_2})^\top]$ . Then we have

$$\mathbb{E}[\Gamma_t^{i,u_2}(\varepsilon_t^{i,u_2})^\top] = -\mathbb{E}\int_t^T \check{\Sigma}_s^i f_2^\top (K_2 K_2^\top)^{-1} (\check{\beta}_s^i)^\top ds.$$

Comparing this with  $\mathbb{E}[\Gamma_t^{i,u_2}(\varepsilon_t^{i,u_2})^\top] = \mathbb{E}\int_0^t \check{\eta}_s^{i,u_2} (K_2 K_2^\top)^{-1} (\check{\beta}_s^i)^\top ds$ , we achieve

$$0 = \mathbb{E}[\Gamma_T^{i,u_2}(\varepsilon_T^{i,u_2})^\top] = \mathbb{E}\int_0^T \check{\eta}_s^{i,u_2} (K_2 K_2^\top)^{-1} (\check{\beta}_s^i)^\top ds,$$

and

$$\mathbb{E}[\Gamma_t^{i,u_2}(\varepsilon_t^{i,u_2})^\top] = -\mathbb{E}\int_t^T \check{\eta}_s^{i,u_2} (K_2 K_2^\top)^{-1} (\check{\beta}_s^i)^\top ds,$$

which implies that  $\check{\eta}_t^i = \check{\Sigma}_t^i f_2^\top(t)$ ,  $0 \leq t \leq T$ . Therefore, we obtain the equation of  $\check{\phi}^{1i,u_2}$ :

$$\begin{cases} -d\check{\phi}_t^{1i,u_2} = \left\{ [A - B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})] \check{\phi}^{1i,u_2} + P^{1i}\alpha + q_{1i} \right. \\ \quad \left. - R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})r_{1i} + P^{1i}B_{2i}u_2 \right\} dt - \check{\gamma}_t^{1i} d\check{U}_t^{u_2}, \\ \check{\phi}_T^{1i,u_2} = g_{1i}, \end{cases} \quad (4.7)$$

where  $\check{\gamma}_t^{1i} \triangleq \check{\Sigma}_t^i f_2^\top(t)(K_2(t)K_2^\top(t))^{-1}$ .

Next, we mainly give the coupled representations of  $\check{\Sigma} \equiv \mathbb{E}[(X^{u_2} - \check{X}^{u_2})(X^{u_2} - \check{X}^{u_2})^\top]$  and  $\check{\Sigma}^i \equiv \mathbb{E}[(\varphi^{1i,u_2} - \check{\phi}^{1i,u_2})(X^{u_2} - \check{X}^{u_2})^\top]$  by the following equations:

$$\begin{aligned} \check{\Sigma}_t = \int_0^t & \left\{ [A - (\check{\Sigma}_s f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2] \check{\Sigma} \right. \\ & + \check{\Sigma} [A - (\check{\Sigma}_s f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2]^\top \\ & - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] \\ & - \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] \left[ \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right]^\top - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\Sigma}^i \\ & \left. - \sum_{i=1}^N \check{\Sigma}^i (B_{1i} R_{1i}^{-1} B_{1i}^\top)^\top + C_1 C_1^\top + \check{\Sigma}_s f_2^\top (K_2 K_2^\top)^{-1} f_2 \check{\Sigma} \right\} ds, \end{aligned} \quad (4.8)$$

and

$$\begin{aligned} \check{\Sigma}_t^i = \int_0^t & \left\{ [A - (\check{\Sigma}_s f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2 - (A - B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}))] \check{\Sigma}^i \right. \\ & - B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E}[(\varphi^{1i,u_2} - \check{\phi}^{1i,u_2})(\hat{X}^{u_2} - \check{X}^{u_2})^\top] \\ & - B_{1i} R_{1i}^{-1} B_{1i}^\top \mathbb{E}[(\varphi^{1i,u_2} - \check{\phi}^{1i,u_2})(\varphi^{1i,u_2} - \check{\phi}^{1i,u_2})^\top] \\ & \left. - \check{\Sigma}_s^i f_2^\top (K_2 K_2^\top)^{-1} f_2 \check{\Sigma} + \lambda^{1i} C_1^\top + \check{\Sigma}_s f_2^\top K_2^{-1} (\check{\gamma}^{1i})^\top \right\} ds, \end{aligned} \quad (4.9)$$

where

$$\begin{aligned}
& \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] \\
&= \int_0^t \left\{ \left[ A - (\tilde{\Sigma}^{u_2} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2 \right] \tilde{\Sigma} \right. \\
&\quad - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\hat{X}^{u_2} - \check{X}^{u_2})^\top] \\
&\quad - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \\
&\quad \left. + \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \tilde{\Sigma} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\Sigma}^i + C_1 C_1^\top \right\} ds,
\end{aligned} \tag{4.10}$$

$$\begin{aligned}
& \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\hat{X}^{u_2} - \check{X}^{u_2})^\top] \\
&= \int_0^t \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\hat{X}^{u_2} - \check{X}^{u_2})^\top] \right. \\
&\quad + \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\hat{X}^{u_2} - \check{X}^{u_2})^\top] \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right]^\top \\
&\quad - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \\
&\quad - \sum_{i=1}^N \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] (B_{1i} R_{1i}^{-1} B_{1i}^\top)^\top \\
&\quad - (\tilde{\Sigma} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2 \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] \\
&\quad - \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] [(\tilde{\Sigma} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2]^\top \\
&\quad \left. + C_1 C_1^\top + (\tilde{\Sigma} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} (\tilde{\Sigma} f_2^\top + C_2 K_2^\top)^\top \right\} ds,
\end{aligned} \tag{4.11}$$

$$\begin{aligned}
& \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \\
&= \int_0^t \left\{ -\tilde{\Sigma} f_2^\top (K_2 K_2^\top)^{-1} f_2 \mathbb{E}[(\hat{X}^{u_2} - \check{X}^{u_2})(\check{X}^{u_2})^\top] \right. \\
&\quad - B_{1i} R_{1i}^{-1} B_{1i}^\top \mathbb{E}[(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \\
&\quad - (\tilde{\Sigma} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} f_2 \check{\Sigma}^i + \lambda^{1i, u_2} C_1^\top \\
&\quad \left. + (\tilde{\Sigma} f_2^\top + C_2 K_2^\top)(K_2 K_2^\top)^{-1} (\check{\gamma}^{1i})^\top \right\} ds,
\end{aligned} \tag{4.12}$$

and

$$\begin{aligned}
& \mathbb{E}[(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \\
&= \int_t^T \left\{ \left[ A - B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \mathbb{E}[(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \right. \\
&\quad + \mathbb{E}[(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})(\varphi^{1i, u_2} - \check{\varphi}^{1i, u_2})^\top] \left[ A - B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right]^\top \\
&\quad \left. + 2\tilde{\Sigma}^i f_2^\top (K_2 K_2^\top)^{-1} f_2 \check{\Sigma}^i - \lambda^{1i, u_2} (\lambda^{1i, u_2})^\top - \check{\gamma}^{1i} (\check{\gamma}^{1i})^\top \right\} ds.
\end{aligned} \tag{4.13}$$

Now, we can regard the partially observed problem of the leader in this section, as the completely observable case with the following state equation:

$$\left\{ \begin{array}{l} d\check{X}_t^{u_2} = \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{X}^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\phi}^{1i, u_2} + B_2 u_2 \right. \\ \quad \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha + (\tilde{\Sigma} f_2^\top + C_2 K_2^\top) (K_2 K_2^\top)^{-1} f_2 \check{X}^{u_2} \right\} dt \\ \quad + \left( \tilde{\Sigma} f_2^\top (K_2^\top)^{-1} + C_2 \right) dW_t^2, \\ -d\check{\phi}_t^{1i, u_2} = \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{\phi}^{1i, u_2} + P^{1i} \alpha + q_{1i} \right. \\ \quad \left. - R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) r_{1i} + P^{1i} B_2 u_2 \right\} dt - \check{\gamma}_t^{1i, u_2} d\check{U}_t^{u_2}, \\ \check{X}_0^{u_2} = x_0, \quad \check{\phi}_T^{1i, u_2} = g_{1i}, \quad i = 1, 2, \dots, N. \end{array} \right. \quad (4.14)$$

In the following, we will consider the following reduced case of the leader's cost functional with  $g_2 = S_2 = q_2 = r_2 = 0$  (taking non-zero values has no essential influence besides the complex computation) and also by same orthogonal decomposition we have:

$$\begin{aligned} \tilde{J}_2(x_0; u_2) &\equiv J_2(x_0; \bar{u}_1, u_2) = \mathbb{E} \left[ \langle G_2 X_T^{u_2}, X_T^{u_2} \rangle + \int_0^T \left( \langle Q_2 X^{u_2}, X^{u_2} \rangle + \langle R_2 u_2, u_2 \rangle \right) dt \right] \\ &= \mathbb{E} \left[ \langle G_2 \check{X}_T^{u_2}, \check{X}_T^{u_2} \rangle + \int_0^T \left( \langle Q_2 \check{X}^{u_2}, \check{X}^{u_2} \rangle + \langle R_2 u_2, u_2 \rangle \right) dt \right] \\ &\quad + \mathbb{E} \left[ \langle G_2 \tilde{X}_T^{u_2}, \tilde{X}_T^{u_2} \rangle + \int_0^T \langle Q_2 \tilde{X}^{u_2}, \tilde{X}^{u_2} \rangle dt \right] \\ &\triangleq \check{J}_2(x_0; u_2) + \tilde{J}_2(x_0). \end{aligned} \quad (4.15)$$

**Remark 4.1.** In the following discussion, the LQ optimal control theory of FBSDEs is necessary only if the control system is considered in the partially observed case on condition that the partially observed control is transformed into the completely observed case due to orthogonal decomposition of state process. The difference is that the fully coupled multi-dimensional system with inhomogeneous term should be considered because of the insert of optimal control of followers. This is always the case whether the followers own the full information or not when the leader can not observe the state system directly. However, another setting may have more interest that all the followers only know partial information but the leader knows all the information, in this case, the result in [8] is no longer applicable, now this question essentially boils down to a LQ stochastic optimal control of fully coupled FBSDEs with general conditional mean-field terms. The interesting extension has been studied in our another working paper while the decoupling technique of mean-filed LQ control are involved.

Apply the stochastic LQ optimal control theory in the Appendix, we now complete the leader's problem. For convenience, we rewrite (4.14) and (4.15) as follows:

$$\left\{ \begin{array}{l} d\check{X}_t^{u_2} = \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{X}^{u_2} - \sum_{i=1}^N B_{1i} R_{1i}^{-1} B_{1i}^\top \check{\phi}^{1i, u_2} + B_2 u_2 \right. \\ \quad \left. - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right\} dt + \sum_{j=1}^{l_2} [\check{\Sigma} f_2^\top (K_2^\top)^{-1} + C_2]^j d\check{U}_t^{j, u_2}, \\ -d\check{\phi}_t^{1i, u_2} = \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) \right] \check{\phi}^{1i, u_2} + P^{1i} \alpha + q_{1i} \right. \\ \quad \left. - R_{1i}^{-1} (B_{1i}^\top P^{1i} + S_{1i}) r_{1i} + P^{1i} B_2 u_2 \right\} dt - \sum_{j=1}^{l_2} \check{\gamma}_t^{1ij, u_2} d\check{U}_t^{j, u_2}, \\ \check{X}_0^{u_2} = x_0, \check{\phi}_T^{1i, u_2} = g_{1i}, i = 1, 2, \dots, N, \end{array} \right. \quad (4.16)$$

and

$$\begin{aligned} \check{J}_2(x_0; u_2) &= \mathbb{E} \left[ \langle G_2 \check{X}_T^{u_2}, \check{X}_T^{u_2} \rangle + \int_0^T \left( \langle Q_2 \check{X}^{u_2}, \check{X}^{u_2} \rangle + \langle R_2 u_2, u_2 \rangle \right) dt \right] \\ &\quad + \mathbb{E} \left[ \langle G_2 \check{X}_T^{u_2}, \check{X}_T^{u_2} \rangle + \int_0^T \langle Q_2 \check{X}^{u_2}, \check{X}^{u_2} \rangle dt \right] \\ &\equiv \check{J}_2(x_0; u_2) + \check{J}_2(x_0). \end{aligned} \quad (4.17)$$

Now, for  $i = 1, \dots, N$  and  $j = 1, \dots, l_2$ , we have

$$\begin{aligned} A_1 &= A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i} P^{1i} + S_{1i}), \quad B_{1i} = -B_{1i} R_{1i}^{-1} B_{1i}^\top, \quad E_1 = -\sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha, \\ D_1 &= B_2, \quad E_2 = \check{\Sigma} f_2^\top (K_2^\top)^{-1} + C_2, \quad B_{3i}^\top = A - B_{1i} R_{1i}^{-1} (B_{1i} P^{1i} + S_{1i}), \quad D_{3i} = P^{1i} B_2, \\ E_{3i} &= P^{1i} \alpha + q_{1i} - R_{1i}^{-1} (B_{1i} P^{1i} + S_{1i}) r_{1i}, \quad A_4 = 2Q_2, \quad D_4 = 2R_2, \quad G = 2G_2, \\ \xi_i &= g_{1i}, \quad A_2^j = A_{3i} = B_{2i}^j = B_{4i} = C_{1i}^j = C_{2i}^{jj} = C_{3i}^j = C_{4i}^j = D_2^j = H_i = F_i = 0, \\ L_1^j &= I_{Nn \times Nn}, \quad L_2^j = I_{n \times n}, \quad L_3^j = 0_{n \times n}, \quad L_4^j = 0_{n \times Nn}, \quad L_5 = 2R_2, \quad S_1^j = P_1, \\ S_2^j &= S_4^j = \check{V}_1^j + P_1 [\check{\Sigma} f_2^\top (K_2^\top)^{-1} + C_2]^j, \quad L_6 = -(2R_2)^{-1} B_2 P_1, \\ L_7 &= -(2R_2)^{-1} B_2^\top ((P^1)^\top + P_2), \quad S_3 = -(2R_2)^{-1} B_2^\top \check{\phi}_1, \quad L_8^j = 0_{n \times n}, \quad L_9^j = 0_{n \times Nn}, \\ L_{10}^j &= 0_{Nn \times n}, \quad L_{11}^j = 0_{Nn \times Nn}, \quad S_5^j = \check{V}_2^j + P_2 [\check{\Sigma} f_2^\top (K_2^\top)^{-1} + C_2]^j. \end{aligned}$$

Thus, the optimal control of the leader is

$$\begin{aligned} \bar{u}_2(t) &= -(2R_2)^{-1} [B_2 P_1 + B_2^\top ((P^1)^\top + P_2) P_3^{-1} P_2^\top] \bar{X}(t) \\ &\quad + (2R_2)^{-1} B_2^\top ((P^1)^\top + P_2) P_3^{-1} \bar{\phi}^1(t) \\ &\quad - (2R_2)^{-1} B_2^\top ((P^1)^\top + P_2) P_3^{-1} \check{\phi}_2(t) - (2R_2)^{-1} B_2^\top \check{\phi}_1(t), \end{aligned} \quad (4.18)$$

where  $\bar{X} \equiv \check{X}^{\bar{u}_2}$  and  $\bar{\phi}^1 = \check{\phi}^{1, \bar{u}_2}$ ,

$$P^1 \equiv \begin{pmatrix} P^{11} \\ P^{12} \\ \vdots \\ P^{1N} \end{pmatrix}$$

satisfies (3.13),  $P_1, P_2, P_3$  satisfy

$$\begin{cases} \dot{P}_1 + P_1 \left[ A - \sum_{i=1}^N B_{1i} R_{1i}^{-1} (B_{1i} P^{1i} + S_{1i}) + B_1^\top P_2^\top \right] \\ + \left[ A^\top - \sum_{i=1}^N (P^{1i} B_{1i}^\top + S_{1i}^\top) R_{1i}^{-1} B_{1i}^\top + P_2 B_1 \right] P_1 - P_1 B_2 (2R_2)^{-1} B_2 P_1 + 2Q_2 = 0, \\ P_1(T) = 2G_2, \end{cases} \quad (4.19)$$

$$\begin{cases} \dot{P}_2 - P_1 B_1^\top P_3 - P_1 B_2 (2R_2)^{-1} B_2^\top ((P^1)^\top + P_2) + P_2 B_3 \\ + \left[ A^\top - \sum_{i=1}^N (P^{1i} B_{1i}^\top + S_{1i}^\top) R_{1i}^{-1} B_{1i}^\top + P_2 B_1 \right] P_2 = 0, \\ P_2(T) = 0, \end{cases} \quad (4.20)$$

$$\begin{cases} \dot{P}_3 + (P_2^\top B_1^\top + B_3^\top) P_3 + P_3 (B_1 P_2 + B_3) - (P^1 + P_2^\top) B_2 (2R_2)^{-1} B_2^\top ((P^1)^\top + P_2) = 0, \\ P_3(T) = 0, \end{cases} \quad (4.21)$$

respectively, and  $(\check{\phi}_1, \check{V}_1), (\check{\phi}_2, \check{V}_2)$  satisfy

$$\begin{cases} d\check{\phi}_1(t) = - \left\{ \left[ P_2 B_1 + A^\top - \sum_{i=1}^N (P^{1i} B_{1i}^\top + S_{1i}^\top) R_{1i}^{-1} B_{1i}^\top - P_1 B_2 (2R_2)^{-1} B_2^\top \right] \check{\phi}_1 \right. \\ \left. + P_1 B_1^\top \check{\phi}_2 + P_1 \left( - \sum_{i=1}^N B_{1i} R_{1i}^{-1} r_{1i} + \alpha \right) \right\} dt + \sum_{j=1}^{l_2} \check{V}_1^j d\check{U}_t^j, \\ d\check{\phi}_2(t) = - \left\{ (P_2^\top B_1^\top + B_3^\top) \check{\phi}_2 - [P_3 B_1 + (P^1 + P_2^\top) B_2 (2R_2)^{-1} B_2^\top] \check{\phi}_1 \right. \\ \left. + P_2^\top E_1 + E_3 \right\} dt + \sum_{j=1}^{l_2} \check{V}_2^j d\check{U}_t^j, \\ \check{\phi}_1(T) = 0, \check{\phi}_2(T) = g_1, \end{cases} \quad (4.22)$$

with  $\check{U}^j \equiv \check{U}^{j, \bar{u}_2}$ . The optimal cost of  $\check{J}_2(x_0; u_2)$  is

$$\check{J}_2(x_0; \bar{u}_2) = \frac{1}{2} \mathbb{E} \left[ \mathbb{R}_2 + \int_0^T M_5 dt \right], \quad (4.23)$$

where  $\mathbb{R}_2 = (X_0 + P_1^{-1}(0) \check{\phi}_1(0))^\top P_1(0) (X_0 + P_1^{-1}(0) \check{\phi}_1(0))$ , and the explicit representation of  $M_5$  is omitted, which indeed take values when insert the notations in this section into (A.29), with

$$\begin{aligned} \tilde{P} &= \begin{pmatrix} P_1 + P_2 P_3^{-1} P_2^\top & -P_2 P_3^{-1} \\ -P_3^{-1} P_2^\top & P_3^{-1} \end{pmatrix}, \\ \check{\phi}_1 &= -P_1^{-1} \check{\phi}_1, \quad \check{\phi}_2 = -P_2^\top P_1^{-1} \check{\phi}_1 + \check{\phi}_2 \\ \check{V}_1^j &= -P_1^{-1} \check{V}_1^j, \quad \check{V}_2^j = -P_2^\top P_1^{-1} \check{V}_1^j + \check{V}_2^j. \end{aligned}$$

Next, we deal with  $\tilde{J}_2(x_0)$  independent of  $u_2$ . First, we need the equation of  $\tilde{X} \equiv \tilde{X}^{\bar{u}_2}$ :

$$\begin{aligned} d\tilde{X}_t = & \left\{ A\tilde{X} - \sum_{i=1}^N B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})(\tilde{X} - \bar{X}) - \sum_{i=1}^N B_{1i}R_{1i}^{-1}B_{1i}^\top(\bar{\varphi}^{1i} - \tilde{\varphi}^{1i}) \right. \\ & \left. - (\tilde{\Sigma}f_2^\top + C_2K_2^\top)(K_2K_2^\top)^{-1}f_2\tilde{X} \right\} dt \\ & + \sum_{j=1}^{l_1} C_1^j dW^{1j} - \sum_{j=1}^{l_2} [\tilde{\Sigma}f_2^\top (K_2^\top)^{-1}]^j dW^{2j}, \end{aligned} \quad (4.24)$$

and introduce the ODE as follows

$$\begin{cases} \dot{p} + p[A - (\tilde{\Sigma}f_2^\top + C_2K_2^\top)(K_2K_2^\top)^{-1}f_2] \\ \quad + [A - (\tilde{\Sigma}f_2^\top + C_2K_2^\top)(K_2K_2^\top)^{-1}f_2]^\top p + Q_2 = 0, \\ p_T = G_2. \end{cases} \quad (4.25)$$

Apply Itô's formula to  $\langle p\tilde{X}, \tilde{X} \rangle$  and put it into  $\tilde{J}_2(x_0)$ , we obtain

$$\begin{aligned} \tilde{J}_2(x_0) = & \int_0^T \left\{ -p \sum_{i=1}^N B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})\mathbb{E}[(\tilde{X} - \bar{X})\tilde{X}^\top] \right. \\ & - \mathbb{E}[(\tilde{X} - \bar{X})\tilde{X}^\top] \sum_{i=1}^N (B_{1i}^\top P^{1i} + S_{1i})^\top R_{1i}^{-1}B_{1i}^\top p \\ & - p \sum_{i=1}^N B_{1i}R_{1i}^{-1}B_{1i}^\top \tilde{\Sigma}^i - \sum_{i=1}^N (\tilde{\Sigma}^i)^\top B_{1i}R_{1i}^{-1}B_{1i}^\top p + \sum_{j=1}^{l_1} (C_1^j)^\top p C_1^j \\ & \left. + \sum_{j=1}^{l_2} [(\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j]^\top (\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j \right\} dt. \end{aligned} \quad (4.26)$$

Finally, we have the optimal cost of the leader as follows:

$$\begin{aligned} \tilde{J}_2(\bar{u}_2) = & \frac{1}{2}\mathbb{R}_2 + \frac{1}{2} \int_0^T \left\{ \mathbb{E}[M_5] - 2p \sum_{i=1}^N B_{1i}R_{1i}^{-1}(B_{1i}^\top P^{1i} + S_{1i})\mathbb{E}[(\tilde{X} - \bar{X})\tilde{X}^\top] \right. \\ & - 2\mathbb{E}[(\tilde{X} - \bar{X})\tilde{X}^\top] \sum_{i=1}^N (B_{1i}^\top P^{1i} + S_{1i})^\top R_{1i}^{-1}B_{1i}^\top p \\ & - 2p \sum_{i=1}^N B_{1i}R_{1i}^{-1}B_{1i}^\top \tilde{\Sigma}^i - 2 \sum_{i=1}^N (\tilde{\Sigma}^i)^\top B_{1i}R_{1i}^{-1}B_{1i}^\top p + 2 \sum_{j=1}^{l_1} (C_1^j)^\top p C_1^j \\ & \left. + 2 \sum_{j=1}^{l_2} [(\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j]^\top (\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j \right\} dt, \end{aligned} \quad (4.27)$$

where  $\tilde{\Sigma}, \tilde{\Sigma}^i$  and  $\mathbb{E}[(\tilde{X} - \bar{X})\tilde{X}^\top]$  can be solved by equations (4.8)-(4.13).

## 5. APPLICATION TO MULTI-AGENT FORMATION CONTROL

There are increasingly interest for the scholars using differential game methodology to model and analyze the optimization in multi-agent formation control problem. Gu [7] formulated the LQ leader-follower formation control where the Nash differential game theory are applied for the agents through the use of graph theory and an open-loop Nash equilibrium solution are investigated. Lin [16] considered a formation control problem for

a multiple-UAV (unmanned aerial vehicle) system, and the formation control problem is formulated and solved as a differential game problem due to the optimization of UAVs' differential objectives based on its local information. Mylvaganam and Astolfi [25] studied a multi-agent formation system consisting of one leader and a group of followers, in which the leader is steered towards a target position while the followers seek to form and maintain a pre-defined formation about the leader, while avoiding collisions, is considered. Therefore, the problem is posed as a differential game. For this problem feedback Nash and Stackelberg equilibrium solutions are equivalent. In particular, the problem simplifies to a LQ differential game when collision avoidance is not taken into account. Moreover, some very foundational insights are provided in [18] which investigates the differential private algorithm for the average output consensus control of continuous-time heterogeneous multi-agent systems, then a sequence of further interesting new control and game results are first developed in [35], which are of great inspiration for our future work. Especially, By making interesting connections to [18, 35], it is worth noting that the consideration and introduction of key ingredients including differentially private, information exchange would motivate more practical applications in our paper and match our hierarchical feature in terms of asymmetrical roles, and try to apply the stochastic Stackelberg differential game theory into the problem [18, 35]. Therefore, in this paper we aim to extend the existing formation control to fall within the stochastic Stackelberg game problem and develop the partially observed stochastic case with the introduction of hierarchical level and observation processes.

A team has  $N + 1$  robots including one leader robot and  $N$  follower robots, each of which is described by its dynamics in the following. For the single leader robot with  $n$ -dimensional coordinates  $q^2 \in \mathbb{R}^n$ , the state and control vectors are  $X_t^2 = [(q_t^2)^\top, (\dot{q}_t^2)^\top]^\top \in \mathbb{R}^{2n}$  and  $u_2 \in \mathbb{R}^m$  and similarly for the follower robots with state and control vectors being  $X_t^{1i} = [(q_t^{1i})^\top, (\dot{q}_t^{1i})^\top]^\top \in \mathbb{R}^{2n}$  and  $u_{1i} \in \mathbb{R}^m$  for  $i = 1, \dots, N$ .

The dynamics of the leader robot and the follower robots are given as follows:

$$\begin{aligned} dX_t^2 &= [aX_t^2 + bu_2(t)]dt + C_1^2 dW_t^1 + C_2^2 dW_t^2, \\ dX_t^{1i} &= [aX_t^{1i} + bu_{1i}(t)]dt + C_1^{1i} dW_t^1 + C_2^{1i} dW_t^2, \quad i = 1, \dots, N, \end{aligned} \quad (5.1)$$

where

$$a = \begin{pmatrix} 0 & I_{n \times n} \\ 0 & 0 \end{pmatrix} \in \mathbb{R}^{2n \times 2n}, \quad b = \begin{pmatrix} 0 \\ I_{n \times m} \end{pmatrix} \in \mathbb{R}^{2n \times m},$$

and  $C_1^2, C_1^{11}, \dots, C_1^{1N} \in \mathbb{R}^{2n \times l_1}$ ,  $C_2^2, C_2^{11}, \dots, C_2^{1N} \in \mathbb{R}^{2n \times l_2}$ .

Concatenating the states of all  $N + 1$  robots in a team into a vector:

$$\begin{aligned} X &= \begin{pmatrix} X^2 \\ X^{11} \\ \vdots \\ X^{1N} \end{pmatrix} \in \mathbb{R}^{2(N+1)n}, \quad C_1 = \begin{pmatrix} C_1^2 \\ C_1^{11} \\ \vdots \\ C_1^{1N} \end{pmatrix} \in \mathbb{R}^{2(N+1)n \times l_1}, \quad C_2 = \begin{pmatrix} C_2^2 \\ C_2^{11} \\ \vdots \\ C_2^{1N} \end{pmatrix} \in \mathbb{R}^{2(N+1)n \times l_2}, \\ \tilde{X} &= \begin{pmatrix} X \\ I_{2n} \end{pmatrix} \in \mathbb{R}^{2(N+2)n}, \quad \tilde{C}_1 = \begin{pmatrix} C_1 \\ 0 \end{pmatrix} \in \mathbb{R}^{2(N+2)n \times l_1}, \quad \tilde{C}_2 = \begin{pmatrix} C_2 \\ 0 \end{pmatrix} \in \mathbb{R}^{2(N+2)n \times l_2}, \end{aligned}$$

where  $I_{2n} \equiv [1, 1, \dots, 1]^\top$  is a  $\mathbb{R}^{2n}$ -valued row vector and let

$$A = \begin{pmatrix} I_{(N+1) \times (N+1)} & \\ & 0 \end{pmatrix} \otimes a \in \mathbb{R}^{2(N+2)n \times 2(N+2)n},$$

$$B_2 = \begin{pmatrix} 1 \\ 0 \\ \vdots \\ 0 \\ 0 \end{pmatrix} \otimes b \in \mathbb{R}^{2(N+2)n \times m}, \quad B_{1i} = \begin{pmatrix} 0 \\ 1 \\ 0 \\ \vdots \\ 0 \end{pmatrix} \otimes b \in \mathbb{R}^{2(N+2)n \times m}, \quad i = 1, \dots, N,$$

where  $(0 \ 1 \ 0 \ \dots \ 0)^\top \in \mathbb{R}^{N+2}$  denotes the vector that the remaining components are all 0 except for the  $(i+1)$ th component being 1. The operator  $\otimes$  is the Kronecker product.

Then we have

$$d\tilde{X}_t = \left[ A\tilde{X}_t + B_2 u_2(t) + \sum_{i=1}^N B_{1i} u_i(t) \right] dt + \tilde{C}_1 dW_t^1 + \tilde{C}_2 dW_t^2. \quad (5.2)$$

Let

$$X^{2,d} = \begin{pmatrix} q^{2,d} \\ \dot{q}^{2,d} \end{pmatrix}, \quad X^{1i,d} = \begin{pmatrix} q^{1i,d} \\ \dot{q}^{1i,d} \end{pmatrix}$$

be the desired state vector for robots. Similarly,

$$\begin{pmatrix} X^{2,d} \\ X^{11,d} \\ \vdots \\ X^{1N,d} \end{pmatrix},$$

where

$$\begin{aligned} dX_t^{2,d} &= [aX_t^{2,d} + bu_2^d(t)] dt, \\ dX_t^{1i,d} &= [aX_t^{1i,d} + bu_{1i}^d(t)] dt, \quad i = 1, \dots, N, \end{aligned} \quad (5.3)$$

and the concatenating state equations is

$$d\tilde{X}_t^d = [A\tilde{X}_t^d + B_2 u_2^d(t) + \sum_{i=1}^N B_{1i} u_{1i}^d(t)] dt. \quad (5.4)$$

Now we use the graph to represent the formation control interconnection between robots based on the original work of Fax and Murray [5] which provides a link between graph theory and the formation control for a given communication topology. A vertex of the graph corresponds to a robot and the edges of the graph capture the dependence of the interconnections. Formally, a directed graph  $\mathcal{G} = (\mathcal{V}, \mathcal{E})$  consists of a set of vertices  $\mathcal{V} = \{v_{11}, \dots, v_{1N}, v_2\}$ , indexed by the robots in a team, and a set of edges  $\mathcal{E} = \{(v_i, v_j) \in \mathcal{V} \times \mathcal{V}\}$ , containing ordered pairs of distinct vertices. Assuming the graph has no loops, i.e.,  $(v_i, v_j) \in \mathcal{E}$  implies  $v_i \neq v_j$ . A graph is connected if for any vertices  $v_i, v_j \in \mathcal{V}$ , there exists a path of edges in  $\mathcal{E}$  from  $v_i$  to  $v_j$ . An edge-weighted graph is a graph in which each edge is assigned a weight. The edge  $(v_i, v_j)$  is associated with weight  $w_{ij} \geq 0$ . To control a team to keep a formation, the graph should be assumed to be connected.

The incidence matrix  $D$  of a directed graph  $\mathcal{G}$  is the  $\{0, \pm 1\}$ -matrix with rows and columns indexed by vertices of  $\mathcal{V}$  and edges of  $\mathcal{E}$ , respectively, such that the  $uv$ th entry of  $D$  is equal to 1 if the vertex  $u$  is the head of the edge  $v$ , -1 if the vertex  $u$  is the tail of the edge  $v$ , and 0, otherwise. If graph  $\mathcal{G}$  has  $m$  vertices and  $|\mathcal{E}|$  edges, then incidence matrix  $D$  of the graph  $\mathcal{G}$  has order  $(N+1) \times |\mathcal{E}|$ .

The cohesion and separation of formation control is defined by the desired distance vector  $d_{ij}^d = X^{i,d} - X^{j,d}$  between two neighbors  $v_i$  and  $v_j$  in  $\{v_{11}, v_{12}, \dots, v_{1N}, v_2\}$ . The formation error vector is defined as  $X^i - X^j - d_{ij}^d$  for edge  $(v_i, v_j)$ .

Next, we consider the representation of the whole team formation error in a matrix form as follows:

$$\begin{aligned}
& \sum_{(i,j) \in \mathcal{E}} w_{ij} \|X^i - X^j - d_{ij}^d\|^2 \\
&= \sum_{(i,j) \in \mathcal{E}} w_{ij} \|X^i - X^j\|^2 + w_{ij} \|d_{ij}^d\|^2 - 2 \langle w_{ij} (X^i - X^j), d_{ij}^d \rangle \\
&= X^\top \hat{D} \hat{W} \hat{D}^\top X + (d^d)^\top \hat{W} d^d - X^\top \hat{D} \hat{W} d^d - (\hat{D} \hat{W} d^d)^\top X \\
&= \tilde{X}^\top \tilde{L} \tilde{X},
\end{aligned} \tag{5.5}$$

where

$$\tilde{L} = \begin{pmatrix} \hat{L} & -\hat{D} \hat{W} d^d I_{2n}^\top \\ -(\hat{D} \hat{W} d^d I_{2n}^\top)^\top & \frac{1}{4n^2} (d^d I_{2n}^\top)^\top \hat{W} d^d I_{2n}^\top \end{pmatrix}$$

and  $\hat{W} = W \otimes I_{2n \times 2n}$ , with  $W = \text{diag}[w_{ij}]$  being a diagonal weight matrix with dimension  $|\mathcal{E}|$ . Define the Laplacian of a graph  $\mathcal{G}$  as  $L = DWD^\top$  which is symmetric and positive semi-definite. Based on  $(X \otimes Y)^\top = (X^\top \otimes Y^\top)$  and  $(X \otimes Y)(U \otimes V) = (XU) \otimes (YV)$ , we have  $\hat{L} = \hat{D} \hat{W} \hat{D}^\top = L \otimes I_{2n \times 2n}$  which is also symmetric and positive semi-definite.

In this case, we consider a more challenging formation control problem that all the robots have their own individual cost functional, in fact, they can choose their objectives based on relative displacement and velocity errors with the immediate neighbours in the graph topology. Now we give the cost functional of the follower robots, for  $i = 1, \dots, N$ ,

$$J_{1i}(u_{1i}, u_2) = \mathbb{E} \left[ \sum_{(i,j) \in \mathcal{E}} w_{ij} \|X_T^i - X_T^j - d_{ij}^d\|^2 + \int_0^T \sum_{(i,j) \in \mathcal{E}} \mu_{ij} \|X_t^i - X_t^j - d_{ij}^d\|^2 + u_{1i}^\top R_{ii} u_{1i} dt \right], \tag{5.6}$$

where  $\mu_{ij}, R_{ii} > 0$ .

Let  $K_{1i} = \hat{L}_{1i} = \hat{D} \hat{W}_{1i} \hat{D}^\top$ ,  $\hat{W}_{1i} = W_{1i} \otimes I_{2n \times 2n}$ ,  $W_{1i} = \text{diag}[w_{ij}]$ ,  $Q_i = \hat{L}_i = \hat{D} \hat{W}_i \hat{D}^\top$ ,  $\hat{W}_i = W_i \otimes I_{2n \times 2n}$ ,  $W_i = \text{diag}[\mu_{ij}]$ .  $K_{1i}$  and  $Q_i$  are symmetric and positive semi-definite. Then (5.6) becomes

$$J_{1i}(u_{1i}, u_2) = \mathbb{E} \left[ \tilde{X}_T^\top \tilde{K}_{1i} \tilde{X}_T + \int_0^T \tilde{X}_t^\top \tilde{Q}_i \tilde{X}_t + u_{1i}^\top R_{ii} u_{1i} dt \right], \tag{5.7}$$

where

$$\begin{aligned}
\tilde{K}_{1i} &= \begin{pmatrix} K_{1i} & -\hat{D} \hat{W}_{1i} d^d I_{2n}^\top \\ -(\hat{D} \hat{W}_{1i} d^d I_{2n}^\top)^\top & \frac{1}{4n^2} (d^d I_{2n}^\top)^\top \hat{W}_{1i} d^d I_{2n}^\top \end{pmatrix}, \\
\tilde{Q}_i &= \begin{pmatrix} Q_i & -\hat{D} \hat{W}_i d^d I_{2n}^\top \\ -(\hat{D} \hat{W}_i d^d I_{2n}^\top)^\top & \frac{1}{4n^2} (d^d I_{2n}^\top)^\top \hat{W}_i d^d I_{2n}^\top \end{pmatrix}.
\end{aligned}$$

To track a special trajectory  $X^{2,d}$ , the leader robot should track  $X^{2,d}$ , so its cost functional is

$$\begin{aligned}
J_2(u_{1i}, u_2) &= \mathbb{E} \left[ \sum_{(i,j) \in \mathcal{E}} v_{ij} \|X_T^i - X_T^j - d_{ij}^d\| + \|X_T^2 - X_T^{2,d}\|_{k_2} \right. \\
&\quad \left. + \int_0^T \sum_{(i,j) \in \mathcal{E}} \theta_{ij} \|X^i - X^j - d_{ij}^d\| + \|X_t^2 - X_t^{2,d}\|_{q_2} + u_2^\top R_{22} U_2 dt \right] \\
&= \mathbb{E} \left[ \tilde{X}_T^\top (\tilde{K}_2 + \tilde{k}_2^1) \tilde{X}_T + \int_0^T \tilde{X}^\top (\tilde{Q}_2 + \tilde{q}_2^1) \tilde{X} + u_2^\top R_{22} u_2 dt \right] \\
&= \mathbb{E} \left[ \tilde{X}_T^\top \tilde{K}_2^1 \tilde{X}_T + \int_0^T \tilde{X}^\top \tilde{Q}_2^1 \tilde{X} + u_2^\top R_{22} u_2 dt \right], \tag{5.8}
\end{aligned}$$

where

$$\begin{aligned}
\tilde{K}_2 &= \begin{pmatrix} K_2 & -\hat{D}\hat{W}_2 d^d I_{2n}^\top \\ -(\hat{D}\hat{W}_2 d^d I_{2n}^\top)^\top & \frac{1}{4n^2} (d^d I_{2n}^\top)^\top \hat{W}_2 d^d I_{2n}^\top \end{pmatrix}, \\
\tilde{k}_2^1 &= \begin{pmatrix} k_2^1 & -k_2^1 X_T^{2,d} I_{2n}^\top \\ -(k_2^1 X_T^{2,d} I_{2n}^\top)^\top & \frac{1}{4n^2} (X_T^{2,d} I_{2n}^\top)^\top k_2^1 X_T^{2,d} I_{2n}^\top \end{pmatrix}, \\
\tilde{Q}_2 &= \begin{pmatrix} Q_2 & -\hat{D}\hat{U}_2 d^d I_{2n}^\top \\ -(\hat{D}\hat{U}_2 d^d I_{2n}^\top)^\top & \frac{1}{4n^2} (d^d I_{2n}^\top)^\top \hat{U}_2 d^d I_{2n}^\top \end{pmatrix}, \\
\tilde{q}_2^1 &= \begin{pmatrix} q_2^1 & -q_2^1 X^{2,d} I_{2n}^\top \\ -(q_2^1 X^{2,d} I_{2n}^\top)^\top & \frac{1}{4n^2} (X^{2,d} I_{2n}^\top)^\top q_2^1 X^{2,d} I_{2n}^\top \end{pmatrix},
\end{aligned}$$

in which  $K_2 = \hat{L}_2 = \hat{D}\hat{W}_2\hat{D}^\top$ ,  $\hat{W}_2 = V_2 \otimes I_{2n \times 2n}$ ,  $V_2 = \text{diag}[v_{ij}]$ ,  $Q_2 = \hat{P}_2 = \hat{D}\hat{U}_2\hat{D}^\top$ ,  $\hat{U}_2 = H_2 \otimes I_{2n \times 2n}$ ,  $H_2 = \text{diag}[\theta_{ij}]$ .  $K_2$  and  $Q_2$  are symmetric and positive semi-definite.  $k_2 = \text{diag}[w_2]$ ,  $q_2 = \text{diag}[\mu_2]$ , and  $k_2^1 = \text{diag}[k_2, 0, \dots, 0]$ ,  $q_2^1 = \text{diag}[q_2, 0, \dots, 0]$ .  $\tilde{K}_2^1, \tilde{Q}_2^1$  are also symmetric and positive semi-definite.  $R_{22}$  is a negative-definite matrix.

We assume that  $\tilde{K}_2, \tilde{Q}_2 = 0$ , i.e., the leader do not take the formation error into consideration and only track the desired trajectory and following him with a fixed distance. Moreover, a robot addresses its cost functional that is only related to part of other robots based on the partial information when fixing a formation shown by connected graph topology. Therefore, we set that all of them can not observe the complete information where the followers know more information than the leader. Then the observable information available to the followers and the leader are described by the following equations:

$$dY_1^{u_1, u_2}(t) = [f_1(t)X_t + g_1(t)]dt + K_1(t)dW_t^1, \tag{5.9}$$

specially,  $f_1(t) = g_1(t) = 0, K_1(t) = I$  implies that  $Y_1(t) = W_t^1$ ; and

$$dY_2^{u_1, u_2}(t) = [f_2(t)X_t + g_2(t)]dt + K_2(t)dW_t^2. \tag{5.10}$$

Then apply the theoretical results in the precious sections 3 and 4, and let  $A = A, B_2 = B_2, B_{1i} = B_{1i}, C_1 = \tilde{C}_1, C_2 = \tilde{C}_2, Q_{1i} = \tilde{Q}_i, R_{1i} = R_{ii}, G_{1i} = \tilde{K}_{1i}, Q_2 = \tilde{Q}_2^1, R_2 = R_{22}, G_2 = \tilde{K}_2^1, S_{1i} = S_2 = q_{1i} = q_2 = r_{1i} = r_2 = g_{1i} = g_2 = \alpha = 0$ , then we obtain the optimal control of the  $i$ th follower robot:

$$\tilde{u}_{1i}(t) = -R_{ii}^{-1}(t)B_{1i}^\top(t)P_t^{1i}\hat{X}_t - R_{ii}^{-1}(t)B_{1i}^\top(t)\varphi_t^{1i}, \tag{5.11}$$

where  $\hat{X}, P^{1i}, \varphi^{1i}$  satisfy

$$d\hat{X}_t = \left[ \left( A(t) - \sum_{i=1}^N B_{1i}(t)R_{ii}^{-1}(t)B_{1i}^\top(t)P_t^{1i} \right) \hat{X}_t - \sum_{i=1}^N B_{1i}(t)R_{ii}^{-1}(t)B_{1i}^\top(t)\varphi_t^{1i} + B_2(t)u_2(t) \right] dt + C_1(t)dW_t^1, \quad (5.12)$$

$$\begin{cases} \dot{P}_t^{1i} + A^\top(t)P_t^{1i} + P_t^{1i}A(t) - P_t^{1i}B_{1i}(t)R_{ii}^{-1}(t)B_{1i}^\top(t)P_t^{1i} + \tilde{Q}_i(t) = 0, \\ P_T^{1i} = \tilde{K}_{1i}, \end{cases} \quad (5.13)$$

and

$$\begin{cases} -d\varphi_t^{1i} = [(A(t) - B_{1i}(t)R_{ii}^{-1}(t)B_{1i}^\top(t)P_t^{1i})^\top \varphi_t^{1i} + P_t^{1i}B_2(t)u_2(t)] dt - \lambda_t^{1i}dW_t^1, \\ \varphi_T^{1i} = 0, \end{cases} \quad (5.14)$$

respectively. Now, for any fixed  $u_2$ , the optimal cost of the follower is given by

$$J_{1i}(u_2) = \mathbb{E}[\langle P_0^{1i}x_0 + 2\varphi_0^{1i}, x_0 \rangle] + \mathbb{E} \int_0^T \left[ \sum_{j=1}^{l_2} \langle \Pi^{1i}\tilde{C}_{2j}, \tilde{C}_{2j} \rangle + \sum_{j=1}^{l_1} \langle P^{1i}\tilde{C}_{1j}, \tilde{C}_{1j} \rangle - \langle R_{ii}^{-1}B_{1i}^\top\varphi^{1i}, B_{1i}^\top\varphi^{1i} \rangle + 2\langle B_2u_2, \varphi^{1i} \rangle + 2\langle \tilde{C}_1, \lambda^{1i} \rangle \right] dt, \quad (5.15)$$

where

$$\begin{cases} \dot{\Pi}_t^{1i} + A^\top\Pi_t^{1i} + \Pi_t^{1i}A + \tilde{Q}_i = 0, \\ \Pi_T^{1i} = \tilde{K}_{1i}. \end{cases} \quad (5.16)$$

Next, the optimal control of the leader robot has the feedback representation as follows:

$$\begin{aligned} \bar{u}_2(t) = & -(2R_{22})^{-1} [B_2P_1 + B_2^\top((P^1)^\top + P_2)P_3^{-1}P_2^\top] \check{X}_t \\ & + (2R_{22})^{-1} B_2^\top((P^1)^\top + P_2)P_3^{-1}\check{\varphi}_t^1, \end{aligned} \quad (5.17)$$

where  $P^{1i}, P_1, P_2, P_3$  satisfy

$$\begin{cases} \dot{P}^{1i} + A^\top P^{1i} + P^{1i}A - P^{1i}B_{1i}R_{ii}^{-1}B_{1i}^\top P^{1i} + \tilde{Q}_i = 0, \\ P_T^{1i} = \tilde{K}_{1i}, \end{cases} \quad (5.18)$$

$$\begin{cases} \dot{P}_1 + P_1 \left( A - \sum_{i=1}^N B_{1i}R_{ii}^{-1}B_{1i}^\top P^{1i} + B_1^\top P_2^\top \right) + \left( A^\top - \sum_{i=1}^N P^{1i}B_{1i}^\top R_{ii}^{-1}B_{1i}^\top + P_2B_1 \right) P_1 \\ \quad - P_1B_2(2R_{22})^{-1}B_2P_1 + 2\tilde{Q}_2^1 = 0, \\ P_1(T) = 2\tilde{K}_2^1, \end{cases} \quad (5.19)$$

$$\begin{cases} \dot{P}_2 - P_1B_1^\top P_3 - P_1B_2(2R_{22})^{-1}B_2^\top((P^1)^\top + P_2) + P_2B_3 \\ \quad + \left( A^\top - \sum_{i=1}^N P^{1i}B_{1i}^\top R_{ii}^{-1}B_{1i}^\top + P_2B_1 \right) P_2 = 0, \\ P_2(T) = 0, \end{cases} \quad (5.20)$$

$$\begin{cases} \dot{P}_3 + (P_2^\top B_1^\top + B_3^\top)P_3 + P_3(B_1P_2 + B_3) - (P^1 + P_2^\top)B_2(2R_{22})^{-1}B_2^\top((P^1)^\top + P_2) = 0, \\ P_3(T) = 0, \end{cases} \quad (5.21)$$

$\check{X}$  satisfies

$$\left\{ \begin{aligned}
d\check{X}_t &= \left\{ \left[ A - \sum_{i=1}^N B_{1i} R_{ii}^{-1} B_{1i}^\top P^{1i} - B_2 (2R_{22})^{-1} (B_2 P_1 + B_2^\top ((P^1)^\top + P_2) P_3^{-1} P_2^\top) \right] \check{X} \right. \\
&\quad \left. - \sum_{i=1}^N B_{1i} R_{ii}^{-1} B_{1i}^\top \check{\phi}^{1i} + B_2 (2R_{22})^{-1} B_2^\top ((P^1)^\top + P_2) P_3^{-1} \check{\phi}^1 \right\} dt \\
&\quad + \sum_{j=1}^{l_2} [\check{\Sigma} f_2^\top (K_2^\top)^{-1} + \check{C}_2]^j d\check{U}_t^j, \\
-d\check{\phi}_t^{1i} &= \left[ (A - B_{1i} R_{ii}^{-1} B_{1i}^\top P^{1i}) \check{\phi}^{1i} + P^{1i} B_2 (2R_{22})^{-1} B_2^\top ((P^1)^\top + P_2) P_3^{-1} \check{\phi}^1 \right. \\
&\quad \left. - P^{1i} B_2 (2R_{22})^{-1} (B_2 P_1 + B_2^\top ((P^1)^\top + P_2) P_3^{-1} P_2^\top) \check{X} \right] dt \\
&\quad - \sum_{j=1}^{l_2} \check{\Upsilon}_t^{1ij} d\check{U}_t^j, \quad i = 1, 2, \dots, N, \\
d\check{\phi}_t^1 &= - \left\{ [A_3 - D_3 D_4^{-1} D_3^\top P_3^{-1} P_2^\top - D_3 D_4^{-1} D_1^\top (P_1 + P_2 P_3^{-1} P_2^\top)] \check{X} \right. \\
&\quad + [B_3^\top + D_3 D_4^{-1} D_3^\top P_3^{-1} + D_3 D_4^{-1} D_1^\top P_2 P_3^{-1}] \check{\phi}^1 \\
&\quad \left. + \sum_{j=1}^{l_2} [(C_3^j)^\top P_2^\top - D_3 D_4^{-1} (D_2^j)^\top P_1] [\check{\Sigma} f_2^\top (K_2^\top)^{-1} + \check{C}_2]^j \right\} dt \\
&\quad + \sum_{j=1}^{l_2} \check{\Upsilon}_t^{1j} dB_t^j, \\
\check{X}_0 &= x_0, \quad \check{\phi}_T^{1i} = 0,
\end{aligned} \right. \tag{5.22}$$

and  $(\check{\phi}_1, \check{V}_1)$ ,  $(\check{\phi}_2, \check{V}_2)$  satisfy

$$\left\{ \begin{aligned}
d\check{\phi}_1 &= - \left[ \left( P_2 B_1 + A^\top - \sum_{i=1}^N P^{1i} B_{1i}^\top R_{ii}^{-1} B_{1i}^\top - P_1 B_2 (2R_{22})^{-1} B_2^\top \right) \check{\phi}_1 \right. \\
&\quad \left. + P_1 B_1^\top \check{\phi}_2 \right] dt + \sum_{j=1}^{l_2} \check{V}_1^j d\check{U}_t^j, \\
d\check{\phi}_2 &= - \left[ (P_2^\top B_1^\top + B_3^\top) \check{\phi}_2 - (P_3 B_1 + (P^1 + P_2^\top) B_2 (2R_{22})^{-1} B_2^\top) \check{\phi}_1 \right] dt \\
&\quad + \sum_{j=1}^{l_2} \check{V}_2^j d\check{U}_t^j, \\
\check{\phi}_1(T) &= 0, \quad \check{\phi}_2(T) = 0,
\end{aligned} \right. \tag{5.23}$$

which admit unique zero solutions.

Then the optimal cost of the leader is as follows:

$$\begin{aligned}
J_2(\bar{u}_2) &= \frac{1}{2}\mathbb{R}_2 + \frac{1}{2}\int_0^T \left\{ \mathbb{E}[M_5] - 2p \sum_{i=1}^N B_{1i}R_{ii}^{-1}B_{1i}^\top P^{1i} \mathbb{E}[(\hat{X} - \check{X})\check{X}^\top] \right. \\
&\quad - 2\mathbb{E}[(\hat{X} - \check{X})\check{X}^\top] \sum_{i=1}^N (B_{1i}^\top P^{1i})^\top R_{ii}^{-1}B_{1i}^\top p \\
&\quad - 2p \sum_{i=1}^N B_{1i}R_{ii}^{-1}B_{1i}^\top \check{\Sigma}^i - 2 \sum_{i=1}^N (\check{\Sigma}^i)^\top B_{1i}R_{ii}^{-1}B_{1i}^\top p + 2 \sum_{j=1}^{l_1} (\tilde{C}_1^j)^\top p \tilde{C}_1^j \\
&\quad \left. + 2 \sum_{j=1}^{l_2} [(\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j]^\top (\tilde{\Sigma}f_2^\top (K_2^\top)^{-1})^j \right\} dt, \tag{5.24}
\end{aligned}$$

where  $\check{X} \triangleq \bar{X} - \check{X}$  satisfies

$$\begin{aligned}
d\check{X}_t &= \left[ A\check{X}_t - \sum_{i=1}^N B_{1i}R_{ii}^{-1}B_{1i}^\top P^{1i}(\hat{X}_t - \check{X}_t) - \sum_{i=1}^N B_{1i}R_{ii}^{-1}B_{1i}^\top(\phi_t^{1i} - \check{\phi}_t^{1i}) \right. \\
&\quad \left. - (\tilde{\Sigma}f_2^\top + \tilde{C}_2K_2^\top)(K_2K_2^\top)^{-1}f_2\check{X}_t \right] dt \\
&\quad + \sum_{j=1}^{l_1} \tilde{C}_1^j dW^{1j} - \sum_{j=1}^{l_2} [\tilde{\Sigma}f_2^\top (K_2^\top)^{-1}]^j dW^{2j}, \\
&\quad \begin{cases} \dot{p} + p[A - (\tilde{\Sigma}f_2^\top + \tilde{C}_2K_2^\top)(K_2K_2^\top)^{-1}f_2 \\ \quad + [A - (\tilde{\Sigma}f_2^\top + \tilde{C}_2K_2^\top)(K_2K_2^\top)^{-1}f_2]^\top p + \tilde{Q}_2^1] = 0, \\ p_T = \tilde{K}_2^1, \end{cases} \tag{5.26}
\end{aligned}$$

with  $\mathbb{R}_2 = X_0^\top P_1(0)X_0$ , and  $\tilde{\Sigma}$ ,  $\check{\Sigma}^i$ ,  $\mathbb{E}[(\hat{X} - \check{X})\check{X}^\top]$  can be solved by equations (4.8)-(4.13) with the corresponding values when replacing  $X$  with  $\check{X}$ .

## 6. CONCLUSION

This paper investigates a class of LQ partially observed stochastic Stackelberg differential game, where a single leader and multiple followers are considered. In our setting, the information available to the leader is less than that known by the followers and assume that all the followers acquire the same partially observable information. Motivated by [31], using the orthogonal decomposition technique, we derive the state filtering feedback form of optimal control of the  $i$ 's follower by the method of completion of square. Next, motivated by the new decoupling technique in [8], we first generalize and extend the LQ stochastic control of multi-dimensional fully coupled FBSDEs with inhomogeneous terms and then is applied to study the LQ partially observed optimal control problem of FBSDEs where we relax the restrict condition imposed on control process in [34] by the orthogonal decomposition of forward and backward state processes. A multi-agent formation control is extended to the stochastic framework and studied by the partially observed Stackelberg differential game approach which differs from the deterministic case.

Another consideration is that the leader knows the complete information and the information available to the followers is comparatively less. In this case, the leader need to solve the LQ optimal control problem of fully coupled conditional mean-field FBSDEs, which is not a trivial extension, and it is under investigation in our another working paper. Another interesting extension is to construct the Stackelberg game theory for providing

the first continuous-time partially observed leader-follower analysis of practical problem in [18, 35] in which the differentially private algorithm is an useful tool to our numerical simulation, as our future research direction

#### REFERENCES

- [1] A. Bensoussan, *Stochastic Control of Partially Observable Systems*, Cambridge University Press, Cambridge, 1992.
- [2] A. Bensoussan, S. K. Chen, and S. P. Sethi, The maximum principle for global solutions of stochastic Stackelberg differential games. *SIAM J. Control Optim.*, **53**(4), 1956-1981, 2015.
- [3] L. Chen, Y. Shen, On a new paradigm of optimal reinsurance: a stochastic Stackelberg differential game between an insurer and a reinsurer. *Astin Bull.*, **48**(2), 905-960, 2018.
- [4] J. Cvitanović, J. F. Zhang, *Contract Theory in Continuous-Time Models*, Springer-Verlag, Berlin, 2013.
- [5] J. A. Fax, R. M. Murray, Information flow and cooperative control of vehicle formations. *IEEE Trans. Automat. Control*, **49**(9), 1465-1476, 2004.
- [6] X. W. Feng, L. Wang, Stackelberg equilibrium with social optima in linear-quadratic-Gaussian mean-field system. *Math. Control Relat. Fields*, **14**(2), 769-799, 2024.
- [7] D. B. Gu, A differential game approach to formation control. *IEEE Trans. Control Syst. Technol.*, **16**(1), 85-93, 2008.
- [8] M. S. Hu, S. L. Ji, and X. L. Xue, Optimization under rational expectations: a framework of fully coupled forward-backward stochastic linear quadratic systems. *Math. Oper. Res.*, **48**(3), 1767-1790, 2023.
- [9] J. H. Huang, B. C. Wang and T. H. Xie, Social optimal in leader-follower mean field linear quadratic control. *ESAIM Control Optim. Calc. Var.*, **27**, suppl. Paper No. S12, 2021.
- [10] N. Li, S. J. Wang, Linear-quadratic stochastic Stackelberg games of  $N$  players for time-delay systems and related FBSDEs. *Appl. Math. Optim.*, **89**(3), Paper No. 67, 2024.
- [11] N. Li, Z. Y. Yu, Forward-backward stochastic differential equations and linear-quadratic generalized Stackelberg games. *SIAM J. Control Optim.*, **56**(6), 4148-4180, 2018.
- [12] N. Li, J. Xiong, and Z. Y. Yu, Linear-quadratic generalized Stackelberg games with jump-diffusion processes and related forward-backward stochastic differential equations. *Sci. China Math.*, **64**(9), 2091-2116, 2021.
- [13] T. Li, S. P. Sethi, A review of dynamic Stackelberg game models. *Discrete Contin. Dyn. Syst. Ser. B*, **22**(1), 125-159, 2017.
- [14] Z. P. Li, D. Marelli, M. Y. Fu, and H. S. Zhang, LQG differential Stackelberg game under nested observation information patterns. *IEEE Trans. Automat. Control*, **68**(8), 5111-5118, 2023.
- [15] A. E. B. Lim, X. Y. Zhou, Linear-quadratic control of backward stochastic differential equations. *SIAM J. Control Optim.*, **40**(2), 450-474, 2001.
- [16] W. Lin, Distributed UAV formation control using differential game approach. *Aerosp. Sci. Technol.*, **35**(1), 54-62, 2014.
- [17] Y. N. Lin, X. S. Jiang, and W. H. Zhang, An open-loop Stackelberg strategy for the linear quadratic mean-field stochastic differential game. *IEEE Trans. Automat. Control*, **64**(1), 97-110, 2019.
- [18] X. K. Liu, J. F. Zhang, and J. M. Wang, Differentially private consensus algorithm for continuous-time heterogeneous multi-agent systems. *Automatica*, **122**, Paper No. 109283, 2020.
- [19] S. Y. Lv, J. Xiong, and X. Zhang, Linear quadratic leader-follower stochastic differential games for mean-field switching diffusions. *Automatica*, **154**, Paper No. 111072, 2023.
- [20] W. J. Meng, J. T. Shi, A linear quadratic stochastic Stackelberg differential games with time delay. *Math. Control Relat. Fields*, **12**(3), 581-609, 2022.
- [21] J. Moon, Linear-quadratic stochastic leader-follower differential games for Markov jump-diffusion models. *Automatica*, **147**, Paper No. 110713, 2023.
- [22] J. Moon, Linear-quadratic stochastic Stackelberg differential games for jump-diffusion systems. *SIAM J. Control Optim.*, **59**(2), 954-976, 2021.
- [23] J. Moon, T. Başar, Linear quadratic mean field Stackelberg differential games. *Automatica*, **97**, 200-213, 2018.
- [24] J. Moon, T. Başar, Separation principle for partially-observed linear-quadratic optimal control for mean-field type stochastic systems. *IEEE Trans. Automat. Control*, DOI: 10.1109/TAC.2024.3409641, 2024.
- [25] T. Mylvaganam, A. Astolfi, A differential game approach to formation control for a team of agents with one leader. In *Proceeding of American Control Conference*, Chicago, IL, USA, July 1-3, 2015, 1469-1474.
- [26] B. Øksendal, L. Sandal, J. Ubøe, Stochastic Stackelberg equilibria with applications to time-dependent newsvendor models. *J. Econom. Dynam. Control*, **37**(7), 1284-1299, 2013.

- [27] L. C. G. Rogers, D. Williams, Diffusions, Markov Processes, and Martingales, Volume 2: Ito Calculus, 2nd ed., Cambridge University Press, Cambridge, 2000.
- [28] J. T. Shi, G. C. Wang, and J. Xiong, Leader-follower stochastic differential game with asymmetric information and applications. *Automatica*, **63**, 60-73, 2016.
- [29] Y. Si, J. T. Shi, An overlapping information linear-quadratic Stackelberg stochastic differential game with two leaders and two followers. *Proc. 43rd Chinese Control Conference*, 1216-1223, 28-31 July, Kunming, P.R. China, 2024.
- [30] H. von. Stackelberg, The Theory of the Market Economy, Oxford University Press, London, 1952.
- [31] J. R. Sun, J. Xiong, Stochastic linear-quadratic optimal control with partial observation. *SIAM J. Control Optim.*, **61**(3), 1231-1247, 2023.
- [32] Y. Wang, W. C. Wang, Partially observed mean-field Stackelberg stochastic differential game with two followers. *Internat. J. Control*, **97**(9), 1999-2008, 2024.
- [33] G. C. Wang, Z. Wu, Kalman-Bucy filtering equations of forward and backward stochastic systems and applications to recursive optimal control problems. *J. Math. Anal. Appl.*, **342**(2), 1280-1296, 2008.
- [34] G. C. Wang, Z. Wu, and J. Xiong, A linear-quadratic optimal control problem of forward-backward stochastic differential equations with partial information. *IEEE Trans. Automat. Control*, **60**(11), 2904-2916, 2015.
- [35] J. M. Wang, J. F. Zhang, and X. K. He, Differentially private distributed algorithms for stochastic aggregative games. *Automatica*, **142**, Paper No. 110440, 2022.
- [36] W. M. Wonham, On the separation theorem of stochastic control. *SIAM J. Control Optim.*, **6**(2), 312-326, 1968.
- [37] J. J. Xu, J. T. Shi, and H. S. Zhang, A leader-follower stochastic linear quadratic differential game with time delay. *Sci. China Inf. Sci.*, **61**(11), 112202, 2018.
- [38] J. M. Yong, A leader-follower stochastic linear quadratic differential game. *SIAM J. Control Optim.*, **41**(4), 1015-1041, 2002.
- [39] Y. Y. Zheng, J. T. Shi, A linear-quadratic partially observed Stackelberg stochastic differential game with application. *Appl. Math. Comput.*, **420**, Paper No. 126819, 2022.

#### APPENDIX A. RESULTS OF FULLY COUPLED FORWARD-BACKWARD STOCHASTIC LQ OPTIMAL CONTROL PROBLEM

We consider an LQ optimal control problem of fully coupled forward-backward stochastic differential controlled system, for the multi-dimensional case with inhomogeneous terms, which is an extension of [8].

We consider the following fully coupled forward-backward stochastic differential controlled system, for the state triple  $(X, Y, Z) \equiv (X, (Y^1, \dots, Y^N)^\top, Z^1 \equiv (Z^{11}, \dots, Z^{N1})^\top, \dots, Z^{l_2} \equiv (Z^{1l_2}, \dots, Z^{Nl_2})^\top)$ :

$$\left\{ \begin{array}{l} dX_t = \left[ A_1 X + B_1^\top Y + \sum_{k=1}^{l_2} (C_1^k)^\top Z^k + D_1 u + E_1 \right] dt \\ \quad + \sum_{j=1}^{l_2} \left[ A_2^j X + (B_2^j)^\top Y + \sum_{k=1}^{l_2} (C_2^{jk})^\top Z^k + D_2^j u + E_2^j \right] dB_t^j, \\ dY_t^i = - \left[ A_{3i} X_t + B_{3i}^\top Y^i + \sum_{j=1}^{l_2} (C_{3i}^j)^\top Z^{ij} + D_{3i} u + E_{3i} \right] dt + \sum_{j=1}^{l_2} Z_t^{ij} dB_t^j, \\ X_0 = x_0, Y_T^i = F_i X_T + \xi_i, \end{array} \right. \quad (\text{A.1})$$

where  $u \in \mathbb{R}$ ,  $X, Y^i, Z^{ij} \in \mathbb{R}^n$  and  $B^j \in \mathbb{R}$  is classical Brownian motion,  $i = 1, \dots, N, j = 1, \dots, l_2$ , and cost functional:

$$J(u(\cdot)) = \frac{1}{2} \mathbb{E} \left[ \int_0^T \left( \langle A_4 X, X \rangle + Y^\top B_4 Y + \sum_{j=1}^{l_2} (Z^j)^\top C_4^j Z^j + \langle D_4 u, u \rangle \right) dt \right. \\ \left. + \langle G X_T, X_T \rangle + Y_0^\top H Y_0 \right]. \quad (\text{A.2})$$

In the above, the coefficients are matrix-valued functions of proper dimensions. Thus, by the maximum principle, the optimal control  $\bar{u}$  satisfies

$$\sum_{i=1}^N D_{3i}^\top h_t^i + D_1^\top m_t + \sum_{j=1}^{l_2} (D_2^j)^\top n_t^j + D_4 \bar{u}_t = 0, \quad (\text{A.3})$$

where adjoint process triple  $(h, m, n) \equiv ((h^1, \dots, h^N)^\top, m, (n^1, \dots, n^{l_2})^\top)$  for  $h^i, m, n^j \in \mathbb{R}^n$ ,  $i = 1, \dots, N, j = 1, \dots, l_2$ , satisfies:

$$\begin{cases} dh_t^i = \left[ B_{3i} h_t^i + B_{1i} m + \sum_{j=1}^{l_2} B_{2i}^j n_t^j + B_{4i} \bar{Y}^i \right] dt \\ \quad + \sum_{j=1}^{l_2} \left[ C_{3i}^j h_t^i + C_{1i}^j m + \sum_{k=1}^{l_2} C_{2i}^{jk} n_t^k + \sum_{k=1}^{l_2} C_{4i}^{jk} \bar{Z}^{ik} \right] dB_t^j, \\ dm_t = - \left[ \sum_{i=1}^N A_{3i} h_t^i + A_1^\top m + \sum_{j=1}^{l_2} (A_2^j)^\top n_t^j + A_4 \bar{X} \right] dt + \sum_{j=1}^{l_2} n_t^j dB_t^j, \\ h_0^i = H_i \bar{Y}_0^i, \quad m_T = G \bar{X}_T + \sum_{i=1}^N F_i^\top h_T^i, \quad i = 1, \dots, N, \end{cases} \quad (\text{A.4})$$

with the optimal state triple  $(\bar{X}, \bar{Y}^i, \bar{Z}^{ik})$ .

**A.1. Definite case.** We suppose that  $D_4 > 0$  in this subsection. Thus the optimal control is:

$$\bar{u}_t = -D_4^{-1} D_3^\top h_t - D_4^{-1} D_1^\top m_t - D_4^{-1} \sum_{j=1}^{l_2} (D_2^j)^\top n_t^j, \quad (\text{A.5})$$

where  $D_3^\top h \equiv \sum_{i=1}^N D_{3i}^\top h^i$ . Insert  $\bar{u}$  back then we have the following matrix-valued FBSDEs:

$$\left\{ \begin{array}{l} d\bar{X}_t = \left[ A_1 \bar{X} + B_1^\top \bar{Y} + \sum_{k=1}^{l_2} (C_1^k)^\top \bar{Z}^k - D_1 D_4^{-1} D_3^\top h - D_1 D_4^{-1} D_1^\top m \right. \\ \quad \left. - D_1 D_4^{-1} \sum_{i=1}^{l_2} (D_2^i)^\top n_i^i + E_1 \right] dt + \sum_{j=1}^{l_2} \left[ A_2^j \bar{X} + (B_2^j)^\top \bar{Y} + \sum_{k=1}^{l_2} (C_2^{jk})^\top \bar{Z}^k \right. \\ \quad \left. - D_2^j D_4^{-1} D_3^\top h - D_2^j D_4^{-1} D_1^\top m - D_2^j D_4^{-1} \sum_{j=1}^{l_2} (D_2^j)^\top n^j + E_2^j \right] dB_t^j, \\ d\bar{Y}_t = - \left[ A_3 \bar{X} + B_3^\top \bar{Y} + \sum_{j=1}^{l_2} (C_3^j)^\top \bar{Z}^j - D_3 D_4^{-1} D_3^\top h - D_3 D_4^{-1} D_1^\top m \right. \\ \quad \left. - \sum_{j=1}^{l_2} D_3 D_4^{-1} (D_2^j)^\top n^j + E_3 \right] dt + \sum_{j=1}^{l_2} \bar{Z}^j dB_t^j, \\ dh_t = \left[ B_3 h + B_1 m + \sum_{j=1}^{l_2} B_2^j n^j + B_4 \bar{Y} \right] dt \\ \quad + \sum_{j=1}^{l_2} [C_3^j h + C_1^j m + \sum_{k=1}^{l_2} C_2^{jk} n^k + \sum_{k=1}^{l_2} C_4^{jk} \bar{Z}^k] dB_t^j, \\ dm_t = - \left[ A_3^\top h + A_1^\top m + \sum_{j=1}^{l_2} (A_2^j)^\top n^j + A_4 \bar{X} \right] dt + \sum_{j=1}^{l_2} n_i^j dB_t^j, \\ \bar{X}_0 = x_0, \bar{Y}_T = F \bar{X}_T + \xi, h_0 = H \bar{Y}_0, m_T = G \bar{X}_T + F^\top h_T, \end{array} \right. \quad (\text{A.6})$$

where

$$\begin{aligned} C_{4i}^j &\triangleq (C_{4i}^{j1}, C_{4i}^{j2}, \dots, C_{4i}^{jl_2}), \quad i = 1, \dots, N, \quad j = 1, \dots, l_2, \\ A_3 &\triangleq \begin{pmatrix} A_{31} \\ A_{32} \\ \vdots \\ A_{3N} \end{pmatrix}, \quad B_1 \triangleq \begin{pmatrix} B_{11} \\ B_{12} \\ \vdots \\ B_{1N} \end{pmatrix}, \quad B_3 \triangleq \begin{pmatrix} B_{31} & & & \\ & B_{32} & & \\ & & \ddots & \\ & & & B_{3N} \end{pmatrix}, \\ C_3^j &\triangleq \begin{pmatrix} C_{31}^j & & & \\ & C_{32}^j & & \\ & & \ddots & \\ & & & C_{3N}^j \end{pmatrix}, \quad j = 1, \dots, l_2, \quad B_2^j \triangleq \begin{pmatrix} B_{21}^j \\ B_{22}^j \\ \vdots \\ B_{2N}^j \end{pmatrix}, \\ D_3 (D_4)^{-1} D_3^\top &\triangleq \begin{pmatrix} D_{31} D_4^{-1} D_{31}^\top & D_{31} D_4^{-1} D_{32}^\top & \cdots & D_{31} D_4^{-1} D_{3N}^\top \\ D_{32} D_4^{-1} D_{31}^\top & D_{32} D_4^{-1} D_{32}^\top & \cdots & D_{32} D_4^{-1} D_{3N}^\top \\ \vdots & \vdots & \ddots & \vdots \\ D_{3N} D_4^{-1} D_{31}^\top & D_{3N} D_4^{-1} D_{32}^\top & \cdots & D_{3N} D_4^{-1} D_{3N}^\top \end{pmatrix}, \end{aligned}$$

and

$$\begin{aligned}
D_3(D_4)^{-1}D_2^\top &\triangleq \begin{pmatrix} D_{31}D_4^{-1}(D_2^1)^\top & D_{31}D_4^{-1}(D_2^2)^\top & \cdots & D_{31}D_4^{-1}(D_2^{l_2})^\top \\ D_{32}D_4^{-1}(D_2^1)^\top & D_{32}D_4^{-1}(D_2^2)^\top & \cdots & D_{32}D_4^{-1}(D_2^{l_2})^\top \\ \vdots & \vdots & \ddots & \vdots \\ D_{3N}D_4^{-1}(D_2^1)^\top & D_{3N}D_4^{-1}(D_2^2)^\top & \cdots & D_{3N}D_4^{-1}(D_2^{l_2})^\top \end{pmatrix}, \\
B_2 &\triangleq \begin{pmatrix} B_{21}^1 & B_{21}^2 & \cdots & B_{21}^{l_2} \\ B_{22}^1 & B_{22}^2 & \cdots & B_{22}^{l_2} \\ \vdots & \vdots & \ddots & \vdots \\ B_{2N}^1 & B_{2N}^2 & \cdots & B_{2N}^{l_2} \end{pmatrix}, \quad B_4 \triangleq \begin{pmatrix} B_{41} & & & \\ & B_{42} & & \\ & & \ddots & \\ & & & B_{4N} \end{pmatrix}, \\
C_4^j &\triangleq \begin{pmatrix} C_{41}^j & & & \\ & C_{42}^j & & \\ & & \ddots & \\ & & & C_{4N}^j \end{pmatrix}, \quad C_2^{jk} = \begin{pmatrix} C_{21}^{jk} \\ C_{22}^{jk} \\ \vdots \\ C_{2N}^{jk} \end{pmatrix}, \quad C_2^j = \begin{pmatrix} C_{21}^{j1} & C_{21}^{j2} & \cdots & C_{21}^{jl_2} \\ C_{22}^{j1} & C_{22}^{j2} & \cdots & C_{22}^{jl_2} \\ \vdots & \vdots & \ddots & \vdots \\ C_{2N}^{j1} & C_{2N}^{j2} & \cdots & C_{2N}^{jl_2} \end{pmatrix}, \\
C_1^j &\triangleq \begin{pmatrix} C_{11}^j \\ C_{12}^j \\ \vdots \\ C_{1N}^j \end{pmatrix}, \quad j = 1, \dots, l_2, \quad D_3 = \begin{pmatrix} D_{31} \\ D_{32} \\ \vdots \\ D_{3N} \end{pmatrix}, \quad E_3 = \begin{pmatrix} E_{31} \\ E_{32} \\ \vdots \\ E_{3N} \end{pmatrix}, \\
H &\triangleq \begin{pmatrix} H_1 & & & \\ & H_2 & & \\ & & \ddots & \\ & & & H_N \end{pmatrix}, \quad F = (F_1, F_2, \dots, F_N)^\top, \quad \xi = (\xi_1, \xi_2, \dots, \xi_N)^\top.
\end{aligned}$$

Set

$$\begin{aligned}
\tilde{X} &\triangleq \begin{pmatrix} \bar{X} \\ h \end{pmatrix}, \quad \tilde{Y} \triangleq \begin{pmatrix} m \\ \bar{Y} \end{pmatrix}, \quad \tilde{Z}^j \triangleq \begin{pmatrix} n^j \\ \bar{Z}^j \end{pmatrix} \in \mathbb{R}^{(N+1)n}, \quad j = 1, \dots, l_2, \\
\tilde{A}_1 &\triangleq \begin{pmatrix} A_1 & -D_1D_4^{-1}D_3^\top \\ 0 & B_3 \end{pmatrix}, \quad \tilde{B}_1 \triangleq \begin{pmatrix} -D_1D_4^{-1}D_1^\top & B_1^\top \\ B_1 & B_4 \end{pmatrix}, \\
\tilde{C}_1^j &\triangleq \begin{pmatrix} -D_1D_4^{-1}(D_2^j)^\top & (C_1^j)^\top \\ B_2^j & 0 \end{pmatrix}, \quad \tilde{A}_2^j \triangleq \begin{pmatrix} A_2^j & -D_2^jD_4^{-1}D_3^\top \\ 0 & C_3^j \end{pmatrix}, \\
\tilde{B}_2^j &\triangleq \begin{pmatrix} -D_2^jD_4^{-1}D_1^\top & (B_2^j)^\top \\ C_1^j & 0 \end{pmatrix}, \quad \tilde{C}_2^{jk} \triangleq \begin{pmatrix} -D_2^jD_4^{-1}(D_2^k)^\top & (C_2^{jk})^\top \\ C_2^{jk} & C_4^{jk} \end{pmatrix}, \\
\tilde{A}_3 &\triangleq \begin{pmatrix} A_4 & A_3^\top \\ A_3 & -D_3D_4^{-1}D_3^\top \end{pmatrix}, \quad \tilde{B}_3 \triangleq \begin{pmatrix} A_1^\top & 0 \\ -D_3D_4^{-1}D_1^\top & B_3^\top \end{pmatrix}, \\
\tilde{C}_3^j &\triangleq \begin{pmatrix} (A_2^j)^\top & 0 \\ -D_3D_4^{-1}(D_2^j)^\top & (C_3^j)^\top \end{pmatrix}, \quad \tilde{X}_0 \triangleq \begin{pmatrix} x_0 \\ H\bar{Y}_0 \end{pmatrix}, \quad \tilde{E}_1 \triangleq \begin{pmatrix} E_1 \\ 0 \end{pmatrix}, \\
\tilde{E}_2^j &\triangleq \begin{pmatrix} E_2^j \\ 0 \end{pmatrix}, \quad \tilde{E}_3 \triangleq \begin{pmatrix} 0 \\ E_3 \end{pmatrix}, \quad \tilde{F} \triangleq \begin{pmatrix} G & F^\top \\ F & 0 \end{pmatrix}, \quad \tilde{\xi} \triangleq \begin{pmatrix} 0 \\ \xi \end{pmatrix},
\end{aligned}$$

we have

$$\begin{cases} d\tilde{X}_t = \left[ \tilde{A}_1 \tilde{X} + \tilde{B}_1 \tilde{Y} + \sum_{j=1}^{l_2} \tilde{C}_1^j \tilde{Z}^j + \tilde{E}_1 \right] dt + \sum_{j=1}^{l_2} \left[ \tilde{A}_2^j \tilde{X} + \tilde{B}_2^j \tilde{Y} + \sum_{k=1}^{l_2} \tilde{C}_2^{jk} \tilde{Z}^k + \tilde{E}_2^j \right] dB_t^j, \\ d\tilde{Y}_t = - \left[ \tilde{A}_3 \tilde{X} + \tilde{B}_3 \tilde{Y} + \sum_{j=1}^{l_2} \tilde{C}_3^j \tilde{Z}^j + \tilde{E}_3 \right] dt + \sum_{j=1}^{l_2} \tilde{Z}_t^j dB_t^j, \\ \tilde{X}_0 = \begin{pmatrix} x_0 \\ H\tilde{Y}_0 \end{pmatrix}, \tilde{Y}_T = \tilde{F}\tilde{X}_T + \tilde{\xi}. \end{cases} \quad (\text{A.7})$$

In the following, we only study the case of

$$C_2^{jk} = \begin{cases} 0, & 1 \leq j \neq k \leq l_2, \\ C_2^{jk}, & j = k, \end{cases}$$

$$C_4^{jk} = \begin{cases} 0, & 1 \leq j \neq k \leq l_2, \\ C_4^{jk}, & j = k, \end{cases}$$

and

$$D_4^{jk} = \begin{cases} 0, & 1 \leq j \neq k \leq m, \\ D_4^{jk}, & j = k, \end{cases}$$

for simplification, and the general case has no intrinsic difficulty but complexity of computation and notation. Now (A.7) becomes

$$\begin{cases} d\tilde{X}_t = \left[ \tilde{A}_1 \tilde{X} + \tilde{B}_1 \tilde{Y} + \sum_{j=1}^{l_2} \tilde{C}_1^j \tilde{Z}^j + \tilde{E}_1 \right] dt + \sum_{j=1}^{l_2} \left[ \tilde{A}_2^j \tilde{X} + \tilde{B}_2^j \tilde{Y} + \tilde{C}_2^{jj} \tilde{Z}^j + \tilde{E}_2^j \right] dB_t^j, \\ d\tilde{Y}_t = - \left[ \tilde{A}_3 \tilde{X} + \tilde{B}_3 \tilde{Y} + \sum_{j=1}^{l_2} \tilde{C}_3^j \tilde{Z}^j + \tilde{E}_3 \right] dt + \sum_{j=1}^{l_2} \tilde{Z}_t^j dB_t^j, \\ \tilde{X}_0 = \begin{pmatrix} x_0 \\ H\tilde{Y}_0 \end{pmatrix}, \tilde{Y}_T = \tilde{F}\tilde{X}_T + \tilde{\xi}. \end{cases} \quad (\text{A.8})$$

Similar to [8], we can build the relation  $\tilde{Y}_t = Q_t \tilde{X}_t + \varphi_t$  with

$$\begin{cases} \dot{Q} + Q\tilde{A}_1 + \tilde{A}_1^\top Q + \sum_{j=1}^{l_2} (\tilde{B}_2^j Q + \tilde{A}_2^j)^\top (I - Q\tilde{C}_2^{jj})^{-1} Q (\tilde{B}_2^j Q + \tilde{A}_2^j) + Q\tilde{B}_1 Q + \tilde{A}_3 = 0, \\ Q_T = \tilde{F}, \end{cases} \quad (\text{A.9})$$

and

$$\begin{cases} d\varphi_t = - \left[ \left( Q\tilde{B}_1 + \tilde{B}_3 + \sum_{j=1}^{l_2} (Q\tilde{C}_1^j + \tilde{C}_3^j) (I - Q\tilde{C}_2^{jj})^{-1} Q\tilde{B}_2^j \right) \varphi \right. \\ \quad \left. + \sum_{j=1}^{l_2} (Q\tilde{C}_1^j + \tilde{C}_3^j) (I - Q\tilde{C}_2^{jj})^{-1} V^j \right. \\ \quad \left. + \sum_{j=1}^{l_2} (Q\tilde{C}_1^j + \tilde{C}_3^j) (I - Q\tilde{C}_2^{jj})^{-1} Q\tilde{E}_2^j + Q\tilde{E}_1 + \tilde{E}_3 \right] dt + \sum_{j=1}^{l_2} V_t^j dB_t^j, \\ \varphi_T = \tilde{\xi}. \end{cases} \quad (\text{A.10})$$

where, noting that  $\tilde{B}_3 \equiv \tilde{A}_1^\top$ ,  $\tilde{C}_1^j \equiv (\tilde{B}_2^j)^\top$ ,  $\tilde{C}_3^j \equiv (\tilde{A}_2^j)^\top$ . Set

$$\begin{aligned} Q &\triangleq \begin{pmatrix} Q_1 & Q_2 \\ Q_3 & -Q_4 \end{pmatrix}, \quad k^j \triangleq (I - Q\tilde{C}_2^{jj})^{-1}Q(\tilde{B}_2^jQ + \tilde{A}_2^j) \equiv \begin{pmatrix} k_1^j & k_2^j \\ k_3^j & k_4^j \end{pmatrix}, \\ \varphi &= \begin{pmatrix} \varphi_1 \\ \varphi_2 \end{pmatrix}, \quad V^j \triangleq \begin{pmatrix} V_1^j \\ V_2^j \end{pmatrix}, \\ \begin{pmatrix} J_1^j & J_2^j \\ J_3^j & J_4^j \end{pmatrix} &\triangleq (I - Q\tilde{C}_2^{jj})^{-1}Q\tilde{B}_2^j, \quad \begin{pmatrix} I_1^j & I_2^j \\ I_3^j & I_4^j \end{pmatrix} \triangleq (I - Q\tilde{C}_2^{jj})^{-1}, \end{aligned}$$

where  $Q_1, k_1^j, J_1^j, I_1^j \in \mathbb{R}^{n \times n}$ ,  $Q_2, k_2^j, J_2^j, I_2^j \in \mathbb{R}^{n \times Nn}$ ,  $Q_3, k_3^j, J_3^j, I_3^j \in \mathbb{R}^{Nn \times n}$ ,  $Q_4, k_4^j, J_4^j, I_4^j \in \mathbb{R}^{Nn \times Nn}$ ,  $\varphi_1, V_1^j \in \mathbb{R}^n$  and  $\varphi_2, V_2^j \in \mathbb{R}^{Nn}$ .

Moreover, the following relationships hold:

$$\begin{aligned} \bar{X} &= X^*, \quad h = h^*, \quad \bar{Y} = Q_3X^* - Q_4h^* + \varphi_2, \quad m = Q_1X^* + Q_2h^* + \varphi_1, \\ \bar{Z}^j &= k_3^jX^* + k_4^jh^* + J_3^j\varphi_1 + J_4^j\varphi_2 + (I_3^jQ_1 + I_4^jQ_3)E_2^j + I_3^jV_1^j + I_4^jV_2^j, \\ n^j &= k_1^jX^* + k_2^jh^* + J_1^j\varphi_1 + J_2^j\varphi_2 + (I_1^jQ_1 + I_2^jQ_3)E_2^j + I_1^jV_1^j + I_2^jV_2^j, \end{aligned} \quad (\text{A.11})$$

and the optimal control is

$$\begin{aligned} \bar{u} &= D_4^{-1} \left( -D_1^\top Q_1 - \sum_{j=1}^{l_2} (D_2^j)^\top k_1^j \right) X^* + D_4^{-1} \left( -D_3^\top - D_1^\top Q_2 - \sum_{j=1}^{l_2} (D_2^j)^\top k_2^j \right) h^* \\ &\quad - D_4^{-1} \left( D_1^\top \varphi_1 + \sum_{j=1}^{l_2} (D_2^j)^\top J_1^j \varphi_1 + \sum_{j=1}^{l_2} (D_2^j)^\top J_2^j \varphi_2 \right) \\ &\quad - D_4^{-1} \left( \sum_{j=1}^{l_2} (D_2^j)^\top I_1^j V_1^j + \sum_{j=1}^{l_2} (D_2^j)^\top I_2^j V_2^j \right) - D_4^{-1} \sum_{j=1}^{l_2} (D_2^j)^\top (I_1^j Q_1 + I_2^j Q_3) E_2^j, \end{aligned} \quad (\text{A.12})$$

where

$$\begin{aligned} d\bar{X}_t^* &= \left[ \left( \tilde{A}_1 + \tilde{B}_1 Q + \sum_{j=1}^{l_2} \tilde{C}_1^j k^j \right) \bar{X}^* + \left( \tilde{B}_1 + \sum_{j=1}^{l_2} \tilde{C}_1^j (I - Q\tilde{C}_2^{jj})^{-1} Q \tilde{B}_2^j \right) \varphi \right. \\ &\quad \left. + \sum_{j=1}^{l_2} \tilde{C}_1^j (I - Q\tilde{C}_2^{jj})^{-1} V^j + \tilde{E}_1 + \sum_{j=1}^{l_2} \tilde{C}_1^j (I - Q\tilde{C}_2^{jj})^{-1} Q \tilde{E}_2^j \right] dt \\ &\quad + \sum_{j=1}^{l_2} \left[ \left( \tilde{A}_2^j + \tilde{B}_2^j Q + \tilde{C}_2^{jj} k^j \right) \bar{X}^* + \left( \tilde{B}_2^j + \tilde{C}_2^{jj} (I - Q\tilde{C}_2^{jj})^{-1} Q \tilde{B}_2^j \right) \varphi \right. \\ &\quad \left. + \tilde{C}_2^{jj} (I - Q\tilde{C}_2^{jj})^{-1} V^j + \tilde{E}_2^j + \tilde{C}_2^{jj} (I - Q\tilde{C}_2^{jj})^{-1} Q \tilde{E}_2^j \right] dB_t^j. \end{aligned} \quad (\text{A.13})$$

**A.2. Indefinite case.** In this subsection, we do not need the condition  $D_4 > 0$ . Therefore, in order to obtain the optimal control, motivated by relations (A.11), we set

$$\begin{aligned} m_t &= P_1(t)\bar{X}_t + P_2(t)h_t + \varphi_1(t), \\ \bar{Y}_t &= P_2^\top(t)\bar{X}_t - P_3(t)h_t + \varphi_2(t), \end{aligned} \quad (\text{A.14})$$

and  $(\varphi_1, V_1), (\varphi_2, V_2)$  satisfy

$$d\varphi_1 = -\gamma_1 dt + \sum_{j=1}^{l_2} V_1^j dB_t^j, \quad d\varphi_2 = -\gamma_2 dt + \sum_{j=1}^{l_2} V_2^j dB_t^j. \quad (\text{A.15})$$

By applying Itô's formula, we have

$$\begin{aligned}
d\bar{Y}_t &= P_2^\top \left[ A_1 \bar{X} + B_1^\top \bar{Y} + \sum_{k=1}^{l_2} (C_1^k)^\top \bar{Z}^k + D_1 \bar{u} + E_1 \right] dt \\
&\quad + P_2^\top \sum_{j=1}^{l_2} [A_2^j \bar{X} + (B_2^j)^\top \bar{Y} + (C_2^{jj})^\top \bar{Z}^j + D_2^j \bar{u} + E_2^j] dB_t^j \\
&\quad + \dot{P}_2^\top \bar{X} dt - P_3 \left[ B_3 h + B_1 m + \sum_{j=1}^{l_2} B_2^j n^j + B_4 \bar{Y} \right] dt \\
&\quad - P_3 \sum_{j=1}^{l_2} [C_3^j h + C_1^j m + C_2^{jj} n^j + C_4^{jj} \bar{Z}^j] dB_t^j - \dot{P}_3 h dt - \gamma_2 dt + \sum_{j=1}^{l_2} V_2^j dB_t^j, \\
dm_t &= P_1 \left[ A_1 \bar{X} + B_1^\top \bar{Y} + \sum_{k=1}^{l_2} (C_1^k)^\top \bar{Z}^k + D_1 \bar{u} + E_1 \right] dt \\
&\quad + P_1 \sum_{j=1}^{l_2} [A_2^j \bar{X} + (B_2^j)^\top \bar{Y} + (C_2^{jj})^\top \bar{Z}^j + D_2^j \bar{u} + E_2^j] dB_t^j \\
&\quad + \dot{P}_1 \bar{X} dt + P_2 \left[ B_3 h + B_1 m + \sum_{j=1}^{l_2} B_2^j n^j + B_4 \bar{Y} \right] dt \\
&\quad + P_2 \sum_{j=1}^{l_2} [C_3^j h + C_1^j m + C_2^{jj} n^j + C_4^{jj} \bar{Z}^j] dB_t^j + \dot{P}_2 h dt - \gamma_1 dt + \sum_{j=1}^{l_2} V_1^j dB_t^j.
\end{aligned}$$

Comparing the coefficients, we have

$$\begin{aligned}
&P_2^\top A_1 \bar{X} + P_2^\top B_1^\top \bar{Y} + P_2^\top \sum_{k=1}^{l_2} (C_1^k)^\top \bar{Z}^k + P_2^\top D_1 \bar{u} + P_2^\top E_1 + \dot{P}_2^\top \bar{X} - P_3 B_3 h - P_3 B_1 m \\
&\quad - P_3 \sum_{j=1}^{l_2} B_2^j n^j - P_3 B_4 \bar{Y} - \dot{P}_3 h - \gamma_2 = - \left[ A_3 \bar{X} + B_3^\top \bar{Y} + \sum_{j=1}^{l_2} (C_3^j)^\top \bar{Z}^j + D_3 \bar{u} + E_3 \right], \\
&P_1 A_1 \bar{X} + P_1 B_1^\top \bar{Y} + P_1 \sum_{k=1}^{l_2} (C_1^k)^\top \bar{Z}^k + P_1 D_1 \bar{u} + P_1 E_1 + \dot{P}_1 \bar{X} + P_2 B_3 h + P_2 B_1 m \\
&\quad + P_2 \sum_{j=1}^{l_2} B_2^j n^j + P_2 B_4 \bar{Y} + \dot{P}_2 h - \gamma_1 = - \left[ A_3^\top h + A_1^\top m + \sum_{j=1}^{l_2} (A_2^j)^\top n^j + A_4 \bar{X} \right],
\end{aligned}$$

and

$$\begin{aligned}
\bar{Z}^j &= P_2^\top A_2^j \bar{X} + P_2^\top (B_2^j)^\top \bar{Y} + P_2^\top (C_2^{jj})^\top \bar{Z}^j + P_2^\top D_2^j \bar{u} + P_2^\top E_2^j - P_3 C_3^j h \\
&\quad - P_3 C_1^j m - P_3 C_2^{jj} n^j - P_3 C_4^{jj} \bar{Z}^j + V_2^j, \\
n_t^j &= P_1 A_2^j \bar{X} + P_1 (B_2^j)^\top \bar{Y} + P_1 (C_2^{jj})^\top \bar{Z}^j + P_1 D_2^j \bar{u} + P_1 E_2^j + P_2 C_3^j h \\
&\quad + P_2 C_1^j m + P_2 C_2^{jj} n^j + P_2 C_4^{jj} \bar{Z}^j + V_1^j,
\end{aligned}$$

which imply that

$$\begin{aligned}
\bar{Z}^j &= (L_1^j)^{-1} \left[ P_2^\top A_2^j \bar{X} + P_2^\top (B_2^j)^\top \bar{Y} - P_2^\top (B_2^j)^\top P_3 h + P_2^\top (B_2^j)^\top \varphi_2 + P_2^\top D_2^j \bar{u} \right. \\
&\quad \left. + P_2^\top E_2^j - P_3 C_3^j h - P_3 C_1^j P_1 \bar{X} - P_3 C_2^{jj} P_1 h - P_3 C_4^{jj} \varphi_1 - P_3 C_2^{jj} n^j + V_2^j \right], \tag{A.16}
\end{aligned}$$

where  $L_1^j \triangleq I - P_2^\top (C_2^{jj})^\top + P_3 C_4^{jj} \in \mathbb{R}^{Nn \times Nn}$ ,

$$\begin{aligned}
n^j &= [P_1 A_2^j + P_1 (B_2^j)^\top P_2^\top + P_2 C_1^j P_1] \bar{X} - P_1 (B_2^j)^\top P_3 h + P_1 (B_2^j)^\top \varphi_2 \\
&\quad + [P_1 (C_2^{jj})^\top + P_2 C_4^{jj}] (L_1^j)^{-1} [P_2^\top A_2^j \bar{X} + P_2^\top (B_2^j)^\top P_2^\top \bar{X} \\
&\quad - P_2^\top (B_2^j)^\top P_3 h + P_2^\top (B_2^j)^\top \varphi_2 + P_2^\top D_2^j \bar{u} + P_2^\top E_2^j - P_3 C_3^j h \\
&\quad - P_3 C_1^j P_1 \bar{X} - P_3 C_1^j P_2 h - P_3 C_1^j \varphi_1 - P_3 C_2^{jj} n^j + V_2^j] \\
&\quad + P_1 D_2^j \bar{u} + P_1 E_2^j + P_2 C_3^j h + P_2 C_1^j P_2 h + P_2 C_1^j \varphi_1 + P_2 C_2^{jj} n^j + V_1^j,
\end{aligned} \tag{A.17}$$

and

$$\begin{aligned}
&[I + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_3 C_2^{jj} - P_2 C_2^{jj}] n^j \\
&= [P_1 A_2^j + P_1 (B_2^j)^\top P_2^\top + P_2 C_1^j P_1 + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} (P_2^\top A_2^j \\
&\quad + P_2^\top (B_2^j)^\top P_2^\top - P_3 C_1^j P_1)] \bar{X} + [-P_1 (B_2^j)^\top P_3 + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) \\
&\quad \times (L_1^j)^{-1} (-P_2^\top (B_2^j)^\top P_3 - P_3 C_3^j - P_3 C_1^j P_2) + P_2 C_3^j + P_2 C_1^j P_2] h \\
&\quad + [P_1 (B_2^j)^\top + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top (B_2^j)^\top] \varphi_2 \\
&\quad + [- (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_3 C_1^j + P_2 C_1^j] \varphi_1 \\
&\quad + [(P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top D_2^j + P_1 D_2^j] \bar{u} + V_1^j \\
&\quad + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} V_2^j + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top E_2^j + P_1 E_2^j.
\end{aligned} \tag{A.18}$$

Denote

$$\begin{aligned}
L_2^j &\triangleq I + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_3 C_2^{jj} - P_2 C_2^{jj} \in \mathbb{R}^{n \times n}, \\
L_3^j &\triangleq P_1 A_2^j + P_1 (B_2^j)^\top P_2^\top + P_2 C_1^j P_1 + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} (P_2^\top A_2^j \\
&\quad + P_2^\top (B_2^j)^\top P_2^\top - P_3 C_1^j P_1) \in \mathbb{R}^{n \times n}, \\
L_4^j &\triangleq -P_1 (B_2^j)^\top P_3 + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} (-P_2^\top (B_2^j)^\top P_3 \\
&\quad - P_3 C_3^j - P_3 C_1^j P_2) + P_2 C_3^j + P_2 C_1^j P_2 \in \mathbb{R}^{n \times Nn}, \\
S_1^j &\triangleq (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top + P_1 \in \mathbb{R}^{n \times n}, \\
S_2^j &\triangleq [P_1 (B_2^j)^\top + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top (B_2^j)^\top] \varphi_2 \\
&\quad + [- (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_3 C_1^j + P_2 C_1^j] \varphi_1 \\
&\quad + V_1^j + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} V_2^j \\
&\quad + (P_1 (C_2^{jj})^\top + P_2 C_4^{jj}) (L_1^j)^{-1} P_2^\top E_2^j + P_1 E_2^j \in \mathbb{R}^n, \\
L_5 &\triangleq D_4 + \sum_{j=1}^{l_2} (D_2^j)^\top (L_2^j)^{-1} S_1^j D_2^j \in \mathbb{R}^{m \times m}, \\
L_6 &\triangleq -L_5^{-1} \left( \sum_{j=1}^{l_2} (D_2^j)^\top (L_2^j)^{-1} L_3^j + D_1^\top P_1 \right) \in \mathbb{R}^{m \times n}, \\
L_7 &\triangleq -L_5^{-1} \left( D_3^\top + \sum_{j=1}^{l_2} (D_2^j)^\top (L_2^j)^{-1} L_4^j + D_1^\top P_2 \right) \in \mathbb{R}^{m \times Nn},
\end{aligned} \tag{A.19}$$

and

$$S_3 \triangleq -L_5^{-1} \left( D_1^\top \varphi_1 + \sum_{j=1}^{l_2} (D_2^j)^\top (L_2^j)^{-1} S_2^j \right) \in \mathbb{R}^m,$$

then we have

$$\bar{u} = L_6 \bar{X} + L_7 h + S_3. \quad (\text{A.20})$$

Insert  $\bar{u}$  of (A.20) back to (A.16) and (A.17), and set

$$\begin{aligned} L_8^j &\triangleq (L_2^j)^{-1} (L_3^j + S_1^j D_2^j L_6) \in \mathbb{R}^{n \times n}, \quad L_9^j \triangleq (L_2^j)^{-1} (L_4^j + S_1^j D_2^j L_7) \in \mathbb{R}^{n \times Nn}, \\ L_{10}^j &\triangleq (L_1^j)^{-1} [P_2^\top A_2^j + P_2^\top (B_2^j)^\top P_2^\top + P_2^\top D_2^j L_6 - P_3 C_1^j P_1 - P_3 C_2^{jj} L_8^j] \in \mathbb{R}^{Nn \times n}, \\ L_{11}^j &\triangleq (L_1^j)^{-1} [-P_2^\top (B_2^j)^\top P_3 + P_2^\top D_2^j L_7 - P_3 C_3^j - P_3 C_1^j P_2 - P_3 C_2^{jj} L_9^j] \in \mathbb{R}^{Nn \times Nn}, \\ S_4^j &\triangleq (L_2^j)^{-1} (S_1^j D_2^j S_3 + S_2^j) \in \mathbb{R}^n, \\ S_5^j &\triangleq (L_1^j)^{-1} [P_2^\top (B_2^j)^\top \varphi_2 + P_2^\top D_2^j S_3 + P_2^\top E_2^j - P_3 C_1^j \varphi_1 - P_3 C_2^{jj} S_4^j + V_2^j] \in \mathbb{R}^{Nn}, \end{aligned}$$

then we get

$$\begin{aligned} n^j &= L_8^j \bar{X} + L_9^j h + S_4^j, \\ \bar{Z}^j &= L_{10}^j \bar{X} + L_{11}^j h + S_5^j. \end{aligned} \quad (\text{A.21})$$

Insert the pairs  $(\bar{Z}, n)$  of (A.21) and  $(\bar{Y}, m)$  of (A.14) back, we have

$$\left\{ \begin{aligned} &\dot{P}_2^\top + P_2^\top (A_1 + B_1^\top P_2^\top) + \sum_{j=1}^{l_2} (P_2^\top (C_1^j)^\top + (C_3^j)^\top) L_{10}^j + (P_2^\top D_1 + D_3) L_6 \\ &\quad - P_3 (B_1 P_1 + B_4 P_2^\top) - P_3 \sum_{j=1}^{l_2} B_2^j L_8^j + A_3 + B_3^\top P_2^\top = 0, \\ &\dot{P}_3 + P_2^\top B_1^\top P_3 - \sum_{j=1}^{l_2} (P_2^\top (C_1^j)^\top + (C_3^j)^\top) L_{11}^j - (P_2^\top D_1 + D_3) L_7 + P_3 B_3 \\ &\quad + P_3 B_1 P_2 + P_3 \sum_{j=1}^{l_2} B_2^j L_9^j - P_3 B_4 P_3 + B_3^\top P_3 = 0, \\ &P_2(T) = F^\top, \quad P_3(T) = 0_{Nn \times Nn}, \end{aligned} \right. \quad (\text{A.22})$$

and

$$\begin{aligned} d\varphi_2 = & - \left[ (P_2^\top B_1^\top - P_3 B_4 + B_3^\top) \varphi_2 - P_3 B_1 \varphi_1 + \sum_{j=1}^{l_2} (P_2^\top (C_1^j)^\top + (C_3^j)^\top) S_5^j \right. \\ & \left. + (P_2^\top D_1 + D_3) S_3 + P_2^\top E_1 - P_3 \sum_{j=1}^{l_2} B_2^j S_4^j + E_3 \right] dt + \sum_{j=1}^{l_2} V_2^j dB_1^j. \end{aligned} \quad (\text{A.23})$$

Next, we can also obtain

$$\left\{ \begin{array}{l} \dot{P}_1 + P_1(A_1 + B_1^\top P_2^\top) + P_2 B_4 P_2^\top + P_1 \sum_{j=1}^{l_2} (C_1^j)^\top L_{10}^j + P_1 D_1 L_6 \\ \quad + (P_2 B_1 + A_1^\top) P_1 + \sum_{j=1}^{l_2} (P_2 B_2^j + (A_2^j)^\top) L_8^j + A_4 = 0, \\ \dot{P}_2 - (P_1 B_1^\top + P_2 B_4) P_3 + P_1 \sum_{j=1}^{l_2} (C_1^j)^\top L_{11}^j + P_1 D_1 L_7 + P_2 B_3 \\ \quad + (P_2 B_1 + A_1^\top) P_2 + \sum_{j=1}^{l_2} (P_2 B_2^j + (A_2^j)^\top) L_9^j + A_3^\top = 0, \\ P_1(T) = G, P_2(T) = F^\top, \end{array} \right. \quad (\text{A.24})$$

and

$$\begin{aligned} d\varphi_1 = & - \left[ (P_1 B_1^\top + P_2 B_4) \varphi_2 + (P_2 B_1 + A_1^\top) \varphi_1 + P_1 \sum_{j=1}^{l_2} (C_1^j)^\top S_5^j \right. \\ & \left. + P_1 D_1 S_3 + P_1 E_1 + \sum_{j=1}^{l_2} (P_2 B_2^j + (A_2^j)^\top) S_4^j \right] dt + \sum_{j=1}^{l_2} V_1^j dB_t^j. \end{aligned} \quad (\text{A.25})$$

Next, similar to the key idea in [15], we can regard the original forward-backward SLQ optimal control problem as a dimension-enlarged forward SLQ one and build the relationship between them. Let

$$\begin{aligned} \tilde{X} &\equiv \begin{pmatrix} X \\ Y \end{pmatrix}, \quad \tilde{u}^j \equiv \begin{pmatrix} u \\ Z^j \end{pmatrix}, \quad \tilde{A} \triangleq \begin{pmatrix} A_1 & B_1^\top \\ -A_3 & -B_3^\top \end{pmatrix}, \\ \tilde{B}^j &\triangleq \begin{pmatrix} \frac{D_1}{l_2} & (C_1^j)^\top \\ -\frac{D_3}{l_2} & -(C_3^j)^\top \end{pmatrix}, \quad \tilde{C}^j \triangleq \begin{pmatrix} A_2^j & (B_2^j)^\top \\ 0 & 0 \end{pmatrix}, \\ \tilde{D}^j &\triangleq \begin{pmatrix} D_2^j & (C_2^{jj})^\top \\ 0 & I_{N_n \times N_n} \end{pmatrix}, \quad \tilde{E} \triangleq \begin{pmatrix} E_1 \\ -E_3 \end{pmatrix}, \quad \tilde{E}^j \triangleq \begin{pmatrix} E_2^j \\ 0 \end{pmatrix}, \end{aligned} \quad (\text{A.26})$$

then the state equation and cost functional become

$$d\tilde{X} = \left[ \tilde{A}\tilde{X} + \sum_{j=1}^{l_2} \tilde{B}^j \tilde{u}^j + \tilde{E} \right] dt + \sum_{j=1}^{l_2} [\tilde{C}^j \tilde{X} + \tilde{D}^j \tilde{u}^j + \tilde{E}^j] dB_t^j, \quad (\text{A.27})$$

and

$$J(u(\cdot)) = \frac{1}{2} \mathbb{E} \left[ \int_0^T \left( \tilde{X}^\top \tilde{Q} \tilde{X} + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top \tilde{R}^j \tilde{u}^j \right) dt + \langle GX_T, X_T \rangle \right], \quad (\text{A.28})$$

where

$$\tilde{Q} \triangleq \begin{pmatrix} A_4 & 0 \\ 0 & B_4 \end{pmatrix} \in \mathbb{R}^{(N+1)n \times (N+1)n}, \quad \tilde{R}^j \triangleq \begin{pmatrix} D_4 & 0 \\ 0 & C_4^j \end{pmatrix} \in \mathbb{R}^{(Nn+m) \times (Nn+m)}.$$

Assume that  $d\tilde{\varphi} = -\tilde{\gamma}dt + \sum_{j=1}^{l_2} \tilde{V}^j dB_t^j$ , and apply Itô's formula, we achieve

$$\begin{aligned}
& d[(\tilde{X} - \tilde{\varphi})^\top \tilde{P}(\tilde{X} - \tilde{\varphi})] + \left[ \tilde{X}^\top \tilde{Q}\tilde{X} + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top \tilde{R}^j \tilde{u}^j \right] dt \\
&= (\tilde{X} - \tilde{\varphi})^\top \tilde{P} \left[ \tilde{A}\tilde{X} + \sum_{j=1}^{l_2} \tilde{B}^j \tilde{u}^j + \tilde{E} + \tilde{\gamma} \right] dt + (\tilde{X} - \tilde{\varphi})^\top \tilde{P} \sum_{j=1}^{l_2} [\tilde{C}^j \tilde{X} + \tilde{D}^j \tilde{u}^j + \tilde{E}^j - \tilde{V}^j] dB_t^j \\
&\quad + (\tilde{X} - \tilde{\varphi})^\top \dot{\tilde{P}}(\tilde{X} - \tilde{\varphi}) dt + \left[ \tilde{X}^\top \tilde{A}^\top + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top (\tilde{B}^j)^\top + \tilde{E}^\top + \tilde{\gamma}^\top \right] \tilde{P}(\tilde{X} - \tilde{\varphi}) dt \\
&\quad + \sum_{j=1}^{l_2} [\tilde{X}^\top (\tilde{C}^j)^\top + (\tilde{u}^j)^\top (\tilde{D}^j)^\top + (\tilde{E}^j)^\top - (\tilde{V}^j)^\top] \tilde{P}(\tilde{X} - \tilde{\varphi}) dB_t^j \\
&\quad + \sum_{j=1}^{l_2} [\tilde{X}^\top (\tilde{C}^j)^\top + (\tilde{u}^j)^\top (\tilde{D}^j)^\top + (\tilde{E}^j)^\top - (\tilde{V}^j)^\top] \tilde{P} [\tilde{C}^j \tilde{X} + \tilde{D}^j \tilde{u}^j + \tilde{E}^j - \tilde{V}^j] dt \\
&\quad + \left[ \tilde{X}^\top \tilde{Q}\tilde{X} + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top \tilde{R}^j \tilde{u}^j \right] dt \\
&= \left\{ \tilde{X}^\top \left[ \tilde{P}\tilde{A} + \dot{\tilde{P}} + \tilde{A}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{C}^j + \tilde{Q} \right] \tilde{X} + \tilde{X}^\top \left[ \tilde{P}\tilde{E} + \tilde{P}\tilde{\gamma} - \dot{\tilde{P}}\tilde{\varphi} - \tilde{A}^\top \tilde{P}\tilde{\varphi} \right. \right. \\
&\quad + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{E}^j - \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{V}^j \left. \right] + \left[ -\tilde{\varphi}^\top \tilde{P}\tilde{A} - \tilde{\varphi}^\top \dot{\tilde{P}} + \tilde{E}^\top \tilde{P} + \tilde{\gamma}^\top \tilde{P} \right. \\
&\quad + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{C}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{C}^j \left. \right] \tilde{X} + \left[ \tilde{X}^\top \sum_{j=1}^{l_2} (\tilde{P}\tilde{B}^j + (\tilde{C}^j)^\top \tilde{P}\tilde{D}^j) \tilde{u}^j \right. \\
&\quad - \tilde{\varphi}^\top \tilde{P} \sum_{j=1}^{l_2} \tilde{B}^j \tilde{u}^j - \sum_{j=1}^{l_2} (\tilde{u}^j)^\top (\tilde{B}^j)^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top ((\tilde{B}^j)^\top \tilde{P} + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j) \tilde{X} \\
&\quad + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j) \tilde{u}^j + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top (\tilde{D}^j)^\top \tilde{P}\tilde{E}^j - \sum_{j=1}^{l_2} (\tilde{u}^j)^\top (\tilde{D}^j)^\top \tilde{P}\tilde{V}^j \\
&\quad + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{D}^j \tilde{u}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{D}^j \tilde{u}^j \left. \right] - \tilde{\varphi}^\top \tilde{P}\tilde{E} - \tilde{\varphi}^\top \tilde{P}\tilde{\gamma} + \tilde{\varphi}^\top \dot{\tilde{P}}\tilde{\varphi} \\
&\quad - \tilde{E}^\top \tilde{P}\tilde{\varphi} - \tilde{\gamma}^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{E}^j - \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{V}^j \\
&\quad - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{E}^j + \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{V}^j \left. \right\} dt + \{\dots\} dB_t^j \\
&= \left\{ \tilde{X}^\top \left[ \tilde{P}\tilde{A} + \dot{\tilde{P}} + \tilde{A}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{C}^j + \tilde{Q} - \sum_{j=1}^{l_2} (\tilde{P}^\top \tilde{B}^j + (\tilde{C}^j)^\top \tilde{P}^\top \tilde{D}^j) \right. \right. \\
&\quad \times (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j)^{-1} ((\tilde{B}^j)^\top \tilde{P} + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j) \left. \right] \tilde{X} + \tilde{X}^\top \left[ \tilde{P}\tilde{E} + \tilde{P}\tilde{\gamma} - \dot{\tilde{P}}\tilde{\varphi} \right. \\
&\quad - \tilde{A}^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{E}^j - \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{V}^j - \sum_{j=1}^{l_2} (\tilde{P}^\top \tilde{B}^j + (\tilde{C}^j)^\top \tilde{P}^\top \tilde{D}^j) \\
&\quad \times (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j)^{-1} ((\tilde{D}^j)^\top \tilde{P}\tilde{E}^j - (\tilde{B}^j)^\top \tilde{P}\tilde{\varphi} - (\tilde{D}^j)^\top \tilde{P}\tilde{V}^j) \left. \right]
\end{aligned}$$

$$\begin{aligned}
& + \left[ -\tilde{\varphi}^\top \tilde{P}\tilde{A} - \tilde{\varphi}^\top \dot{\tilde{P}} + \tilde{E}^\top \tilde{P} + \tilde{\gamma}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{C}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{C}^j \right. \\
& - \sum_{j=1}^{l_2} [(\tilde{E}^j)^\top \tilde{P}^\top \tilde{D}^j - \tilde{\varphi}^\top \tilde{P}^\top \tilde{B}^j - (\tilde{V}^j)^\top \tilde{P}^\top \tilde{D}^j] (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}^\top \tilde{D}^j)^{-1} \\
& \times ((\tilde{B}^j)^\top \tilde{P} + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j) \tilde{X} - \sum_{j=1}^{l_2} [(\tilde{E}^j)^\top \tilde{P}^\top \tilde{D}^j - \tilde{\varphi}^\top \tilde{P}^\top \tilde{B}^j \\
& - (\tilde{V}^j)^\top \tilde{P}^\top \tilde{D}^j] (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}^\top \tilde{D}^j)^{-1} [(\tilde{D}^j)^\top \tilde{P}\tilde{E}^j - (\tilde{B}^j)^\top \tilde{P}\tilde{\varphi} - (\tilde{D}^j)^\top \tilde{P}\tilde{V}^j] \\
& - \tilde{\varphi}^\top \tilde{P}\tilde{E} - \tilde{\varphi}^\top \tilde{P}\tilde{\gamma} + \tilde{\varphi}^\top \dot{\tilde{P}}\tilde{\varphi} - \tilde{E}^\top \tilde{P}\tilde{\varphi} - \tilde{\gamma}^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{E}^j - \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{V}^j \\
& - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{E}^j + \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{V}^j + \sum_{j=1}^{l_2} \left\{ \tilde{u}^j + (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j)^{-1} [((\tilde{B}^j)^\top \tilde{P} \right. \\
& + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j) \tilde{X} + (\tilde{D}^j)^\top \tilde{P}\tilde{E}^j - (\tilde{B}^j)^\top \tilde{P}\tilde{\varphi} - (\tilde{D}^j)^\top \tilde{P}\tilde{V}^j] \left. \right\}^\top (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j) \\
& \times \left\{ \tilde{u}^j + (\tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j)^{-1} [((\tilde{B}^j)^\top \tilde{P} + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j) \tilde{X} + (\tilde{D}^j)^\top \tilde{P}\tilde{E}^j \right. \\
& \left. - (\tilde{B}^j)^\top \tilde{P}\tilde{\varphi} - (\tilde{D}^j)^\top \tilde{P}\tilde{V}^j] \right\} dt + \{\dots\} dB_t^j \\
& = \left\{ \sum_{j=1}^{l_2} \left\{ \tilde{u}^j + (M_1^j)^{-1} [M_2^j \tilde{X} - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j] \right\}^\top M_1^j \left\{ \tilde{u}^j + (M_1^j)^{-1} [M_2^j \tilde{X} \right. \right. \\
& \left. \left. - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j] \right\} + \tilde{X}^\top \left[ \tilde{P}\tilde{A} + \dot{\tilde{P}} + \tilde{A}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{C}^j + \tilde{Q} \right. \right. \\
& \left. \left. - \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} M_2^j \right] \tilde{X} + \tilde{X}^\top \left[ \tilde{P}\tilde{E} + \tilde{P}\tilde{\gamma} - \dot{\tilde{P}}\tilde{\varphi} - \tilde{A}^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{E}^j \right. \right. \\
& \left. \left. - \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{V}^j - \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} (M_4^j \tilde{E}^j - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j) \right] + \left[ -\tilde{\varphi}^\top \tilde{P}\tilde{A} \right. \right. \\
& \left. \left. - \tilde{\varphi}^\top \dot{\tilde{P}} + \tilde{E}^\top \tilde{P} + \tilde{\gamma}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{C}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{C}^j - \sum_{j=1}^{l_2} [(\tilde{E}^j)^\top (M_4^j)^\top \right. \right. \\
& \left. \left. - \tilde{\varphi}^\top (M_3^j)^\top - (\tilde{V}^j)^\top (M_4^j)^\top] (M_1^j)^{-1} M_2^j \right] \tilde{X} + M_5 \right\} dt + \{\dots\} dB_t^j,
\end{aligned}$$

where

$$\begin{aligned}
M_1^j & \triangleq \tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j \in \mathbb{R}^{(Nn+m) \times (Nn+m)}, \\
M_2^j & \triangleq (\tilde{B}^j)^\top \tilde{P} + (\tilde{D}^j)^\top \tilde{P}\tilde{C}^j \in \mathbb{R}^{(Nn+m) \times (N+1)n}, \\
M_3^j & \triangleq (\tilde{B}^j)^\top \tilde{P} \in \mathbb{R}^{(Nn+m) \times (N+1)n}, \quad M_4^j \triangleq (\tilde{D}^j)^\top \tilde{P} \in \mathbb{R}^{(Nn+m) \times (N+1)n}, \\
M_5 & \triangleq - \sum_{j=1}^{l_2} [\tilde{E}^j M_4^{\top} - \tilde{\varphi}^\top (M_3^j)^\top - (\tilde{V}^j)^\top (M_4^j)^\top] (M_1^j)^{-1} (M_4^j \tilde{E}^j - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j)
\end{aligned}$$

$$\begin{aligned}
& -\tilde{\varphi}^\top \tilde{P}\tilde{E} - \tilde{\varphi}^\top \tilde{P}\tilde{\gamma} + \tilde{\varphi}^\top \dot{\tilde{P}}\tilde{\varphi} - \tilde{E}^\top \tilde{P}\tilde{\varphi} - \tilde{\gamma}^\top \tilde{P}\tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{E}^j \\
& - \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P}\tilde{V}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{E}^j + \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P}\tilde{V}^j.
\end{aligned} \tag{A.29}$$

Then we introduce the Riccati equation:

$$\begin{cases} \dot{\tilde{P}} = -\tilde{P}\tilde{A} - \tilde{A}^\top \tilde{P} - \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P}\tilde{C}^j - \tilde{Q} + \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} M_2^j, \\ \tilde{R}^j + (\tilde{D}^j)^\top \tilde{P}\tilde{D}^j > 0, \\ \tilde{u}^j = -(M_1^j)^{-1} [M_2^j \tilde{X} - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j], \end{cases} \tag{A.30}$$

and

$$\begin{aligned}
\tilde{\gamma} = \tilde{P}^{-1} & \left[ \left( \dot{\tilde{P}} + \tilde{A}^\top \tilde{P} - \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} (M_3^j)^\top \right) \tilde{\varphi} + \sum_{j=1}^{l_2} \left( (\tilde{C}^j)^\top \tilde{P} \right. \right. \\
& \left. \left. - (M_2^j)^\top (M_1^j)^{-1} M_4^j \right) \tilde{V}^j - \tilde{P}\tilde{E} - \sum_{j=1}^{l_2} [(\tilde{C}^j)^\top \tilde{P} - (M_2^j)^\top (M_1^j)^{-1} M_4^j] \tilde{E}^j \right].
\end{aligned} \tag{A.31}$$

It is known that

$$\begin{pmatrix} m \\ -h \end{pmatrix} \equiv \tilde{P}(\tilde{X} - \tilde{\varphi}) \equiv \begin{pmatrix} \tilde{P}_1(\tilde{X} - \tilde{\varphi}_1) + \tilde{P}_2(\tilde{Y} - \tilde{\varphi}_2) \\ \tilde{P}_2^\top(\tilde{X} - \tilde{\varphi}_1) + \tilde{P}_3(\tilde{Y} - \tilde{\varphi}_2) \end{pmatrix},$$

where

$$\tilde{P} \equiv \begin{pmatrix} \tilde{P}_1 & \tilde{P}_2 \\ \tilde{P}_2^\top & \tilde{P}_3 \end{pmatrix}, \quad \tilde{\varphi} = \begin{pmatrix} \tilde{\varphi}_1 \\ \tilde{\varphi}_2 \end{pmatrix}, \quad \tilde{V}^j = \begin{pmatrix} \tilde{V}_1^j \\ \tilde{V}_2^j \end{pmatrix},$$

and compare with

$$\begin{aligned}
m &= (P_1 + P_2 P_3^{-1} P_2^\top) \tilde{X} - P_2 P_3^{-1} \tilde{Y} + P_2 P_3^{-1} \varphi_2 + \varphi_1, \\
h &= P_3^{-1} P_2^\top \tilde{X} - P_3^{-1} \tilde{Y} + P_3^{-1} \varphi_2,
\end{aligned} \tag{A.32}$$

then we can obtain

$$\begin{cases} \tilde{P}_1 = P_1 + P_2 P_3^{-1} P_2^\top, & \tilde{P}_2 = -P_2 P_3^{-1}, & \tilde{P}_3 = P_3^{-1}, \\ \tilde{\varphi}_1 = -P_1^{-1} \varphi_1, & \tilde{V}_1^j = -P_1^{-1} V_1^j, \\ \tilde{\varphi}_2 = -P_2^\top P_1^{-1} \varphi_1 + \varphi_2, & \tilde{V}_2^j = -P_2^\top P_1^{-1} V_1^j + V_2^j. \end{cases} \tag{A.33}$$

As a result of  $P_3(T) = 0$ ,  $P_3(T)^{-1}$  makes no sense. We consider

$$P^i(t) \equiv \begin{pmatrix} P_{1,i} & P_{2,i} \\ P_{2,i}^\top & P_{3,i} \end{pmatrix}, \quad \varphi^i = \begin{pmatrix} \varphi_{1,i} \\ \varphi_{2,i} \end{pmatrix}, \quad V^{j,i} = \begin{pmatrix} V_{1,i}^j \\ V_{2,i}^j \end{pmatrix}$$

to be the solution to equations corresponding to

$$P^i(T) = \begin{pmatrix} G & F^\top \\ F & \frac{1}{i} I_{Nn \times Nn} \end{pmatrix}, \quad \varphi_T^i = \begin{pmatrix} 0 \\ \xi \end{pmatrix}. \tag{A.34}$$

It corresponds to a sequence of solutions to Riccati equations for

$$\tilde{P}^i \equiv \begin{pmatrix} \tilde{P}_{1,i} & \tilde{P}_{2,i} \\ \tilde{P}_{2,i}^\top & \tilde{P}_{3,i} \end{pmatrix}, \quad \tilde{\varphi}^i = \begin{pmatrix} \tilde{\varphi}_{1,i} \\ \tilde{\varphi}_{2,i} \end{pmatrix}, \quad \tilde{V}^{j,i} = \begin{pmatrix} \tilde{V}_{1,i}^j \\ \tilde{V}_{2,i}^j \end{pmatrix},$$

with terminal conditions

$$\tilde{P}^i(T) = \begin{pmatrix} G + iF^\top F & -iF^\top \\ -iF & iI_{Nn \times Nn} \end{pmatrix}, \quad \tilde{\varphi}_T^i = \begin{pmatrix} 0 \\ \xi \end{pmatrix}, \quad (\text{A.35})$$

and similarly

$$\begin{aligned} P_{1,i} &= \tilde{P}_{1,i} - P_{2,i} P_{3,i}^{-1} P_{2,i}^\top, & P_{2,i} &= -\tilde{P}_{2,i} \tilde{P}_{3,i}^{-1}, & P_{3,i} &= \tilde{P}_{3,i}^{-1}, \\ \varphi_{1,i} &= -P_{1,i} \tilde{\varphi}_{1,i}, & V_{1,i}^j &= -P_{1,i} \tilde{V}_{1,i}^j, \\ \varphi_{2,i} &= \tilde{\varphi}_{2,i} - P_{2,i}^\top \tilde{\varphi}_{1,i}, & V_{2,i}^j &= \tilde{V}_{2,i}^j - P_{2,i}^\top \tilde{V}_{1,i}^j. \end{aligned} \quad (\text{A.36})$$

In the following, we have the relationships

$$\begin{aligned} (M_{1,i}^j)^{-1} M_{2,i}^j &= - \begin{pmatrix} L_{6,i} + L_{7,i} P_{3,i}^{-1} P_{2,i}^\top & -L_{7,i} P_{3,i}^{-1} \\ L_{10,i} + L_{11,i} P_{3,i}^{-1} P_{2,i}^\top & -L_{11,i} P_{3,i}^{-1} \end{pmatrix} \in \mathbb{R}^{(Nn+m) \times (N+1)n}, \\ (M_{1,i}^j)^{-1} [M_{3,i}^j \tilde{\varphi}^i + M_{4,i}^j \tilde{V}^{j,i} + M_{4,i}^j \tilde{E}^j] &= \begin{pmatrix} L_{7,i} P_{3,i}^{-1} \varphi_{2,i} + S_{3,i} \\ L_{11,i} P_{3,i}^{-1} \varphi_{2,i} + S_{5,i} \end{pmatrix} \in \mathbb{R}^{Nn+m}. \end{aligned} \quad (\text{A.37})$$

The proof of relation (A.37) and the solvabilities of Riccati equations are similar to those in [8]. Thus they are omitted.

Next, we derive the feedback optimal control in the indefinite case. First, according to Lemma 4.12 in [8], it implies that  $M_{5,i}$  is uniformly bounded, and assume that  $P_3 = \lim_{i \rightarrow \infty} P_{3,i} > 0$ . Set  $\bar{u} = L_6 X^* + L_7 h^* + S_3$ , and let

$$\begin{aligned} N_1 &\triangleq A_1 + B_1^\top P_2^\top + \sum_{j=1}^{l_2} (C_1^j)^\top L_{10}^j + D_1 L_6, & N_2 &\triangleq -B_1^\top P_3 + \sum_{j=1}^{l_2} (C_1^j)^\top L_{11}^j + D_1 L_7, \\ N_3 &\triangleq B_1^\top \varphi_2 + \sum_{j=1}^{l_2} (C_1^j)^\top S_5^j + E_1 + D_1 S_3, & N_4^j &\triangleq A_2^j + (B_2^j)^\top P_2^\top + (C_2^{jj})^\top L_{10}^j + D_2^j L_6, \\ N_5^j &\triangleq -(B_2^j)^\top P_3 + (C_2^{jj})^\top L_{11}^j + D_2^j L_7, & N_6^j &\triangleq (B_2^j)^\top \varphi_2 + (C_2^{jj})^\top S_5^j + D_2^j S_3 + E_2^j, \\ N_7 &\triangleq B_1 P_1 + \sum_{j=1}^{l_2} B_2^j L_8^j + B_4 P_2^\top, & N_8 &\triangleq B_3 + B_1 P_2 + \sum_{j=1}^{l_2} B_2^j L_9^j - B_4 P_3, \\ N_9 &\triangleq B_1 \varphi_1 + \sum_{j=1}^{l_2} B_2^j S_4^j + B_4 \varphi_2, & N_{10}^j &\triangleq C_1^j P_1 + C_2^{jj} L_8^j + C_4^{jj} L_{10}^j, \\ N_{11}^j &\triangleq C_3^j + C_1^j P_2 + C_2^{jj} L_9^j + C_4^{jj} L_{11}^j, & N_{12}^j &\triangleq C_1^j \varphi_1 + C_2^{jj} S_4^j + C_4^{jj} S_5^j, \end{aligned}$$

then we have

$$\begin{cases} dX^* = (N_1 X^* + N_2 h^* + N_3) dt + \sum_{j=1}^{l_2} (N_4^j X^* + N_5^j h^* + N_6^j) dB_t^j, \\ dh^* = (N_7 X^* + N_8 h^* + N_9) dt + \sum_{j=1}^{l_2} (N_{10}^j X^* + N_{11}^j h^* + N_{12}^j) dB_t^j, \\ X_0^* = x_0, h_0^* = (I_{Nn \times Nn} + H P_3(0))^{-1} H (P_2^\top(0) X_0 + \varphi_2(0)). \end{cases} \quad (\text{A.38})$$

Moreover

$$\begin{aligned}\bar{X}_t &= X_t^*, \quad h_t = h_t^*, \\ n_t^j &= L_8^j \bar{X}_t + L_9^j h_t + S_4^j, \quad m_t = P_1(t) \bar{X}_t + P_2(t) h_t + \varphi_1(t), \\ \bar{Z}_t^j &= L_{10}^j \bar{X}_t + L_{11}^j h_t + S_5^j, \quad \bar{Y}_t = P_2^\top(t) \bar{X}_t - P_3(t) h_t + \varphi_2(t).\end{aligned}\tag{A.39}$$

Set

$$\tilde{P} = \begin{pmatrix} P_1 + P_2 P_3^{-1} P_2^\top & -P_2 P_3^{-1} \\ -P_3^{-1} P_2^\top & P_3^{-1} \end{pmatrix}.\tag{A.40}$$

For any given  $\varepsilon > 0$ ,  $\tilde{P}$  solves the Riccati equations on  $[0, T - \varepsilon]$ . By the completion of square technique, recalling that

$$\begin{aligned}& d[(\tilde{X} - \tilde{\varphi})^\top \tilde{P}(\tilde{X} - \tilde{\varphi})] + \left[ \tilde{X}^\top \tilde{Q} \tilde{X} + \sum_{j=1}^{l_2} (\tilde{u}^j)^\top \tilde{R}^j \tilde{u}^j \right] dt \\ &= \left\{ \sum_{j=1}^{l_2} \left\{ \tilde{u}^j + (M_1^j)^{-1} [M_2^j \tilde{X} - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j] \right\}^\top M_1^j \left\{ \tilde{u}^j + (M_1^j)^{-1} [M_2^j \tilde{X} \right. \right. \\ &\quad \left. \left. - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j] \right\} + \tilde{X}^\top \left[ \tilde{P} \tilde{A} + \dot{\tilde{P}} + \tilde{A}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P} \tilde{C}^j + \tilde{Q} \right. \right. \\ &\quad \left. \left. - \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} M_2^j \right] \tilde{X} + \tilde{X}^\top \left[ \tilde{P} \tilde{E} + \tilde{P} \tilde{\gamma} - \dot{\tilde{P}} \tilde{\varphi} - \tilde{A}^\top \tilde{P} \tilde{\varphi} + \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P} \tilde{E}^j \right. \right. \\ &\quad \left. \left. - \sum_{j=1}^{l_2} (\tilde{C}^j)^\top \tilde{P} \tilde{V}^j - \sum_{j=1}^{l_2} (M_2^j)^\top (M_1^j)^{-1} (M_4^j \tilde{E}^j - M_3^j \tilde{\varphi} - M_4^j \tilde{V}^j) \right] + \left[ -\tilde{\varphi}^\top \tilde{P} \tilde{A} \right. \right. \\ &\quad \left. \left. - \tilde{\varphi}^\top \dot{\tilde{P}} + \tilde{E}^\top \tilde{P} + \tilde{\gamma}^\top \tilde{P} + \sum_{j=1}^{l_2} (\tilde{E}^j)^\top \tilde{P} \tilde{C}^j - \sum_{j=1}^{l_2} (\tilde{V}^j)^\top \tilde{P} \tilde{C}^j - \sum_{j=1}^{l_2} [(\tilde{E}^j)^\top (M_4^j)^\top \right. \right. \\ &\quad \left. \left. - \tilde{\varphi}^\top (M_3^j)^\top - (\tilde{V}^j)^\top (M_4^j)^\top] (M_1^j)^{-1} M_2^j \right] \tilde{X} + M_5 \right\} dt + \{\dots\} dB_t^j,\end{aligned}$$

we obtain

$$\begin{aligned}J(\bar{u}) &= \frac{1}{2} \mathbb{E} \left[ \int_0^{T-\varepsilon} \left( \bar{X} A_4 \bar{X} + \bar{Y}^\top B_4 \bar{Y} + \sum_{j=1}^{l_2} (\bar{Z}^j)^\top C_4^j \bar{Z}^j + \bar{u} D_4 \bar{u} \right) dt \right. \\ &\quad \left. + \int_{T-\varepsilon}^T \left( \bar{X} A_4 \bar{X} + \bar{Y}^\top B_4 \bar{Y} + \sum_{j=1}^{l_2} (\bar{Z}^j)^\top C_4^j \bar{Z}^j + \bar{u} D_4 \bar{u} \right) dt + \bar{Y}_0^\top H \bar{Y}_0 + \bar{X}_T^\top G \bar{X}_T \right] \\ &= \frac{1}{2} \mathbb{E} [(\bar{X}_0 - \bar{\varphi}_0)^\top \tilde{P}_0 (\bar{X}_0 - \bar{\varphi}_0) - (\bar{X}_{T-\varepsilon} - \bar{\varphi}_{T-\varepsilon})^\top \tilde{P}_{T-\varepsilon} (\bar{X}_{T-\varepsilon} - \bar{\varphi}_{T-\varepsilon})] \\ &\quad + \frac{1}{2} \mathbb{E} \int_0^{T-\varepsilon} \sum_{j=1}^{l_2} \left[ \tilde{u}^j + (M_1^j)^{-1} (M_2^j \bar{X} - M_3^j \bar{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j) \right]^\top \\ &\quad \times M_1^j \left[ \tilde{u}^j + (M_1^j)^{-1} (M_2^j \bar{X} - M_3^j \bar{\varphi} - M_4^j \tilde{V}^j + M_4^j \tilde{E}^j) \right] dt + \frac{1}{2} \mathbb{E} \int_0^{T-\varepsilon} M_5 dt \\ &\quad + \frac{1}{2} \mathbb{E} \int_{T-\varepsilon}^T \left[ \bar{X} A_4 \bar{X} + \bar{Y}^\top B_4 \bar{Y} + \sum_{j=1}^{l_2} (\bar{Z}^j)^\top C_4^j \bar{Z}^j + \bar{u} D_4 \bar{u} \right] dt \\ &\quad + \frac{1}{2} \mathbb{E} [\bar{Y}_0^\top H \bar{Y}_0 + \bar{X}_T^\top G \bar{X}_T],\end{aligned}$$

where

$$\begin{aligned} & (X_0^\top - \tilde{\varphi}_1^\top(0), \bar{Y}_0^\top - \tilde{\varphi}_2^\top(0)) \begin{pmatrix} \tilde{P}_1(0) & \tilde{P}_2(0) \\ \tilde{P}_2^\top(0) & \tilde{P}_3(0) \end{pmatrix} \begin{pmatrix} X_0 - \varphi_1(0) \\ \bar{Y}_0 - \varphi_2(0) \end{pmatrix} + \bar{Y}_0^\top H \bar{Y}_0 \\ &= \mathbb{R}_2 + (\bar{Y}_0 - (I_{Nn \times Nn} + P_3(0)H)^{-1} (P_2^\top(0)X_0 + \varphi_2(0)))^\top (H + P_3^{-1}(0)) \\ & \quad \times (\bar{Y}_0 - (I_{Nn \times Nn} + P_3(0)H)^{-1} (P_2^\top(0)X_0 + \varphi_2(0))), \end{aligned}$$

with

$$\begin{aligned} \mathbb{R}_2 \triangleq & (X_0 + P_1^{-1}(0)\varphi_1(0))^\top P_1(0)(X_0 + P_1^{-1}(0)\varphi_1(0)) \\ & + (P_2^\top(0)X_0 + \varphi_2(0))^\top (HP_3(0) + I_{Nn \times Nn})^{-1} H (P_2^\top(0)X_0 + \varphi_2(0)), \end{aligned}$$

and

$$\begin{aligned} & \bar{X}_T^\top G \bar{X}_T - (\bar{X}_{T-\varepsilon} - \tilde{\varphi}_{T-\varepsilon})^\top \tilde{P}(T-\varepsilon) (\bar{X}_{T-\varepsilon} - \tilde{\varphi}_{T-\varepsilon}) \\ &= \bar{X}_T^\top G \bar{X}_T - (\bar{X}_{T-\varepsilon} + P_1^{-1}(T-\varepsilon)\varphi_1(T-\varepsilon))^\top P_1(T-\varepsilon) (\bar{X}_{T-\varepsilon} \\ & \quad + P_1^{-1}(T-\varepsilon)\varphi_1(T-\varepsilon)) - h_{T-\varepsilon}^\top P_3(T-\varepsilon) h_{T-\varepsilon} \rightarrow 0, \text{ when } \varepsilon \rightarrow 0. \end{aligned}$$

Similar to [8], we have

$$J(\bar{u}) = \frac{1}{2} \mathbb{E} \left[ \mathbb{R}_2 + \int_0^T M_5(t) dt \right], \quad (\text{A.41})$$

and  $J(u) \geq J(\bar{u})$ , which means  $\bar{u}$  is optimal, and finally by (A.37)

$$\bar{u} = (L_6 + L_7 P_3^{-1} P_2^\top) \bar{X} - L_7 P_3^{-1} \bar{Y} + L_7 P_3^{-1} \varphi_2 + S_3. \quad (\text{A.42})$$

where  $P_1(t) = \lim_{i \rightarrow \infty} P_{1,i}$ ,  $P_2(t) = \lim_{i \rightarrow \infty} P_{2,i}$  and  $L_6, L_7, S_3$  are defined in (A.19).

We conclude the above analysis as the following main theorem.

**Theorem A.1.** *Suppose that the bounded conditions for coefficients with approximate dimensions similar to [8, Assumption 2.3 (i-ii)] and  $E_1, E_2^j, E_{3i} \in L^\infty(0, T; \mathbb{R}^n)$ ,  $i = 1, \dots, N$ ,  $j = 1, \dots, l_2$  hold, and there exist  $i_0$  such that for  $i > i_0$ , the Riccati equation (A.30) has a positive definite solution  $\tilde{P}^i(t)$  satisfying terminal condition (A.35). Moreover, suppose that  $(L_{1,i}^j(t))^{-1}, (L_{2,j}^j(t))^{-1}$  exist where (A.36) hold and  $L_{1,i}^j, L_{2,i}^j$  are defined as above with replacing  $P_1(t), P_2(t), P_3(t)$  by  $P_{1,i}(t), P_{2,i}(t), P_{3,i}(t)$ . Let for each  $i \geq i_0$ ,  $(\tilde{R}^j(\cdot) + (\tilde{D}^j(\cdot))^\top \tilde{P}^i(\cdot) \tilde{D}(\cdot))^{-1}$  is bounded,  $j = 1, \dots, l_2$  and  $P_{1,i}$  have an upper bound and  $|P_{2,i}(\cdot)|, (L_{1,i}^j(\cdot))^{-1}, (L_{2,i}^j(\cdot))^{-1}, (L_{5,i}(\cdot))^{-1}$  are uniformly bounded. Assume that  $P_3(t) = \lim_{i \rightarrow \infty} P_{3,i}(t) > 0$  for  $t \in [0, T)$ . Then the optimal control problem (A.1) and (A.2) has an optimal control (A.42).*

**Remark A.2.** By the above analysis, we can find the optimal control (A.42) actually take the same form as (A.20). However, only the candidate (A.20) is obtained (may be optimal in form) based on the guess of relations (A.14) (motivated by relations (A.11)) but not gives the optimal cost in the indefinite case. Therefore, the core of adopting the second idea from (A.26), (A.27) and (A.28) is to guarantee the final form of optimal control (A.42) (or (A.20)) under the classical forward stochastic LQ control problem by the completion of square technique and most importantly to get the optimal cost correspondingly based on the relation (A.36) and (A.37) when  $i$  converges to infinity.

KEY LABORATORY OF SMART MANUFACTURING IN ENERGY CHEMICAL PROCESS, MINISTRY OF EDUCATION, EAST CHINA UNIVERSITY OF SCIENCE AND TECHNOLOGY, SHANGHAI 200237, CHINA  
*Email address:* yichunli953@gmail.com

SCHOOL OF MATHEMATICS, SHANDONG UNIVERSITY, JINAN, SHANDONG 250100, CHINA  
*Email address:* shijingtao@sdu.edu.cn

SCHOOL OF MATHEMATICAL SCIENCES, FUDAN UNIVERSITY, SHANGHAI 200433, CHINA  
*Email address:* zhengyueyang0106@163.com