

# Spherical to Cartesian Coordinates Transformation for Solid Harmonics Revisited

Chiara Ribaldone<sup>1</sup> and Jacques Kontak Desmarais<sup>1</sup>

*Dipartimento di Chimica, University of Torino, via Giuria 5, 10125, Torino, Italy*

(\*Electronic mail: jacqueskontak.desmarais@unito.it)

(\*Electronic mail: chiara.ribaldone@unito.it)

(Dated: 24 December 2024)

Spherical Harmonic Gaussian type orbitals and Slater functions can be expressed using spherical coordinates or a linear combinations of the appropriate Cartesian functions. General expressions for the transformation coefficients between the two representations are provided. Values for the transformation coefficients are tabulated up to the quantum number  $\ell = 10$ .

## I. INTRODUCTION

Harmonics are obtained as a solution to Laplace's equation and have a wide range of physical applications, for instance, in calculating the Coulomb potential,<sup>1</sup> and in the representation of electromagnetic and gravitation fields<sup>2,3</sup> as well as acoustic modes in spherical coordinates.<sup>4</sup> With reference to a given point  $\mathbf{r} = (x, y, z)$  in a three dimensional space, unnormalized complex solid harmonics are defined as<sup>5</sup>

$$Y_\ell^m(\mathbf{r}) = r^\ell P_\ell^{|m|}(\cos \theta) e^{im\varphi} \quad (1)$$

where  $r = \|\mathbf{r}\|$  is the norm of the position vector,  $P_\ell^{|m|}(\cos \theta)$  is the associated Legendre function characterized by the quantum numbers  $\ell$  and  $m$  such that  $\ell \geq 0$  and  $-\ell \leq m \leq \ell$  while  $(\mathbf{r}, \theta, \varphi)$  are the spherical polar coordinates.

In electronic structure theory, the spherical harmonics appear in the analytical solution of the Schrödinger and Dirac equations for the Hydrogen atom. A success of quantum chemistry is the expansion of the many-body wavefunction into basis functions that resemble those of Hydrogen. The workhorse of quantum chemical calculations, the Gaussian-type orbitals (GTOs) of Boys and McWeeny,<sup>6,7</sup> as well as Slater's functions,<sup>8</sup> both employ spherical harmonics as a key component.

The characteristic property of the spherical harmonic Gaussian-type orbitals (SGTOs) and Slater functions is that they remain eigenfunctions of the total electronic angular momentum operator  $L^2$  and its  $z$ -component  $L_z$ , which is advantageous for interpretation of the calculation in terms of conventional chemical intuition. The many-electron integral algorithms, on the other hand, are most often developed in Cartesian coordinates.<sup>9-12</sup> Examples are the algorithms of McMurchie and Davidson,<sup>13</sup> and of Obara and Saika,<sup>14,15</sup> as well as their refinements.<sup>16-20</sup> Direct use of spherical harmonics in such algorithms leads to integrals which cannot be exactly factorized in terms of Cartesian products. Though, it remains advantageous to work with SGTOs, so as to reduce the amount of basis functions in the calculation, especially when employing high quantum numbers. For instance, at  $\ell = 2$ , there are 6 distinct Cartesian Gaussian-type orbitals (CGTOs), but only 5 SGTOs. At quantum number  $\ell = 10$ , there are 66 unique CGTOs, but merely 21 SGTOs.<sup>21</sup>

It is possible to work with the reduced SGTO  $S_\ell^m(\mathbf{r})$  basis, while taking advantage of the convenience of CGTOs  $G_{tuv}(\mathbf{r})$  for integral evaluation, through an expansion<sup>22,23</sup>

$$S_\ell^m(\mathbf{r}) = \sum_{tuv} C_{tuv}^{\ell m} G_{tuv}(\mathbf{r}) \quad \text{where} \quad t + u + v = \ell \quad (2)$$

in which  $S_\ell^m(\mathbf{r}) = Y_\ell^m(\mathbf{r}) e^{-\alpha r^2}$  is a complex solid and unnormalized SGTO, and  $G_{tuv}(\mathbf{r}) = x^t y^u z^v e^{-\alpha r^2}$  is an (exactly factorizable) unnormalized CGTO, while  $C_{tuv}^{\ell m}$  are linear coefficients. Analogous formulae may be derived for the Slater functions by a replacement of the radial functions  $e^{-\alpha r^2}$  in favour of  $e^{-\alpha r}$ .

The problem may be further simplified by considering that the harmonics satisfy  $[Y_\ell^m(\mathbf{r})]^* = (-1)^m Y_\ell^{-m}(\mathbf{r})$ .<sup>24</sup> Thus, we may only consider positive values of  $m$ . This also implies that the real functions

$$X_\ell^m(\mathbf{r}) = \begin{cases} \Re [Y_\ell^{|m|}(\mathbf{r})] & m \geq 0 \\ \Im [Y_\ell^{|m|}(\mathbf{r})] & m < 0 \end{cases} \quad (3)$$

span the same space as the  $Y_\ell^m(\mathbf{r})$ , which means that the calculation may be formulated entirely in real algebra. The resulting basis functions  $R_\ell^m(\mathbf{r}) = X_\ell^m(\mathbf{r}) e^{-\alpha r^2}$  are conventionally known as real solid SGTOs.

Schlegel and Frisch proposed an analytical formula to calculate the coefficients  $C_{tuv}^{\ell m}$  of Eq. (2).<sup>25</sup> Their analysis, however, has significant limitations. For instance, when representing Eq. (1) in Cartesian coordinates, derivatives w.r.t. the  $z$ -component are applied on a function which does not depend on  $z$  (2nd line of Eq. (6) of Ref. 25). In their Eq. (14), terms depending on a summation index are present outside the sum. Last, but not least, in their final Eq. (15) for the  $C_{tuv}^{\ell m}$  coefficients, a summation includes a noninteger upper bound. Here, we investigate these loose ends, provide the general formula for transformation from spherical to Cartesian forms, as well as values of the transformation coefficients up to  $\ell = 10$ .

Our interest is in introducing CGTO based methods in the CRYSTAL code, which traditionally employs a basis of real solid SGTOs to evaluate electron repulsion integrals for molecules as well as  $d = 1, 2, 3$  dimensional periodic

systems.<sup>26,27</sup> The strategy includes a particularly efficient procedure for electrostatic summations in extended systems, employing the Ewald potential with a model density of distributed point multipoles.<sup>28</sup> Analytical gradients of the integrals are also available.<sup>29-32</sup> Nonetheless, our results are transferrable to other types of calculations that employ spherical harmonics as a central component.

## II. THEORY

### A. Coefficients for complex harmonics

Using Rodrigues' formula (pp. 48 of Ref. 24) for the associated Legendre function, we write

$$P_\ell^{|m|}(\cos \theta) = \frac{1}{2^\ell \ell!} \left[ 1 - (\cos \theta)^2 \right]^{|m|/2} \times \frac{d^{\ell+|m|}}{d(\cos \theta)^{\ell+|m|}} \left[ (\cos \theta)^2 - 1 \right]^\ell \quad (4)$$

Inserting this formula for the unnormalized complex solid harmonics, we rewrite Eq. (1) as

$$Y_\ell^{|m|}(\mathbf{r}) = \frac{r^\ell}{2^\ell \ell!} e^{i|m|\varphi} \left[ 1 - (\cos \theta)^2 \right]^{|m|/2} \times \frac{d^{\ell+|m|}}{d(\cos \theta)^{\ell+|m|}} \left[ (\cos \theta)^2 - 1 \right]^\ell \quad (5)$$

The set of Cartesian coordinates can then be retrieved from the spherical system of coordinates

$$x = r \sin \theta \cos \varphi \quad y = r \sin \theta \sin \varphi \quad z = r \cos \theta \quad (6)$$

where  $r \in [0, \infty)$ ,  $\theta \in [0, \pi]$  and  $\varphi \in [0, 2\pi)$ . These transformations can be used in the right hand side of Eq. (5) to express the solid harmonic functions in Cartesian coordinates. First of all, the exponential term on the left hand side of Eq. (5) can be reformulated as

$$e^{i|m|\varphi} = (r \sin \theta)^{-|m|} (x + iy)^{|m|} = (r^2 - z^2)^{-|m|/2} (x + iy)^{|m|} \quad (7)$$

Using the previous Eq. (7), together with the last transformation in Eq. (6), the unnormalized complex solid harmonics of Eq. (5) can be written, as functions of the Cartesian coordinates, in the following way

$$Y_\ell^{|m|}(\mathbf{r}) = \frac{r^{\ell-|m|}}{2^\ell \ell!} (x + iy)^{|m|} \frac{d^{\ell+|m|}}{d(z/r)^{\ell+|m|}} \left[ \left( \frac{z}{r} \right)^2 - 1 \right]^\ell = \frac{r^{\ell-|m|}}{2^\ell \ell!} (x + iy)^{|m|} \sum_{k=0}^{\ell} \binom{\ell}{k} (-1)^k \frac{d^{\ell+|m|}}{d(z/r)^{\ell+|m|}} \left( \frac{z}{r} \right)^{2\ell-2k} \quad (8)$$

where the binomial theorem has been used in the last identity to conveniently rewrite the polynomial on which the derivative acts. In order to evaluate the derivative in the last expression, the following basic rule can be verified

$$\left( \frac{\partial}{\partial x} \right)^n (x + a)^m = \frac{m!}{(m-n)!} (x + a)^{m-n} \quad (9)$$

so that Eq. (8) can be expressed more explicitly as

$$Y_\ell^{|m|}(\mathbf{r}) = \frac{1}{2^\ell \ell!} (x + iy)^{|m|} \times \sum_{k=0}^{\sigma_{\ell|m|}} \binom{\ell}{k} \frac{(-1)^k (2\ell - 2k)!}{(\ell - |m| - 2k)!} r^{2k} z^{\ell-|m|-2k} \quad (10)$$

where  $\sigma_{\ell|m|} = \lfloor (\ell - |m|)/2 \rfloor$  and the upper limit of the summation is fixed to  $k \leq \sigma_{\ell|m|}$  (with  $\lfloor \dots \rfloor$  denoting the round down operation) because the derivative in Eq. (8) vanishes if its order exceeds the degree of the monomial  $(z/r)$ . At this point, using the relation

$$r^2 = x^2 + y^2 + z^2 \quad (11)$$

Eq. (10) can be reformulated, in terms of Cartesian coordinates, as

$$Y_\ell^{|m|}(\mathbf{r}) = \frac{1}{2^\ell \ell!} (x + iy)^{|m|} \sum_{k=0}^{\sigma_{\ell|m|}} \binom{\ell}{k} \frac{(-1)^k (2\ell - 2k)!}{(\ell - |m| - 2k)!} \times (x^2 + y^2 + z^2)^k z^{\ell-|m|-2k} \quad (12)$$

Eq. (12) provides a representation of solid harmonics as a sum of polynomials of the Cartesian coordinates. They can be converted to a sum of monomials of the coordinates by considering the expansion

$$Y_\ell^{|m|}(\mathbf{r}) = \sum_{tuv}^{\ell} C_{tuv}^{\ell|m|} x^t y^u z^v \quad \text{where } t + u + v = \ell \quad (13)$$

and by differentiating both sides of Eq. (13) with respect to the  $(x, y, z)$  variables and then evaluating the derivatives at  $x = y = z = 0$ . To this end, equation (12) can be reformulated using the binomial theorem leading to

$$\sum_{tuv}^{\ell} C_{tuv}^{\ell|m|} x^t y^u z^v = \frac{1}{2^\ell \ell!} \sum_{s=0}^{|m|} \sum_{k=0}^{\sigma_{\ell|m|}} \binom{|m|}{s} \binom{\ell}{k} \frac{(-1)^{k+(|m|-s)/2} (2\ell - 2k)!}{(\ell - |m| - 2k)!} \times \sum_{p=0}^k \sum_{q=0}^p \binom{k}{p} \binom{p}{q} x^{s+2q} y^{|m|-s+2p-2q} z^{\ell-|m|-2p} \quad (14)$$

with the restriction  $t + u + v = \ell$  for the summation in the left hand side.

At this point, by applying the derivatives  $\partial_x^\tau \partial_y^\mu \partial_z^\nu$  on both sides of Eq. (14), and evaluating the derivatives at  $x = y = z = 0$ , the analytic expression for the expansion coefficients  $C_{tuv}^{\ell|m|}$  can be easily found. Indeed, taking the derivatives on the left hand side of Eq. (14) by means of Eq. (9), gives the result

$$\partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ \sum_{tuv}^{\ell} C_{tuv}^{\ell|m|} x^t y^u z^v \right] \Big|_{x,y,z=0} = \tau! \mu! \nu! C_{\tau\mu\nu}^{\ell|m|} = \partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ Y_\ell^{|m|}(\mathbf{r}) \right] \Big|_{x,y,z=0} \quad (15)$$

where the order of the derivatives must respect the condition  $\tau + \mu + \nu = \ell$  imposed for the order of the monomial appearing in the summation, as defined in the expansion of Eq. (13).

$(\ell, m)$	Non zero $D_{tuv}^{\ell m}$					
(0,0)	1 (0,0,0)					
(1,-1)	1 (0,1,0)					
(1,0)	1 (0,0,1)					
(1,1)	1 (1,0,0)					
(2,-2)	6 (1,1,0)					
(2,-1)	3 (0,1,1)					
(2,0)	1 (0,0,2)	-1/2 (0,2,0)	-1/2 (2,0,0)			
(2,1)	3 (1,0,1)					
(2,2)	-3 (0,2,0)	3 (2,0,0)				
(3,-3)	-15 (0,3,0)	45 (2,1,0)				
(3,-2)	30 (1,1,1)					
(3,-1)	6 (0,1,2)	-3/2 (0,3,0)	-3/2 (2,1,0)			
(3,0)	1 (0,0,3)	-3/2 (0,2,1)	-3/2 (2,0,1)			
(3,1)	6 (1,0,2)	-3/2 (1,2,0)	-3/2 (3,0,0)			
(3,2)	-15 (0,2,1)	15 (2,0,1)				
(3,3)	-45 (1,2,0)	15 (3,0,0)				
(4,-4)	-420 (1,3,0)	420 (3,1,0)				
(4,-3)	-105 (0,3,1)	315 (2,1,1)				
(4,-2)	90 (1,1,2)	-15 (1,3,0)	-15 (3,1,0)			
(4,-1)	10 (0,1,3)	-15/2 (0,3,1)	-15/2 (2,1,1)			
(4,0)	1 (0,0,4)	-3 (0,2,2)	3/8 (0,4,0)	-3 (2,0,2)	3/4 (2,2,0)	3/8 (4,0,0)
(4,1)	10 (1,0,3)	-15/2 (1,2,1)	-15/2 (3,0,1)			
(4,2)	-45 (0,2,2)	15/2 (0,4,0)	45 (2,0,2)	-15/2 (4,0,0)		
(4,3)	-315 (1,2,1)	105 (3,0,1)				
(4,4)	105 (0,4,0)	-630 (2,2,0)	105 (4,0,0)			

TABLE I. Non zero  $D_{tuv}^{\ell m}$  coefficients in the polynomial representation of the real solid harmonics up to  $\ell = 4$ . The triplet of integers in brackets after each coefficient specifies the corresponding exponents  $t, u, v$ . For instance:  $X_3^3 = 15x^3 - 45xy^2$

On the other hand, taking the derivatives on the right hand side

of Eq. (14) by means of Eq. (9) leads to the expression

$$\left. \partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ \sum_{p=0}^k \sum_{q=0}^p \binom{k}{p} \binom{p}{q} x^{s+2q} y^{|m|-s+2p-2q} z^{\ell-|m|-2p} \right] \right|_{x,y,z=0} = \tau! \mu! \nu! \sum_{p=0}^k \sum_{q=0}^p \binom{k}{p} \binom{p}{q} \delta_{s+2q}^\tau \delta_{|m|-s+2p-2q}^\mu \delta_{\ell-|m|-2p}^\nu \quad (16)$$

The Kronecker delta functions in the previous expression can be rearranged as follows

$$\begin{aligned} \delta_{s+2q}^\tau \delta_{|m|-s+2p-2q}^\mu \delta_{\ell-|m|-2p}^\nu &= \delta_{s+2q}^\tau \delta_{|m|-s+2p-2q}^\mu \delta_{\ell-\mu-s-2q}^\nu \\ &= \delta_{s+2q}^\tau \delta_{|m|-s+2p-2q}^\mu \delta_{\ell-\mu-\tau}^\nu = \delta_{s+2q}^\tau \delta_{|m|-s+2p-2q}^\mu \delta_\ell^{\tau+\mu+\nu} \end{aligned} \quad (17)$$

where in the first equality the condition imposed by the second

delta function,

$$|m| - s + 2p - 2q = \mu \quad \rightarrow \quad |m| + 2p = \mu + s + 2q \quad (18)$$

has been applied on the indices of the third delta function, while in the second identity the condition established by the first delta function,

$$s + 2q = \tau \quad (19)$$

has been used to rewrite the indices of the third delta. Now, combining the results obtained in Eqs. (15) and (16) with the

formula (14) yields the expression

$$\begin{aligned} & \left. \partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ Y_\ell^{|\mathbf{m}|}(\mathbf{r}) \right] \right|_{x,y,z=0} = \\ & \left. \partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ \frac{1}{2^\ell \ell!} \sum_{s=0}^{|\mathbf{m}|} \sum_{k=0}^{\sigma_{\ell|\mathbf{m}|}} \binom{|\mathbf{m}|}{s} \binom{\ell}{k} \frac{(-1)^{k+(|\mathbf{m}|-s)/2} (2\ell-2k)!}{(\ell-|\mathbf{m}|-2k)!} \sum_{p=0}^k \sum_{q=0}^p \binom{k}{p} \binom{p}{q} x^{s+2q} y^{|\mathbf{m}|-s+2p-2q} z^{\ell-|\mathbf{m}|-2p} \right] \right|_{x,y,z=0} \\ & = \tau! \mu! \nu! \left[ \frac{1}{2^\ell \ell!} \sum_{s=0}^{|\mathbf{m}|} \sum_{k=0}^{\sigma_{\ell|\mathbf{m}|}} \sum_{p=0}^k \sum_{q=0}^p \binom{\ell}{k} \binom{k}{p} \binom{p}{q} \binom{|\mathbf{m}|}{s} \frac{(-1)^{k+(|\mathbf{m}|-s)/2} (2\ell-2k)!}{(\ell-|\mathbf{m}|-2k)!} \delta_{s+2q}^\tau \delta_{|\mathbf{m}|-s+2p-2q}^\mu \right] \delta_\ell^{\tau+\mu+\nu} \quad (20) \end{aligned}$$

Considering the last line of Eq. (20), the delta functions induce the following constraints on summation indices, as well as quantum numbers

$$0 \leq \tau - 2q \leq |\mathbf{m}| \quad (21)$$

and

$$\frac{\tau + \mu - |\mathbf{m}|}{2} \leq k \quad \text{with} \quad \frac{\tau + \mu - |\mathbf{m}|}{2} \in \mathbb{N} \quad (22)$$

where  $\mathbb{N} = 0, 1, 2, \dots$  denotes the set of natural numbers. Eqs. (21) and (22) may be imposed onto Eq. (20) as follows

$$\begin{aligned} & \left. \partial_x^\tau \partial_y^\mu \partial_z^\nu \left[ Y_\ell^{|\mathbf{m}|}(\mathbf{r}) \right] \right|_{x,y,z=0} = \\ & \tau! \mu! \nu! \left[ \frac{M_{\tau\mu|\mathbf{m}|}}{2^\ell \ell!} \sum_{k=0}^{\sigma_{\ell|\mathbf{m}|}} \sum_{q=0}^{\eta_{\tau\mu|\mathbf{m}|}} \binom{\ell}{k} \binom{k}{\eta_{\tau\mu|\mathbf{m}|}} \binom{\eta_{\tau\mu|\mathbf{m}|}}{q} \binom{|\mathbf{m}|}{\tau-2q} \frac{(-1)^{k+(|\mathbf{m}|-\tau+2q)/2} (2\ell-2k)!}{(\ell-|\mathbf{m}|-2k)!} \Theta_{\tau\mu|\mathbf{m}|kq} \right] \delta_\ell^{\tau+\mu+\nu} \quad (23) \end{aligned}$$

in which the compact notation:

$$M_{\tau\mu|\mathbf{m}|} = [1 - \text{mod}(\tau + \mu - |\mathbf{m}|, 2)] H[\tau + \mu - |\mathbf{m}|] \quad (24)$$

$$\eta_{\tau\mu|\mathbf{m}|} \equiv \frac{\tau + \mu - |\mathbf{m}|}{2} \quad (25)$$

and

$$\Theta_{\tau\mu|\mathbf{m}|kq} = H[k - \eta_{\tau\mu|\mathbf{m}|}] H[\tau - 2q] H[|\mathbf{m}| - \tau + 2q] \quad (26)$$

has been introduced, with  $\text{mod}(n, m)$  representing the modulus of division  $n/m$ , and  $H[n]$  being the Heaviside step function in the  $H[0] = 1$  convention. Combining Eqs. (15) and (23), we finally obtain

$$C_{tuv}^{\ell|\mathbf{m}|} = \frac{M_{tu|\mathbf{m}|}}{2^\ell \ell!} \sum_{k=0}^{\sigma_{\ell|\mathbf{m}|}} \binom{\ell}{k} \binom{k}{\eta_{tu|\mathbf{m}|}} \frac{(-1)^k (2\ell-2k)!}{(\ell-|\mathbf{m}|-2k)!} \sum_{q=0}^{\eta_{tu|\mathbf{m}|}} \binom{\eta_{tu|\mathbf{m}|}}{q} \binom{|\mathbf{m}|}{t-2q} (-1)^{(|\mathbf{m}|-t+2q)/2} \Theta_{tu|\mathbf{m}|kq} \delta_\ell^{t+u+v} \quad (27)$$

where the free indices  $(\tau, \mu, \nu)$  have been renamed as  $(t, u, v)$ , respectively. The most important difference of our Eq. (27) in comparison with the result of Ref. 25 is that we obtained a round down operation on the upper limit  $\sigma_{\ell|\mathbf{m}|} = \lfloor (\ell - |\mathbf{m}|)/2 \rfloor$  of the  $k$  summation.

## B. Coefficients for real harmonics

The coefficients  $D_{tuv}^{\ell m}$  associated with the unnormalized real solid harmonics can then be derived from Eq. (3). Indeed, taking the real (for  $m \geq 0$ ) and imaginary (for  $m < 0$ ) parts in

$(\ell, m)$	Non zero $D_{tuv}^{\ell m}$					
(5, -5)	945 (0,5,0)	-9450 (2,3,0)	4725 (4,1,0)			
(5, -4)	-3780 (1,3,1)	3780 (3,1,1)				
(5, -3)	-420 (0,3,2)	105/2 (0,5,0)	1260 (2,1,2)	-105 (2,3,0)	-315/2 (4,1,0)	
(5, -2)	210 (1,1,3)	-105 (1,3,1)	-105 (3,1,1)			
(5, -1)	15 (0,1,4)	-45/2 (0,3,2)	15/8 (0,5,0)	-45/2 (2,1,2)	15/4 (2,3,0)	15/8 (4,1,0)
(5, 0)	1 (0,0,5)	-5 (0,2,3)	15/8 (0,4,1)	-5 (2,0,3)	15/4 (2,2,1)	15/8 (4,0,1)
(5, 1)	15 (1,0,4)	-45/2 (1,2,2)	15/8 (1,4,0)	-45/2 (3,0,2)	15/4 (3,2,0)	15/8 (5,0,0)
(5, 2)	-105 (0,2,3)	105/2 (0,4,1)	105 (2,0,3)	-105/2 (4,0,1)		
(5, 3)	-1260 (1,2,2)	315/2 (1,4,0)	420 (3,0,2)	105 (3,2,0)	-105/2 (5,0,0)	
(5, 4)	945 (0,4,1)	-5670 (2,2,1)	945 (4,0,1)			
(5, 5)	4725 (1,4,0)	-9450 (3,2,0)	945 (5,0,0)			
(6, -6)	62370 (1,5,0)	-207900 (3,3,0)	62370 (5,1,0)			
(6, -5)	10395 (0,5,1)	-103950 (2,3,1)	51975 (4,1,1)			
(6, -4)	-18900 (1,3,2)	1890 (1,5,0)	18900 (3,1,2)	-1890 (5,1,0)		
(6, -3)	-1260 (0,3,3)	945/2 (0,5,1)	3780 (2,1,3)	-945 (2,3,1)	-2835/2 (4,1,1)	
(6, -2)	420 (1,1,4)	-420 (1,3,2)	105/4 (1,5,0)	-420 (3,1,2)	105/2 (3,3,0)	105/4 (5,1,0)
(6, -1)	21 (0,1,5)	-105/2 (0,3,3)	105/8 (0,5,1)	-105/2 (2,1,3)	105/4 (2,3,1)	105/8 (4,1,1)
(6, 0)	1 (0,0,6)	-15/2 (0,2,4)	45/8 (0,4,2)	-5/16 (0,6,0)	-15/2 (2,0,4)	45/4 (2,2,2)
	-15/16 (2,4,0)	45/8 (4,0,2)	-15/16 (4,2,0)	-5/16 (6,0,0)		
(6, 1)	21 (1,0,5)	-105/2 (1,2,3)	105/8 (1,4,1)	-105/2 (3,0,3)	105/4 (3,2,1)	105/8 (5,0,1)
(6, 2)	-210 (0,2,4)	210 (0,4,2)	-105/8 (0,6,0)	210 (2,0,4)	-105/8 (2,4,0)	-210 (4,0,2)
	105/8 (4,2,0)	105/8 (6,0,0)				
(6, 3)	-3780 (1,2,3)	2835/2 (1,4,1)	1260 (3,0,3)	945 (3,2,1)	-945/2 (5,0,1)	
(6, 4)	4725 (0,4,2)	-945/2 (0,6,0)	-28350 (2,2,2)	4725/2 (2,4,0)	4725 (4,0,2)	4725/2 (4,2,0)
	-945/2 (6,0,0)					
(6, 5)	51975 (1,4,1)	-103950 (3,2,1)	10395 (5,0,1)			
(6, 6)	-10395 (0,6,0)	155925 (2,4,0)	-155925 (4,2,0)	10395 (6,0,0)		

TABLE II. Same as Table I, but for quantum number  $\ell = 5$  and  $\ell = 6$ .

Eq. (13), leads to the equation

$$X_{\ell}^m(\mathbf{r}) = \sum_{tuv}^{\ell} D_{tuv}^{\ell m} x^t y^u z^v \quad \text{where} \quad t + u + v = \ell \quad (28)$$

with

$$D_{tuv}^{\ell m} = \begin{cases} \Re [C_{tuv}^{\ell|m|}] & m \geq 0 \\ \Im [C_{tuv}^{\ell|m|}] & m < 0 \end{cases} \quad (29)$$

Values of the  $D_{tuv}^{\ell m}$  coefficients calculated through Eqs. (27) and (29) are listed in Tables I and II, up to the quantum number

$\ell = 6$ , while we provide the Fortran08 source code up to a user provided maximum value of the  $\ell$  quantum number, as well as tabulated values up to  $\ell = 10$ , in the Supplementary Material.

### III. CONCLUSIONS

A formula for the transformation coefficients of complex and real spherical solid harmonic Gaussian type orbitals (and Slater functions) in terms of (exactly factorizable) Cartesian functions has been given. Explicit expressions of the coefficients are tabulated up to the quantum number  $\ell = 10$ , with source code also provided. The coefficients are presently being applied in our density-fitting engine under development in the CRYSTAL code.

<sup>1</sup>R. J. Buehler and J. O. Hirschfelder, "Bipolar expansion of coulombic potentials," Physical Review **83**, 628 (1951).

<sup>2</sup>Y. Takahashi and D. Scheeres, "Small body surface gravity fields via spher-

ical harmonic expansions," Celestial Mechanics and Dynamical Astronomy **119**, 169–206 (2014).

<sup>3</sup>B. Carrascal, G. Estevez, P. Lee, and V. Lorenzo, "Vector spherical harmon-

- ics and their application to classical electrodynamics,” *European Journal of Physics* **12**, 184 (1991).
- <sup>4</sup>L. Kumar and R. M. Hegde, “Near-field acoustic source localization and beamforming in spherical harmonics domain,” *IEEE Transactions on Signal Processing* **64**, 3351–3361 (2016).
- <sup>5</sup>E. W. Hobson, *The theory of spherical and ellipsoidal harmonics* (CUP Archive, 1931).
- <sup>6</sup>S. F. Boys, “Electronic wave functions-i. a general method of calculation for the stationary states of any molecular system,” *Proc. R. Soc. Lond.* **200**, 542–554 (1950).
- <sup>7</sup>R. McWeeny, “Gaussian approximations, to wave functions,” *Nature* **166**, 21–22 (1950).
- <sup>8</sup>J. C. Slater, “Analytic atomic wave functions,” *Physical Review* **42**, 33 (1932).
- <sup>9</sup>P. M. Gill, “Molecular integrals over gaussian basis functions,” in *Advances in quantum chemistry*, Vol. 25 (1994) pp. 141–205.
- <sup>10</sup>M. Dupuis, J. Rys, and H. F. King, “Evaluation of molecular integrals over gaussian basis functions,” *The Journal of Chemical Physics* **65**, 111–116 (1976).
- <sup>11</sup>T. Helgaker and P. R. Taylor, “Gaussian basis sets and molecular integrals,” *Modern Electronic Structure Theory: Part II*, 725–856 (1995).
- <sup>12</sup>V. Saunders, “Molecular integrals for gaussian type functions,” in *Methods in computational molecular physics* (1983) pp. 1–36.
- <sup>13</sup>L. E. McMurchie and E. R. Davidson, “One-and two-electron integrals over cartesian gaussian functions,” *Journal of Computational Physics* **26**, 218–231 (1978).
- <sup>14</sup>S. Obara and A. Saika, “Efficient recursive computation of molecular integrals over cartesian gaussian functions,” *The Journal of chemical physics* **84**, 3963–3974 (1986).
- <sup>15</sup>S. Obara and A. Saika, “General recurrence formulas for molecular integrals over cartesian gaussian functions,” *The Journal of chemical physics* **89**, 1540–1559 (1988).
- <sup>16</sup>M. Head-Gordon and J. A. Pople, “A method for two-electron gaussian integral and integral derivative evaluation using recurrence relations,” *The Journal of chemical physics* **89**, 5777–5786 (1988).
- <sup>17</sup>P. M. Gill and J. A. Pople, “The prism algorithm for two-electron integrals,” *International journal of quantum chemistry* **40**, 753–772 (1991).
- <sup>18</sup>B. G. Johnson, P. M. Gill, and J. A. Pople, “Exact and approximate solutions to the one-center mcmurchie–davidson tree-search problem,” *Int. J. Quant. Chem.* **40**, 809–827 (1991).
- <sup>19</sup>G. Cisneros, “Improved solutions to the one-center mcmurchie–davidson tree search problem,” *J. Comput. Chem.* **14**, 452–454 (1993).
- <sup>20</sup>P. M. Gill, M. Head-Gordon, and J. A. Pople, “An efficient algorithm for the generation of two-electron repulsion integrals over gaussian basis functions,” *Int. J. Quant. Chem.* **36**, 269–280 (1989).
- <sup>21</sup>The general formula for the number of CGTOs at given  $\ell$  is provided by the “stars and bars” (also known as “sticks and stones”) problem of combinatorics and reads  $\binom{\ell+2}{2}$ , while the number of SGTOs is just  $2\ell+1$ .
- <sup>22</sup>R. D. C. Pisani and C. Roetti, *Hartree Fock Ab Initio Treatment of Crystalline Systems (Lecture Notes in Chemistry)* (Springer-Verlag, Berlin, 1988).
- <sup>23</sup>V. R. Saunders, “in *Handbook of Molecular Physics and Quantum Chemistry, Volume 2*, Chapter 29. Molecular Integrals over Gaussian-type Functions,” in *Handbook of Molecular Physics and Quantum Chemistry, Volume 2* (S. Wilson, John Wiley and Sons, Ltd., 2003).
- <sup>24</sup>W. Bell, *Special Functions for Scientists and Engineers* (Butler and Tanner Ltd., Frome and London, 1968).
- <sup>25</sup>H. B. Schlegel and M. J. Frisch, “Transformation between cartesian and pure spherical harmonic gaussians,” *International Journal of Quantum Chemistry* **54**, 83–87 (1995).
- <sup>26</sup>A. Erba, J. K. Desmarais, S. Casassa, B. Civalleri, L. Donà, I. J. Bush, B. Searle, L. Maschio, L. Edith-Daga, A. Cossard, *et al.*, “Crystal23: A program for computational solid state physics and chemistry,” *Journal of Chemical Theory and Computation* **19**, 6891–6932 (2022).
- <sup>27</sup>J. K. Desmarais, A. Erba, and R. Dovesi, “Generalization of the periodic lcao approach in the crystal code to g-type orbitals,” *Theoretical Chemistry Accounts* **137**, 1–11 (2018).
- <sup>28</sup>V. Saunders, C. Freyria-Fava, R. Dovesi, L. Salasco, and C. Roetti, “On the electrostatic potential in crystalline systems where the charge density is expanded in gaussian functions,” *Molecular Physics* **77**, 629–665 (1992).
- <sup>29</sup>J. K. Desmarais, A. De Frenza, and A. Erba, “Efficient calculation of derivatives of integrals in a basis of non-separable gaussians,” *The Journal of Chemical Physics* **158** (2023).
- <sup>30</sup>K. Doll, V. Saunders, and N. Harrison, “Analytical hartree–fock gradients for periodic systems,” *Int. J. Q. Chem.* **82**, 1–13 (2001).
- <sup>31</sup>K. Doll, “Implementation of analytical hartree–fock gradients for periodic systems,” *Comput. Phys. Commun.* **137**, 74–88 (2001).
- <sup>32</sup>K. Doll, R. Dovesi, and R. Orlando, “Analytical hartree–fock gradients with respect to the cell parameter: systems periodic in one and two dimensions,” *Theor. Chem. Acc.* **115**, 354–360 (2006).